

FortiLink (7.4.10) Release Notes

FortiSwitchOS 7.4.9



FORTINET DOCUMENT LIBRARY

<https://docs.fortinet.com>

FORTINET VIDEO GUIDE

<https://video.fortinet.com>

FORTINET BLOG

<https://blog.fortinet.com>

CUSTOMER SERVICE & SUPPORT

<https://support.fortinet.com>

FORTINET TRAINING & CERTIFICATION PROGRAM

<https://www.fortinet.com/training-certification>

NSE INSTITUTE

<https://training.fortinet.com>

FORTIGUARD CENTER

<https://www.fortiguard.com>

END USER LICENSE AGREEMENT

<https://www.fortinet.com/doc/legal/EULA.pdf>

FEEDBACK

Email: techdoc@fortinet.com



January 20, 2026

FortiSwitchOS 7.4.9 FortiLink (7.4.10) Release Notes

11-7410-1242278-20260120

TABLE OF CONTENTS

Change log	4
What's new in FortiOS 7.4.10	5
Introduction	6
Special notices	8
Support of FortiLink features	8
Upgrade information	9
Product integration and support	10
FortiSwitchOS 7.4.9 support	10
Resolved issues	11
Known issues	12

Change log

Date	Change Description
January 20, 2026	Initial document release for FortiOS 7.4.10

What's new in FortiOS 7.4.10

This release is a patch release only. No new managed FortiSwitch features have been added in FortiOS 7.4.10.

Introduction

This document provides the following information for FortiSwitch 7.4.9 devices managed by FortiOS 7.4.10 build 2867:

- [Special notices on page 8](#)
- [Upgrade information on page 9](#)
- [Product integration and support on page 10](#)
- [Resolved issues on page 11](#)
- [Known issues on page 12](#)

See the [Fortinet Document Library](#) for FortiSwitchOS documentation.

Refer to the [FortiLink Compatibility matrix](#) to find which FortiSwitchOS versions support which FortiOS versions.



FortiLink is not supported in transparent mode.

The maximum number of supported FortiSwitch units depends on the FortiGate model:

FortiGate Model Range	Number of FortiSwitch Units Supported
FortiGate 40F, FortiGate-VM01	8
FortiGate 6xE, 8xE, 90E, 91E	16
FGR-60F, FG-60F, FGR-60F-3G4G, FG-61F, FGR-70F, FGR-70F-3G4G, FG-80F, FG-80FB, FG-80FP, FG-81F, FG-81FP, FG-90G, FG-91G	24
FortiGate 100D, FortiGate-VM02	24
FortiGate 100E, 100EF, 100F, 101E, 140E, 140E-POE	32
FortiGate 200E, 201E	64
FortiGate 300D to 500D	48
FortiGate 300E to 500E	72
FortiGate 600D to 900D and FortiGate-VM04	64
FortiGate 600E to 900E	96
FortiGate 1000D to 15xxD	128
FortiGate 1100E to 26xxF	196
FortiGate-3xxx and up and FortiGate-VM08 and up	300



New models (NPI releases) might not support FortiLink. Contact [Customer Service & Support](#) to check support for FortiLink.

Special notices

Support of FortiLink features

Refer to the [FortiSwitchOS feature matrix](#) for details about the FortiLink features supported by each FortiSwitchOS model.

Upgrade information



Check the FortiSwitchOS Release Notes before upgrading the FortiSwitch firmware from the FortiGate Switch Controller.

FortiSwitchOS 7.4.9 supports upgrading from FortiSwitchOS 3.5.0 and later.

To determine a compatible FortiOS version, check the [FortiLink Compatibility matrix](#).

Within the Security Fabric, the FortiSwitch upgrade is done after the FortiGate upgrade. Refer to the latest [FortiOS Release Notes](#) for the complete Security Fabric upgrade order.

Product integration and support

FortiSwitchOS 7.4.9 support

The following table lists FortiSwitchOS 7.4.9 product integration and support information.

Web browser	<ul style="list-style-type: none">• Microsoft Edge 135• Mozilla Firefox version 138• Google Chrome version 136 <p>Other browser versions have not been tested but might fully function. Other web browsers might function correctly but are not supported by Fortinet.</p>
FortiOS (FortiLink Support)	Refer to the FortiLink Compatibility matrix to find which FortiSwitchOS versions support which FortiOS versions.

Resolved issues

The following issues have been fixed in FortiOS 7.4.10. For inquiries about a particular bug, please contact [Customer Service & Support](#).

Bug ID	Description
1149978	There are CPU usage issues during flcfgd iteration over WAD user-device-store entries in a FortiLink setup.
1164685	Local MAC addresses are filtered out from being added to the user device list when mab-entry-as dynamic mode is enabled on FortiSwitch units.
1170323	Interfaces cannot be enabled as FortiLink interfaces on FortiGate devices with hardware revision 2.
1198110	FortiSwitch disconnection observed when adding managed switches,
1199780	The configuration status remains as “Wait” when FortiGate configuration changes are not reflected on FortiSwitch units.

Known issues

The following known issues have been identified with FortiOS 7.4.10. For inquiries about a particular bug or to report a bug, please contact [Fortinet Customer Service & Support](#).

Bug ID	Description
298348, 298994	Enabling the <code>hw-switch-ether-filter</code> command on the FG-92D model (the default setting) causes FortiSwitch devices to not be discovered.
520954	When a “FortiLink mode over a layer-3 network” topology has been configured, the FortiGate GUI does not always display the complete network.
527695	Starting in FortiOS 6.4.0, VLAN optimization is enabled by default (<code>set vlan-optimization enable</code> under <code>config switch-controller global</code>). On a network running FortiSwitchOS earlier than 6.0.0, this change results in a synchronization error, but the network still functions normally. If you have FortiSwitchOS 6.0.x, you can upgrade to remove the synchronization error or disable VLAN optimization. On a network with <code>set allowed-vlans-all enable</code> configured (under <code>config switch-controller vlan-policy</code>), the setting reverts to the default, which is disabled, when upgrading to FortiOS 6.4.0. If you want to maintain the allowed-vlans-all behavior, you can restore it after the upgrade.
586801	NetBIOS stops working when proxy ARP is configured and the access VLAN is enabled because FortiGate units do not support NetBIOS proxy.
621785	<code>user.nac-policy[].switch-scope</code> might contain a data reference to <code>switch-controller.managed-switch</code> . When this reference is set by an admin, the admin needs to remove this reference before deleting the <code>managed-switch</code> .
789914	<ul style="list-style-type: none"> When LAN segments are enabled on the FS-108E, FS-108E-POE, FS-108E-FPOE, FS-108F, FS-108F-POE, FS-108F-FPOE, FS-124E, FS-124E-POE, FS-124E-FPOE, FS-148E, FS-148E-POE, FS-148F, FS-148F-POE, FS-148F-FPOE, FS-124F, FS-124F-POE, and FS-124F-FPOE models, the internal VLAN (<code>set lan-internal-vlan</code>) is assigned automatically by default. If the same VLAN is configured on the FortiGate device, the configuration fails when it is pushed to the FortiSwitch unit without any warning message. WORKAROUND: Use a custom command. All sub-VLANs must belong to the same MSTP instance if the FortiLink configuration includes the FS-108E, FS-108E-POE, FS-108E-FPOE, FS-108F, FS-108F-POE, FS-108F-FPOE, FS-124E, FS-124E-POE, FS-124E-FPOE, FS-148E, FS-148E-POE, FS-148F, FS-148F-POE, FS-148F-FPOE, FS-124F, FS-124F-POE, and FS-124F-FPOE models.
813216	After CAPWAP offload is enabled or disabled, FortiLink goes down.

Bug ID	Description
910962	<p>After setting values for <code>src-mac</code>, <code>dst-mac</code>, and <code>vlan</code> for the ACL classifier, you cannot use the <code>unset</code> command to remove these settings.</p> <p>WORKAROUND:</p> <ol style="list-style-type: none"> 1. Remove <code>set acl-group <ACL_group_name></code> from under the <code>config switch-controller managed-switch</code> command. 2. Delete the ACL group. 3. Delete the ACL. 4. Reconfigure the ACL.
940248	When both network device detection (<code>config switch network-monitor settings</code>) and the switch controller routing offload are enabled, the FS-1048E switch generates duplicate packets.
1150215	Offline FortiSwitch units are shown incorrectly as online in the List view. Workaround: Use the Topology view.
1153175	There are intermittent issues configuring allowed VLANs on the MLAG interface using the FortiGate GUI and CLI.
1153905	The <i>WiFi & Switch Controller > FortiSwitch Clients</i> page and <i>WiFi & Switch Controller > FortiSwitch Ports</i> page keep loading.



www.fortinet.com

Copyright© 2026 Fortinet, Inc. All rights reserved. Fortinet®, FortiGate®, FortiCare® and FortiGuard®, and certain other marks are registered trademarks of Fortinet, Inc., in the U.S. and other jurisdictions, and other Fortinet names herein may also be registered and/or common law trademarks of Fortinet. All other product or company names may be trademarks of their respective owners. Performance and other metrics contained herein were attained in internal lab tests under ideal conditions, and actual performance and other results may vary. Network variables, different network environments and other conditions may affect performance results. Nothing herein represents any binding commitment by Fortinet, and Fortinet disclaims all warranties, whether express or implied, except to the extent Fortinet enters a binding written contract, signed by Fortinet's General Counsel, with a purchaser that expressly warrants that the identified product will perform according to certain expressly-identified performance metrics and, in such event, only the specific performance metrics expressly identified in such binding written contract shall be binding on Fortinet. For absolute clarity, any such warranty will be limited to performance in the same ideal conditions as in Fortinet's internal lab tests. In no event does Fortinet make any commitment related to future deliverables, features or development, and circumstances may change such that any forward-looking statements herein are not accurate. Fortinet disclaims in full any covenants, representations, and guarantees pursuant hereto, whether express or implied. Fortinet reserves the right to change, modify, transfer, or otherwise revise this publication without notice, and the most current version of the publication shall be applicable.