

FortiSwitch Release Notes

Version 6.2.7

FORTINET DOCUMENT LIBRARY

<http://docs.fortinet.com>

FORTINET VIDEO GUIDE

<http://video.fortinet.com>

FORTINET BLOG

<https://blog.fortinet.com>

CUSTOMER SERVICE & SUPPORT

<https://support.fortinet.com>

<http://cookbook.fortinet.com/how-to-work-with-fortinet-support/>

FORTIGATE COOKBOOK

<http://cookbook.fortinet.com>

FORTINET TRAINING SERVICES

<http://www.fortinet.com/training>

FORTIGUARD CENTER

<http://www.fortiguard.com>

FORTICAST

<http://forticast.fortinet.com>

END USER LICENSE AGREEMENT

<http://www.fortinet.com/doc/legal/EULA.pdf>

FORTINET PRIVACY POLICY

<https://www.fortinet.com/corporate/about-us/privacy.html>

FEEDBACK

Email: techdocs@fortinet.com



FortiSwitch Release Notes

May 4, 2021

11-627-674486-20210504

TABLE OF CONTENTS

| | |
|---|-----------|
| Change log | 4 |
| Introduction | 5 |
| Supported models..... | 5 |
| What's new in FortiSwitchOS 6.2.7..... | 5 |
| Special notices | 6 |
| Supported features for FortiSwitchOS 6.2.7..... | 6 |
| Connecting multiple FSR-112D-POE switches..... | 13 |
| Upgrade information | 14 |
| Cooperative Security Fabric upgrade..... | 14 |
| Product integration and support | 15 |
| FortiSwitch 6.2.7 support..... | 15 |
| Resolved issues | 16 |
| Common vulnerabilities and exposures..... | 16 |
| Known issues | 17 |

Change log

| Date | Change Description |
|----------------|---|
| March 18, 2021 | Initial release for FortiSwitchOS 6.2.7 |
| May 4, 2021 | Added the “Common vulnerabilities and exposures” section. |

Introduction

This document provides the following information for FortiSwitch 6.2.7 build: 0228.

NOTE: The build number is different for all 4xxE models.

- [Supported models on page 5](#)
- [Special notices on page 6](#)
- [Upgrade information on page 14](#)
- [Product integration and support on page 15](#)
- [Resolved issues on page 16](#)
- [Known issues on page 17](#)

See the [Fortinet Document Library](#) for FortiSwitch documentation.

Supported models

FortiSwitch 6.2.7 supports the following models:

| | |
|---------------------------|--|
| FortiSwitch 1xx | FS-108E, FS-108E-POE, FS-108E-FPOE, FS-124E, FS-124E-POE, FS-124E-FPOE, FS-148E, FS-148E-POE |
| FortiSwitch 2xx | FS-224D-FPOE, FS-224E, FS-224E-POE, FS-248D, FS-248E-POE, FS-248E-FPOE |
| FortiSwitch 4xx | FS-424D, FS-424D-FPOE, FS-424D-POE, FS-424E, FS-424E-POE, FS-424E-FPOE, FS-424E-Fiber, FS-M426E-FPOE, FS-448D, FS-448D-FPOE, FS-448D-POE, FS-448E, FS-448E-POE, FS-448E-FPOE |
| FortiSwitch 5xx | FS-524D-FPOE, FS-524D, FS-548D, FS-548D-FPOE |
| FortiSwitch 1xxx | FS-1024D, FS-1048D, FS-1048E |
| FortiSwitch 3xxx | FS-3032D, FS-3032E |
| FortiSwitch Rugged | FSR-112D-POE, FSR-124D |

What's new in FortiSwitchOS 6.2.7

FortiSwitch 6.2.7 is a patch release only. No new features or enhancements have been implemented in this release.

Special notices

Supported features for FortiSwitchOS 6.2.7

The following table lists the FortiSwitch features in Release 6.2.7 that are supported on each series of FortiSwitch models. All features are available in Release 6.2.7, unless otherwise stated.

| Feature | GUI supported | 112D-POE | FSR-124D | 1xxE | 4xxE | 200 Series 400 Series | 500 Series | 1024D 1048D 1048E | 3032D 3032E |
|---|---------------|----------|----------|------------------|------|--------------------------|------------|-------------------------|----------------|
| Management and Configuration | | | | | | | | | |
| CPLD software upgrade support for OS | — | — | — | — | — | — | — | 1024D 1048D | — |
| Firmware image rotation (dual-firmware image support) | — | ✓ | ✓ | 148E 148E-POE | ✓ | ✓ | ✓ | ✓ | ✓ |
| HTTP REST APIs for configuration and monitoring | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Support for switch SNMP OID | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| IP conflict detection and notification | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| FortiSwitch Cloud configuration | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Security and Visibility | | | | | | | | | |
| 802.1x port mode | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| 802.1x MAC-based security mode | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| User-based (802.1x) VLAN assignment | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |

| Feature | GUI supported | 112D-POE | FSR-124D | 1xxE | 4xxE | 200 Series 400 Series | 500 Series | 1024D 1048D 1048E | 3032D 3032E |
|---|---------------|----------|----------|------|------|-----------------------|------------|-------------------|-------------|
| 802.1x enhancements, including MAB | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| MAB reauthentication disabled | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| open-auth mode | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Support of the RADIUS accounting server | Partial | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Support of RADIUS CoA and disconnect messages | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| EAP Pass-Through | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Network device detection | — | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| IP-MAC binding | ✓ | — | — | — | — | — | ✓ | ✓ | ✓ |
| sFlow | ✓ | ✓ | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| Flow export | — | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| ACL | — | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| Multistage ACL | — | — | — | — | — | — | ✓ | ✓ | ✓ |
| Multiple ingress ACLs | — | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| Schedule for ACLs | — | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| DHCP snooping | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Allowed DHCP server list | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| DHCP blocking | — | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |

| Feature | GUI supported | 112D-POE | FSR-124D | 1xxE | 4xxE | 200 Series 400 Series | 500 Series | 1024D 1048D 1048E | 3032D 3032E |
|---|---------------|----------|----------|------|------|-----------------------|------------|-------------------|-------------|
| IP source guard | — | — | ✓ | — | ✓ | ✓ | — | — | — |
| Dynamic ARP inspection | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| ARP timeout value | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Access VLANs | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| VLAN tag by ACL | — | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| RMON group 1 | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Reliable syslog (RFC 6587) | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Packet capture | — | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| Layer 2 | | | | | | | | | |
| Link aggregation group size (maximum number of ports) (See Note 2.) | ✓ | 8 | 8 | 8 | 8 | 8 | 24/48 | 24/48 | 24/64 |
| LAG min-max-bundle | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| IPv6 RA guard | — | — | — | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| IGMP snooping | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| IGMP proxy | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| IGMP querier | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| LLDP transmit | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| LLDP-MED | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| LLDP-MED: ELIN support | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |

| Feature | GUI supported | 112D-POE | FSR-124D | 1xxE | 4xxE | 200 Series 400 Series | 500 Series | 1024D 1048D 1048E | 3032D 3032E |
|--|---------------|----------|----------|------|------|-----------------------|------------|-------------------|-------------|
| LLPD-MED: PoE negotiation | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | — | — |
| Per-port max for learned MACs | — | — | ✓ | ✓ | ✓ | ✓ | ✓ | — | — |
| MAC learning limit (See Note 4.) | — | — | ✓ | ✓ | ✓ | ✓ | ✓ | — | — |
| Learning limit violation log (See Note 4.) | — | — | ✓ | ✓ | ✓ | ✓ | ✓ | — | — |
| set mac-violation-timer | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Sticky MAC | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Total MAC entries | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| MSTP instances | — | 0-15 | 0-15 | 0-15 | 0-15 | 0-15 | 0-32 | 0-32 | 0-32 |
| STP root guard | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| STP BPDU guard | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Rapid PVST interoperation | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| 'forced-untagged' or 'force-tagged' setting on switch interfaces | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Private VLANs | ✓ | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| Multi-stage load balancing | — | — | — | — | — | — | — | ✓ | ✓ |
| Priority-based flow control | — | — | — | — | — | — | ✓ | ✓ | ✓ |
| Storm control | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Per-port storm control | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |

| Feature | GUI supported | 112D-POE | FSR-124D | 1xxE | 4xxE | 200 Series 400 Series | 500 Series | 1024D 1048D 1048E | 3032D 3032E |
|---------------------------------------|---------------|----------|----------|------|------|-----------------------|------------|-------------------|-------------|
| MAC/IP/protocol-based VLAN assignment | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Virtual wire | ✓ | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| Loop guard | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Percentage rate control | ✓ | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| VLAN stacking (QinQ) | — | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| VLAN mapping | — | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| SPAN | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| RSPAN and ERSPAN | — | RSPAN | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| Layer 3 | | | | | | | | | |
| Static routing (v4 v6) | ✓ | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| Hardware routing offload (v4 v6) | ✓ | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| Software routing only | ✓ | ✓ | — | ✓ | — | — | — | — | — |
| OSPF (See Note 3.) | ✓ | — | — | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| RIP (See Note 3.) | ✓ | — | — | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| VRRP (See Note 3.) | ✓ | — | — | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| BGP (See Note 3.) | — | — | — | — | — | — | ✓ | ✓ | ✓ |
| IS-IS (See Note 3.) | — | — | — | — | — | — | ✓ | ✓ | ✓ |
| PIM (See Note 3.) | — | — | — | — | — | — | ✓ | ✓ | ✓ |
| Hardware-based ECMP | — | — | — | — | — | — | ✓ | ✓ | ✓ |

| Feature | GUI supported | 112D-POE | FSR-124D | 1xxE | 4xxE | 200 Series 400 Series | 500 Series | 1024D 1048D 1048E | 3032D 3032E |
|---|---------------|----------|----------|-------------|------|-----------------------|------------|-------------------|-------------|
| Static BFD | — | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| uRPF | — | — | — | — | — | — | ✓ | ✓ | ✓ |
| DHCP relay feature | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| DHCP server | — | — | — | — | ✓ | 4xx only | ✓ | ✓ | ✓ |
| High Availability | | | | | | | | | |
| MCLAG (multichassis link aggregation) | Partial | — | — | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| STP supported in MCLAGs | — | — | — | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| IGMP snooping support in MCLAG | ✓ | — | — | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| Quality of Service | | | | | | | | | |
| 802.1p support, including priority queuing trunk and WRED | ✓ | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| QoS queue counters | — | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| QoS marking | — | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| Summary of configured queue mappings | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Egress priority tagging | — | — | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| Miscellaneous | | | | | | | | | |
| PoE-pre-standard detection (See Note 1.) | — | ✓ | ✓ | FS-1xxE POE | ✓ | ✓ | ✓ | — | — |

| Feature | GUI supported | 112D-POE | FSR-124D | 1xxE | 4xxE | 200 Series 400 Series | 500 Series | 1024D 1048D 1048E | 3032D 3032E |
|--|---------------|----------|----------|-------------|------|-----------------------|------------|-------------------|-------------|
| PoE modes support: first come, first served or priority based (PoE models) | — | ✓ | ✓ | FS-1xxE POE | ✓ | ✓ | ✓ | — | — |
| Control of temperature alerts | — | ✓ | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| Split port (See Note 6.) | Partial | — | — | — | — | — | ✓ | 1048E | ✓ |
| TDR (time-domain reflectometer)/cable diagnostics support | ✓ | — | ✓ | — | ✓ | ✓ | ✓ | — | — |
| Auto module max speed detection and notification | ✓ | — | — | — | — | — | ✓ | ✓ | — |
| Monitor system temperature (threshold configuration and SNMP trap support) | — | ✓ | ✓ | — | ✓ | ✓ | ✓ | ✓ | ✓ |
| Cut-through switching | — | — | — | — | — | — | — | ✓ | ✓ |
| Add CLI to show the details of port statistics | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ |
| Configuration of the QSFP low-power mode | — | — | — | — | — | — | ✓ | 1048D 1048E | ✓ |
| Energy-efficient Ethernet | — | ✓ | ✓ | ✓ | ✓ | ✓ | ✓ | — | — |
| PHY Forward Error Correction (see Note 5) | — | — | — | — | — | — | — | 1048E | 3032E |

Notes

1. PoE features are applicable only to the model numbers with a POE or FPOE suffix.
2. 24-port LAG is applicable to 524D, 524-FPOE, 1024D, and 3032D models. 48-port LAG is applicable to 548D, 548-FPOE, and 1048D models.
3. To use the dynamic layer-3 protocols, you must have an advanced features license.
4. The per-VLAN MAC learning limit and per-trunk MAC learning limit are not supported on the 448D/448D-POE/448D-FPOE/248E-POE/248E-FPOE/248D series.
5. Supported only in 100G mode (clause 91).
6. On the 3032E, you can split one port at the full base speed, split one port into four sub-ports of 25 Gbps each (100G QSFP only), or split one port into four sub-ports of 10 Gbps each (40G or 100G QSFP).

Connecting multiple FSR-112D-POE switches

The FSR-112D-POE switch does not support interconnectivity to other FSR-112D-POE switches using the PoE ports. Fortinet recommends using the SFP ports to interconnect switches.

Upgrade information

FortiSwitch 6.2.7 supports upgrading from FortiSwitch 3.5.0 and later.

Cooperative Security Fabric upgrade

FortiOS 5.4.1 greatly increases the interoperability between other Fortinet products. This includes:

- FortiClient 5.4.1
- FortiClient EMS 1.0.1
- FortiAP 5.4.1
- FortiSwitch 3.4.2

The upgrade of the firmware for each product must be completed in a precise order so the network connectivity is maintained without the need of manual steps. Customers must read the following two documents prior to upgrading any product in their network:

- *Cooperative Security Framework - Upgrade Guide*
- *FortiOS 5.4.0 to 5.4.1 Upgrade Guide for Managed FortiSwitch Devices*

This document is available in the Customer Support Firmware Images download directory for FortiSwitch 3.4.2.

Product integration and support

FortiSwitch 6.2.7 support

The following table lists 6.2.7 product integration and support information.

| | |
|------------------------------------|---|
| Web browser | <ul style="list-style-type: none">• Mozilla Firefox version 52• Google Chrome version 56 Other web browsers may function correctly, but are not supported by Fortinet. |
| FortiOS (FortiLink Support) | FortiLink is supported on all FortiSwitch models when running FortiOS 5.4.0 and later and FortiSwitchOS 3.2.1 and later. |

Resolved issues

The following issues have been fixed in 6.2.7. For inquiries about a particular bug, please contact [Customer Service & Support](#).

| Bug ID | Description |
|--------|---|
| 672440 | FortiSwitchOS logs an “Access vlan add failed entry-id” error before FortiLink goes down. |
| 684986 | When a three-tier FortiLink MCLAG topology was configured, secondary FortiSwitch units in tier-2 and tier-3 go offline unexpectedly. |
| 685954 | When an Asian language (such as Japanese, Korean, or Chinese) is configured, the browser-based console stops responding. |
| 692314 | When a FortiGate device is in FIPS-CC mode, it cannot push the configuration to the managed FortiSwitch unit, even when fips-enforce is disabled. |

Common vulnerabilities and exposures

FortiSwitchOS 6.2.7 is no longer vulnerable to the following CVEs:

- CVE-2021-26111

Visit <https://fortiguard.com/psirt> for more information.

Known issues


The following known issues have been identified with 6.2.7. For inquiries about a particular bug or to report a bug, please contact [Fortinet Customer Service & Support](#).

| Bug ID | Description |
|--|--|
| 382518, 417024, 417073, 417099, 438441 | DHCP snooping and dynamic ARP inspection (DAI) do not work with private VLANs (PVLANS). |
| 414972 | IGMP snooping might not work correctly when used with 802.1x Dynamic VLAN functionality. |
| 480605 | <p>When DHCP snooping is enabled on the FSR-112D-POE, the switched virtual interface (SVI) cannot get the IP address from the DHCP server.</p> <p>Workarounds:</p> <ul style="list-style-type: none">—Use a static IP address in the SVI when DHCP snooping is enabled on that VLAN.—Temporarily disable dhcp-snooping on vlan, issue the <code>execute interface dhcpclient-renew <interface></code> command to renew the IP address. After the SVI gets the IP address from the DHCP server, you can enable DHCP snooping. |
| 510943 | <p>The time-domain reflectometer (TDR) function (cable diagnostics feature) reports unexpected values.</p> <p>Workaround: When using the cable diagnostics feature on a port (with the <code>diagnose switch physical-ports cable-diag <physical port name></code> CLI command), ensure that the physical link on its neighbor port is down. You can disable the neighbor ports or physically remove the cables.</p> |
| 520954 | When a “FortiLink mode over a layer-3 network” topology has been configured, the FortiGate GUI does not always display the complete network. |
| 542031 | For the 5xx switches, the <code>diagnose switch physical-ports led-flash</code> command flashes only the SFP port LEDs, instead of all the port LEDs. |
| 548783 | Some models support setting the mirror destination to “internal.” This is intended only for debugging purposes and might prevent critical protocols from operating on ports being used as mirror sources. |
| 572052 | <p>Backup files from FortiSwitchOS 3.x that have 16-character-long passwords fail when restored on FortiSwitchOS 6.x. In FortiSwitchOS 6.x, file backups fail with passwords longer than 15 characters.</p> <p>Workaround: Use passwords with a maximum of 15 characters for FortiSwitchOS 3.x and 6.x.</p> |

| Bug ID | Description |
|--------|--|
| 585550 | When packet sampling is enabled on an interface, packets that should be dropped by uRPF will be forwarded. |



FORTINET®



Copyright© 2021 Fortinet, Inc. All rights reserved. Fortinet®, FortiGate®, FortiCare® and FortiGuard®, and certain other marks are registered trademarks of Fortinet, Inc., in the U.S. and other jurisdictions, and other Fortinet names herein may also be registered and/or common law trademarks of Fortinet. All other product or company names may be trademarks of their respective owners. Performance and other metrics contained herein were attained in internal lab tests under ideal conditions, and actual performance and other results may vary. Network variables, different network environments and other conditions may affect performance results. Nothing herein represents any binding commitment by Fortinet, and Fortinet disclaims all warranties, whether express or implied, except to the extent Fortinet enters a binding written contract, signed by Fortinet's General Counsel, with a purchaser that expressly warrants that the identified product will perform according to certain expressly-identified performance metrics and, in such event, only the specific performance metrics expressly identified in such binding written contract shall be binding on Fortinet. For absolute clarity, any such warranty will be limited to performance in the same ideal conditions as in Fortinet's internal lab tests. In no event does Fortinet make any commitment related to future deliverables, features, or development, and circumstances may change such that any forward-looking statements herein are not accurate. Fortinet disclaims in full any covenants, representations, and guarantees pursuant hereto, whether express or implied. Fortinet reserves the right to change, modify, transfer, or otherwise revise this publication without notice, and the most current version of the publication shall be applicable.