



# FortiAnalyzer - Release Notes

Version 6.2.0

**FORTINET DOCUMENT LIBRARY**

<https://docs.fortinet.com>

**FORTINET VIDEO GUIDE**

<https://video.fortinet.com>

**FORTINET BLOG**

<https://blog.fortinet.com>

**CUSTOMER SERVICE & SUPPORT**

<https://support.fortinet.com>

**FORTINET TRAINING & CERTIFICATION PROGRAM**

<https://www.fortinet.com/support-and-training/training.html>

**NSE INSTITUTE**

<https://training.fortinet.com>

**FORTIGUARD CENTER**

<https://fortiguard.com/>

**END USER LICENSE AGREEMENT**

<https://www.fortinet.com/doc/legal/EULA.pdf>

**FEEDBACK**

Email: [techdoc@fortinet.com](mailto:techdoc@fortinet.com)



November 29, 2019

FortiAnalyzer 6.2.0 Release Notes

05-620-523223-20191129

# TABLE OF CONTENTS

<b>FortiAnalyzer 6.2.0 Release</b>	<b>4</b>
Supported models	4
What's new	4
<b>Special Notices</b>	<b>5</b>
Port 8443 reserved	5
All OFTP connections must be encrypted for FortiAnalyzer 6.2.0 (or higher)	5
Hyper-V FortiAnalyzer-VM running on an AMD CPU	5
SSLv3 on FortiAnalyzer-VM64-AWS	5
Pre-processing logic of ebtime	5
<b>Upgrade Information</b>	<b>7</b>
Downgrading to previous versions	7
Firmware image checksums	7
FortiAnalyzer VM firmware	8
SNMP MIB files	9
<b>Product Integration and Support</b>	<b>10</b>
FortiAnalyzer version 6.2.0 support	10
Feature support	12
Language support	13
Supported models	14
FortiGate models	14
FortiCarrier models	17
FortiDDoS models	18
FortiAnalyzer models	18
FortiMail models	19
FortiSandbox models	20
FortiSwitch ATCA models	20
FortiWeb models	21
FortiCache models	22
FortiProxy models	22
FortiAuthenticator models	22
<b>Resolved Issues</b>	<b>23</b>
<b>Known Issues</b>	<b>25</b>
<b>Change Log</b>	<b>28</b>

# FortiAnalyzer 6.2.0 Release

This document provides information about FortiAnalyzer version 6.2.0 build 1050.



The recommended minimum screen resolution for the FortiAnalyzer GUI is 1280 x 800. Please adjust the screen resolution accordingly. Otherwise, the GUI may not display properly.

This section includes the following topics:

- [Supported models on page 4](#)
- [What's new on page 4](#)

## Supported models

FortiAnalyzer version 6.2.0 supports the following models:

<b>FortiAnalyzer</b>	FAZ-200F, FAZ-300F, FAZ-400E, FAZ-800F, FAZ-1000E, FAZ-2000E, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3700F and FAZ-3900E.
<b>FortiAnalyzer VM</b>	FAZ-VM64, FAZ-VM64-Ali, FAZ-VM64-AWS, FAZ-VM64-AWS-OnDemand, FAZ-VM64-Azure, FAZ-VM64-GCP, FAZ-VM64-HV, FAZ-VM64-KVM, FAZ-VM64-OPC, and FAZ-VM64-XEN (Citrix XenServer and Open Source Xen).

## What's new

For information about what's new in FortiAnalyzer 6.2.0, see the [FortiAnalyzer New Features Guide](#).

# Special Notices

This section highlights some of the operational changes that administrators should be aware of in FortiAnalyzer version 6.2.0.

## Port 8443 reserved

Port 8443 is reserved for https-logging from FortiClient EMS for Chromebooks.

## All OFTP connections must be encrypted for FortiAnalyzer 6.2.0 (or higher)

Prior to upgrading to FortiAnalyzer 6.2, make sure that all FortiGate devices are configured to use encryption when communicating with FortiAnalyzer. Starting with FortiAnalyzer 6.2.0, all OFTP communications must be encrypted.

## Hyper-V FortiAnalyzer-VM running on an AMD CPU

A Hyper-V FAZ-VM running on a PC with an AMD CPU may experience a kernel panic. Fortinet recommends running VMs on an Intel-based PC.

## SSLv3 on FortiAnalyzer-VM64-AWS

Due to known vulnerabilities in the SSLv3 protocol, FortiAnalyzer-VM64-AWS only enables TLSv1 by default. All other models enable both TLSv1 and SSLv3. If you wish to disable SSLv3 support, please run:

```
config system global
    set ssl-protocol tlsv1
end
```

## Pre-processing logic of ebtime

Logs with the following conditions met are considered usable for the calculation of estimated browsing time:

Traffic logs with `logid` of 13 or 2, when `logid == 13`, `hostname` must not be empty. The `service` field should be either HTTP, 80/TCP or 443/TCP.

If all above conditions are met, then `devid`, `vdom`, and `user` (`srcip` if `user` is empty) are combined as a key to identify a user. For time estimation, the current value of `duration` is calculated against history session start and end time, only un-overlapped part are used as the `ebtime` of the current log.

# Upgrade Information

You can upgrade FortiAnalyzer 6.0.3 or later directly to 6.2.0.



For details about upgrading your FortiAnalyzer, see *FortiAnalyzer Upgrade Guide*.



Upgrading to FortiAnalyzer 6.0.2 from 6.0 or 6.0.1 is supported and does not trigger a log database rebuild.

---

This section contains the following topics:

- [Downgrading to previous versions on page 7](#)
- [Firmware image checksums on page 7](#)
- [FortiAnalyzer VM firmware on page 8](#)
- [SNMP MIB files on page 9](#)

## Downgrading to previous versions

FortiAnalyzer does not provide a full downgrade path. You can downgrade to a previous firmware release via the GUI or CLI, but doing so results in configuration loss. A system reset is required after the firmware downgrading process has completed. To reset the system, use the following CLI commands via a console port connection:

```
execute reset all-settings
execute format {disk | disk-ext4}
```

## Firmware image checksums

The MD5 checksums for all Fortinet software and firmware releases are available at the Customer Service & Support portal, <https://support.fortinet.com>. To verify the integrity of the download, select the *Checksum* link next to the *HTTPS* download link. A dialog box will be displayed with the image file name and checksum code. Compare this checksum with the checksum of the firmware image.

## FortiAnalyzer VM firmware

Fortinet provides FortiAnalyzer VM firmware images for Amazon AWS, Citrix and Open Source XenServer, Linux KVM, Microsoft Hyper-V Server, and VMware ESX/ESXi virtualization environments.

### Aliyun

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.out.kvm.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains QCOW2 that can be used by qemu.

### Amazon Web Services

- The 64-bit Amazon Machine Image (AMI) is available on the AWS marketplace.

### Citrix XenServer and Open Source XenServer

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.out.OpenXen.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains the QCOW2 file for the Open Source Xen Server.
- `.out.CitrixXen.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains the Citrix XenServer Disk (VHD), and OVF files.

### Linux KVM

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.out.kvm.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains QCOW2 that can be used by qemu.

### Microsoft Azure

The files for Microsoft Azure have AZURE in the filenames, for example `FAZ_VM64_AZURE-v<number>-build<number>-FORTINET.out.hyperv.zip`.

- `.out`: Download the firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.hyperv.zip`: Download the package for a new FortiAnalyzer VM installation. This package contains a Virtual Hard Disk (VHD) file for Microsoft Azure.

### Microsoft Hyper-V Server

The files for Microsoft Hyper-V Server have HV in the filenames, for example, `FAZ_VM64_HV-v<number>-build<number>-FORTINET.out.hyperv.zip`.

- `.out`: Download the firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.hyperv.zip`: Download the package for a new FortiAnalyzer VM installation. This package contains a Virtual Hard Disk (VHD) file for Microsoft Hyper-V Server.



Microsoft Hyper-V 2016 is supported.

---



### VMware ESX/ESXi

- `.out`: Download either the 64-bit firmware image to upgrade your existing VM installation.
- `.ovf.zip`: Download either the 64-bit package for a new VM installation. This package contains an Open Virtualization Format (OVF) file for VMware and two Virtual Machine Disk Format (VMDK) files used by the OVF file during deployment.



For more information see the FortiAnalyzer product data sheet available on the Fortinet web site, <https://www.fortinet.com/products/management/fortianalyzer.html>. VM installation guides are available in the [Fortinet Document Library](#).

---

## SNMP MIB files

You can download the *FORTINET-FORTIMANAGER-FORTIANALYZER.mib* MIB file in the firmware image file folder. The Fortinet Core MIB file is located in the main FortiAnalyzer v5.00 file folder.

# Product Integration and Support

This section lists FortiAnalyzer 6.2.0 support of other Fortinet products. It also identifies what FortiAnalyzer features are supported for log devices and what languages FortiAnalyzer GUI and reports support. It also lists which Fortinet models can send logs to FortiAnalyzer.

The section contains the following topics:

- [FortiAnalyzer version 6.2.0 support on page 10](#)
- [Feature support on page 12](#)
- [Language support on page 13](#)
- [Supported models on page 14](#)

## FortiAnalyzer version 6.2.0 support

The following table lists FortiAnalyzer version 6.2.0 product integration and support information:

<b>Web Browsers</b>	<ul style="list-style-type: none"><li>• Microsoft Edge 40 Due to limitation on Microsoft Edge, it may not completely render a page with a large set of policies or objects.</li><li>• Mozilla Firefox version 66</li><li>• Google Chrome version 73</li></ul> Other web browsers may function correctly, but are not supported by Fortinet.
<b>FortiOS/FortiOS Carrier</b>	<ul style="list-style-type: none"><li>• 6.2.0</li><li>• 6.0.0 to 6.0.3</li><li>• 5.6.0 to 5.6.9</li><li>• 5.4.0 to 5.4.9</li></ul>
<b>FortiAnalyzer</b>	<ul style="list-style-type: none"><li>• 6.2.0</li><li>• 6.0.0 and later</li><li>• 5.6.0 and later</li><li>• 5.4.0 and later</li><li>• 5.2.0 and later</li><li>• 5.0.0 and later</li></ul>
<b>FortiCache</b>	<ul style="list-style-type: none"><li>• 4.2.9</li><li>• 4.1.6</li><li>• 4.0.4</li></ul>
<b>FortiClient</b>	<ul style="list-style-type: none"><li>• 6.0.5 and later</li><li>• 6.0.0 and later</li><li>• 5.6.0 and later</li><li>• 5.4.0 and later</li><li>• 5.2.0 and later</li></ul>

	<ul style="list-style-type: none"><li>• 5.0.4 and later</li></ul>
<b>FortiMail</b>	<ul style="list-style-type: none"><li>• 6.0.4</li><li>• 5.4.9</li><li>• 5.3.12</li><li>• 5.2.10</li><li>• 5.1.7</li><li>• 5.0.10</li></ul>
<b>FortiManager</b>	<ul style="list-style-type: none"><li>• 6.2.0 and later</li><li>• 6.0.0 and later</li><li>• 5.6.0 and later</li><li>• 5.4.0 and later</li><li>• 5.2.0 and later</li><li>• 5.0.0 and later</li></ul>
<b>FortiSandbox</b>	<ul style="list-style-type: none"><li>• 3.0.4</li><li>• 2.5.2</li><li>• 2.4.1</li><li>• 2.3.3</li><li>• 2.2.2</li><li>• 2.1.3</li><li>• 2.0.3</li><li>• 1.4.0 and later</li><li>• 1.3.0</li><li>• 1.2.3</li></ul>
<b>FortiSwitch ATCA</b>	<ul style="list-style-type: none"><li>• 5.0.0 and later</li><li>• 4.3.0 and later</li><li>• 4.2.0 and later</li></ul>
<b>FortiWeb</b>	<ul style="list-style-type: none"><li>• 6.1.0</li><li>• 6.0.3</li><li>• 6.0.1</li><li>• 5.9.1</li><li>• 5.8.6</li><li>• 5.7.2</li><li>• 5.6.1</li><li>• 5.5.6</li><li>• 5.4.1</li><li>• 5.3.9</li><li>• 5.2.4</li><li>• 5.1.4</li><li>• 5.0.6</li></ul>
<b>FortiDDoS</b>	<ul style="list-style-type: none"><li>• 5.0.0</li><li>• 4.7.0</li><li>• 4.6.0</li><li>• 4.5.0</li></ul>

	<ul style="list-style-type: none"> <li>• 4.4.2</li> <li>• 4.3.2</li> <li>• 4.2.3</li> <li>• 4.1.12</li> </ul>
<b>FortiAuthenticator</b>	<ul style="list-style-type: none"> <li>• 5.5.0</li> <li>• 5.4.1</li> <li>• 5.3.1</li> <li>• 5.2.2</li> <li>• 5.1.0</li> <li>• 5.0.0</li> <li>• 4.3.0</li> <li>• 4.2.0</li> <li>• 4.1.0</li> <li>• 4.0.0</li> </ul>
<b>FortiProxy</b>	<ul style="list-style-type: none"> <li>• 1.0</li> </ul>
<b>Virtualization</b>	<ul style="list-style-type: none"> <li>• Amazon Web Service AMI, Amazon EC2, Amazon EBS</li> <li>• Citrix XenServer 7.2</li> <li>• Linux KVM Redhat 7.1</li> <li>• Microsoft Azure</li> <li>• Microsoft Hyper-V Server 2012 and 2016</li> <li>• OpenSource XenServer 4.2.5</li> <li>• VMware ESXi versions 5.0, 5.5, 6.0, 6.5 and 6.7</li> </ul>



Always review the Release Notes of the supported platform firmware version before upgrading your device.

## Feature support

The following table lists FortiAnalyzer feature support for log devices.

Platform	Log View	FortiView	Event Management	Reports
FortiGate	✓	✓	✓	✓
FortiCarrier	✓	✓	✓	✓
FortiAnalyzer	✓		✓	
FortiAuthenticator	✓			
FortiCache	✓		✓	✓
FortiClient registered to FortiGate	✓	✓		✓

Platform	Log View	FortiView	Event Management	Reports
FortiClient registered to FortiClient EMS	✓	✓		✓
FortiDDoS	✓	✓	✓	✓
FortiMail	✓		✓	✓
FortiManager	✓		✓	
FortiSandbox	✓		✓	✓
FortiWeb	✓		✓	✓
Syslog	✓		✓	✓

## Language support

The following table lists FortiAnalyzer language support information.

Language	GUI	Reports
English	✓	✓
Chinese (Simplified)	✓	✓
Chinese (Traditional)	✓	✓
French		✓
Hebrew		✓
Hungarian		✓
Japanese	✓	✓
Korean	✓	✓
Portuguese		✓
Russian		✓
Spanish		✓

To change the FortiAnalyzer language setting, go to *System Settings > Admin > Admin Settings*, in *Administrative Settings > Language* select the desired language from the drop-down list. The default value is *Auto Detect*.

Russian, Hebrew, and Hungarian are not included in the default report languages. You can create your own language translation files for these languages by exporting a predefined language from FortiAnalyzer, modifying the text to a different language, saving the file as a different language name, and then importing the file into FortiAnalyzer. For more information, see the *FortiAnalyzer Administration Guide*.

## Supported models

This section identifies which FortiGate, FortiCarrier, FortiDDoS, FortiAnalyzer, FortiMail, FortiSandbox, FortiSwitch, FortiWeb, FortiCache, and FortiProxy models and firmware versions can send logs to a FortiAnalyzer appliance running version 6.2.0. Please ensure that the log devices are supported before completing the upgrade.



Software license activated LENC devices are supported, if their platforms are in the supported models list. For example, support of FG-3200D indicates support of FG-3200D-LENC.

This section contains the following topics:

- [FortiGate models on page 14](#)
- [FortiCarrier models on page 17](#)
- [FortiDDoS models on page 18](#)
- [FortiAnalyzer models on page 18](#)
- [FortiMail models on page 19](#)
- [FortiSandbox models on page 20](#)
- [FortiSwitch ATCA models on page 20](#)
- [FortiWeb models on page 21](#)
- [FortiCache models on page 22](#)
- [FortiProxy models on page 22](#)
- [FortiAuthenticator models on page 22](#)

## FortiGate models

Model	Firmware Version
<b>FortiGate:</b> FortiGate-30E, FortiGate-30E-3G4G-INTL, FortiGate-30E-3G4G-NAM, FortiGate-50E, FortiGate-51E, FortiGate-52E, FortiGate-60E, FortiGate-60E-POE, FortiGate-61E, FortiGate-80D, FortiGate-80E, FortiGate-80E-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-90E, FortiGate-91E, FortiGate-92D, FortiGate-100D, FortiGate-100E, FortiGate-100EF, FortiGate-101E, FortiGate-140D, FortiGate-140D-POE, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-201E, FortiGate-300D, FortiGate-300E, FortiGate-301E, FortiGate-400D, FortiGate-500D, FortiGate-500E, FortiGate-501E, FortiGate-600D, FortiGate-600E, FortiGate-601E, FortiGate-800D, FortiGate-900D, FortiGate-1000D, FortiGate-1200D, FortiGate-1500D, FortiGate-1500DT, FortiGate-2000E, FortiGate-2500E, FortiGate-3000D, FortiGate-3100D, FortiGate-3200D, FortiGate-3700D, FortiGate-3800D, FortiGate-3810D, FortiGate-3815D, FortiGate-3960E, FortiGate-3980E <b>FortiGate 5000 Series:</b> FortiGate-5001D, FortiGate-5001E, FortiGate-5001E1 <b>FortiGate DC:</b> FortiGate-80C-DC, FortiGate-600C-DC, FortiGate-800C-DC, FortiGate-800D-DC, FortiGate-1000C-DC, FortiGate-1500D-DC, FortiGate-3000D-DC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3240C-DC, FortiGate-3600C-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3810D-DC, FortiGate-3815D-DC, FortiGate-3960E-DC, FortiGate-3980E-DC	6.2

Model	Firmware Version
<b>FortiGate Hardware Low Encryption:</b> FortiGate-80C-LENC, FortiGate-600C-LENC, FortiGate-1000C-LENC <b>FortiWiFi:</b> FortiWiFi-30D, FortiWiFi-30D-POE, FortiWiFi-30E, FortiWiFi-30E-3G4G-INTL, FortiWiFi-30E-3G4G-NAM, FortiWiFi-50E, FortiWiFi-50E-2R, FortiWiFi-51E, FortiWiFi-60E, FortiWiFi-60E-DSL, FortiWiFi-60E-DSLJ, FortiWiFi-61E, FortiWiFi-80CM, FortiWiFi-81CM <b>FortiGate-VM:</b> FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-ALIONDEMAND, FortiGate-VM64-AWS, FortiGate-VM64-AWSONDEMAND, FortiGate-VM64-AZUREONDEMAND, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-GCPONDEMAND, FortiGate-VM64-HV, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-Xen, FortiGate-VMX-Service-Manager <b>FortiGate Rugged:</b> FortiGateRugged-30D, FortiGateRugged-30D-ADSL-A, FortiGateRugged-35D <b>FortiOS:</b> FortiOS-VM64, FortiOS-VM64-HV, FortiOS-VM64-KVM, FortiOS-VM64-Xen	
<b>FortiGate:</b> FG-30D, FG-30D-POE, FG-30E, FG-30E-3G4G-INTL, FG-30E-3G4G-NAM, FG50E, FG-51E, FG-52E, FG-60D, FG-60D-POE, FG-60E, FG-60E-POE, FG-61E, FG-70D, FG-70D-POE, FG-80D, FG-80E, FG-80E-POE, FG-81E, FG-81E-POE, FG-90D, FG-90D-POE, FG-90E, FG-91E, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-100E, FG-100EF, FG-101E, FG-140D, FG-140D-POE, FG-140E, FG-140E-POE, FG200D, FG-200D-POE, FG-200E, FG-201E, FG-240D, FG-240-POE, FG-280D-POE, FG300D, FG-300E, FG-301E, FG-400D, FG-500D, FG-500E, FG-501E, FG-600D, FG-800D, FG-900D, FG-1000D, FG-1200D, FG-1500D, FG-1500DT, FG-2000E, FG-2500E, FG-3000D, FG-3100D, FG-3200D, FG-3600C, FG3700D, FG-3800D, FG-3810D, FG-3815D, FG-3960E, FG-3980E <b>FortiGate 5000 Series:</b> FG-5001D, FG-5001E, FG-5001E1 <b>FortiGate DC:</b> FG-800D-DC, FG1500D-DC, FG-3000D-DC, FG-3100D-DC, FG-3200D-DC, FG-3700D-DC, FG-3800D-DC, FG-3810D-DC, FG-3815D-DC <b>FortiGate Hardware Low Encryption:</b> FG-100D-LENC, <b>Note:</b> All license-based LENC is supported based on the FortiGate support list. <b>FortiWiFi:</b> FWF-30D, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FWF-60D-POE, FWF-60E, FWF-61E, FWF-90D, FWF-90D-POE, FWF-92D <b>FortiGate VM:</b> FG-VM64, FG-VM64-AWS, FG-VM64-AWSONDEMAND, FG-VM64-AZUREONDEMAND, FG-VM64-Azure, FG-VM64-GCP, FG-VM64-GCPONDEMAND, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-XEN, FG-VMX-Service-Manager, FOS-VM64, FOS-VM64-KVM, FOS-VM64-Xen <b>FortiGate Rugged:</b> FGR-30D, FGR-35D, FGR-60D, FGR-90D	6.0

Model	Firmware Version
<p><b>FortiGate:</b> FG-30D, FG-30D-POE, FG-30E, FG-30E-3G4G-INTL, FG-30E-3G4G-NAM, FG-50E, FG-51E, FG-52E, FG-60D, FG-60D-POE, FG-60E, FG-60E-POE, FG-60E-DSL, FG-61E, FG-70D, FG-70D-POE, FG-80C, FG-80CM, FG-80D, FG-80E, FG-80E-POE, FG-81E, FG-81E-POE, FG-90D, FG-90D-POE, FG-90E, FG-91E, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-100E, FG-100EF, FG-101E, FG-140D, FG-140D-POE, FG-140E, FG-140E-POE, FG-200D, FG-200D-POE, FG-200E, FG-201E, FG-240D, FG-240-POE, FG-280D-POE, FG-300D, FG-300E, FG-301E, FG-400D, FG-500D, FG-500E, FG-501E, FG-600C, FG-600D, FG-800C, FG-800D, FG-900D, FG-1000C, FG-1000D, FG-1200D, FG-1500D, FG-1500DT, FG-2000E, FG-2500E, FG-3000D, FG-3100D, FG-3200D, FG-3240C, FG-3600C, FG-3700D, FG-3700DX, FG-3800D, FG-3810D, FG-3815D, FG-3960E, FG-3980E,</p> <p><b>FortiGate 5000 Series:</b> FG-5001C, FG-5001D, FG-5001E, FG-5001E1</p> <p><b>FortiGate 6000 Series:</b> FG-6300F, FG-6301F, FG-6500F, FG-6501F</p> <p><b>FortiGate 7000 Series:</b> FG-7030E, FG-7040E, FG-7060E</p> <p><b>FortiGate DC:</b> FG-80C-DC, FG-600C-DC, FG-800C-DC, FG-800D-DC, FG-1000C-DC, FG-1500D-DC, FG-3000D-DC, FG-3100D-DC, FG-3200D-DC, FG-3240C-DC, FG-3600C-DC, FG-3700D-DC, FG-3800D-DC, FG-3810D-DC, FG-3815D-DC, FG-7060E-8-DC</p> <p><b>FortiGate Hardware Low Encryption:</b> FG-80C-LENC, FG-100D-LENC, FG-600C-LENC, FG-1000C-LENC</p> <p><b>Note:</b> All license-based LENC is supported based on the FortiGate support list.</p> <p><b>FortiWiFi:</b> FWF-30D, FWF-30D-POE, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FWF-60D-POE, FWF-60E, FWF-61E, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D</p> <p><b>FortiGate VM:</b> FG-VM64, FG-VM64-AWS, FG-VM64-AWSONDEMAND, FG-VM64-Azure, FG-VM64-AZUREONDEMAND, FG-VM64-GCP, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-XEN, FG-VMX-Service-Manager, FOSVM64, FOSVM64-KVM, FOS-VM64-Xen</p> <p><b>FortiGate Rugged:</b> FGR-30D, FGR-35D, FGR-60D, FGR-90D</p>	5.6
<p><b>FortiGate:</b> FG-30D, FG-30D-POE, FG-30E, FG-30E-3G4G-INTL, FG-30E-3G4G-NAM, FG-50E, FG-51E, FG-52E, FG-60D, FG-60D-POE, FG-60E, FG-60E-DSL, FG-60E-POE, FG-61E, FG-70D, FG-70D-POE, FG-80C, FG-80CM, FG-80D, FG-80E, FG-80E-POE, FG-81E, FG-81E-POE, FG-90D, FG-90D-POE, FG-90E, FG-91E, FG-92D, FG-94D-POE, FG-98D-POE, FG-100D, FG-100E, FG-100EF, FG-101E, FG-140D, FG-140D-POE, FG-140E, FG-140-POE, FG-200D, FG-200D-POE, FG-240D, FG-240D-POE, FG-280D-POE, FG-200E, FG-201E, FGT-300D, FGT-300E, FGT-301E, FG-400D, FG-500D, FG-500E, FG-501E, FG-600C, FG-600D, FG-800C, FG-800D, FG-900D, FG-1000C, FG-1000D, FG-1200D, FG-1500D, FG-1500DT, FG-3000D, FG-3100D, FG-3200D, FG-3240C, FG-3600C, FG-3700D, FG-3700DX, FG 3800D, FG-3810D, FG-3815D, FG-3960E, FG3980E, FG-2000E, FG-2500E</p> <p><b>FortiGate 5000 Series:</b> FG-5001C, FG-5001D, FG-5001E, FG-5001E1</p> <p><b>FortiGate 6000 Series:</b> FG-6300F, FG-6301F, FG-6500F, FG-6501F</p> <p><b>FortiGate 7000 Series:</b> FG-7030E-Q, FG-7030E-S, FG-7040E-1, FG-7040E-2, FG-7040E-3, FG-7040E-4, FG-7040E-5, FG-7040E-6, FG-7040E-8, FG-7040E-8-DC, FG-7060E-1, FG-7060E-2, FG-7060E-3, FG-7060E-4, FG-7060E-5, FG-7060E-6, FG-7060E-8</p>	5.4



Model	Firmware Version
<b>FortiGate DC:</b> FG-80C-DC, FG-600C-DC, FG-800C-DC, FG-800D-DC, FG-1000C-DC, FG-1500D-DC, FG-3000D-DC, FG-3100D-DC, FG-3200D-DC, FG-3240C-DC, FG-3600C-DC, FG-3700D-DC, FG-3800D-DC, FG-3810D-DC, FG-3815DC, FG-7060E-8-DC <b>FortiGate Hardware Low Encryption:</b> FG-80C-LENC, FG-100D-LENC, FG-600C-LENC, FG-1000C-LENC <b>Note:</b> All license-based LENC is supported based on the FortiGate support list. <b>FortiWiFi:</b> FWF-30D, FWF-30D-POE, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FWF-60D-POE, FWF-60E-DSL, FWF-60E, FWF-61E, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D <b>FortiGate VM:</b> FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWSONDEMAND, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-XEN, FG-VMX-Service-Manager, FOS-VM64, FOS-VM64-KVM <b>FortiGate Rugged:</b> FGR-30D, FGR-30D-ADSL-A, FGR-35D, FGR-60D, FGR-90D	

## FortiCarrier models

Model	Firmware Version
<b>FortiCarrier:</b> FortiCarrier-3000D, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3700D, FortiCarrier-3800D, FortiCarrier-3810D, FortiCarrier-3815D, FortiCarrier-3960E, FortiCarrier-5001D, FortiCarrier-5001E, FortiCarrier-5001E1 <b>FortiCarrier-DC:</b> FortiCarrier-3000D-DC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3810D-DC, FortiCarrier-3815D-DC, FortiCarrier-3960E-DC <b>FortiCarrier-VM:</b> FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen	
FortiCarrier: FGT-3000D, FGT-3100D, FGT-3200D, FGT-3700D, FGT-3800D, FGT-3810D, FGT-3960E, FGT-3980E, FGT-5001D, FGT-5001E FortiCarrier-DC: FGT-3000D-DC, FGT-3100D-DC, FGT-3200D-DC, FGT-3700D-DC, FGT-3800D-DC, FGT-3810D-DC, FGT-3960E-DC, FGT-3980E-DC FortiCarrier-VM: FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-Azure, FG-VM64-GCP, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-Xen	6.0
<b>FortiCarrier:</b> FGT-3000D, FGT-3100D, FGT-3200D, FGT-3240C, FGT-3600C, FGT-3700D, FGT-3700DX, FGT-3800D, FGT-3810D, FGT-3960E, FGT-3980E, FGT-5001C, FGT-5001D, FGT-5001E <b>FortiCarrier 6000 Series:</b> FG-6300F, FG-6301F, FG-6500F, FG-6501F <b>FortiCarrier 7000 Series:</b> FG-7030E, FG-7040E, FG-7060E <b>FortiCarrier-DC:</b> FGT-3000D-DC, FGT-3100D-DC, FGT-3200D-DC, FGT-3240C-DC, FGT-3600C-DC, FGT-3700D-DC, FGT-3800D-DC, FGT-3810D-DC, FGT-3960E-DC, FGT-3980E-DC, FGT-7060E-8-DC	5.6

Model	Firmware Version
<b>FortiCarrier-VM:</b> FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWS-AWSONDEMAND, FG-VM64-Azure, FG-VM64-GCP, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-Xen  <b>FortiCarrier:</b> FGT-3000D, FGT-3100D, FGT-3200D, FGT-3240C, FGT-3600C, FGT-3700D, FGT-3700DX, FGT-3800D, FGT-3810D, FGT-5001C, FGT-5001D, FGT-7030E, FGT-7040E  <b>FortiCarrier 6000 Series:</b> FG-6300F, FG-6301F, FG-6500F, FG-6501F <b>FortiCarrier 7000 Series:</b> FG-7030E, FG-7040E, FG-7060E <b>FortiCarrier-DC:</b> FGT-3000D-DC, FGT-3100D-DC, FGT-3200D-DC, FGT-3240C-DC, FGT-3600C-DC, FGT-3700D-DC, FGT-3800D-DC, FGT-3810D-DC, FGT-7060E-8-DC <b>FortiCarrier-VM:</b> FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWS-AWSONDEMAND, FG-VM64-Azure, FG-VM64-HV, FG-VM64-KVM, FG-VM64-OPC, FG-VM64-Xen	5.4
<b>FortiCarrier:</b> FGT-3000D, FGT-3100D, FGT-3200D, FGT-3240C, FGT-3600C, FGT-3700D, FGT-3700DX, , FGT-3810A, FGT-3810D, FGT-3950B, FGT-3951B, FGT-5100B, FGT-5100C, FGT-5001D, FGT-5101C, FS-5203B, FT-5902D <b>FortiCarrier-DC:</b> FGT-3000D-DC, FGT-3100D-DC, FGT-3200D-DC, FGT-3240C-DC, FGT-3600C-DC, FGT-3700D-DC, FGT-3810A-DC, FGT-3810D-DC, FGT-3950B-DC, FGT-3951B-DC <b>FortiCarrier-VM:</b> FG-VM, FG-VM64, FG-VM64-AWS, FG-VM64-AWS-AWSONDEMAND, FG-VM64-HV, FG-VM64-KVM, FG-VM64-Xen	5.2

## FortiDDoS models

Model	Firmware Version
<b>FortiDDoS:</b> FI-1500E	5.0
<b>FortiDDoS:</b> FI-200B, FI-400B, FI-600B, FI-800B, FI-900B, FI-1000B, FI-1200B, FI-2000B	4.0, 4.1, 4.2, 4.3, 4.4, 4.5, 4.7

## FortiAnalyzer models

Model	Firmware Version
<b>FortiAnalyzer:</b> FAZ-200F, FAZ-300F, FAZ-400E, FAZ-800F, FAZ-1000E, FAZ-2000E, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3700F and FAZ-3900E.  <b>FortiAnalyzer VM:</b> FAZ-VM64, FAZ-VM64-Ali, FAZ-VM64-AWS, FAZ-VM64-AWS-OnDemand, FAZ-VM64-Azure, FAZ-VM64-GCP, FAZ-VM64-HV, FAZ-VM64-KVM, FAZ-VM64-OPC, and FAZ-VM64-XEN (Citrix XenServer and Open Source Xen).	6.2

Model	Firmware Version
<b>FortiAnalyzer:</b> FAZ-200D, FAZ-200F, FAZ-300D, FAZ-300F, FAZ-400E, FAZ-800F, FAZ-1000D, FAZ-1000E, FAZ-2000E, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3700F and FAZ-3900E.  <b>FortiAnalyzer VM:</b> FAZ-VM64, FAZ-VM64-ALI, FAZ-VM64-AWS, FAZ-VM64-AWS-OnDemand, FAZ-VM64-Azure, FAZ-VM64-GCP, FAZ-VM64-HV, FAZ-VM64-KVM, FAZ-VM64-OPC, and FAZ-VM64-XEN (Citrix XenServer and Open Source Xen).	6.0
<b>FortiAnalyzer:</b> FAZ-200D, FAZ-300D, FAZ-400E, FAZ-1000D, FAZ-1000E, FAZ-2000E, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, and FAZ-3900E.  <b>FortiAnalyzer VM:</b> FAZ-VM64, FAZ-VM64-AWS, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-KVM, and FAZ-VM64-XEN (Citrix XenServer and Open Source Xen).	5.6
<b>FortiAnalyzer:</b> FAZ-200D, FAZ-300D, FAZ-400E, FAZ-1000D, FAZ-1000E, FAZ-2000B, FAZ-2000E, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3900E, and FAZ-4000B.  <b>FortiAnalyzer VM:</b> FAZ-VM64, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-XEN (Citrix XenServer and Open Source Xen), FAZ-VM64-KVM, and FAZ-VM64-AWS.	5.4
<b>FortiAnalyzer:</b> FAZ-100C, FAZ-200D, FAZ-200E, FAZ-300D, FAZ-400C, FAZ-400E, FAZ-1000C, FAZ-1000D, FAZ-1000E, FAZ-2000B, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-3900E, FAZ-4000B  <b>FortiAnalyzer VM:</b> FAZ-VM, FAZ-VM-AWS, FAZ-VM64, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM64-KVM, FAZ-VM64-XEN	5.2
<b>FortiAnalyzer:</b> FAZ-100C, FAZ-200D, FAZ-200E, FAZ-300D, FAZ-400B, FAZ-400C, FAZ-400E, FAZ-1000B, FAZ-1000C, FAZ-1000D, FAZ-1000E, FAZ-2000A, FAZ-2000B, FAZ-3000D, FAZ-3000E, FAZ-3000F, FAZ-3500E, FAZ-3500F, FAZ-4000A, FAZ-4000B  <b>FortiAnalyzer VM:</b> FAZ-VM, FAZ-VM64, FAZ-VM64-AWS, FAZ-VM64-Azure, FAZ-VM64-HV, FAZ-VM-KVM, FAZ-VM-XEN	5.0

## FortiMail models

Model	Firmware Version
<b>FortiMail:</b> FE-60D, FE-200D, FE-200E, FE-400E, FE-1000D, FE-2000E, FE-3000D, FE-3000E, FE-3200E, FE-VM	6.0
<b>FortiMail:</b> FE-60D, FE-200D, FE-200E, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-2000E, FE-3000C, FE-3000E, FE-3200E  <b>FortiMail Low Encryption:</b> FE-3000C-LENC	5.4
<b>FortiMail:</b> FE-60D, FE-200D, FE-200E, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-2000E, FE-3000C, FE-3000D, FE-3000E, FE-3200E, FE-5002B  <b>FortiMail Low Encryption:</b> FE-3000C-LENC <b>FortiMail VM:</b> FE-VM64, FE-VM64-HV, FE-VM64-XEN	5.3

Model	Firmware Version
<b>FortiMail:</b> FE-60D, FE-200D, FE-200E, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-3000C, FE-3000D, FE-5002B <b>FortiMail VM:</b> FE-VM64, FE-VM64-HV, FE-VM64-XEN	5.2
<b>FortiMail:</b> FE-100C, FE-200D, FE-200E, FE-400B, FE-400C, FE-400E, FE-1000D, FE-2000B, FE-3000C, FE-3000D, FE-5001A, FE-5002B <b>FortiMail VM:</b> FE-VM64	5.1
<b>FortiMail:</b> FE-100C, FE-200D, FE-200E, FE-400B, FE-400C, FE-1000D, FE-2000A, FE-2000B, FE-3000C, FE-3000D, FE-4000A, FE-5001A, FE-5002B <b>FortiMail VM:</b> FE-VM64	5.0

## FortiSandbox models

Model	Firmware Version
<b>FortiSandbox:</b> FSA-1000D, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3500D, FSA-500F, FSA-1000F <b>FortiSandbox VM:</b> FSA-KVM, FSA-VM	3.0.4 2.5.2
<b>FortiSandbox:</b> FSA-1000D, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3500D <b>FortiSandbox VM:</b> FSA-VM	2.4.1 2.4.0 2.3.3 2.3.2
<b>FortiSandbox:</b> FSA-1000D, FSA-3000D, FSA-3500D <b>FortiSandbox VM:</b> FSA-VM	2.2.2 2.1.3
<b>FortiSandbox:</b> FSA-1000D, FSA-3000D <b>FortiSandbox VM:</b> FSA-VM	2.0.3 1.4.2
<b>FortiSandbox:</b> FSA-1000D, FSA-3000D	1.4.1 1.3.0 1.2.0 and later

## FortiSwitch ATCA models

Model	Firmware Version
<b>FortiController:</b> FTCL-5103B, FTCL-5902D, FTCL-5903C, FTCL-59	5.2.0
<b>FortiSwitch-ATCA:</b> FS-5003A, FS-5003B <b>FortiController:</b> FTCL-5103B, FTCL-5903C, FTCL-5913C	5.0.0
<b>FortiSwitch-ATCA:</b> FS-5003A, FS-5003B	4.3.0 4.2.0

## FortiWeb models

Model	Firmware Version
<b>FortiWeb:</b> FWB-100D, FWB-400C, FWB-400D, FWB-600D, FWB-1000D, FWB-1000E, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E <b>FortiWeb VM:</b> FWB-VM, FWB-HYPERV, FWB-XENOPEN, FWB-XENSERVR	6.0.1
<b>FortiWeb:</b> FWB-1000D, FWB-1000E, FWB-100D, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E, FWB-400C, FWB-400D, FWB-600D <b>FortiWeb VM:</b> FWB-Azure, FWB-CMINTF, FWB-HYPERV, FWB-KVM, FWB-KVM-PAYG, FWB-VM, FWB-VM-PAYG, FWB-XENAWS, FWB-XENAWS-Ondemand, FWB-XENOPEN	5.9.1
<b>FortiWeb:</b> FWB-1000C, FWB-1000D, FWB-1000E, FWB-100D, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E, FWB-400C, FWB-400D, FWB-600D <b>FortiWeb VM:</b> FWB-Azure, FWB-Azure-Ondemand, FWB-CMINTF, FWB-HYPERV, FWB-KVM, FWB-KVM-PAYG, FWB-VM, FWB-VM-PAYG, FWB-XENAWS, FWB-XENAWS-Ondemand, FWB-XENOPEN	5.8.6
<b>FortiWeb:</b> FWB-1000C, FWB-1000D, FWB-100D, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E, FWB-400C, FWB-400D, FWB-600D <b>FortiWeb VM:</b> FWB-Azure, FWB-HYPERV, FWB-KVM, FWB-OS1, FWB-VM, FWB-XENAWS, FWB-XENAWS-Ondemand, FWB-XENOPEN	5.7.2
<b>FortiWeb:</b> FWB-1000C, FWB-1000D, FWB-100D, FWB-2000E, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E, FWB-400C, FWB-400D, FWB-600D <b>FortiWeb VM:</b> FWB-Azure, FWB-HYPERV, FWB-KVM, FWB-VM, FWB-XENAWS, FWB-XENAWS-Ondemand, FWB-XENOPEN	5.6.1
<b>FortiWeb:</b> FWB-100D, FWB-400C, FWB-400D, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-3010E, FWB-4000C, FWB-4000D, FWB-4000E <b>FortiWeb VM:</b> FWB-VM-64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR, FWB-HYPERV, FWB-KVM, FWB-AZURE	5.5.6
<b>FortiWeb:</b> FWB-100D, FWB-400C, FWB-1000C, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E <b>FortiWeb VM:</b> FWB-VM64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR, FWB-HYPERV	5.4.1

Model	Firmware Version
<b>FortiWeb:</b> FWB-100D, FWB-400B, FWB-400C, FWB-1000B, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E  <b>FortiWeb VM:</b> FWB-VM64, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR, and FWB-HYPERV	5.3.9
<b>FortiWeb:</b> FWB-100D, FWB-400B, FWB-400C, FWB-1000B, FWB-1000C, FWB-1000D, FWB-3000C, FWB-3000CFSX, FWB-3000D, FWB-3000DFSX, FWB-3000E, FWB-4000C, FWB-4000D, FWB-4000E  <b>FortiWeb VM:</b> FWB-VM64, FWB-HYPERV, FWB-XENAWS, FWB-XENOPEN, FWB-XENSERVR	5.2.4

## FortiCache models

Model	Firmware Version
<b>FortiCache:</b> FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3900E <b>FortiCache VM:</b> FCH-VM64	4.0, 4.1, 4.2

## FortiProxy models

Model	Firmware Version
<b>FortiProxy:</b> FPX-400E, FPX-2000E <b>FortiProxy VM:</b> FPX-KVM, FPX-VM64	1.0

## FortiAuthenticator models

Model	Firmware Version
<b>FortiAuthenticator:</b> FAC-200D, FAC-200E, FAC-400C, FAC-400E, FAC-1000C, FAC-1000D, FAC-2000E, FAC-3000D, FAC-3000E <b>FortiAuthenticator VM:</b> FAC-VM, FAC-VM-HV, FAC-VM-KVM, FAC-VM-XEN	5.5.0

# Resolved Issues

The following issues have been fixed in FortiAnalyzer version 6.2.0. For inquiries about a particular bug, please contact [Customer Service & Support](#).

Bug ID	Description
404298	The free-text filter for log forwarding does not work on syslog that does not follow a specific format.
405993	FortiAnalyzer models FAZ-300D and FAZ-400E fail to download the <code>geoip</code> database. Consequently, these FortiAnalyzer models will not be able to get site's location by IP address and show them on maps.
442713	Regular searches for strings that contain a space character combined with an "OR" operation returns a blank result.
501805	When a user configures FortiAnalyzer HA, there is no indication on the FortiAnalyzer dashboard that it is configured or the status thereof.
502046	FortiAnalyzer stops responding to GUI access and many services are in Z state.
505853	FortiAnalyzer should be able to restrict access to the admins for specific device groups.
505853	FortiAnalyzer should be able to restrict access to the admins for specific device groups.
510401	Date format change is not applied to Chart when type is Area or Line.
512413	Malformed compact v3 log may cause daemon to crash due to log parsing error.
514656	The SNMP OID "hrStorageUsed" might report incorrect value.
515101	Admin users are unable to login from the GUI when their password contains two sequential question marks.
515686	The <code>sqllogd</code> daemon crashes on processing certain text logs with long fields.
516098	Real-time view for all devices does not show any data and returns no records found.
517559	FortiAnalyzer has multiple scheduled reports across multiple ADOMs that do not run as scheduled.
517724	Dashboard widget "System Resources" shows wrong output for the time period.
518285	Source and Destination interface information is not being sent from FortiAnalyzer to FortiGate's FortiView.
518346	Export to report stuck at 5% after drill down under Top Browsing Users.
519683	Automatically uploading reports to SFTP fails for some reports with error message that the action "is abandoned because of file not exist!".
519791	Users cannot manually add FortiAuthenticator 5.4 and 5.5.
520607	When requesting Compromised Host Blacklist details, the results are not sorted correctly when sort by "event_num" is requested.

Bug ID	Description
523055	FortiView takes very long to show the Policy Hit count chart.
523258	Report should exclude forwarded traffic with logid=21.
523445	FortiView on FortiOS reports unrealistically high traffic counters for sources with long-lived sessions.
524136	Report IOC blacklist provides different output than FortiView IOC.
524252	Event Management's Handler may not be able to trigger IPS alert when receiving anomaly log from FortiGate v6.0 devices.
524252	FortiAnalyzer cannot trigger IPS alert when anomaly logs are detected for FortiGate 6.0/6.2.
527616	FortiAnalyzer sporadically stops receiving logs.
528395	Deleting device from Device Manager removes the report filter but does not stop schedule and notifications.
529091	The maximum number of VDOMs allowed for FortiMail devices is set to be 2048.
529518	The Columns for Email Server, From and To, should have a minimum guaranteed width regardless of how long the entry is in the Email server field.
530217	When the time zone on the FortiGate is "(GMT +5:00) Ekaterinburg", 'dtime' in the FortiAnalyzer database is one hour ahead.
531411	Users are unable to set available quota as <i>Maximum Allowed</i> in ADOM quota settings.
531481	FortiAnalyzer log files may not be decompressed and inserted into the database.
534096	Current page's log messages should be downloaded if the download option <i>Current Page</i> is checked.
534783	Normal search with multiple values should highlight all search values used in the filter.
537076	FortiAnalyzer doesn't delete quarantined file automatically.
537535	FortiView intermittently shows <i>no data</i> message when trying to filter out data.
537977	The <i>Sort by</i> function does not work under storage information.
541249	The <i>diagnose test application oftpd 3</i> command occasionally causes FortiAnalyzer to freeze.



# Known Issues

The following issues have been identified in FortiAnalyzer version 6.2.0. For inquiries about a particular bug or to report a bug, please contact [Fortinet Customer Service & Support](#).

Bug ID	Description
552610	FortiAnalyzer cannot save an email address in the "From" field on Incidents & Events when TLD has five or more characters.
540397	In Fabric ADOM, subnet list should validate all fields instead of only the <code>srcip</code> and <code>dstip</code> fields.
540766	The new HA master cannot receive logs after HA failover on Azure.
541346	In Fabric ADOM, if handler is for non-FortiGate devices, drill-down of an event is not properly displayed.
542286	HA cannot work on unicast mode when members are located in different subnets.
542606	Local device event alerts should not be synchronize from HA Master to Slave.
542607	Drill-down of <i>Applications &amp; Websites - Top Web Sites(FortiClient)</i> always shows <i>No entry found</i> .
543623	UEBA pop-up cannot show <i>epname</i> when endpoint is set with group by.
544064	The firewall sessions chart should be a bar chart classified by devices in the FortiCare 360 report.
544071	Network Interface Availability Faults Over Time Chart should be classified by devices in the FortiCare 360 report.
546067	FortiRecorder should display disk usage information for FortiRecorder in the Camera Manager page.
546073	When camera IP address is changed to <i>Static</i> mode, FortiRecorder identifies it with an incorrect address.
546990	Log files cannot be seen in the Log View for a long time after the files are imported from CLI.
547496	When report is run for a particular device, it should show data for only that device.
547583	After clearing the filter in FortiView, GUI still sends query with the filter and Log View still shows filtered logs.
547904	Device Manager HA Status column show devices' status as up when the device dashboard's cluster members always shows the status as down.
548112	After enabled resolving IP address, FortiView is not showing hostname on the column "Destination" in "Top Destinations" table.
548201	Under FortiView, it is missing the column "# of Clients" in the "Top Applications" table chart.
548245	SMAL configuration is not synchronized from Master to Slave.

Bug ID	Description
548826	In SOC Monitor, FortiAnalyzer cannot show Sandbox Execution Details clearly in Night/Ocean theme.
548866	Master unit in FortiAnalyzer HA Cluster responds with VIP only for SNMP traffic.
548872	The footer in FortiAnalyzer report cover page is set to transparent and it does not work the same way as it was in previous releases.
548974	Under FortiView, policy-info is updated when moving FortiGate to a different ADOM.
549243	In <i>Top SSID</i> drill-down view, it cannot show related logs for a WiFi client.
549245	When camera wire-mode is changed from DHCP to Static, the gateway IP is always missing resulting in camera status error.
549343	The SOC period should be hidden or disable on the Compromised Host for FortiView.
549459	FortiCam network setting to TCP/HTTP results in connection error or network unreachable.
549481	Export to report chart from drill down panel in NOC fails.
549548	In FortiGate ADOM, widget count is not correct for some widget categories in Add Widget.
549718	Log Browse File Name cannot be filtered due to quotation marks.
549739	After upgrade, widgets displayed size are not scale with the content.
550068	FortiView drill-down to log view with <code>unauthuser</code> shows no result.
550113	In SOC widget "Security Rating report", the user cannot select Region and Industry and it is shown as undefined.
550136	Advanced options cannot be edited in an existing fabric connector (Storage).
550276	First time adding a new camera always shows unexpected MAC address.
550355	UEBA pop-up shows <i>[object object]</i> on some events.
550373	Avatar cannot be updated.
550544	When manually adding device, FortiWeb is missing v6.1 and FortiAuthenticator is missing v6.0.
550570	IOC drill down view shows incorrect <i>last detect</i> time.
550600	The <code>fazsvcd</code> process may use excessive memory on the system.
550619	UEBA may show some IPv6 source IPs that are unreadable.
550663	Exporting chart from FortiView main view <i>Top Country/Region</i> has an additional line, <i>Reserved</i> .
550894	Quickly switching from <i>Top Threat</i> to <i>Top Application</i> leads to SQL query error.
550933	Authorized FortiCarrier device does not shows up in the Fabric ADOM's FortiGate device drop-down list.
551125	When setting Event Handler with filter threshold over 25, FortiAnalyzer may not display any event.

Bug ID	Description
551178	FortiAnalyzer may fail to reply to XML requests. This affects only the following models: FAZ-200F, FAZ-300F, FAZ-400E, FAZ-800F, FAZ-1000E, FAZ-2000E, FAZ-3000F, FAZ-3700F.
551243	In Fabric ADOM, <i>View Related Logs</i> in the FortiDDoS widget re-directs to an inaccurate page in Log View.
554116	Unable to receive logs from 5.6 FortiGate cluster.

# Change Log

Date	Change Description
2019-04-11	Initial release of 6.2.0.
2019-04-15	Added support for FortiClient 6.0.5.
2019-04-18	Removed FAZ-200D, FAZ-300D, FAZ-1000, FAZ-3000 from <i>Supported Models</i> .
2019-04-22	Added support for FSA-500F and FSA-1000F.
2019-04-24	Added support for FortiAnalyzer 6.2. Added FortiAnalyzer 6.0 and 6.2 models.
2019-04-29	Removed support for FortiOS 5.2 as per 554599.
2019-04-30	Removed FortiGate models for FortiOS 5.2.
2019-05-03	Added 554116 to <i>Known Issues</i> .
2019-06-10	Added a special notice.
2019-06-11	Added support for FortiOS 5.6.9.
2019-06-28	Added a Special Notice.
2019-07-24	Updated the <i>Product Integration</i> section.
2019-08-01	Added FortiProxy to <i>Product Integration</i> .
2019-11-29	Updated <a href="#">Known Issues on page 25</a> .



**FORTINET®**



Copyright© 2019 Fortinet, Inc. All rights reserved. Fortinet®, FortiGate®, FortiCare® and FortiGuard®, and certain other marks are registered trademarks of Fortinet, Inc., in the U.S. and other jurisdictions, and other Fortinet names herein may also be registered and/or common law trademarks of Fortinet. All other product or company names may be trademarks of their respective owners. Performance and other metrics contained herein were attained in internal lab tests under ideal conditions, and actual performance and other results may vary. Network variables, different network environments and other conditions may affect performance results. Nothing herein represents any binding commitment by Fortinet, and Fortinet disclaims all warranties, whether express or implied, except to the extent Fortinet enters a binding written contract, signed by Fortinet's General Counsel, with a purchaser that expressly warrants that the identified product will perform according to certain expressly-identified performance metrics and, in such event, only the specific performance metrics expressly identified in such binding written contract shall be binding on Fortinet. For absolute clarity, any such warranty will be limited to performance in the same ideal conditions as in Fortinet's internal lab tests. In no event does Fortinet make any commitment related to future deliverables, features or development, and circumstances may change such that any forward-looking statements herein are not accurate. Fortinet disclaims in full any covenants, representations, and guarantees pursuant hereto, whether express or implied. Fortinet reserves the right to change, modify, transfer, or otherwise revise this publication without notice, and the most current version of the publication shall be applicable.