



Release Notes

FortiAnalyzer 7.4.10



FORTINET DOCUMENT LIBRARY

<https://docs.fortinet.com>

FORTINET VIDEO LIBRARY

<https://video.fortinet.com>

FORTINET BLOG

<https://blog.fortinet.com>

CUSTOMER SERVICE & SUPPORT

<https://support.fortinet.com>

FORTINET TRAINING & CERTIFICATION PROGRAM

<https://www.fortinet.com/training-certification>

FORTINET TRAINING INSTITUTE

<https://training.fortinet.com>

FORTIGUARD LABS

<https://www.fortiguard.com>

END USER LICENSE AGREEMENT

<https://www.fortinet.com/doc/legal/EULA.pdf>

FEEDBACK

Email: techdoc@fortinet.com



March 5, 2026

FortiAnalyzer 7.4.10 Release Notes

05-7410-1243976-20260305

TABLE OF CONTENTS

Change Log	6
FortiAnalyzer 7.4.10 Release	7
Supported models	7
Special branch supported models	7
FortiAnalyzer VM subscription license	8
Special Notices	9
MEAs removed in FortiAnalyzer 7.4.7	9
legacy-auth-mode command added	9
Upgrading from 7.4.3 to 7.4.10 with FIPS mode enabled	9
Field name when log forwarding to CEF	10
Shell access has been removed	10
Events and Incidents FortiView monitors removed	10
Alert notifications generated by FortiAnalyzer and sent by syslog	10
Additional configuration required for SSO users	11
FortiAnalyzer 7.2.3 and later firmware on FortiGuard	11
Configuration backup requires a password	11
FortiAnalyzer-3500E support	11
PostgreSQL database upgrade	12
Serial console has changed for FortiAnalyzer deployments on Xen	13
OpenXen in PV mode is not supported in FortiAnalyzer 7.4.1	13
Default GUI theme changed	14
FortiManager Features removed	14
Setup wizard requires FortiCare registration	14
Hyperscale firewall mode	14
Modifying the interface status with the CLI	15
Citrix XenServer default limits and upgrade	15
FortiAnalyzer VM upgrade requires more memory	15
Maximum ADOM limits for FortiAnalyzer	16
Port 8443 reserved	16
Hyper-V FortiAnalyzer-VM running on an AMD CPU	16
SSLv3 on FortiAnalyzer-VM64-AWS	16
Upgrade Information	17
Downgrading to previous firmware versions	17
Firmware image checksums	17
FortiAnalyzer VM firmware	17
SNMP MIB files	19
Product Integration and Support	20
Supported software	20
Web browsers	21
FortiOS and FortiOS Carrier	21
FortiADC	21

FortiAnalyzer	22
FortiAuthenticator	22
FortiCache	22
FortiCASB	22
FortiClient	23
FortiDDoS	23
FortiDeceptor	23
FortiFirewall and FortiFirewallCarrier	23
FortiIsolator	24
FortiMail	24
FortiManager	24
FortiNAC	24
FortiNDR	24
FortiPAM	25
FortiPortal	25
FortiProxy	25
FortiSandbox	25
FortiSASE	26
FortiSOAR	26
FortiSRA	26
FortiSwitch ATCA	26
FortiToken	26
FortiWeb	26
Virtualization	27
Feature support	27
Language support	28
Supported models	29
FortiGate models	30
FortiGate special branch models	37
FortiCarrier models	41
FortiCarrier special branch models	44
FortiADC models	46
FortiAnalyzer models	47
FortiAuthenticator models	48
FortiCache models	48
FortiDDoS models	49
FortiDeceptor models	49
FortiFirewall models	49
FortiFirewallCarrier models	50
FortiIsolator models	51
FortiMail models	51
FortiNAC models	52
FortiNDR models	53
FortiPAM models	53
FortiProxy models	53
FortiSandbox models	54
FortiSOAR models	54
FortiSRA models	54
FortiSwitch ATCA models	54

FortiWeb models	55
Resolved issues	56
Common Vulnerabilities and Exposures	56
Known issues	57
New known issues	57
Existing known issues	57
System Settings	57
Appendix A - Default and maximum number of ADOMs supported	58
Hardware models	58
Virtual Machines	59
FortiAnalyzer subscription license	59
FortiAnalyzer perpetual license	59

Change Log

Date	Change Description
2026-01-27	Initial release.
2026-01-28	Updated Web browsers on page 21.
2026-02-05	Updated Supported models on page 7.
2026-03-02	Updated Appendix A - Default and maximum number of ADOMs supported on page 58.
2026-03-05	Added FortiPortal on page 25.

FortiAnalyzer 7.4.10 Release

This document provides information about FortiAnalyzer version 7.4.10 build 2778.



The recommended minimum screen resolution for the FortiAnalyzer GUI is 1920 x 1080. Please adjust the screen resolution accordingly. Otherwise, the GUI may not display properly.

This section includes the following topics:

- [Supported models on page 7](#)
- [FortiAnalyzer VM subscription license on page 8](#)

Supported models

FortiAnalyzer version 7.4.10 supports the following models:

FortiAnalyzer	FAZ-150G, FAZ-300F, FAZ-300G, FAZ-400E, FAZ-800F, FAZ-800G, FAZ-810G, FAZ-1000F, FAZ-1000G, FAZ-2000E, FAZ-3000F, FAZ-3000G, FAZ-3100G, FAZ-3500F, FAZ-3500G, FAZ-3510G, FAZ-3700F, and FAZ-3700G.
FortiAnalyzer VM	FAZ_VM64, FAZ_VM64_ALI, FAZ_VM64_AWS, FAZ_VM64_AWSOnDemand, FAZ_VM64_Azure, FAZ_VM64_GCP, FAZ_VM64_IBM, FAZ_VM64_HV (including Hyper-V 2016, 2019, and 2022), FAZ_VM64_KVM, FAZ_VM64_OPC, FAZ_VM64_XEN (for both Citrix and Open Source Xen).



FAZ-300F supports the subscription license for the SOC service. However performance may be impacted because FAZ-300F has fewer resources and a smaller CPU than other FortiAnalyzer models that support the SOC service.

Special branch supported models

The following models are released on a special branch of FortiAnalyzer 7.4.10. To confirm that you are running the correct build, run the CLI command `get system status` and check that the Branch point field shows 2778.

FAZ-3750G	is released on build 6143.
------------------	----------------------------



For access to container versions of FortiAnalyzer, contact [Fortinet Support](#).

FortiAnalyzer VM subscription license

The FortiAnalyzer VM subscription license supports FortiAnalyzer version 6.4.1 and later. For information about supported firmware, see [FortiAnalyzer VM firmware on page 17](#).

See also [Appendix A - Default and maximum number of ADOMs supported on page 58](#).



You can use the FortiAnalyzer VM subscription license with new FAZ-VM installations. For existing FAZ-VM installations, you can migrate to a FortiAnalyzer VM subscription license, starting with FortiAnalyzer 7.0.1. See the [FortiAnalyzer 7.0.1 VM License Migration Guide](#).

Special Notices

This section highlights some of the operational changes that administrators should be aware of in FortiAnalyzer version 7.4.10.

MEAs removed in FortiAnalyzer 7.4.7

There is no support for MEAs in FortiAnalyzer 7.4.7.

The following management extension applications (MEAs) are removed in FortiAnalyzer 7.4.7:

- FortiSIEM
- FortiSOAR

legacy-auth-mode command added

A new CLI command, `legacy-auth-mode`, has been introduced to enhance the flexibility of OFTP connections between devices and FortiAnalyzer when needed. By default, FortiAnalyzer enforces certificate-based authentication for OFTP connections and validates the device's certificate by checking the Common Name (CN) field — if the CN matches the device's serial number (SN), the connection is accepted.

However, for devices like FortiWeb, FortiMail, and FortiADC, the certificate CN often does not match the SN, causing the OFTP connection to fail. When `legacy-auth-mode` is enabled, FortiAnalyzer allows OFTP connections to fall back to username/password authentication if the certificate CN does not match the SN. This enables compatibility with devices whose certificates use alternative CN formats while still providing a level of authentication. In line with security best practices, the OFTP port should not be exposed when `legacy-auth-mode` is enabled unless proper access restrictions are applied.

```
config system log settings
(settings)# set legacy-auth-mode ?
    disable - Disable support for legacy authentication mode.
    enable - Enable support for legacy authentication mode.
```

Upgrading from 7.4.3 to 7.4.10 with FIPS mode enabled

When FIPS mode is enabled, upgrading from 7.4.3 to 7.4.10 might fail due to the following error message: "FIPS firmware signature verification failed". The following steps should be taken as workaround:

1. Backup FortiAnalyzer-v7.4.3-fips-cc mode DB.
2. Disable FortiAnalyzer-v7.4.3-fips mode to normal mode.
3. Upgrade FortiAnalyzer-v7.4.3 normal mode to v7.4.10.
4. FortiAnalyzer-v7.4.10 enable fips-cc mode.
5. Restore FortiAnalyzer-v7.4.3-fips DB on FortiAnalyzer-v7.4.10-fips.

Note that you do not need to follow this workaround if upgrading from 7.4.4 or later to 7.4.10.

Field name when log forwarding to CEF

As of FortiAnalyzer 7.4.3, the field names no longer include the "ad." prefix when log forwarding to a CEF server.

Shell access has been removed

As of FortiAnalyzer 7.4.4, shell access has been removed.

The following CLI variables have been removed, which were previously used to enable shell access:

```
config system admin setting
    set shell-access {enable | disable}
    set shell-password <passwd>
```

The following CLI command has been removed, which was previously used to access shell when enabled:

```
execute shell
```

Events and Incidents FortiView monitors removed

In FortiAnalyzer 7.4.3, the following FortiView monitors are removed from the GUI:

- *FortiView > Threats & Events > Events*
- *FortiView > Threats & Events > Incidents*

Alert notifications generated by FortiAnalyzer and sent by syslog

Beginning in 7.4.3, alert notifications generated by FortiAnalyzer and sent by syslog will use the RFC-5424 format.

Additional configuration required for SSO users

Beginning in 7.4.3, additional configuration is needed for FortiAnalyzer Users declared as wildcard SSO users.

When configuring Administrators as wildcard SSO users, the `ext-auth-accprofile-override` and/or `ext-auth-adom-override` features, under *Advanced Options*, should be enabled if the intent is to obtain the ADOMs list and/or permission profile from the SAML IdP.

FortiAnalyzer 7.2.3 and later firmware on FortiGuard

Starting in FortiAnalyzer 7.2.1, a setup wizard executes to prompt the user for various configuration steps and registration with FortiCare. During the execution, the FortiAnalyzer unit attempts to communicate with FortiGuard for a list of FortiAnalyzer firmware images currently available on FortiGuard – older and newer.

In the case of FortiAnalyzer 7.2.2, a bug in the GUI prevents the wizard from completing and prevents the user from accessing the FortiAnalyzer unit. The issue has been fixed in 7.2.3 and later and a CLI command has been added to bypass the setup wizard at login time.

```
config system admin setting
    set firmware-upgrade-check disable
end
```

Fortinet has not uploaded FortiAnalyzer 7.2.3 and later firmware to FortiGuard in order to work around the GUI bug, however, the firmware is available for download from the [Fortinet Support website](#).

Configuration backup requires a password

As of FortiAnalyzer 7.4.2, configuration backup files are automatically encrypted and require you to set a password. The password is required for scheduled backups as well.

In previous versions, the encryption and password were optional.

For more information, see the [FortiAnalyzer Administration Guide](#).

FortiAnalyzer-3500E support

FortiAnalyzer 7.4.2 and later does not support the FortiAnalyzer-3500E device.

FortiAnalyzer 7.4.2 introduces an upgrade of the OpenSSL library to address known vulnerabilities in the library. As a result, the SSL connection that is setup between the FortiAnalyzer-3500E device and the Google Map

server hosted by Fortinet uses a SHA2 (2048) public key length. The certificate stored on the BIOS that is used during the setup of the SSL connection contains a SHA1 public key length, which causes the connection setup to fail. Running the following command shows the key length.

```
FAZ3500E # config system certificate local
(local)# ed Fortinet_Local
(Fortinet_Local)# get
  name : Fortinet_Local
  password : *
  comment : Default local certificate
  private-key :
  certificate :
    Subject: C = US, ST = California, L = Sunnyvale, O = Fortinet, OU = FortiAnalyzer, CN =
      FL3K5E3M1500074, emailAddress = support@fortinet.com
    Issuer: C = US, ST = California, L = Sunnyvale, O = Fortinet, OU = Certificate Authority,
      CN = support, emailAddress = support@fortinet.com
    Valid from: 2015-03-06 16:22:10 GMT
    Valid to: 2038-01-19 03:14:07 GMT
    Fingerprint: FC:D0:0C:8D:DC:57:B6:16:58:DF:90:22:77:6F:2C:1B
    Public key: rsaEncryption (1024 bits)
    Signature: sha1WithRSAEncryption
    Root CA: No
    Version: 3
    Serial Num:
    1e:07:7a
    Extension 1: X509v3 Basic Constraints:
    CA:FALSE
    ...
(Fortinet_Local)#
```

PostgreSQL database upgrade

FortiAnalyzer 7.2.6 and 7.4.1 include an upgrade of the PostgreSQL database. By default analytical features, such as Log View, FortiView, Reports, and Event Management are unavailable until the PostgreSQL database finishes upgrading. During this time, FortiAnalyzer will continue to receive new logs, but they will not be inserted into the PostgreSQL database. PostgreSQL database upgrade times depend on the number of ADOM configured and the analytical log volume. Some sample upgrade times are shown below.

Model	Number of ADOMs	Analytical Data Size	DB Upgrade Time
FAZ-3700F	1200	5TB	one hour
FAZ-3500G	100	1TB	15 minutes
FAZ-3000F	1	12TB	10 minutes



Do not reboot or proceed to another upgrade while the PostgreSQL database upgrade is in progress.

If you are upgrading from a version prior to 7.2.6 (such as 7.2.0, 7.2.1, 7.2.2, and so on) or 7.4.0, you must wait for the PostgreSQL database upgrade to complete before accessing the analytical features or continuing your upgrade path. For example, if your upgrade path is 7.2.5 > latest 7.2 > 7.4.10, you must wait for the PostgreSQL upgrade to complete in the latest 7.2 before upgrading to FortiAnalyzer 7.4.10.

There is a GUI notification to track the progress of the upgrade. You can also use the following command to check the progress in the CLI:

```
diag sql status upgrade-db
```

For customers who prefer to not wait for accessing the analytical features, such as *Log View*, *FortiView*, *Reports*, and *Event Management*, for new logs, they can execute a SQL. This command can take a long time to complete depending on the amount of data.

```
FAZVM64 # exec sql-local rebuild-db
```

Rebuild the entire log SQL database has been requested.

This operation will remove the log SQL database and rebuild from log data.

This operation will reboot the device.

Do you want to continue? (y/n)

Serial console has changed for FortiAnalyzer deployments on Xen

In FortiAnalyzer 7.4.1, the serial console for Xen deployments has changed from hvc0 (Xen specific) to ttyS0 (standard).

OpenXen in PV mode is not supported in FortiAnalyzer 7.4.1

As of FortiAnalyzer 7.4.1, kernel and rootfs are encrypted. OpenXen in PV mode tries to unzip the kernel and rootfs, but it will fail. Therefore, OpenXen in PV mode cannot be used when deploying or upgrading to FortiAnalyzer 7.4.1. Only HVM (hardware virtual machine) mode is supported for OpenXen in FortiAnalyzer 7.4.1.

Default GUI theme changed

As of FortiAnalyzer 7.4.1, the default GUI theme is *Jade*. The default theme can be changed from *System Settings > Settings*.

FortiManager Features removed

FortiAnalyzer 7.2.1 and later no longer supports FortiManager Features. If you have FortiManager Features enabled before upgrading to FortiAnalyzer 7.2.1, FortiManager Features will be permanently disabled after upgrading to FortiAnalyzer 7.2.1.

Setup wizard requires FortiCare registration

Starting in FortiAnalyzer 7.2.1, the FortiAnalyzer Setup wizard requires you to complete the *Register with FortiCare* step before you can access the FortiAnalyzer appliance or VM. Previously the step was optional.

For FortiAnalyzer units operating in a closed environment, contact customer service to receive an entitlement file, and then load the entitlement file to FortiAnalyzer by using the CLI.

When FortiManager is managing FortiAnalyzer in a closed environment, FortiManager contains the FortiAnalyzer contract information, and you can point FortiAnalyzer to FortiManager.

Hyperscale firewall mode

FortiAnalyzer does not support logs from the following models when they have hyperscale firewall mode and netflow enabled:

- FortiGate-1800F
- FortiGate-1801F
- FortiGate-2600F
- FortiGate-2601F
- FortiGate-4200F
- FortiGate-4201F
- FortiGate-4400F
- FortiGate-4401F

FortiAnalyzer only supports logs when the normal firewall mode with standard FortiGate logging are enabled.

Modifying the interface status with the CLI

Starting in version 7.0.1, the CLI to modify the interface status has been changed from up/down to enable/disable.

For example:

```
config system interface
  edit port2
    set status <enable/disable>
  next
end
```

Citrix XenServer default limits and upgrade

Citrix XenServer limits ramdisk to 128M by default. However the FAZ-VM64-XEN image is larger than 128M. Before updating to FortiAnalyzer 6.4, increase the size of the ramdisk setting on Citrix XenServer.

To increase the size of the ramdisk setting:

1. On Citrix XenServer, run the following command:
`xenstore-write /mh/limits/pv-ramdisk-max-size 536,870,912`
2. Confirm the setting is in effect by running `xenstore-ls`.

`limits = ""`
`pv-kernel-max-size = "33554432"`
`pv-ramdisk-max-size = "536,870,912"`
`boot-time = ""`

3. Remove the pending files left in `/run/xen/pygrub`.



The ramdisk setting returns to the default value after rebooting.

FortiAnalyzer VM upgrade requires more memory

When upgrading FortiAnalyzer VM units from a previous version to FortiAnalyzer 7.2.2 or higher, the upgrade may fail because of memory allocation. As of FortiAnalyzer 7.2.2, FortiAnalyzer VM requires 16 GB of RAM and 4 CPU.

Workaround: Before upgrading FortiAnalyzer VM to FortiAnalyzer 7.2.2, change the memory allocation to 16 GB of RAM.

Maximum ADOM limits for FortiAnalyzer

FortiAnalyzer hardware devices and VMs display a warning when the maximum number of ADOMs is reached. For more details, see [Appendix A - Default and maximum number of ADOMs supported on page 58](#).

Port 8443 reserved

Port 8443 is reserved for https-logging from FortiClient EMS for Chromebooks. See also [FortiAnalyzer 7.0 Ports Reference](#) on the Docs Library.

Hyper-V FortiAnalyzer-VM running on an AMD CPU

A Hyper-V FAZ-VM running on a PC with an AMD CPU may experience a kernel panic. Fortinet recommends running VMs on an Intel-based PC.

SSLv3 on FortiAnalyzer-VM64-AWS

Due to known vulnerabilities in the SSLv3 protocol, FortiAnalyzer-VM64-AWS only enables TLSv1 by default. All other models enable both TLSv1 and SSLv3. If you wish to disable SSLv3 support, please run:

```
config system global
    set ssl-protocol tls1
end
```

Upgrade Information



Prior to upgrading your FortiAnalyzer, please review the FortiAnalyzer Upgrade Guide in detail as it includes all of the necessary steps and associated details required to upgrade your FortiAnalyzer device or VM, including recommended upgrade paths. See the *FortiAnalyzer Upgrade Guide* in the [Fortinet Document Library](#).

This section contains the following topics:

- [Downgrading to previous firmware versions on page 17](#)
- [Firmware image checksums on page 17](#)
- [FortiAnalyzer VM firmware on page 17](#)
- [SNMP MIB files on page 19](#)

Downgrading to previous firmware versions

FortiAnalyzer does not provide a full downgrade path. You can downgrade to a previous firmware release by using the GUI or CLI, but doing so results in configuration loss. A system reset is required after the firmware downgrade process has completed. To reset the system, use the following CLI commands via a console port connection:

```
execute reset {all-settings | all-except-ip}  
execute format disk
```

Firmware image checksums

The MD5 checksums for all Fortinet software and firmware releases are available at the Customer Service & Support portal, <https://support.fortinet.com>. After logging in, go to *Download > Firmware Image Checksums*, enter the image file name including the extension, and select *Get Checksum Code*.

FortiAnalyzer VM firmware

Fortinet provides FortiAnalyzer VM firmware images for Amazon AWS, Amazon AWSOnDemand, Citrix and Open Source XenServer, Linux KVM, Microsoft Hyper-V Server, and VMware ESX/ESXi virtualization environments.

Amazon Web Services

- The 64-bit Amazon Machine Image (AMI) is available on the AWS marketplace.

Citrix XenServer and Open Source XenServer

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.out.OpenXen.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains the QCOW2 file for the Open Source Xen Server.
- `.out.CitrixXen.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains the Citrix XenServer Virtual Appliance (XVA), Virtual Hard Disk (VHD), and OVF files.

Google Cloud Platform

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.out.gcp.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation.

Linux KVM

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.out.kvm.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains QCOW2 that can be used by qemu.

Microsoft Azure

The files for Microsoft Azure have AZURE in the filenames, for example `<product>_VM64_AZURE-v<number>-build<number>-FORTINET.out.hyperv.zip`.

- `.out`: Download the firmware image to upgrade your existing FortiAnalyzer VM installation.

Microsoft Hyper-V Server

The files for Microsoft Hyper-V Server have HV in the filenames, for example, `<product>_VM64_HV-v<number>-build<number>-FORTINET.out.hyperv.zip`.

- `.out`: Download the firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.hyperv.zip`: Download the package for a new FortiAnalyzer VM installation. This package contains a Virtual Hard Disk (VHD) file for Microsoft Hyper-V Server.

Oracle Private Cloud

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.out.opc.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation.

VMware ESX/ESXi

- `.out`: Download the 64-bit firmware image to upgrade your existing VM installation.
- `.ovf.zip`: Download either the 64-bit package for a new VM installation. This package contains an Open Virtualization Format (OVF) file for VMware and two Virtual Machine Disk Format (VMDK) files used by the OVF file during deployment.



For more information, see the [FortiAnalyzer Data Sheet](#) available on the Fortinet web site. VM installation guides are available in the [Fortinet Document Library](#).

SNMP MIB files

You can download the *FORTINET-FORTIMANAGER-FORTIANALYZER.mib* MIB file in the firmware image file folder. The Fortinet Core MIB file is located in the main FortiAnalyzer version 5.00 file folder.

Product Integration and Support

This section lists FortiAnalyzer 7.4.10 support of other Fortinet products. It also identifies what FortiAnalyzer features are supported for managed platforms and what languages FortiAnalyzer supports. It also lists which Fortinet models can be managed by FortiAnalyzer.

The section contains the following topics:

- [Supported software on page 20](#)
- [Feature support on page 27](#)
- [Language support on page 28](#)
- [Supported models on page 29](#)

Supported software

FortiAnalyzer 7.4.10 supports the following software:

- [Web browsers on page 21](#)
- [FortiOS and FortiOS Carrier on page 21](#)
- [FortiADC on page 21](#)
- [FortiAnalyzer on page 22](#)
- [FortiAuthenticator on page 22](#)
- [FortiCache on page 22](#)
- [FortiCASB on page 22](#)
- [FortiClient on page 23](#)
- [FortiDDoS on page 23](#)
- [FortiDeceptor on page 23](#)
- [FortiFirewall and FortiFirewallCarrier on page 23](#)
- [FortiIsolator on page 24](#)
- [FortiMail on page 24](#)
- [FortiManager on page 24](#)
- [FortiNAC on page 24](#)
- [FortiNDR on page 24](#)
- [FortiPAM on page 25](#)
- [FortiPortal on page 25](#)
- [FortiProxy on page 25](#)
- [FortiSandbox on page 25](#)
- [FortiSASE on page 26](#)
- [FortiSOAR on page 26](#)
- [FortiSRA on page 26](#)

- [FortiSwitch ATCA](#) on page 26
- [FortiToken](#) on page 26
- [FortiWeb](#) on page 26
- [Virtualization](#) on page 27



To confirm that a device model or firmware version is supported by the current firmware version running on FortiAnalyzer, run the following CLI command:
`diagnose dvm supported-platforms list`



Always review the Release Notes of the supported platform firmware version before upgrading your device.

Web browsers

FortiAnalyzer 7.4.10 supports the following web browsers:

- Google Chrome version 144
- Microsoft Edge version 144
- Mozilla Firefox 147

Other web browsers may function correctly, but are not supported by Fortinet.

FortiOS and FortiOS Carrier



The *FortiAnalyzer Release Notes* communicate support for FortiOS versions that are available at the time of the FortiAnalyzer 7.4.10 release. For additional information about other supported FortiOS versions, please refer to the FortiAnalyzer compatibility chart in the [Fortinet Document Library](#).

See [FortiAnalyzer compatibility with FortiOS](#).

FortiAnalyzer 7.4.10 supports the following versions of FortiOS and FortiOS Carrier:

- 7.4.0 to 7.4.11
- 7.2.0 to 7.2.13
- 7.0.0 to 7.0.19
- 6.4.0 to 6.4.16
- 6.2.0 to 6.2.16
- 6.0.0 to 6.0.18

FortiADC

FortiAnalyzer 7.4.10 supports the following versions of FortiADC:

- 7.4.0 and later
- 7.2.0 and later
- 7.1.0 and later
- 7.0.0 and later
- 6.2.0 and later
- 6.1.0 and later
- 6.0.0 and later

FortiAnalyzer

FortiAnalyzer 7.4.10 supports the following versions of FortiAnalyzer:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

FortiAuthenticator

FortiAnalyzer 7.4.10 supports the following versions of FortiAuthenticator:

- 6.6.0 and later
- 6.5.0 and later
- 6.4.0 and later
- 6.3.0 and later
- 6.2.0 and later
- 6.1.0 and later
- 6.0.0 and later

FortiCache

FortiAnalyzer 7.4.10 supports the following versions of FortiCache:

- 4.2.0 and later
- 4.1.0 and later
- 4.0.0 and later

FortiCASB

FortiAnalyzer 7.4.10 supports the following versions of FortiCASB:

- 23.2.0 and later

FortiClient

FortiAnalyzer 7.4.10 supports the following versions of FortiClient:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later
- 6.4.0 and later

When using FortiClient with FortiAnalyzer, it is recommended to upgrade both to their latest versions. The versions between the two products should match. For example, if using FortiAnalyzer 7.2.0, use FortiClient 7.2.0.

FortiDDoS

FortiAnalyzer 7.4.10 supports the following versions of FortiDDoS:

- 7.0.0 and later
- 6.6.0 and later
- 6.5.0 and later
- 6.4.0 and later
- 5.7.0 and later
- 5.6.0 and later

Limited support. For more information, see [Feature support on page 27](#).

FortiDeceptor

FortiAnalyzer 7.4.10 supports the following versions of FortiDeceptor:

- 5.3.0 and later
- 5.2.0 and later
- 5.1.0 and later
- 5.0.0 and later
- 4.3.0 and later

FortiFirewall and FortiFirewallCarrier

FortiAnalyzer 7.4.10 supports the following versions of FortiFirewall and FortiFirewallCarrier:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later
- 6.4.0 and later

- 6.2.0 and later
- 6.0.0 and later

Fortisolator

FortiAnalyzer 7.4.10 supports the following versions of Fortisolator:

- 2.4.0 and later

FortiMail

FortiAnalyzer 7.4.10 supports the following versions of FortiMail:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later
- 6.4.0 and later
- 6.2.0 and later

FortiManager

FortiAnalyzer 7.4.10 supports the following versions of FortiManager:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

FortiNAC

FortiAnalyzer 7.4.10 supports the following versions of FortiNAC:

- 9.4.0 and later
- 9.2.0 and later
- 9.1.0 and later
- 7.4.0 and later
- 7.2.0 and later

FortiNDR

FortiAnalyzer 7.4.10 supports the following versions of FortiNDR:

- 7.4.0 and later
- 7.2.0 and later
- 7.1.0 and later
- 7.0.0 and later

FortiPAM

FortiAnalyzer 7.4.10 supports the following versions of FortiPAM:

- 1.8.0 and later
- 1.7.0 and later
- 1.6.0 and later
- 1.5.0 and later
- 1.4.0 and later
- 1.3.0 and later
- 1.2.0 and later
- 1.1.0 and later
- 1.0.0 and later

FortiPortal

For more information about compatibility with FortiPortal, see *FortiPortal Compatibility* in the [Fortinet Document Library](#).

FortiProxy

FortiAnalyzer 7.4.10 supports the following versions of FortiProxy:

- 7.4.0 to 7.4.13
- 7.2.0 to 7.2.15
- 7.0.0 to 7.0.22
- 2.0.0 to 2.0.5
- 1.2.0 to 1.2.13
- 1.1.0 to 1.1.6
- 1.0.0 to 1.0.7

FortiSandbox

FortiAnalyzer 7.4.10 supports the following versions of FortiSandbox:

- 4.4.0 and later
- 4.2.0 and later

- 4.0.0 and later
- 3.2.0 and later

FortiSASE

For more information about compatibility, see the [FortiSASE Release Notes](#).

FortiSOAR

FortiAnalyzer 7.4.10 supports the following versions of FortiSOAR:

- 7.4.0 and later
- 7.3.0 and later
- 7.2.0 and later

FortiSRA

FortiAnalyzer 7.4.10 supports the following versions of FortiSRA:

- 1.1.0 and later
- 1.0.0 and later

FortiSwitch ATCA

FortiAnalyzer 7.4.10 supports the following versions of FortiSwitch ATCA:

- 5.2.0 and later
- 5.0.0 and later
- 4.3.0 and later

FortiToken

FortiAnalyzer 7.4.10 supports the following versions of FortiToken:

- 3.0.0 and later

FortiAnalyzer supports logs from FortiToken Cloud.

FortiWeb

FortiAnalyzer 7.4.10 supports the following versions of FortiWeb:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

Virtualization

FortiAnalyzer 7.4.10 supports the following virtualization software:

Public Cloud

- Amazon Web Service AMI, Amazon EC2, Amazon EBS
- Alibaba Cloud
- Google Cloud Platform
- IBM Cloud
- Microsoft Azure
- Oracle Cloud Infrastructure

Private Cloud

- Citrix XenServer 8.2 and later
- OpenSource XenServer 4.2.5
- Microsoft Hyper-V Server 2016, 2019, and 2022
- Nutanix
 - AHV 20220304 and later
 - AOS 6.5 and later
 - NCC 4.6 and later
 - LCM 3.0 and later
- RedHat 9.1
 - Other versions and Linux KVM distributions are also supported
- VMware ESXi versions 6.5 and later

Feature support

The following table lists FortiAnalyzer feature support for log devices.

Platform	Log View	FortiView	Event Management	Reports
FortiGate	✓	✓	✓	✓
FortiCarrier	✓	✓	✓	✓

Platform	Log View	FortiView	Event Management	Reports
FortiADC	✓		✓	✓
FortiAnalyzer	✓		✓	
FortiAuthenticator	✓			
FortiCache	✓		✓	✓
FortiClient registered to FortiClient EMS	✓	✓		✓
FortiClient registered to FortiGate	✓	✓		✓
FortiDDoS	✓	✓	✓	✓
FortiDeceptor	✓			
FortiFirewall	✓	✓	✓	✓
FortiMail	✓		✓	✓
FortiManager	✓		✓	
FortiNAC	✓			
FortiNDR	✓	✓	✓	✓
FortiPAM	✓		✓	✓
FortiProxy	✓	✓	✓	✓
FortiSandbox	✓		✓	✓
FortiSOAR	✓		✓	✓
FortiSRA	✓		✓	✓
FortiWeb	✓		✓	✓
Syslog	✓		✓	✓

Language support

The following table lists FortiAnalyzer language support information.

Language	GUI	Reports
English	✓	✓

Language	GUI	Reports
Chinese (Simplified)	✓	✓
Chinese (Traditional)	✓	✓
French	✓	✓
Hebrew		✓
Hungarian		✓
Japanese	✓	✓
Korean	✓	✓
Portuguese		✓
Russian		✓
Spanish	✓	✓

To change the FortiAnalyzer language setting, go to *System Settings > Admin > Admin Settings*, in *Administrative Settings > Language* select the desired language on the drop-down menu. The default value is *Auto Detect*.

Russian, Hebrew, and Hungarian are not included in the default report languages. You can create your own language translation files for these languages by exporting a predefined language from FortiAnalyzer, modifying the text to a different language, saving the file as a different language name, and then importing the file into FortiAnalyzer. For more information, see the *FortiAnalyzer Administration Guide*.

Supported models

The following tables list which FortiGate, FortiCarrier, FortiDDoS, FortiAnalyzer, FortiMail, FortiSandbox, FortiSwitch, FortiWeb, FortiCache, FortiProxy, FortiAuthenticator, and other Fortinet product models and firmware versions can send logs to a FortiAnalyzer running version 7.4.10.



Software license activated LENC devices are supported, if their platforms are in the supported models list. For example, support of FG-3200D indicates support of FG-3200D-LENC.

This section contains the following topics:

- [FortiGate models on page 30](#)
- [FortiGate special branch models on page 37](#)
- [FortiCarrier models on page 41](#)
- [FortiCarrier special branch models on page 44](#)
- [FortiADC models on page 46](#)
- [FortiAnalyzer models on page 47](#)
- [FortiAuthenticator models on page 48](#)

- [FortiCache models on page 48](#)
- [FortiDDoS models on page 49](#)
- [FortiDeceptor models on page 49](#)
- [FortiFirewall models on page 49](#)
- [FortiFirewallCarrier models on page 50](#)
- [FortiIsolator models on page 51](#)
- [FortiMail models on page 51](#)
- [FortiNAC models on page 52](#)
- [FortiNDR models on page 53](#)
- [FortiPAM models on page 53](#)
- [FortiProxy models on page 53](#)
- [FortiSandbox models on page 54](#)
- [FortiSOAR models on page 54](#)
- [FortiSRA models on page 54](#)
- [FortiSwitch ATCA models on page 54](#)
- [FortiWeb models on page 55](#)

FortiGate models

The following FortiGate models are released with FortiOS firmware. For information about supported FortiGate models on special branch releases of FortiOS firmware, see [FortiGate special branch models on page 37](#).

Model	Firmware Version
FortiGate: FortiGate-30G, FortiGate-31G, FortiGate-40F, FortiGate-40F-3G4G, FortiGate-50G, FortiGate-50G-5G, FortiGate-50G-DSL, FortiGate-50G-SFP, FortiGate-50G-SFP-POE, FortiGate-51G, FortiGate-51G-5G, FortiGate-51G-SFP-POE, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-70F, FortiGate-70G, FortiGate-70G-POE, FortiGate-71F, FortiGate-71G, FortiGate-71G-POE, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-DSL, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-90G, FortiGate-91E, FortiGate-91G, FortiGate-100F, FortiGate-101F, FortiGate-120G, FortiGate-121G, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-200G, FortiGate-201E, FortiGate-201F, FortiGate-201G, FortiGate-300E, FortiGate-301E, FortiGate-400E, FortiGate-400F, FortiGate-400E-Bypass, FortiGate-401E, FortiGate-401F, FortiGate-500E, FortiGate-501E, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-700G, FortiGate-701G, FortiGate-800D, FortiGate-900D, FortiGate-900G, FortiGate-901G, FortiGate-1000D, FortiGate-1000F, FortiGate-1001F, FortiGate-1100E, FortiGate-1101E, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3200F, FortiGate-3201F, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3600E-DC, FortiGate-3601E, FortiGate-3700D, FortiGate-3700F, FortiGate-3701F, FortiGate-3800D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate-4800F, FortiGate-4801F, FortiGate-4801F-NEBS FortiGate 5000 Series: FortiGate-5001E, FortiGate-5001E1 FortiGate 6000 Series: FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC FortiGate 7000 Series: FortiGate-7000E, FortiGate-7000F, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC FortiGate DC: FortiGate-400F-DC, FortiGate-401F-DC, FortiGate-401E-DC, FortiGate-800D-DC, FortiGate-900G-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-DC, FortiGate-3000F-ACDC, FortiGate-3001F-DC, FortiGate-3001F-ACDC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC, FortiGate-4801F-DC, FortiGate-4801F-DC-NEBS	7.4

Model	Firmware Version
FortiWiFi: FWF-30G, FWF-31G, FWF-40F, FWF-40F-3G4G, FWF-50G, FWF-50G-5G, FWF-50G-DSL, FWF-50G-SFP, FWF-51G, FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-70G, FWF-70G-POE, FWF-71G, FWF-80F-2R, FWF-81F-2R, FWF-80F-2R-3G4G-DSL, FWF-81F-2R-3G4G-DSL, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE	
FortiGate VM: FortiGate-ARM64-AWS, FortiGate-ARM64-Azure, FortiGate-ARM64-GCP, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-Xen	
FortiGate Rugged: FGR-50G-5G, FGR-60F, FGR-60F-3G4G, FGR-70F, FGR-70F-3G4G, FGR-70G, FGR-70G-5G-Dual	
FortiGate: Container-FortiOS, FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-70F, FortiGate-70G, FortiGate-70G-POE, FortiGate-71F, FortiGate-71G, FortiGate-71G-POE, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-DSL, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-90G, FortiGate-91E, FortiGate-91G, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-120G, FortiGate-121G, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300E, FortiGate-301E, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-400F, FortiGate-401E, FortiGate-401F, FortiGate-500E, FortiGate-501E, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-800D, FortiGate-900D, FortiGate-900G, FortiGate-901G, FortiGate-1000D, FortiGate-1000F, FortiGate-1001F, FortiGate-1100E, FortiGate-1101E, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3200F, FortiGate-3201F, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3601E, FortiGate-3700D, FortiGate-3700F, FortiGate-3701F, FortiGate-3800D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate-4800F, FortiGate-4801F, FortiGate-4801F-NEBS	7.2
FortiGate 5000 Series: FortiGate-5001E, FortiGate-5001E1	
FortiGate 6000 Series: FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC	
FortiGate 7000 Series: FortiGate-7000E, FortiGate-7000F, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC	

Model	Firmware Version
FortiGate DC: FortiGate-400F-DC, FortiGate-401F-DC, FortiGate-401E-DC, FortiGate-800D-DC, FortiGate-900G-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-DC, FortiGate-3000F-ACDC, FortiGate-3001F-DC, FortiGate-3001F-ACDC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC, FortiGate-4800F-DC, FortiGate-4801F-DC, FortiGate-4801F-DC-NEBS FortiWiFi: FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-70G, FWF-71G, FWF-80F-2R, FWF-80F-2R-3G4G-DSL, FWF-81F-2R, FWF-81F-2R-3G4G-DSL, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE FortiGate VM: FortiGate-ARM64-AWS, FortiGate-ARM64-Azure, FortiGate-ARM64-GCP, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager FortiOS-VM: FOS-VM64, FOS-VM64-HV, FOS-VM64-KVM, FOS-VM64-Xen FortiGate Rugged: FGR-60F, FGR-60F-3G4G, FGR-70F, FGR-70F-3G4G	
FortiGate: FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-70F, FortiGate-71F, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-91E, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300D, FortiGate-300E, FortiGate-301E, FortiGate-400D, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-400F, FortiGate-401E, FortiGate-401F, FortiGate-500D, FortiGate-500E, FortiGate-501E, FortiGate-600D, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-800D, FortiGate-900D, FortiGate-1000D, FortiGate-1100E, FortiGate-1101E, FortiGate-1200D, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3601E, FortiGate-3700D, FortiGate-3800D, FortiGate-3810D, FortiGate-3815D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate 5000 Series: FortiGate-5001D, FortiGate-5001E, FortiGate-5001E1	7.0

Model	Firmware Version
FortiGate DC: FortiGate-400F-DC, FortiGate-401F-DC, FortiGate-401E-DC, FortiGate-800D-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-DC, FortiGate-3000F-ACDC, FortiGate-3001F-DC, FortiGate-3001F-ACDC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3810D-DC, FortiGate-3815D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC FortiWiFi: FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-80F-2R, FWF-81F-2R, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE FortiGate VM: FortiGate-ARM64-AWS, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager FortiOS-VM: FOS-VM64, FOS-VM64-HV, FOS-VM64-KVM, FOS-VM64-Xen FortiGate Rugged: FGR-60F, FGR-60F-3G4G	
FortiGate: FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-91E, FortiGate-100D, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300D, FortiGate-300E, FortiGate-301E, FortiGate-400D, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-401E, FortiGate-500D, FortiGate-500E, FortiGate-501E, FortiGate-600D, FortiGate-600E, FortiGate-601E, FortiGate-800D, FortiGate-900D, FortiGate-1000D, FortiGate-1100E, FortiGate-1101E, FortiGate-1200D, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3100D, FortiGate-3200D, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3600E, FortiGate-3601E, FortiGate-3700D, FortiGate-3800D, FortiGate-3810D, FortiGate-3815D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate 5000 Series: FortiGate-5001D, FortiGate-5001E, FortiGate-5001E1 FortiGate DC: FortiGate-401E-DC, FortiGate-800D-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3810D-DC, FortiGate-3815D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC	6.4

Model	Firmware Version
FortiGate Hardware Low Encryption: FortiGate-100D-LENC FortiWiFi: FWF-40F, FWF-40F-3G4G, FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-80F-2R, FWF-81F-2R, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE FortiGate VM: FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-ALIONDEMAND, FortiGate-VM64-AWS, FortiGate-VM64-AZUREONDEMAND, FortiGate-VM64-Azure, FortiGate-VM64-GCP, VM64-GCPONDEMAND, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager FortiOS-VM: FOS-VM64, FOS-VM64-HV, FOS-VM64-KVM, FOS-VM64-Xen FortiGate Rugged: FGR-60F, FGR-60F-3G4G	
FortiGate: FortiGate-30E, FortiGate-30E-3G4G-GBL, FortiGate-30E-3G4G-INTL, FortiGate-30E-3G4G-NAM, FortiGate-40F, FortiGate-40F-3G4G, FortiGate-50E, FortiGate-51E, FortiGate-52E, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-91E, FortiGate-92D, FortiGate-100D, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-140D, FortiGate-140D-POE, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-300D, FortiGate-300E, FortiGate-301E, FortiGate-400D, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-401E, FortiGate-500D, FortiGate-500E, FortiGate-501E, FortiGate-600D, FortiGate-600E, FortiGate-601E, FortiGate-800D, FortiGate-900D, FortiGate-1000D, FortiGate-1100E, FortiGate-1101E, FortiGate-1200D, FortiGate-1500D, FortiGate-1500DT, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-3000D, FortiGate-3100D, FortiGate-3200D, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3600E, FortiGate-3700D, FortiGate-3800D, FortiGate-3810D, FortiGate-3815D, FortiGate-3960E, FortiGate-3980E FortiGate 5000 Series: FortiGate-5001D, FortiGate-5001E, FortiGate-5001E1 FortiGate DC: FortiGate-401E-DC, FortiGate-800D-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-2201E-ACDC, FortiGate-3000D-DC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3810D-DC, FortiGate-3815D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC FortiGate Hardware Low Encryption: FortiGate-100D-LENC FortiWiFi: FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-40F, FWF-40F-3G4G, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-80F-2R, FortiWiFi-80F-2R-3G4G-DSL, FWF-81F-2R, FWF-81F-2R-POE	6.2

Model	Firmware Version
FortiGate VM: FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-ALIONDEMAND, FortiGate-VM64-AWS, FortiGate-VM64-AWSONDEMAND, FortiGate-VM64-AZUREONDEMAND, FortiGate-VM64-Azure, FortiGate-VM64-GCP, VM64-GCPONDEMAND, FortiGate-VM64-HV, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager FortiOS-VM: FOS-VM64, FOS-VM64-HV, FOS-VM64-KVM, FOS-VM64-Xen FortiGate Rugged: FGR-30D, FGR-35D, FGR-60F, FGR-60F-3G4G, FGR-90D	
FortiGate: FortiGate-30D, FortiGate-30D-POE, FortiGate-30E, FortiGate-30E-3G4G-GBL, FortiGate-30E-3G4G-INTL, FortiGate-30E-3G4G-NAM, FortiGate-50E, FortiGate-51E, FortiGate-52E, FortiGate-60D, FortiGate-60D-POE, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-70D, FortiGate-70D-POE, FortiGate-80C, FortiGate-80CM, FortiGate-80D, FortiGate-80E, FortiGate-80E-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-90D, FortiGate-90D-POE, FortiGate-90E, FortiGate-91E, FortiGate-92D, FortiGate-94D-POE, FortiGate-98D-POE, FortiGate-100D, FortiGate-100E, FortiGate-100EF, FortiGate-101E, FortiGate-140D, FortiGate-140D-POE, FortiGate-140E, FortiGate-140E-POE, FortiGate-200D, FortiGate-200D-POE, FortiGate-200E, FortiGate-201E, FortiGate-240D, FortiGate-240D-POE, FortiGate-280D-POE, FortiGate-300D, FortiGate-300E, FortiGate-301E, FortiGate-400D, FortiGate-400E, FortiGate-401E, FortiGate-500D, FortiGate-500E, FortiGate-501E, FortiGate-600C, FortiGate-600D, FortiGate-600E, FortiGate-601E, FortiGate-800C, FortiGate-800D, FortiGate-900D, FortiGate-1000C, FortiGate-1000D, FortiGate-1200D, FortiGate-1500D, FortiGate-1500DT, FortiGate-2000E, FortiGate-2500E, FortiGate-3000D, FortiGate-3100D, FortiGate-3200D, FortiGate-3400E, FortiGate-3401E, FortiGate-3600C, FortiGate-3600E, FortiGate-3700D, FortiGate-3800D, FortiGate-3810D, FortiGate-3815D, FortiGate-3960E, FortiGate-3980E FortiGate 5000 Series: FortiGate-5001D, FortiGate-5001E, FortiGate-5001E1 FortiGate 6000 Series: FortiGate-6000F, FortiGate-6300F, FortiGate-6301F, FortiGate-6500F, FortiGate-6501F FortiGate 7000 Series: FortiGate-7000E, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E FortiGate DC: FortiGate-80C-DC, FortiGate-401E-DC, FortiGate-600C-DC, FortiGate-800C-DC, FortiGate-1000C-DC, FortiGate-1500D-DC, FortiGate-3000D-DC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600C-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3810D-DC, FortiGate-3815D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-6000F-DC, FortiGate-6300F-DC, FortiGate-6301F-DC, FortiGate-6500F-DC, FortiGate-6501F-DC, FortiGate-7060E-8-DC FortiGate Hardware Low Encryption: FortiGate-80C-LENC, FortiGate-100D-LENC, FortiGate-600C-LENC, FortiGate-1000C-LENC Note: All license-based LENC is supported based on the FortiGate support list.	6.0

Model	Firmware Version
FortiWiFi: FWF-30D, FWF-30D-POE, FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-41F, FWF-41F-3G4G, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60D, FWF-60D-POE, FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-61E, FWF-80CM, FWF-81CM, FWF-90D, FWF-90D-POE, FWF-92D FortiGate VM: FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-ALIONDEMAND, FortiGate-VM64-AWS, FortiGate-VM64-AWSONDEMAND, FortiGate-VM64-AZUREONDEMAND, FortiGate-VM64-Azure, FortiGate-VM64-GCP, VM64-GCPONDEMAND, FortiGate-VM64-HV, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager FortiOS-VM: FOS-VM64, FOS-VM64-KVM, FOS-VM64-Xen FortiGate Rugged: FGR-30D, FGR-30D-ADSL-A, FGR-35D, FGR-60D, FGR-90D	

FortiGate special branch models

The following FortiGate models are released on special branches of FortiOS. FortiAnalyzer version 7.4.10 supports these models on the identified FortiOS version and build number.

For information about supported FortiGate models released with FortiOS firmware, see [FortiGate models on page 30](#).

FortiOS 7.4

FortiGate Model	FortiOS Version	FortiOS Build
FortiGate-70G-POE-5G, FortiGate-71G-POE-5G	7.4.8	6345
FortiGate-3800G	7.4.8	6564
FortiGate-3801G	7.4.8	6438
FortiGateRugged-60G	7.4.8	6300
FortiGateRugged-70G-5G	7.4.8	6340

FortiOS 7.2

FortiGate Model	FortiOS Version	FortiOS Build
FortiGate-30G, FortiGate-31G	7.2.12	6666
FortiGate-70G, FortiGate-70G-POE	7.2.12	6659
FortiGate-71G	7.2.11	6570

FortiGate Model	FortiOS Version	FortiOS Build
FortiGate-71G-POE	7.2.11	6559
FortiGate-200G, FortiGate-201G	7.2.12	6660
FortiGate-700G, FortiGate-701G	7.2.11	6531
FortiWiFi-30G, FortiWiFi-31G	7.2.12	6662
FortiWiFi-70G, FortiWiFi-70G-POE FortiWiFi-71G	7.2.11	6566

FortiOS 7.0

FortiGate Model	FortiOS Version	FortiOS Build
FortiGate-50G, FortiGate-50G-5G, FortiGate-50G-DSL, FortiGate-50G-SFP, FortiGate-51G, FortiGate-51G-5G, FortiGate-51G-SFP-POE	7.0.17	7592
FortiGate-80F-DSL	7.0.17	7558
FortiGate-90G, FortiGate-91G	7.0.17	7558
FortiGate-120G, FortiGate-121G	7.0.16	7534
FortiGate-900G, FortiGate-900G-DC, FortiGate-901G, FortiGate-901G-DC	7.0.17	7551
FortiGate-1000F, FortiGate-1001F	7.0.17	7552
FortiGate-3200F, FortiGate-3201F	7.0.17	7553
FortiGate-3700F, FortiGate-3701F	7.0.17	7553
FortiGate-4800F, FortiGate-4800F-DC FortiGate-4801F, FortiGate-4801F-DC, FortiGate-4801F-DC-NEBS, FortiGate- 4801F-NEBS	7.0.17	7553
FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC	7.0.16	0280
FortiGate-7000E, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC	7.0.16	0280

FortiGate Model	FortiOS Version	FortiOS Build
FortiGate-7000F, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC	7.0.16	0280
FortiGateRugged-50G-5G	7.0.17	7577
FortiGateRugged-70F, FortiGateRugged-70F-3G4G	7.0.17	7557
FortiGateRugged-70G	7.0.15	7496
FortiGateRugged-70G-5G-Dual	7.0.16	7550
FortiWiFi-50G, FortiWiFi-50G-5G, FortiWiFi-50G-DSL, FortiWiFi-50G-SFP	7.0.17	7592
FortiWiFi-51G	7.0.17	7592
FortiWiFi-51G-5G	7.0.17	7537
FortiWiFi-80F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-DSL	7.0.17	7558

FortiOS 6.4

FortiGate Model	FortiOS Version	FortiOS Build
FortiGate-400F, FortiGate-401F	6.4.13	5455
FortiGate-600F, FortiGate-601F	6.4.13	5455
FortiGate-3500F	6.4.6	5886
FortiGate-3501F	6.4.6	6132
FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC	6.4.13	1926
FortiGate-7000E, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC	6.4.13	1926
FortiGate-7000F, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC	6.4.13	1926

FortiGate Model	FortiOS Version	FortiOS Build
FortiWiFi-80F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-DSL	6.4.7	6690

FortiOS 6.2

FortiGate Model	FortiOS Version	FortiOS Build
FortiGate-80D	6.2.13	5238
FortiGate-200F, FortiGate-201F	6.2.13	7249
FortiGate-1800F, FortiGate-1800F-DC FortiGate-1801F, FortiGate-1801F-DC	6.2.9	7197
FortiGate-2600F, FortiGate-2600F-DC FortiGate-2601F, FortiGate-2601F-DC	6.2.9	7197
FortiGate-4200F, FortiGate-4200F-DC FortiGate-4201F, FortiGate-4201F-DC	6.2.9	7197
FortiGate-4400F, FortiGate-4400F-DC FortiGate-4401F, FortiGate-4401F-DC	6.2.9	7197
FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC	6.2.13	1271
FortiGate-7000E, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC FortiGate-7000F, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2- DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F- DC	6.2.13	1271
FortiWiFi-80F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-DSL	6.2.6	7219

FortiOS 6.0

FortiGate Model	FortiOS Version	FortiOS Build
FortiGate-30E-3G4G-GBL	6.0	5486
FortiGate-40F, FortiGate-40F-3G4G	6.0	6887

FortiGate Model	FortiOS Version	FortiOS Build
FortiGate-41F	6.0.6	6445
FortiGate-41F-3G4G	6.0.6	6674
FortiGate-60F, FortiGate-61F	6.0	6890
FortiGate-100F, FortiGate-101F	6.0	6890
FortiGate-1100E, FortiGate-1100E-DC, FortiGate-1101E	6.0	6886
FortiGate-1800F, FortiGate-1800F-DC FortiGate-1801F, FortiGate-1801F-DC	6.0	6889
FortiGate-2200E, FortiGate-2201E, FortiGate-2201E-ACDC	6.0	6888
FortiGate-3300E, FortiGate-3301E	6.0	6888
FortiWiFi-40F, FortiWiFi-40F-3G4G	6.0	6887
FortiWiFi-41F	6.0.6	6674
FortiWiFi-41F-3G4G	6.0.6	6445
FortiWiFi-60F, FortiWiFi-61F	6.0	6890

FortiCarrier models

The following FortiCarrier models are released with FortiCarrier firmware.

For information about supported FortiCarrier models on special branch releases of FortiCarrier firmware, see [FortiCarrier special branch models on page 44](#).

Model	Firmware Version
FortiCarrier: FortiCarrier-2600F, FortiCarrier-2601F, FortiCarrier-3000D, FortiCarrier-3000F, FortiCarrier-3001F, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3200F, FortiCarrier-3201F, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3700F, FortiCarrier-3701F, FortiCarrier-3800D, FortiCarrier-3960E, FortiCarrier-3980E, FortiCarrier-4200F, FortiCarrier-4201F, FortiCarrier-4400F, FortiCarrier-4401F, FortiCarrier-4800F, FortiCarrier-4801F, FortiCarrier-4801F-NEBS FortiCarrier 5000 Series: FortiCarrier-5001E, FortiCarrier-5001E1 FortiCarrier 6000 Series: FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC	7.4

Model	Firmware Version
FortiCarrier 7000 Series: FortiCarrier-7000E, FortiCarrier-7000F, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC FortiCarrier-DC: FortiCarrier-2600F-DC, FortiCarrier-2601F-DC, FortiCarrier-3000D-DC, FortiCarrier-3000F-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC, FortiCarrier-4200F-DC, FortiCarrier-4201F-DC, FortiCarrier-4400F-DC, FortiCarrier-4401F-DC, FortiCarrier-4801F-DC, FortiCarrier-4801F-DC-NEBS FortiCarrier-VM: FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-Azure, FortiCarrier-ARM64-GCP, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-KVM, FortiCarrier-VM64-IBM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen	
FortiCarrier: FortiCarrier-2600F, FortiCarrier-2601F, FortiCarrier-3000D, FortiCarrier-3000F, FortiCarrier-3001F, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3200F, FortiCarrier-3201F, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3700F, FortiCarrier-3701F, FortiCarrier-3800D, FortiCarrier-3960E, FortiCarrier-3980E, FortiCarrier-4200F, FortiCarrier-4201F, FortiCarrier-4400F, FortiCarrier-4401F, FortiCarrier-4800F, FortiCarrier-4801F, FortiCarrier-4801F-NEBS FortiCarrier 5000 Series: FortiCarrier-5001E, FortiCarrier-5001E1 FortiCarrier 6000 Series: FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC FortiCarrier 7000 Series: FortiCarrier-7000E, FortiCarrier-7000F, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC FortiCarrier-DC: FortiCarrier-2600F-DC, FortiCarrier-2601F-DC, FortiCarrier-3000D-DC, FortiCarrier-3000F-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC, FortiCarrier-4200F-DC, FortiCarrier-4201F-DC, FortiCarrier-4400F-DC, FortiCarrier-4401F-DC, FortiCarrier-4801F-DC, FortiCarrier-4801F-DC-NEBS FortiCarrier-VM: FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-Azure, FortiCarrier-ARM64-GCP, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen	7.2

Model	Firmware Version
FortiCarrier: FortiCarrier-2600F, FortiCarrier-2601F, FortiCarrier-3000D, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3800D, FortiCarrier-3810D, FortiCarrier-3815D, FortiCarrier-3960E, FortiCarrier-3980E FortiCarrier 5000 Series: FortiCarrier-5001D, FortiCarrier-5001E, FortiCarrier-5001E1 FortiCarrier-DC: FortiCarrier-2600F-DC, FortiCarrier-2601F-DC, FortiCarrier-3000D-DC, FortiCarrier-3000F-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3810D-DC, FortiCarrier-3815D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC FortiCarrier-VM: FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen, FortiCarrier-ARM64-KVM	7.0
FortiCarrier: FortiCarrier-3000D, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3800D, FortiCarrier-3810D, FortiCarrier-3815D, FortiCarrier-3960E, FortiCarrier-3980E FortiCarrier 5000 Series: FortiCarrier-5001D, FortiCarrier-5001E, FortiCarrier-5001E1 FortiCarrier-DC: FortiCarrier-3000D-DC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3810D-DC, FortiCarrier-3815D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC FortiCarrier-VM: FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen	6.4
FortiCarrier: FortiCarrier-3000D, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3800D, FortiCarrier-3810D, FortiCarrier-3815D, FortiCarrier-3960E, FortiCarrier-3980E FortiCarrier 5000 Series: FortiCarrier-5001D, FortiCarrier-5001E, FortiCarrier-5001E1 FortiCarrier-DC: FortiCarrier-3000D-DC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3810D-DC, FortiCarrier-3815D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC FortiCarrier 6K and 7K: FortiCarrier-6000F, FortiCarrier-6300F, FortiCarrier-6301F, FortiCarrier-6500F, FortiCarrier-6501F, FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7000F, FortiCarrier-7121F, FortiCarrier-7121F-2	6.2

Model	Firmware Version
FortiCarrier 6K and 7K DC: FortiCarrier-6000F-DC, FortiCarrier-6300F-DC, FortiCarrier-6301F-DC, FortiCarrier-6500F-DC, FortiCarrier-6501F-DC, FortiCarrier-7060E-8-DC, FortiCarrier-7121F-DC, FortiCarrier-7121F-2-DC FortiCarrier-VM: FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen	
FortiCarrier: FortiCarrier-3000D, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3800D, FortiCarrier-3810D, FortiCarrier-3815D, FortiCarrier-3960E, FortiCarrier-3980E FortiCarrier 5000 Series: FortiCarrier-5001D, FortiCarrier-5001E, FortiCarrier-5001E1 FortiCarrier-DC: FortiCarrier-3000D-DC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3810D-DC, FortiCarrier-3815D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC FortiCarrier-VM: FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-AWSONDEMAND, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen	6.0

FortiCarrier special branch models

The following FortiCarrier models are released on special branches of FortiOS Carrier. FortiAnalyzer version 7.4.10 supports these models on the identified FortiOS Carrier version and build number.

For information about supported FortiCarrier models released with FortiOS Carrier firmware, see [FortiCarrier models on page 41](#).

FortiCarrier 7.4

FortiCarrier Model	FortiCarrier Version	FortiCarrier Build
FortiCarrier-3800G	7.4.8	6564
FortiCarrier-3801G	7.4.8	6438

FortiCarrier 7.0

FortiCarrier Model	FortiCarrier Version	FortiCarrier Build
FortiCarrier-3200F, FortiCarrier-3201F	7.0.17	7553
FortiCarrier-3700F, FortiCarrier-3701F	7.0.17	7553

FortiCarrier Model	FortiCarrier Version	FortiCarrier Build
FortiCarrier-4800F, FortiCarrier-4800F-DC	7.0.17	7553
FortiCarrier-4801F, FortiCarrier-4801F-DC, FortiCarrier-4801F-DC-NEBS, FortiCarrier-4801F-NEBS		
FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC	7.0.16	0280
FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC	7.0.16	0280
FortiCarrier-7000F, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC	7.0.16	0280

FortiCarrier 6.4

FortiCarrier Model	FortiCarrier Version	FortiCarrier Build
FortiCarrier-3500F	6.4.6	5886
FortiCarrier-3501F	6.4.6	6132
FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC	6.4.13	1926
FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC	6.4.13	1926
FortiCarrier-7000F, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC	6.4.13	1926

FortiCarrier 6.2

FortiCarrier Model	FortiCarrier Version	FortiCarrier Build
FortiCarrier-4200F, FortiCarrier-4200F-DC FortiCarrier-4201F, FortiCarrier-4201F-DC FortiCarrier-4400F, FortiCarrier-4400F-DC, FortiCarrier-4401F, FortiCarrier-4401F-DC	6.2.9	7197
FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC	6.2.13	1271
FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC FortiCarrier-7000F, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC	6.2.13	1271

FortiCarrier 6.0

FortiCarrier Model	FortiCarrier Version	FortiCarrier Build
FortiCarrier-VM64-Azure	6.0	5485

FortiADC models

Model	Firmware Version
FortiADC: FortiADC-100F, FortiADC-120F, FortiADC-200D, FortiADC-200F, FortiADC-220F, FortiADC-300D, FortiADC-300F, FortiADC-400D, FortiADC-400F, FortiADC-420F, FortiADC-700D, FortiADC-1000F, FortiADC-1200F, FortiADC-1500D, FortiADC-2000D, FortiADC-2000F, FortiADC-2200F, FortiADC-4000D, FortiADC-4000F, FortiADC-4200F, FortiADC-5000F	7.4

Model	Firmware Version
FortiADC VM: FortiADC-ALI, FortiADC-ALI_ONDEMAND, FortiADC-AZURE, FortiADC-AZURE_ONDEMAND, FortiADC-GCP, FortiADC-GCP_ONDEMAND, FortiADC-HYV, FortiADC-IBM, FortiADC-KVM, FortiADC-OCI, FortiADC-VM, FortiADC-XENAWS, FortiADC-XENAWS_ONDEMAND, FortiADC-XENOPEN, FortiADC-XENSERVEN	
FortiADC: FortiADC-100F, FortiADC-120F, FortiADC-200D, FortiADC-200F, FortiADC-220F, FortiADC-300D, FortiADC-300F, FortiADC-400D, FortiADC-400F, FortiADC-700D, FortiADC-1000F, FortiADC-1200F, FortiADC-1500D, FortiADC-2000D, FortiADC-2000F, FortiADC-2200F, FortiADC-4000D, FortiADC-4000F, FortiADC-4200F, FortiADC-5000F	6.2, 7.0, 7.1, 7.2
FortiADC VM: FortiADC-ALI, FortiADC-ALI_ONDEMAND, FortiADC-AZURE, FortiADC-AZURE_ONDEMAND, FortiADC-GCP, FortiADC-GCP_ONDEMAND, FortiADC-HYV, FortiADC-IBM, FortiADC-KVM, FortiADC-OCI, FortiADC-VM, FortiADC-XENAWS, FortiADC-XENAWS_ONDEMAND, FortiADC-XENOPEN, FortiADC-XENSERVEN	
FortiADC: FortiADC-100F, FortiADC-200D, FortiADC-200F, FortiADC-220F, FortiADC-300D, FortiADC-300F, FortiADC-400D, FortiADC-400F, FortiADC-700D, FortiADC-1000F, FortiADC-1200F, FortiADC-1500D, FortiADC-2000D, FortiADC-2000F, FortiADC-2200F, FortiADC-4000D, FortiADC-4000F, FortiADC-4200F, FortiADC-5000F	6.0, 6.1
FortiADC VM: FortiADC-ALI, FortiADC-ALI_ONDEMAND, FortiADC-AZURE, FortiADC-AZURE_ONDEMAND, FortiADC-GCP, FortiADC-GCP_ONDEMAND, FortiADC-HYV, FortiADC-IBM, FortiADC-KVM, FortiADC-OCI, FortiADC-VM, FortiADC-XENAWS, FortiADC-XENAWS_ONDEMAND, FortiADC-XENOPEN, FortiADC-XENSERVEN	

FortiAnalyzer models

Model	Firmware Version
FortiAnalyzer: FortiAnalyzer-150G, FortiAnalyzer-300F, FortiAnalyzer-300G, FortiAnalyzer-400E, FortiAnalyzer-800F, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-2000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3510G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3900E	7.4
FortiAnalyzer VM: FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-AWS-OnDemand, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-Azure-OnDemand, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-Xen	
FortiAnalyzer: FortiAnalyzer-150G, FortiAnalyzer-300F, FortiAnalyzer-300G, FortiAnalyzer-400E, FortiAnalyzer-800F, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-2000E, FortiAnalyzer-3000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3500E, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3510G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3900E	7.2

Model	Firmware Version
FortiAnalyzer VM: FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-AWS-OnDemand, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-Azure-OnDemand, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-Xen	
FortiAnalyzer: FortiAnalyzer-150G, FortiAnalyzer-200F, FortiAnalyzer-300F, FortiAnalyzer-300G, FortiAnalyzer-400E, FortiAnalyzer-800F, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-2000E, FortiAnalyzer-3000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3500E, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3900E	7.0
FortiAnalyzer VM: FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-ALI-OnDemand, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-Azure-OnDemand, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-GCP-OnDemand, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-Xen	

FortiAuthenticator models

Model	Firmware Version
FortiAuthenticator: FAC-200E, FAC-300F, FAC-400E, FAC-800F, FAC-2000E, FAC-3000E, FAC-3000F	6.5, 6.6
FortiAuthenticator VM: FAC-VM	
FortiAuthenticator: FAC-200D, FAC-200E, FAC-300F, FAC-400C, FAC-400E, FAC-800F, FAC-1000C, FAC-1000D, FAC-2000E, FAC-3000D, FAC-3000E, FAC-3000F	6.4
FortiAuthenticator VM: FAC-VM	
FortiAuthenticator: FAC-200D, FAC-200E, FAC-300F, FAC-400C, FAC-400E, FAC-800F, FAC-1000C, FAC-1000D, FAC-2000E, FAC-3000D, FAC-3000E	6.0, 6.1, 6.2, 6.3
FortiAuthenticator VM: FAC-VM	

FortiCache models

Model	Firmware Version
FortiCache: FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3000E, FCH-3900E	4.1, 4.2
FortiCache VM: FCH-KVM, FCH-VM64	
FortiCache: FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3900E	4.0
FortiCache VM: FCH-VM64	

FortiDDoS models

Model	Firmware Version
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-1500G, FortiDDoS-1500G-LR, FortiDDoS-2000F, FortiDDoS-2000G, FortiDDoS-3000F, FortiDDoS-3000G FortiDDoS VM: FortiDDoS-VM	7.0
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-2000F, FortiDDoS-3000F FortiDDoS VM: FortiDDoS-VM	6.6
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-2000F, FortiDDoS-3000F FortiDDoS VM: FortiDDoS-VM	6.5
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-2000F, FortiDDoS-3000F FortiDDoS VM: FortiDDoS-VM	6.4
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-2000F FortiDDoS VM: FortiDDoS-VM	6.3
FortiDDoS: FortiDDoS-200B, FortiDDoS-400B, FortiDDoS-600B, FortiDDoS-800B, FortiDDoS-900B, FortiDDoS-1000B, FortiDDoS-1200B, FortiDDoS-1500E, FortiDDoS-2000B, FortiDDoS-2000E	5.6, 5.7

FortiDeceptor models

Model	Firmware Version
FortiDeceptor: FDC-100G, FDC-1000F, FDC-1000G FortiDeceptor Rugged: FDCR-100G FortiDeceptor VM: FDC-VM	5.0, 5.1, 5.2, 5.3, 6.0
FortiDeceptor: FDC-1000F, FDC-1000G FortiDeceptor Rugged: FDCR-100G FortiDeceptor VM: FDC-VM	4.3

FortiFirewall models

Some of the following FortiFirewall models are released on special branches of FortiFirewall firmware. FortiAnalyzer version 7.4.10 supports these models on the identified FortiFirewall firmware version and build number.

FortiFirewall 7.4

Model	Firmware Version
FortiFirewall: FortiFirewall-1801F, FortiFirewall-2600F, FortiFirewall-3001F, FortiFirewall-3501F, FortiFirewall-3980E, FortiFirewall-4200F, FortiFirewall-4400F, FortiFirewall-4401F, FortiFirewall-4801F, FortiFirewall-4801F-NEBS, FortiFirewall-4801F-DC-NEBS FortiFirewall DC: FortiFirewall-3001F-DC, FortiFirewall-3980E-DC, FortiFirewall-4200F-DC, FortiFirewall-4400F-DC, FortiFirewall-4401F-DC FortiFirewall-VM: FortiFirewall-VM64, FortiFirewall-VM64-KVM	7.4

FortiFirewall 7.2

Model	Firmware Version
FortiFirewall: FortiFirewall-3980E, FortiFirewall-4200F, FortiFirewall-4400F, FortiFirewall-4401F, FortiFirewall-4801F, FortiFirewall-4801F-NEBS, FortiFirewall-4801F-DC-NEBS FortiFirewall DC: FortiFirewall-4200F-DC, FortiFirewall-4401F-DC FortiFirewall-VM: FortiFirewall-VM64, FortiFirewall-VM64-KVM	7.2

FortiFirewall 7.0

Model	Firmware Version	Firmware Build (for special branch)
FortiFirewall: FortiFirewall-3001F FortiFirewall DC: FortiFirewall-3001F-DC	7.0.10	4955
FortiFirewall: FortiFirewall-3501F	7.0.10	4955
FortiFirewall: FortiFirewall-3980E FortiFirewall DC: FortiFirewall-3980E-DC FortiFirewall-VM: FortiFirewall-VM64, FortiFirewall-VM64-KVM	7.0	

FortiFirewallCarrier models

Some of the following FortiFirewallCarrier models are released on special branches of FortiFirewallCarrier firmware. FortiAnalyzer version 7.4.10 supports these models on the identified FortiFirewallCarrier firmware version and build number.

Model	Firmware Version
FortiFirewallCarrier: FortiFirewallCarrier-1801F, FortiFirewallCarrier-2600F, FortiFirewallCarrier-3501F, FortiFirewallCarrier-3980E, FortiFirewallCarrier-4200F, FortiFirewallCarrier-4400F, FortiFirewallCarrier-4401F, FortiFirewallCarrier-4801F, FortiFirewallCarrier-4801F-NEBS, FortiFirewallCarrier-4801F-DC-NEBS FortiFirewallCarrier DC: FortiFirewallCarrier-1801F-DC, FortiFirewallCarrier-4200F-DC, FortiFirewallCarrier-4401F-DC FortiFirewallCarrier-VM: FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	7.4
FortiFirewallCarrier: FortiFirewallCarrier-2600F, FortiFirewallCarrier-3980E, FortiFirewallCarrier-4200F, FortiFirewallCarrier-4400F, FortiFirewallCarrier-4801F, FortiFirewallCarrier-4801F-NEBS, FortiFirewallCarrier-4801F-DC-NEBS FortiFirewallCarrier DC: FortiFirewallCarrier-4200F-DC FortiFirewallCarrier-VM: FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	7.2
FortiFirewallCarrier-VM: FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	7.0

FortiFirewall special branch models

Model	Firmware Version	Firmware Build
FortiFirewallCarrier: FortiFirewallCarrier-1801F, FortiFirewallCarrier-4401F	7.2.6	4609
FortiFirewallCarrier: FortiFirewallCarrier-3001F	7.0.10	4955
FortiFirewallCarrier: FortiFirewallCarrier-3501F	7.0.10	4940

Fortisolator models

Model	Firmware Version
Fortisolator: Fortisolator-1000F, Fortisolator-1000G, Fortisolator-3000F Fortisolator-VM: Fortisolator-VM	2.4

FortiMail models

Model	Firmware Version
FortiMail: FE-200F, FE-400F, FE-900F, FE-2000E, FE-2000F, FE-3000E, FE-3000F, FE-3200E FortiMail VM: FML-VM, FML-VM-ALI, FML-VM-AWS, FML-VM-Azure, FML-VM-DK, FML-VM-GCP, FML-VM-HV, FML-VM-KVM, FML-VM-OCF, FML-VM-XEN,	7.4

Model	Firmware Version
FortiMail Cloud	
FortiMail: FE-60D, FE-200D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-2000E, FE-2000F, FE-3000E, FE-3000F, FE-3200E FortiMail VM: FML-VM, FML-VM-ALI, FML-VM-AWS, FML-VM-Azure, FML-VM-DK, FML-VM-GCP, FML-VM-HV, FML-VM-KVM, FML-VM-OCP, FML-VM-XEN, FortiMail Cloud	7.2
FortiMail: FE-60D, FE-200D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-1000D, FE-2000E, FE-2000F, FE-3000D, FE-3000E, FE-3000F, FE-3200E FortiMail VM: FML-VM, FML-VM-ALI, FML-VM-AWS, FML-VM-Azure, FML-VM-DK, FML-VM-GCP, FML-VM-HV, FML-VM-KVM, FML-VM-OCP, FML-VM-XEN, FortiMail Cloud	7.0
FortiMail: FE-60D, FE-200D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-1000D, FE-2000E, FE-3000D, FE-3000E, FE-3200E FortiMail VM: FML-VM, FML-VM-ALI, FML-VM-AWS, FML-VM-Azure, FML-VM-DK, FML-VM-GCP, FML-VM-HV, FML-VM-KVM, FML-VM-OCP, FML-VM-XEN, FortiMail Cloud	6.2, 6.4

FortiNAC models

Model	Firmware Version
FortiNAC: FortiNAC-500, FortiNAC-600, FortiNAC-700, FortiNAC-C-1000C, FortiNAC-C-2000C, FortiNAC-CA-500C, FortiNAC-Manager-550 FortiNAC VM: FortiNAC-C-VM, FortiNAC-CA-VM, FortiNAC-M-VM	9.4
FortiNAC: FortiNAC-500, FortiNAC-600, FortiNAC-700, FortiNAC-C-1000C, FortiNAC-C-2000C, FortiNAC-Manager-550 FortiNAC VM: FortiNAC-C-VM, FortiNAC-CA-VM, FortiNAC-M-VM	9.1, 9.2
FortiNAC: FortiNAC-CA-500F, FortiNAC-M-550F, FortiNAC-CA-600F, FortiNAC-CA-700F FortiNAC VM: FortiNAC-VM-ESXI, FortiNAC-MX-VM	7.4
FortiNAC: FortiNAC-CA-500F, FortiNAC-M-550F, FortiNAC-CA-600F, FortiNAC-CA-700F FortiNAC VM: FortiNAC-F-VM, FortiNAC-VM-ESXI, FortiNAC-MX-VM	7.2

FortiNDR models

Model	Firmware Version
FortiNDR: FortiNDR-1000F, FortiNDR-3500F, FortiNDR-3600G FortiNDR-VM: FortiNDR-KVM, FortiNDR-VM, FortiNDR-VMC	7.4
FortiNDR: FortiNDR-1000F, FortiNDR-3500F FortiNDR-VM: FortiNDR-KVM, FortiNDR-VM	7.2
FortiNDR: FortiNDR-3500F FortiNDR-VM: FortiNDR-KVM, FortiNDR-VM	7.0, 7.1

FortiPAM models

Model	Firmware Version
FortiPAM: FortiPAM-100G, FortiPAM-400G, FortiPAM-1100G, FortiPAM-3100G	1.8
FortiPAM: FortiPAM-1000G, FortiPAM-3000G FortiPAM VM: FortiPAM-AWS, FortiPAM-Azure, FortiPAM-GCP, FortiPAM-HyperV, FortiPAM-KVM, FortiPAM-VM64	1.0, 1.1, 1.2, 1.3, 1.4

FortiProxy models

Model	Firmware Version
FortiProxy: FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G FortiProxy VM: FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-OPC, FortiProxy-VM64	7.4
FortiProxy: FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G FortiProxy VM: FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-VM64	7.2
FortiProxy: FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G FortiProxy VM: FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-OPC, FortiProxy-VM64	7.0
FortiProxy: FPX-400E, FPX-2000E, FPX-4000E FortiProxy VM: FortiProxy-KVM, FortiProxy-VM64	1.0, 1.1, 1.2, 2.0

FortiSandbox models

Model	Firmware Version
FortiSandbox: FSA-500F, FSA-500G, FSA-1000D, FSA-1000F, FSA-1500G, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3000F, FSA-3500D FortiSandbox DC: FSA-1000F-DC FortiSandbox-VM: FortiSandbox-AWS, FortiSandbox-Cloud, FSA-VM	4.2, 4.4
FortiSandbox: FSA-500F, FSA-1000D, FSA-1000F, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3000F, FSA-3500D FortiSandbox DC: FSA-1000F-DC FortiSandbox-VM: FortiSandbox-AWS, FortiSandbox-Cloud, FSA-VM	4.0
FortiSandbox: FSA-500F, FSA-1000D, FSA-1000F, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3500D FortiSandbox DC: FSA-1000F-DC FortiSandbox-VM: FortiSandbox-AWS, FSA-VM	3.2

FortiSOAR models

Model	Firmware Version
FortiSOAR VM: FortiSOAR-VM	7.2, 7.3, 7.4

FortiSRA models

Model	Firmware Version
FortiSRA: FortiSRA-1000G, FortiSRA-3000G FortiSRA-VM: FortiSRA-Azure, FortiSRA-HyperV, FortiSRA-KVM, FortiSRA-VM64	1.0, 1.1

FortiSwitch ATCA models

Model	Firmware Version
FortiController: FTCL-5103B, FTCL-5903C, FTCL-5913C	5.2
FortiSwitch: FS-5003A, FS-5003B FortiController: FTCL-5103B	5.0
FortiSwitch: FS-5003A, FS-5003B	4.3

FortiWeb models

Model	Firmware Version
FortiWeb: FortiWeb-100D, FortiWeb-100E, FortiWeb-100F, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-400F, FortiWeb-600D, FortiWeb-600E, FortiWeb-600F, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-1000F, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer FortiWeb Cloud, including FortiAppSec Cloud.	7.4
FortiWeb: FortiWeb-100D, FortiWeb-100E, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-600D, FortiWeb-600E, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-1000F, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer FortiWeb Cloud, including FortiAppSec Cloud.	7.2
FortiWeb: FortiWeb-100D, FortiWeb-100E, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-600D, FortiWeb-600E, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer FortiWeb Cloud, including FortiAppSec Cloud.	7.0

Resolved issues

The following issues have been fixed in 7.4.10. To inquire about a particular bug, please contact [Customer Service & Support](#).

Common Vulnerabilities and Exposures

Visit <https://fortiguard.com/psirt> for more information.

Bug ID	CVE references
1247736	FortiAnalyzer 7.4.10 is no longer vulnerable to the following CVE Reference: • CVE-2026-24858

Known issues

Known issues are organized into the following categories:

- [New known issues](#)
- [Existing known issues](#)

To inquire about a particular bug or to report a bug, please contact [Fortinet Customer Service & Support](#).

New known issues

No new issues have been identified in version 7.4.10.

Existing known issues

The following issues have been identified in a previous version of FortiAnalyzer and remain in FortiAnalyzer 7.4.10.

System Settings

Bug ID	Description
1220686	SAML SSO synchronization prevents admin SSO login after HA failover.

Appendix A - Default and maximum number of ADOMs supported

This section identifies the supported number of ADOMs for FortiAnalyzer hardware models and virtual machines.



When operating as a Fabric supervisor, FortiAnalyzer does not count member ADOMs and devices toward its license limit.

See also the [FortiAnalyzer Data Sheet](#).

Hardware models

FortiAnalyzer supports a default number of ADOMs based on hardware model.

Some hardware models support an ADOM subscription license. When you purchase an ADOM subscription license, you increase the number of supported ADOMs. For example, you can purchase an ADOM subscription license for the FAZ-3000G series, which allows you to use up to a maximum of 1200 ADOMs. Other hardware models do not support the ADOM subscription license.

Some older hardware models do not enforce ADOM limits. These models will display a warning message when the ADOM limit is reached or exceeded; adding more ADOMs may affect performance. These devices are still subject to maximum device limits which are listed in the FortiAnalyzer Data Sheet.

The table below lists the maximum number of ADOMs by platform. Models that enforce the maximum as a hard limit are indicated in the *Hard limit* column.

FortiAnalyzer Platform	Maximum number of ADOMs	Hard limit
Desktop models	1	✓
150G	3	✓
300F	25	
300G	25	✓
400E	25	
800F	50	
800G and 810G	50	✓

FortiAnalyzer Platform	Maximum number of ADOMs	Hard limit
1000F	50	✓
1000G	50	✓
2000E	250	
3000F	500	
3000G and 3100G	500 *1200	✓
3500F	500	
3500G and 3510G	500 *500	✓
3700F	1200	
3700G and 3750G	1200 *10,000	✓

*Maximum number of supported ADOMs can be increased to this value with an ADOM subscription license.

Virtual Machines



For subscription licenses, FortiAnalyzer enforces the ADOM limits.
For perpetual licenses, ADOM limits are recommended, but not enforced.

FortiAnalyzer subscription license

Five (5) ADOMs are included with FortiAnalyzer VM subscription licenses. Additional ADOMs can be purchased with an ADOM subscription license.

FortiAnalyzer perpetual license

Recommended maximum number of ADOMs supported:

FortiAnalyzer Platform	Default number of ADOMs
1 GB/Day < License <= 5 GB/Day	10

FortiAnalyzer Platform	Default number of ADOMs
5 GB/Day < License <= 25 GB/Day	25
25 GB/Day < License <= 100 GB/Day	50
100 GB/Day < License <= 500 GB/Day	250
500 GB/Day < License <= 1000 GB/Day	500
1000 GB/Day < License <= 5000 GB/Day	800
License > 5000 GB/Day	1200



- FortiAnalyzer-VM subscription licenses are fully stackable.
- For FortiAnalyzer-VM perpetual licenses, only the GB/Day is stackable.



www.fortinet.com

Copyright© 2026 Fortinet, Inc. All rights reserved. Fortinet®, FortiGate®, FortiCare® and FortiGuard®, and certain other marks are registered trademarks of Fortinet, Inc., and other Fortinet names herein may also be registered and/or common law trademarks of Fortinet. All other product or company names may be trademarks of their respective owners. Performance and other metrics contained herein were attained in internal lab tests under ideal conditions, and actual performance and other results may vary. Network variables, different network environments and other conditions may affect performance results. Nothing herein represents any binding commitment by Fortinet, and Fortinet disclaims all warranties, whether express or implied, except to the extent Fortinet enters a binding written contract, signed by Fortinet's Chief Legal Officer, with a purchaser that expressly warrants that the identified product will perform according to certain expressly-identified performance metrics and, in such event, only the specific performance metrics expressly identified in such binding written contract shall be binding on Fortinet. For absolute clarity, any such warranty will be limited to performance in the same ideal conditions as in Fortinet's internal lab tests. Fortinet disclaims in full any covenants, representations, and guarantees pursuant hereto, whether express or implied. Fortinet reserves the right to change, modify, transfer, or otherwise revise this publication without notice, and the most current version of the publication shall be applicable.