

# Release Notes

FortiAnalyzer 7.6.4



**FORTINET DOCUMENT LIBRARY**

<https://docs.fortinet.com>

**FORTINET VIDEO LIBRARY**

<https://video.fortinet.com>

**FORTINET BLOG**

<https://blog.fortinet.com>

**CUSTOMER SERVICE & SUPPORT**

<https://support.fortinet.com>

**FORTINET TRAINING & CERTIFICATION PROGRAM**

<https://www.fortinet.com/training-certification>

**FORTINET TRAINING INSTITUTE**

<https://training.fortinet.com>

**FORTIGUARD LABS**

<https://www.fortiguard.com>

**END USER LICENSE AGREEMENT**

<https://www.fortinet.com/doc/legal/EULA.pdf>

**FEEDBACK**

Email: [techdoc@fortinet.com](mailto:techdoc@fortinet.com)



March 10, 2026

FortiAnalyzer 7.6.4 Release Notes

05-764-1168463-20260310

# TABLE OF CONTENTS

<b>Change Log</b> .....	<b>6</b>
<b>FortiAnalyzer 7.6.4 Release</b> .....	<b>7</b>
Supported models .....	7
FortiAnalyzer VM subscription license .....	7
<b>Special Notices</b> .....	<b>9</b>
FortiManager Connector .....	9
Default password policy for local users .....	9
Quotations applied to fields containing string-type data .....	9
MEAs removed in FortiAnalyzer 7.6.3 .....	9
Migrating the log database from Postgres to ClickHouse .....	10
Shell access has been removed .....	10
Alert notifications generated by FortiAnalyzer and sent by syslog .....	10
Additional configuration required for SSO users .....	10
FortiAnalyzer 7.2.3 and later firmware on FortiGuard .....	11
Configuration backup requires a password .....	11
FortiAnalyzer-3500E support .....	11
Serial console has changed for FortiAnalyzer deployments on Xen .....	12
OpenXen in PV mode is not supported in FortiAnalyzer 7.4.1 .....	12
Default GUI theme changed .....	12
FortiManager Features removed .....	13
Setup wizard requires FortiCare registration .....	13
Hyperscale firewall mode .....	13
Modifying the interface status with the CLI .....	13
Citrix XenServer default limits and upgrade .....	14
FortiAnalyzer VM upgrade requires more memory .....	14
Maximum ADOM limits for FortiAnalyzer .....	14
Port 8443 reserved .....	15
Hyper-V FortiAnalyzer-VM running on an AMD CPU .....	15
SSLv3 on FortiAnalyzer-VM64-AWS .....	15
<b>New features</b> .....	<b>16</b>
<b>Upgrade Information</b> .....	<b>17</b>
Downgrading to previous firmware versions .....	17
Firmware image checksums .....	17
FortiAnalyzer VM firmware .....	17
SNMP MIB files .....	19
<b>Product Integration and Support</b> .....	<b>20</b>
Supported software .....	20
Web browsers .....	21
FortiOS and FortiOS Carrier .....	21
FortiADC .....	21
FortiNDR .....	22

FortiAnalyzer	22
FortiAP	22
FortiAuthenticator	23
FortiCache	23
FortiCASB	23
FortiClient	23
FortiDDoS	23
FortiDeceptor	24
FortiFirewall and FortiFirewallCarrier	24
FortiIsolator	24
FortiMail	25
FortiManager	25
FortiNAC	25
FortiPAM	25
FortiProxy	26
FortiSandbox	26
FortiSASE	26
FortiSOAR	26
FortiSRA	26
FortiSwitch ATCA	27
FortiToken	27
FortiWeb	27
Virtualization	27
Feature support	28
Language support	29
Supported models	30
FortiGate models	31
FortiGate special branch models	37
FortiCarrier models	41
FortiCarrier special branch models	44
FortiADC models	46
FortiNDR models	47
FortiAnalyzer models	47
FortiAP models	48
FortiAuthenticator models	49
FortiCache models	50
FortiDDoS models	50
FortiDeceptor models	50
FortiFirewall models	51
FortiFirewallCarrier models	52
FortiIsolator models	53
FortiMail models	53
FortiNAC models	53
FortiPAM models	54
FortiProxy models	54
FortiSandbox models	55
FortiSOAR models	55
FortiSRA models	55
FortiSwitch ATCA models	56

---

FortiWeb models .....	56
<b>Resolved Issues .....</b>	<b>58</b>
Device Manager .....	58
Log View .....	58
Others .....	58
Reports .....	59
Common Vulnerabilities and Exposures .....	59
<b>Known issues .....</b>	<b>60</b>
New known issues .....	60
Others .....	60
Existing known issues .....	60
FortiView .....	60
Log View .....	61
Others .....	61
System Settings .....	61
<b>Appendix A - Default and maximum number of ADOMs supported .....</b>	<b>62</b>
Hardware models .....	62
Virtual Machines .....	63
FortiAnalyzer subscription license .....	63
FortiAnalyzer perpetual license .....	63

# Change Log

Date	Change Description
2025-08-26	Initial release of 7.6.4.
2025-08-27	Updated <a href="#">Resolved Issues</a> on page 58. Updated <a href="#">Web browsers</a> on page 21.
2025-08-28	Added "FortiManager Connector" to <a href="#">Special Notices</a> on page 9.
2025-09-12	Updated <a href="#">Known issues</a> on page 60. Updated "Maximum ADOM limits for FortiAnalyzer" in <a href="#">Special Notices</a> on page 9. Updated <a href="#">Appendix A - Default and maximum number of ADOMs supported</a> on page 62.
2025-09-19	Updated <a href="#">Appendix A - Default and maximum number of ADOMs supported</a> on page 62.
2025-09-23	Updated <a href="#">Supported models</a> on page 7. Updated <a href="#">Appendix A - Default and maximum number of ADOMs supported</a> on page 62.
2025-10-31	Updated <a href="#">Known issues</a> on page 60.
2025-11-04	Updated <a href="#">Resolved Issues</a> on page 58.
2025-12-30	Updated <a href="#">Supported models</a> on page 7.
2026-01-06	Updated <a href="#">Supported models</a> on page 7.
2026-01-14	Updated <a href="#">Supported models</a> on page 7.
2026-03-10	Updated <a href="#">Resolved Issues</a> on page 58.

# FortiAnalyzer 7.6.4 Release

This document provides information about FortiAnalyzer version 7.6.4 build 3579.



The recommended minimum screen resolution for the FortiAnalyzer GUI is 1920 x 1080. Please adjust the screen resolution accordingly. Otherwise, the GUI may not display properly.

This section includes the following topics:

- [Supported models on page 7](#)
- [FortiAnalyzer VM subscription license on page 7](#)

## Supported models

FortiAnalyzer version 7.6.4 supports the following models:

<b>FortiAnalyzer</b>	FAZ-150G, FAZ-300G, FAZ-800G, FAZ-810G, FAZ-1000F, FAZ-1000G, FAZ-2000E, FAZ-3000F, FAZ-3000G, FAZ-3100G, FAZ-3500F, FAZ-3500G, FAZ-3510G, FAZ-3700F, and FAZ-3700G.
<b>FortiAnalyzer VM</b>	FAZ_VM64, FAZ_VM64_ALI, FAZ_VM64_AWS, FAZ_VM64_AWSOnDemand, FAZ_VM64_Azure, FAZ_VM64_GCP, FAZ_VM64_HV (including Hyper-V 2016, 2019, and 2022), FAZ_VM64_IBM, FAZ_VM64_KVM, FAZ_VM64_OPC, FAZ_VM64_XEN (for both Citrix and Open Source Xen).



For access to container versions of FortiAnalyzer, contact [Fortinet Support](#).

## FortiAnalyzer VM subscription license

The FortiAnalyzer VM subscription license supports FortiAnalyzer version 6.4.1 and later. For information about supported firmware, see [FortiAnalyzer VM firmware on page 17](#).

See also [Appendix A - Default and maximum number of ADOMs supported on page 62](#).



---

You can use the FortiAnalyzer VM subscription license with new FortiAnalyzer-VM installations.

For existing FortiAnalyzer-VM installations, you can migrate to a FortiAnalyzer VM subscription license, starting with FortiAnalyzer 7.0.1. See the [FortiAnalyzer Administration Guide](#).

---

# Special Notices

This section highlights some of the operational changes that administrators should be aware of in FortiAnalyzer version 7.6.4.

## FortiManager Connector

In FortiAnalyzer 7.6.4, the FMG Connector is moved to *Incidents & Events > Automation > Active Connectors*.

## Default password policy for local users

Beginning in FortiAnalyzer 7.6.4, a password policy for local users is enabled and configured by default. If you are setting up FortiAnalyzer 7.6.4 or later, the password created at setup must be at least 8 characters and must contain uppercase letter(s), lowercase letter(s), number(s), and special character(s).

Note that existing password policy settings are maintained after upgrading. For example, if the password policy is disabled prior to upgrading to FortiAnalyzer 7.6.4 or later, it will remain disabled after the upgrade.

## Quotations applied to fields containing string-type data

Starting from version 7.6.3, quotations are consistently applied to the fields containing string-type data. For example: srcip, dstip, transip, date, and time.

## MEAs removed in FortiAnalyzer 7.6.3

There is no support for MEAs in FortiAnalyzer 7.6.3 and later.

The following management extension applications (MEAs) are removed in FortiAnalyzer 7.6.3:

- FortiSIEM
- FortiSOAR

## Migrating the log database from Postgres to ClickHouse

Beginning in FortiAnalyzer 7.6.0, FortiAnalyzer stores logs in a ClickHouse SQL database rather than a Postgres SQL database.

For more information, see the [FortiAnalyzer 7.6.0 Upgrade Guide](#).

## Shell access has been removed

As of FortiAnalyzer 7.6.0, shell access has been removed.

The following CLI variables have been removed, which were previously used to enable shell access:

```
config system admin setting
  set shell-access {enable | disable}
  set shell-password <passwd>
```

The following CLI command has been removed, which was previously used to access shell when enabled:

```
execute shell
```

## Alert notifications generated by FortiAnalyzer and sent by syslog

Beginning in 7.4.3, alert notifications generated by FortiAnalyzer and sent by syslog will use the RFC-5424 format.

## Additional configuration required for SSO users

Beginning in 7.4.3, additional configuration is needed for FortiAnalyzer Users declared as wildcard SSO users.

When configuring Administrators as wildcard SSO users, the `ext-auth-accprofile-override` and/or `ext-auth-adom-override` features, under *Advanced Options*, should be enabled if the intent is to obtain the ADOMs list and/or permission profile from the SAML IdP.

## FortiAnalyzer 7.2.3 and later firmware on FortiGuard

Starting in FortiAnalyzer 7.2.1, a setup wizard executes to prompt the user for various configuration steps and registration with FortiCare. During the execution, the FortiAnalyzer unit attempts to communicate with FortiGuard for a list of FortiAnalyzer firmware images currently available on FortiGuard – older and newer.

In the case of FortiAnalyzer 7.2.2, a bug in the GUI prevents the wizard from completing and prevents the user from accessing the FortiAnalyzer unit. The issue has been fixed in 7.2.3 and later and a CLI command has been added to bypass the setup wizard at login time.

```
config system admin setting
  set firmware-upgrade-check disable
end
```

Fortinet has not uploaded FortiAnalyzer 7.2.3 and later firmware to FortiGuard in order to work around the GUI bug, however, the firmware is available for download from the [Fortinet Support website](#).

## Configuration backup requires a password

As of FortiAnalyzer 7.4.2, configuration backup files are automatically encrypted and require you to set a password. The password is required for scheduled backups as well.

In previous versions, the encryption and password were optional.

For more information, see the [FortiAnalyzer Administration Guide](#).

## FortiAnalyzer-3500E support

FortiAnalyzer 7.4.2 and later does not support the FortiAnalyzer-3500E device.

FortiAnalyzer 7.4.2 introduces an upgrade of the OpenSSL library to address known vulnerabilities in the library. As a result, the SSL connection that is setup between the FortiAnalyzer-3500E device and the Google Map server hosted by Fortinet uses a SHA2 (2048) public key length. The certificate stored on the BIOS that is used during the setup of the SSL connection contains a SHA1 public key length, which causes the connection setup to fail. Running the following command shows the key length.

```
FAZ3500E # config system certificate local
(local)# ed Fortinet_Local
(Fortinet_Local)# get
  name : Fortinet_Local
  password : *
  comment : Default local certificate
  private-key :
  certificate :
```

```
Subject: C = US, ST = California, L = Sunnyvale, O = Fortinet, OU = FortiAnalyzer, CN =
        FL3K5E3M1500074, emailAddress = support@fortinet.com
Issuer: C = US, ST = California, L = Sunnyvale, O = Fortinet, OU = Certificate Authority,
        CN = support, emailAddress = support@fortinet.com
Valid from: 2015-03-06 16:22:10 GMT
Valid to: 2038-01-19 03:14:07 GMT
Fingerprint: FC:D0:0C:8D:DC:57:B6:16:58:DF:90:22:77:6F:2C:1B
Public key: rsaEncryption (1024 bits)
Signature: sha1WithRSAEncryption
Root CA: No
Version: 3
Serial Num:
1e:07:7a
Extension 1: X509v3 Basic Constraints:
CA:FALSE
...
(Fortinet_Local)#
```

## Serial console has changed for FortiAnalyzer deployments on Xen

In FortiAnalyzer 7.4.1, the serial console for Xen deployments has changed from hvc0 (Xen specific) to ttyS0 (standard).

## OpenXen in PV mode is not supported in FortiAnalyzer 7.4.1

As of FortiAnalyzer 7.4.1, kernel and rootfs are encrypted. OpenXen in PV mode tries to unzip the kernel and rootfs, but it will fail. Therefore, OpenXen in PV mode cannot be used when deploying or upgrading to FortiAnalyzer 7.4.1. Only HVM (hardware virtual machine) mode is supported for OpenXen in FortiAnalyzer 7.4.1.

## Default GUI theme changed

As of FortiAnalyzer 7.4.1, the default GUI theme is *Jade*. The default theme can be changed from *System Settings > Settings*.

## FortiManager Features removed

FortiAnalyzer 7.2.1 and later no longer supports FortiManager Features. If you have FortiManager Features enabled before upgrading to FortiAnalyzer 7.2.1, FortiManager Features will be permanently disabled after upgrading to FortiAnalyzer 7.2.1.

## Setup wizard requires FortiCare registration

Starting in FortiAnalyzer 7.2.1, the FortiAnalyzer Setup wizard requires you to complete the *Register with FortiCare* step before you can access the FortiAnalyzer appliance or VM. Previously the step was optional.

For FortiAnalyzer units operating in a closed environment, contact customer service to receive an entitlement file, and then load the entitlement file to FortiAnalyzer by using the CLI.

When FortiManager is managing FortiAnalyzer in a closed environment, FortiManager contains the FortiAnalyzer contract information, and you can point FortiAnalyzer to FortiManager.

## Hyperscale firewall mode

FortiAnalyzer does not support logs from the following models when they have hyperscale firewall mode and netflow enabled:

- FortiGate-1800F
- FortiGate-1801F
- FortiGate-2600F
- FortiGate-2601F
- FortiGate-4200F
- FortiGate-4201F
- FortiGate-4400F
- FortiGate-4401F

FortiAnalyzer only supports logs when the normal firewall mode with standard FortiGate logging are enabled.

## Modifying the interface status with the CLI

Starting in version 7.0.1, the CLI to modify the interface status has been changed from up/down to enable/disable.

For example:

```
config system interface
  edit port2
    set status <enable/disable>
  next
end
```

## Citrix XenServer default limits and upgrade

Citrix XenServer limits ramdisk to 128M by default. However the FAZ-VM64-XEN image is larger than 128M. Before updating to FortiAnalyzer 6.4, increase the size of the ramdisk setting on Citrix XenServer.

### To increase the size of the ramdisk setting:

1. On Citrix XenServer, run the following command:  
`xenstore-write /mh/limits/pv-ramdisk-max-size 536,870,912`
2. Confirm the setting is in effect by running `xenstore-ls`.

```
-----
limits = ""
pv-kernel-max-size = "33554432"
pv-ramdisk-max-size = "536,870,912"
boot-time = ""
-----
```

3. Remove the pending files left in `/run/xen/pygrub`.



The ramdisk setting returns to the default value after rebooting.

---

## FortiAnalyzer VM upgrade requires more memory

When upgrading FortiAnalyzer VM units from a previous version to FortiAnalyzer 7.2.2 or higher, the upgrade may fail because of memory allocation. As of FortiAnalyzer 7.2.2, FortiAnalyzer VM requires 16 GB of RAM and 4 CPU.

**Workaround:** Before upgrading FortiAnalyzer VM to FortiAnalyzer 7.2.2, change the memory allocation to 16 GB of RAM.

## Maximum ADOM limits for FortiAnalyzer

FortiAnalyzer hardware devices and VMs display a warning when the maximum number of ADOMs is reached. For more details, see [Appendix A - Default and maximum number of ADOMs supported on page 62](#).

## Port 8443 reserved

Port 8443 is reserved for https-logging from FortiClient EMS for Chromebooks. See also [FortiAnalyzer 7.0 Ports Reference](#) on the Docs Library.

## Hyper-V FortiAnalyzer-VM running on an AMD CPU

A Hyper-V FAZ-VM running on a PC with an AMD CPU may experience a kernel panic. Fortinet recommends running VMs on an Intel-based PC.

## SSLv3 on FortiAnalyzer-VM64-AWS

Due to known vulnerabilities in the SSLv3 protocol, FortiAnalyzer-VM64-AWS only enables TLSv1 by default. All other models enable both TLSv1 and SSLv3. If you wish to disable SSLv3 support, please run:

```
config system global
    set ssl-protocol t1sv1
end
```

# New features

For information about what's new in FortiAnalyzer 7.6.4, see the [FortiAnalyzer 7.6 New Features Guide](#). The [index](#) in the New Features Guide lists new features by release.

# Upgrade Information



Prior to upgrading your FortiAnalyzer, please review the FortiAnalyzer Upgrade Guide in detail as it includes all of the necessary steps and associated details required to upgrade your FortiAnalyzer device or VM, including recommended upgrade paths. See the *FortiAnalyzer Upgrade Guide* in the [Fortinet Document Library](#).

---

This section contains the following topics:

- [Downgrading to previous firmware versions on page 17](#)
- [Firmware image checksums on page 17](#)
- [FortiAnalyzer VM firmware on page 17](#)
- [SNMP MIB files on page 19](#)

## Downgrading to previous firmware versions

FortiAnalyzer does not provide a full downgrade path. You can downgrade to a previous firmware release by using the GUI or CLI, but doing so results in configuration loss. A system reset is required after the firmware downgrade process has completed. To reset the system, use the following CLI commands via a console port connection:

```
execute reset {all-settings | all-except-ip}  
execute format disk
```

## Firmware image checksums

The MD5 checksums for all Fortinet software and firmware releases are available at the Customer Service & Support portal, <https://support.fortinet.com>. After logging in, go to *Download > Firmware Image Checksums*, enter the image file name including the extension, and select *Get Checksum Code*.

## FortiAnalyzer VM firmware

Fortinet provides FortiAnalyzer VM firmware images for Amazon AWS, Amazon AWSOnDemand, Citrix and Open Source XenServer, Linux KVM, Microsoft Hyper-V Server, and VMware ESX/ESXi virtualization environments.

### Amazon Web Services

- The 64-bit Amazon Machine Image (AMI) is available on the AWS marketplace.

### Citrix XenServer and Open Source XenServer

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.out.OpenXen.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains the QCOW2 file for the Open Source Xen Server.
- `.out.CitrixXen.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains the Citrix XenServer Virtual Appliance (XVA), Virtual Hard Disk (VHD), and OVF files.

### Google Cloud Platform

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.out.gcp.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation.

### Linux KVM

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.out.kvm.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains QCOW2 that can be used by qemu.

### Microsoft Azure

The files for Microsoft Azure have AZURE in the filenames, for example `<product>_VM64_AZURE-v<number>-build<number>-FORTINET.out.hyperv.zip`.

- `.out`: Download the firmware image to upgrade your existing FortiAnalyzer VM installation.

### Microsoft Hyper-V Server

The files for Microsoft Hyper-V Server have HV in the filenames, for example, `<product>_VM64_HV-v<number>-build<number>-FORTINET.out.hyperv.zip`.

- `.out`: Download the firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.hyperv.zip`: Download the package for a new FortiAnalyzer VM installation. This package contains a Virtual Hard Disk (VHD) file for Microsoft Hyper-V Server.

### Oracle Private Cloud

- `.out`: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- `.out.opc.zip`: Download the 64-bit package for a new FortiAnalyzer VM installation.

### VMware ESX/ESXi

- `.out`: Download the 64-bit firmware image to upgrade your existing VM installation.
- `.ovf.zip`: Download either the 64-bit package for a new VM installation. This package contains an Open Virtualization Format (OVF) file for VMware and two Virtual Machine Disk Format (VMDK) files used by the OVF file during deployment.



For more information, see the [FortiAnalyzer Data Sheet](#) available on the Fortinet web site. VM installation guides are available in the [Fortinet Document Library](#).

---

## SNMP MIB files

You can download the *FORTINET-FORTIMANAGER-FORTIANALYZER.mib* MIB file in the firmware image file folder. The Fortinet Core MIB file is located in the main FortiAnalyzer version 5.00 file folder.

# Product Integration and Support

This section lists FortiAnalyzer 7.6.4 support of other Fortinet products. It also identifies what FortiAnalyzer features are supported for managed platforms and what languages FortiAnalyzer supports. It also lists which Fortinet models can be managed by FortiAnalyzer.

The section contains the following topics:

- [Supported software on page 20](#)
- [Feature support on page 28](#)
- [Language support on page 29](#)
- [Supported models on page 30](#)

## Supported software

FortiAnalyzer 7.6.4 supports the following software:

- [Web browsers on page 21](#)
- [FortiOS and FortiOS Carrier on page 21](#)
- [FortiADC on page 21](#)
- [FortiNDR on page 22](#)
- [FortiAnalyzer on page 22](#)
- [FortiAP on page 22](#)
- [FortiAuthenticator on page 23](#)
- [FortiCache on page 23](#)
- [FortiCASB on page 23](#)
- [FortiClient on page 23](#)
- [FortiDDoS on page 23](#)
- [FortiDeceptor on page 24](#)
- [FortiFirewall and FortiFirewallCarrier on page 24](#)
- [FortiIsolator on page 24](#)
- [FortiMail on page 25](#)
- [FortiManager on page 25](#)
- [FortiNAC on page 25](#)
- [FortiPAM on page 25](#)
- [FortiProxy on page 26](#)
- [FortiSandbox on page 26](#)
- [FortiSASE on page 26](#)
- [FortiSOAR on page 26](#)
- [FortiSwitch ATCA on page 27](#)

- [FortiToken on page 27](#)
- [FortiWeb on page 27](#)
- [Virtualization on page 27](#)



To confirm that a device model or firmware version is supported by the current firmware version running on FortiAnalyzer, run the following CLI command:  
`diagnose dvm supported-platforms list`

---



Always review the Release Notes of the supported platform firmware version before upgrading your device.

---

## Web browsers

FortiAnalyzer 7.6.4 supports the following web browsers:

- Google Chrome version 139.0.7258.155
- Microsoft Edge version 139.0.3405.119
- Mozilla Firefox 142.0.1

Other web browsers may function correctly, but are not supported by Fortinet.

## FortiOS and FortiOS Carrier



The *FortiAnalyzer Release Notes* communicate support for FortiOS versions that are available at the time of the FortiAnalyzer 7.6.4 release. For additional information about other supported FortiOS versions, please refer to the FortiAnalyzer compatibility chart in the [Fortinet Document Library](#).

See [FortiAnalyzer compatibility with FortiOS](#).

---

FortiAnalyzer 7.6.4 supports the following versions of FortiOS and FortiOS Carrier:

- 7.6.0 to 7.6.4
- 7.4.0 to 7.4.9
- 7.2.0 to 7.2.11
- 7.0.0 to 7.0.18
- 6.4.0 to 6.4.15
- 6.2.0 to 6.2.16

## FortiADC

FortiAnalyzer 7.6.4 supports the following versions of FortiADC:

- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later
- 7.1.0 and later
- 7.0.0 and later
- 6.2.0 and later
- 6.1.0 and later
- 6.0.0 and later

## FortiNDR

FortiAnalyzer 7.6.4 supports the following versions of FortiNDR:

- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later
- 7.1.0 and later
- 7.0.0 and later

## FortiAnalyzer

FortiAnalyzer 7.6.4 supports the following versions of FortiAnalyzer:

- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

## FortiAP

FortiAnalyzer 7.6.4 supports the following versions of FortiAP:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later
- 6.4.0 and later
- 6.2.0 and later
- 5.6.0 and later
- 5.4.0 and later
- 5.2.0 and later
- 5.0.0 and later

## FortiAuthenticator

FortiAnalyzer 7.6.4 supports the following versions of FortiAuthenticator:

- 6.6.0 and later
- 6.5.0 and later
- 6.4.0 and later
- 6.3.0 and later
- 6.2.0 and later
- 6.1.0 and later
- 6.0.0 and later

## FortiCache

FortiAnalyzer 7.6.4 supports the following versions of FortiCache:

- 4.2.0 and later
- 4.1.0 and later
- 4.0.0 and later

## FortiCASB

FortiAnalyzer 7.6.4 supports the following versions of FortiCASB:

- 23.2.0 and later

## FortiClient

FortiAnalyzer 7.6.4 supports the following versions of FortiClient:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later
- 6.4.0 and later

When using FortiClient with FortiAnalyzer, it is recommended to upgrade both to their latest versions. The versions between the two products should match. For example, if using FortiAnalyzer 7.2.0, use FortiClient 7.2.0.

## FortiDDoS

FortiAnalyzer 7.6.4 supports the following versions of FortiDDoS:

- 7.0.0 and later
- 6.6.0 and later
- 6.5.0 and later
- 6.4.0 and later
- 6.3.0 and later
- 6.2.0 and later
- 6.1.0 and later
- 5.7.0 and later
- 5.6.0 and later

Limited support. For more information, see [Feature support on page 28](#).

## FortiDeceptor

FortiAnalyzer 7.6.4 supports the following versions of FortiDeceptor:

- 6.1.0 and later
- 6.0.0 and later
- 5.3.0 and later
- 5.2.0 and later
- 5.1.0 and later
- 5.0.0 and later
- 4.3.0 and later

## FortiFirewall and FortiFirewallCarrier

FortiAnalyzer 7.6.4 supports the following versions of FortiFirewall and FortiFirewallCarrier:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later
- 6.4.0 and later
- 6.2.0 and later
- 6.0.0 and later

## Fortisolator

FortiAnalyzer 7.6.4 supports the following versions of Fortisolator:

- 2.4.0 and later

## FortiMail

FortiAnalyzer 7.6.4 supports the following versions of FortiMail:

- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later
- 6.4.0 and later
- 6.2.0 and later

## FortiManager

FortiAnalyzer 7.6.4 supports the following versions of FortiManager:

- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

## FortiNAC

FortiAnalyzer 7.6.4 supports the following versions of FortiNAC:

- 9.4.0 and later
- 9.2.0 and later
- 9.1.0 and later
- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later

## FortiPAM

FortiAnalyzer 7.6.4 supports the following versions of FortiPAM:

- 1.4.0 and later
- 1.3.0 and later
- 1.2.0 and later
- 1.1.0 and later
- 1.0.0 and later

## FortiProxy

FortiAnalyzer 7.6.4 supports the following versions of FortiProxy:

- 7.6.0 to 7.6.3
- 7.4.0 to 7.4.9
- 7.2.0 to 7.2.13
- 7.0.0 to 7.0.21
- 2.0.0 to 2.0.5
- 1.2.0 to 1.2.13
- 1.1.0 to 1.1.6
- 1.0.0 to 1.0.7

## FortiSandbox

FortiAnalyzer 7.6.4 supports the following versions of FortiSandbox:

- 5.0.0 and later
- 4.4.0 and later
- 4.2.0 and later
- 4.0.0 and later
- 3.2.0 and later

## FortiSASE

For more information about compatibility, see the [FortiSASE Release Notes](#).

## FortiSOAR

FortiAnalyzer 7.6.4 supports the following versions of FortiSOAR:

- 7.6.0 and later
- 7.5.0 and later
- 7.4.0 and later
- 7.3.0 and later
- 7.2.0 and later

## FortiSRA

FortiAnalyzer 7.6.4 supports the following versions of FortiSRA:

- 1.1.0 and later
- 1.0.0 and later

## FortiSwitch ATCA

FortiAnalyzer 7.6.4 supports the following versions of FortiSwitch ATCA:

- 5.2.0 and later
- 5.0.0 and later
- 4.3.0 and later

## FortiToken

FortiAnalyzer 7.6.4 supports the following versions of FortiToken:

- 3.0.0 and later

FortiAnalyzer supports logs from FortiToken Cloud.

## FortiWeb

FortiAnalyzer 7.6.4 supports the following versions of FortiWeb:

- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

FortiAnalyzer also supports FortiWeb Cloud, including FortiAppSec Cloud.

## Virtualization

FortiAnalyzer 7.6.4 supports the following virtualization software:

### Public Cloud

- Amazon Web Service AMI, Amazon EC2, Amazon EBS
- Alibaba Cloud
- Google Cloud Platform
- IBM Cloud
- Microsoft Azure
- Oracle Cloud Infrastructure

**Private Cloud**

- Citrix XenServer 8.2 and later
- OpenSource XenServer 4.2.5
- Microsoft Hyper-V Server 2016, 2019, and 2022
- Nutanix
  - AHV 20220304 and later
  - AOS 6.5 and later
  - NCC 4.6 and later
  - LCM 3.0 and later
- RedHat 9.1
  - Other versions and Linux KVM distributions are also supported
- VMware ESXi versions 6.5 and later

## Feature support

The following table lists FortiAnalyzer feature support for log devices.

Platform	Log View	FortiView	Event Management	Reports
FortiGate	✓	✓	✓	✓
FortiCarrier	✓	✓	✓	✓
FortiADC	✓		✓	✓
FortiAnalyzer	✓		✓	
FortiAP	✓		✓	✓
FortiAuthenticator	✓			
FortiCache	✓		✓	✓
FortiClient registered to FortiGate	✓	✓		✓
FortiClient registered to FortiClient EMS	✓	✓		✓
FortiDDoS	✓	✓	✓	✓
FortiDeceptor	✓			
FortiFirewall	✓	✓	✓	✓
FortiMail	✓		✓	✓

Platform	Log View	FortiView	Event Management	Reports
FortiManager	✓		✓	
FortiNAC	✓			
FortiNDR	✓	✓	✓	✓
FortiPAM	✓		✓	✓
FortiProxy	✓	✓	✓	✓
FortiSandbox	✓		✓	✓
FortiSOAR	✓		✓	✓
FortiSRA	✓		✓	✓
FortiWeb	✓		✓	✓
Syslog	✓		✓	✓

## Language support

The following table lists FortiAnalyzer language support information.

Language	GUI	Reports
<b>English</b>	✓	✓
<b>Chinese (Simplified)</b>	✓	✓
<b>Chinese (Traditional)</b>	✓	✓
<b>French</b>	✓	✓
<b>Hebrew</b>		✓
<b>Hungarian</b>		✓
<b>Japanese</b>	✓	✓
<b>Korean</b>	✓	✓
<b>Portuguese</b>		✓
<b>Russian</b>		✓
<b>Spanish</b>	✓	✓

To change the FortiAnalyzer language setting, go to *System Settings > Admin > Admin Settings*, in *Administrative Settings > Language* select the desired language on the drop-down menu. The default value is *Auto Detect*.

Russian, Hebrew, and Hungarian are not included in the default report languages. You can create your own language translation files for these languages by exporting a predefined language from FortiAnalyzer, modifying the text to a different language, saving the file as a different language name, and then importing the file into FortiAnalyzer. For more information, see the *FortiAnalyzer Administration Guide*.

## Supported models

The following tables list which FortiGate, FortiCarrier, FortiDDoS, FortiAnalyzer, FortiMail, FortiSandbox, FortiSwitch, FortiWeb, FortiCache, FortiProxy, FortiAuthenticator, and other Fortinet product models and firmware versions can send logs to a FortiAnalyzer running version 7.6.4.



Software license activated LENC devices are supported, if their platforms are in the supported models list. For example, support of FG-3200D indicates support of FG-3200D-LENC.

---

This section contains the following topics:

- [FortiGate models on page 31](#)
- [FortiGate special branch models on page 37](#)
- [FortiCarrier models on page 41](#)
- [FortiCarrier special branch models on page 44](#)
- [FortiADC models on page 46](#)
- [FortiNDR models on page 47](#)
- [FortiAnalyzer models on page 47](#)
- [FortiAP models on page 48](#)
- [FortiAuthenticator models on page 49](#)
- [FortiCache models on page 50](#)
- [FortiDDoS models on page 50](#)
- [FortiDeceptor models on page 50](#)
- [FortiFirewall models on page 51](#)
- [FortiFirewallCarrier models on page 52](#)
- [Fortisolator models on page 53](#)
- [FortiMail models on page 53](#)
- [FortiNAC models on page 53](#)
- [FortiPAM models on page 54](#)
- [FortiProxy models on page 54](#)
- [FortiSandbox models on page 55](#)
- [FortiSOAR models on page 55](#)
- [FortiSwitch ATCA models on page 56](#)
- [FortiWeb models on page 56](#)

## FortiGate models

The following FortiGate models are released with FortiOS firmware. For information about supported FortiGate models on special branch releases of FortiOS firmware, see [FortiGate special branch models on page 37](#).

Model	Firmware Version
<b>FortiGate:</b> FortiGate-40F, FortiGate-40F-3G4G, FortiGate-50G, FortiGate-50G-5G, FortiGate-50G-DSL, FortiGate-50G-SFP, FortiGate-50G-SFP-POE, FortiGate-51G, FortiGate-51G-5G, FortiGate-51G-SFP-POE, FortiGate-60F, FortiGate-61F, FortiGate-70F, FortiGate-70G, FortiGate-70G-POE, FortiGate-71G, FortiGate-71G-POE, FortiGate-71F, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90G, FortiGate-91G, FortiGate-100F, FortiGate-101F, FortiGate-120G, FortiGate-121G, FortiGate-200E, FortiGate-200F, FortiGate-200G, FortiGate-201E, FortiGate-201F, FortiGate-201G, FortiGate-300E, FortiGate-301E, FortiGate-400E, FortiGate-400F, FortiGate-400E-Bypass, FortiGate-401E, FortiGate-401F, FortiGate-500E, FortiGate-501E, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-800D, FortiGate-900D, FortiGate-900G, FortiGate-901G, FortiGate-1000D, FortiGate-1000F, FortiGate-1001F, FortiGate-1100E, FortiGate-1101E, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3200F, FortiGate-3201F, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3600E-DC, FortiGate-3601E, FortiGate-3700D, FortiGate-3700F, FortiGate-3701F, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate-4800F, FortiGate-4801F, FortiGate-4801F-NEBS <b>FortiGate 5000 Series:</b> FortiGate-5001E, FortiGate-5001E1 <b>FortiGate 6000 Series:</b> FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC <b>FortiGate 7000 Series:</b> FortiGate-7000E, FortiGate-7000F, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC <b>FortiGate DC:</b> FortiGate-400F-DC, FortiGate-401E-DC, FortiGate-401F-DC, FortiGate-800D-DC, FortiGate-900G-DC, FortiGate-901G-DC, FortiGate-1100E-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-ACDC, FortiGate-3000F-DC, FortiGate-3001F-ACDC, FortiGate-3001F-DC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3700D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC, FortiGate-4800F-DC, FortiGate-4801F-DC, FortiGate-4801F-DC-NEBS	7.6

Model	Firmware Version
<p><b>FortiWiFi:</b> FWF-40F, FWF-40F-3G4G, FWF-50G, FWF-50G-5G, FWF-50G-DSL, FWF-50G-SFP, FWF-51G, FWF-60F, FWF-61F, FWF-70G, FWF-70G-POE, FWF-71G, FWF-80F-2R, FWF-81F-2R, FWF-80F-2R-3G4G-DSL, FWF-81F-2R-3G4G-DSL, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE</p> <p><b>FortiGate VM:</b> FortiGate-ARM64-AWS, FortiGate-ARM64-Azure, FortiGate-ARM64-GCP, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-Xen</p> <p><b>FortiGate Rugged:</b> FGR-50G-5G, FGR-60F, FGR-60F-3G4G, FGR-70F, FGR-70F-3G4G, FGR-70G, FGR-70G-5G-Dual</p>	
<p><b>FortiGate:</b> FortiGate-40F, FortiGate-40F-3G4G, FortiGate-50G, FortiGate-50G-5G, FortiGate-50G-DSL, FortiGate-50G-SFP, FortiGate-50G-SFP-POE, FortiGate-51G, FortiGate-51G-5G, FortiGate-51G-SFP-POE, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-70F, FortiGate-71F, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-DSL, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-90G, FortiGate-91E, FortiGate-91G, FortiGate-100F, FortiGate-101F, FortiGate-120G, FortiGate-121G, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-200G, FortiGate-201E, FortiGate-201F, FortiGate-201G, FortiGate-300E, FortiGate-301E, FortiGate-400E, FortiGate-400F, FortiGate-400E-Bypass, FortiGate-401E, FortiGate-401F, FortiGate-500E, FortiGate-501E, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-800D, FortiGate-900D, FortiGate-900G, FortiGate-901G, FortiGate-1000D, FortiGate-1000F, FortiGate-1001F, FortiGate-1100E, FortiGate-1101E, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3200F, FortiGate-3201F, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3600E-DC, FortiGate-3601E, FortiGate-3700D, FortiGate-3700F, FortiGate-3701F, FortiGate-3800D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate-4800F, FortiGate-4801F, FortiGate-4801F-NEBS</p> <p><b>FortiGate 5000 Series:</b> FortiGate-5001E, FortiGate-5001E1</p> <p><b>FortiGate 6000 Series:</b> FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC</p> <p><b>FortiGate 7000 Series:</b> FortiGate-7000E, FortiGate-7000F, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC</p>	7.4

Model	Firmware Version
<p><b>FortiGate DC:</b> FortiGate-400F-DC, FortiGate-401E-DC, FortiGate-401F-DC, FortiGate-800D-DC, FortiGate-900G-DC, FortiGate-901G-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-DC, FortiGate-3000F-ACDC, FortiGate-3001F-DC, FortiGate-3001F-ACDC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC, FortiGate-4801F-DC-NEBS</p> <p><b>FortiWiFi:</b> FWF-40F, FWF-40F-3G4G, FWF-50G, FWF-50G-5G, FWF-50G-DSL, FWF-50G-SFP, FWF-51G, FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-80F-2R, FWF-81F-2R, FWF-80F-2R-3G4G-DSL, FWF-81F-2R-3G4G-DSL, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE</p> <p><b>FortiGate VM:</b> FortiGate-ARM64-AWS, FortiGate-ARM64-Azure, FortiGate-ARM64-GCP, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-Xen</p> <p><b>FortiGate Rugged:</b> FGR-60F, FGR-60F-3G4G, FGR-70F, FGR-70F-3G4G</p>	
<p><b>FortiGate:</b> Container-FortiOS, FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-70F, FortiGate-70G, FortiGate-70G-POE, FortiGate-71F, FortiGate-71G, FortiGate-71G-POE, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-DSL, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90G, FortiGate-91E, FortiGate-91G, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-120G, FortiGate-121G, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300E, FortiGate-301E, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-400F, FortiGate-401E, FortiGate-401F, FortiGate-500E, FortiGate-501E, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-800D, FortiGate-900D, FortiGate-900G, FortiGate-901G, FortiGate-1000D, FortiGate-1000F, FortiGate-1001F, FortiGate-1100E, FortiGate-1101E, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3200F, FortiGate-3201F, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3601E, FortiGate-3700D, FortiGate-3700F, FortiGate-3701F, FortiGate-3800D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate-4800F, FortiGate-4801F, FortiGate-4801F-NEBS</p> <p><b>FortiGate 5000 Series:</b> FortiGate-5001E, FortiGate-5001E1</p>	7.2

Model	Firmware Version
<p><b>FortiGate 6000 Series:</b> FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC</p>	
<p><b>FortiGate 7000 Series:</b> FortiGate-7000E, FortiGate-7000F, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC</p>	
<p><b>FortiGate DC:</b> FortiGate-400F-DC, FortiGate-401E-DC, FortiGate-401F-DC, FortiGate-800D-DC, FortiGate-900G-DC, FortiGate-901G-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-DC, FortiGate-3000F-ACDC, FortiGate-3001F-DC, FortiGate-3001F-ACDC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC, FortiGate-4800F-DC, FortiGate-4801F-DC, FortiGate-4801F-DC-NEBS</p>	
<p><b>FortiWiFi:</b> FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-70G, FWF-71G, FWF-80F-2R, FWF-80F-2R-3G4G-DSL, FWF-81F-2R, FWF-81F-2R-3G4G-DSL, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE</p>	
<p><b>FortiGate VM:</b> FortiGate-ARM64-AWS, FortiGate-ARM64-Azure, FortiGate-ARM64-GCP, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager</p>	
<p><b>FortiOS-VM:</b> FOS-VM64, FOS-VM64-HV, FOS-VM64-KVM, FOS-VM64-Xen</p>	
<p><b>FortiGate Rugged:</b> FGR-60F, FGR-60F-3G4G, FGR-70F, FGR-70F-3G4G</p>	

Model	Firmware Version
<p><b>FortiGate:</b> FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-70F, FortiGate-71F, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-91E, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300D, FortiGate-300E, FortiGate-301E, FortiGate-400D, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-400F, FortiGate-401E, FortiGate-401F, FortiGate-500D, FortiGate-500E, FortiGate-501E, FortiGate-600D, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-800D, FortiGate-900D, FortiGate-1000D, FortiGate-1100E, FortiGate-1101E, FortiGate-1200D, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3601E, FortiGate-3700D, FortiGate-3800D, FortiGate-3810D, FortiGate-3815D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F,</p> <p><b>FortiGate 5000 Series:</b> FortiGate-5001D, FortiGate-5001E, FortiGate-5001E1</p> <p><b>FortiGate DC:</b> FortiGate-400F-DC, FortiGate-401E-DC, FortiGate-401F-DC, FortiGate-800D-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-DC, FortiGate-3000F-ACDC, FortiGate-3001F-DC, FortiGate-3001F-ACDC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3810D-DC, FortiGate-3815D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC</p> <p><b>FortiWiFi:</b> FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-80F-2R, FWF-81F-2R, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE</p> <p><b>FortiGate VM:</b> FortiGate-ARM64-AWS, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager</p> <p><b>FortiOS-VM:</b> FOS-VM64, FOS-VM64-HV, FOS-VM64-KVM, FOS-VM64-Xen</p> <p><b>FortiGate Rugged:</b> FGR-60F, FGR-60F-3G4G</p>	7.0

Model	Firmware Version
<p><b>FortiGate:</b> FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-91E, FortiGate-100D, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300D, FortiGate-300E, FortiGate-301E, FortiGate-400D, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-401E, FortiGate-500D, FortiGate-500E, FortiGate-501E, FortiGate-600D, FortiGate-600E, FortiGate-601E, FortiGate-800D, FortiGate-900D, FortiGate-1000D, FortiGate-1100E, FortiGate-1101E, FortiGate-1200D, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3100D, FortiGate-3200D, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3600E, FortiGate-3601E, FortiGate-3700D, FortiGate-3800D, FortiGate-3810D, FortiGate-3815D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F,</p> <p><b>FortiGate 5000 Series:</b> FortiGate-5001D, FortiGate-5001E, FortiGate-5001E1</p> <p><b>FortiGate DC:</b> FortiGate-401E-DC, FortiGate-800D-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3810D-DC, FortiGate-3815D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC</p> <p><b>FortiGate Hardware Low Encryption:</b> FortiGate-100D-LENC</p> <p><b>FortiWiFi:</b> FWF-40F, FWF-40F-3G4G, FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-80F-2R, FWF-81F-2R, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE</p> <p><b>FortiGate VM:</b> FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-ALIONDEMAND, FortiGate-VM64-AWS, FortiGate-VM64-AZUREONDEMAND, FortiGate-VM64-Azure, FortiGate-VM64-GCP, VM64-GCPONDEMAND, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager</p> <p><b>FortiOS-VM:</b> FOS-VM64, FOS-VM64-HV, FOS-VM64-KVM, FOS-VM64-Xen</p> <p><b>FortiGate Rugged:</b> FGR-60F, FGR-60F-3G4G</p>	6.4

Model	Firmware Version
<p><b>FortiGate:</b> FortiGate-30E, FortiGate-30E-3G4G-GBL, FortiGate-30E-3G4G-INTL, FortiGate-30E-3G4G-NAM, FortiGate-40F, FortiGate-40F-3G4G, FortiGate-50E, FortiGate-51E, FortiGate-52E, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-80D, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-91E, FortiGate-92D, FortiGate-100D, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-140D, FortiGate-140D-POE, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201F, FortiGate-201E, FortiGate-300D, FortiGate-300E, FortiGate-301E, FortiGate-400D, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-401E, FortiGate-500D, FortiGate-500E, FortiGate-501E, FortiGate-600D, FortiGate-600E, FortiGate-601E, FortiGate-800D, FortiGate-900D, FortiGate-1000D, FortiGate-1100E, FortiGate-1101E, FortiGate-1200D, FortiGate-1500D, FortiGate-1500DT, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-3000D, FortiGate-3100D, FortiGate-3200D, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3600E, FortiGate-3700D, FortiGate-3800D, FortiGate-3810D, FortiGate-3815D, FortiGate-3960E, FortiGate-3980E</p> <p><b>FortiGate 5000 Series:</b> FortiGate-5001D, FortiGate-5001E, FortiGate-5001E1</p> <p><b>FortiGate DC:</b> FortiGate-401E-DC, FortiGate-800D-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-2201E-ACDC, FortiGate-3000D-DC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3810D-DC, FortiGate-3815D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC</p> <p><b>FortiGate Hardware Low Encryption:</b> FortiGate-100D-LENC</p> <p><b>FortiWiFi:</b> FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-40F, FWF-40F-3G4G, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-80F-2R, FortiWiFi-80F-2R-3G4G-DSL, FWF-81F-2R, FWF-81F-2R-POE</p> <p><b>FortiGate VM:</b> FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-ALIONDEMAND, FortiGate-VM64-AWS, FortiGate-VM64-AWSONDEMAND, FortiGate-VM64-AZUREONDEMAND, FortiGate-VM64-Azure, FortiGate-VM64-GCP, VM64-GCPONDEMAND, FortiGate-VM64-HV, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager</p> <p><b>FortiOS-VM:</b> FOS-VM64, FOS-VM64-HV, FOS-VM64-KVM, FOS-VM64-Xen</p> <p><b>FortiGate Rugged:</b> FGR-30D, FGR-35D, FGR-60F, FGR-60F-3G4G, FGR-90D</p>	6.2

## FortiGate special branch models

The following FortiGate models are released on special branches of FortiOS. FortiAnalyzer version 7.6.4 supports these models on the identified FortiOS version and build number.

For information about supported FortiGate models released with FortiOS firmware, see [FortiGate models on page 31](#).

## FortiOS 7.4

FortiGate Model	FortiOS Version
FortiGate-30G, FortiGate-31G	7.4.8
FortiGate-70G, FortiGate-70G-POE, FortiGate-70G-POE-5G FortiGate-71G, FortiGate-71G-POE, FortiGate-71G-POE-5G	7.4.8
FortiGateRugged-50G-5G	7.4.8
FortiGateRugged-60G, FortiGateRugged-60G-5G, FortiGateRugged-60G-5G-M12, FortiGateRugged-60G-M12	7.4.8
FortiGateRugged-70G, FortiGateRugged-70G-5G, FortiGateRugged-70G-5G-Dual	7.4.8
FortiWiFi-30G, FortiWiFi-31G	7.4.8
FortiWiFi-70G, FortiWiFi-70G-POE, FortiWiFi-71G	7.4.8

## FortiOS 7.2

FortiGate Model	FortiOS Version
FortiGate-30G, FortiGate-31G	7.2.11
FortiGate-70G, FortiGate-71G	7.2.11
FortiGate-70G-POE, FortiGate-71G-POE	7.2.11
FortiGate-200G, FortiGate-201G	7.2.11
FortiGate-700G, FortiGate-701G	7.2.11
FortiWiFi-30G, FortiWiFi-31G	7.2.11
FortiWiFi-70G, FortiWiFi-70G-POE, FortiWiFi-71G	7.2.11

## FortiOS 7.0

FortiGate Model	FortiOS Version
FortiGate-50G, FortiGate-50G-5G, FortiGate-50G-DSL, FortiGate-50G-SFP, FortiGate-50G-SFP-POE	7.0.17
FortiGate-51G, FortiGate-51G-5G, FortiGate-51G-SFP-POE	7.0.17

FortiGate Model	FortiOS Version
FortiGate-80F-DSL	7.0.17
FortiGate-90G, FortiGate-91G	7.0.17
FortiGate-120G, FortiGate-121G	7.0.16
FortiGate-900G, FortiGate-900G-DC FortiGate-901G, FortiGate-901G-DC	7.0.17
FortiGate-1000F, FortiGate-1001F	7.0.17
FortiGate-3200F, FortiGate-3201F	7.0.17
FortiGate-3700F, FortiGate-3701F	7.0.17
FortiGate-4800F, FortiGate-4800F-DC FortiGate-4801F, FortiGate-4801F-DC, FortiGate-4801F-NEBS, FortiGate-4801F-DC-NEBS	7.0.17
FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC	7.0.16
FortiGate-7000E, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC	7.0.16
FortiGate-7000F, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC	7.0.16
FortiGateRugged-50G-5G	7.0.17
FortiGateRugged-70F, FortiGateRugged-70F-3G4G	7.0.17
FortiGateRugged-70G	7.0.15
FortiGateRugged-70G-5G-Dual	7.0.16
FortiWiFi-50G, FortiWiFi-50G-5G, FortiWiFi-50G-DSL, FortiWiFi-50G-SFP	7.0.17
FortiWiFi-51G	7.0.17
FortiWiFi-51G-5G	7.0.15
FortiWiFi-80F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-DSL	7.0.17

## FortiOS 6.4

FortiGate Model	FortiOS Version
FortiGate-400F, FortiGate-401F, FortiGate-400F-DC, FortiGate-401F-DC	6.4.13
FortiGate-600F, FortiGate-601F	6.4.13

FortiGate Model	FortiOS Version
FortiGate-3500F	6.4.6
FortiGate-3501F	6.4.6
FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC	6.4.13
FortiGate-7000E, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC	6.4.13
FortiGate-7000F, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC	6.4.13
FortiWiFi-80F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-DSL	6.4.7

## FortiOS 6.2

FortiGate Model	FortiOS Version
FortiGate-1800F, FortiGate-1800F-DC FortiGate-1801F, FortiGate-1801F-DC	6.2.9
FortiGate-2600F, FortiGate-2600F-DC FortiGate-2601F, FortiGate-2601F-DC	6.2.9
FortiGate-4200F, FortiGate-4200F-DC FortiGate-4201F, FortiGate-4201F-DC	6.2.9
FortiGate-4400F, FortiGate-4400F-DC FortiGate-4401F, FortiGate-4401F-DC	6.2.9
FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC	6.2.13
FortiGate-7000E, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC FortiGate-7000F, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC	6.2.13
FortiWiFi-80F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-DSL	6.2.6

## FortiOS 6.0

FortiGate Model	FortiOS Version
FortiGate-30E-3G4G-GBL	6.0

FortiGate Model	FortiOS Version
FortiGate-40F, FortiGate-40F-3G4G	6.0
FortiGate-41F	6.0.6
FortiGate-41F-3G4G	6.0.6
FortiGate-60F, FortiGate-61F	6.0
FortiGate-100F, FortiGate-101F	6.0
FortiGate-1100E, FortiGate-1100E-DC, FortiGate-1101E	6.0
FortiGate-1800F, FortiGate-1800F-DC	6.0
FortiGate-1801F, FortiGate-1801F-DC	6.0
FortiGate-2200E, FortiGate-2201E, FortiGate-2201E-ACDC	6.0
FortiGate-3300E, FortiGate-3301E	6.0
FortiWiFi-40F, FortiWiFi-40F-3G4G	6.0
FortiWiFi-41F	6.0.6
FortiWiFi-41F-3G4G	6.0.6
FortiWiFi-60F, FortiWiFi-61F	6.0

## FortiCarrier models

The following FortiCarrier models are released with FortiCarrier firmware.

For information about supported FortiCarrier models on special branch releases of FortiCarrier firmware, see [FortiCarrier special branch models on page 44](#).

Model	Firmware Version
<b>FortiCarrier:</b> FortiCarrier-3000D, FortiCarrier-3000F, FortiCarrier-3001F, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3200F, FortiCarrier-3201F, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3700F, FortiCarrier-3701F, FortiCarrier-3960E, FortiCarrier-3980E, FortiCarrier-4200F, FortiCarrier-4201F, FortiCarrier-4400F, FortiCarrier-4401F, FortiCarrier-4800F, FortiCarrier-4801F, FortiCarrier-4801F-NEBS <b>FortiCarrier 5000 Series:</b> FortiCarrier-5001E, FortiCarrier-5001E1 <b>FortiCarrier 6000 Series:</b> FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC <b>FortiCarrier 7000 Series:</b> FortiCarrier-7000E, FortiCarrier-7000F, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC	7.6

Model	Firmware Version
<p><b>FortiCarrier-DC:</b> FortiCarrier-3000D-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3000F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC, FortiCarrier-4200F-DC, FortiCarrier-4201F-DC, FortiCarrier-4400F-DC, FortiCarrier-4401F-DC, FortiCarrier-4800F-DC, FortiCarrier-4801F-DC, FortiCarrier-4801F-DC-NEBS</p> <p><b>FortiCarrier-VM:</b> FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-Azure, FortiCarrier-ARM64-GCP, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen</p>	
<p><b>FortiCarrier:</b> FortiCarrier-2600F, FortiCarrier-2601F, FortiCarrier-3000D, FortiCarrier-3000F, FortiCarrier-3001F, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3200F, FortiCarrier-3201F, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3700F, FortiCarrier-3701F, FortiCarrier-3800D, FortiCarrier-3960E, FortiCarrier-3980E, FortiCarrier-4200F, FortiCarrier-4201F, FortiCarrier-4400F, FortiCarrier-4401F, FortiCarrier-4800F, FortiCarrier-4801F, FortiCarrier-4801F-NEBS</p> <p><b>FortiCarrier 5000 Series:</b> FortiCarrier-5001E, FortiCarrier-5001E1</p> <p><b>FortiCarrier 6000 Series:</b> FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC</p> <p><b>FortiCarrier 7000 Series:</b> FortiCarrier-7000E, FortiCarrier-7000F, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC</p> <p><b>FortiCarrier-DC:</b> FortiCarrier-2600F-DC, FortiCarrier-2601F-DC, FortiCarrier-3000D-DC, FortiCarrier-3000F-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC, FortiCarrier-4200F-DC, FortiCarrier-4201F-DC, FortiCarrier-4400F-DC, FortiCarrier-4401F-DC, FortiCarrier-4801F-DC-NEBS</p> <p><b>FortiCarrier-VM:</b> FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-Azure, FortiCarrier-ARM64-GCP, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-KVM, FortiCarrier-VM64-IBM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen</p>	7.4

Model	Firmware Version
<p><b>FortiCarrier:</b> FortiCarrier-2600F, FortiCarrier-2601F, FortiCarrier-3000D, FortiCarrier-3000F, FortiCarrier-3001F, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3200F, FortiCarrier-3201F, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3700F, FortiCarrier-3701F, FortiCarrier-3800D, FortiCarrier-3960E, FortiCarrier-3980E, FortiCarrier-4200F, FortiCarrier-4201F, FortiCarrier-4400F, FortiCarrier-4401F, FortiCarrier-4800F, FortiCarrier-4801F, FortiCarrier-4801F-NEBS</p> <p><b>FortiCarrier 5000 Series:</b> FortiCarrier-5001E, FortiCarrier-5001E1</p> <p><b>FortiCarrier 6000 Series:</b> FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC</p> <p><b>FortiCarrier 7000 Series:</b> FortiCarrier-7000E, FortiCarrier-7000F, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC</p> <p><b>FortiCarrier-DC:</b> FortiCarrier-2600F-DC, FortiCarrier-2601F-DC, FortiCarrier-3000D-DC, FortiCarrier-3000F-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC, FortiCarrier-4200F-DC, FortiCarrier-4201F-DC, FortiCarrier-4400F-DC, FortiCarrier-4401F-DC, FortiCarrier-4801F-DC-NEBS</p> <p><b>FortiCarrier-VM:</b> FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-Azure, FortiCarrier-ARM64-GCP, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen</p>	7.2
<p><b>FortiCarrier:</b> FortiCarrier-2600F, FortiCarrier-2601F, FortiCarrier-3000D, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3800D, FortiCarrier-3810D, FortiCarrier-3815D, FortiCarrier-3960E, FortiCarrier-3980E</p> <p><b>FortiCarrier 5000 Series:</b> FortiCarrier-5001D, FortiCarrier-5001E, FortiCarrier-5001E1</p> <p><b>FortiCarrier-DC:</b> FortiCarrier-2600F-DC, FortiCarrier-2601F-DC, FortiCarrier-3000D-DC, FortiCarrier-3000F-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3810D-DC, FortiCarrier-3815D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC</p> <p><b>FortiCarrier-VM:</b> FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen, FortiCarrier-ARM64-KVM</p>	7.0

Model	Firmware Version
<p><b>FortiCarrier:</b> FortiCarrier-3000D, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3800D, FortiCarrier-3810D, FortiCarrier-3815D, FortiCarrier-3960E, FortiCarrier-3980E</p> <p><b>FortiCarrier 5000 Series:</b> FortiCarrier-5001D, FortiCarrier-5001E, FortiCarrier-5001E1</p> <p><b>FortiCarrier-DC:</b> FortiCarrier-3000D-DC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3810D-DC, FortiCarrier-3815D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC</p> <p><b>FortiCarrier-VM:</b> FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen</p>	6.4
<p><b>FortiCarrier:</b> FortiCarrier-3000D, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3800D, FortiCarrier-3810D, FortiCarrier-3815D, FortiCarrier-3960E, FortiCarrier-3980E</p> <p><b>FortiCarrier 5000 Series:</b> FortiCarrier-5001D, FortiCarrier-5001E, FortiCarrier-5001E1</p> <p><b>FortiCarrier-DC:</b> FortiCarrier-3000D-DC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3810D-DC, FortiCarrier-3815D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC</p> <p><b>FortiCarrier 6K and 7K:</b> FortiCarrier-6000F, FortiCarrier-6300F, FortiCarrier-6301F, FortiCarrier-6500F, FortiCarrier-6501F, FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7000F, FortiCarrier-7121F, FortiCarrier-7121F-2</p> <p><b>FortiCarrier 6K and 7K DC:</b> FortiCarrier-6000F-DC, FortiCarrier-6300F-DC, FortiCarrier-6301F-DC, FortiCarrier-6500F-DC, FortiCarrier-6501F-DC, FortiCarrier-7060E-8-DC, FortiCarrier-7121F-DC, FortiCarrier-7121F-2-DC</p> <p><b>FortiCarrier-VM:</b> FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen</p>	6.2

## FortiCarrier special branch models

The following FortiCarrier models are released on special branches of FortiOS Carrier. FortiAnalyzer version 7.6.4 supports these models on the identified FortiOS Carrier version and build number.

For information about supported FortiCarrier models released with FortiOS Carrier firmware, see [FortiCarrier models on page 41](#).

## FortiCarrier 7.0

FortiCarrier Model	FortiCarrier Version
FortiCarrier-3200F, FortiCarrier-3201F	7.0.17
FortiCarrier-3700F, FortiCarrier-3701F	7.0.17
FortiCarrier-4800F, FortiCarrier-4800F-DC FortiCarrier-4801F, FortiCarrier-4801F-DC, FortiCarrier-4801F-NEBS, FortiCarrier-4801F-DC-NEBS	7.0.17
FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC	7.0.16
FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC	7.0.16
FortiCarrier-7000F, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC	7.0.16

## FortiCarrier 6.4

FortiCarrier Model	FortiCarrier Version
FortiCarrier-3500F	6.4.6
FortiCarrier-3501F	6.4.6
FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC	6.4.13
FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC	6.4.13
FortiCarrier-7000F, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC	6.4.13

## FortiCarrier 6.2

FortiCarrier Model	FortiCarrier Version
FortiCarrier-4200F, FortiCarrier-4200F-DC FortiCarrier-4201F, FortiCarrier-4201F-DC FortiCarrier-4400F, FortiCarrier-4400F-DC, FortiCarrier-4401F, FortiCarrier-4401F-DC	6.2.9

FortiCarrier Model	FortiCarrier Version
FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC	6.2.13
FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC	6.2.13
FortiCarrier-7000F, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC	

## FortiCarrier 6.0

FortiCarrier Model	FortiCarrier Version
FortiCarrier-VM64-Azure	6.0

## FortiADC models

Model	Firmware Version
<b>FortiADC:</b> FortiADC-100F, FortiADC-120F, FortiADC-200F, FortiADC-220F, FortiADC-300D, FortiADC-300F, FortiADC-320F, FortiADC-400F, FortiADC-420F, FortiADC-1000F, FortiADC-1200F, FortiADC-2000F, FortiADC-2200F, FortiADC-4000F, FortiADC-4200F, FortiADC-5000F <b>FortiADC VM:</b> FortiADC-ALI, FortiADC-ALI_ONDEMAND, FortiADC-AZURE, FortiADC-AZURE_ONDEMAND, FortiADC-GCP, FortiADC-GCP_ONDEMAND, FortiADC-HYV, FortiADC-IBM, FortiADC-KVM, FortiADC-OCI, FortiADC-XENAWS, FortiADC-XENAWS_ONDEMAND, FortiADC-XENOPEN, FortiADC-XENSERVER, FortiADC-VM	7.6
<b>FortiADC:</b> FortiADC-100F, FortiADC-120F, FortiADC-200D, FortiADC-200F, FortiADC-220F, FortiADC-300D, FortiADC-300F, FortiADC-320F, FortiADC-400D, FortiADC-400F, FortiADC-420F, FortiADC-700D, FortiADC-1000F, FortiADC-1200F, FortiADC-1500D, FortiADC-2000D, FortiADC-2000F, FortiADC-2200F, FortiADC-4000D, FortiADC-4000F, FortiADC-4200F, FortiADC-5000F <b>FortiADC VM:</b> FortiADC-ALI, FortiADC-ALI_ONDEMAND, FortiADC-AZURE, FortiADC-AZURE_ONDEMAND, FortiADC-GCP, FortiADC-GCP_ONDEMAND, FortiADC-HYV, FortiADC-IBM, FortiADC-KVM, FortiADC-OCI, FortiADC-XENAWS, FortiADC-XENAWS_ONDEMAND, FortiADC-XENOPEN, FortiADC-XENSERVER, FortiADC-VM	7.4
<b>FortiADC:</b> FortiADC-100F, FortiADC-120F, FortiADC-200D, FortiADC-200F, FortiADC-220F, FortiADC-300D, FortiADC-300F, FortiADC-400D, FortiADC-400F, FortiADC-700D, FortiADC-1000F, FortiADC-1200F, FortiADC-1500D, FortiADC-2000D, FortiADC-2000F, FortiADC-2200F, FortiADC-4000D, FortiADC-4000F, FortiADC-4200F, FortiADC-5000F	6.2, 7.0, 7.1, 7.2

Model	Firmware Version
<b>FortiADC VM:</b> FortiADC-ALI, FortiADC-ALI_ONDEMAND, FortiADC-AZURE, FortiADC-AZURE_ONDEMAND, FortiADC-GCP, FortiADC-GCP_ONDEMAND, FortiADC-HYV, FortiADC-IBM, FortiADC-KVM, FortiADC-OCI, FortiADC-XENAWS, FortiADC-XENAWS_ONDEMAND, FortiADC-XENOPEN, FortiADC-XENSERVEN, FortiADC-VM	

## FortiNDR models

Model	Firmware Version
<b>FortiNDR:</b> FortiNDR-1000F, FortiNDR-2500G, FortiNDR-3500F, FortiNDR-3600G <b>FortiNDR-VM:</b> FortiNDR-KVM, FortiNDR-VM, FortiNDR-VMC	7.4, 7.6
<b>FortiNDR:</b> FortiNDR-1000F, FortiNDR-3500F <b>FortiNDR-VM:</b> FortiNDR-KVM, FortiNDR-VM	7.2
<b>FortiNDR:</b> FortiNDR-3500F <b>FortiNDR-VM:</b> FortiNDR-KVM, FortiNDR-VM	7.0, 7.1

## FortiAnalyzer models

Model	Firmware Version
<b>FortiAnalyzer:</b> FortiAnalyzer-150G, FortiAnalyzer-300G, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-1000G, FortiAnalyzer-2000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3100G, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3510G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3900E, FortiAnalyzer-K8S-CLOUD <b>FortiAnalyzer VM:</b> FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-AWS-OnDemand, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-KVM-CLOUD, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-VIO-CLOUD, FortiAnalyzer-VM64-Xen	7.6
<b>FortiAnalyzer:</b> FortiAnalyzer-150G, FortiAnalyzer-300F, FortiAnalyzer-300G, FortiAnalyzer-400E, FortiAnalyzer-800F, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-1000G, FortiAnalyzer-2000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3100G, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3510G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3900E, FortiAnalyzer-K8S-CLOUD	7.4

Model	Firmware Version
<b>FortiAnalyzer VM:</b> FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-AWS-OnDemand, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-Azure-OnDemand, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-KVM-CLOUD, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-VIO-CLOUD, FortiAnalyzer-VM64-Xen	
<b>FortiAnalyzer:</b> FortiAnalyzer-150G, FortiAnalyzer-300F, FortiAnalyzer-300G, FortiAnalyzer-400E, FortiAnalyzer-800F, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-1000G, FortiAnalyzer-2000E, FortiAnalyzer-3000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3100G, FortiAnalyzer-3500E, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3510G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3900E, FortiAnalyzer-K8S-CLOUD	7.2
<b>FortiAnalyzer VM:</b> FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-AWS-OnDemand, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-Azure-OnDemand, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-KVM-CLOUD, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-VIO-CLOUD, FortiAnalyzer-VM64-Xen	
<b>FortiAnalyzer:</b> FortiAnalyzer-150G, FortiAnalyzer-200F, FortiAnalyzer-300F, FortiAnalyzer-300G, FortiAnalyzer-400E, FortiAnalyzer-800F, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-1000G, FortiAnalyzer-2000E, FortiAnalyzer-3000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3100G, FortiAnalyzer-3500E, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3900E, FortiAnalyzer-K8S-CLOUD	7.0
<b>FortiAnalyzer VM:</b> FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-ALI-OnDemand, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-Azure-OnDemand, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-GCP-OnDemand, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-KVM-CLOUD, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-VIO-CLOUD, FortiAnalyzer-VM64-Xen	

## FortiAP models

Model	Firmware Version
FortiAP-231FL, FortiAP-231K, FortiAP-241K, FortiAP-243K, FortiAP-431FL, FortiAP-432FR, FortiAP-432G, FortiAP-433FL, FortiAP-441K, FortiAP-443K	7.4
FortiAP-23JF, FortiAP-221E, FortiAP-222E, FortiAP-223E, FortiAP-224E, FortiAP-231E, FortiAP-231F, FortiAP-231G, FortiAP-233G, FortiAP-234F, FortiAP-234G, FortiAP-431F, FortiAP-431G, FortiAP-432F, FortiAP-432G, FortiAP-433F, FortiAP-433G, FortiAP-831F	7.2

Model	Firmware Version
FortiAP-23JF, FortiAP-221E, FortiAP-222E, FortiAP-223E, FortiAP-224E, FortiAP-231E, FortiAP-231F, FortiAP-234F, FortiAP-431F, FortiAP-432F, FortiAP-433F, FortiAP-831F	7.0
FortiAP-23JF, FortiAP-221E, FortiAP-222E, FortiAP-223E, FortiAP-224E, FortiAP-231E, FortiAP-231F, FortiAP-234F, FortiAP-321E, FortiAP-421E, FortiAP-423E, FortiAP-431F, FortiAP-432F, FortiAP-433F, FortiAP-831F, FortiAP-S221E, FortiAP-S223E, FortiAP-S421E, FortiAP-S422E, FortiAP-S423E	6.4
FortiAP-221E, FortiAP-222E, FortiAP-223E, FortiAP-231E, FortiAP-321E, FortiAP-421E, FortiAP-423E, FortiAP-S221E, FortiAP-S223E, FortiAP-S421E, FortiAP-S422E, FortiAP-S423E	6.2
FortiAP-11C, FortiAP-14C, FortiAP-21B, FortiAP-21D, FortiAP-22B, FortiAP-24D, FortiAP-25D, FortiAP-28C, FortiAP-112B, FortiAP-112D, FortiAP-214B, FortiAP-221B, FortiAP-221C, FortiAP-221E, FortiAP-222, FortiAP-222C, FortiAP-222E, FortiAP-223B, FortiAP-223C, FortiAP-223E, FortiAP-224D, FortiAP-224E, FortiAP-231E, FortiAP-320B, FortiAP-320C, FortiAP-321C, FortiAP-321CR, FortiAP-321E, FortiAP-322CR, FortiAP-323CR, FortiAP-421E, FortiAP-423E, FortiAP-C23JD, FortiAP-C24JE, FortiAP-C220C, FortiAP-C225C, FortiAP-S221E, FortiAP-S223E, FortiAP-S311C, FortiAP-S313C, FortiAP-S321C, FortiAP-S322C, FortiAP-S323C, FortiAP-S421E, FortiAP-S422E, FortiAP-S423E, FortiAP-U24JEV, FortiAP-U221EV, FortiAP-U223EV, FortiAP-U231F, FortiAP-U231G, FortiAP-U234F, FortiAP-U321EV, FortiAP-U323EV, FortiAP-U421EV, FortiAP-U422EV, FortiAP-U423EV, FortiAP-U431F, FortiAP-U432F, FortiAP-U433F	6.0

## FortiAuthenticator models

Model	Firmware Version
<b>FortiAuthenticator:</b> FAC-200E, FAC-300F, FAC-400E, FAC-800F, FAC-2000E, FAC-3000E, FAC-3000F <b>FortiAuthenticator VM:</b> FAC-VM	6.5, 6.6
<b>FortiAuthenticator:</b> FAC-200D, FAC-200E, FAC-300F, FAC-400C, FAC-400E, FAC-800F, FAC-1000C, FAC-1000D, FAC-2000E, FAC-3000D, FAC-3000E, FAC-3000F <b>FortiAuthenticator VM:</b> FAC-VM	6.4
<b>FortiAuthenticator:</b> FAC-200D, FAC-200E, FAC-300F, FAC-400C, FAC-400E, FAC-800F, FAC-1000C, FAC-1000D, FAC-2000E, FAC-3000D, FAC-3000E <b>FortiAuthenticator VM:</b> FAC-VM	6.0, 6.1, 6.2, 6.3

## FortiCache models

Model	Firmware Version
<b>FortiCache:</b> FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3000E, FCH-3900E <b>FortiCache VM:</b> FCH-KVM, FCH-VM64	4.1, 4.2
<b>FortiCache:</b> FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3900E <b>FortiCache VM:</b> FCH-VM64	4.0

## FortiDDoS models

Model	Firmware Version
<b>FortiDDoS:</b> FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-1500G, FortiDDoS-1500G-LR, FortiDDoS-2000F, FortiDDoS-2000G, FortiDDoS-3000F, FortiDDoS-3000G <b>FortiDDoS VM:</b> FortiDDoS-VM	7.0
<b>FortiDDoS:</b> FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-2000F, FortiDDoS-3000F <b>FortiDDoS VM:</b> FortiDDoS-VM	6.4, 6.5, 6.6
<b>FortiDDoS:</b> FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-2000F <b>FortiDDoS VM:</b> FortiDDoS-VM	6.3
<b>FortiDDoS:</b> FortiDDoS-200F, FortiDDoS-1500F <b>FortiDDoS VM:</b> FortiDDoS-VM	6.2
<b>FortiDDoS:</b> FortiDDoS-200B, FortiDDoS-400B, FortiDDoS-600B, FortiDDoS-800B, FortiDDoS-900B, FortiDDoS-1000B, FortiDDoS-1200B, FortiDDoS-1500E, FortiDDoS-2000B, FortiDDoS-2000E	5.6, 5.7

## FortiDeceptor models

Model	Firmware Version
<b>FortiDeceptor:</b> FDC-100G, FDC-1000F, FDC-1000G <b>FortiDeceptor Rugged:</b> FDCR-100G <b>FortiDeceptor VM:</b> FDC-VM	5.0, 5.1, 5.2, 5.3, 6.0, 6.1
<b>FortiDeceptor:</b> FDC-1000F, FDC-1000G <b>FortiDeceptor Rugged:</b> FDCR-100G <b>FortiDeceptor VM:</b> FDC-VM	4.3

## FortiFirewall models

Some of the following FortiFirewall models are released on special branches of FortiFirewall firmware. FortiAnalyzer version 7.6.4 supports these models on the identified FortiFirewall firmware version and build number.

Model	Firmware Version
<b>FortiFirewall:</b> FortiFirewall-1801F, FortiFirewall-2600F, FortiFirewall-3001F, FortiFirewall-3501F, FortiFirewall-3980E, FortiFirewall-4200F, FortiFirewall-4400F, FortiFirewall-4401F, FortiFirewall-4801F, FortiFirewall-4801F-NEBS <b>FortiFirewall DC:</b> FortiFirewall-3001F-DC, FortiFirewall-3980E-DC, FortiFirewall-4200F-DC, FortiFirewall-4400F-DC, FortiFirewall-4401F-DC, FortiFirewall-4801F-DC-NEBS <b>FortiFirewall-VM:</b> FortiFirewall-VM64, FortiFirewall-VM64-KVM	7.6
<b>FortiFirewall:</b> FortiFirewall-1801F, FortiFirewall-2600F, FortiFirewall-3001F, FortiFirewall-3501F, FortiFirewall-3980E, FortiFirewall-4200F, FortiFirewall-4400F, FortiFirewall-4401F, FortiFirewall-4801F, FortiFirewall-4801F-NEBS <b>FortiFirewall DC:</b> FortiFirewall-3001F-DC, FortiFirewall-3980E-DC, FortiFirewall-4200F-DC, FortiFirewall-4400F-DC, FortiFirewall-4401F-DC, FortiFirewall-4801F-DC-NEBS <b>FortiFirewall-VM:</b> FortiFirewall-VM64, FortiFirewall-VM64-KVM	7.4
<b>FortiFirewall:</b> FortiFirewall-3980E, FortiFirewall-4200F, FortiFirewall-4400F, FortiFirewall-4401F, FortiFirewall-4801F, FortiFirewall-4801F-NEBS <b>FortiFirewall DC:</b> FortiFirewall-4200F-DC, FortiFirewall-4401F-DC, FortiFirewall-4801F-DC-NEBS <b>FortiFirewall-VM:</b> FortiFirewall-VM64, FortiFirewall-VM64-KVM	7.2
<b>FortiFirewall:</b> FortiFirewall-3980E <b>FortiFirewall DC:</b> FortiFirewall-3980E-DC <b>FortiFirewall-VM:</b> FortiFirewall-VM64, FortiFirewall-VM64-KVM	7.0

## FortiFirewall special branch models

Model	Firmware Version	Firmware Build (for special branch)
<b>FortiFirewall:</b> FortiFirewall-3001F <b>FortiFirewall DC:</b> FortiFirewall-3001F-DC,	7.0.10	4955
<b>FortiFirewall:</b> FortiFirewall-3501F <b>FortiFirewall DC:</b> FortiFirewall-3001F-DC,	7.0.10	4955

## FortiFirewallCarrier models

Some of the following FortiFirewallCarrier models are released on special branches of FortiFirewallCarrier firmware. FortiAnalyzer version 7.6.4 supports these models on the identified FortiFirewallCarrier firmware version and build number.

Model	Firmware Version
<b>FortiFirewallCarrier:</b> FortiFirewallCarrier-3001F, FortiFirewallCarrier-3501F, FortiFirewallCarrier-3980E, FortiFirewallCarrier-4200F, FortiFirewallCarrier-4400F, FortiFirewallCarrier-4401F, FortiFirewallCarrier-4801F, FortiFirewallCarrier-4801F-NEBS <b>FortiFirewallCarrier DC:</b> FortiFirewallCarrier-4200F-DC, FortiFirewallCarrier-4401F-DC, FortiFirewallCarrier-4801F-DC-NEBS <b>FortiFirewallCarrier-VM:</b> FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	7.6
<b>FortiFirewallCarrier:</b> FortiFirewallCarrier-1801F, FortiFirewallCarrier-2600F, FortiFirewallCarrier-3001F, FortiFirewallCarrier-3501F, FortiFirewallCarrier-3980E, FortiFirewallCarrier-4200F, FortiFirewallCarrier-4400F, FortiFirewallCarrier-4401F, FortiFirewallCarrier-4801F, FortiFirewallCarrier-4801F-NEBS <b>FortiFirewallCarrier DC:</b> FortiFirewallCarrier-1801F-DC, FortiFirewallCarrier-4200F-DC, FortiFirewallCarrier-4401F-DC, FortiFirewallCarrier-4801F-DC-NEBS <b>FortiFirewallCarrier-VM:</b> FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	7.4
<b>FortiFirewallCarrier:</b> FortiFirewallCarrier-2600F, FortiFirewallCarrier-3980E, FortiFirewallCarrier-4200F, FortiFirewallCarrier-4400F, FortiFirewallCarrier-4801F, FortiFirewallCarrier-4801F-NEBS <b>FortiFirewallCarrier DC:</b> FortiFirewallCarrier-4200F-DC, FortiFirewallCarrier-4801F-DC-NEBS <b>FortiFirewallCarrier-VM:</b> FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	7.2
<b>FortiFirewallCarrier-VM:</b> FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	7.0

## FortiFirewall special branch models

Model	Firmware Version	Firmware Build
<b>FortiFirewallCarrier:</b> FortiFirewallCarrier-1801F, FortiFirewallCarrier-4401F	7.2.6	4609
<b>FortiFirewallCarrier:</b> FortiFirewallCarrier-3001F	7.0.10	4955
<b>FortiFirewallCarrier:</b> FortiFirewallCarrier-3501F	7.0.10	4940

## Fortisolator models

Model	Firmware Version
<b>Fortisolator:</b> Fortisolator-1000F, Fortisolator-1000G, Fortisolator-3000F	2.4
<b>Fortisolator-VM:</b> Fortisolator-VM	

## FortiMail models

Model	Firmware Version
<b>FortiMail:</b> FE-60D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-900G, FE-2000E, FE-2000F, FE-3000D, FE-3000E, FE-3000F, FE-3200E	7.6
<b>FortiMail VM:</b> FML-VM, FML-VM-ALI, FML-VM-AWS, FML-VM-Azure, FML-VM-DK, FML-VM-GCP, FML-VM-HV, FML-VM-KVM, FML-VM-OCP, FML-VM-XEN, FortiMail Cloud	
<b>FortiMail:</b> FE-60D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-2000E, FE-2000F, FE-3000D, FE-3000E, FE-3000F, FE-3200E	7.4
<b>FortiMail VM:</b> FML-VM, FML-VM-ALI, FML-VM-AWS, FML-VM-Azure, FML-VM-DK, FML-VM-GCP, FML-VM-HV, FML-VM-KVM, FML-VM-OCP, FML-VM-XEN	
<b>FortiMail:</b> FE-60D, FE-200D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-2000E, FE-2000F, FE-3000D, FE-3000E, FE-3000F, FE-3200E	7.2
<b>FortiMail VM:</b> FML-VM, FML-VM-ALI, FML-VM-AWS, FML-VM-Azure, FML-VM-DK, FML-VM-GCP, FML-VM-HV, FML-VM-KVM, FML-VM-OCP, FML-VM-XEN	
<b>FortiMail:</b> FE-60D, FE-200D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-1000D, FE-2000E, FE-2000F, FE-3000D, FE-3000E, FE-3000F, FE-3200E	7.0
<b>FortiMail VM:</b> FML-VM, FML-VM-ALI, FML-VM-AWS, FML-VM-Azure, FML-VM-DK, FML-VM-GCP, FML-VM-HV, FML-VM-KVM, FML-VM-OCP, FML-VM-XEN	
<b>FortiMail:</b> FE-60D, FE-200D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-1000D, FE-2000E, FE-3000D, FE-3000E, FE-3200E	6.2, 6.4
<b>FortiMail VM:</b> FML-VM, FML-VM-ALI, FML-VM-AWS, FML-VM-Azure, FML-VM-DK, FML-VM-GCP, FML-VM-HV, FML-VM-KVM, FML-VM-OCP, FML-VM-XEN, <b>FortiMail Cloud</b>	

## FortiNAC models

Model	Firmware Version
<b>FortiNAC:</b> FortiNAC-500, FortiNAC-600, FortiNAC-700, FortiNAC-C-1000C, FortiNAC-C-2000C, FortiNAC-CA-500C, FortiNAC-Manager-550	9.4
<b>FortiNAC VM:</b> FortiNAC-C-VM, FortiNAC-CA-VM, FortiNAC-M-VM	

Model	Firmware Version
<b>FortiNAC:</b> FortiNAC-500, FortiNAC-600, FortiNAC-700, FortiNAC-C-1000C, FortiNAC-C-2000C, FortiNAC-Manager-550 <b>FortiNAC VM:</b> FortiNAC-C-VM, FortiNAC-CA-VM, FortiNAC-M-VM	9.1, 9.2
<b>FortiNAC:</b> FortiNAC-CA-500F, FortiNAC-M-550F, FortiNAC-CA-600F, FortiNAC-CA-700F <b>FortiNAC VM:</b> FortiNAC-VM-ESXI	7.6
<b>FortiNAC:</b> FortiNAC-CA-500F, FortiNAC-M-550F, FortiNAC-CA-600F, FortiNAC-CA-700F <b>FortiNAC VM:</b> FortiNAC-VM-ESXI, FortiNAC-MX-VM	7.4
<b>FortiNAC:</b> FortiNAC-CA-500F, FortiNAC-M-550F, FortiNAC-CA-600F, FortiNAC-CA-700F <b>FortiNAC VM:</b> FortiNAC-F-VM, FortiNAC-VM-ESXI, FortiNAC-MX-VM	7.2

## FortiPAM models

Model	Firmware Version
<b>FortiPAM:</b> FortiPAM-1000G, FortiPAM-3000G <b>FortiPAM VM:</b> FortiPAM-AWS, FortiPAM-Azure, FortiPAM-GCP, FortiPAM-HyperV, FortiPAM-KVM, FortiPAM-VM64	1.0, 1.1, 1.2, 1.3, 1.4

## FortiProxy models

Model	Firmware Version
<b>FortiProxy:</b> FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G <b>FortiProxy VM:</b> FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-OPC, FortiProxy-VM64	7.6
<b>FortiProxy:</b> FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G <b>FortiProxy VM:</b> FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-OPC, FortiProxy-VM64	7.4
<b>FortiProxy:</b> FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G <b>FortiProxy VM:</b> FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-VM64	7.2
<b>FortiProxy:</b> FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G <b>FortiProxy VM:</b> FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-OPC, FortiProxy-VM64	7.0
<b>FortiProxy:</b> FPX-400E, FPX-2000E, FPX-4000E <b>FortiProxy VM:</b> FortiProxy-KVM, FortiProxy-VM64	1.0, 1.1, 1.2, 2.0

## FortiSandbox models

Model	Firmware Version
<b>FortiSandbox:</b> FSA-500F, FSA-500G, FSA-1000F, FSA-1500G, FSA-2000E, FSA-3000E, FSA-3000F <b>FortiSandbox DC:</b> FSA-1000F-DC <b>FortiSandbox-VM:</b> FSA-AliCloud, FSA-AliCloud-Nested, FSA-AWS, FSA-AWS-Nested, FSA-Azure, FSA-Azure-Nested, FSA-Cloud, FSA-GCP, FSA-GCP-Nested, FSA-HYPERV, FSA-KVM, FSA-OCI-Nested, FSA-VM	5.0
<b>FortiSandbox:</b> FSA-500F, FSA-500G, FSA-1000D, FSA-1000F, FSA-1500G, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3000F, FSA-3500D <b>FortiSandbox DC:</b> FSA-1000F-DC <b>FortiSandbox-VM:</b> FSA-AWS, FSA-Cloud, FSA-VM	4.2, 4.4
<b>FortiSandbox:</b> FSA-500F, FSA-1000D, FSA-1000F, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3000F, FSA-3500D <b>FortiSandbox DC:</b> FSA-1000F-DC <b>FortiSandbox-VM:</b> FSA-AWS, FSA-Cloud, FSA-VM	4.0
<b>FortiSandbox:</b> FSA-500F, FSA-1000D, FSA-1000F, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3500D <b>FortiSandbox DC:</b> FSA-1000F-DC <b>FortiSandbox-VM:</b> FSA-AWS, FSA-VM	3.2

## FortiSOAR models

Model	Firmware Version
<b>FortiSOAR VM:</b> FortiSOAR-VM	7.2, 7.3, 7.4, 7.5, 7.6

## FortiSRA models

Model	Firmware Version
<b>FortiSRA:</b> FortiSRA-1000G, FortiSRA-3000G <b>FortiSRA-VM:</b> FortiSRA-Azure, FortiSRA-HyperV, FortiSRA-KVM, FortiSRA-VM64	1.0, 1.1

## FortiSwitch ATCA models

Model	Firmware Version
<b>FortiController:</b> FTCL-5103B, FTCL-5903C, FTCL-5913C	5.2
<b>FortiSwitch:</b> FS-5003A, FS-5003B <b>FortiController:</b> FTCL-5103B	5.0
<b>FortiSwitch:</b> FS-5003A, FS-5003B	4.3

## FortiWeb models

Model	Firmware Version
<p><b>FortiWeb:</b> FortiWeb-100D, FortiWeb-100E, FortiWeb-100F, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-400F, FortiWeb-600D, FortiWeb-600E, FortiWeb-600F, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-1000F, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F</p> <p><b>FortiWeb VM:</b> FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer</p> <p><b>FortiWeb Cloud</b>, including FortiAppSec Cloud.</p>	7.6
<p><b>FortiWeb:</b> FortiWeb-100D, FortiWeb-100E, FortiWeb-100F, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-400F, FortiWeb-600D, FortiWeb-600E, FortiWeb-600F, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-1000F, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F</p> <p><b>FortiWeb VM:</b> FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer</p> <p><b>FortiWeb Cloud</b>, including FortiAppSec Cloud.</p>	7.4
<p><b>FortiWeb:</b> FortiWeb-100D, FortiWeb-100E, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-600D, FortiWeb-600E, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-1000F, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F</p> <p><b>FortiWeb VM:</b> FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer</p> <p><b>FortiWeb Cloud</b>, including FortiAppSec Cloud.</p>	7.2

Model	Firmware Version
<p><b>FortiWeb:</b> FortiWeb-100D, FortiWeb-100E, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-600D, FortiWeb-600E, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F</p> <p><b>FortiWeb VM:</b> FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer</p> <p><b>FortiWeb Cloud</b>, including FortiAppSec Cloud.</p>	7.0

# Resolved Issues

The following issues have been fixed in FortiAnalyzer version 7.6.4. To inquire about a particular bug, please contact [Customer Service & Support](#).

## Device Manager

Bug ID	Description
1140464	In FortiAnalyzer, the <i>Device Manager</i> displays "(Beta 0)" for the FortiGate versions. This has been observed when FortiAnalyzer is receiving forwarded logs from another FortiAnalyzer operating in Collector mode.

## Log View

Bug ID	Description
1114303	Privacy masking does not work properly.
1170935	Message field is truncated in syslog type adom when opening log details window.

## Others

Bug ID	Description
1001388	FortiAnalyzer in Collector Mode does not forward logs for all FortiGates to the FortiAnalyzer working in Analyzer Mode.
1127437	When FortiAnalyzer does not have direct Internet access and is configured behind a Web Proxy, the <i>Outbreak Alerts</i> page located under <i>Incidents &amp; Events &gt; FortiGuard Services</i> may either appear blank or fail to display properly when accessed by the FortiAnalyzer administrator.
1157494	Continuous crashes (signal 11 for fgfmd) have been observed for FortiAnalyzer that is managed by FortiManager.
1165215	The Webhook Connectors are sending the null notification after the FortiAnalyzer upgrade.

## Reports

Bug ID	Description
1013026	Network Interface Utilization Charts are blank in Reports.
1123597	When the report or chart filter is set to "All Devices", the chart displays data as expected. However, when the report or chart is filtered to a specific device, the message "No matching log data for this report" appears in the chart.

## Common Vulnerabilities and Exposures

Visit <https://fortiguard.com/psirt> for more information.

Bug ID	CVE references
1157806	FortiAnalyzer 7.6.4 is no longer vulnerable to the following CVE Reference: <ul style="list-style-type: none"><li>• CVE-2025-53845</li></ul>
1159008	FortiAnalyzer 7.6.4 is no longer vulnerable to the following CVE Reference: <ul style="list-style-type: none"><li>• CVE-2025-49784</li></ul>
1172234	FortiAnalyzer 7.6.4 is no longer vulnerable to the following CVE Reference: <ul style="list-style-type: none"><li>• CVE-2025-48418</li></ul>
1194441	FortiAnalyzer 7.6.4 is no longer vulnerable to the following CVE Reference: <ul style="list-style-type: none"><li>• CVE-2026-22572</li></ul>

# Known issues

Known issues are organized into the following categories:

- [New known issues on page 60](#)
- [Existing known issues on page 60](#)

To inquire about a particular bug or to report a bug, please contact [Fortinet Customer Service & Support](#).

## New known issues

The following issues have been identified in version 7.6.4.

### Others

Bug ID	Description
1196384	The "jitterentropy-rngd" process is using very high CPU even without FIPS enabled in FortiAnalyzer Hardware platform.

## Existing known issues

The following issues have been identified in a previous version of FortiAnalyzer and remain in FortiAnalyzer 7.6.4.

### FortiView

Bug ID	Description
1092311	FortiAnalyzer may not display any data when accessing <i>FortiView</i> in the VPN site-to-site tab.

## Log View

Bug ID	Description
1188362	Some detailed information in FortiMail logs is encapsulated within large message chunks. The current FortiAnalyzer log parsing logic does not yet support extracting these details from those chunks.

## Others

Bug ID	Description
1179768	Due to the FortiGate's log schema upgrades/updates, upon FortiAnalyzer's upgrade, the Postgres table schema will be updated, which may take a significant amount of time to complete. The database migration from Postgres to ClickHouse will only begin after the Postgres schema upgrade has successfully finished. As a result, the process might appear to be stuck but it is simply progressing slowly. The only recommended action is to wait patiently for the upgrade to complete.

## System Settings

Bug ID	Description
1142016	The <i>Index Fetched Logs</i> feature in <i>Request Fetch</i> under <i>Advanced &gt; Log Fetch</i> is not functioning as expected.
1063040	Unable to import a local certificate into FortiAnalyzer. This issue may occur if the certificate is encrypted with a newer OpenSSL version that FortiAnalyzer does not yet support. <b>Workaround:</b> Convert the latest certificate to the legacy format before uploading it to FortiAnalyzer.

# Appendix A - Default and maximum number of ADOMs supported

This section identifies the supported number of ADOMs for FortiAnalyzer hardware models and virtual machines.



When operating as a Fabric supervisor, FortiAnalyzer does not count member ADOMs and devices toward its license limit.

See also the [FortiAnalyzer Data Sheet](#).

## Hardware models

FortiAnalyzer supports a default number of ADOMs based on hardware model.

Some hardware models support an ADOM subscription license. When you purchase an ADOM subscription license, you increase the number of supported ADOMs. For example, you can purchase an ADOM subscription license for the FAZ-3000G series, which allows you to use up to a maximum of 1200 ADOMs. Other hardware models do not support the ADOM subscription license.

Some older hardware models do not enforce ADOM limits. These models will display a warning message when the ADOM limit is reached or exceeded; adding more ADOMs may affect performance. These devices are still subject to maximum device limits which are listed in the FortiAnalyzer Data Sheet.

The table below lists the maximum number of ADOMs by platform. Models that enforce the maximum as a hard limit are indicated in the *Hard limit* column.

FortiAnalyzer Platform	Maximum number of ADOMs	Hard limit
Desktop models	1	✓
150G	3	✓
300G	25	✓
800G and 810G	50	✓
1000F	50	✓
1000G	50	✓
2000E	250	

FortiAnalyzer Platform	Maximum number of ADOMs	Hard limit
3000F	500	
3000G	500 *1200	✓
3500F	500	
3500G	500 *500	✓
3700F	1200	
3700G	1200 *10,000	✓

\*Maximum number of supported ADOMs can be increased to this value with an ADOM subscription license.

## Virtual Machines



For subscription licenses, FortiAnalyzer enforces the ADOM limits.  
For perpetual licenses, ADOM limits are recommended, but not enforced.

## FortiAnalyzer subscription license

Five (5) ADOMs are included with FortiAnalyzer VM subscription licenses. Additional ADOMs can be purchased with an ADOM subscription license.

## FortiAnalyzer perpetual license

Recommended maximum number of ADOMs supported:

FortiAnalyzer Platform	Default number of ADOMs
1 GB/Day < License <= 5 GB/Day	10
5 GB/Day < License <= 25 GB/Day	25
25 GB/Day < License <= 100 GB/Day	50
100 GB/Day < License <= 500 GB/Day	250

FortiAnalyzer Platform	Default number of ADOMs
500 GB/Day < License <= 1000 GB/Day	500
1000 GB/Day < License <= 5000 GB/Day	800
License > 5000 GB/Day	1200

---



- FortiAnalyzer-VM subscription licenses are fully stackable.
  - For FortiAnalyzer-VM perpetual licenses, only the GB/Day is stackable.
-



[www.fortinet.com](http://www.fortinet.com)

Copyright © 2026 Fortinet, Inc. All rights reserved. Fortinet®, FortiGate®, FortiCare® and FortiGuard®, and certain other marks are registered trademarks of Fortinet, Inc., and other Fortinet names herein may also be registered and/or common law trademarks of Fortinet. All other product or company names may be trademarks of their respective owners. Performance and other metrics contained herein were attained in internal lab tests under ideal conditions, and actual performance and other results may vary. Network variables, different network environments and other conditions may affect performance results. Nothing herein represents any binding commitment by Fortinet, and Fortinet disclaims all warranties, whether express or implied, except to the extent Fortinet enters a binding written contract, signed by Fortinet's Chief Legal Officer, with a purchaser that expressly warrants that the identified product will perform according to certain expressly-identified performance metrics and, in such event, only the specific performance metrics expressly identified in such binding written contract shall be binding on Fortinet. For absolute clarity, any such warranty will be limited to performance in the same ideal conditions as in Fortinet's internal lab tests. Fortinet disclaims in full any covenants, representations, and guarantees pursuant hereto, whether express or implied. Fortinet reserves the right to change, modify, transfer, or otherwise revise this publication without notice, and the most current version of the publication shall be applicable.