

Release Notes

FortiAnalyzer 7.6.2



FORTINET DOCUMENT LIBRARY

<https://docs.fortinet.com>

FORTINET VIDEO LIBRARY

<https://video.fortinet.com>

FORTINET BLOG

<https://blog.fortinet.com>

CUSTOMER SERVICE & SUPPORT

<https://support.fortinet.com>

FORTINET TRAINING & CERTIFICATION PROGRAM

<https://www.fortinet.com/training-certification>

FORTINET TRAINING INSTITUTE

<https://training.fortinet.com>

FORTIGUARD LABS

<https://www.fortiguard.com>

END USER LICENSE AGREEMENT

<https://www.fortinet.com/doc/legal/EULA.pdf>

FEEDBACK

Email: techdoc@fortinet.com



January 14, 2026

FortiAnalyzer 7.6.2 Release Notes

05-762-1092549-20260114

TABLE OF CONTENTS

Change Log	6
FortiAnalyzer 7.6.2 Release	7
Supported models	7
FortiAnalyzer VM subscription license	7
Management extension applications	8
Supported models for MEA	8
Minimum system requirements	8
Special Notices	10
FortiAnalyzer-3700G v2 support	10
Migrating the log database from Postgres to ClickHouse	10
Shell access has been removed	10
FortiSOAR MEA license must be activated or uploaded	11
Alert notifications generated by FortiAnalyzer and sent by syslog	11
Additional configuration required for SSO users	11
FortiAnalyzer 7.2.3 and later firmware on FortiGuard	12
Configuration backup requires a password	12
FortiAnalyzer-3500E support	12
Serial console has changed for FortiAnalyzer deployments on Xen	13
OpenXen in PV mode is not supported in FortiAnalyzer 7.4.1	13
Default GUI theme changed	13
Management Extensions visibility in the GUI	14
FortiManager Features removed	14
Setup wizard requires FortiCare registration	14
Hyperscale firewall mode	14
Modifying the interface status with the CLI	15
Citrix XenServer default limits and upgrade	15
FortiAnalyzer VM upgrade requires more memory	15
Maximum ADOM limits for FortiAnalyzer	16
Port 8443 reserved	16
Hyper-V FortiAnalyzer-VM running on an AMD CPU	16
SSLv3 on FortiAnalyzer-VM64-AWS	16
Upgrade Information	17
Downgrading to previous firmware versions	17
Firmware image checksums	17
FortiAnalyzer VM firmware	17
SNMP MIB files	19
Product Integration and Support	20
Supported software	20
Web browsers	21
FortiOS and FortiOS Carrier	21
FortiADC	21
FortiNDR	22

FortiAnalyzer	22
FortiAP	22
FortiAuthenticator	22
FortiCache	23
FortiCASB	23
FortiClient	23
FortiDDoS	23
FortiDeceptor	24
FortiFirewall and FortiFirewallCarrier	24
FortiIsolator	24
FortiMail	24
FortiManager	25
FortiNAC	25
FortiPAM	25
FortiProxy	25
FortiSandbox	26
FortiSASE	26
FortiSOAR	26
FortiSRA	26
FortiSwitch ATCA	26
FortiToken	26
FortiWeb	27
Virtualization	27
Feature support	28
Language support	29
Supported models	29
FortiGate models	30
FortiGate special branch models	36
FortiCarrier models	40
FortiCarrier special branch models	43
FortiADC models	45
FortiNDR models	45
FortiAnalyzer models	45
FortiAP models	46
FortiAuthenticator models	47
FortiCache models	48
FortiDDoS models	48
FortiDeceptor models	48
FortiFirewall models	49
FortiFirewallCarrier models	49
FortiIsolator models	50
FortiMail models	51
FortiNAC models	51
FortiPAM models	51
FortiProxy models	52
FortiSandbox models	52
FortiSOAR models	53
FortiSRA models	53
FortiSwitch ATCA models	53

FortiWeb models	53
Resolved Issues	55
Device Manager	55
Fabric View	55
FortiView	55
Log View	56
Others	56
System Settings	56
Common Vulnerabilities and Exposures	57
Known issues	58
New known issues	58
Log View	58
Existing known issues	58
Device Manager	59
FortiSOC	59
FortiView	59
Others	59
Reports	60
System Settings	60
Appendix A - Default and maximum number of ADOMs supported	61
Hardware models	61
Virtual Machines	62
FortiAnalyzer subscription license	62
FortiAnalyzer perpetual license	62

Change Log

Date	Change Description
2024-12-12	Initial release of 7.6.2.
2025-01-06	Updated Resolved Issues on page 55 and Known issues on page 58 .
2025-01-15	Updated Resolved Issues on page 55 .
2025-02-04	Updated FortiProxy on page 25 . Updated Known issues on page 58 .
2025-02-07	Updated Resolved Issues on page 55 and Known issues on page 58 .
2025-02-18	Updated Virtualization on page 27 .
2025-02-25	Updated Known issues on page 58 .
2025-02-27	Added "FortiAnalyzer-3700G v2 support" to Special Notices on page 10 .
2025-03-06	Updated Known issues on page 58 .
2025-03-13	Updated Resolved Issues on page 55 .
2025-04-08	Updated Resolved Issues on page 55 .
2025-04-17	Updated FortiOS and FortiOS Carrier on page 21 .
2025-04-21	Updated FortiGate special branch models on page 36 . Updated FortiWeb models on page 53 .
2025-05-06	Updated Known issues on page 58 .
2025-05-28	Updated Known issues on page 58 .
2025-07-08	Updated Resolved Issues on page 55 .
2025-09-12	Updated "Maximum ADOM limits for FortiAnalyzer" in Special Notices on page 10 . Updated Appendix A - Default and maximum number of ADOMs supported on page 61 .
2025-12-30	Updated Supported models on page 7 .
2026-01-06	Updated Supported models on page 7 .
2026-01-14	Updated Supported models on page 7 .

FortiAnalyzer 7.6.2 Release

This document provides information about FortiAnalyzer version 7.6.2 build 3415.



The recommended minimum screen resolution for the FortiAnalyzer GUI is 1920 x 1080. Please adjust the screen resolution accordingly. Otherwise, the GUI may not display properly.

This section includes the following topics:

- [Supported models on page 7](#)
- [FortiAnalyzer VM subscription license on page 7](#)
- [Management extension applications on page 8](#)

Supported models

FortiAnalyzer version 7.6.2 supports the following models:

FortiAnalyzer	FAZ-150G, FAZ-300G, FAZ-800G, FAZ-810G, FAZ-1000F, FAZ-1000G, FAZ-2000E, FAZ-3000F, FAZ-3000G, FAZ-3100G, FAZ-3500F, FAZ-3500G, FAZ-3510G, FAZ-3700F, and FAZ-3700G.
FortiAnalyzer VM	FAZ_VM64, FAZ_VM64_ALI, FAZ_VM64_AWS, FAZ_VM64_AWSOnDemand, FAZ_VM64_Azure, FAZ_VM64_GCP, FAZ_VM64_HV (including Hyper-V 2016, 2019, and 2022), FAZ_VM64_IBM, FAZ_VM64_KVM, FAZ_VM64_OPC, FAZ_VM64_XEN (for both Citrix and Open Source Xen).



For access to container versions of FortiAnalyzer, contact [Fortinet Support](#).

FortiAnalyzer VM subscription license

The FortiAnalyzer VM subscription license supports FortiAnalyzer version 6.4.1 and later. For information about supported firmware, see [FortiAnalyzer VM firmware on page 17](#).

See also [Appendix A - Default and maximum number of ADOMs supported on page 61](#).



You can use the FortiAnalyzer VM subscription license with new FortiAnalyzer-VM installations.

For existing FortiAnalyzer-VM installations, you can migrate to a FortiAnalyzer VM subscription license, starting with FortiAnalyzer 7.0.1. See the [FortiAnalyzer Administration Guide](#).

Management extension applications

The following section describes supported models and minimum system requirements for management extension applications (MEA) in FortiAnalyzer 7.6.2.



FortiAnalyzer uses port TCP/443 or TCP/4443 to connect to the Fortinet registry and download MEAs. Ensure that the port is also open on any upstream FortiGates. For more information about incoming and outgoing ports, see the [7.6 Ports Guide](#).

As of FortiAnalyzer 7.4.0, the *Management Extensions* pane is only visible in the GUI when docker status is enabled and at least one MEA is enabled and downloaded. For more information about enabling and using the MEAs, see the Management Extensions documentation in the [FortiAnalyzer Documents Library](#).

Supported models for MEA

You can use any of the following FortiAnalyzer models as a host for management extension applications:

FortiAnalyzer	FAZ-3000F, FAZ-3000G, FAZ-3100G, FAZ-3500F, FAZ-3500G, FAZ-3510G, FAZ-3700F, and FAZ-3700G.
FortiAnalyzer VM	FAZ_VM64, FAZ_VM64_ALI, FAZ_VM64_AWS, FAZ_VM64_AWSOnDemand, FAZ_VM64_Azure, FAZ_VM64_GCP, FAZ_VM64_HV (including Hyper-V 2016, 2019, and 2022), FAZ_VM64_IBM, FAZ_VM64_KVM, FAZ_VM64_OPC, FAZ_VM64_XEN (for both Citrix and Open Source Xen).

Minimum system requirements

By default FortiAnalyzer VMs use the following system resource settings:

- 4 vCPU
- 16 GB RAM
- 500 GB disk space

Starting with FortiAnalyzer 7.0.0, RAM and CPU is capped at 50% for MEAs. (Use the `config system docker` command to view the setting.) If FortiAnalyzer has 8 CPUs and 16 GB RAM, then only 4 CPUs and 8 GB RAM are available to MEAs by default, and the 4 CPUs and 8 GB RAM are used for all enabled MEAs.

Some MEAs have minimum system requirements that require you to increase system resources. The following table identifies the minimum requirements for each MEA as well as the recommended system resources to function well in a production environment.

MEA minimum system requirements apply only to the individual MEA and do not take into consideration any system requirements for resource-sensitive FortiAnalyzer features or multiple, enabled MEAs.

Management Extension Application	Minimum system requirements	Recommended system resources for production*
FortiSIEM	<ul style="list-style-type: none">• 4 vCPU• 4 GB RAM• No change for disk storage	<ul style="list-style-type: none">• 12 vCPU• 16 GB RAM• 500 GB
FortiSOAR	<ul style="list-style-type: none">• 4 vCPU• 8 GB RAM• 500 GB disk storage	<ul style="list-style-type: none">• 16 vCPU• 64 GB RAM• No change for disk storage

*The numbers in the *Recommended system resources for production* column are a combination of the default system resource settings for FortiAnalyzer plus the recommended system requirements for the MEA.

Special Notices

This section highlights some of the operational changes that administrators should be aware of in FortiAnalyzer version 7.6.2.

FortiAnalyzer-3700G v2 support

A second variant of the FortiAnalyzer 3700G has been introduced, featuring an updated RAID controller subsystem. This change was necessary as the previous RAID subsystem has reached end-of-life with our OEM partner.

To verify the system part number, use the following command:

```
get system status
```

For example:

- FAZ-3700G v1 system part number: P26596-**01**
- FAZ-3700G v2 system part number: P26596-**10**

Using an image compatible with the first variant on a second variant device may result in the hardware RAID controller not being recognized properly. If the new variant is detected and firmware versions 7.4.6 or 7.6.2 are required, a special build image must be used. Please contact our support team to obtain this special image.

Versions 7.2.9, 7.4.6, 7.6.2, and earlier support only the first variant. Versions 7.2.10, 7.4.7, 7.6.3, and later support both variants.

Migrating the log database from Postgres to ClickHouse

Beginning in FortiAnalyzer 7.6.0, FortiAnalyzer stores logs in a ClickHouse SQL database rather than a Postgres SQL database.

For more information, see the [FortiAnalyzer 7.6.0 Upgrade Guide](#).

Shell access has been removed

As of FortiAnalyzer 7.6.0, shell access has been removed.

The following CLI variables have been removed, which were previously used to enable shell access:

```
config system admin setting
  set shell-access {enable | disable}
  set shell-password <passwd>
```

The following CLI command has been removed, which was previously used to access shell when enabled:

```
execute shell
```

FortiSOAR MEA license must be activated or uploaded

In previous versions, the trial license was automatically activated when the FortiSOAR MEA was enabled. Beginning in FortiAnalyzer 7.6.0, which includes the FortiSOAR MEA 7.6.0, you must activate the trial license or upload a license to use the FortiSOAR MEA.

After enabling the FortiSOAR MEA, go to *Management Extensions > FortiSOAR* to activate or upload the license. For more information, see the Management Extensions documentation in the [FortiAnalyzer Document Library](#).

Alert notifications generated by FortiAnalyzer and sent by syslog

Beginning in 7.4.3, alert notifications generated by FortiAnalyzer and sent by syslog will use the RFC-5424 format.

Additional configuration required for SSO users

Beginning in 7.4.3, additional configuration is needed for FortiAnalyzer Users declared as wildcard SSO users.

When configuring Administrators as wildcard SSO users, the `ext-auth-accprofile-override` and/or `ext-auth-adom-override` features, under *Advanced Options*, should be enabled if the intent is to obtain the ADOMs list and/or permission profile from the SAML IdP.

FortiAnalyzer 7.2.3 and later firmware on FortiGuard

Starting in FortiAnalyzer 7.2.1, a setup wizard executes to prompt the user for various configuration steps and registration with FortiCare. During the execution, the FortiAnalyzer unit attempts to communicate with FortiGuard for a list of FortiAnalyzer firmware images currently available on FortiGuard – older and newer.

In the case of FortiAnalyzer 7.2.2, a bug in the GUI prevents the wizard from completing and prevents the user from accessing the FortiAnalyzer unit. The issue has been fixed in 7.2.3 and later and a CLI command has been added to bypass the setup wizard at login time.

```
config system admin setting
    set firmware-upgrade-check disable
end
```

Fortinet has not uploaded FortiAnalyzer 7.2.3 and later firmware to FortiGuard in order to work around the GUI bug, however, the firmware is available for download from the [Fortinet Support website](#).

Configuration backup requires a password

As of FortiAnalyzer 7.4.2, configuration backup files are automatically encrypted and require you to set a password. The password is required for scheduled backups as well.

In previous versions, the encryption and password were optional.

For more information, see the [FortiAnalyzer Administration Guide](#).

FortiAnalyzer-3500E support

FortiAnalyzer 7.4.2 and later does not support the FortiAnalyzer-3500E device.

FortiAnalyzer 7.4.2 introduces an upgrade of the OpenSSL library to address known vulnerabilities in the library. As a result, the SSL connection that is setup between the FortiAnalyzer-3500E device and the Google Map server hosted by Fortinet uses a SHA2 (2048) public key length. The certificate stored on the BIOS that is used during the setup of the SSL connection contains a SHA1 public key length, which causes the connection setup to fail. Running the following command shows the key length.

```
FAZ3500E # config system certificate local
(local)# ed Fortinet_Local
(Fortinet_Local)# get
    name : Fortinet_Local
    password : *
    comment : Default local certificate
    private-key :
    certificate :
```

```
Subject: C = US, ST = California, L = Sunnyvale, O = Fortinet, OU = FortiAnalyzer, CN =
        FL3K5E3M1500074, emailAddress = support@fortinet.com
Issuer: C = US, ST = California, L = Sunnyvale, O = Fortinet, OU = Certificate Authority,
        CN = support, emailAddress = support@fortinet.com
Valid from: 2015-03-06 16:22:10 GMT
Valid to: 2038-01-19 03:14:07 GMT
Fingerprint: FC:D0:0C:8D:DC:57:B6:16:58:DF:90:22:77:6F:2C:1B
Public key: rsaEncryption (1024 bits)
Signature: sha1WithRSAEncryption
Root CA: No
Version: 3
Serial Num:
1e:07:7a
Extension 1: X509v3 Basic Constraints:
CA:FALSE
...
(Fortinet_Local)#
```

Serial console has changed for FortiAnalyzer deployments on Xen

In FortiAnalyzer 7.4.1, the serial console for Xen deployments has changed from hvc0 (Xen specific) to ttyS0 (standard).

OpenXen in PV mode is not supported in FortiAnalyzer 7.4.1

As of FortiAnalyzer 7.4.1, kernel and rootfs are encrypted. OpenXen in PV mode tries to unzip the kernel and rootfs, but it will fail. Therefore, OpenXen in PV mode cannot be used when deploying or upgrading to FortiAnalyzer 7.4.1. Only HVM (hardware virtual machine) mode is supported for OpenXen in FortiAnalyzer 7.4.1.

Default GUI theme changed

As of FortiAnalyzer 7.4.1, the default GUI theme is *Jade*. The default theme can be changed from *System Settings > Settings*.

Management Extensions visibility in the GUI

As of FortiAnalyzer 7.4.0, the *Management Extensions* pane is only visible in the GUI when docker status is enabled and at least one management extension application (MEA) is enabled and downloaded. For more information about enabling and using the MEAs, see the Management Extensions documentation in the [FortiAnalyzer Documents Library](#).

FortiManager Features removed

FortiAnalyzer 7.2.1 and later no longer supports FortiManager Features. If you have FortiManager Features enabled before upgrading to FortiAnalyzer 7.2.1, FortiManager Features will be permanently disabled after upgrading to FortiAnalyzer 7.2.1.

Setup wizard requires FortiCare registration

Starting in FortiAnalyzer 7.2.1, the FortiAnalyzer Setup wizard requires you to complete the *Register with FortiCare* step before you can access the FortiAnalyzer appliance or VM. Previously the step was optional.

For FortiAnalyzer units operating in a closed environment, contact customer service to receive an entitlement file, and then load the entitlement file to FortiAnalyzer by using the CLI.

When FortiManager is managing FortiAnalyzer in a closed environment, FortiManager contains the FortiAnalyzer contract information, and you can point FortiAnalyzer to FortiManager.

Hyperscale firewall mode

FortiAnalyzer does not support logs from the following models when they have hyperscale firewall mode and netflow enabled:

- FortiGate-1800F
- FortiGate-1801F
- FortiGate-2600F
- FortiGate-2601F
- FortiGate-4200F
- FortiGate-4201F
- FortiGate-4400F
- FortiGate-4401F

FortiAnalyzer only supports logs when the normal firewall mode with standard FortiGate logging are enabled.

Modifying the interface status with the CLI

Starting in version 7.0.1, the CLI to modify the interface status has been changed from up/down to enable/disable.

For example:

```
config system interface
  edit port2
    set status <enable/disable>
  next
end
```

Citrix XenServer default limits and upgrade

Citrix XenServer limits ramdisk to 128M by default. However the FAZ-VM64-XEN image is larger than 128M. Before updating to FortiAnalyzer 6.4, increase the size of the ramdisk setting on Citrix XenServer.

To increase the size of the ramdisk setting:

1. On Citrix XenServer, run the following command:
`xenstore-write /mh/limits/pv-ramdisk-max-size 536,870,912`
2. Confirm the setting is in effect by running `xenstore-ls`.

```
-----
limits = ""
pv-kernel-max-size = "33554432"
pv-ramdisk-max-size = "536,870,912"
boot-time = ""
-----
```

3. Remove the pending files left in `/run/xen/pygrub`.



The ramdisk setting returns to the default value after rebooting.

FortiAnalyzer VM upgrade requires more memory

When upgrading FortiAnalyzer VM units from a previous version to FortiAnalyzer 7.2.2 or higher, the upgrade may fail because of memory allocation. As of FortiAnalyzer 7.2.2, FortiAnalyzer VM requires 16 GB of RAM and 4 CPU.

Workaround: Before upgrading FortiAnalyzer VM to FortiAnalyzer 7.2.2, change the memory allocation to 16 GB of RAM.

Maximum ADOM limits for FortiAnalyzer

FortiAnalyzer hardware devices and VMs display a warning when the maximum number of ADOMs is reached. For more details, see [Appendix A - Default and maximum number of ADOMs supported on page 61](#).

Port 8443 reserved

Port 8443 is reserved for https-logging from FortiClient EMS for Chromebooks. See also [FortiAnalyzer 7.0 Ports Reference](#) on the Docs Library.

Hyper-V FortiAnalyzer-VM running on an AMD CPU

A Hyper-V FAZ-VM running on a PC with an AMD CPU may experience a kernel panic. Fortinet recommends running VMs on an Intel-based PC.

SSLv3 on FortiAnalyzer-VM64-AWS

Due to known vulnerabilities in the SSLv3 protocol, FortiAnalyzer-VM64-AWS only enables TLSv1 by default. All other models enable both TLSv1 and SSLv3. If you wish to disable SSLv3 support, please run:

```
config system global
    set ssl-protocol t1sv1
end
```

Upgrade Information



Prior to upgrading your FortiAnalyzer, please review the FortiAnalyzer Upgrade Guide in detail as it includes all of the necessary steps and associated details required to upgrade your FortiAnalyzer device or VM, including recommended upgrade paths. See the *FortiAnalyzer Upgrade Guide* in the [Fortinet Document Library](#).

This section contains the following topics:

- [Downgrading to previous firmware versions on page 17](#)
- [Firmware image checksums on page 17](#)
- [FortiAnalyzer VM firmware on page 17](#)
- [SNMP MIB files on page 19](#)

Downgrading to previous firmware versions

FortiAnalyzer does not provide a full downgrade path. You can downgrade to a previous firmware release by using the GUI or CLI, but doing so results in configuration loss. A system reset is required after the firmware downgrade process has completed. To reset the system, use the following CLI commands via a console port connection:

```
execute reset {all-settings | all-except-ip}  
execute format {disk | disk-ext4 | disk-ext3}
```

Firmware image checksums

The MD5 checksums for all Fortinet software and firmware releases are available at the Customer Service & Support portal, <https://support.fortinet.com>. After logging in, go to *Download > Firmware Image Checksums*, enter the image file name including the extension, and select *Get Checksum Code*.

FortiAnalyzer VM firmware

Fortinet provides FortiAnalyzer VM firmware images for Amazon AWS, Amazon AWSOnDemand, Citrix and Open Source XenServer, Linux KVM, Microsoft Hyper-V Server, and VMware ESX/ESXi virtualization environments.

Amazon Web Services

- The 64-bit Amazon Machine Image (AMI) is available on the AWS marketplace.

Citrix XenServer and Open Source XenServer

- .out: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- .out.OpenXen.zip: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains the QCOW2 file for the Open Source Xen Server.
- .out.CitrixXen.zip: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains the Citrix XenServer Virtual Appliance (XVA), Virtual Hard Disk (VHD), and OVF files.

Google Cloud Platform

- .out: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- .out.gcp.zip: Download the 64-bit package for a new FortiAnalyzer VM installation.

Linux KVM

- .out: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- .out.kvm.zip: Download the 64-bit package for a new FortiAnalyzer VM installation. This package contains QCOW2 that can be used by qemu.

Microsoft Azure

The files for Microsoft Azure have AZURE in the filenames, for example <product>_VM64_AZURE-v<number>-build<number>-FORTINET.out.hyperv.zip.

- .out: Download the firmware image to upgrade your existing FortiAnalyzer VM installation.

Microsoft Hyper-V Server

The files for Microsoft Hyper-V Server have HV in the filenames, for example, <product>_VM64_HV-v<number>-build<number>-FORTINET.out.hyperv.zip.

- .out: Download the firmware image to upgrade your existing FortiAnalyzer VM installation.
- .hyperv.zip: Download the package for a new FortiAnalyzer VM installation. This package contains a Virtual Hard Disk (VHD) file for Microsoft Hyper-V Server.



Microsoft Hyper-V 2016 is supported.

Oracle Private Cloud

- .out: Download the 64-bit firmware image to upgrade your existing FortiAnalyzer VM installation.
- .out.opc.zip: Download the 64-bit package for a new FortiAnalyzer VM installation.

VMware ESX/ESXi

- .out: Download the 64-bit firmware image to upgrade your existing VM installation.
- .ovf.zip: Download either the 64-bit package for a new VM installation. This package contains an Open Virtualization Format (OVF) file for VMware and two Virtual Machine Disk Format (VMDK) files used by the OVF file during deployment.



For more information, see the [FortiAnalyzer Data Sheet](#) available on the Fortinet web site. VM installation guides are available in the [Fortinet Document Library](#).

SNMP MIB files

You can download the *FORTINET-FORTIMANAGER-FORTIANALYZER.mib* MIB file in the firmware image file folder. The Fortinet Core MIB file is located in the main FortiAnalyzer version 5.00 file folder.

Product Integration and Support

This section lists FortiAnalyzer 7.6.2 support of other Fortinet products. It also identifies what FortiAnalyzer features are supported for managed platforms and what languages FortiAnalyzer supports. It also lists which Fortinet models can be managed by FortiAnalyzer.

The section contains the following topics:

- [Supported software on page 20](#)
- [Feature support on page 28](#)
- [Language support on page 29](#)
- [Supported models on page 29](#)

Supported software

FortiAnalyzer 7.6.2 supports the following software:

- [Web browsers on page 21](#)
- [FortiOS and FortiOS Carrier on page 21](#)
- [FortiADC on page 21](#)
- [FortiNDR on page 22](#)
- [FortiAnalyzer on page 22](#)
- [FortiAP on page 22](#)
- [FortiAuthenticator on page 22](#)
- [FortiCache on page 23](#)
- [FortiCASB on page 23](#)
- [FortiClient on page 23](#)
- [FortiDDoS on page 23](#)
- [FortiDeceptor on page 24](#)
- [FortiFirewall and FortiFirewallCarrier on page 24](#)
- [FortiIsolator on page 24](#)
- [FortiMail on page 24](#)
- [FortiManager on page 25](#)
- [FortiNAC on page 25](#)
- [FortiPAM on page 25](#)
- [FortiProxy on page 25](#)
- [FortiSandbox on page 26](#)
- [FortiSASE on page 26](#)
- [FortiSOAR on page 26](#)
- [FortiSwitch ATCA on page 26](#)

- [FortiToken on page 26](#)
- [FortiWeb on page 27](#)
- [Virtualization on page 27](#)



To confirm that a device model or firmware version is supported by the current firmware version running on FortiAnalyzer, run the following CLI command:
`diagnose dvm supported-platforms list`



Always review the Release Notes of the supported platform firmware version before upgrading your device.

Web browsers

FortiAnalyzer 7.6.2 supports the following web browsers:

- Microsoft Edge 114
- Mozilla Firefox version 96
- Google Chrome version 114

Other web browsers may function correctly, but are not supported by Fortinet.

FortiOS and FortiOS Carrier



The *FortiAnalyzer Release Notes* communicate support for FortiOS versions that are available at the time of the FortiAnalyzer 7.6.2 release. For additional information about other supported FortiOS versions, please refer to the FortiAnalyzer compatibility chart in the [Fortinet Document Library](#).

See [FortiAnalyzer compatibility with FortiOS](#).

FortiAnalyzer 7.6.2 supports the following versions of FortiOS and FortiOS Carrier:

- 7.6.0 to 7.6.2
- 7.4.0 to 7.4.7
- 7.2.0 to 7.2.11
- 7.0.0 to 7.0.16
- 6.4.0 to 6.4.15
- 6.2.0 to 6.2.16

FortiADC

FortiAnalyzer 7.6.2 supports the following versions of FortiADC:

- 7.4.0 and later
- 7.2.0 and later
- 7.1.0 and later

FortiNDR

FortiAnalyzer 7.6.2 supports the following versions of FortiNDR:

- 7.4.0 and later
- 7.2.0 and later
- 7.1.0 and later
- 7.0.0 and later

FortiAnalyzer

FortiAnalyzer 7.6.2 supports the following versions of FortiAnalyzer:

- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

FortiAP

FortiAnalyzer 7.6.2 supports the following versions of FortiAP:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later
- 6.4.0 and later
- 6.2.0 and later
- 5.6.0 and later
- 5.4.0 and later
- 5.2.0 and later
- 5.0.0 and later

FortiAuthenticator

FortiAnalyzer 7.6.2 supports the following versions of FortiAuthenticator:

- 6.6.0 and later
- 6.5.0 and later

- 6.4.0 and later
- 6.3.0 and later

FortiCache

FortiAnalyzer 7.6.2 supports the following versions of FortiCache:

- 4.2.0 and later
- 4.1.0 and later
- 4.0.0 and later

FortiCASB

FortiAnalyzer 7.6.2 supports the following versions of FortiCASB:

- 23.2.0 and later

FortiClient

FortiAnalyzer 7.6.2 supports the following versions of FortiClient:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later
- 6.4.0 and later

When using FortiClient with FortiAnalyzer, it is recommended to upgrade both to their latest versions. The versions between the two products should match. For example, if using FortiAnalyzer 7.2.0, use FortiClient 7.2.0.

FortiDDoS

FortiAnalyzer 7.6.2 supports the following versions of FortiDDoS:

- 7.0.0 and later
- 6.6.0 and later
- 6.5.0 and later
- 6.4.0 and later
- 6.3.0 and later
- 6.2.0 and later
- 6.1.0 and later
- 5.7.0 and later
- 5.6.0 and later

Limited support. For more information, see [Feature support on page 28](#).

FortiDeceptor

FortiAnalyzer 7.6.2 supports the following versions of FortiDeceptor:

- 6.0.0 and later
- 5.3.0 and later
- 5.2.0 and later
- 5.1.0 and later
- 5.0.0 and later
- 4.3.0 and later

FortiFirewall and FortiFirewallCarrier

FortiAnalyzer 7.6.2 supports the following versions of FortiFirewall and FortiFirewallCarrier:

- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later
- 6.4.0 and later
- 6.2.0 and later
- 6.0.0 and later

Fortisolator

FortiAnalyzer 7.6.2 supports the following versions of Fortisolator:

- 2.4.0 and later

FortiMail

FortiAnalyzer 7.6.2 supports the following versions of FortiMail:

- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

FortiManager

FortiAnalyzer 7.6.2 supports the following versions of FortiManager:

- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

FortiNAC

FortiAnalyzer 7.6.2 supports the following versions of FortiNAC:

- 9.4.0 and later
- 9.2.0 and later
- 9.1.0 and later
- 7.4.0 and later
- 7.2.0 and later

FortiPAM

FortiAnalyzer 7.6.2 supports the following versions of FortiPAM:

- 1.4.0 and later
- 1.3.0 and later
- 1.2.0 and later
- 1.1.0 and later
- 1.0.0 and later

FortiProxy

FortiAnalyzer 7.6.2 supports the following versions of FortiProxy:

- 7.4.0 to 7.4.5
- 7.2.0 to 7.2.11
- 7.0.0 to 7.0.20
- 2.0.0 to 2.0.5
- 1.2.0 to 1.2.13
- 1.1.0 to 1.1.6
- 1.0.0 to 1.0.7

FortiSandbox

FortiAnalyzer 7.6.2 supports the following versions of FortiSandbox:

- 4.4.0 and later
- 4.2.0 and later
- 4.0.0 and later
- 3.2.0 and later

FortiSASE

For more information about compatibility, see the [FortiSASE Release Notes](#).

FortiSOAR

FortiAnalyzer 7.6.2 supports the following versions of FortiSOAR:

- 7.6.0 and later
- 7.5.0 and later
- 7.4.0 and later
- 7.3.0 and later
- 7.2.0 and later

FortiSRA

FortiAnalyzer 7.6.2 supports the following versions of FortiSRA:

- 1.1.0 and later
- 1.0.0 and later

FortiSwitch ATCA

FortiAnalyzer 7.6.2 supports the following versions of FortiSwitch ATCA:

- 5.2.0 and later
- 5.0.0 and later
- 4.3.0 and later

FortiToken

FortiAnalyzer 7.6.2 supports the following versions of FortiToken:

- 3.0.0 and later

FortiAnalyzer supports logs from FortiToken Cloud.

FortiWeb

FortiAnalyzer 7.6.2 supports the following versions of FortiWeb:

- 7.6.0 and later
- 7.4.0 and later
- 7.2.0 and later
- 7.0.0 and later

FortiAnalyzer also supports FortiWeb Cloud, including FortiAppSec Cloud.

Virtualization

FortiAnalyzer 7.6.2 supports the following virtualization software:

Public Cloud

- Amazon Web Service AMI, Amazon EC2, Amazon EBS
- Alibaba Cloud
- Google Cloud Platform
- IBM Cloud
- Microsoft Azure
- Oracle Cloud Infrastructure

Private Cloud

- Citrix XenServer 8.2 and later
- OpenSource XenServer 4.2.5
- Microsoft Hyper-V Server 2016, 2019, and 2022
- Nutanix
 - AHV 20220304 and later
 - AOS 6.5 and later
 - NCC 4.6 and later
 - LCM 3.0 and later
- RedHat 9.1
 - Other versions and Linux KVM distributions are also supported
- VMware ESXi versions 6.5 and later

Feature support

The following table lists FortiAnalyzer feature support for log devices.

Platform	Log View	FortiView	Event Management	Reports
FortiGate	✓	✓	✓	✓
FortiCarrier	✓	✓	✓	✓
FortiADC	✓		✓	✓
FortiAnalyzer	✓		✓	
FortiAP	✓		✓	✓
FortiAuthenticator	✓			
FortiCache	✓		✓	✓
FortiClient registered to FortiGate	✓	✓		✓
FortiClient registered to FortiClient EMS	✓	✓		✓
FortiDDoS	✓	✓	✓	✓
FortiDeceptor	✓			
FortiFirewall	✓	✓	✓	✓
FortiMail	✓		✓	✓
FortiManager	✓		✓	
FortiNAC	✓			
FortiNDR	✓	✓	✓	✓
FortiPAM	✓		✓	✓
FortiProxy	✓	✓	✓	✓
FortiSandbox	✓		✓	✓
FortiSOAR	✓		✓	✓
FortiSRA	✓		✓	✓
FortiWeb	✓		✓	✓
Syslog	✓		✓	✓

Language support

The following table lists FortiAnalyzer language support information.

Language	GUI	Reports
English	✓	✓
Chinese (Simplified)	✓	✓
Chinese (Traditional)	✓	✓
French	✓	✓
Hebrew		✓
Hungarian		✓
Japanese	✓	✓
Korean	✓	✓
Portuguese		✓
Russian		✓
Spanish		✓

To change the FortiAnalyzer language setting, go to *System Settings > Admin > Admin Settings*, in *Administrative Settings > Language* select the desired language on the drop-down menu. The default value is *Auto Detect*.

Russian, Hebrew, and Hungarian are not included in the default report languages. You can create your own language translation files for these languages by exporting a predefined language from FortiAnalyzer, modifying the text to a different language, saving the file as a different language name, and then importing the file into FortiAnalyzer. For more information, see the *FortiAnalyzer Administration Guide*.

Supported models

The following tables list which FortiGate, FortiCarrier, FortiDDoS, FortiAnalyzer, FortiMail, FortiSandbox, FortiSwitch ATCA, FortiWeb, FortiCache, FortiProxy, FortiAuthenticator, and other Fortinet product models and firmware versions can send logs to a FortiAnalyzer running version 7.6.2.



Software license activated LENC devices are supported, if their platforms are in the supported models list. For example, support of FG-3200D indicates support of FG-3200D-LENC.

This section contains the following topics:

- [FortiGate models on page 30](#)
- [FortiGate special branch models on page 36](#)
- [FortiCarrier models on page 40](#)
- [FortiCarrier special branch models on page 43](#)
- [FortiADC models on page 45](#)
- [FortiNDR models on page 45](#)
- [FortiAnalyzer models on page 45](#)
- [FortiAP models on page 46](#)
- [FortiAuthenticator models on page 47](#)
- [FortiCache models on page 48](#)
- [FortiDDoS models on page 48](#)
- [FortiDeceptor models on page 48](#)
- [FortiFirewall models on page 49](#)
- [FortiFirewallCarrier models on page 49](#)
- [FortiIsolator models on page 50](#)
- [FortiMail models on page 51](#)
- [FortiNAC models on page 51](#)
- [FortiPAM models on page 51](#)
- [FortiProxy models on page 52](#)
- [FortiSandbox models on page 52](#)
- [FortiSOAR models on page 53](#)
- [FortiSwitch ATCA models on page 53](#)
- [FortiWeb models on page 53](#)

FortiGate models

The following FortiGate models are released with FortiOS firmware. For information about supported FortiGate models on special branch releases of FortiOS firmware, see [FortiGate special branch models on page 36](#).

Model	Firmware Version
<p>FortiGate: FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60F, FortiGate-61F, FortiGate-70F, FortiGate-71F, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90G, FortiGate-91G, FortiGate-100F, FortiGate-101F, FortiGate-120G, FortiGate-121G, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300E, FortiGate-301E, FortiGate-400E, FortiGate-400F, FortiGate-400E-Bypass, FortiGate-401E, FortiGate-401F, FortiGate-500E, FortiGate-501E, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-800D, FortiGate-900D, FortiGate-900G, FortiGate-901G, FortiGate-1000D, FortiGate-1000F, FortiGate-1001F, FortiGate-1100E, FortiGate-1101E, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3200F, FortiGate-3201F, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3600E-DC, FortiGate-3601E, FortiGate-3700D, FortiGate-3700F, FortiGate-3701F, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate-4800F, FortiGate-4801F</p> <p>FortiGate 5000 Series: FortiGate-5001E, FortiGate-5001E1</p> <p>FortiGate 6000 Series: FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC</p> <p>FortiGate 7000 Series: FortiGate-7000E, FortiGate-7000F, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC</p> <p>FortiGate DC: FortiGate-400F-DC, FortiGate-401E-DC, FortiGate-401F-DC, FortiGate-800D-DC, FortiGate-900G-DC, FortiGate-901G-DC, FortiGate-1100E-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-ACDC, FortiGate-3000F-DC, FortiGate-3001F-ACDC, FortiGate-3001F-DC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3700D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC, FortiGate-4800F-DC, FortiGate-4801F-DC</p> <p>FortiWiFi: FWF-40F, FWF-40F-3G4G, FWF-60F, FWF-61F, FWF-80F-2R, FWF-81F-2R, FWF-80F-2R-3G4G-DSL, FWF-81F-2R-3G4G-DSL, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE</p> <p>FortiGate VM: FortiGate-ARM64-AWS, FortiGate-ARM64-Azure, FortiGate-ARM64-GCP, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-Xen</p> <p>FortiGate Rugged: FGR-60F, FGR-60F-3G4G, FGR-70F, FGR-70F-3G4G</p>	7.6

Model	Firmware Version
<p>FortiGate: FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-70F, FortiGate-71F, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-DSL, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-90G, FortiGate-91E, FortiGate-91G, FortiGate-100F, FortiGate-101F, FortiGate-120G, FortiGate-121G, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300E, FortiGate-301E, FortiGate-400E, FortiGate-400F, FortiGate-400E-Bypass, FortiGate-401E, FortiGate-401F, FortiGate-500E, FortiGate-501E, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-800D, FortiGate-900D, FortiGate-900G, FortiGate-901G, FortiGate-1000D, FortiGate-1000F, FortiGate-1001F, FortiGate-1100E, FortiGate-1101E, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3200F, FortiGate-3201F, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3600E-DC, FortiGate-3601E, FortiGate-3700D, FortiGate-3700F, FortiGate-3701F, FortiGate-3800D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate-4800F, FortiGate-4801F</p> <p>FortiGate 5000 Series: FortiGate-5001E, FortiGate-5001E1</p> <p>FortiGate 6000 Series: FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC</p> <p>FortiGate 7000 Series: FortiGate-7000E, FortiGate-7000F, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC</p> <p>FortiGate DC: FortiGate-400F-DC, FortiGate-401E-DC, FortiGate-401F-DC, FortiGate-800D-DC, FortiGate-900G-DC, FortiGate-901G-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-DC, FortiGate-3000F-ACDC, FortiGate-3001F-DC, FortiGate-3001F-ACDC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC</p> <p>FortiWiFi: FWF-40F, FWF-40F-3G4G, FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-80F-2R, FWF-81F-2R, FWF-80F-2R-3G4G-DSL, FWF-81F-2R-3G4G-DSL, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE</p> <p>FortiGate VM: FortiGate-ARM64-AWS, FortiGate-ARM64-Azure, FortiGate-ARM64-GCP, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-Xen</p>	7.4

Model	Firmware Version
FortiGate Rugged: FGR-60F, FGR-60F-3G4G, FGR-70F, FGR-70F-3G4G	
<p>FortiGate: Container-FortiOS, FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-70F, FortiGate-70G, FortiGate-70G-POE, FortiGate-71F, FortiGate-71G, FortiGate-71G-POE, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-DSL, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90G, FortiGate-91E, FortiGate-91G, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-120G, FortiGate-121G, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300E, FortiGate-301E, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-400F, FortiGate-401E, FortiGate-401F, FortiGate-500E, FortiGate-501E, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-800D, FortiGate-900D, FortiGate-900G, FortiGate-901G, FortiGate-1000D, FortiGate-1000F, FortiGate-1001F, FortiGate-1100E, FortiGate-1101E, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3200F, FortiGate-3201F, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3601E, FortiGate-3700D, FortiGate-3700F, FortiGate-3701F, FortiGate-3800D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate-4800F, FortiGate-4801F</p> <p>FortiGate 5000 Series: FortiGate-5001E, FortiGate-5001E1</p> <p>FortiGate 6000 Series: FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC</p> <p>FortiGate 7000 Series: FortiGate-7000E, FortiGate-7000F, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC</p> <p>FortiGate DC: FortiGate-400F-DC, FortiGate-401E-DC, FortiGate-401F-DC, FortiGate-800D-DC, FortiGate-900G-DC, FortiGate-901G-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-DC, FortiGate-3000F-ACDC, FortiGate-3001F-DC, FortiGate-3001F-ACDC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC, FortiGate-4800F-DC, FortiGate-4801F-DC</p> <p>FortiWiFi: FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-70G, FWF-71G, FWF-80F-2R, FWF-80F-2R-3G4G-DSL, FWF-81F-2R, FWF-81F-2R-3G4G-DSL, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE</p>	7.2

Model	Firmware Version
<p>FortiGate VM: FortiGate-ARM64-AWS, FortiGate-ARM64-Azure, FortiGate-ARM64-GCP, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager</p> <p>FortiOS-VM: FOS-VM64, FOS-VM64-HV, FOS-VM64-KVM, FOS-VM64-Xen</p> <p>FortiGate Rugged: FGR-60F, FGR-60F-3G4G, FGR-70F, FGR-70F-3G4G</p>	
<p>FortiGate: FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-70F, FortiGate-71F, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-91E, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300D, FortiGate-300E, FortiGate-301E, FortiGate-400D, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-400F, FortiGate-401E, FortiGate-401F, FortiGate-500D, FortiGate-500E, FortiGate-501E, FortiGate-600D, FortiGate-600E, FortiGate-600F, FortiGate-601E, FortiGate-601F, FortiGate-800D, FortiGate-900D, FortiGate-1000D, FortiGate-1100E, FortiGate-1101E, FortiGate-1200D, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3000F, FortiGate-3001F, FortiGate-3100D, FortiGate-3200D, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3500F, FortiGate-3501F, FortiGate-3600E, FortiGate-3601E, FortiGate-3700D, FortiGate-3800D, FortiGate-3810D, FortiGate-3815D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F,</p> <p>FortiGate 5000 Series: FortiGate-5001D, FortiGate-5001E, FortiGate-5001E1</p> <p>FortiGate DC: FortiGate-400F-DC, FortiGate-401E-DC, FortiGate-401F-DC, FortiGate-800D-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3000F-DC, FortiGate-3000F-ACDC, FortiGate-3001F-DC, FortiGate-3001F-ACDC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3810D-DC, FortiGate-3815D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC</p> <p>FortiWiFi: FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-80F-2R, FWF-81F-2R, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE</p> <p>FortiGate VM: FortiGate-ARM64-AWS, FortiGate-ARM64-KVM, FortiGate-ARM64-OCI, FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-AWS, FortiGate-VM64-Azure, FortiGate-VM64-GCP, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager</p>	7.0

Model	Firmware Version
FortiOS-VM: FOS-VM64, FOS-VM64-HV, FOS-VM64-KVM, FOS-VM64-Xen FortiGate Rugged: FGR-60F, FGR-60F-3G4G	
FortiGate: FortiGate-40F, FortiGate-40F-3G4G, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-91E, FortiGate-100D, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-201F, FortiGate-300D, FortiGate-300E, FortiGate-301E, FortiGate-400D, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-401E, FortiGate-500D, FortiGate-500E, FortiGate-501E, FortiGate-600D, FortiGate-600E, FortiGate-601E, FortiGate-800D, FortiGate-900D, FortiGate-1000D, FortiGate-1100E, FortiGate-1101E, FortiGate-1200D, FortiGate-1500D, FortiGate-1500DT, FortiGate-1800F, FortiGate-1801F, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-2600F, FortiGate-2601F, FortiGate-3000D, FortiGate-3100D, FortiGate-3200D, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3600E, FortiGate-3601E, FortiGate-3700D, FortiGate-3800D, FortiGate-3810D, FortiGate-3815D, FortiGate-3960E, FortiGate-3980E, FortiGate-4200F, FortiGate-4201F, FortiGate-4400F, FortiGate-4401F, FortiGate 5000 Series: FortiGate-5001D, FortiGate-5001E, FortiGate-5001E1 FortiGate DC: FortiGate-401E-DC, FortiGate-800D-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-1800F-DC, FortiGate-1801F-DC, FortiGate-2201E-ACDC, FortiGate-2600F-DC, FortiGate-2601F-DC, FortiGate-3000D-DC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3810D-DC, FortiGate-3815D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC, FortiGate-4200F-DC, FortiGate-4201F-DC, FortiGate-4400F-DC, FortiGate-4401F-DC FortiGate Hardware Low Encryption: FortiGate-100D-LENC FortiWiFi: FWF-40F, FWF-40F-3G4G, FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-80F-2R, FWF-81F-2R, FWF-81F-2R-3G4G-POE, FWF-81F-2R-POE FortiGate VM: FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-ALIONDEMAND, FortiGate-VM64-AWS, FortiGate-VM64-AZUREONDEMAND, FortiGate-VM64-Azure, FortiGate-VM64-GCP, VM64-GCPONDEMAND, FortiGate-VM64-HV, FortiGate-VM64-IBM, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager FortiOS-VM: FOS-VM64, FOS-VM64-HV, FOS-VM64-KVM, FOS-VM64-Xen FortiGate Rugged: FGR-60F, FGR-60F-3G4G	6.4

Model	Firmware Version
<p>FortiGate: FortiGate-30E, FortiGate-30E-3G4G-GBL, FortiGate-30E-3G4G-INTL, FortiGate-30E-3G4G-NAM, FortiGate-40F, FortiGate-40F-3G4G, FortiGate-50E, FortiGate-51E, FortiGate-52E, FortiGate-60E, FortiGate-60E-DSL, FortiGate-60E-DSLJ, FortiGate-60E-POE, FortiGate-60F, FortiGate-61E, FortiGate-61F, FortiGate-80E, FortiGate-80E-POE, FortiGate-80F, FortiGate-80F-Bypass, FortiGate-80F-POE, FortiGate-81E, FortiGate-81E-POE, FortiGate-81F, FortiGate-81F-POE, FortiGate-90E, FortiGate-91E, FortiGate-92D, FortiGate-100D, FortiGate-100E, FortiGate-100EF, FortiGate-100F, FortiGate-101E, FortiGate-101F, FortiGate-140D, FortiGate-140D-POE, FortiGate-140E, FortiGate-140E-POE, FortiGate-200E, FortiGate-200F, FortiGate-201E, FortiGate-300D, FortiGate-300E, FortiGate-301E, FortiGate-400D, FortiGate-400E, FortiGate-400E-Bypass, FortiGate-401E, FortiGate-500D, FortiGate-500E, FortiGate-501E, FortiGate-600D, FortiGate-600E, FortiGate-601E, FortiGate-800D, FortiGate-900D, FortiGate-1000D, FortiGate-1100E, FortiGate-1101E, FortiGate-1200D, FortiGate-1500D, FortiGate-1500DT, FortiGate-2000E, FortiGate-2200E, FortiGate-2201E, FortiGate-2500E, FortiGate-3000D, FortiGate-3100D, FortiGate-3200D, FortiGate-3300E, FortiGate-3301E, FortiGate-3400E, FortiGate-3401E, FortiGate-3600E, FortiGate-3700D, FortiGate-3800D, FortiGate-3810D, FortiGate-3815D, FortiGate-3960E, FortiGate-3980E</p> <p>FortiGate 5000 Series: FortiGate-5001D, FortiGate-5001E, FortiGate-5001E1</p> <p>FortiGate DC: FortiGate-401E-DC, FortiGate-800D-DC, FortiGate-1100E-DC, FortiGate-1500D-DC, FortiGate-2201E-ACDC, FortiGate-3000D-DC, FortiGate-3100D-DC, FortiGate-3200D-DC, FortiGate-3400E-DC, FortiGate-3401E-DC, FortiGate-3600E-DC, FortiGate-3700D-DC, FortiGate-3800D-DC, FortiGate-3810D-DC, FortiGate-3815D-DC, FortiGate-3960E-ACDC, FortiGate-3960E-DC, FortiGate-3980E-DC</p> <p>FortiGate Hardware Low Encryption: FortiGate-100D-LENC</p> <p>FortiWiFi: FWF-30E, FWF-30E-3G4G-INTL, FWF-30E-3G4G-NAM, FWF-40F, FWF-40F-3G4G, FWF-50E, FWF-50E-2R, FWF-51E, FWF-60E, FWF-60E-DSL, FWF-60E-DSLJ, FWF-60F, FWF-61E, FWF-61F, FWF-80F-2R, FortiWiFi-80F-2R-3G4G-DSL, FWF-81F-2R, FWF-81F-2R-POE</p> <p>FortiGate VM: FortiGate-VM64, FortiGate-VM64-ALI, FortiGate-VM64-ALIONDEMAND, FortiGate-VM64-AWS, FortiGate-VM64-AWSONDEMAND, FortiGate-VM64-AZUREONDEMAND, FortiGate-VM64-Azure, FortiGate-VM64-GCP, VM64-GCPONDEMAND, FortiGate-VM64-HV, FortiGate-VM64-KVM, FortiGate-VM64-OPC, FortiGate-VM64-RAXONDEMAND, FortiGate-VM64-XEN, FortiGate-VMX-Service-Manager</p> <p>FortiOS-VM: FOS-VM64, FOS-VM64-HV, FOS-VM64-KVM, FOS-VM64-Xen</p> <p>FortiGate Rugged: FGR-30D, FGR-35D, FGR-60F, FGR-60F-3G4G, FGR-90D</p>	6.2

FortiGate special branch models

The following FortiGate models are released on special branches of FortiOS. FortiAnalyzer version 7.6.2 supports these models on the identified FortiOS version and build number.

For information about supported FortiGate models released with FortiOS firmware, see [FortiGate models on page 30](#).

FortiOS 7.2

FortiGate Model	FortiOS Version
FortiGate-30G	7.2.8
FortiWiFi-30G	7.2.8
FortiGate-70G, FortiGate-71G	7.2.8
FortiGate-70G-POE, FortiGate-71G-POE	7.2.8
FortiGate-200G, FortiGate-201G	7.2.11
FortiWiFi-70G, FortiWiFi-71G	7.2.8

FortiOS 7.0

FortiGate Model	FortiOS Version
FortiGate-50G-DSL	7.0.12
FortiGate-50G-SFP	7.0.12
FortiGate-50G-SFP-POE	7.0.12
FortiGate-51G-SFP-POE	7.0.12
FortiGate-80F-DSL	7.0.15
FortiGate-90G, FortiGate-91G	7.0.15
FortiGate-120G, FortiGate-121G	7.0.15
FortiGate-900G, FortiGate-901G, FortiGate-900G-DC, FortiGate-901G-DC	7.0.15
FortiGate-1000F, FortiGate-1001F	7.0.15
FortiGate-3200F	7.0.15
FortiGate-3201F	7.0.15
FortiGate-3700F, FortiGate-3701F	7.0.15
FortiGate-4800F, FortiGate-4800F-DC, FortiGate-4801F, FortiGate-4801F-DC	7.0.15
FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC	7.0.15

FortiGate Model	FortiOS Version
FortiGate-7000E, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC	7.0.15
FortiGate-7000F, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC	7.0.15
FortiGateRugged-70F, FortiGateRugged-70F-3G4G	7.0.15
FortiWiFi-50G-5G	7.0.12
FortiWiFi-50G-DSL	7.0.12
FortiWiFi-50G-SFP	7.0.12
FortiWiFi-80F-2R-3G4G-DSL	7.0.15
FortiWiFi-81F-2R-3G4G-DSL	7.0.15

FortiOS 6.4

FortiGate Model	FortiOS Version
FortiGate-400F, FortiGate-401F, FortiGate-400F-DC, FortiGate-401F-DC	6.4.13
FortiGate-600F, FortiGate-601F	6.4.13
FortiGate-3500F	6.4.6
FortiGate-3501F	6.4.6
FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC	6.4.13
FortiGate-7000E, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC	6.4.13
FortiGate-7000F, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC	6.4.13
FortiWiFi-80F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-DSL	6.4.7

FortiOS 6.2

FortiGate Model	FortiOS Version
FortiGate-80D	6.2.13
FortiGate-200F, FortiGate-201F	6.2.13
FortiGate-1800F, FortiGate-1800F-DC	6.2.9

FortiGate Model	FortiOS Version
FortiGate-1801F, FortiGate-1801F-DC	
FortiGate-2600F, FortiGate-2600F-DC FortiGate-2601F, FortiGate-2601F-DC	6.2.9
FortiGate-4200F, FortiGate-4200F-DC FortiGate-4201F, FortiGate-4201F-DC	6.2.9
FortiGate-4400F, FortiGate-4400F-DC FortiGate-4401F, FortiGate-4401F-DC	6.2.9
FortiGate-6000F, FortiGate-6001F, FortiGate-6300F, FortiGate-6300F-DC, FortiGate-6301F, FortiGate-6301F-DC, FortiGate-6500F, FortiGate-6500F-DC, FortiGate-6501F, FortiGate-6501F-DC	6.2.13
FortiGate-7000E, FortiGate-7030E, FortiGate-7040E, FortiGate-7060E, FortiGate-7060E-8-DC FortiGate-7000F, FortiGate-7081F, FortiGate-7081F-DC, FortiGate-7081F-2-DC, FortiGate-7121F, FortiGate-7121F-2, FortiGate-7121F-2-DC, FortiGate-7121F-DC	6.2.13
FortiWiFi-80F-2R-3G4G-DSL, FortiWiFi-81F-2R-3G4G-DSL	6.2.6

FortiOS 6.0

FortiGate Model	FortiOS Version
FortiGate-30E-3G4G-GBL	6.0
FortiGate-40F, FortiGate-40F-3G4G	6.0
FortiGate-41F	6.0.6
FortiGate-41F-3G4G	6.0.6
FortiGate-60F, FortiGate-61F	6.0
FortiGate-100F, FortiGate-101F	6.0
FortiGate-1100E, FortiGate-1100E-DC, FortiGate-1101E	6.0
FortiGate-1800F, FortiGate-1800F-DC FortiGate-1801F, FortiGate-1801F-DC	6.0
FortiGate-2200E, FortiGate-2201E, FortiGate-2201E-ACDC	6.0
FortiGate-3300E, FortiGate-3301E	6.0
FortiWiFi-40F, FortiWiFi-40F-3G4G	6.0
FortiWiFi-41F	6.0.6
FortiWiFi-41F-3G4G	6.0.6
FortiWiFi-60F, FortiWiFi-61F	6.0

FortiCarrier models

The following FortiCarrier models are released with FortiCarrier firmware.

For information about supported FortiCarrier models on special branch releases of FortiCarrier firmware, see [FortiCarrier special branch models on page 43](#).

Model	Firmware Version
<p>FortiCarrier: FortiCarrier-3000D, FortiCarrier-3000F, FortiCarrier-3001F, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3200F, FortiCarrier-3201F, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3700F, FortiCarrier-3701F, FortiCarrier-3960E, FortiCarrier-3980E, FortiCarrier-4200F, FortiCarrier-4201F, FortiCarrier-4400F, FortiCarrier-4401F, FortiCarrier-4800F, FortiCarrier-4801F</p> <p>FortiCarrier 5000 Series: FortiCarrier-5001E, FortiCarrier-5001E1</p> <p>FortiCarrier 6000 Series: FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC</p> <p>FortiCarrier 7000 Series: FortiCarrier-7000E, FortiCarrier-7000F, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC</p> <p>FortiCarrier-DC: FortiCarrier-3000D-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3000F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC, FortiCarrier-4200F-DC, FortiCarrier-4201F-DC, FortiCarrier-4400F-DC, FortiCarrier-4401F-DC, FortiCarrier-4800F-DC, FortiCarrier-4801F-DC</p> <p>FortiCarrier-VM: FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-Azure, FortiCarrier-ARM64-GCP, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen</p>	7.6
<p>FortiCarrier: FortiCarrier-2600F, FortiCarrier-2601F, FortiCarrier-3000D, FortiCarrier-3000F, FortiCarrier-3001F, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3200F, FortiCarrier-3201F, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3700F, FortiCarrier-3701F, FortiCarrier-3800D, FortiCarrier-3960E, FortiCarrier-3980E, FortiCarrier-4200F, FortiCarrier-4201F, FortiCarrier-4400F, FortiCarrier-4401F, FortiCarrier-4800F, FortiCarrier-4801F</p> <p>FortiCarrier 5000 Series: FortiCarrier-5001E, FortiCarrier-5001E1</p> <p>FortiCarrier 6000 Series: FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC</p>	7.4

Model	Firmware Version
<p>FortiCarrier 7000 Series: FortiCarrier-7000E, FortiCarrier-7000F, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC</p> <p>FortiCarrier-DC: FortiCarrier-2600F-DC, FortiCarrier-2601F-DC, FortiCarrier-3000D-DC, FortiCarrier-3000F-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC, FortiCarrier-4200F-DC, FortiCarrier-4201F-DC, FortiCarrier-4400F-DC, FortiCarrier-4401F-DC</p> <p>FortiCarrier-VM: FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-Azure, FortiCarrier-ARM64-GCP, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-KVM, FortiCarrier-VM64-IBM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen</p>	
<p>FortiCarrier: FortiCarrier-2600F, FortiCarrier-2601F, FortiCarrier-3000D, FortiCarrier-3000F, FortiCarrier-3001F, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3200F, FortiCarrier-3201F, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3700F, FortiCarrier-3701F, FortiCarrier-3800D, FortiCarrier-3960E, FortiCarrier-3980E, FortiCarrier-4200F, FortiCarrier-4201F, FortiCarrier-4400F, FortiCarrier-4401F, FortiCarrier-4800F, FortiCarrier-4801F</p> <p>FortiCarrier 5000 Series: FortiCarrier-5001E, FortiCarrier-5001E1</p> <p>FortiCarrier 6000 Series: FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC</p> <p>FortiCarrier 7000 Series: FortiCarrier-7000E, FortiCarrier-7000F, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC</p> <p>FortiCarrier-DC: FortiCarrier-2600F-DC, FortiCarrier-2601F-DC, FortiCarrier-3000D-DC, FortiCarrier-3000F-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC, FortiCarrier-4200F-DC, FortiCarrier-4201F-DC, FortiCarrier-4400F-DC, FortiCarrier-4401F-DC</p> <p>FortiCarrier-VM: FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-Azure, FortiCarrier-ARM64-GCP, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen</p>	7.2

Model	Firmware Version
<p>FortiCarrier: FortiCarrier-2600F, FortiCarrier-2601F, FortiCarrier-3000D, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3800D, FortiCarrier-3810D, FortiCarrier-3815D, FortiCarrier-3960E, FortiCarrier-3980E</p> <p>FortiCarrier 5000 Series: FortiCarrier-5001D, FortiCarrier-5001E, FortiCarrier-5001E1</p> <p>FortiCarrier-DC: FortiCarrier-2600F-DC, FortiCarrier-2601F-DC, FortiCarrier-3000D-DC, FortiCarrier-3000F-DC, FortiCarrier-3000F-ACDC, FortiCarrier-3001F-DC, FortiCarrier-3001F-ACDC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3810D-DC, FortiCarrier-3815D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC</p> <p>FortiCarrier-VM: FortiCarrier-ARM64-AWS, FortiCarrier-ARM64-KVM, FortiCarrier-ARM64-OCI, FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen, FortiCarrier-ARM64-KVM</p>	7.0
<p>FortiCarrier: FortiCarrier-3000D, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3500F, FortiCarrier-3501F, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3800D, FortiCarrier-3810D, FortiCarrier-3815D, FortiCarrier-3960E, FortiCarrier-3980E</p> <p>FortiCarrier 5000 Series: FortiCarrier-5001D, FortiCarrier-5001E, FortiCarrier-5001E1</p> <p>FortiCarrier-DC: FortiCarrier-3000D-DC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3810D-DC, FortiCarrier-3815D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC</p> <p>FortiCarrier-VM: FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-IBM, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen</p>	6.4
<p>FortiCarrier: FortiCarrier-3000D, FortiCarrier-3100D, FortiCarrier-3200D, FortiCarrier-3300E, FortiCarrier-3301E, FortiCarrier-3400E, FortiCarrier-3401E, FortiCarrier-3600E, FortiCarrier-3601E, FortiCarrier-3700D, FortiCarrier-3800D, FortiCarrier-3810D, FortiCarrier-3815D, FortiCarrier-3960E, FortiCarrier-3980E</p> <p>FortiCarrier 5000 Series: FortiCarrier-5001D, FortiCarrier-5001E, FortiCarrier-5001E1</p> <p>FortiCarrier-DC: FortiCarrier-3000D-DC, FortiCarrier-3100D-DC, FortiCarrier-3200D-DC, FortiCarrier-3400E-DC, FortiCarrier-3401E-DC, FortiCarrier-3600E-DC, FortiCarrier-3700D-DC, FortiCarrier-3800D-DC, FortiCarrier-3810D-DC, FortiCarrier-3815D-DC, FortiCarrier-3960E-DC, FortiCarrier-3980E-DC</p> <p>FortiCarrier 6K and 7K: FortiCarrier-6000F, FortiCarrier-6300F, FortiCarrier-6301F, FortiCarrier-6500F, FortiCarrier-6501F, FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7000F, FortiCarrier-7121F, FortiCarrier-7121F-2</p>	6.2

Model	Firmware Version
FortiCarrier 6K and 7K DC: FortiCarrier-6000F-DC, FortiCarrier-6300F-DC, FortiCarrier-6301F-DC, FortiCarrier-6500F-DC, FortiCarrier-6501F-DC, FortiCarrier-7060E-8-DC, FortiCarrier-7121F-DC, FortiCarrier-7121F-2-DC	
FortiCarrier-VM: FortiCarrier-VM64, FortiCarrier-VM64-ALI, FortiCarrier-VM64-AWS, FortiCarrier-VM64-Azure, FortiCarrier-VM64-GCP, FortiCarrier-VM64-HV, FortiCarrier-VM64-KVM, FortiCarrier-VM64-OPC, FortiCarrier-VM64-Xen	

FortiCarrier special branch models

The following FortiCarrier models are released on special branches of FortiOS Carrier. FortiAnalyzer version 7.6.2 supports these models on the identified FortiOS Carrier version and build number.

For information about supported FortiCarrier models released with FortiOS Carrier firmware, see [FortiCarrier models on page 40](#).

FortiCarrier 7.0

FortiCarrier Model	FortiCarrier Version
FortiCarrier-3200F	7.0.15
FortiCarrier-3201F	7.0.15
FortiCarrier-3700F, FortiCarrier-3701F	7.0.15
FortiCarrier-4800F, FortiCarrier-4800F-DC, FortiCarrier-4801F, FortiCarrier-4801F-DC	7.0.15
FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC	7.0.15
FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC	7.0.15
FortiCarrier-7000F, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC	7.0.15

FortiCarrier 6.4

FortiCarrier Model	FortiCarrier Version
FortiCarrier-3500F	6.4.6
FortiCarrier-3501F	6.4.6

FortiCarrier Model	FortiCarrier Version
FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC	6.4.13
FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC	6.4.13
FortiCarrier-7000F, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC	6.4.13

FortiCarrier 6.2

FortiCarrier Model	FortiCarrier Version
FortiCarrier-4200F, FortiCarrier-4200F-DC FortiCarrier-4201F, FortiCarrier-4201F-DC FortiCarrier-4400F, FortiCarrier-4400F-DC, FortiCarrier-4401F, FortiCarrier-4401F-DC	6.2.9
FortiCarrier-6000F, FortiCarrier-6001F, FortiCarrier-6300F, FortiCarrier-6300F-DC, FortiCarrier-6301F, FortiCarrier-6301F-DC, FortiCarrier-6500F, FortiCarrier-6500F-DC, FortiCarrier-65001F, FortiCarrier-6501F-DC	6.2.13
FortiCarrier-7000E, FortiCarrier-7030E, FortiCarrier-7040E, FortiCarrier-7060E, FortiCarrier-7060E-8-DC FortiCarrier-7000F, FortiCarrier-7081F, FortiCarrier-7081F-DC, FortiCarrier-7081F-2-DC, FortiCarrier-7121F, FortiCarrier-7121F-2, FortiCarrier-7121F-2-DC, FortiCarrier-7121F-DC	6.2.13

FortiCarrier 6.0

FortiCarrier Model	FortiCarrier Version
FortiCarrier-VM64-Azure	6.0

FortiADC models

Model	Firmware Version
FortiADC: FortiADC-100F, FortiADC-120F, FortiADC-200D, FortiADC-200F, FortiADC-220F, FortiADC-300D, FortiADC-300F, FortiADC-320F, FortiADC-400D, FortiADC-400F, FortiADC-420F, FortiADC-700D, FortiADC-1000F, FortiADC-1200F, FortiADC-1500D, FortiADC-2000D, FortiADC-2000F, FortiADC-2200F, FortiADC-4000D, FortiADC-4000F, FortiADC-4200F, FortiADC-5000F FortiADC VM: FortiADC-VM	7.4
FortiADC: FortiADC-100F, FortiADC-120F, FortiADC-200D, FortiADC-200F, FortiADC-220F, FortiADC-300D, FortiADC-300F, FortiADC-400D, FortiADC-400F, FortiADC-700D, FortiADC-1000F, FortiADC-1200F, FortiADC-1500D, FortiADC-2000D, FortiADC-2000F, FortiADC-2200F, FortiADC-4000D, FortiADC-4000F, FortiADC-4200F, FortiADC-5000F FortiADC VM: FortiADC-VM	7.1, 7.2

FortiNDR models

Model	Firmware Version
FortiNDR: FortiNDR-1000F, FortiNDR-3500F, FortiNDR-3600G FortiNDR-VM: FortiNDR-KVM, FortiNDR-VM, FortiNDR-VMC	7.4
FortiNDR: FortiNDR-1000F, FortiNDR-3500F FortiNDR-VM: FortiNDR-KVM, FortiNDR-VM	7.2
FortiNDR: FortiNDR-3500F FortiNDR-VM: FortiNDR-KVM, FortiNDR-VM	7.0, 7.1

FortiAnalyzer models

Model	Firmware Version
FortiAnalyzer: FortiAnalyzer-150G, FortiAnalyzer-300G, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-1000G, FortiAnalyzer-2000E, FortiAnalyzer-3000F, FortiAnalyzer-3100G, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3510G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3900E FortiAnalyzer VM: FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-AWS-OnDemand, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-Xen	7.6

Model	Firmware Version
<p>FortiAnalyzer: FortiAnalyzer-150G, FortiAnalyzer-300F, FortiAnalyzer-300G, FortiAnalyzer-400E, FortiAnalyzer-800F, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-1000G, FortiAnalyzer-2000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3100G, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3510G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3900E</p> <p>FortiAnalyzer VM: FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-AWS-OnDemand, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-Azure-OnDemand, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-Xen</p>	7.4
<p>FortiAnalyzer: FortiAnalyzer-150G, FortiAnalyzer-300F, FortiAnalyzer-300G, FortiAnalyzer-400E, FortiAnalyzer-800F, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-1000G, FortiAnalyzer-2000E, FortiAnalyzer-3000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3100G, FortiAnalyzer-3500E, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3510G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3900E</p> <p>FortiAnalyzer VM: FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-AWS-OnDemand, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-Azure-OnDemand, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-Xen</p>	7.2
<p>FortiAnalyzer: FortiAnalyzer-150G, FortiAnalyzer-200F, FortiAnalyzer-300F, FortiAnalyzer-300G, FortiAnalyzer-400E, FortiAnalyzer-800F, FortiAnalyzer-800G, FortiAnalyzer-810G, FortiAnalyzer-1000F, FortiAnalyzer-1000G, FortiAnalyzer-2000E, FortiAnalyzer-3000E, FortiAnalyzer-3000F, FortiAnalyzer-3000G, FortiAnalyzer-3100G, FortiAnalyzer-3500E, FortiAnalyzer-3500F, FortiAnalyzer-3500G, FortiAnalyzer-3700F, FortiAnalyzer-3700G, FortiAnalyzer-3900E</p> <p>FortiAnalyzer VM: FortiAnalyzer-VM64, FortiAnalyzer-VM64-ALI, FortiAnalyzer-VM64-ALI-OnDemand, FortiAnalyzer-VM64-AWS, FortiAnalyzer-VM64-Azure, FortiAnalyzer-VM64-Azure-OnDemand, FortiAnalyzer-VM64-GCP, FortiAnalyzer-VM64-GCP-OnDemand, FortiAnalyzer-VM64-HV, FortiAnalyzer-VM64-IBM, FortiAnalyzer-VM64-KVM, FortiAnalyzer-VM64-OPC, FortiAnalyzer-VM64-Xen</p>	7.0

FortiAP models

Model	Firmware Version
FortiAP-231K, FortiAP-241K, FortiAP-243K, FortiAP-432FR, FortiAP-432G, FortiAP-441K, FortiAP-443K	7.4

Model	Firmware Version
FortiAP-23JF, FortiAP-221E, FortiAP-222E, FortiAP-223E, FortiAP-224E, FortiAP-231E, FortiAP-231F, FortiAP-231G, FortiAP-233G, FortiAP-234F, FortiAP-234G, FortiAP-431F, FortiAP-431G, FortiAP-432F, FortiAP-432G, FortiAP-433F, FortiAP-433G, FortiAP-831F	7.2
FortiAP-23JF, FortiAP-221E, FortiAP-222E, FortiAP-223E, FortiAP-224E, FortiAP-231E, FortiAP-231F, FortiAP-234F, FortiAP-431F, FortiAP-432F, FortiAP-433F, FortiAP-831F	7.0
FortiAP-23JF, FortiAP-221E, FortiAP-222E, FortiAP-223E, FortiAP-224E, FortiAP-231E, FortiAP-231F, FortiAP-234F, FortiAP-321E, FortiAP-421E, FortiAP-423E, FortiAP-431F, FortiAP-432F, FortiAP-433F, FortiAP-831F, FortiAP-S221E, FortiAP-S223E, FortiAP-S421E, FortiAP-S422E, FortiAP-S423E	6.4
FortiAP-221E, FortiAP-222E, FortiAP-223E, FortiAP-231E, FortiAP-321E, FortiAP-421E, FortiAP-423E, FortiAP-S221E, FortiAP-S223E, FortiAP-S421E, FortiAP-S422E, FortiAP-S423E	6.2
FortiAP-11C, FortiAP-14C, FortiAP-21B, FortiAP-21D, FortiAP-22B, FortiAP-24D, FortiAP-25D, FortiAP-28C, FortiAP-112B, FortiAP-112D, FortiAP-214B, FortiAP-221B, FortiAP-221C, FortiAP-221E, FortiAP-222, FortiAP-222C, FortiAP-222E, FortiAP-223B, FortiAP-223C, FortiAP-223E, FortiAP-224D, FortiAP-224E, FortiAP-231E, FortiAP-320B, FortiAP-320C, FortiAP-321C, FortiAP-321CR, FortiAP-321E, FortiAP-322CR, FortiAP-323CR, FortiAP-421E, FortiAP-423E, FortiAP-C23JD, FortiAP-C24JE, FortiAP-C220C, FortiAP-C225C, FortiAP-S221E, FortiAP-S223E, FortiAP-S311C, FortiAP-S313C, FortiAP-S321C, FortiAP-S322C, FortiAP-S323C, FortiAP-S421E, FortiAP-S422E, FortiAP-S423E, FortiAP-U24JEV, FortiAP-U221EV, FortiAP-U223EV, FortiAP-U231F, FortiAP-U234F, FortiAP-U321EV, FortiAP-U323EV, FortiAP-U421EV, FortiAP-U422EV, FortiAP-U423EV, FortiAP-U431F, FortiAP-U432F, FortiAP-U433F	6.0

FortiAuthenticator models

Model	Firmware Version
FortiAuthenticator: FAC-200E, FAC-300F, FAC-400E, FAC-800F, FAC-2000E, FAC-3000E, FAC-3000F FortiAuthenticator VM: FAC-VM	6.6
FortiAuthenticator: FAC-200E, FAC-300F, FAC-400E, FAC-800F, FAC-2000E, FAC-3000E, FAC-3000F FortiAuthenticator VM: FAC-VM	6.5
FortiAuthenticator: FAC-200D, FAC-200E, FAC-300F, FAC-400C, FAC-400E, FAC-800F, FAC-1000C, FAC-1000D, FAC-2000E, FAC-3000D, FAC-3000E, FAC-3000F FortiAuthenticator VM: FAC-VM	6.4
FortiAuthenticator: FAC-200D, FAC-200E, FAC-300F, FAC-400C, FAC-400E, FAC-800F, FAC-1000C, FAC-1000D, FAC-2000E, FAC-3000D, FAC-3000E FortiAuthenticator VM: FAC-VM	6.3

FortiCache models

Model	Firmware Version
FortiCache: FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3000E, FCH-3900E FortiCache VM: FCH-KVM, FCH-VM64	4.1, 4.2
FortiCache: FCH-400C, FCH-400E, FCH-1000C, FCH-1000D, FCH-3000C, FCH-3000D, FCH-3900E FortiCache VM: FCH-VM64	4.0

FortiDDoS models

Model	Firmware Version
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-2000F, FortiDDoS-3000F FortiDDoS VM: FortiDDoS-VM	6.4, 6.5, 6.6, 7.0
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F, FortiDDoS-2000F FortiDDoS VM: FortiDDoS-VM	6.3
FortiDDoS: FortiDDoS-200F, FortiDDoS-1500F FortiDDoS VM: FortiDDoS-VM	6.2
FortiDDoS: FortiDDoS-200B, FortiDDoS-400B, FortiDDoS-600B, FortiDDoS-800B, FortiDDoS-900B, FortiDDoS-1000B, FortiDDoS-1200B, FortiDDoS-1500E, FortiDDoS-2000B, FortiDDoS-2000E	5.6, 5.7

FortiDeceptor models

Model	Firmware Version
FortiDeceptor: FDC-100G, FDC-1000F, FDC-1000G FortiDeceptor Rugged: FDCR-100G FortiDeceptor VM: FDC-VM	5.0, 5.1, 5.2, 5.3, 6.0
FortiDeceptor: FDC-1000F, FDC-1000G FortiDeceptor Rugged: FDCR-100G FortiDeceptor VM: FDC-VM	4.3

FortiFirewall models

Some of the following FortiFirewall models are released on special branches of FortiFirewall firmware. FortiAnalyzer version 7.6.2 supports these models on the identified FortiFirewall firmware version and build number.

Model	Firmware Version
FortiFirewall: FortiFirewall-1801F, FortiFirewall-2600F, FortiFirewall-3001F, FortiFirewall-3501F, FortiFirewall-3980E, FortiFirewall-4200F, FortiFirewall-4400F, FortiFirewall-4401F, FortiFirewall-4801F FortiFirewall DC: FortiFirewall-3980E-DC, FortiFirewall-4200F-DC, FortiFirewall-4400F-DC, FortiFirewall-4401F-DC FortiFirewall-VM: FortiFirewall-VM64, FortiFirewall-VM64-KVM	7.6
FortiFirewall: FortiFirewall-1801F, FortiFirewall-2600F, FortiFirewall-3001F, FortiFirewall-3501F, FortiFirewall-3980E, FortiFirewall-4200F, FortiFirewall-4400F, FortiFirewall-4401F, FortiFirewall-4801F FortiFirewall DC: FortiFirewall-3980E-DC, FortiFirewall-4200F-DC, FortiFirewall-4400F-DC, FortiFirewall-4401F-DC FortiFirewall-VM: FortiFirewall-VM64, FortiFirewall-VM64-KVM	7.4
FortiFirewall: FortiFirewall-3980E, FortiFirewall-4200F, FortiFirewall-4400F, FortiFirewall-4401F, FortiFirewall-4801F FortiFirewall DC: FortiFirewall-4200F-DC, FortiFirewall-4401F-DC FortiFirewall-VM: FortiFirewall-VM64, FortiFirewall-VM64-KVM	7.2
FortiFirewall: FortiFirewall-3980E FortiFirewall DC: FortiFirewall-3980E-DC FortiFirewall-VM: FortiFirewall-VM64, FortiFirewall-VM64-KVM	7.0

FortiFirewall special branch models

Model	Firmware Version	Firmware Build (for special branch)
FortiFirewall: FortiFirewall-3001F	7.0.10	4955
FortiFirewall: FortiFirewall-3501F	7.0.10	4955

FortiFirewallCarrier models

Some of the following FortiFirewallCarrier models are released on special branches of FortiFirewallCarrier firmware. FortiAnalyzer version 7.6.2 supports these models on the identified FortiFirewallCarrier firmware version and build number.

Model	Firmware Version
FortiFirewallCarrier: FortiFirewallCarrier-3001F, FortiFirewallCarrier-3501F, FortiFirewallCarrier-3980E, FortiFirewallCarrier-4200F, FortiFirewallCarrier-4400F, FortiFirewallCarrier-4401F, FortiFirewallCarrier-4801F FortiFirewallCarrier DC: FortiFirewallCarrier-4200F-DC, FortiFirewallCarrier-4401F-DC FortiFirewallCarrier-VM: FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	7.6
FortiFirewallCarrier: FortiFirewallCarrier-1801F, FortiFirewallCarrier-2600F, FortiFirewallCarrier-3001F, FortiFirewallCarrier-3501F, FortiFirewallCarrier-3980E, FortiFirewallCarrier-4200F, FortiFirewallCarrier-4400F, FortiFirewallCarrier-4401F, FortiFirewallCarrier-4801F FortiFirewallCarrier DC: FortiFirewallCarrier-1801F-DC, FortiFirewallCarrier-4200F-DC, FortiFirewallCarrier-4401F-DC FortiFirewallCarrier-VM: FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	7.4
FortiFirewallCarrier: FortiFirewallCarrier-2600F, FortiFirewallCarrier-3980E, FortiFirewallCarrier-4200F, FortiFirewallCarrier-4400F, FortiFirewallCarrier-4801F FortiFirewallCarrier DC: FortiFirewallCarrier-4200F-DC FortiFirewallCarrier-VM: FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	7.2
FortiFirewallCarrier-VM: FortiFirewallCarrier-VM64, FortiFirewallCarrier-VM64-KVM	7.0

FortiFirewall special branch models

Model	Firmware Version	Firmware Build
FortiFirewallCarrier: FortiFirewallCarrier-1801F, FortiFirewallCarrier-4401F	7.2.6	4609
FortiFirewallCarrier: FortiFirewallCarrier-3001F	7.0.10	4955
FortiFirewallCarrier: FortiFirewallCarrier-3501F	7.0.10	4940

Fortisolator models

Model	Firmware Version
Fortisolator: Fortisolator-1000F, Fortisolator-1000G, Fortisolator-3000F Fortisolator-VM: Fortisolator-VM	2.4

FortiMail models

Model	Firmware Version
FortiMail: FE-60D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-900G, FE-2000E, FE-2000F, FE-3000D, FE-3000E, FE-3000F, FE-3200E FortiMail VM: FML-VM, FML-VM-AWS, FortiMail Cloud	7.6
FortiMail: FE-60D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-2000E, FE-2000F, FE-3000D, FE-3000E, FE-3000F, FE-3200E FortiMail VM: FML-VM, FML-VM-AWS, FortiMail Cloud	7.4
FortiMail: FE-60D, FE-200D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-2000E, FE-2000F, FE-3000D, FE-3000E, FE-3000F, FE-3200E FortiMail VM: FML-VM, FortiMail Cloud	7.2
FortiMail: FE-60D, FE-200D, FE-200E, FE-200F, FE-400E, FE-400F, FE-900F, FE-1000D, FE-2000E, FE-2000F, FE-3000D, FE-3000E, FE-3000F, FE-3200E FortiMail VM: FML-VM, FortiMail Cloud	7.0

FortiNAC models

Model	Firmware Version
FortiNAC: FortiNAC-500, FortiNAC-600, FortiNAC-700, FortiNAC-C-1000C, FortiNAC-C-2000C, FortiNAC-CA-500C, FortiNAC-Manager-550 FortiNAC VM: FortiNAC-C-VM, FortiNAC-CA-VM, FortiNAC-M-VM	9.4
FortiNAC: FortiNAC-500, FortiNAC-600, FortiNAC-700, FortiNAC-C-1000C, FortiNAC-C-2000C, FortiNAC-Manager-550 FortiNAC VM: FortiNAC-C-VM, FortiNAC-CA-VM, FortiNAC-M-VM	9.1, 9.2
FortiNAC: FortiNAC-CA-500F, FortiNAC-M-550F, FortiNAC-CA-600F, FortiNAC-CA-700F FortiNAC VM: FortiNAC-VM-ESXI, FortiNAC-MX-VM	7.4
FortiNAC: FortiNAC-CA-500F, FortiNAC-M-550F, FortiNAC-CA-600F, FortiNAC-CA-700F FortiNAC VM: FortiNAC-F-VM, FortiNAC-VM-ESXI, FortiNAC-MX-VM	7.2

FortiPAM models

Model	Firmware Version
FortiPAM: FortiPAM-1000G, FortiPAM-3000G	1.0, 1.1, 1.2, 1.3, 1.4

Model	Firmware Version
FortiPAM VM: FortiPAM-AWS, FortiPAM-Azure, FortiPAM-GCP, FortiPAM-HyperV, FortiPAM-KVM, FortiPAM-VM64	

FortiProxy models

Model	Firmware Version
FortiProxy: FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G FortiProxy VM: FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-OPC, FortiProxy-VM64	7.4
FortiProxy: FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G FortiProxy VM: FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-VM64	7.2
FortiProxy: FPX-400E, FPX-400G, FPX-2000E, FPX-2000G, FPX-4000E, FPX-4000G FortiProxy VM: FortiProxy-AliCloud, FortiProxy-AWS, FortiProxy-Azure, FortiProxy-GCP, FortiProxy-HyperV, FortiProxy-KVM, FortiProxy-OPC, FortiProxy-VM64	7.0
FortiProxy: FPX-400E, FPX-2000E, FPX-4000E FortiProxy VM: FortiProxy-KVM, FortiProxy-VM64	1.0, 1.1, 1.2, 2.0

FortiSandbox models

Model	Firmware Version
FortiSandbox: FSA-500F, FSA-500G, FSA-1000D, FSA-1000F, FSA-1500G, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3000F, FSA-3500D FortiSandbox DC: FSA-1000F-DC FortiSandbox-VM: FortiSandbox-AWS, FortiSandbox-Cloud, FSA-VM	4.2, 4.4
FortiSandbox: FSA-500F, FSA-1000D, FSA-1000F, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3000F, FSA-3500D FortiSandbox DC: FSA-1000F-DC FortiSandbox-VM: FortiSandbox-AWS, FortiSandbox-Cloud, FSA-VM	4.0
FortiSandbox: FSA-500F, FSA-1000D, FSA-1000F, FSA-2000E, FSA-3000D, FSA-3000E, FSA-3500D FortiSandbox DC: FSA-1000F-DC FortiSandbox-VM: FortiSandbox-AWS, FSA-VM	3.2

FortiSOAR models

Model	Firmware Version
FortiSOAR VM: FortiSOAR-VM	7.2, 7.3, 7.4, 7.5, 7.6

FortiSRA models

Model	Firmware Version
FortiSRA: FortiSRA-1000G, FortiSRA-3000G	1.0, 1.1
FortiSRA-VM: FortiSRA-Azure, FortiSRA-HyperV, FortiSRA-KVM, FortiSRA-VM64	

FortiSwitch ATCA models

Model	Firmware Version
FortiController: FTCL-5103B, FTCL-5903C, FTCL-5913C	5.2
FortiSwitch-ATCA: FS-5003A, FS-5003B FortiController: FTCL-5103B	5.0
FortiSwitch-ATCA: FS-5003A, FS-5003B	4.3

FortiWeb models

Model	Firmware Version
FortiWeb: FortiWeb-100D, FortiWeb-100E, FortiWeb-100F, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-400F, FortiWeb-600D, FortiWeb-600E, FortiWeb-600F, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-1000F, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F	7.6
FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer	
FortiWeb Cloud, including FortiAppSec Cloud.	

Model	Firmware Version
<p>FortiWeb: FortiWeb-100D, FortiWeb-100E, FortiWeb-100F, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-400F, FortiWeb-600D, FortiWeb-600E, FortiWeb-600F, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-1000F, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F</p> <p>FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer</p> <p>FortiWeb Cloud, including FortiAppSec Cloud.</p>	7.4
<p>FortiWeb: FortiWeb-100D, FortiWeb-100E, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-600D, FortiWeb-600E, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-1000F, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F</p> <p>FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer</p> <p>FortiWeb Cloud, including FortiAppSec Cloud.</p>	7.2
<p>FortiWeb: FortiWeb-100D, FortiWeb-100E, FortiWeb-400C, FortiWeb-400D, FortiWeb-400E, FortiWeb-600D, FortiWeb-600E, FortiWeb-1000D, FortiWeb-1000E, FortiWeb-2000E, FortiWeb-2000F, FortiWeb-3000C, FortiWeb-3000CFSX, FortiWeb-3000D, FortiWeb-3000DFSX, FortiWeb-3000E, FortiWeb-3000F, FortiWeb-3010E, FortiWeb-4000C, FortiWeb-4000D, FortiWeb-4000E, FortiWeb-4000F</p> <p>FortiWeb VM: FortiWeb-Azure, FortiWeb-Azure_OnDemand, FortiWeb-GCP, FortiWeb-GCP_OnDemand, FortiWeb-HyperV, FortiWeb-VM, FortiWeb-XENOpenSource, FortiWeb-XENServer</p> <p>FortiWeb Cloud, including FortiAppSec Cloud.</p>	7.0

Resolved Issues

The following issues have been fixed in FortiAnalyzer version 7.6.2. To inquire about a particular bug, please contact [Customer Service & Support](#).

Device Manager

Bug ID	Description
1106056	Deleting a model device may result in the removal of the Logs folder under Storage. This issue occurs only if the model device never comes online and does not match a FortiGate.

Fabric View

Bug ID	Description
1078817	The "FortiClient EMS Cloud" Fabric Connector (existing/newly added) may not function properly, causing FortiAnalyzer to potentially fail in establishing a successful connection with the "FortiClient EMS Cloud" due to this issue.

FortiView

Bug ID	Description
922053	Mismatched Username Detected for the Same IP Address in IOC Compromised Hosts.
1050052	In some cases, the compromised host entry may display different FSSO users and source IPs than the actual users and source IPs on the drill-down page.

Log View

Bug ID	Description
1058278	The Preview under the Chart Builder displays "No record found". Dataset is saved but chart is not saved.
1061367	The Webfilter logs are not visible on the FortiGate's GUI if the source set to FortiAnalyzer.

Others

Bug ID	Description
1060337	The log insertion might be interrupted if FortiAnalyzer is upgraded directly from version (7.4.0/7.4.1) to 7.6.0/7.6.1.
1062128	After upgrading to the latest available build, the FortiAnalyzer GUI displays the warning message: "A new firmware version is available".
1064103	The "siemdb" daemon may fail to start on a FortiAnalyzer VM running version 7.6.0, which can prevent log migration from completing. This issue may occur due to inconsistencies in the number of CPUs reported by the system during initialization. Certain CPU-related settings might trigger this problem. For more details, see "The "siemdb" daemon may fail to start on a FortiAnalyzer 7.6.0/7.6.1 VM" special notice in the FortiAnalyzer 7.6.1 Release Notes .

System Settings

Bug ID	Description
766197	An admin user limited to a device group can view all device's log.
1027547	In certain cases, the License Status on FortiAnalyzer may be incorrectly displayed as "Expired" despite the license being active in the account.
1058282	Remote administrators may be unable to review the Event Logs, as the GUI might display the following message: "Web Server Error 500."
1063040	Unable to import a local certificate into FortiAnalyzer. This issue may occur if the certificate is encrypted with a newer OpenSSL version that FortiAnalyzer does not yet support.

Common Vulnerabilities and Exposures

Visit <https://fortiguard.com/psirt> for more information.

Bug ID	CVE references
1055001	FortiAnalyzer 7.6.2 is no longer vulnerable to the following CVE Reference: <ul style="list-style-type: none">• CVE-2024-3596
1060887	FortiAnalyzer 7.6.2 is no longer vulnerable to the following CVE Reference: <ul style="list-style-type: none">• CVE-2024-50563
1108960	FortiAnalyzer 7.6.2 is no longer vulnerable to the following CVE Reference: <ul style="list-style-type: none">• CVE-2024-52962
1125739	FortiAnalyzer 7.6.2 is no longer vulnerable to the following CVE Reference: <ul style="list-style-type: none">• CVE-2025-24474

Known issues

Known issues are organized into the following categories:

- [New known issues on page 58](#)
- [Existing known issues on page 58](#)

To inquire about a particular bug or to report a bug, please contact [Fortinet Customer Service & Support](#).

New known issues

The following issues have been identified in version 7.6.2.

Log View

Bug ID	Description
1098480	After upgrading to 7.6.2, log insertion might be interrupted after some time. Workaround: Reboot the FortiAnalyzer or restart the "sqllogd" process by using the following command: <code>diagnose test application sqllogd 99</code>
1117011	After upgrading to 7.6.2, analytic logs may not display any logs. Workaround: Run the following command to rebuild the database: <code>execute sql-local rebuild-db</code>

Existing known issues

The following issues have been identified in a previous version of FortiAnalyzer and remain in FortiAnalyzer 7.6.2.

Device Manager

Bug ID	Description
927113	FortiAnalyzer displays incorrect EMS server version, IP address, and connectivity status.

FortiSOC

Bug ID	Description
872637	The status of FortiGate Connectors under FortiSOC is intermittently down.

FortiView

Bug ID	Description
954542	When the time range is extensive, FortiAnalyzer may experience limitations in handling data points, resulting in potential omissions of data entries in the final results for <i>FortiView</i> SD-WAN Monitors widgets.
989446	FortiView SD-WAN Bandwidth Overview displays no data.
1092311	FortiAnalyzer may not display any data when accessing FortiView in the VPN site-to-site tab.

Others

Bug ID	Description
1053830	MEAs cannot be enabled from FortiAnalyzer's GUI. Workaround: Use the following CLI command to enable them (in this example, universalconnector): <pre>config system docker set status enable set universalconnector enable end</pre>
1098690	After an upgrade, users (prior to the upgrade) who were created and assigned to a custom admin profile (with the super_user_profile enabled) may encounter a GUI issue. Upon successful login, the login prompt disappears, but only the background color remains visible with no additional GUI elements loaded.

Reports

Bug ID	Description
895106	Top destination by bandwidth dataset does not exclude long-live session.
937700	Source IP on the report is shown as the Victim in the default Security Analysis report.
1013026	Network Interface Utilization Charts are blank in Reports.
1069669	The filter feature for 'subnet' in <i>Reports</i> does not work accurately.

System Settings

Bug ID	Description
1050063	FortiAnalyzer experiences issues when log forwarding is configured (Log forward filter).

Appendix A - Default and maximum number of ADOMs supported

This section identifies the supported number of ADOMs for FortiAnalyzer hardware models and virtual machines.

See also the [FortiAnalyzer Data Sheet](#).

Hardware models

FortiAnalyzer supports a default number of ADOMs based on hardware model.

Some hardware models support an ADOM subscription license. When you purchase an ADOM subscription license, you increase the number of supported ADOMs. For example, you can purchase an ADOM subscription license for the FAZ-3000G series, which allows you to use up to a maximum of 1200 ADOMs. Other hardware models do not support the ADOM subscription license.

Some older hardware models do not enforce ADOM limits. These models will display a warning message when the ADOM limit is reached or exceeded; adding more ADOMs may affect performance. These devices are still subject to maximum device limits which are listed in the FortiAnalyzer Data Sheet.

The table below lists the maximum number of ADOMs by platform. Models that enforce the maximum as a hard limit are indicated in the *Hard limit* column.

FortiAnalyzer Platform	Maximum number of ADOMs	Hard limit
Desktop models	1	✓
150G	3	✓
300G	25	✓
800G	50	✓
1000F	50	✓
2000E	250	
3000F	500	
3000G	500 *1200	✓
3500F	500	
3500G	500	✓

FortiAnalyzer Platform	Maximum number of ADOMs	Hard limit
	*500	
3700F	1200	
3700G	1200	✓
	*10,000	

*Maximum number of supported ADOMs can be increased to this value with an ADOM subscription license.

Virtual Machines



For subscription licenses, FortiAnalyzer enforces the ADOM limits.
 For perpetual licenses, ADOM limits are recommended, but not enforced.

FortiAnalyzer subscription license

Five (5) ADOMs are included with FortiAnalyzer VM subscription licenses. Additional ADOMs can be purchased with an ADOM subscription license.

FortiAnalyzer perpetual license

Recommended maximum number of ADOMs supported:

FortiAnalyzer Platform	Default number of ADOMs
1 GB/Day < License <= 5 GB/Day	10
5 GB/Day < License <= 25 GB/Day	25
25 GB/Day < License <= 100 GB/Day	50
100 GB/Day < License <= 500 GB/Day	250
500 GB/Day < License <= 1000 GB/Day	500
1000 GB/Day < License <= 5000 GB/Day	800
License > 5000 GB/Day	1200



- FortiAnalyzer-VM subscription licenses are fully stackable.
- For FortiAnalyzer-VM perpetual licenses, only the GB/Day is stackable.



www.fortinet.com

Copyright © 2026 Fortinet, Inc. All rights reserved. Fortinet®, FortiGate®, FortiCare® and FortiGuard®, and certain other marks are registered trademarks of Fortinet, Inc., and other Fortinet names herein may also be registered and/or common law trademarks of Fortinet. All other product or company names may be trademarks of their respective owners. Performance and other metrics contained herein were attained in internal lab tests under ideal conditions, and actual performance and other results may vary. Network variables, different network environments and other conditions may affect performance results. Nothing herein represents any binding commitment by Fortinet, and Fortinet disclaims all warranties, whether express or implied, except to the extent Fortinet enters a binding written contract, signed by Fortinet's Chief Legal Officer, with a purchaser that expressly warrants that the identified product will perform according to certain expressly-identified performance metrics and, in such event, only the specific performance metrics expressly identified in such binding written contract shall be binding on Fortinet. For absolute clarity, any such warranty will be limited to performance in the same ideal conditions as in Fortinet's internal lab tests. Fortinet disclaims in full any covenants, representations, and guarantees pursuant hereto, whether express or implied. Fortinet reserves the right to change, modify, transfer, or otherwise revise this publication without notice, and the most current version of the publication shall be applicable.