




CLI Reference

FortiProxy 7.4.11



FORTINET DOCUMENT LIBRARY

<https://docs.fortinet.com>

FORTINET VIDEO LIBRARY

<https://video.fortinet.com>

FORTINET BLOG

<https://blog.fortinet.com>

CUSTOMER SERVICE & SUPPORT

<https://support.fortinet.com>

FORTINET TRAINING & CERTIFICATION PROGRAM

<https://www.fortinet.com/training-certification>

FORTINET TRAINING INSTITUTE

<https://training.fortinet.com>

FORTIGUARD LABS

<https://www.fortiguard.com>

END USER LICENSE AGREEMENT

<https://www.fortinet.com/doc/legal/EULA.pdf>

FEEDBACK

Email: techdoc@fortinet.com



August 25, 2025

FortiProxy 7.4.11 CLI Reference

45-7411-1024864-20250825

TABLE OF CONTENTS

Change log	64
FortiProxy CLI Interface	65
CLI configuration commands	66
alertemail	67
config alertemail setting	67
antivirus	74
config antivirus exempt-list	74
config antivirus profile	75
config antivirus quarantine	106
config antivirus settings	111
application	113
config application custom	113
config application group	114
config application list	115
config application name	124
config application rule-settings	126
authentication	127
config authentication rule	127
config authentication scheme	130
config authentication setting	132
automation	136
config automation setting	136
casb	137
config casb profile	137
config casb saas-application	140
config casb user-activity	141
certificate	148
config certificate ca	148
config certificate crt	150
config certificate local	151
config certificate remote	156
dlp	158
config dlp data-type	158
config dlp dictionary	160
config dlp exact-data-match	162
config dlp filepattern	163
config dlp fp-doc-source	166
config dlp profile	169
config dlp sensitivity	174
config dlp sensor	175
config dlp settings	176
dnsfilter	178
config dnsfilter domain-filter	178
config dnsfilter profile	179
emailfilter	186

config emailfilter block-allow-list	186
config emailfilter bword	188
config emailfilter dnsbl	190
config emailfilter fortishield	192
config emailfilter iptrust	192
config emailfilter mheader	194
config emailfilter options	195
config emailfilter profile	196
endpoint-control	204
config endpoint-control fctems	204
file-filter	209
config file-filter profile	209
firewall	212
config firewall access-proxy	213
config firewall access-proxy6	250
config firewall access-proxy-ssh-client-cert	250
config firewall access-proxy-virtual-host	253
config firewall address	254
config firewall address6	259
config firewall address6-template	263
config firewall addrgrp	265
config firewall addrgrp6	267
config firewall auth-portal	268
config firewall central-snat-map	269
config firewall city	271
config firewall country	271
config firewall decrypted-traffic-mirror	272
config firewall global	273
config firewall identity-based-route	274
config firewall internet-service	275
config firewall internet-service-addition	277
config firewall internet-service-append	278
config firewall internet-service-botnet	279
config firewall internet-service-custom	280
config firewall internet-service-custom-group	282
config firewall internet-service-definition	282
config firewall internet-service-extension	284
config firewall internet-service-group	288
config firewall internet-service-ipbl-reason	289
config firewall internet-service-ipbl-vendor	289
config firewall internet-service-list	290
config firewall internet-service-name	290
config firewall internet-service-owner	291
config firewall internet-service-reputation	292
config firewall internet-service-sld	293
config firewall internet-service-subapp	293
config firewall ippool	294
config firewall ippool6	294
config firewall network-service-dynamic	295

config firewall policy	296
config firewall profile-group	310
config firewall profile-protocol-options	311
config firewall proxy-address	336
config firewall proxy-address6	341
config firewall proxy-addrgrp	346
config firewall proxy-addrgrp6	347
config firewall region	348
config firewall response-shaping-policy	349
config firewall schedule group	352
config firewall schedule onetime	352
config firewall schedule recurring	353
config firewall service category	355
config firewall service custom	355
config firewall service group	359
config firewall shaper per-ip-shaper	360
config firewall shaper traffic-shaper	362
config firewall shaping-policy	364
config firewall shaping-profile	368
config firewall sniffer	370
config firewall ssh host-key	371
config firewall ssh local-ca	373
config firewall ssh local-key	374
config firewall ssh setting	374
config firewall ssl default-certificate	376
config firewall ssl keyring-list	376
config firewall ssl setting	377
config firewall ssl-server	378
config firewall ssl-ssh-profile	381
config firewall traffic-class	413
config firewall ttl-policy	414
config firewall vendor-mac	415
config firewall vendor-mac-summary	416
config firewall vip	416
config firewall vipgrp	451
config firewall wildcard-fqdn custom	451
config firewall wildcard-fqdn group	452
ftp-proxy	454
config ftp-proxy explicit	454
hardware	457
config hardware cpu	457
config hardware memory	457
config hardware nic	457
config hardware status	458
icap	459
config icap local-server	459
config icap profile	462
config icap remote-server	471
config icap remote-server-group	472

image-analyzer	474
config image-analyzer profile	474
ips	479
config ips custom	479
config ips decoder	481
config ips global	481
config ips rule	485
config ips rule-settings	487
config ips sensor	487
config ips session	493
config ips settings	493
config ips view-map	494
ipsec	496
config ipsec tunnel	496
isolator	497
config isolator profile	497
config isolator setting	498
log	500
config log custom-field	501
config log disk filter	502
config log disk setting	505
config log eventfilter	511
config log fortianalyzer filter	515
config log fortianalyzer override-filter	518
config log fortianalyzer override-setting	522
config log fortianalyzer setting	526
config log fortianalyzer2 filter	531
config log fortianalyzer2 override-filter	534
config log fortianalyzer2 override-setting	538
config log fortianalyzer2 setting	543
config log fortianalyzer3 filter	547
config log fortianalyzer3 override-filter	551
config log fortianalyzer3 override-setting	554
config log fortianalyzer3 setting	559
config log fortianalyzer-cloud filter	563
config log fortianalyzer-cloud override-filter	567
config log fortianalyzer-cloud override-setting	570
config log fortianalyzer-cloud setting	571
config log fortiguard filter	574
config log fortiguard override-filter	578
config log fortiguard override-setting	581
config log fortiguard setting	583
config log gui-display	585
config log memory filter	586
config log memory global-setting	590
config log memory setting	590
config log null-device filter	591
config log null-device setting	594
config log setting	595

config log syslogd filter	599
config log syslogd override-filter	603
config log syslogd override-setting	606
config log syslogd setting	611
config log syslogd2 filter	616
config log syslogd2 override-filter	620
config log syslogd2 override-setting	623
config log syslogd2 setting	628
config log syslogd3 filter	633
config log syslogd3 override-filter	637
config log syslogd3 override-setting	640
config log syslogd3 setting	645
config log syslogd4 filter	650
config log syslogd4 override-filter	654
config log syslogd4 override-setting	657
config log syslogd4 setting	662
config log tacacs+accounting filter	667
config log tacacs+accounting setting	668
config log tacacs+accounting2 filter	669
config log tacacs+accounting2 setting	670
config log tacacs+accounting3 filter	671
config log tacacs+accounting3 setting	672
config log threat-weight	673
config log webtrends filter	685
config log webtrends setting	688
mgmt-data	690
config mgmt-data status	690
report	691
config report layout	691
config report setting	699
config report sql status	700
router	701
config router policy	701
config router static	703
config router static6	705
rule	708
config rule fmwp	708
ssh-filter	711
config ssh-filter profile	711
system	714
config system accprofile	717
config system acme	727
config system admin	728
config system affinity-interrupt	736
config system affinity-packet-redistribution	737
config system alarm	738
config system alias	741
config system api-user	741

config system arp	743
config system arp-table	743
config system automation-action	744
config system automation-destination	750
config system automation-stitch	751
config system automation-trigger	752
config system autoupdate schedule	757
config system autoupdate tunneling	758
config system auto-install	759
config system auto-script	760
config system auto-update status	761
config system auto-update versions	761
config system central-management	761
config system central-mgmt	766
config system checksum status	767
config system cmdb	767
config system console	767
config system csf	768
config system custom-language	774
config system ddns	775
config system device-upgrade	778
config system dhcp server	781
config system dhcp6 server	796
config system dns	799
config system dns-database	802
config system dns-server	806
config system dscp-based-priority	807
config system email-server	808
config system external-resource	810
config system fabric-vpn	813
config system federated-upgrade	817
config system fips-cc	820
config system fortianalyzer-connectivity	821
config system fortiguard	821
config system fortiguard-log-service	832
config system fortiguard-service	832
config system fortindr	833
config system fortisandbox	833
config system fsso-polling	835
config system ftm-push	836
config system geoip-country	837
config system geoip-override	838
config system global	839
config system gre-tunnel	895
config system ha	897
config system ha-lic	908
config system ha-monitor	909
config system ha-nonsync-csum	909
config system info admin ssh	910

config system info admin status	910
config system interface	910
config system ipam	944
config system ips	946
config system ips-urlfilter-dns	947
config system ips-urlfilter-dns6	948
config system ipv6-neighbor-cache	948
config system ip-conflict status	949
config system link-monitor	949
config system management-tunnel	954
config system mgmt-csum	956
config system nethsm	956
config system network-visibility	960
config system ntp	961
config system object-tagging	965
config system password-policy	966
config system password-policy-guest-admin	968
config system performance status	971
config system performance top	971
config system probe-response	971
config system proxy-arp	973
config system ptp	973
config system replacemsg admin	975
config system replacemsg alertmail	976
config system replacemsg auth	977
config system replacemsg automation	978
config system replacemsg custom-message	979
config system replacemsg fortiguard-wf	980
config system replacemsg ftp	981
config system replacemsg http	982
config system replacemsg icap	983
config system replacemsg mail	984
config system replacemsg nac-quar	985
config system replacemsg spam	986
config system replacemsg sslvpn	987
config system replacemsg traffic-quota	988
config system replacemsg utm	989
config system replacemsg webproxy	990
config system replacemsg-group	991
config system replacemsg-image	1004
config system resource-limits	1005
config system saml	1007
config system sdn-connector	1011
config system session	1019
config system session6	1019
config system session-ttl	1020
config system settings	1021
config system sms-server	1035
config system snmp community	1036

config system snmp mib-view	1042
config system snmp sysinfo	1043
config system snmp user	1045
config system source-ip status	1050
config system span-port	1050
config system speed-test-schedule	1051
config system speed-test-server	1053
config system speed-test-setting	1055
config system sso-admin	1055
config system sso-forticloud-admin	1056
config system sso-fortigate-cloud-admin	1057
config system startup-error-log	1057
config system status	1057
config system storage	1058
config system vdom	1059
config system vdom-dns	1060
config system vdom-exception	1062
config system vdom-link	1065
config system vdom-property	1065
config system vdom-radius-server	1067
config system vne-tunnel	1067
config system vxlan	1069
config system wccp	1070
config system zone	1074
test	1075
config test acd	1076
config test acsd	1077
config test autod	1077
config test awsd	1078
config test azd	1078
config test bfd	1078
config test csfd	1079
config test ddnsd	1079
config test dhcp6c	1079
config test dhcp6r	1080
config test dhcprelay	1080
config test dlpfingerprint	1081
config test dlpfpcache	1081
config test dnsproxy	1081
config test dsd	1082
config test eap_supp	1082
config test fas	1082
config test fcnacd	1083
config test fds_notify	1083
config test fgtlogd	1084
config test fnbamd	1084
config test forticldd	1084
config test forticron	1085
config test fsd	1085

config test fsvr	1085
config test gcpd	1086
config test harelay	1086
config test hasync	1087
config test hatalk	1087
config test ibmd	1087
config test imap	1088
config test init	1088
config test iotd	1088
config test ipamd	1089
config test ipamsd	1089
config test ipldb	1090
config test ipsengine	1090
config test ipsmonitor	1090
config test ipsufd	1091
config test kubed	1091
config test l2tpcd	1091
config test lnkmt	1092
config test locallogd	1092
config test miglogd	1093
config test mrd	1093
config test netxd	1093
config test nntp	1094
config test ocid	1094
config test openstackd	1094
config test ovrd	1095
config test pop3	1095
config test pptpcd	1096
config test quarantined	1096
config test radiusd	1096
config test radius-das	1097
config test radvd	1097
config test reportd	1097
config test rt_router	1098
config test sdn	1098
config test sdn	1099
config test sepmd	1099
config test sessionsync	1099
config test sfupgraded	1100
config test smtp	1100
config test snmpd	1100
config test syslogd	1101
config test updated	1101
config test uploadd	1102
config test urlfilter	1102
config test vned	1102
config test wad	1103
config test wccpd	1103
config test wf_monitor	1103

config test wiredapd	1104
user	1105
config user adgrp	1105
config user certificate	1106
config user domain-controller	1107
config user exchange	1111
config user external-identity-provider	1113
config user fortitoken	1115
config user fsso	1116
config user fsso-polling	1120
config user group	1122
config user krb-keytab	1128
config user ldap	1129
config user local	1138
config user password-policy	1141
config user peer	1142
config user peergrp	1144
config user pop3	1145
config user radius	1146
config user saml	1159
config user security-exempt-list	1163
config user setting	1164
config user tacacs+	1169
videofilter	1171
config videofilter profile	1171
config videofilter youtube-channel-filter	1173
config videofilter youtube-key	1175
vpn	1176
config vpn certificate ca	1176
config vpn certificate crt	1178
config vpn certificate local	1179
config vpn certificate ocsf-server	1184
config vpn certificate remote	1185
config vpn certificate setting	1186
config vpn ipsec phase1-interface	1192
config vpn ipsec phase2-interface	1208
waf	1217
config waf main-class	1217
config waf profile	1217
config waf signature	1242
config waf sub-class	1243
wanopt	1244
config wanopt auth-group	1244
config wanopt cache-service	1245
config wanopt content-delivery-network-rule	1247
config wanopt peer	1253
config wanopt profile	1253
config wanopt remote-storage	1262
config wanopt settings	1263

web-proxy	1264
config web-proxy debug-url	1264
config web-proxy dynamic-bypass	1265
config web-proxy explicit-proxy	1266
config web-proxy forward-server	1272
config web-proxy forward-server-group	1275
config web-proxy global	1276
config web-proxy implicit-proxy-rule	1281
config web-proxy implicit-proxy-setting	1283
config web-proxy isolator-server	1283
config web-proxy pac-policy	1285
config web-proxy profile	1286
config web-proxy redirect-profile	1291
config web-proxy url-list	1292
config web-proxy url-match	1293
config web-proxy wisp	1295
webcache	1297
config webcache prefetch	1297
config webcache reverse-cache-server	1298
config webcache settings	1299
config webcache user-agent	1303
webfilter	1304
config webfilter categories	1304
config webfilter content	1304
config webfilter content-header	1306
config webfilter domain-list	1307
config webfilter fortiguard	1308
config webfilter ftgd-local-cat	1311
config webfilter ftgd-local-rating	1311
config webfilter ftgd-local-risk	1312
config webfilter ftgd-risk-level	1313
config webfilter ftgd-statistics	1314
config webfilter ips-urlfilter-cache-setting	1314
config webfilter ips-urlfilter-setting	1314
config webfilter ips-urlfilter-setting6	1315
config webfilter override	1316
config webfilter override-usr	1317
config webfilter profile	1318
config webfilter search-engine	1336
config webfilter status	1337
config webfilter urlfilter	1337
config webfilter url-list	1341
CLI diagnose commands	1343
diagnose alertconsole	1344
diagnose alertconsole clear	1345
diagnose alertconsole fgd-retrieve	1345
diagnose alertconsole list	1345
diagnose alertconsole test	1345

diagnose antivirus	1345
diagnose antivirus database-info	1346
diagnose antivirus outbreak-prevention	1346
diagnose antivirus outbreak-prevention statistics	1346
diagnose antivirus outbreak-prevention statistics flush	1346
diagnose antivirus outbreak-prevention statistics list	1346
diagnose antivirus quarantine	1346
diagnose antivirus quarantine delete	1347
diagnose antivirus quarantine list	1347
diagnose antivirus quarantine purge	1347
diagnose antivirus test	1347
diagnose automation	1348
diagnose automation test	1348
diagnose autoupdate	1348
diagnose autoupdate downgrade	1348
diagnose autoupdate downgrade disable	1348
diagnose autoupdate downgrade enable	1349
diagnose autoupdate status	1349
diagnose autoupdate versions	1349
diagnose casb	1349
diagnose casb show	1349
diagnose casb show apps	1349
diagnose debug	1350
diagnose debug admin	1356
diagnose debug admin error-log	1356
diagnose debug application	1356
diagnose debug application acd	1357
diagnose debug application acid	1357
diagnose debug application alarmd	1357
diagnose debug application alertmail	1357
diagnose debug application alicloud-ha	1357
diagnose debug application alicloud-sdn	1358
diagnose debug application authd	1358
diagnose debug application autod	1358
diagnose debug application awsd	1358
diagnose debug application azd	1359
diagnose debug application azd-ha	1359
diagnose debug application bfdd	1359
diagnose debug application cert-update	1359
diagnose debug application chassis	1360
diagnose debug application cid	1360
diagnose debug application clearpass	1360
diagnose debug application cloudinitd	1360
diagnose debug application cmp	1360
diagnose debug application cri-update	1361
diagnose debug application crwl	1361
diagnose debug application csfd	1361
diagnose debug application ddnsd	1362
diagnose debug application dhcp6c	1362

diagnose debug application dhcp6r	1362
diagnose debug application dhcp6s	1362
diagnose debug application dhcpc	1363
diagnose debug application dhcprelay	1363
diagnose debug application dhcps	1363
diagnose debug application dlpfingerprint	1363
diagnose debug application dnp	1364
diagnose debug application dnsproxy	1364
diagnose debug application eap_proxy	1364
diagnose debug application eap_supp	1364
diagnose debug application extenderd	1365
diagnose debug application fcid	1365
diagnose debug application fcnacd	1365
diagnose debug application fds_notify	1365
diagnose debug application fgd_alert	1365
diagnose debug application fgfmd	1366
diagnose debug application fgtlogd	1366
diagnose debug application fnbamd	1366
diagnose debug application foauthd	1366
diagnose debug application forticldd	1367
diagnose debug application forticron	1367
diagnose debug application fsd	1367
diagnose debug application fsso_ldap	1367
diagnose debug application fssod	1368
diagnose debug application fsvrd	1368
diagnose debug application ftm-push	1368
diagnose debug application garpd	1368
diagnose debug application gcpd	1368
diagnose debug application hamonitord	1369
diagnose debug application harelay	1369
diagnose debug application hasync	1369
diagnose debug application hatalk	1369
diagnose debug application httpsd	1370
diagnose debug application ibmd	1370
diagnose debug application imap	1370
diagnose debug application init	1370
diagnose debug application iotd	1371
diagnose debug application ipamd	1371
diagnose debug application ipamsd	1371
diagnose debug application ipldbd	1371
diagnose debug application ipsengine	1372
diagnose debug application ipsmonitor	1372
diagnose debug application ipsufd	1372
diagnose debug application iptables	1372
diagnose debug application kmiglogd	1372
diagnose debug application kubed	1373
diagnose debug application l2tp	1373
diagnose debug application link-monitor	1373
diagnose debug application link-monitor-passive	1373

diagnose debug application lldptx	1374
diagnose debug application locallogd	1374
diagnose debug application lpm d	1374
diagnose debug application miglogd	1374
diagnose debug application mrd	1375
diagnose debug application nethsm	1375
diagnose debug application netxd	1375
diagnose debug application nntp	1375
diagnose debug application nodejs	1375
diagnose debug application npd	1376
diagnose debug application ntnxd	1376
diagnose debug application ntpd	1376
diagnose debug application ocid	1376
diagnose debug application ocvpn	1377
diagnose debug application openstackd	1377
diagnose debug application ovrd	1377
diagnose debug application pop3	1377
diagnose debug application ppp	1378
diagnose debug application pppoed	1378
diagnose debug application pptp	1378
diagnose debug application pptpc	1378
diagnose debug application proxy	1378
diagnose debug application ptpd	1379
diagnose debug application quarantine	1379
diagnose debug application radius-das	1379
diagnose debug application radiusd	1379
diagnose debug application radvd	1380
diagnose debug application reportd	1380
diagnose debug application rt-router	1380
diagnose debug application samld	1380
diagnose debug application sapd	1381
diagnose debug application sccp	1381
diagnose debug application scep	1381
diagnose debug application sdncd	1381
diagnose debug application sdwan	1382
diagnose debug application sepmd	1382
diagnose debug application server-probe	1382
diagnose debug application sessionsync	1382
diagnose debug application sflowd	1383
diagnose debug application sfupgraded	1383
diagnose debug application sip	1383
diagnose debug application smbcd	1383
diagnose debug application smtp	1383
diagnose debug application snmpd	1384
diagnose debug application spareblock	1384
diagnose debug application speedtest	1384
diagnose debug application speedtestd	1384
diagnose debug application sshd	1385
diagnose debug application syslogd	1385

diagnose debug application tvc	1385
diagnose debug application update	1385
diagnose debug application uploadd	1386
diagnose debug application urlfilter	1386
diagnose debug application vmtoolsd	1386
diagnose debug application vmwd	1386
diagnose debug application vned	1386
diagnose debug application vpd	1387
diagnose debug application vrrpd	1387
diagnose debug application wabcs	1387
diagnose debug application waocs	1387
diagnose debug application wccpd	1388
diagnose debug application wf_monitor	1388
diagnose debug authd	1388
diagnose debug authd clear	1388
diagnose debug authd fsso	1388
diagnose debug authd fsso clear-logons	1389
diagnose debug authd fsso filter	1389
diagnose debug authd fsso filter clear	1389
diagnose debug authd fsso filter group	1389
diagnose debug authd fsso filter server	1389
diagnose debug authd fsso filter source	1390
diagnose debug authd fsso filter user	1390
diagnose debug authd fsso list	1390
diagnose debug authd fsso refresh-groups	1390
diagnose debug authd fsso refresh-logons	1390
diagnose debug authd fsso server-status	1391
diagnose debug authd fsso show-address	1391
diagnose debug authd fsso summary	1391
diagnose debug authd memory	1391
diagnose debug cli	1391
diagnose debug cloudinit	1391
diagnose debug cloudinit clear	1392
diagnose debug cloudinit show	1392
diagnose debug cmdb-trace	1392
diagnose debug cmdb-walk	1392
diagnose debug config-error-log	1392
diagnose debug config-error-log clear	1393
diagnose debug config-error-log read	1393
diagnose debug console	1393
diagnose debug console no-user-log-msg	1393
diagnose debug console no-user-log-msg disable	1393
diagnose debug console no-user-log-msg enable	1393
diagnose debug console retry-log-msg	1394
diagnose debug console retry-log-msg disable	1394
diagnose debug console retry-log-msg enable	1394
diagnose debug console send	1394
diagnose debug console timestamp	1394
diagnose debug console timestamp disable	1395

diagnose debug console timestamp enable	1395
diagnose debug crashlog	1395
diagnose debug crashlog clear	1395
diagnose debug crashlog get	1395
diagnose debug crashlog history	1395
diagnose debug crashlog interval	1396
diagnose debug disable	1396
diagnose debug duration	1396
diagnose debug enable	1396
diagnose debug flow	1396
diagnose debug flow filter	1397
diagnose debug flow filter addr	1397
diagnose debug flow filter clear	1397
diagnose debug flow filter daddr	1397
diagnose debug flow filter dport	1397
diagnose debug flow filter negate	1398
diagnose debug flow filter negate addr	1398
diagnose debug flow filter negate daddr	1398
diagnose debug flow filter negate dport	1398
diagnose debug flow filter negate port	1398
diagnose debug flow filter negate proto	1398
diagnose debug flow filter negate saddr	1399
diagnose debug flow filter negate sport	1399
diagnose debug flow filter negate vd	1399
diagnose debug flow filter port	1399
diagnose debug flow filter proto	1399
diagnose debug flow filter saddr	1400
diagnose debug flow filter sport	1400
diagnose debug flow filter vd	1400
diagnose debug flow filter vd-name	1400
diagnose debug flow filter6	1401
diagnose debug flow filter6 addr	1401
diagnose debug flow filter6 clear	1401
diagnose debug flow filter6 daddr	1401
diagnose debug flow filter6 dport	1401
diagnose debug flow filter6 negate	1402
diagnose debug flow filter6 negate addr	1402
diagnose debug flow filter6 negate daddr	1402
diagnose debug flow filter6 negate dport	1402
diagnose debug flow filter6 negate port	1402
diagnose debug flow filter6 negate proto	1402
diagnose debug flow filter6 negate saddr	1403
diagnose debug flow filter6 negate sport	1403
diagnose debug flow filter6 negate vd	1403
diagnose debug flow filter6 port	1403
diagnose debug flow filter6 proto	1403
diagnose debug flow filter6 saddr	1404
diagnose debug flow filter6 sport	1404
diagnose debug flow filter6 vd	1404

diagnose debug flow filter6 vd-name	1404
diagnose debug flow show	1405
diagnose debug flow show function-name	1405
diagnose debug flow show function-name disable	1405
diagnose debug flow show function-name enable	1405
diagnose debug flow trace	1405
diagnose debug flow trace start	1405
diagnose debug flow trace start6	1406
diagnose debug flow trace stop	1406
diagnose debug flow trace stop6	1406
diagnose debug fsso-polling	1406
diagnose debug fsso-polling client	1406
diagnose debug fsso-polling detail	1406
diagnose debug fsso-polling group	1407
diagnose debug fsso-polling refresh-user	1407
diagnose debug fsso-polling set-log-source	1407
diagnose debug fsso-polling summary	1407
diagnose debug fsso-polling user	1408
diagnose debug info	1408
diagnose debug intf-band-error	1408
diagnose debug kernel	1408
diagnose debug kernel ha	1408
diagnose debug kernel level	1409
diagnose debug kernel log	1409
diagnose debug kernel log clear	1409
diagnose debug kernel log show	1409
diagnose debug kernel sysrq	1409
diagnose debug kernel sysrq command	1409
diagnose debug kernel sysrq command crash	1410
diagnose debug kernel sysrq disable	1410
diagnose debug kernel sysrq enable	1410
diagnose debug kernel sysrq status	1410
diagnose debug rating	1410
diagnose debug remote-extender	1410
diagnose debug remote-extender extenderd	1411
diagnose debug remote-extender modem-manager	1411
diagnose debug report	1411
diagnose debug report reset	1411
diagnose debug reset	1411
diagnose debug sdnc	1412
diagnose debug sql-log-error	1412
diagnose debug sql-log-error clear	1412
diagnose debug sql-log-error read	1412
diagnose debug sql-log-error status	1412
diagnose debug traffic	1412
diagnose debug traffic history	1413
diagnose debug traffic interface	1413
diagnose debug traffic peek	1413
diagnose debug urlfilter	1413

diagnose debug urlfilter src-addr	1413
diagnose debug urlfilter test-url	1414
diagnose debug vm-print-license	1414
diagnose disktest	1414
diagnose disktest block	1414
diagnose disktest block 1	1415
diagnose disktest block 16	1415
diagnose disktest block 256	1415
diagnose disktest block 4	1415
diagnose disktest block 64	1415
diagnose disktest device	1415
diagnose disktest run	1416
diagnose disktest size	1416
diagnose disktest time	1416
diagnose emailfilter	1416
diagnose emailfilter bword	1417
diagnose emailfilter bword matchfilter	1417
diagnose emailfilter fortishield	1417
diagnose emailfilter fortishield servers	1417
diagnose emailfilter fortishield statistics	1417
diagnose emailfilter fortishield statistics flush	1418
diagnose emailfilter fortishield statistics list	1418
diagnose endpoint	1418
diagnose endpoint avatar	1420
diagnose endpoint avatar allow-nodisk	1420
diagnose endpoint avatar delete-archived	1420
diagnose endpoint avatar find	1420
diagnose endpoint avatar find fingerprint	1421
diagnose endpoint avatar find link	1421
diagnose endpoint avatar list	1421
diagnose endpoint avatar list active	1421
diagnose endpoint avatar list archived	1421
diagnose endpoint avatar list fingerprint	1422
diagnose endpoint avatar purge-all	1422
diagnose endpoint avatar purge-archived	1422
diagnose endpoint debug-zone	1422
diagnose endpoint debug-zone dump	1422
diagnose endpoint debug-zone set-lls-quota	1423
diagnose endpoint ec-shared	1423
diagnose endpoint ec-shared find	1423
diagnose endpoint ec-shared list	1423
diagnose endpoint fctems	1423
diagnose endpoint fctems api-status	1424
diagnose endpoint fctems api-status clear	1424
diagnose endpoint fctems get-pub-addr	1424
diagnose endpoint fctems json	1424
diagnose endpoint fctems json deep-inspect-cert-sync	1424
diagnose endpoint fctems json gateway-mac-request	1425
diagnose endpoint fctems queue-complete-calls	1425

diagnose endpoint fctems test-authorization	1425
diagnose endpoint fctems test-connectivity	1425
diagnose endpoint filter	1425
diagnose endpoint filter avatar-fingerprint	1426
diagnose endpoint filter clear	1426
diagnose endpoint filter ems-sn	1426
diagnose endpoint filter ftcl-uid	1426
diagnose endpoint filter list	1426
diagnose endpoint filter show-large-data	1427
diagnose endpoint lls-comm	1427
diagnose endpoint lls-comm connect	1427
diagnose endpoint lls-comm disconnect	1427
diagnose endpoint lls-comm recv	1427
diagnose endpoint lls-comm send	1428
diagnose endpoint lls-comm send echo	1428
diagnose endpoint lls-comm send echo echo	1428
diagnose endpoint lls-comm send general	1428
diagnose endpoint lls-comm send general get-index	1428
diagnose endpoint lls-comm send general register	1428
diagnose endpoint lls-comm send general unregister	1429
diagnose endpoint lls-comm send ping	1429
diagnose endpoint lls-comm send ping set-interval	1429
diagnose endpoint lls-comm send ztna	1429
diagnose endpoint lls-comm send ztna find-ip-vdom	1429
diagnose endpoint lls-comm send ztna find-uid	1430
diagnose endpoint lls-comm send ztna message-format	1430
diagnose endpoint lls-comm send ztna subscribe-all	1430
diagnose endpoint lls-comm send ztna unsubscribe-all	1431
diagnose endpoint lls-comm send ztna unsubscribe-uid	1431
diagnose endpoint lls-comm status	1431
diagnose endpoint record	1431
diagnose endpoint record delete	1431
diagnose endpoint record list	1432
diagnose endpoint record summary	1432
diagnose endpoint record update-by-json	1432
diagnose endpoint tags	1432
diagnose endpoint tags remove-by-id	1433
diagnose endpoint tags remove-by-name	1433
diagnose endpoint tags remove-by-name-legacy	1433
diagnose endpoint tags remove-by-sn	1433
diagnose endpoint tags test-common-tag-update	1434
diagnose endpoint tags test-update	1434
diagnose fdsm	1434
diagnose fdsm account-info	1435
diagnose fdsm central-mgmt-status	1435
diagnose fdsm cfg-diff	1435
diagnose fdsm cfg-download	1436
diagnose fdsm cfg-list	1436
diagnose fdsm cfg-upload	1436

diagnose fdsm contract-controller-update	1436
diagnose fdsm fap-fsw-contract-download	1436
diagnose fdsm fc-installer-download	1437
diagnose fdsm fds-update	1437
diagnose fdsm fmg-auto-discovery-status	1437
diagnose fdsm forticlient-net-info	1437
diagnose fdsm forticlient-update	1437
diagnose fdsm fortiex-download	1438
diagnose fdsm fortiex-latest-ver	1438
diagnose fdsm fortisw-download	1438
diagnose fdsm fortisw-latest-ver	1438
diagnose fdsm ftk-activate	1438
diagnose fdsm image-download	1439
diagnose fdsm image-list	1439
diagnose fdsm image-upgrade-matrix	1439
diagnose fdsm log-controller-update	1439
diagnose fdsm message-update	1439
diagnose fdsm modem-list	1439
diagnose fdsm report-download	1440
diagnose fdsm report-list	1440
diagnose firewall	1440
diagnose firewall auth	1442
diagnose firewall auth clear	1442
diagnose firewall auth filter	1443
diagnose firewall auth filter clear	1443
diagnose firewall auth filter group	1443
diagnose firewall auth filter mac	1443
diagnose firewall auth filter method	1443
diagnose firewall auth filter policy	1444
diagnose firewall auth filter source	1444
diagnose firewall auth filter source6	1444
diagnose firewall auth filter user	1445
diagnose firewall auth ipv6	1445
diagnose firewall auth ipv6 clear	1445
diagnose firewall auth ipv6 list	1445
diagnose firewall auth list	1445
diagnose firewall auth mac	1446
diagnose firewall auth mac clear	1446
diagnose firewall auth mac list	1446
diagnose firewall dynamic	1446
diagnose firewall dynamic address	1446
diagnose firewall dynamic list	1446
diagnose firewall dynamic6	1447
diagnose firewall dynamic6 address	1447
diagnose firewall dynamic6 list	1447
diagnose firewall fqdn	1447
diagnose firewall fqdn get-ip	1447
diagnose firewall fqdn get-mac	1448
diagnose firewall fqdn getinfo-ip	1448

diagnose firewall fqdn getinfo-mac	1448
diagnose firewall fqdn list-all	1448
diagnose firewall fqdn list-ip	1449
diagnose firewall fqdn list-mac	1449
diagnose firewall fqdn6	1449
diagnose firewall fqdn6 get	1449
diagnose firewall fqdn6 list	1449
diagnose firewall internet-service	1449
diagnose firewall internet-service list	1450
diagnose firewall internet-service-app-ctrl	1450
diagnose firewall internet-service-cache	1450
diagnose firewall internet-service-cache list	1450
diagnose firewall internet-service-custom	1450
diagnose firewall internet-service-custom list	1450
diagnose firewall internet-service-disable	1451
diagnose firewall internet-service-disable list	1451
diagnose firewall internet-service-extension	1451
diagnose firewall internet-service-extension list	1451
diagnose firewall internet-service-prio-id	1451
diagnose firewall internet-service-prio-id list	1452
diagnose firewall internet-service6	1452
diagnose firewall internet-service6 list	1452
diagnose firewall internet-service6-cache	1452
diagnose firewall internet-service6-cache list	1452
diagnose firewall internet-service6-custom	1452
diagnose firewall internet-service6-custom list	1453
diagnose firewall internet-service6-disable	1453
diagnose firewall internet-service6-disable list	1453
diagnose firewall internet-service6-extension	1453
diagnose firewall internet-service6-extension list	1453
diagnose firewall internet-service6-prio-id	1454
diagnose firewall internet-service6-prio-id list	1454
diagnose firewall ipgeo	1454
diagnose firewall ipgeo copyright-notice	1454
diagnose firewall ipgeo country-list	1454
diagnose firewall ipgeo ip-list	1454
diagnose firewall ipgeo ip2country	1455
diagnose firewall ipgeo override	1455
diagnose firewall network-service-dynamic	1455
diagnose firewall network-service-dynamic list	1455
diagnose firewall nslookup	1455
diagnose firewall shaper	1456
diagnose firewall shaper per-ip-shaper	1456
diagnose firewall shaper per-ip-shaper clear	1456
diagnose firewall shaper per-ip-shaper list	1456
diagnose firewall shaper per-ip-shaper state	1456
diagnose firewall shaper per-ip-shaper stats	1456
diagnose firewall shaper traffic-shaper	1457
diagnose firewall shaper traffic-shaper list	1457

diagnose firewall shaper traffic-shaper stats	1457
diagnose firewall shaper traffic-shaper stats clear	1457
diagnose firewall shaper traffic-shaper stats list	1457
diagnose firewall snat-ippool	1457
diagnose firewall snat-ippool list	1458
diagnose firewall snat-ippool list6	1458
diagnose forticlient	1458
diagnose forticlient add-connection	1458
diagnose forticlient close-all-connection	1459
diagnose forticlient close-connection	1459
diagnose fortiguard-resources	1459
diagnose fortiguard-resources delete	1460
diagnose fortiguard-resources delete app-categories	1460
diagnose fortiguard-resources delete app-info	1460
diagnose fortiguard-resources delete fortiap-end-of-support	1461
diagnose fortiguard-resources delete fortixtender-end-of-support	1461
diagnose fortiguard-resources delete fortigate-end-of-support	1461
diagnose fortiguard-resources delete fortiswitch-end-of-support	1461
diagnose fortiguard-resources delete ips-information	1461
diagnose fortiguard-resources delete prefix-links	1462
diagnose fortiguard-resources delete sprite-isdb	1462
diagnose fortiguard-resources delete sprite-map	1462
diagnose fortiguard-resources delete static-links	1462
diagnose fortiguard-resources delete wf-categories	1462
diagnose fortiguard-resources downloads	1462
diagnose fortiguard-resources downloads disable	1463
diagnose fortiguard-resources downloads enable	1463
diagnose fortiguard-resources info	1463
diagnose fortiguard-resources info app-categories	1463
diagnose fortiguard-resources info app-info	1463
diagnose fortiguard-resources info fortiap-end-of-support	1464
diagnose fortiguard-resources info fortixtender-end-of-support	1464
diagnose fortiguard-resources info fortigate-end-of-support	1464
diagnose fortiguard-resources info fortiswitch-end-of-support	1464
diagnose fortiguard-resources info ips-information	1464
diagnose fortiguard-resources info prefix-links	1465
diagnose fortiguard-resources info sprite-isdb.css	1465
diagnose fortiguard-resources info sprite-isdb.png	1465
diagnose fortiguard-resources info sprite-map.css	1465
diagnose fortiguard-resources info sprite-map.png	1465
diagnose fortiguard-resources info static-links	1465
diagnose fortiguard-resources info wf-categories	1466
diagnose fortiguard-resources update	1466
diagnose fortiguard-resources update app-categories	1466
diagnose fortiguard-resources update app-info	1466
diagnose fortiguard-resources update fortiap-end-of-support	1466
diagnose fortiguard-resources update fortixtender-end-of-support	1466
diagnose fortiguard-resources update fortigate-end-of-support	1467
diagnose fortiguard-resources update fortiswitch-end-of-support	1467

diagnose fortiguard-resources update ips-information	1467
diagnose fortiguard-resources update prefix-links	1467
diagnose fortiguard-resources update sprite-isdb	1467
diagnose fortiguard-resources update sprite-map	1468
diagnose fortiguard-resources update static-links	1468
diagnose fortiguard-resources update wf-categories	1468
diagnose fortitoken	1468
diagnose fortitoken debug	1468
diagnose fortitoken debug disable	1468
diagnose fortitoken debug enable	1469
diagnose fortitoken info	1469
diagnose fortitoken test	1469
diagnose fortitoken-cloud	1469
diagnose fortitoken-cloud clear	1470
diagnose fortitoken-cloud debug	1470
diagnose fortitoken-cloud debug disable	1470
diagnose fortitoken-cloud debug enable	1470
diagnose fortitoken-cloud debug info	1470
diagnose fortitoken-cloud delete	1471
diagnose fortitoken-cloud migrate-ftm	1471
diagnose fortitoken-cloud server	1471
diagnose fortitoken-cloud set-http	1471
diagnose fortitoken-cloud show	1472
diagnose fortitoken-cloud sync	1472
diagnose fortiview	1472
diagnose geoip	1472
diagnose geoip delete-geoip-db	1473
diagnose geoip geoip-query	1473
diagnose geoip ip2country	1473
diagnose geoip iprange	1473
diagnose geoip iprange6	1473
diagnose hardware	1474
diagnose hardware certificate	1474
diagnose hardware deviceinfo	1474
diagnose hardware deviceinfo disk	1475
diagnose hardware deviceinfo nic	1475
diagnose hardware deviceinfo nic-channel	1475
diagnose hardware deviceinfo nic-stats	1475
diagnose hardware lspci	1475
diagnose hardware mii	1475
diagnose hardware sysinfo	1476
diagnose hardware sysinfo conserve	1476
diagnose hardware sysinfo cpu	1476
diagnose hardware sysinfo interrupts	1476
diagnose hardware sysinfo iomem	1476
diagnose hardware sysinfo ioports	1476
diagnose hardware sysinfo memory	1477
diagnose hardware sysinfo mtrr	1477
diagnose hardware sysinfo slab	1477

diagnose http-view	1477
diagnose http-view clear	1477
diagnose http-view debug	1477
diagnose http-view log-show	1478
diagnose http-view restart	1478
diagnose http-view stats	1478
diagnose ip	1478
diagnose ip address	1479
diagnose ip address add	1479
diagnose ip address delete	1479
diagnose ip address list	1480
diagnose ip arp	1480
diagnose ip arp add	1480
diagnose ip arp delete	1480
diagnose ip arp list	1481
diagnose ip route	1481
diagnose ip route add	1481
diagnose ip route delete	1481
diagnose ip route list	1482
diagnose ip route match	1482
diagnose ip route verify	1482
diagnose ip tcp	1483
diagnose ip tcp list	1483
diagnose ip udp	1483
diagnose ip udp list	1483
diagnose ip address	1483
diagnose ip address add	1484
diagnose ip address delete	1484
diagnose ip address list	1484
diagnose ip arp	1484
diagnose ip arp add	1485
diagnose ip arp delete	1485
diagnose ip arp list	1485
diagnose ip route	1485
diagnose ip route add	1486
diagnose ip route delete	1486
diagnose ip route list	1487
diagnose ip route match	1487
diagnose ip route verify	1487
diagnose ip tcp	1488
diagnose ip tcp list	1488
diagnose ip udp	1488
diagnose ip udp list	1488
diagnose ipsec	1488
diagnose ipsec connect	1489
diagnose ipsec list-conn	1489
diagnose ipsec list-sa	1489
diagnose ipsec p1-status	1489

diagnose ipsec reload-ca	1489
diagnose ipsec reload-ipsec	1489
diagnose ipset	1490
diagnose ipset list	1490
diagnose iptables	1490
diagnose iptables dry-run	1490
diagnose iptables list	1490
diagnose iptables list6	1491
diagnose iptables refresh	1491
diagnose iptables shaper	1491
diagnose iptables shaper-stats	1491
diagnose ipv6	1491
diagnose ipv6 address	1492
diagnose ipv6 address add	1492
diagnose ipv6 address delete	1492
diagnose ipv6 address list	1492
diagnose ipv6 devconf	1493
diagnose ipv6 devconf accept-dad	1493
diagnose ipv6 devconf disable_ipv6	1493
diagnose ipv6 neighbor-cache	1493
diagnose ipv6 neighbor-cache add	1493
diagnose ipv6 neighbor-cache delete	1494
diagnose ipv6 neighbor-cache flush	1494
diagnose ipv6 neighbor-cache list	1494
diagnose ipv6 route	1494
diagnose ipv6 route list	1495
diagnose ipv6 address	1495
diagnose ipv6 address add	1495
diagnose ipv6 address delete	1495
diagnose ipv6 address list	1496
diagnose ipv6 devconf	1496
diagnose ipv6 devconf accept-dad	1496
diagnose ipv6 devconf disable_ipv6	1496
diagnose ipv6 neighbor-cache	1496
diagnose ipv6 neighbor-cache add	1497
diagnose ipv6 neighbor-cache delete	1497
diagnose ipv6 neighbor-cache flush	1497
diagnose ipv6 neighbor-cache list	1498
diagnose ipv6 route	1498
diagnose ipv6 route list	1498
diagnose lldprx	1498
diagnose lldprx config	1499
diagnose lldprx neighbor	1499
diagnose lldprx neighbor clear	1499
diagnose lldprx neighbor details	1499
diagnose lldprx neighbor summary	1499
diagnose lldprx port	1499
diagnose lldprx port details	1500

diagnose lldprx port neighbor	1500
diagnose lldprx port neighbor clear	1500
diagnose lldprx port neighbor details	1500
diagnose lldprx port neighbor summary	1500
diagnose lldprx port summary	1500
diagnose lldprx restart	1501
diagnose lldprx stats	1501
diagnose lldprx stats config	1501
diagnose lldprx stats crash	1501
diagnose lldprx stats manager	1501
diagnose lldprx stats scan	1501
diagnose log	1502
diagnose log alertmail	1502
diagnose log alertmail authcode	1502
diagnose log alertmail test	1502
diagnose log clear-kernel-stats	1503
diagnose log kernel-stats	1503
diagnose log show	1503
diagnose log test	1503
diagnose log test-text	1503
diagnose netlink	1503
diagnose netlink backlog	1504
diagnose netlink backlog get	1504
diagnose netlink backlog set	1504
diagnose netlink brctl	1505
diagnose netlink brctl forward-domain-status	1505
diagnose netlink brctl interface-stats	1505
diagnose netlink brctl list	1505
diagnose netlink brctl name	1505
diagnose netlink brctl vlan-filt-conf	1506
diagnose netlink device	1506
diagnose netlink device list	1506
diagnose netlink interface	1506
diagnose netlink interface clear	1506
diagnose netlink interface list	1506
diagnose netlink interface packet-rate	1507
diagnose netlink interface speed-test	1507
diagnose netlink interface speed-test-result	1507
diagnose netlink interface speed-test-result-clear	1507
diagnose netlink intf-class	1507
diagnose netlink intf-class list	1508
diagnose netlink intf-qdisc	1508
diagnose netlink intf-qdisc list	1508
diagnose netlink qlen	1508
diagnose netlink qlen get	1508
diagnose netlink qlen set	1509
diagnose nodejs	1509
diagnose nodejs health-check	1509
diagnose nodejs health-check ping	1509

diagnose nodejs logs	1510
diagnose nodejs logs delete	1510
diagnose nodejs logs list	1510
diagnose nodejs logs show	1510
diagnose nodejs logs show-all	1510
diagnose nodejs process	1511
diagnose nodejs process restart	1511
diagnose oci	1511
diagnose oci pubkey	1511
diagnose preload	1511
diagnose preload clear	1512
diagnose preload debug	1512
diagnose preload log-show	1512
diagnose preload restart	1512
diagnose preload stats	1512
diagnose report	1513
diagnose report-runner	1513
diagnose report-runner clean	1513
diagnose report-runner trigger	1513
diagnose report-runner trigger security-rating-reports	1513
diagnose settings	1514
diagnose settings info	1514
diagnose settings reset	1514
diagnose sniffer	1514
diagnose sniffer migsock	1515
diagnose sniffer migsock debug-trace	1515
diagnose sniffer migsock debug-trace disable	1515
diagnose sniffer migsock debug-trace enable	1515
diagnose sniffer migsock filter	1515
diagnose sniffer migsock ssl-trace	1515
diagnose sniffer migsock ssl-trace disable	1516
diagnose sniffer migsock ssl-trace enable	1516
diagnose sniffer migsock start	1516
diagnose sniffer migsock timestamp	1516
diagnose sniffer migsock timestamp disable	1516
diagnose sniffer migsock timestamp enable	1516
diagnose sniffer packet	1517
diagnose snmp	1517
diagnose snmp ip	1518
diagnose snmp ip frags	1518
diagnose snmp ip icmp	1518
diagnose snmp ip ip	1518
diagnose snmp ip tcp	1519
diagnose snmp ip udp	1519
diagnose snmp ip6	1519
diagnose snmp ip6 frags	1519
diagnose snmp ip6 icmp6	1520
diagnose snmp ip6 ip6	1520

diagnose snmp ip6 udp6	1520
diagnose snmp net	1520
diagnose snmp net stat	1520
diagnose snmp trap	1521
diagnose snmp trap send	1521
diagnose sys	1521
diagnose sys botnet-domain	1530
diagnose sys botnet-domain hit	1530
diagnose sys botnet-domain list	1530
diagnose sys botnet-ip	1530
diagnose sys botnet-ip find	1531
diagnose sys botnet-ip flush	1531
diagnose sys botnet-ip hit	1531
diagnose sys botnet-ip list	1531
diagnose sys cmdb	1531
diagnose sys cmdb check-lock	1532
diagnose sys cmdb dump	1532
diagnose sys cmdb dump vdom	1532
diagnose sys cmdb flag	1532
diagnose sys cmdb flag info	1532
diagnose sys cmdb flag reset	1532
diagnose sys cmdb flag reset script-running	1533
diagnose sys cmdb info	1533
diagnose sys cmdb refcnt	1533
diagnose sys cmdb refcnt reset	1533
diagnose sys cmdb refcnt show	1533
diagnose sys config-transaction	1534
diagnose sys config-transaction show	1534
diagnose sys config-transaction show entity-by-txn	1534
diagnose sys config-transaction show mctx	1534
diagnose sys config-transaction show txn-cli-commands	1534
diagnose sys config-transaction show txn-entity	1535
diagnose sys config-transaction show txn-info	1535
diagnose sys config-transaction show txn-lock	1535
diagnose sys config-transaction show txn-meta	1535
diagnose sys config-transaction status	1535
diagnose sys conntrack	1535
diagnose sys conntrack clear	1536
diagnose sys conntrack count	1536
diagnose sys conntrack list-dying4	1536
diagnose sys conntrack list-dying6	1536
diagnose sys conntrack list-unconfirmed4	1536
diagnose sys conntrack list-unconfirmed6	1536
diagnose sys conntrack list4	1537
diagnose sys conntrack list6	1537
diagnose sys conntrack stats	1537
diagnose sys csf	1537
diagnose sys csf authorization	1537
diagnose sys csf authorization accept	1537

diagnose sys csf authorization deny	1538
diagnose sys csf authorization pending-list	1538
diagnose sys csf downstream	1538
diagnose sys csf downstream-devices	1538
diagnose sys csf dynamic-sync-read	1539
diagnose sys csf dynamic-sync-request	1539
diagnose sys csf dynamic-sync-update	1539
diagnose sys csf fabric-device	1539
diagnose sys csf fabric-device list	1539
diagnose sys csf file	1540
diagnose sys csf file cat	1540
diagnose sys csf file top-mem	1540
diagnose sys csf forticloud-id-list	1540
diagnose sys csf get-bulk-global-view	1540
diagnose sys csf global	1541
diagnose sys csf initialize-cmd	1541
diagnose sys csf license	1541
diagnose sys csf merge-cmd	1541
diagnose sys csf neighbor	1542
diagnose sys csf neighbor flush	1542
diagnose sys csf neighbor list	1542
diagnose sys csf query	1542
diagnose sys csf tunnel-test-listener	1543
diagnose sys csf tunnel-test-sender	1543
diagnose sys csf upstream	1543
diagnose sys csf versions	1543
diagnose sys dayst-info	1543
diagnose sys device	1544
diagnose sys device add	1544
diagnose sys device delete	1544
diagnose sys device list	1544
diagnose sys external-resource	1544
diagnose sys external-resource list	1545
diagnose sys external-resource push-add	1545
diagnose sys external-resource push-api-json-commands	1545
diagnose sys external-resource push-remove	1545
diagnose sys external-resource push-snapshot	1545
diagnose sys external-resource stats	1546
diagnose sys filesystem	1546
diagnose sys filesystem hash	1546
diagnose sys filesystem last-modified-files	1546
diagnose sys filesystem tree	1546
diagnose sys fips	1547
diagnose sys fips error-mode	1547
diagnose sys ha	1547
diagnose sys ha check-vc	1547
diagnose sys ha checksum	1547
diagnose sys ha checksum cached	1547
diagnose sys ha checksum cluster	1548

diagnose sys ha checksum log	1548
diagnose sys ha checksum log clear	1548
diagnose sys ha checksum log disable	1548
diagnose sys ha checksum log enable	1548
diagnose sys ha checksum recalculate	1549
diagnose sys ha checksum show	1549
diagnose sys ha checksum show-nonsync	1549
diagnose sys ha checksum test	1549
diagnose sys ha dump-by	1550
diagnose sys ha dump-by debug-zone	1550
diagnose sys ha dump-by device	1550
diagnose sys ha dump-by group	1550
diagnose sys ha dump-by kernel	1550
diagnose sys ha dump-by rcache	1550
diagnose sys ha dump-by vcluster	1551
diagnose sys ha dump-by vdom	1551
diagnose sys ha extfile-sig	1551
diagnose sys ha fgsp-zone	1551
diagnose sys ha fib	1551
diagnose sys ha hactx-stats	1551
diagnose sys ha hactx-stats clear	1552
diagnose sys ha hadiff	1552
diagnose sys ha hadiff log	1552
diagnose sys ha hadiff log clear	1552
diagnose sys ha hadiff log disable	1552
diagnose sys ha hadiff log enable	1552
diagnose sys ha hadiff max-sync-turns	1553
diagnose sys ha hadiff max-unsync-wait	1553
diagnose sys ha hadiff status	1553
diagnose sys ha hasync-conn-max-buf	1553
diagnose sys ha hasync-stats	1553
diagnose sys ha hasync-stats all	1554
diagnose sys ha hasync-stats by-object	1554
diagnose sys ha hasync-stats most-recent	1554
diagnose sys ha hasync-stats most-time	1554
diagnose sys ha heartbeat	1554
diagnose sys ha history	1555
diagnose sys ha history clear	1555
diagnose sys ha history read	1555
diagnose sys ha mac	1555
diagnose sys ha pingsvr-secondary-force-reset	1555
diagnose sys ha recalculate-extfile-signature	1555
diagnose sys ha reset-health-status	1556
diagnose sys ha reset-uptime	1556
diagnose sys ha session-sync-dev	1556
diagnose sys ha session-sync-dev clear	1556
diagnose sys ha session-sync-dev set	1556
diagnose sys ha standalone-peers	1556
diagnose sys ha standalone-peers reset-stats	1557

diagnose sys ha stats	1557
diagnose sys ha status	1557
diagnose sys ha sync-stats	1557
diagnose sys ha sync-stats-reset	1557
diagnose sys ha vlan-hb-monitor	1557
diagnose sys icap-remote-server	1558
diagnose sys icap-remote-server status	1558
diagnose sys iotop	1558
diagnose sys link-monitor	1558
diagnose sys link-monitor filter	1558
diagnose sys link-monitor filter clear	1558
diagnose sys link-monitor filter name	1559
diagnose sys link-monitor interface	1559
diagnose sys link-monitor launch	1559
diagnose sys link-monitor status	1559
diagnose sys mpstat	1560
diagnose sys nmi-watchdog	1560
diagnose sys nmi-watchdog disable	1560
diagnose sys nmi-watchdog enable	1560
diagnose sys nmi-watchdog reboot	1560
diagnose sys nmi-watchdog reboot disable	1560
diagnose sys nmi-watchdog reboot enable	1561
diagnose sys nmi-watchdog threshold	1561
diagnose sys ntp	1561
diagnose sys ntp status	1561
diagnose sys pair	1561
diagnose sys process	1561
diagnose sys process dump	1562
diagnose sys process nameof	1562
diagnose sys process pidof	1562
diagnose sys process pstack	1562
diagnose sys process sock-mem	1562
diagnose sys process socket	1563
diagnose sys process trace	1563
diagnose sys profile	1563
diagnose sys profile cpumask	1563
diagnose sys profile show	1563
diagnose sys profile show detail	1564
diagnose sys profile show order	1564
diagnose sys profile start	1564
diagnose sys profile step	1564
diagnose sys profile stop	1564
diagnose sys profile sysmap	1564
diagnose sys ptp	1565
diagnose sys ptp status	1565
diagnose sys scanunit	1565
diagnose sys scanunit av-filetype-reuse	1565
diagnose sys scanunit av-filetype-reuse disable	1565
diagnose sys scanunit av-filetype-reuse enable	1565

diagnose sys scanunit bypass	1566
diagnose sys scanunit bypass clear	1566
diagnose sys scanunit bypass disable	1566
diagnose sys scanunit bypass disable category	1566
diagnose sys scanunit bypass disable category all	1566
diagnose sys scanunit bypass disable category av-engine	1566
diagnose sys scanunit bypass disable category scanunit	1567
diagnose sys scanunit bypass disable protocol	1567
diagnose sys scanunit bypass disable protocol all	1567
diagnose sys scanunit bypass disable protocol cifs	1567
diagnose sys scanunit bypass disable protocol ftp	1567
diagnose sys scanunit bypass disable protocol http	1567
diagnose sys scanunit bypass disable protocol imap	1568
diagnose sys scanunit bypass disable protocol nntp	1568
diagnose sys scanunit bypass disable protocol pop3	1568
diagnose sys scanunit bypass disable protocol smtp	1568
diagnose sys scanunit bypass enable	1568
diagnose sys scanunit bypass enable category	1568
diagnose sys scanunit bypass enable category all	1569
diagnose sys scanunit bypass enable category av-engine	1569
diagnose sys scanunit bypass enable category scanunit	1569
diagnose sys scanunit bypass enable protocol	1569
diagnose sys scanunit bypass enable protocol all	1569
diagnose sys scanunit bypass enable protocol cifs	1569
diagnose sys scanunit bypass enable protocol ftp	1570
diagnose sys scanunit bypass enable protocol http	1570
diagnose sys scanunit bypass enable protocol imap	1570
diagnose sys scanunit bypass enable protocol nntp	1570
diagnose sys scanunit bypass enable protocol pop3	1570
diagnose sys scanunit bypass enable protocol smtp	1570
diagnose sys scanunit bypass show	1571
diagnose sys scanunit crash-dump	1571
diagnose sys scanunit crash-dump clear	1571
diagnose sys scanunit crash-dump disable	1571
diagnose sys scanunit crash-dump enable	1571
diagnose sys scanunit crash-dump read	1571
diagnose sys scanunit debug	1572
diagnose sys scanunit debug all	1572
diagnose sys scanunit debug analytics	1572
diagnose sys scanunit debug antisipam	1572
diagnose sys scanunit debug daemon	1572
diagnose sys scanunit debug dlp	1573
diagnose sys scanunit debug file-filter	1573
diagnose sys scanunit debug ia	1573
diagnose sys scanunit debug icb	1573
diagnose sys scanunit debug job	1574
diagnose sys scanunit debug level	1574
diagnose sys scanunit debug level error	1574
diagnose sys scanunit debug level info	1574

diagnose sys scanunit debug level verbose	1574
diagnose sys scanunit debug level warning	1574
diagnose sys scanunit debug outbreak-prevention	1575
diagnose sys scanunit debug quarantine	1575
diagnose sys scanunit debug reset	1575
diagnose sys scanunit debug sane	1575
diagnose sys scanunit debug show	1575
diagnose sys scanunit file-hash	1576
diagnose sys scanunit file-hash list	1576
diagnose sys scanunit file-hash list all	1576
diagnose sys scanunit file-hash list md5	1576
diagnose sys scanunit file-hash list sha1	1576
diagnose sys scanunit file-hash list sha256	1576
diagnose sys scanunit file-hash query	1577
diagnose sys scanunit file-hash query md5	1577
diagnose sys scanunit file-hash query sha1	1577
diagnose sys scanunit file-hash query sha256	1577
diagnose sys scanunit file-hash status	1577
diagnose sys scanunit filter	1578
diagnose sys scanunit filter clear	1578
diagnose sys scanunit filter list	1578
diagnose sys scanunit filter negate	1578
diagnose sys scanunit filter negate vd	1578
diagnose sys scanunit filter vd	1578
diagnose sys scanunit log	1579
diagnose sys scanunit log filter	1579
diagnose sys scanunit log filter clear	1579
diagnose sys scanunit log filter list	1579
diagnose sys scanunit log filter negate	1579
diagnose sys scanunit log filter negate vd	1579
diagnose sys scanunit log filter vd	1580
diagnose sys scanunit reload-avdb	1580
diagnose sys scanunit reload-aveng	1580
diagnose sys scanunit restart	1580
diagnose sys scanunit stats	1580
diagnose sys scanunit stats all	1580
diagnose sys scanunit stats clear	1581
diagnose sys scanunit stats list	1581
diagnose sys scanunit vdom-stats	1581
diagnose sys scanunit vdom-stats all	1581
diagnose sys scanunit vdom-stats clear	1581
diagnose sys scanunit vdom-stats clear-all	1581
diagnose sys scanunit vdom-stats list	1582
diagnose sys sdn	1582
diagnose sys sdn cache	1582
diagnose sys sdn status	1582
diagnose sys server-probe	1583
diagnose sys server-probe response	1583
diagnose sys session	1583

diagnose sys session clear	1583
diagnose sys session count	1583
diagnose sys session exp-stat	1583
diagnose sys session expectation	1584
diagnose sys session filter	1584
diagnose sys session filter clear	1584
diagnose sys session filter clear dintf	1584
diagnose sys session filter clear dport	1584
diagnose sys session filter clear dst	1584
diagnose sys session filter clear nsrc	1585
diagnose sys session filter clear policy	1585
diagnose sys session filter clear proto	1585
diagnose sys session filter clear proto-state	1585
diagnose sys session filter clear sintf	1585
diagnose sys session filter clear sport	1585
diagnose sys session filter clear src	1586
diagnose sys session filter dintf	1586
diagnose sys session filter dport	1586
diagnose sys session filter dst	1586
diagnose sys session filter nsrc	1586
diagnose sys session filter policy	1587
diagnose sys session filter proto	1587
diagnose sys session filter sintf	1587
diagnose sys session filter sport	1587
diagnose sys session filter src	1588
diagnose sys session full-stat	1588
diagnose sys session list	1588
diagnose sys session list-verbose	1588
diagnose sys session stat	1588
diagnose sys session ttl	1589
diagnose sys session6	1589
diagnose sys session6 clear	1589
diagnose sys session6 expectation	1589
diagnose sys session6 filter	1589
diagnose sys session6 filter clear	1589
diagnose sys session6 filter clear dintf	1590
diagnose sys session6 filter clear dport	1590
diagnose sys session6 filter clear dst	1590
diagnose sys session6 filter clear nsrc	1590
diagnose sys session6 filter clear policy	1590
diagnose sys session6 filter clear proto	1590
diagnose sys session6 filter clear proto-state	1591
diagnose sys session6 filter clear sintf	1591
diagnose sys session6 filter clear sport	1591
diagnose sys session6 filter clear src	1591
diagnose sys session6 filter clear vd	1591
diagnose sys session6 filter dintf	1591
diagnose sys session6 filter dport	1592
diagnose sys session6 filter dst	1592

diagnose sys session6 filter nsrc	1592
diagnose sys session6 filter policy	1592
diagnose sys session6 filter proto	1593
diagnose sys session6 filter sintf	1593
diagnose sys session6 filter sport	1593
diagnose sys session6 filter src	1593
diagnose sys session6 list	1594
diagnose sys session6 list-verbose	1594
diagnose sys tcp-option	1594
diagnose sys tcp-option disable	1594
diagnose sys tcp-option enable	1594
diagnose sys tcpsock	1594
diagnose sys tcpsock6	1595
diagnose sys top	1595
diagnose sys top-all	1595
diagnose sys top-fd	1595
diagnose sys top-fd detail	1596
diagnose sys top-mem	1596
diagnose sys top-mem detail	1596
diagnose sys top-sockmem	1596
diagnose sys traffic	1597
diagnose sys traffic app-stats	1597
diagnose sys traffic app-stats list	1597
diagnose sys udpsock	1597
diagnose sys udpsock6	1597
diagnose sys uuid	1598
diagnose sys uuid allow-manual-set	1598
diagnose sys uuid allow-manual-set disable	1598
diagnose sys uuid allow-manual-set enable	1598
diagnose sys uuid generate	1598
diagnose sys var-zone	1598
diagnose sys var-zone show	1599
diagnose sys vd	1599
diagnose sys vd add	1599
diagnose sys vd delete	1599
diagnose sys vd list	1599
diagnose sys vd set	1600
diagnose sys vd stats	1600
diagnose sys vlan	1600
diagnose sys vlan list	1600
diagnose sys vxlan	1600
diagnose sys vxlan fdb	1600
diagnose sys vxlan fdb list	1601
diagnose test analytics-pdf-report	1601
diagnose test analytics-pdf-report list	1601
diagnose test analytics-pdf-report max	1601
diagnose test analytics-pdf-report request	1601
diagnose test analytics-pdf-report status	1602
diagnose test analytics-report	1602

diagnose test analytics-report checksum	1602
diagnose test application	1602
diagnose test application acd	1604
diagnose test application acsd	1604
diagnose test application autod	1604
diagnose test application awsd	1605
diagnose test application azd	1605
diagnose test application bfd	1605
diagnose test application csfd	1605
diagnose test application ddnsd	1606
diagnose test application dhcp6c	1606
diagnose test application dhcp6r	1606
diagnose test application dhcprelay	1606
diagnose test application dlpfingerprint	1607
diagnose test application dlpfpcache	1607
diagnose test application dnsproxy	1607
diagnose test application dsd	1607
diagnose test application eap_supp	1608
diagnose test application fas	1608
diagnose test application fcncd	1608
diagnose test application fds_notify	1608
diagnose test application fgtlogd	1608
diagnose test application fnbamd	1609
diagnose test application forticldd	1609
diagnose test application forticron	1609
diagnose test application fsd	1609
diagnose test application fsvrd	1610
diagnose test application gcpcd	1610
diagnose test application harelay	1610
diagnose test application hasync	1610
diagnose test application hataik	1611
diagnose test application ibmd	1611
diagnose test application imap	1611
diagnose test application init	1611
diagnose test application iotd	1611
diagnose test application ipamd	1612
diagnose test application ipamsd	1612
diagnose test application ipldb	1612
diagnose test application ipsengine	1612
diagnose test application ipsmonitor	1613
diagnose test application ipsufd	1613
diagnose test application kubed	1613
diagnose test application l2tpcd	1613
diagnose test application lnkmt	1614
diagnose test application locallogd	1614
diagnose test application miglogd	1614
diagnose test application mrd	1614
diagnose test application netxd	1615
diagnose test application nntp	1615

diagnose test application ocid	1615
diagnose test application openstackd	1615
diagnose test application ovrd	1615
diagnose test application pop3	1616
diagnose test application pptpcd	1616
diagnose test application quarantined	1616
diagnose test application radius-das	1616
diagnose test application radiusd	1617
diagnose test application radvd	1617
diagnose test application reportd	1617
diagnose test application rt_router	1617
diagnose test application sdncd	1618
diagnose test application sdnd	1618
diagnose test application sepmd	1618
diagnose test application sessionsync	1618
diagnose test application sfupgraded	1618
diagnose test application smtp	1619
diagnose test application snmpd	1619
diagnose test application syslogd	1619
diagnose test application updated	1619
diagnose test application uploadd	1620
diagnose test application urlfilter	1620
diagnose test application vned	1620
diagnose test application wad	1620
diagnose test application wccpd	1621
diagnose test application wf_monitor	1621
diagnose test application wiredapd	1621
diagnose test authserver	1621
diagnose test authserver cert	1622
diagnose test authserver ext-idp	1622
diagnose test authserver ldap	1622
diagnose test authserver ldap-digest	1622
diagnose test authserver ldap-direct	1622
diagnose test authserver ldap-search	1623
diagnose test authserver local	1623
diagnose test authserver pop3	1623
diagnose test authserver radius	1623
diagnose test authserver radius-direct	1623
diagnose test authserver tacacs+	1623
diagnose test authserver tacacs+-direct	1624
diagnose test authserver user	1624
diagnose test guest	1624
diagnose test guest add	1624
diagnose test guest del	1624
diagnose test guest list	1624
diagnose test update	1625
diagnose test update info	1625
diagnose traffictest	1625
diagnose traffictest client-intf	1625

diagnose traffictest port	1626
diagnose traffictest proto	1626
diagnose traffictest proto 0	1626
diagnose traffictest proto 1	1626
diagnose traffictest run	1626
diagnose traffictest server-intf	1627
diagnose traffictest show	1627
diagnose user	1628
diagnose user banned-ip	1629
diagnose user banned-ip add	1629
diagnose user banned-ip add src4	1629
diagnose user banned-ip add src6	1629
diagnose user banned-ip clear	1630
diagnose user banned-ip delete	1630
diagnose user banned-ip delete src4	1630
diagnose user banned-ip delete src6	1630
diagnose user banned-ip list	1630
diagnose user banned-ip list all	1631
diagnose user banned-ip list src4	1631
diagnose user banned-ip list src6	1631
diagnose user banned-ip stat	1631
diagnose user device	1631
diagnose user device clear	1631
diagnose user device del	1632
diagnose user device filter	1632
diagnose user device filter addr	1632
diagnose user device filter clear	1632
diagnose user device filter clear addr	1632
diagnose user device filter clear generation	1633
diagnose user device filter clear index	1633
diagnose user device filter clear joined	1633
diagnose user device filter clear vd	1633
diagnose user device filter generation	1633
diagnose user device filter joined	1633
diagnose user device filter list	1634
diagnose user device filter negate	1634
diagnose user device filter negate addr	1634
diagnose user device filter negate generation	1634
diagnose user device filter negate index	1634
diagnose user device filter negate joined	1634
diagnose user device filter negate vd	1635
diagnose user device filter vd	1635
diagnose user device get	1635
diagnose user device list	1635
diagnose user device stats	1635
diagnose user-device-store	1636
diagnose user-device-store device	1637
diagnose user-device-store device memory	1637
diagnose user-device-store device memory list	1637

diagnose user-device-store device memory ot-purdue-set	1637
diagnose user-device-store device memory query	1637
diagnose user-device-store device memory uid	1638
diagnose user-device-store device memory uid add	1638
diagnose user-device-store device memory uid delete	1638
diagnose user-device-store device memory uid update	1638
diagnose user-device-store device memory vulnerability-fetch	1638
diagnose user-device-store iot-vuln	1638
diagnose user-device-store iot-vuln list	1639
diagnose user-device-store iot-vuln query	1639
diagnose user-device-store unified	1639
diagnose user-device-store unified clear	1639
diagnose user-device-store unified debug	1639
diagnose user-device-store unified debug disable	1639
diagnose user-device-store unified debug enable	1640
diagnose user-device-store unified delete	1640
diagnose user-device-store unified device-memory-query	1640
diagnose user-device-store unified device-memory-query filters-and	1640
diagnose user-device-store unified device-memory-query filters-or	1640
diagnose user-device-store unified device-query	1640
diagnose user-device-store unified device-query filters-and	1641
diagnose user-device-store unified device-query filters-or	1641
diagnose user-device-store unified dump	1641
diagnose user-device-store unified list	1641
diagnose user-device-store unified re-query	1641
diagnose user-device-store unified stats	1641
diagnose user-device-store unified user-memory-query	1642
diagnose user-device-store unified user-memory-query filters-and	1642
diagnose user-device-store unified user-memory-query filters-or	1642
diagnose user-device-store unified user-query	1642
diagnose user-device-store unified user-query filters-and	1642
diagnose user-device-store unified user-query filters-or	1642
diagnose user-device-store user	1643
diagnose user-device-store user memory	1643
diagnose user-device-store user memory list	1643
diagnose user-device-store user memory query	1643
diagnose user-device-store user-count	1643
diagnose user-device-store user-count list	1643
diagnose user-device-store user-count query	1644
diagnose user-device-store user-stats	1644
diagnose user-device-store user-stats query	1644
diagnose vendor-mac	1644
diagnose vendor-mac id	1644
diagnose vendor-mac id-summary	1645
diagnose vendor-mac info	1645
diagnose vendor-mac match	1645
diagnose vmware	1645
diagnose vmware ovfenv	1646
diagnose vpn ssl	1646

diagnose wacs	1646
diagnose wacs clear	1646
diagnose wacs restart	1646
diagnose wacs stats	1646
diagnose wad	1647
diagnose wad access-proxy	1659
diagnose wad access-proxy health-check	1659
diagnose wad access-proxy health-check status	1659
diagnose wad console-log	1659
diagnose wad console-log disable	1659
diagnose wad console-log enable	1659
diagnose wad csvc	1660
diagnose wad csvc bytcache	1660
diagnose wad csvc bytcache clear	1660
diagnose wad csvc bytcache flush	1660
diagnose wad csvc bytcache lists	1660
diagnose wad csvc bytcache stats	1661
diagnose wad csvc memcache	1661
diagnose wad csvc memcache clear	1661
diagnose wad csvc memcache flush	1661
diagnose wad csvc memcache lists	1661
diagnose wad csvc memcache stats	1662
diagnose wad csvc restart	1662
diagnose wad csvc webcache	1662
diagnose wad csvc webcache clear	1662
diagnose wad csvc webcache flush	1663
diagnose wad csvc webcache lists	1663
diagnose wad csvc webcache stats	1663
diagnose wad debug	1663
diagnose wad debug clear	1663
diagnose wad debug crash	1664
diagnose wad debug crash clear	1664
diagnose wad debug crash disable	1664
diagnose wad debug crash enable	1664
diagnose wad debug crash list	1664
diagnose wad debug crash max	1664
diagnose wad debug crash read	1665
diagnose wad debug disable	1665
diagnose wad debug disable category	1665
diagnose wad debug disable category aio	1665
diagnose wad debug disable category antiphish	1665
diagnose wad debug disable category auth	1665
diagnose wad debug disable category autotest	1666
diagnose wad debug disable category bytcache	1666
diagnose wad debug disable category cache_server	1666
diagnose wad debug disable category casb	1666
diagnose wad debug disable category cifs	1666
diagnose wad debug disable category config	1666
diagnose wad debug disable category csvc	1667

diagnose wad debug disable category detail	1667
diagnose wad debug disable category devuln	1667
diagnose wad debug disable category diag	1667
diagnose wad debug disable category dispatcher	1667
diagnose wad debug disable category dns	1667
diagnose wad debug disable category dskd	1668
diagnose wad debug disable category extension	1668
diagnose wad debug disable category ftp	1668
diagnose wad debug disable category http	1668
diagnose wad debug disable category http2	1668
diagnose wad debug disable category http3	1668
diagnose wad debug disable category icap	1669
diagnose wad debug disable category icap_server	1669
diagnose wad debug disable category icbsvc	1669
diagnose wad debug disable category info	1669
diagnose wad debug disable category ips	1669
diagnose wad debug disable category isolator	1669
diagnose wad debug disable category license	1670
diagnose wad debug disable category mapi	1670
diagnose wad debug disable category memblk	1670
diagnose wad debug disable category monitor	1670
diagnose wad debug disable category packet	1670
diagnose wad debug disable category policy	1670
diagnose wad debug disable category policy_test	1671
diagnose wad debug disable category proc	1671
diagnose wad debug disable category quic	1671
diagnose wad debug disable category quic_cc	1671
diagnose wad debug disable category rpc	1671
diagnose wad debug disable category scan	1671
diagnose wad debug disable category scp	1672
diagnose wad debug disable category session	1672
diagnose wad debug disable category sftp	1672
diagnose wad debug disable category socks	1672
diagnose wad debug disable category ssh	1672
diagnose wad debug disable category ssl	1672
diagnose wad debug disable category sys	1673
diagnose wad debug disable category tls_fingerprint	1673
diagnose wad debug disable category tunnel	1673
diagnose wad debug disable category uih	1673
diagnose wad debug disable category video	1673
diagnose wad debug disable category vs	1673
diagnose wad debug disable category waf	1674
diagnose wad debug disable category webcache	1674
diagnose wad debug display	1674
diagnose wad debug display pid	1674
diagnose wad debug display pid disable	1674
diagnose wad debug display pid enable	1674
diagnose wad debug enable	1675
diagnose wad debug enable all	1675

diagnose wad debug enable category	1675
diagnose wad debug enable category aio	1675
diagnose wad debug enable category all	1675
diagnose wad debug enable category antiphish	1675
diagnose wad debug enable category auth	1676
diagnose wad debug enable category autotest	1676
diagnose wad debug enable category bytcache	1676
diagnose wad debug enable category cache_server	1676
diagnose wad debug enable category casb	1676
diagnose wad debug enable category cifs	1676
diagnose wad debug enable category config	1677
diagnose wad debug enable category csvc	1677
diagnose wad debug enable category detail	1677
diagnose wad debug enable category devuln	1677
diagnose wad debug enable category diag	1677
diagnose wad debug enable category dispatcher	1677
diagnose wad debug enable category dns	1678
diagnose wad debug enable category dskd	1678
diagnose wad debug enable category extension	1678
diagnose wad debug enable category ftp	1678
diagnose wad debug enable category http	1678
diagnose wad debug enable category http2	1678
diagnose wad debug enable category http3	1679
diagnose wad debug enable category icap	1679
diagnose wad debug enable category icap_server	1679
diagnose wad debug enable category icbsvc	1679
diagnose wad debug enable category info	1679
diagnose wad debug enable category ips	1679
diagnose wad debug enable category isolator	1680
diagnose wad debug enable category license	1680
diagnose wad debug enable category mapi	1680
diagnose wad debug enable category memblk	1680
diagnose wad debug enable category monitor	1680
diagnose wad debug enable category packet	1680
diagnose wad debug enable category policy	1681
diagnose wad debug enable category policy_test	1681
diagnose wad debug enable category proc	1681
diagnose wad debug enable category quic	1681
diagnose wad debug enable category quic_cc	1681
diagnose wad debug enable category rpc	1681
diagnose wad debug enable category scan	1682
diagnose wad debug enable category scp	1682
diagnose wad debug enable category session	1682
diagnose wad debug enable category sftp	1682
diagnose wad debug enable category socks	1682
diagnose wad debug enable category ssh	1682
diagnose wad debug enable category ssl	1683
diagnose wad debug enable category sys	1683
diagnose wad debug enable category tls_fingerprint	1683

diagnose wad debug enable category tunnel	1683
diagnose wad debug enable category uih	1683
diagnose wad debug enable category video	1683
diagnose wad debug enable category vs	1684
diagnose wad debug enable category waf	1684
diagnose wad debug enable category webcache	1684
diagnose wad debug enable level	1684
diagnose wad debug enable level error	1684
diagnose wad debug enable level info	1684
diagnose wad debug enable level verbose	1685
diagnose wad debug enable level warn	1685
diagnose wad debug ips-db	1685
diagnose wad debug ips-db status	1685
diagnose wad debug save-http-req-crash	1685
diagnose wad debug save-http-req-crash disable	1685
diagnose wad debug save-http-req-crash enable	1686
diagnose wad debug show	1686
diagnose wad dev	1686
diagnose wad dev fcnacd	1686
diagnose wad dev fcnacd delete	1686
diagnose wad dev fcnacd ip-err	1686
diagnose wad dev fcnacd uid-err	1687
diagnose wad dev fcnacd update	1687
diagnose wad dev query-by	1687
diagnose wad dev query-by ipv4	1687
diagnose wad dev query-by ipv6	1687
diagnose wad dev query-by uid	1687
diagnose wad dev-vuln	1688
diagnose wad dev-vuln query	1688
diagnose wad dev-vuln query-by-id	1688
diagnose wad dev-vuln query-ftgd	1688
diagnose wad dynamic-bypass	1688
diagnose wad dynamic-bypass clear	1688
diagnose wad dynamic-bypass flush	1689
diagnose wad dynamic-bypass show	1689
diagnose wad exp-fw-policy-test	1689
diagnose wad exp-fw-policy-test-save	1689
diagnose wad filter	1690
diagnose wad filter clear	1690
diagnose wad filter dport	1690
diagnose wad filter drop-unknown-session	1690
diagnose wad filter dst	1691
diagnose wad filter dst6	1691
diagnose wad filter explicit-policy	1691
diagnose wad filter firewall-policy	1692
diagnose wad filter list	1692
diagnose wad filter negate	1692
diagnose wad filter process-id	1692
diagnose wad filter process-id-by-src	1692

diagnose wad filter process-type	1693
diagnose wad filter protocol	1693
diagnose wad filter proxy-policy-list-increment	1693
diagnose wad filter sport	1694
diagnose wad filter src	1694
diagnose wad filter src6	1694
diagnose wad filter vd	1695
diagnose wad fw-policy-test-get	1695
diagnose wad health	1695
diagnose wad health debug	1695
diagnose wad health fs	1695
diagnose wad health worker	1696
diagnose wad history	1696
diagnose wad history clear	1696
diagnose wad history list	1696
diagnose wad icap	1696
diagnose wad icap list	1696
diagnose wad kxp	1697
diagnose wad kxp clear	1697
diagnose wad kxp list	1697
diagnose wad license	1697
diagnose wad license clear	1697
diagnose wad license detail	1697
diagnose wad license glob-usage	1698
diagnose wad license summary	1698
diagnose wad license test	1698
diagnose wad license usage	1698
diagnose wad memory	1698
diagnose wad memory monitor	1699
diagnose wad memory monitor disable	1699
diagnose wad memory monitor enable	1699
diagnose wad memory monitor interval	1699
diagnose wad memory monitor list	1699
diagnose wad memory monitor max-report-files	1699
diagnose wad memory monitor mem-threshold-red	1700
diagnose wad memory overused	1700
diagnose wad memory report	1700
diagnose wad memory sum	1700
diagnose wad memory track	1700
diagnose wad memory workers	1701
diagnose wad nbi	1701
diagnose wad nbi license	1701
diagnose wad nbi packages	1701
diagnose wad nbi status	1701
diagnose wad process	1701
diagnose wad process YouTube-filter-cache-service	1702
diagnose wad process algo	1704
diagnose wad process byte-cache	1706
diagnose wad process cache-service-cs	1708

diagnose wad process cache-service-db	1710
diagnose wad process cert-inspection	1712
diagnose wad process config-notify	1714
diagnose wad process debug	1716
diagnose wad process dev-vuln	1718
diagnose wad process dispatcher	1720
diagnose wad process ia-cache	1722
diagnose wad process informer	1724
diagnose wad process isolator	1726
diagnose wad process manager	1728
diagnose wad process object-cache	1730
diagnose wad process preload daemon	1732
diagnose wad process staled-worker	1734
diagnose wad process tls-fgpt-service	1736
diagnose wad process traffic aggregator	1738
diagnose wad process user-info	1740
diagnose wad process user-info-history	1742
diagnose wad process worker	1744
diagnose wad report	1746
diagnose wad report policy	1746
diagnose wad report session	1746
diagnose wad report user	1746
diagnose wad restore	1746
diagnose wad restore cdn-rules	1746
diagnose wad restore cdn-rules all	1747
diagnose wad session	1747
diagnose wad session clear	1747
diagnose wad session count	1747
diagnose wad session list	1747
diagnose wad session list-http2	1747
diagnose wad sshproxy	1748
diagnose wad sshproxy clear	1748
diagnose wad sshproxy list	1748
diagnose wad stats	1748
diagnose wad stats algo	1748
diagnose wad stats algo.antiphish	1749
diagnose wad stats algo.casb	1749
diagnose wad stats algo.dev_info	1749
diagnose wad stats algo.dev_stats	1749
diagnose wad stats algo.fast_tb	1749
diagnose wad stats algo.fw_policy	1750
diagnose wad stats algo.icap_client	1750
diagnose wad stats algo.inet_app	1750
diagnose wad stats algo.ips_builder	1750
diagnose wad stats algo.ipsscan	1751
diagnose wad stats algo.krl	1751
diagnose wad stats algo.pattern_match	1751
diagnose wad stats algo.proc_common	1751
diagnose wad stats algo.sec_prof	1752

diagnose wad stats algo.ssl	1752
diagnose wad stats algo.url_filter	1752
diagnose wad stats algo.urlredirect	1752
diagnose wad stats algo.wisp	1752
diagnose wad stats cache_service	1753
diagnose wad stats cache_service.proc_common	1753
diagnose wad stats cache_service.tcp	1753
diagnose wad stats cic	1753
diagnose wad stats cic.proc_common	1754
diagnose wad stats cic.ssl_cic	1754
diagnose wad stats common	1754
diagnose wad stats config	1754
diagnose wad stats config.config	1755
diagnose wad stats config.proc_common	1755
diagnose wad stats config.shm_stats	1755
diagnose wad stats config.sscan	1755
diagnose wad stats debug	1755
diagnose wad stats debug.crash_handler	1756
diagnose wad stats debug.proc_common	1756
diagnose wad stats debug.tls_fgpt_svc_cp	1756
diagnose wad stats dispatcher	1756
diagnose wad stats dispatcher.cifs	1757
diagnose wad stats dispatcher.dns_proxy	1757
diagnose wad stats dispatcher.http_msg	1757
diagnose wad stats dispatcher.icap_local_server	1757
diagnose wad stats dispatcher.llm	1758
diagnose wad stats dispatcher.proc_common	1758
diagnose wad stats dispatcher.ssh	1758
diagnose wad stats dispatcher.tcp	1758
diagnose wad stats dispatcher.tunnel	1758
diagnose wad stats fgpt	1759
diagnose wad stats fgpt.fgpt_self	1759
diagnose wad stats fgpt.proc_common	1759
diagnose wad stats fgpt.tls_fgpt_svc_cp	1759
diagnose wad stats ia_cache	1760
diagnose wad stats ia_cache.proc_common	1760
diagnose wad stats informer	1760
diagnose wad stats informer.dev_info	1760
diagnose wad stats informer.dev_stats	1761
diagnose wad stats informer.fsae	1761
diagnose wad stats informer.informer_dev	1761
diagnose wad stats informer.informer_self	1761
diagnose wad stats informer.proc_common	1761
diagnose wad stats informer.ztna_jwt	1762
diagnose wad stats isolator	1762
diagnose wad stats isolator.dns_req	1762
diagnose wad stats isolator.isolator_self	1762
diagnose wad stats isolator.proc_common	1763
diagnose wad stats isolator.ssl	1763

diagnose wad stats isolator.tcp	1763
diagnose wad stats mgr	1763
diagnose wad stats mgr.mgr_self	1764
diagnose wad stats mgr.proc_common	1764
diagnose wad stats mgr.shm_stats	1764
diagnose wad stats uih	1764
diagnose wad stats uih.proc_common	1764
diagnose wad stats uih.uih_self	1765
diagnose wad stats usr_info	1765
diagnose wad stats usr_info.dev_info	1765
diagnose wad stats usr_info.dev_stats	1765
diagnose wad stats usr_info.dns_req	1766
diagnose wad stats usr_info.ftgd_agent	1766
diagnose wad stats usr_info.ldap	1766
diagnose wad stats usr_info.pattern_match	1766
diagnose wad stats usr_info.proc_common	1767
diagnose wad stats usr_info.ssl	1767
diagnose wad stats usr_info.tcp	1767
diagnose wad stats usr_info.user_device_store	1767
diagnose wad stats usr_info.usr_info_self	1767
diagnose wad stats vfcs	1768
diagnose wad stats vfcs.proc_common	1768
diagnose wad stats worker	1768
diagnose wad stats worker.aio	1768
diagnose wad stats worker.antiphish	1769
diagnose wad stats worker.app_mgr	1769
diagnose wad stats worker.auth	1769
diagnose wad stats worker.auth_rule	1769
diagnose wad stats worker.auth_user	1770
diagnose wad stats worker.cache_resource	1770
diagnose wad stats worker.cache_store	1770
diagnose wad stats worker.casb	1770
diagnose wad stats worker.cert_cache	1770
diagnose wad stats worker.chunk_cache	1771
diagnose wad stats worker.cifs	1771
diagnose wad stats worker.config_delta	1771
diagnose wad stats worker.conn_pool	1771
diagnose wad stats worker.db	1772
diagnose wad stats worker.dev_info	1772
diagnose wad stats worker.dev_stats	1772
diagnose wad stats worker.dns_proxy	1772
diagnose wad stats worker.dns_req	1773
diagnose wad stats worker.fast_match	1773
diagnose wad stats worker.fnbam	1773
diagnose wad stats worker.fsae	1773
diagnose wad stats worker.ftgd_agent	1773
diagnose wad stats worker.ftp	1774
diagnose wad stats worker.fw_policy	1774
diagnose wad stats worker.fwd_svr	1774

diagnose wad stats worker.http_auth	1774
diagnose wad stats worker.http_engine	1775
diagnose wad stats worker.http_ffbk	1775
diagnose wad stats worker.http_msg	1775
diagnose wad stats worker.http_scan	1775
diagnose wad stats worker.http_srv_selector	1776
diagnose wad stats worker.http_view	1776
diagnose wad stats worker.icap_client	1776
diagnose wad stats worker.icap_local_server	1776
diagnose wad stats worker.icap_parser	1776
diagnose wad stats worker.icap_remote_server	1777
diagnose wad stats worker.inet_app	1777
diagnose wad stats worker.infection_cache	1777
diagnose wad stats worker.ipseng	1777
diagnose wad stats worker.krb_pac	1778
diagnose wad stats worker.krl	1778
diagnose wad stats worker.kwd_dfa	1778
diagnose wad stats worker.ldap	1778
diagnose wad stats worker.llm	1779
diagnose wad stats worker.pattern_match	1779
diagnose wad stats worker.pol_test	1779
diagnose wad stats worker.policy_profile	1779
diagnose wad stats worker.proc_common	1779
diagnose wad stats worker.protos	1780
diagnose wad stats worker.quic	1780
diagnose wad stats worker.runtime_info	1780
diagnose wad stats worker.scan_cache	1780
diagnose wad stats worker.sec_prof	1781
diagnose wad stats worker.shaping	1781
diagnose wad stats worker.shm_stats	1781
diagnose wad stats worker.smb_prot	1781
diagnose wad stats worker.ssh	1782
diagnose wad stats worker.ssl	1782
diagnose wad stats worker.ssl_cic	1782
diagnose wad stats worker.sysmem	1782
diagnose wad stats worker.tcp	1782
diagnose wad stats worker.tls_fgpt_svc_cp	1783
diagnose wad stats worker.traffic_mirror	1783
diagnose wad stats worker.tunnel	1783
diagnose wad stats worker.url_filter	1783
diagnose wad stats worker.url_match	1784
diagnose wad stats worker.urlredir	1784
diagnose wad stats worker.wisp	1784
diagnose wad stats worker.worker_self	1784
diagnose wad stats worker.ztna_jwt	1785
diagnose wad stream-scan	1785
diagnose wad stream-scan av-intf	1785
diagnose wad stream-scan av-intf disable	1785
diagnose wad stream-scan av-intf enable	1785

diagnose wad stream-scan av-test	1785
diagnose wad tcp-connection	1786
diagnose wad tcp-connection list	1786
diagnose wad toggle	1786
diagnose wad tp-fw-policy-test	1786
diagnose wad tp-fw-policy-test-save	1787
diagnose wad tunnel	1787
diagnose wad tunnel clear	1787
diagnose wad tunnel list	1788
diagnose wad url-lookup	1788
diagnose wad user	1788
diagnose wad user clear	1788
diagnose wad user count	1788
diagnose wad user device	1789
diagnose wad user domain-controller	1789
diagnose wad user domain-controller dns	1789
diagnose wad user domain-controller dns list	1789
diagnose wad user domain-controller dns test	1789
diagnose wad user exchange	1789
diagnose wad user exchange get-matches	1790
diagnose wad user exchange query-rows	1790
diagnose wad user exchange reset	1790
diagnose wad user exchange resolve-names	1790
diagnose wad user exchange test-auto-discover	1790
diagnose wad user filter	1790
diagnose wad user list	1791
diagnose wad webcache	1791
diagnose wad webcache clear	1791
diagnose wad webcache list	1791
diagnose wad webproxy	1791
diagnose wad webproxy clear	1792
diagnose wad webproxy forward-server	1792
diagnose wad webproxy forward-server detail	1792
diagnose wad webproxy forward-server summary	1792
diagnose wad webproxy forward-server-group	1792
diagnose wad webproxy list	1792
diagnose wad worker	1793
diagnose wad worker avscan	1793
diagnose wad worker avscan clear	1793
diagnose wad worker avscan list	1793
diagnose wad worker bytcache	1793
diagnose wad worker bytcache clear	1793
diagnose wad worker bytcache flush	1794
diagnose wad worker bytcache stats	1794
diagnose wad worker cookie	1794
diagnose wad worker cookie map	1794
diagnose wad worker filter	1794
diagnose wad worker filter clear	1795
diagnose wad worker filter list	1795

diagnose wad worker imagecache	1795
diagnose wad worker imagecache flush	1795
diagnose wad worker imagecache stats	1795
diagnose wad worker memcache	1795
diagnose wad worker memcache clear	1796
diagnose wad worker memcache flush	1796
diagnose wad worker memcache stats	1796
diagnose wad worker peer	1796
diagnose wad worker peer clear	1796
diagnose wad worker peer list	1797
diagnose wad worker policy	1797
diagnose wad worker policy clear	1797
diagnose wad worker policy list	1797
diagnose wad worker restart	1797
diagnose wad worker scripts	1797
diagnose wad worker scripts clear	1798
diagnose wad worker scripts list	1798
diagnose wad worker webcache	1798
diagnose wad worker webcache clear	1798
diagnose wad worker webcache flush	1798
diagnose wad worker webcache stats	1799
diagnose wad worker webcache summary	1799
diagnose wadbd	1799
diagnose wadbd clear	1799
diagnose wadbd log-show	1799
diagnose wadbd restart	1800
diagnose wadbd stats	1800
diagnose waf	1800
diagnose waf dump	1800
diagnose waf info	1800
diagnose webfilter	1801
diagnose webfilter bword	1801
diagnose webfilter bword matchfilter	1801
diagnose webfilter fortiguard	1802
diagnose webfilter fortiguard cache	1802
diagnose webfilter fortiguard cache dump	1802
diagnose webfilter fortiguard cache obs	1802
diagnose webfilter fortiguard cache prefix	1802
diagnose webfilter fortiguard cache tree	1802
diagnose webfilter fortiguard cache ttl	1803
diagnose webfilter fortiguard override	1803
diagnose webfilter fortiguard override all-admin-override	1803
diagnose webfilter fortiguard override all-user-override	1803
diagnose webfilter fortiguard override all-warning	1803
diagnose webfilter fortiguard override obs	1803
diagnose webfilter fortiguard override statistics	1804
diagnose webfilter fortiguard statistics	1804
diagnose webfilter fortiguard statistics flush	1804
diagnose webfilter fortiguard statistics list	1804

diagnose web-ui	1804
diagnose web-ui api-cache	1805
diagnose web-ui api-cache statistic	1805
diagnose web-ui api-stats	1805
diagnose web-ui api-stats disable	1805
diagnose web-ui api-stats enable	1805
diagnose web-ui api-stats list	1805
diagnose web-ui api-stats reset	1806
diagnose web-ui api-stats status	1806
diagnose web-ui backtrace	1806
diagnose web-ui backtrace clear	1806
diagnose web-ui backtrace disable	1806
diagnose web-ui backtrace enable	1806
diagnose web-ui backtrace httpsd	1807
diagnose web-ui backtrace status	1807
CLI execute commands	1808
execute api-user	1810
execute api-user generate-key	1810
execute auto-script	1810
execute auto-script backup ftp	1811
execute auto-script backup tftp	1811
execute auto-script delete	1811
execute auto-script result	1812
execute auto-script start	1812
execute auto-script status	1812
execute auto-script stop	1812
execute auto-script stopall	1813
execute backup	1813
execute backup config flash	1814
execute backup config ftp	1814
execute backup config management-station	1815
execute backup config sftp	1815
execute backup config tftp	1815
execute backup config usb	1816
execute backup config usb-mode	1816
execute backup disk alllogs ftp	1816
execute backup disk alllogs tftp	1816
execute backup disk alllogs usb	1817
execute backup disk ipsarchives ftp	1817
execute backup disk ipsarchives tftp	1817
execute backup disk ipsarchives usb	1817
execute backup disk log ftp	1818
execute backup disk log tftp	1818
execute backup disk log usb	1818
execute backup full-config ftp	1819
execute backup full-config sftp	1819
execute backup full-config tftp	1819
execute backup full-config usb	1820
execute backup full-config usb-mode	1820

execute backup ipsuserdefsig ftp	1820
execute backup ipsuserdefsig tftp	1821
execute backup memory alllogs ftp	1821
execute backup memory alllogs tftp	1821
execute backup memory log ftp	1821
execute backup memory log tftp	1822
execute backup obfuscated-config ftp	1822
execute backup obfuscated-config management-station	1823
execute backup obfuscated-config sftp	1823
execute backup obfuscated-config tftp	1823
execute backup obfuscated-config usb	1824
execute backup obfuscated-full-config ftp	1824
execute backup obfuscated-full-config sftp	1824
execute backup obfuscated-full-config tftp	1825
execute backup obfuscated-full-config usb	1825
execute backup obfuscated-yaml-config ftp	1825
execute backup obfuscated-yaml-config tftp	1826
execute backup tls-finger-print tftp	1826
execute backup yaml-config ftp	1826
execute backup yaml-config tftp	1827
execute batch	1827
execute batch end	1827
execute batch lastlog	1828
execute batch start	1828
execute batch status	1828
execute central-mgmt	1828
execute central-mgmt register-device	1828
execute central-mgmt set-mgmt-id	1829
execute central-mgmt unregister-device	1829
execute cfg	1829
execute cfg reload	1829
execute cfg save	1830
execute clear	1830
execute clear system arp table	1830
execute cli	1830
execute cli check-template-status	1830
execute cli status-msg-only	1831
execute config-transaction	1831
execute config-transaction abort	1831
execute config-transaction commit	1831
execute config-transaction start	1831
execute cpu	1832
execute cpu add	1832
execute cpu show	1832
execute date	1832
execute device-upgrade	1833
execute device-upgrade cancel	1833
execute device-upgrade immediate	1833

execute dhcp	1833
execute dhcp lease-clear	1834
execute dhcp lease-list	1834
execute dhcp6	1834
execute dhcp6 lease-clear	1835
execute dhcp6 lease-list	1835
execute disconnect-admin-session	1835
execute disk	1835
execute disk format	1836
execute disk list	1836
execute disk scan	1836
execute enter	1836
execute erase-disk	1836
execute fabric-vpn	1837
execute fabric-vpn flush-setup	1837
execute fabric-vpn update-setup	1837
execute factoryreset	1837
execute factoryreset2	1837
execute factoryreset-for-central-management	1838
execute factoryreset-shutdown	1838
execute fctems	1838
execute fctems is-verified	1839
execute fctems unverify	1839
execute fctems verify	1839
execute federated-upgrade	1839
execute federated-upgrade cancel	1840
execute federated-upgrade initialize	1840
execute federated-upgrade quick-fortigate-upgrade	1840
execute federated-upgrade quick-full-upgrade	1840
execute federated-upgrade restart	1841
execute federated-upgrade status	1841
execute firewall	1841
execute firewall ssh generate local-ca	1841
execute firewall ssh generate local-key	1842
execute formatlogdisk	1842
execute forticloud-sandbox	1842
execute forticloud-sandbox region	1842
execute forticloud-sandbox update	1842
execute fortiguard-log	1843
execute fortiguard-log certificate-activation	1843
execute fortiguard-log migration	1843
execute fortiguard-log update	1843
execute fortiguard-message	1844
execute fortiguard-message add	1844
execute fortiguard-message info	1844
execute fortiguard-message update	1844
execute fortitoken	1844

execute fortitoken activate	1845
execute fortitoken import ftp	1846
execute fortitoken import tftp	1846
execute fortitoken import usb	1846
execute fortitoken import-sn-file	1846
execute fortitoken sync	1847
execute fortitoken-cloud	1847
execute fortitoken-cloud migrate-ftm	1847
execute fortitoken-cloud new	1848
execute fortitoken-cloud show	1848
execute fortitoken-cloud sync	1848
execute fortitoken-cloud trial	1848
execute fortitoken-cloud update	1848
execute fortitoken-mobile	1849
execute fortitoken-mobile import	1849
execute fortitoken-mobile poll	1849
execute fortitoken-mobile provision	1849
execute fortitoken-mobile renew	1849
execute fsso	1850
execute fsso refresh	1850
execute ha	1850
execute ha disconnect	1850
execute ha failover set	1851
execute ha failover status	1851
execute ha failover unset	1851
execute ha manage	1852
execute ha synchronize	1852
execute http-view	1852
execute http-view report	1852
execute interface	1853
execute interface dhcp6client-renew	1853
execute interface dhcpclient-renew	1853
execute interface pppoe-reconnect	1853
execute internet-service4	1854
execute internet-service4 refresh	1854
execute internet-service6	1854
execute internet-service6 refresh	1854
execute ipam	1854
execute ipam create-dhcp-server	1854
execute log	1855
execute log backup ftp	1856
execute log backup local	1856
execute log backup tftp	1856
execute log delete	1857
execute log delete-all	1857
execute log detail	1857
execute log display	1857
execute log filter category	1857

execute log filter device	1858
execute log filter dump	1858
execute log filter field	1858
execute log filter free-style	1859
execute log filter ha-member	1859
execute log filter local-search-mode	1859
execute log filter max-checklines	1859
execute log filter pre-fetch-pages	1859
execute log filter reset	1860
execute log filter start-line	1860
execute log filter view-lines	1860
execute log flush-cache	1860
execute log flush-cache-all	1861
execute log fortianalyzer manual-failover	1861
execute log fortianalyzer test-connectivity	1861
execute log fortianalyzer-cloud test-connectivity	1861
execute log fortianalyzer2 manual-failover	1861
execute log fortianalyzer3 manual-failover	1861
execute log fortiguard test-connectivity	1862
execute log list	1862
execute log raw-backup ftp	1862
execute log raw-backup tftp	1862
execute log roll	1863
execute log upload	1863
execute log upload-progress	1863
execute mem	1863
execute mem add	1863
execute nethsm	1863
execute nethsm primus clear-pkcs-provider-log	1864
execute nethsm primus clear-primus-log	1864
execute nethsm primus delete-object	1865
execute nethsm primus dump-pkcs-provider-log	1865
execute nethsm primus dump-primus-log	1865
execute nethsm primus inspect-primus-library-info	1865
execute nethsm primus list-objects	1865
execute nethsm primus upload-primus-cfg	1865
execute nethsm primus upload-primus-cfg-raw	1866
execute nethsm safenet clear-log	1866
execute nethsm safenet client-cert-create	1866
execute nethsm safenet client-cert-export ftp	1867
execute nethsm safenet client-cert-export tftp	1867
execute nethsm safenet client-cert-show	1867
execute nethsm safenet config-export ftp	1867
execute nethsm safenet config-export tftp	1868
execute nethsm safenet config-import ftp	1868
execute nethsm safenet config-import tftp	1868
execute nethsm safenet config-show	1869
execute nethsm safenet diagnose	1869
execute nethsm safenet hagroup-add	1869

execute nethsm safenet hagroup-del	1869
execute nethsm safenet hagroup-list	1869
execute nethsm safenet register	1870
execute nethsm safenet reset	1870
execute nethsm safenet restore-conf	1870
execute nethsm safenet set-conf-opt	1870
execute nethsm safenet show-log	1870
execute nethsm safenet status	1870
execute nethsm safenet unregister	1871
execute nsx	1871
execute nsx group delete	1871
execute nsx group import	1871
execute nsx group list	1872
execute ping	1872
execute ping6	1872
execute ping6-options	1872
execute ping6-options adaptive-ping	1873
execute ping6-options data-size	1873
execute ping6-options interface	1873
execute ping6-options interval	1874
execute ping6-options pattern	1874
execute ping6-options repeat-count	1874
execute ping6-options reset	1874
execute ping6-options source6	1875
execute ping6-options timeout	1875
execute ping6-options tos	1875
execute ping6-options ttl	1875
execute ping6-options validate-reply	1876
execute ping6-options view-settings	1876
execute ping-options	1876
execute ping-options adaptive-ping	1876
execute ping-options data-size	1877
execute ping-options df-bit	1877
execute ping-options interface	1877
execute ping-options interval	1877
execute ping-options pattern	1878
execute ping-options repeat-count	1878
execute ping-options reset	1878
execute ping-options source	1878
execute ping-options timeout	1879
execute ping-options tos	1879
execute ping-options ttl	1879
execute ping-options use-sdwan	1879
execute ping-options validate-reply	1880
execute ping-options view-settings	1880
execute policy-packet-capture	1880
execute policy-packet-capture delete-all	1880
execute preload	1880

execute preload http-transaction-log disable	1881
execute preload http-transaction-log enable	1881
execute preload list	1881
execute preload show-log	1881
execute preload url	1881
execute preload url-delete	1882
execute private-encryption-key	1882
execute private-encryption-key sample	1882
execute private-encryption-key verify	1882
execute reboot	1883
execute report	1883
execute report flush-cache	1883
execute report recreate-db	1883
execute report run	1884
execute report-config	1884
execute report-config reset	1884
execute restore	1884
execute restore av ftp	1885
execute restore av tftp	1886
execute restore config dhcp	1886
execute restore config flash	1886
execute restore config ftp	1886
execute restore config management-station normal	1887
execute restore config management-station script	1887
execute restore config management-station template	1887
execute restore config tftp	1888
execute restore config usb	1888
execute restore config usb-mode	1888
execute restore image flash	1888
execute restore image ftp	1889
execute restore image management-station	1889
execute restore image tftp	1889
execute restore image url	1889
execute restore image usb	1890
execute restore ips ftp	1890
execute restore ips tftp	1890
execute restore ipsuserdefsig ftp	1891
execute restore ipsuserdefsig tftp	1891
execute restore manual-license ftp	1891
execute restore manual-license tftp	1892
execute restore other-objects ftp	1892
execute restore other-objects tftp	1892
execute restore script ftp	1893
execute restore script lastlog	1893
execute restore script scp	1893
execute restore script tftp	1893
execute restore tls-finger-print tftp	1894
execute restore vmlicense ftp	1894
execute restore vmlicense tftp	1894

execute revision	1895
execute revision delete config	1895
execute revision delete image	1895
execute revision list config	1895
execute revision list image	1896
execute send-fds-statistics	1896
execute send-fmg-list	1896
execute set	1896
execute set system session filter clear all	1897
execute set system session filter clear dport	1897
execute set system session filter clear dst	1897
execute set system session filter clear duration	1897
execute set system session filter clear expire	1898
execute set system session filter clear policy	1898
execute set system session filter clear proto	1898
execute set system session filter clear sport	1898
execute set system session filter clear src	1898
execute set system session filter clear vd	1898
execute set system session filter dport	1899
execute set system session filter dst	1899
execute set system session filter duration	1899
execute set system session filter expire	1899
execute set system session filter list	1900
execute set system session filter negate dport	1900
execute set system session filter negate dst	1900
execute set system session filter negate duration	1900
execute set system session filter negate expire	1900
execute set system session filter negate policy	1900
execute set system session filter negate proto	1901
execute set system session filter negate sport	1901
execute set system session filter negate src	1901
execute set system session filter negate vd	1901
execute set system session filter policy	1901
execute set system session filter proto	1902
execute set system session filter sport	1902
execute set system session filter src	1902
execute set system session filter vd	1902
execute shutdown	1903
execute speed-test	1903
execute speed-test-dynamic	1903
execute speed-test-server	1904
execute speed-test-server download	1904
execute speed-test-server list	1904
execute ssh	1904
execute ssh6	1904
execute ssh6-options	1905
execute ssh6-options interface	1905
execute ssh6-options reset	1905

execute ssh6-options source6	1905
execute ssh6-options view-settings	1906
execute ssh-options	1906
execute ssh-options interface	1906
execute ssh-options reset	1906
execute ssh-options source	1906
execute ssh-options view-settings	1907
execute ssh-regen-keys	1907
execute sync-IPSec	1907
execute sync-session	1907
execute system	1907
execute system custom-language import	1908
execute system fortisandbox test-alternative-connectivity	1908
execute system fortisandbox test-primary-connectivity	1908
execute tac	1908
execute tac report	1909
execute telnet	1909
execute telnet-options	1909
execute telnet-options interface	1909
execute telnet-options reset	1910
execute telnet-options source	1910
execute telnet-options view-settings	1910
execute time	1910
execute traceroute	1910
execute traceroute-options	1911
execute traceroute-options device	1911
execute traceroute-options queries	1911
execute traceroute-options source	1911
execute traceroute-options use-sdwan	1912
execute traceroute-options view-settings	1912
execute tracert6	1912
execute update-av	1912
execute update-external-resource	1912
execute update-ffdb-on-demand	1913
execute update-geo-ip	1913
execute update-ips	1913
execute update-list	1913
execute update-now	1913
execute update-src-vis	1914
execute upd-vd-license	1914
execute upload	1914
execute upload config ftp	1915
execute upload config tftp	1915
execute upload config usb	1915
execute upload fortinbi-installer cloud	1916
execute upload fortinbi-installer tftp	1916
execute upload fortinbi-isolator-image cloud	1916

execute upload fortinbi-isolator-image tftp	1916
execute upload image ftp	1916
execute upload image tftp	1917
execute upload image usb	1917
execute upload report-img ftp	1917
execute upload report-img tftp	1918
execute usb-device	1918
execute usb-device disconnect	1918
execute usb-device list	1919
execute usb-device modeswitch	1919
execute usb-disk	1919
execute usb-disk delete	1919
execute usb-disk eject	1920
execute usb-disk format	1920
execute usb-disk list	1920
execute usb-disk rename	1920
execute vm-license	1920
execute vm-license-options	1921
execute vm-license-options account-id	1921
execute vm-license-options account-password	1921
execute vm-license-options count	1921
execute vm-license-options government	1922
execute vm-license-options interval	1922
execute vm-license-options proxy	1922
execute vm-license-options reset	1922
execute vm-license-options show	1923
execute vm-license-options token	1923
execute vpn	1923
execute vpn certificate ca export tftp	1924
execute vpn certificate ca import auto	1924
execute vpn certificate ca import bundle	1924
execute vpn certificate ca import tftp	1925
execute vpn certificate crl import auto	1925
execute vpn certificate ems_ca import tftp	1925
execute vpn certificate hsm primus generate ec	1925
execute vpn certificate hsm primus generate rsa	1926
execute vpn certificate hsm primus load-key	1927
execute vpn certificate hsm safenet generate rsa	1928
execute vpn certificate local export tftp	1928
execute vpn certificate local generate cmp	1929
execute vpn certificate local generate default-gui-mgmt-cert	1929
execute vpn certificate local generate default-ssl-ca	1930
execute vpn certificate local generate default-ssl-ca-untrusted	1930
execute vpn certificate local generate default-ssl-key-certs	1930
execute vpn certificate local generate default-ssl-serv-key	1930
execute vpn certificate local generate ec	1930
execute vpn certificate local generate rsa	1931
execute vpn certificate local import tftp	1932
execute vpn certificate local verify	1932

execute vpn certificate remote export tftp	1933
execute vpn certificate remote import tftp	1933
execute vpn ipsec tunnel down	1933
execute vpn ipsec tunnel up	1933
execute wake-on-lan	1934
execute webcache	1934
execute webcache delete regular-expression	1934
execute webcache delete simple-string	1935
execute webcache delete status	1935
execute webcache delete wildcard	1935
execute webfilter	1935
execute webfilter quota-reset	1936

Change log

Date	Change Description
2025-08-25	Initial release.

FortiProxy CLI Interface

This document describes FortiProxy 7.4.11 CLI commands that are used to configure and manage FortiProxy from the command line interface (CLI). For information on using the CLI, see the [FortiProxy 7.4.11 Administration Guide](#).

CLI configuration commands

Use configuration commands to configure and manage a FortiProxy unit from the command line interface (CLI).

The CLI syntax is created by processing the schema from FortiProxy models running FortiProxy 7.4.11 and reformatting the resultant CLI output. If you have comments on this content, its format, or requests for commands that are not included, contact us at techdoc@fortinet.com.

alertemail

This section includes syntax for the following commands:

- [config alertemail setting on page 67](#)

config alertemail setting

Configure alert email settings.

```
config alertemail setting
  Description: Configure alert email settings.
  set username {string}
  set mailto1 {string}
  set mailto2 {string}
  set mailto3 {string}
  set filter-mode [category|threshold]
  set email-interval {integer}
  set IPS-logs [enable|disable]
  set firewall-authentication-failure-logs [enable|disable]
  set HA-logs [enable|disable]
  set IPsec-errors-logs [enable|disable]
  set FDS-update-logs [enable|disable]
  set PPP-errors-logs [enable|disable]
  set antivirus-logs [enable|disable]
  set webfilter-logs [enable|disable]
  set configuration-changes-logs [enable|disable]
  set violation-traffic-logs [enable|disable]
  set admin-login-logs [enable|disable]
  set FDS-license-expiring-warning [enable|disable]
  set log-disk-usage-warning [enable|disable]
  set fortiguard-log-quota-warning [enable|disable]
  set amc-interface-bypass-mode [enable|disable]
  set FIPS-CC-errors [enable|disable]
  set FSSO-disconnect-logs [enable|disable]
  set ssh-logs [enable|disable]
  set fpx-license-logs [enable|disable]
  set FDS-license-expiring-days {integer}
  set local-disk-usage {integer}
  set emergency-interval {integer}
  set alert-interval {integer}
  set critical-interval {integer}
  set error-interval {integer}
  set warning-interval {integer}
  set notification-interval {integer}
  set information-interval {integer}
```

```

set debug-interval {integer}
set severity [emergency|alert|...]
end

```

config alertemail setting

Parameter	Description	Type	Size	Default						
username	Name that appears in the From: field of alert emails (max. 63 characters).	string	Maximum length: 63							
mailto1	Email address to send alert email to (usually a system administrator) (max. 63 characters).	string	Maximum length: 63							
mailto2	Optional second email address to send alert email to (max. 63 characters).	string	Maximum length: 63							
mailto3	Optional third email address to send alert email to (max. 63 characters).	string	Maximum length: 63							
filter-mode	How to filter log messages that are sent to alert emails.	option	-	category						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>category</i></td><td>Filter based on category.</td></tr><tr><td><i>threshold</i></td><td>Filter based on severity.</td></tr></table>				Option	Description	<i>category</i>	Filter based on category.	<i>threshold</i>	Filter based on severity.
Option	Description									
<i>category</i>	Filter based on category.									
<i>threshold</i>	Filter based on severity.									
email-interval	Interval between sending alert emails (1 - 99999 min, default = 5).	integer	Minimum value: 1 Maximum value: 99999	5						
IPS-logs	Enable/disable IPS logs in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable IPS logs in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable IPS logs in alert email.</td></tr></table>				Option	Description	<i>enable</i>	Enable IPS logs in alert email.	<i>disable</i>	Disable IPS logs in alert email.
Option	Description									
<i>enable</i>	Enable IPS logs in alert email.									
<i>disable</i>	Disable IPS logs in alert email.									
firewall-authentication-failure-logs	Enable/disable firewall authentication failure logs in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable firewall authentication failure logs in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable firewall authentication failure logs in alert email.</td></tr></table>				Option	Description	<i>enable</i>	Enable firewall authentication failure logs in alert email.	<i>disable</i>	Disable firewall authentication failure logs in alert email.
Option	Description									
<i>enable</i>	Enable firewall authentication failure logs in alert email.									
<i>disable</i>	Disable firewall authentication failure logs in alert email.									

Parameter	Description	Type	Size	Default						
HA-logs	Enable/disable HA logs in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable HA logs in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable HA logs in alert email.</td></tr></table>	Option	Description	<i>enable</i>	Enable HA logs in alert email.	<i>disable</i>	Disable HA logs in alert email.			
Option	Description									
<i>enable</i>	Enable HA logs in alert email.									
<i>disable</i>	Disable HA logs in alert email.									
IPsec-errors-logs	Enable/disable IPsec error logs in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable IPsec error logs in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable IPsec error logs in alert email.</td></tr></table>	Option	Description	<i>enable</i>	Enable IPsec error logs in alert email.	<i>disable</i>	Disable IPsec error logs in alert email.			
Option	Description									
<i>enable</i>	Enable IPsec error logs in alert email.									
<i>disable</i>	Disable IPsec error logs in alert email.									
FDS-update-logs	Enable/disable FortiGuard update logs in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable FortiGuard update logs in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable FortiGuard update logs in alert email.</td></tr></table>	Option	Description	<i>enable</i>	Enable FortiGuard update logs in alert email.	<i>disable</i>	Disable FortiGuard update logs in alert email.			
Option	Description									
<i>enable</i>	Enable FortiGuard update logs in alert email.									
<i>disable</i>	Disable FortiGuard update logs in alert email.									
PPP-errors-logs	Enable/disable PPP error logs in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable PPP error logs in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable PPP error logs in alert email.</td></tr></table>	Option	Description	<i>enable</i>	Enable PPP error logs in alert email.	<i>disable</i>	Disable PPP error logs in alert email.			
Option	Description									
<i>enable</i>	Enable PPP error logs in alert email.									
<i>disable</i>	Disable PPP error logs in alert email.									
antivirus-logs	Enable/disable antivirus logs in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable antivirus logs in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable antivirus logs in alert email.</td></tr></table>	Option	Description	<i>enable</i>	Enable antivirus logs in alert email.	<i>disable</i>	Disable antivirus logs in alert email.			
Option	Description									
<i>enable</i>	Enable antivirus logs in alert email.									
<i>disable</i>	Disable antivirus logs in alert email.									
webfilter-logs	Enable/disable web filter logs in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable web filter logs in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable web filter logs in alert email.</td></tr></table>	Option	Description	<i>enable</i>	Enable web filter logs in alert email.	<i>disable</i>	Disable web filter logs in alert email.			
Option	Description									
<i>enable</i>	Enable web filter logs in alert email.									
<i>disable</i>	Disable web filter logs in alert email.									

Parameter	Description	Type	Size	Default						
configuration-changes-logs	Enable/disable configuration change logs in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable configuration change logs in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable configuration change logs in alert email.</td></tr></table>	Option	Description	<i>enable</i>	Enable configuration change logs in alert email.	<i>disable</i>	Disable configuration change logs in alert email.			
Option	Description									
<i>enable</i>	Enable configuration change logs in alert email.									
<i>disable</i>	Disable configuration change logs in alert email.									
violation-traffic-logs	Enable/disable violation traffic logs in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable violation traffic logs in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable violation traffic logs in alert email.</td></tr></table>	Option	Description	<i>enable</i>	Enable violation traffic logs in alert email.	<i>disable</i>	Disable violation traffic logs in alert email.			
Option	Description									
<i>enable</i>	Enable violation traffic logs in alert email.									
<i>disable</i>	Disable violation traffic logs in alert email.									
admin-login-logs	Enable/disable administrator login/logout logs in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable administrator login/logout logs in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable administrator login/logout logs in alert email.</td></tr></table>	Option	Description	<i>enable</i>	Enable administrator login/logout logs in alert email.	<i>disable</i>	Disable administrator login/logout logs in alert email.			
Option	Description									
<i>enable</i>	Enable administrator login/logout logs in alert email.									
<i>disable</i>	Disable administrator login/logout logs in alert email.									
FDS-license-expiring-warning	Enable/disable FortiGuard license expiration warnings in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable FortiGuard license expiration warnings in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable FortiGuard license expiration warnings in alert email.</td></tr></table>	Option	Description	<i>enable</i>	Enable FortiGuard license expiration warnings in alert email.	<i>disable</i>	Disable FortiGuard license expiration warnings in alert email.			
Option	Description									
<i>enable</i>	Enable FortiGuard license expiration warnings in alert email.									
<i>disable</i>	Disable FortiGuard license expiration warnings in alert email.									
log-disk-usage-warning	Enable/disable disk usage warnings in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable disk usage warnings in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable disk usage warnings in alert email.</td></tr></table>	Option	Description	<i>enable</i>	Enable disk usage warnings in alert email.	<i>disable</i>	Disable disk usage warnings in alert email.			
Option	Description									
<i>enable</i>	Enable disk usage warnings in alert email.									
<i>disable</i>	Disable disk usage warnings in alert email.									
fortiguard-log-quota-warning	Enable/disable FortiCloud log quota warnings in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable FortiCloud log quota warnings in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable FortiCloud log quota warnings in alert email.</td></tr></table>	Option	Description	<i>enable</i>	Enable FortiCloud log quota warnings in alert email.	<i>disable</i>	Disable FortiCloud log quota warnings in alert email.			
Option	Description									
<i>enable</i>	Enable FortiCloud log quota warnings in alert email.									
<i>disable</i>	Disable FortiCloud log quota warnings in alert email.									

Parameter	Description	Type	Size	Default						
amc-interface-bypass-mode	Enable/disable Fortinet Advanced Mezzanine Card (AMC) interface bypass mode logs in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable Fortinet Advanced Mezzanine Card (AMC) interface bypass mode logs in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable Fortinet Advanced Mezzanine Card (AMC) interface bypass mode logs in alert email.</td></tr></table>	Option	Description	<i>enable</i>	Enable Fortinet Advanced Mezzanine Card (AMC) interface bypass mode logs in alert email.	<i>disable</i>	Disable Fortinet Advanced Mezzanine Card (AMC) interface bypass mode logs in alert email.			
Option	Description									
<i>enable</i>	Enable Fortinet Advanced Mezzanine Card (AMC) interface bypass mode logs in alert email.									
<i>disable</i>	Disable Fortinet Advanced Mezzanine Card (AMC) interface bypass mode logs in alert email.									
FIPS-CC-errors	Enable/disable FIPS and Common Criteria error logs in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable FIPS and Common Criteria error logs in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable FIPS and Common Criteria error logs in alert email.</td></tr></table>	Option	Description	<i>enable</i>	Enable FIPS and Common Criteria error logs in alert email.	<i>disable</i>	Disable FIPS and Common Criteria error logs in alert email.			
Option	Description									
<i>enable</i>	Enable FIPS and Common Criteria error logs in alert email.									
<i>disable</i>	Disable FIPS and Common Criteria error logs in alert email.									
FSSO-disconnect-logs	Enable/disable logging of FSSO collector agent disconnect.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable logging of FSSO collector agent disconnect.</td></tr><tr><td><i>disable</i></td><td>Disable logging of FSSO collector agent disconnect.</td></tr></table>	Option	Description	<i>enable</i>	Enable logging of FSSO collector agent disconnect.	<i>disable</i>	Disable logging of FSSO collector agent disconnect.			
Option	Description									
<i>enable</i>	Enable logging of FSSO collector agent disconnect.									
<i>disable</i>	Disable logging of FSSO collector agent disconnect.									
ssh-logs	Enable/disable SSH logs in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable SSH logs in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable SSH logs in alert email.</td></tr></table>	Option	Description	<i>enable</i>	Enable SSH logs in alert email.	<i>disable</i>	Disable SSH logs in alert email.			
Option	Description									
<i>enable</i>	Enable SSH logs in alert email.									
<i>disable</i>	Disable SSH logs in alert email.									
fpx-license-logs	Enable/disable FortiProxy license related logs in alert email.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable FortiProxy license related warnings in alert email.</td></tr><tr><td><i>disable</i></td><td>Disable FortiProxy license related warnings in alert email.</td></tr></table>	Option	Description	<i>enable</i>	Enable FortiProxy license related warnings in alert email.	<i>disable</i>	Disable FortiProxy license related warnings in alert email.			
Option	Description									
<i>enable</i>	Enable FortiProxy license related warnings in alert email.									
<i>disable</i>	Disable FortiProxy license related warnings in alert email.									
FDS-license-expiring-days	Number of days to send alert email prior to FortiGuard license expiration (1 - 100 days, default = 15).	integer	Minimum value: 1 Maximum value: 100	15						

Parameter	Description	Type	Size	Default
local-disk-usage	Disk usage percentage at which to send alert email (1 - 99 percent, default = 75).	integer	Minimum value: 1 Maximum value: 99	75
emergency-interval	Emergency alert interval in minutes.	integer	Minimum value: 1 Maximum value: 99999	1
alert-interval	Alert alert interval in minutes.	integer	Minimum value: 1 Maximum value: 99999	2
critical-interval	Critical alert interval in minutes.	integer	Minimum value: 1 Maximum value: 99999	3
error-interval	Error alert interval in minutes.	integer	Minimum value: 1 Maximum value: 99999	5
warning-interval	Warning alert interval in minutes.	integer	Minimum value: 1 Maximum value: 99999	10
notification-interval	Notification alert interval in minutes.	integer	Minimum value: 1 Maximum value: 99999	20
information-interval	Information alert interval in minutes.	integer	Minimum value: 1 Maximum value: 99999	30

Parameter	Description	Type	Size	Default
debug-interval	Debug alert interval in minutes.	integer	Minimum value: 1 Maximum value: 99999	60
severity	Lowest severity level to log.	option	-	alert
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		

antivirus

This section includes syntax for the following commands:

- [config antivirus exempt-list on page 74](#)
- [config antivirus profile on page 75](#)
- [config antivirus quarantine on page 106](#)
- [config antivirus settings on page 111](#)

config antivirus exempt-list

Configure a list of hashes to be exempt from AV scanning.

```
config antivirus exempt-list
  Description: Configure a list of hashes to be exempt from AV scanning.
  edit <name>
    set comment {var-string}
    set hash-type [md5|sha1|...]
    set hash {string}
    set status [disable|enable]
  next
end
```

config antivirus exempt-list

Parameter	Description	Type	Size	Default								
name	Table entry name.	string	Maximum length: 35									
comment	Comment.	var-string	Maximum length: 255									
hash-type	Hash type.	option	-	sha1								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>md5</i></td><td>MD5 hash value (32 characters in length).</td></tr><tr><td><i>sha1</i></td><td>SHA1 hash value (40 characters in length).</td></tr><tr><td><i>sha256</i></td><td>SHA256 hash value (64 characters in length).</td></tr></table>				Option	Description	<i>md5</i>	MD5 hash value (32 characters in length).	<i>sha1</i>	SHA1 hash value (40 characters in length).	<i>sha256</i>	SHA256 hash value (64 characters in length).
	Option	Description										
	<i>md5</i>	MD5 hash value (32 characters in length).										
	<i>sha1</i>	SHA1 hash value (40 characters in length).										
<i>sha256</i>	SHA256 hash value (64 characters in length).											
hash	Hash value to be matched.	string	Maximum length: 64									

Parameter	Description	Type	Size	Default
status	Enable/disable table entry.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable AV exempt-list table entry.		
	<i>enable</i>	Enable AV exempt-list table entry.		

config antivirus profile

Configure AntiVirus profiles.

```

config antivirus profile
  Description: Configure AntiVirus profiles.
  edit <name>
    set comment {var-string}
    set replacemsg-group {string}
    set fortisandbox-mode [inline|analytics-suspicious|...]
    set fortisandbox-max-upload {integer}
    set analytics-ignore-filetype {integer}
    set analytics-accept-filetype {integer}
    set analytics-db [disable|enable]
    set mobile-malware-db [disable|enable]
  config http
    Description: Configure HTTP AntiVirus options.
    set av-scan [disable|block|...]
    set outbreak-prevention [disable|block|...]
    set external-blocklist [disable|block|...]
    set fortindr [disable|block|...]
    set fortisandbox [disable|block|...]
    set quarantine [disable|enable]
    set archive-block {option1}, {option2}, ...
    set archive-log {option1}, {option2}, ...
    set emulator [enable|disable]
    set content-disarm [disable|enable]
  end
  config ftp
    Description: Configure FTP AntiVirus options.
    set av-scan [disable|block|...]
    set outbreak-prevention [disable|block|...]
    set external-blocklist [disable|block|...]
    set fortindr [disable|block|...]
    set fortisandbox [disable|block|...]
    set quarantine [disable|enable]
    set archive-block {option1}, {option2}, ...
    set archive-log {option1}, {option2}, ...
    set emulator [enable|disable]
  end
  config imap

```

```

Description: Configure IMAP AntiVirus options.
set av-scan [disable|block|...]
set outbreak-prevention [disable|block|...]
set external-blocklist [disable|block|...]
set fortindr [disable|block|...]
set fortisandbox [disable|block|...]
set quarantine [disable|enable]
set archive-block {option1}, {option2}, ...
set archive-log {option1}, {option2}, ...
set emulator [enable|disable]
set executables [default|virus]
set content-disarm [disable|enable]
end
config pop3
Description: Configure POP3 AntiVirus options.
set av-scan [disable|block|...]
set outbreak-prevention [disable|block|...]
set external-blocklist [disable|block|...]
set fortindr [disable|block|...]
set fortisandbox [disable|block|...]
set quarantine [disable|enable]
set archive-block {option1}, {option2}, ...
set archive-log {option1}, {option2}, ...
set emulator [enable|disable]
set executables [default|virus]
set content-disarm [disable|enable]
end
config smtp
Description: Configure SMTP AntiVirus options.
set av-scan [disable|block|...]
set outbreak-prevention [disable|block|...]
set external-blocklist [disable|block|...]
set fortindr [disable|block|...]
set fortisandbox [disable|block|...]
set quarantine [disable|enable]
set archive-block {option1}, {option2}, ...
set archive-log {option1}, {option2}, ...
set emulator [enable|disable]
set executables [default|virus]
set content-disarm [disable|enable]
end
config mapi
Description: Configure MAPI AntiVirus options.
set av-scan [disable|block|...]
set outbreak-prevention [disable|block|...]
set external-blocklist [disable|block|...]
set fortindr [disable|block|...]
set fortisandbox [disable|block|...]
set quarantine [disable|enable]
set archive-block {option1}, {option2}, ...
set archive-log {option1}, {option2}, ...
set emulator [enable|disable]

```

```

    set executables [default|virus]
end
config nntp
    Description: Configure NNTP AntiVirus options.
    set av-scan [disable|block|...]
    set outbreak-prevention [disable|block|...]
    set external-blocklist [disable|block|...]
    set fortindr [disable|block|...]
    set fortisandbox [disable|block|...]
    set quarantine [disable|enable]
    set archive-block {option1}, {option2}, ...
    set archive-log {option1}, {option2}, ...
    set emulator [enable|disable]
end
config cifs
    Description: Configure CIFS AntiVirus options.
    set av-scan [disable|block|...]
    set outbreak-prevention [disable|block|...]
    set external-blocklist [disable|block|...]
    set fortindr [disable|block|...]
    set fortisandbox [disable|block|...]
    set quarantine [disable|enable]
    set archive-block {option1}, {option2}, ...
    set archive-log {option1}, {option2}, ...
    set emulator [enable|disable]
end
config ssh
    Description: Configure SFTP and SCP AntiVirus options.
    set av-scan [disable|block|...]
    set outbreak-prevention [disable|block|...]
    set external-blocklist [disable|block|...]
    set fortindr [disable|block|...]
    set fortisandbox [disable|block|...]
    set quarantine [disable|enable]
    set archive-block {option1}, {option2}, ...
    set archive-log {option1}, {option2}, ...
    set emulator [enable|disable]
end
config nac-quar
    Description: Configure AntiVirus quarantine settings.
    set infected [none|quar-src-ip]
    set expiry {user}
    set log [enable|disable]
end
config content-disarm
    Description: AV Content Disarm and Reconstruction settings.
    set original-file-destination [fortisandbox|quarantine|...]
    set error-action [block|log-only|...]
    set office-macro [disable|enable]
    set office-hylink [disable|enable]
    set office-linked [disable|enable]
    set office-embed [disable|enable]

```

```

set office-dde [disable|enable]
set office-action [disable|enable]
set pdf-javacode [disable|enable]
set pdf-embedfile [disable|enable]
set pdf-hyperlink [disable|enable]
set pdf-act-gotor [disable|enable]
set pdf-act-launch [disable|enable]
set pdf-act-sound [disable|enable]
set pdf-act-movie [disable|enable]
set pdf-act-java [disable|enable]
set pdf-act-form [disable|enable]
set cover-page [disable|enable]
set detect-only [disable|enable]
end
set outbreak-prevention-archive-scan [disable|enable]
set external-blocklist-enable-all [disable|enable]
set external-blocklist <name1>, <name2>, ...
set ems-threat-feed [disable|enable]
set fortindr-error-action [log-only|block|...]
set fortindr-timeout-action [log-only|block|...]
set fortisandbox-error-action [log-only|block|...]
set fortisandbox-timeout-action [log-only|block|...]
set av-virus-log [enable|disable]
set av-block-log [enable|disable]
set scan-mode [default|legacy]
next
end

```

config antivirus profile

Parameter	Description	Type	Size	Default
name	Profile name.	string	Maximum length: 35	
comment	Comment.	var-string	Maximum length: 255	
replacemsg-group	Replacement message group customized for this profile.	string	Maximum length: 35	
fortisandbox-mode	FortiSandbox scan modes.	option	-	analytics-everything
	Option	Description		
	<i>inline</i>	FortiSandbox inline scan.		
	<i>analytics-suspicious</i>	FortiSandbox post-transfer scan: submit supported files if heuristics or other methods determine they are suspicious.		

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>analytics-everything</i></td><td>FortiSandbox post-transfer scan: submit supported files and known infected files.</td></tr></table>	Option	Description	<i>analytics-everything</i>	FortiSandbox post-transfer scan: submit supported files and known infected files.					
Option	Description									
<i>analytics-everything</i>	FortiSandbox post-transfer scan: submit supported files and known infected files.									
fortisandbox-max-upload	Maximum size of files that can be uploaded to FortiSandbox.	integer	Minimum value: 1 Maximum value: 4095	10						
analytics-ignore-filetype	Do not submit files matching this DLP file-pattern to FortiSandbox (post-transfer scan only).	integer	Minimum value: 0 Maximum value: 4294967295	0						
analytics-accept-filetype	Only submit files matching this DLP file-pattern to FortiSandbox (post-transfer scan only).	integer	Minimum value: 0 Maximum value: 4294967295	0						
analytics-db	Enable/disable using the FortiSandbox signature database to supplement the AV signature databases.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Use only the standard AV signature databases.</td></tr><tr><td><i>enable</i></td><td>Also use the FortiSandbox signature database.</td></tr></table>	Option	Description	<i>disable</i>	Use only the standard AV signature databases.	<i>enable</i>	Also use the FortiSandbox signature database.			
Option	Description									
<i>disable</i>	Use only the standard AV signature databases.									
<i>enable</i>	Also use the FortiSandbox signature database.									
mobile-malware-db	Enable/disable using the mobile malware signature database.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not use the mobile malware signature database.</td></tr><tr><td><i>enable</i></td><td>Also use the mobile malware signature database.</td></tr></table>	Option	Description	<i>disable</i>	Do not use the mobile malware signature database.	<i>enable</i>	Also use the mobile malware signature database.			
Option	Description									
<i>disable</i>	Do not use the mobile malware signature database.									
<i>enable</i>	Also use the mobile malware signature database.									
outbreak-prevention-archive-scan	Enable/disable outbreak-prevention archive scanning.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Analyze files as sent, not the content of archives.</td></tr><tr><td><i>enable</i></td><td>Analyze files including the content of archives.</td></tr></table>	Option	Description	<i>disable</i>	Analyze files as sent, not the content of archives.	<i>enable</i>	Analyze files including the content of archives.			
Option	Description									
<i>disable</i>	Analyze files as sent, not the content of archives.									
<i>enable</i>	Analyze files including the content of archives.									

Parameter	Description	Type	Size	Default								
external-blocklist-enable-all	Enable/disable all external blocklists.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Use configured external blocklists.</td></tr><tr><td><i>enable</i></td><td>Enable all external blocklists.</td></tr></table>	Option	Description	<i>disable</i>	Use configured external blocklists.	<i>enable</i>	Enable all external blocklists.					
Option	Description											
<i>disable</i>	Use configured external blocklists.											
<i>enable</i>	Enable all external blocklists.											
external-blocklist <name>	One or more external malware block lists. External blocklist.	string	Maximum length: 79									
ems-threat-feed	Enable/disable use of EMS threat feed when performing AntiVirus scan. Analyzes files including the content of archives.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable use of EMS threat feed when performing AntiVirus scan.</td></tr><tr><td><i>enable</i></td><td>Enable use of EMS threat feed when performing AntiVirus scan.</td></tr></table>	Option	Description	<i>disable</i>	Disable use of EMS threat feed when performing AntiVirus scan.	<i>enable</i>	Enable use of EMS threat feed when performing AntiVirus scan.					
Option	Description											
<i>disable</i>	Disable use of EMS threat feed when performing AntiVirus scan.											
<i>enable</i>	Enable use of EMS threat feed when performing AntiVirus scan.											
fortindr-error-action	Action to take if FortiNDR encounters an error.	option	-	log-only								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>log-only</i></td><td>Log FortiNDR error, but allow the file.</td></tr><tr><td><i>block</i></td><td>Block the file on FortiNDR error.</td></tr><tr><td><i>ignore</i></td><td>Do nothing on FortiNDR error.</td></tr></table>	Option	Description	<i>log-only</i>	Log FortiNDR error, but allow the file.	<i>block</i>	Block the file on FortiNDR error.	<i>ignore</i>	Do nothing on FortiNDR error.			
Option	Description											
<i>log-only</i>	Log FortiNDR error, but allow the file.											
<i>block</i>	Block the file on FortiNDR error.											
<i>ignore</i>	Do nothing on FortiNDR error.											
fortindr-timeout-action	Action to take if FortiNDR encounters a scan timeout.	option	-	log-only								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>log-only</i></td><td>Log FortiNDR scan timeout, but allow the file.</td></tr><tr><td><i>block</i></td><td>Block the file on FortiNDR scan timeout.</td></tr><tr><td><i>ignore</i></td><td>Do nothing on FortiNDR scan timeout.</td></tr></table>	Option	Description	<i>log-only</i>	Log FortiNDR scan timeout, but allow the file.	<i>block</i>	Block the file on FortiNDR scan timeout.	<i>ignore</i>	Do nothing on FortiNDR scan timeout.			
Option	Description											
<i>log-only</i>	Log FortiNDR scan timeout, but allow the file.											
<i>block</i>	Block the file on FortiNDR scan timeout.											
<i>ignore</i>	Do nothing on FortiNDR scan timeout.											
fortisandbox-error-action	Action to take if FortiSandbox inline scan encounters an error.	option	-	log-only								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>log-only</i>	Log FortiSandbox inline scan error, but allow the file.		
	<i>block</i>	Block the file on FortiSandbox inline scan error.		
	<i>ignore</i>	Do nothing on FortiSandbox inline scan error.		
fortisandbox-timeout-action	Action to take if FortiSandbox inline scan encounters a scan timeout.	option	-	log-only
	Option	Description		
	<i>log-only</i>	Log FortiSandbox inline scan timeout, but allow the file.		
	<i>block</i>	Block the file on FortiSandbox inline scan timeout.		
	<i>ignore</i>	Do nothing on FortiSandbox inline scan timeout.		
av-virus-log	Enable/disable AntiVirus logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
av-block-log	Enable/disable logging for AntiVirus file blocking.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
scan-mode	Configure scan mode (default or legacy).	option	-	default
	Option	Description		
	<i>default</i>	On the fly decompression and scanning of certain archive files.		
	<i>legacy</i>	Scan archive files only after the entire file is received.		

config http

Parameter	Description	Type	Size	Default
av-scan	Enable AntiVirus scan service.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the virus infected files.		
	<i>monitor</i>	Log the virus infected files.		
outbreak-prevention	Enable virus outbreak prevention service.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the matched files.		
	<i>monitor</i>	Log the matched files.		
external-blocklist	Enable external-blocklist. Analyzes files including the content of archives.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the matched files.		
	<i>monitor</i>	Log the matched files.		
fortindr	Enable scanning of files by FortiNDR.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the FortiNDR detected infections.		
	<i>monitor</i>	Log the FortiNDR detected infections.		
fortisandbox	Enable scanning of files by FortiSandbox.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the FortiSandbox detected infections.		
	<i>monitor</i>	Log the FortiSandbox detected infections.		
quarantine	Enable/disable quarantine for infected files.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable quarantine for infected files.		
	<i>enable</i>	Enable quarantine for infected files.		
archive-block	Select the archive types to block.	option	-	
	Option	Description		
	<i>encrypted</i>	Block encrypted archives.		
	<i>corrupted</i>	Block corrupted archives.		
	<i>partiallycorrupted</i>	Block partially corrupted archives.		
	<i>multipart</i>	Block multipart archives.		
	<i>nested</i>	Block nested archives that exceed uncompressed nest limit.		
	<i>mailbomb</i>	Block mail bomb archives.		
	<i>timeout</i>	Block scan timeout.		
	<i>unhandled</i>	Block archives that FortiProxy cannot open.		
archive-log	Select the archive types to log.	option	-	
	Option	Description		
	<i>encrypted</i>	Log encrypted archives.		
	<i>corrupted</i>	Log corrupted archives.		
	<i>partiallycorrupted</i>	Log partially corrupted archives.		
	<i>multipart</i>	Log multipart archives.		
	<i>nested</i>	Log nested archives that exceed uncompressed nest limit.		
	<i>mailbomb</i>	Log mail bomb archives.		
	<i>timeout</i>	Log scan timeout.		
	<i>unhandled</i>	Log archives that FortiProxy cannot open.		
emulator	Enable/disable the virus emulator.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable the virus emulator.		
	<i>disable</i>	Disable the virus emulator.		

Parameter	Description	Type	Size	Default						
content-disarm	Enable/disable Content Disarm and Reconstruction when performing AntiVirus scan.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable Content Disarm and Reconstruction when performing AntiVirus scan.</td></tr><tr><td><i>enable</i></td><td>Enable Content Disarm and Reconstruction when performing AntiVirus scan.</td></tr></table>	Option	Description	<i>disable</i>	Disable Content Disarm and Reconstruction when performing AntiVirus scan.	<i>enable</i>	Enable Content Disarm and Reconstruction when performing AntiVirus scan.			
Option	Description									
<i>disable</i>	Disable Content Disarm and Reconstruction when performing AntiVirus scan.									
<i>enable</i>	Enable Content Disarm and Reconstruction when performing AntiVirus scan.									

config ftp

Parameter	Description	Type	Size	Default								
av-scan	Enable AntiVirus scan service.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr><tr><td><i>block</i></td><td>Block the virus infected files.</td></tr><tr><td><i>monitor</i></td><td>Log the virus infected files.</td></tr></table>	Option	Description	<i>disable</i>	Disable.	<i>block</i>	Block the virus infected files.	<i>monitor</i>	Log the virus infected files.			
Option	Description											
<i>disable</i>	Disable.											
<i>block</i>	Block the virus infected files.											
<i>monitor</i>	Log the virus infected files.											
outbreak-prevention	Enable virus outbreak prevention service.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr><tr><td><i>block</i></td><td>Block the matched files.</td></tr><tr><td><i>monitor</i></td><td>Log the matched files.</td></tr></table>	Option	Description	<i>disable</i>	Disable.	<i>block</i>	Block the matched files.	<i>monitor</i>	Log the matched files.			
Option	Description											
<i>disable</i>	Disable.											
<i>block</i>	Block the matched files.											
<i>monitor</i>	Log the matched files.											
external-blocklist	Enable external-blocklist. Analyzes files including the content of archives.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr><tr><td><i>block</i></td><td>Block the matched files.</td></tr><tr><td><i>monitor</i></td><td>Log the matched files.</td></tr></table>	Option	Description	<i>disable</i>	Disable.	<i>block</i>	Block the matched files.	<i>monitor</i>	Log the matched files.			
Option	Description											
<i>disable</i>	Disable.											
<i>block</i>	Block the matched files.											
<i>monitor</i>	Log the matched files.											
fortindr	Enable scanning of files by FortiNDR.	option	-	disable								

Parameter	Description	Type	Size	Default
	Option Description			
	<i>disable</i>	Disable.		
	<i>block</i>	Block the FortiNDR detected infections.		
	<i>monitor</i>	Log the FortiNDR detected infections.		
fortisandbox	Enable scanning of files by FortiSandbox.	option	-	disable
	Option Description			
	<i>disable</i>	Disable.		
	<i>block</i>	Block the FortiSandbox detected infections.		
	<i>monitor</i>	Log the FortiSandbox detected infections.		
quarantine	Enable/disable quarantine for infected files.	option	-	disable
	Option Description			
	<i>disable</i>	Disable quarantine for infected files.		
	<i>enable</i>	Enable quarantine for infected files.		
archive-block	Select the archive types to block.	option	-	
	Option Description			
	<i>encrypted</i>	Block encrypted archives.		
	<i>corrupted</i>	Block corrupted archives.		
	<i>partiallycorrupted</i>	Block partially corrupted archives.		
	<i>multipart</i>	Block multipart archives.		
	<i>nested</i>	Block nested archives that exceed uncompressed nest limit.		
	<i>mailbomb</i>	Block mail bomb archives.		
	<i>timeout</i>	Block scan timeout.		
	<i>unhandled</i>	Block archives that FortiProxy cannot open.		
archive-log	Select the archive types to log.	option	-	
	Option Description			
	<i>encrypted</i>	Log encrypted archives.		
	<i>corrupted</i>	Log corrupted archives.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>partiallycorrupted</i>	Log partially corrupted archives.		
	<i>multipart</i>	Log multipart archives.		
	<i>nested</i>	Log nested archives that exceed uncompressed nest limit.		
	<i>mailbomb</i>	Log mail bomb archives.		
	<i>timeout</i>	Log scan timeout.		
	<i>unhandled</i>	Log archives that FortiProxy cannot open.		
emulator	Enable/disable the virus emulator.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable the virus emulator.		
	<i>disable</i>	Disable the virus emulator.		

config imap

Parameter	Description	Type	Size	Default
av-scan	Enable AntiVirus scan service.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the virus infected files.		
	<i>monitor</i>	Log the virus infected files.		
outbreak-prevention	Enable virus outbreak prevention service.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the matched files.		
	<i>monitor</i>	Log the matched files.		
external-blocklist	Enable external-blocklist. Analyzes files including the content of archives.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>block</i>	Block the matched files.		
	<i>monitor</i>	Log the matched files.		
fortindr	Enable scanning of files by FortiNDR.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the FortiNDR detected infections.		
	<i>monitor</i>	Log the FortiNDR detected infections.		
fortisandbox	Enable scanning of files by FortiSandbox.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the FortiSandbox detected infections.		
	<i>monitor</i>	Log the FortiSandbox detected infections.		
quarantine	Enable/disable quarantine for infected files.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable quarantine for infected files.		
	<i>enable</i>	Enable quarantine for infected files.		
archive-block	Select the archive types to block.	option	-	
	Option	Description		
	<i>encrypted</i>	Block encrypted archives.		
	<i>corrupted</i>	Block corrupted archives.		
	<i>partiallycorrupted</i>	Block partially corrupted archives.		
	<i>multipart</i>	Block multipart archives.		
	<i>nested</i>	Block nested archives that exceed uncompressed nest limit.		
	<i>mailbomb</i>	Block mail bomb archives.		
	<i>timeout</i>	Block scan timeout.		
	<i>unhandled</i>	Block archives that FortiProxy cannot open.		

Parameter	Description	Type	Size	Default																		
archive-log	Select the archive types to log.	option	-																			
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>encrypted</i></td><td>Log encrypted archives.</td></tr><tr><td><i>corrupted</i></td><td>Log corrupted archives.</td></tr><tr><td><i>partiallycorrupted</i></td><td>Log partially corrupted archives.</td></tr><tr><td><i>multipart</i></td><td>Log multipart archives.</td></tr><tr><td><i>nested</i></td><td>Log nested archives that exceed uncompressed nest limit.</td></tr><tr><td><i>mailbomb</i></td><td>Log mail bomb archives.</td></tr><tr><td><i>timeout</i></td><td>Log scan timeout.</td></tr><tr><td><i>unhandled</i></td><td>Log archives that FortiProxy cannot open.</td></tr></table>	Option	Description	<i>encrypted</i>	Log encrypted archives.	<i>corrupted</i>	Log corrupted archives.	<i>partiallycorrupted</i>	Log partially corrupted archives.	<i>multipart</i>	Log multipart archives.	<i>nested</i>	Log nested archives that exceed uncompressed nest limit.	<i>mailbomb</i>	Log mail bomb archives.	<i>timeout</i>	Log scan timeout.	<i>unhandled</i>	Log archives that FortiProxy cannot open.			
Option	Description																					
<i>encrypted</i>	Log encrypted archives.																					
<i>corrupted</i>	Log corrupted archives.																					
<i>partiallycorrupted</i>	Log partially corrupted archives.																					
<i>multipart</i>	Log multipart archives.																					
<i>nested</i>	Log nested archives that exceed uncompressed nest limit.																					
<i>mailbomb</i>	Log mail bomb archives.																					
<i>timeout</i>	Log scan timeout.																					
<i>unhandled</i>	Log archives that FortiProxy cannot open.																					
emulator	Enable/disable the virus emulator.	option	-	enable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable the virus emulator.</td></tr><tr><td><i>disable</i></td><td>Disable the virus emulator.</td></tr></table>	Option	Description	<i>enable</i>	Enable the virus emulator.	<i>disable</i>	Disable the virus emulator.															
Option	Description																					
<i>enable</i>	Enable the virus emulator.																					
<i>disable</i>	Disable the virus emulator.																					
executables	Treat Windows executable files as viruses for the purpose of blocking or monitoring.	option	-	default																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Perform standard AntiVirus scanning of Windows executable files.</td></tr><tr><td><i>virus</i></td><td>Treat Windows executables as viruses.</td></tr></table>	Option	Description	<i>default</i>	Perform standard AntiVirus scanning of Windows executable files.	<i>virus</i>	Treat Windows executables as viruses.															
Option	Description																					
<i>default</i>	Perform standard AntiVirus scanning of Windows executable files.																					
<i>virus</i>	Treat Windows executables as viruses.																					
content-disarm	Enable/disable Content Disarm and Reconstruction when performing AntiVirus scan.	option	-	disable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable Content Disarm and Reconstruction when performing AntiVirus scan.</td></tr><tr><td><i>enable</i></td><td>Enable Content Disarm and Reconstruction when performing AntiVirus scan.</td></tr></table>	Option	Description	<i>disable</i>	Disable Content Disarm and Reconstruction when performing AntiVirus scan.	<i>enable</i>	Enable Content Disarm and Reconstruction when performing AntiVirus scan.															
Option	Description																					
<i>disable</i>	Disable Content Disarm and Reconstruction when performing AntiVirus scan.																					
<i>enable</i>	Enable Content Disarm and Reconstruction when performing AntiVirus scan.																					

config pop3

Parameter	Description	Type	Size	Default								
av-scan	Enable AntiVirus scan service.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr><tr><td><i>block</i></td><td>Block the virus infected files.</td></tr><tr><td><i>monitor</i></td><td>Log the virus infected files.</td></tr></table>	Option	Description	<i>disable</i>	Disable.	<i>block</i>	Block the virus infected files.	<i>monitor</i>	Log the virus infected files.			
Option	Description											
<i>disable</i>	Disable.											
<i>block</i>	Block the virus infected files.											
<i>monitor</i>	Log the virus infected files.											
outbreak-prevention	Enable virus outbreak prevention service.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr><tr><td><i>block</i></td><td>Block the matched files.</td></tr><tr><td><i>monitor</i></td><td>Log the matched files.</td></tr></table>	Option	Description	<i>disable</i>	Disable.	<i>block</i>	Block the matched files.	<i>monitor</i>	Log the matched files.			
Option	Description											
<i>disable</i>	Disable.											
<i>block</i>	Block the matched files.											
<i>monitor</i>	Log the matched files.											
external-blocklist	Enable external-blocklist. Analyzes files including the content of archives.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr><tr><td><i>block</i></td><td>Block the matched files.</td></tr><tr><td><i>monitor</i></td><td>Log the matched files.</td></tr></table>	Option	Description	<i>disable</i>	Disable.	<i>block</i>	Block the matched files.	<i>monitor</i>	Log the matched files.			
Option	Description											
<i>disable</i>	Disable.											
<i>block</i>	Block the matched files.											
<i>monitor</i>	Log the matched files.											
fortindr	Enable scanning of files by FortiNDR.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr><tr><td><i>block</i></td><td>Block the FortiNDR detected infections.</td></tr><tr><td><i>monitor</i></td><td>Log the FortiNDR detected infections.</td></tr></table>	Option	Description	<i>disable</i>	Disable.	<i>block</i>	Block the FortiNDR detected infections.	<i>monitor</i>	Log the FortiNDR detected infections.			
Option	Description											
<i>disable</i>	Disable.											
<i>block</i>	Block the FortiNDR detected infections.											
<i>monitor</i>	Log the FortiNDR detected infections.											
fortisandbox	Enable scanning of files by FortiSandbox.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr><tr><td><i>block</i></td><td>Block the FortiSandbox detected infections.</td></tr><tr><td><i>monitor</i></td><td>Log the FortiSandbox detected infections.</td></tr></table>	Option	Description	<i>disable</i>	Disable.	<i>block</i>	Block the FortiSandbox detected infections.	<i>monitor</i>	Log the FortiSandbox detected infections.			
Option	Description											
<i>disable</i>	Disable.											
<i>block</i>	Block the FortiSandbox detected infections.											
<i>monitor</i>	Log the FortiSandbox detected infections.											
quarantine	Enable/disable quarantine for infected files.	option	-	disable								

Parameter	Description	Type	Size	Default																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable quarantine for infected files.</td></tr><tr><td><i>enable</i></td><td>Enable quarantine for infected files.</td></tr></table>	Option	Description	<i>disable</i>	Disable quarantine for infected files.	<i>enable</i>	Enable quarantine for infected files.															
	Option	Description																				
	<i>disable</i>	Disable quarantine for infected files.																				
<i>enable</i>	Enable quarantine for infected files.																					
archive-block	Select the archive types to block.	option	-																			
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>encrypted</i></td><td>Block encrypted archives.</td></tr><tr><td><i>corrupted</i></td><td>Block corrupted archives.</td></tr><tr><td><i>partiallycorrupted</i></td><td>Block partially corrupted archives.</td></tr><tr><td><i>multipart</i></td><td>Block multipart archives.</td></tr><tr><td><i>nested</i></td><td>Block nested archives that exceed uncompressed nest limit.</td></tr><tr><td><i>mailbomb</i></td><td>Block mail bomb archives.</td></tr><tr><td><i>timeout</i></td><td>Block scan timeout.</td></tr><tr><td><i>unhandled</i></td><td>Block archives that FortiProxy cannot open.</td></tr></table>	Option	Description	<i>encrypted</i>	Block encrypted archives.	<i>corrupted</i>	Block corrupted archives.	<i>partiallycorrupted</i>	Block partially corrupted archives.	<i>multipart</i>	Block multipart archives.	<i>nested</i>	Block nested archives that exceed uncompressed nest limit.	<i>mailbomb</i>	Block mail bomb archives.	<i>timeout</i>	Block scan timeout.	<i>unhandled</i>	Block archives that FortiProxy cannot open.			
	Option	Description																				
	<i>encrypted</i>	Block encrypted archives.																				
	<i>corrupted</i>	Block corrupted archives.																				
	<i>partiallycorrupted</i>	Block partially corrupted archives.																				
	<i>multipart</i>	Block multipart archives.																				
	<i>nested</i>	Block nested archives that exceed uncompressed nest limit.																				
	<i>mailbomb</i>	Block mail bomb archives.																				
	<i>timeout</i>	Block scan timeout.																				
<i>unhandled</i>	Block archives that FortiProxy cannot open.																					
archive-log	Select the archive types to log.	option	-																			
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>encrypted</i></td><td>Log encrypted archives.</td></tr><tr><td><i>corrupted</i></td><td>Log corrupted archives.</td></tr><tr><td><i>partiallycorrupted</i></td><td>Log partially corrupted archives.</td></tr><tr><td><i>multipart</i></td><td>Log multipart archives.</td></tr><tr><td><i>nested</i></td><td>Log nested archives that exceed uncompressed nest limit.</td></tr><tr><td><i>mailbomb</i></td><td>Log mail bomb archives.</td></tr><tr><td><i>timeout</i></td><td>Log scan timeout.</td></tr><tr><td><i>unhandled</i></td><td>Log archives that FortiProxy cannot open.</td></tr></table>	Option	Description	<i>encrypted</i>	Log encrypted archives.	<i>corrupted</i>	Log corrupted archives.	<i>partiallycorrupted</i>	Log partially corrupted archives.	<i>multipart</i>	Log multipart archives.	<i>nested</i>	Log nested archives that exceed uncompressed nest limit.	<i>mailbomb</i>	Log mail bomb archives.	<i>timeout</i>	Log scan timeout.	<i>unhandled</i>	Log archives that FortiProxy cannot open.			
	Option	Description																				
	<i>encrypted</i>	Log encrypted archives.																				
	<i>corrupted</i>	Log corrupted archives.																				
	<i>partiallycorrupted</i>	Log partially corrupted archives.																				
	<i>multipart</i>	Log multipart archives.																				
	<i>nested</i>	Log nested archives that exceed uncompressed nest limit.																				
	<i>mailbomb</i>	Log mail bomb archives.																				
	<i>timeout</i>	Log scan timeout.																				
<i>unhandled</i>	Log archives that FortiProxy cannot open.																					
emulator	Enable/disable the virus emulator.	option	-	enable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable the virus emulator.</td></tr><tr><td><i>disable</i></td><td>Disable the virus emulator.</td></tr></table>	Option	Description	<i>enable</i>	Enable the virus emulator.	<i>disable</i>	Disable the virus emulator.															
	Option	Description																				
	<i>enable</i>	Enable the virus emulator.																				
<i>disable</i>	Disable the virus emulator.																					

Parameter	Description	Type	Size	Default						
executables	Treat Windows executable files as viruses for the purpose of blocking or monitoring.	option	-	default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Perform standard AntiVirus scanning of Windows executable files.</td></tr><tr><td><i>virus</i></td><td>Treat Windows executables as viruses.</td></tr></table>	Option	Description	<i>default</i>	Perform standard AntiVirus scanning of Windows executable files.	<i>virus</i>	Treat Windows executables as viruses.			
Option	Description									
<i>default</i>	Perform standard AntiVirus scanning of Windows executable files.									
<i>virus</i>	Treat Windows executables as viruses.									
content-disarm	Enable/disable Content Disarm and Reconstruction when performing AntiVirus scan.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable Content Disarm and Reconstruction when performing AntiVirus scan.</td></tr><tr><td><i>enable</i></td><td>Enable Content Disarm and Reconstruction when performing AntiVirus scan.</td></tr></table>	Option	Description	<i>disable</i>	Disable Content Disarm and Reconstruction when performing AntiVirus scan.	<i>enable</i>	Enable Content Disarm and Reconstruction when performing AntiVirus scan.			
Option	Description									
<i>disable</i>	Disable Content Disarm and Reconstruction when performing AntiVirus scan.									
<i>enable</i>	Enable Content Disarm and Reconstruction when performing AntiVirus scan.									

config smtp

Parameter	Description	Type	Size	Default
av-scan	Enable AntiVirus scan service.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the virus infected files.		
	<i>monitor</i>	Log the virus infected files.		
outbreak-prevention	Enable virus outbreak prevention service.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the matched files.		
	<i>monitor</i>	Log the matched files.		
external-blocklist	Enable external-blocklist. Analyzes files including the content of archives.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the matched files.		
	<i>monitor</i>	Log the matched files.		
fortindr	Enable scanning of files by FortiNDR.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the FortiNDR detected infections.		
	<i>monitor</i>	Log the FortiNDR detected infections.		
fortisandbox	Enable scanning of files by FortiSandbox.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the FortiSandbox detected infections.		
	<i>monitor</i>	Log the FortiSandbox detected infections.		
quarantine	Enable/disable quarantine for infected files.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable quarantine for infected files.		
	<i>enable</i>	Enable quarantine for infected files.		
archive-block	Select the archive types to block.	option	-	
	Option	Description		
	<i>encrypted</i>	Block encrypted archives.		
	<i>corrupted</i>	Block corrupted archives.		
	<i>partiallycorrupted</i>	Block partially corrupted archives.		
	<i>multipart</i>	Block multipart archives.		
	<i>nested</i>	Block nested archives that exceed uncompressed nest limit.		
	<i>mailbomb</i>	Block mail bomb archives.		
	<i>timeout</i>	Block scan timeout.		
	<i>unhandled</i>	Block archives that FortiProxy cannot open.		

Parameter	Description	Type	Size	Default																		
archive-log	Select the archive types to log.	option	-																			
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>encrypted</i></td><td>Log encrypted archives.</td></tr><tr><td><i>corrupted</i></td><td>Log corrupted archives.</td></tr><tr><td><i>partiallycorrupted</i></td><td>Log partially corrupted archives.</td></tr><tr><td><i>multipart</i></td><td>Log multipart archives.</td></tr><tr><td><i>nested</i></td><td>Log nested archives that exceed uncompressed nest limit.</td></tr><tr><td><i>mailbomb</i></td><td>Log mail bomb archives.</td></tr><tr><td><i>timeout</i></td><td>Log scan timeout.</td></tr><tr><td><i>unhandled</i></td><td>Log archives that FortiProxy cannot open.</td></tr></table>	Option	Description	<i>encrypted</i>	Log encrypted archives.	<i>corrupted</i>	Log corrupted archives.	<i>partiallycorrupted</i>	Log partially corrupted archives.	<i>multipart</i>	Log multipart archives.	<i>nested</i>	Log nested archives that exceed uncompressed nest limit.	<i>mailbomb</i>	Log mail bomb archives.	<i>timeout</i>	Log scan timeout.	<i>unhandled</i>	Log archives that FortiProxy cannot open.			
Option	Description																					
<i>encrypted</i>	Log encrypted archives.																					
<i>corrupted</i>	Log corrupted archives.																					
<i>partiallycorrupted</i>	Log partially corrupted archives.																					
<i>multipart</i>	Log multipart archives.																					
<i>nested</i>	Log nested archives that exceed uncompressed nest limit.																					
<i>mailbomb</i>	Log mail bomb archives.																					
<i>timeout</i>	Log scan timeout.																					
<i>unhandled</i>	Log archives that FortiProxy cannot open.																					
emulator	Enable/disable the virus emulator.	option	-	enable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable the virus emulator.</td></tr><tr><td><i>disable</i></td><td>Disable the virus emulator.</td></tr></table>	Option	Description	<i>enable</i>	Enable the virus emulator.	<i>disable</i>	Disable the virus emulator.															
Option	Description																					
<i>enable</i>	Enable the virus emulator.																					
<i>disable</i>	Disable the virus emulator.																					
executables	Treat Windows executable files as viruses for the purpose of blocking or monitoring.	option	-	default																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Perform standard AntiVirus scanning of Windows executable files.</td></tr><tr><td><i>virus</i></td><td>Treat Windows executables as viruses.</td></tr></table>	Option	Description	<i>default</i>	Perform standard AntiVirus scanning of Windows executable files.	<i>virus</i>	Treat Windows executables as viruses.															
Option	Description																					
<i>default</i>	Perform standard AntiVirus scanning of Windows executable files.																					
<i>virus</i>	Treat Windows executables as viruses.																					
content-disarm	Enable/disable Content Disarm and Reconstruction when performing AntiVirus scan.	option	-	disable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable Content Disarm and Reconstruction when performing AntiVirus scan.</td></tr><tr><td><i>enable</i></td><td>Enable Content Disarm and Reconstruction when performing AntiVirus scan.</td></tr></table>	Option	Description	<i>disable</i>	Disable Content Disarm and Reconstruction when performing AntiVirus scan.	<i>enable</i>	Enable Content Disarm and Reconstruction when performing AntiVirus scan.															
Option	Description																					
<i>disable</i>	Disable Content Disarm and Reconstruction when performing AntiVirus scan.																					
<i>enable</i>	Enable Content Disarm and Reconstruction when performing AntiVirus scan.																					

config mapi

Parameter	Description	Type	Size	Default
av-scan	Enable AntiVirus scan service.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the virus infected files.		
	<i>monitor</i>	Log the virus infected files.		
outbreak-prevention	Enable virus outbreak prevention service.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the matched files.		
	<i>monitor</i>	Log the matched files.		
external-blocklist	Enable external-blocklist. Analyzes files including the content of archives.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the matched files.		
	<i>monitor</i>	Log the matched files.		
fortindr	Enable scanning of files by FortiNDR.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the FortiNDR detected infections.		
	<i>monitor</i>	Log the FortiNDR detected infections.		
fortisandbox	Enable scanning of files by FortiSandbox.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the FortiSandbox detected infections.		
	<i>monitor</i>	Log the FortiSandbox detected infections.		
quarantine	Enable/disable quarantine for infected files.	option	-	disable

Parameter	Description	Type	Size	Default																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable quarantine for infected files.</td></tr><tr><td><i>enable</i></td><td>Enable quarantine for infected files.</td></tr></table>	Option	Description	<i>disable</i>	Disable quarantine for infected files.	<i>enable</i>	Enable quarantine for infected files.															
	Option	Description																				
	<i>disable</i>	Disable quarantine for infected files.																				
<i>enable</i>	Enable quarantine for infected files.																					
archive-block	Select the archive types to block.	option	-																			
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>encrypted</i></td><td>Block encrypted archives.</td></tr><tr><td><i>corrupted</i></td><td>Block corrupted archives.</td></tr><tr><td><i>partiallycorrupted</i></td><td>Block partially corrupted archives.</td></tr><tr><td><i>multipart</i></td><td>Block multipart archives.</td></tr><tr><td><i>nested</i></td><td>Block nested archives that exceed uncompressed nest limit.</td></tr><tr><td><i>mailbomb</i></td><td>Block mail bomb archives.</td></tr><tr><td><i>timeout</i></td><td>Block scan timeout.</td></tr><tr><td><i>unhandled</i></td><td>Block archives that FortiProxy cannot open.</td></tr></table>	Option	Description	<i>encrypted</i>	Block encrypted archives.	<i>corrupted</i>	Block corrupted archives.	<i>partiallycorrupted</i>	Block partially corrupted archives.	<i>multipart</i>	Block multipart archives.	<i>nested</i>	Block nested archives that exceed uncompressed nest limit.	<i>mailbomb</i>	Block mail bomb archives.	<i>timeout</i>	Block scan timeout.	<i>unhandled</i>	Block archives that FortiProxy cannot open.			
	Option	Description																				
	<i>encrypted</i>	Block encrypted archives.																				
	<i>corrupted</i>	Block corrupted archives.																				
	<i>partiallycorrupted</i>	Block partially corrupted archives.																				
	<i>multipart</i>	Block multipart archives.																				
	<i>nested</i>	Block nested archives that exceed uncompressed nest limit.																				
	<i>mailbomb</i>	Block mail bomb archives.																				
	<i>timeout</i>	Block scan timeout.																				
<i>unhandled</i>	Block archives that FortiProxy cannot open.																					
archive-log	Select the archive types to log.	option	-																			
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>encrypted</i></td><td>Log encrypted archives.</td></tr><tr><td><i>corrupted</i></td><td>Log corrupted archives.</td></tr><tr><td><i>partiallycorrupted</i></td><td>Log partially corrupted archives.</td></tr><tr><td><i>multipart</i></td><td>Log multipart archives.</td></tr><tr><td><i>nested</i></td><td>Log nested archives that exceed uncompressed nest limit.</td></tr><tr><td><i>mailbomb</i></td><td>Log mail bomb archives.</td></tr><tr><td><i>timeout</i></td><td>Log scan timeout.</td></tr><tr><td><i>unhandled</i></td><td>Log archives that FortiProxy cannot open.</td></tr></table>	Option	Description	<i>encrypted</i>	Log encrypted archives.	<i>corrupted</i>	Log corrupted archives.	<i>partiallycorrupted</i>	Log partially corrupted archives.	<i>multipart</i>	Log multipart archives.	<i>nested</i>	Log nested archives that exceed uncompressed nest limit.	<i>mailbomb</i>	Log mail bomb archives.	<i>timeout</i>	Log scan timeout.	<i>unhandled</i>	Log archives that FortiProxy cannot open.			
	Option	Description																				
	<i>encrypted</i>	Log encrypted archives.																				
	<i>corrupted</i>	Log corrupted archives.																				
	<i>partiallycorrupted</i>	Log partially corrupted archives.																				
	<i>multipart</i>	Log multipart archives.																				
	<i>nested</i>	Log nested archives that exceed uncompressed nest limit.																				
	<i>mailbomb</i>	Log mail bomb archives.																				
	<i>timeout</i>	Log scan timeout.																				
<i>unhandled</i>	Log archives that FortiProxy cannot open.																					
emulator	Enable/disable the virus emulator.	option	-	enable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable the virus emulator.</td></tr><tr><td><i>disable</i></td><td>Disable the virus emulator.</td></tr></table>	Option	Description	<i>enable</i>	Enable the virus emulator.	<i>disable</i>	Disable the virus emulator.															
	Option	Description																				
	<i>enable</i>	Enable the virus emulator.																				
<i>disable</i>	Disable the virus emulator.																					

Parameter	Description	Type	Size	Default						
executables	Treat Windows executable files as viruses for the purpose of blocking or monitoring.	option	-	default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Perform standard AntiVirus scanning of Windows executable files.</td></tr><tr><td><i>virus</i></td><td>Treat Windows executables as viruses.</td></tr></table>	Option	Description	<i>default</i>	Perform standard AntiVirus scanning of Windows executable files.	<i>virus</i>	Treat Windows executables as viruses.			
Option	Description									
<i>default</i>	Perform standard AntiVirus scanning of Windows executable files.									
<i>virus</i>	Treat Windows executables as viruses.									

config nntp

Parameter	Description	Type	Size	Default								
av-scan	Enable AntiVirus scan service.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr><tr><td><i>block</i></td><td>Block the virus infected files.</td></tr><tr><td><i>monitor</i></td><td>Log the virus infected files.</td></tr></table>	Option	Description	<i>disable</i>	Disable.	<i>block</i>	Block the virus infected files.	<i>monitor</i>	Log the virus infected files.			
Option	Description											
<i>disable</i>	Disable.											
<i>block</i>	Block the virus infected files.											
<i>monitor</i>	Log the virus infected files.											
outbreak-prevention	Enable virus outbreak prevention service.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr><tr><td><i>block</i></td><td>Block the matched files.</td></tr><tr><td><i>monitor</i></td><td>Log the matched files.</td></tr></table>	Option	Description	<i>disable</i>	Disable.	<i>block</i>	Block the matched files.	<i>monitor</i>	Log the matched files.			
Option	Description											
<i>disable</i>	Disable.											
<i>block</i>	Block the matched files.											
<i>monitor</i>	Log the matched files.											
external-blocklist	Enable external-blocklist. Analyzes files including the content of archives.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr><tr><td><i>block</i></td><td>Block the matched files.</td></tr><tr><td><i>monitor</i></td><td>Log the matched files.</td></tr></table>	Option	Description	<i>disable</i>	Disable.	<i>block</i>	Block the matched files.	<i>monitor</i>	Log the matched files.			
Option	Description											
<i>disable</i>	Disable.											
<i>block</i>	Block the matched files.											
<i>monitor</i>	Log the matched files.											
fortindr	Enable scanning of files by FortiNDR.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr></table>	Option	Description	<i>disable</i>	Disable.							
Option	Description											
<i>disable</i>	Disable.											

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>block</i>	Block the FortiNDR detected infections.		
	<i>monitor</i>	Log the FortiNDR detected infections.		
fortisandbox	Enable scanning of files by FortiSandbox.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the FortiSandbox detected infections.		
	<i>monitor</i>	Log the FortiSandbox detected infections.		
quarantine	Enable/disable quarantine for infected files.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable quarantine for infected files.		
	<i>enable</i>	Enable quarantine for infected files.		
archive-block	Select the archive types to block.	option	-	
	Option	Description		
	<i>encrypted</i>	Block encrypted archives.		
	<i>corrupted</i>	Block corrupted archives.		
	<i>partiallycorrupted</i>	Block partially corrupted archives.		
	<i>multipart</i>	Block multipart archives.		
	<i>nested</i>	Block nested archives that exceed uncompressed nest limit.		
	<i>mailbomb</i>	Block mail bomb archives.		
	<i>timeout</i>	Block scan timeout.		
	<i>unhandled</i>	Block archives that FortiProxy cannot open.		
archive-log	Select the archive types to log.	option	-	
	Option	Description		
	<i>encrypted</i>	Log encrypted archives.		
	<i>corrupted</i>	Log corrupted archives.		
	<i>partiallycorrupted</i>	Log partially corrupted archives.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>multipart</i>	Log multipart archives.		
	<i>nested</i>	Log nested archives that exceed uncompressed nest limit.		
	<i>mailbomb</i>	Log mail bomb archives.		
	<i>timeout</i>	Log scan timeout.		
	<i>unhandled</i>	Log archives that FortiProxy cannot open.		
emulator	Enable/disable the virus emulator.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable the virus emulator.		
	<i>disable</i>	Disable the virus emulator.		

config cifs

Parameter	Description	Type	Size	Default
av-scan	Enable AntiVirus scan service.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the virus infected files.		
	<i>monitor</i>	Log the virus infected files.		
outbreak-prevention	Enable virus outbreak prevention service.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the matched files.		
	<i>monitor</i>	Log the matched files.		
external-blocklist	Enable external-blocklist. Analyzes files including the content of archives.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the matched files.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>monitor</i>	Log the matched files.		
fortindr	Enable scanning of files by FortiNDR.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the FortiNDR detected infections.		
	<i>monitor</i>	Log the FortiNDR detected infections.		
fortisandbox	Enable scanning of files by FortiSandbox.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the FortiSandbox detected infections.		
	<i>monitor</i>	Log the FortiSandbox detected infections.		
quarantine	Enable/disable quarantine for infected files.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable quarantine for infected files.		
	<i>enable</i>	Enable quarantine for infected files.		
archive-block	Select the archive types to block.	option	-	
	Option	Description		
	<i>encrypted</i>	Block encrypted archives.		
	<i>corrupted</i>	Block corrupted archives.		
	<i>partiallycorrupted</i>	Block partially corrupted archives.		
	<i>multipart</i>	Block multipart archives.		
	<i>nested</i>	Block nested archives that exceed uncompressed nest limit.		
	<i>mailbomb</i>	Block mail bomb archives.		
	<i>timeout</i>	Block scan timeout.		
	<i>unhandled</i>	Block archives that FortiProxy cannot open.		
archive-log	Select the archive types to log.	option	-	

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>encrypted</i>	Log encrypted archives.		
	<i>corrupted</i>	Log corrupted archives.		
	<i>partiallycorrupted</i>	Log partially corrupted archives.		
	<i>multipart</i>	Log multipart archives.		
	<i>nested</i>	Log nested archives that exceed uncompressed nest limit.		
	<i>mailbomb</i>	Log mail bomb archives.		
	<i>timeout</i>	Log scan timeout.		
	<i>unhandled</i>	Log archives that FortiProxy cannot open.		
emulator	Enable/disable the virus emulator.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable the virus emulator.		
	<i>disable</i>	Disable the virus emulator.		

config ssh

Parameter	Description	Type	Size	Default
av-scan	Enable AntiVirus scan service.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the virus infected files.		
	<i>monitor</i>	Log the virus infected files.		
outbreak-prevention	Enable virus outbreak prevention service.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the matched files.		
	<i>monitor</i>	Log the matched files.		
external-blocklist	Enable external-blocklist. Analyzes files including the content of archives.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the matched files.		
	<i>monitor</i>	Log the matched files.		
fortindr	Enable scanning of files by FortiNDR.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the FortiNDR detected infections.		
	<i>monitor</i>	Log the FortiNDR detected infections.		
fortisandbox	Enable scanning of files by FortiSandbox.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>block</i>	Block the FortiSandbox detected infections.		
	<i>monitor</i>	Log the FortiSandbox detected infections.		
quarantine	Enable/disable quarantine for infected files.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable quarantine for infected files.		
	<i>enable</i>	Enable quarantine for infected files.		
archive-block	Select the archive types to block.	option	-	
	Option	Description		
	<i>encrypted</i>	Block encrypted archives.		
	<i>corrupted</i>	Block corrupted archives.		
	<i>partiallycorrupted</i>	Block partially corrupted archives.		
	<i>multipart</i>	Block multipart archives.		
	<i>nested</i>	Block nested archives that exceed uncompressed nest limit.		
	<i>mailbomb</i>	Block mail bomb archives.		
	<i>timeout</i>	Block scan timeout.		
	<i>unhandled</i>	Block archives that FortiProxy cannot open.		

Parameter	Description	Type	Size	Default																		
archive-log	Select the archive types to log.	option	-																			
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>encrypted</i></td><td>Log encrypted archives.</td></tr><tr><td><i>corrupted</i></td><td>Log corrupted archives.</td></tr><tr><td><i>partiallycorrupted</i></td><td>Log partially corrupted archives.</td></tr><tr><td><i>multipart</i></td><td>Log multipart archives.</td></tr><tr><td><i>nested</i></td><td>Log nested archives that exceed uncompressed nest limit.</td></tr><tr><td><i>mailbomb</i></td><td>Log mail bomb archives.</td></tr><tr><td><i>timeout</i></td><td>Log scan timeout.</td></tr><tr><td><i>unhandled</i></td><td>Log archives that FortiProxy cannot open.</td></tr></table>	Option	Description	<i>encrypted</i>	Log encrypted archives.	<i>corrupted</i>	Log corrupted archives.	<i>partiallycorrupted</i>	Log partially corrupted archives.	<i>multipart</i>	Log multipart archives.	<i>nested</i>	Log nested archives that exceed uncompressed nest limit.	<i>mailbomb</i>	Log mail bomb archives.	<i>timeout</i>	Log scan timeout.	<i>unhandled</i>	Log archives that FortiProxy cannot open.			
Option	Description																					
<i>encrypted</i>	Log encrypted archives.																					
<i>corrupted</i>	Log corrupted archives.																					
<i>partiallycorrupted</i>	Log partially corrupted archives.																					
<i>multipart</i>	Log multipart archives.																					
<i>nested</i>	Log nested archives that exceed uncompressed nest limit.																					
<i>mailbomb</i>	Log mail bomb archives.																					
<i>timeout</i>	Log scan timeout.																					
<i>unhandled</i>	Log archives that FortiProxy cannot open.																					
emulator	Enable/disable the virus emulator.	option	-	enable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable the virus emulator.</td></tr><tr><td><i>disable</i></td><td>Disable the virus emulator.</td></tr></table>	Option	Description	<i>enable</i>	Enable the virus emulator.	<i>disable</i>	Disable the virus emulator.															
Option	Description																					
<i>enable</i>	Enable the virus emulator.																					
<i>disable</i>	Disable the virus emulator.																					

config nac-quar

Parameter	Description	Type	Size	Default						
infected	Enable/Disable quarantining infected hosts to the banned user list.	option	-	none						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>none</i></td><td>Do not quarantine infected hosts.</td></tr><tr><td><i>quar-src-ip</i></td><td>Quarantine all traffic from the infected hosts source IP.</td></tr></table>	Option	Description	<i>none</i>	Do not quarantine infected hosts.	<i>quar-src-ip</i>	Quarantine all traffic from the infected hosts source IP.			
Option	Description									
<i>none</i>	Do not quarantine infected hosts.									
<i>quar-src-ip</i>	Quarantine all traffic from the infected hosts source IP.									
expiry	Duration of quarantine.	user	Not Specified	5m						
log	Enable/disable AntiVirus quarantine logging.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable AntiVirus quarantine logging.</td></tr><tr><td><i>disable</i></td><td>Disable AntiVirus quarantine logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable AntiVirus quarantine logging.	<i>disable</i>	Disable AntiVirus quarantine logging.			
Option	Description									
<i>enable</i>	Enable AntiVirus quarantine logging.									
<i>disable</i>	Disable AntiVirus quarantine logging.									

config content-disarm

Parameter	Description	Type	Size	Default								
original-file-destination	Destination to send original file if active content is removed.	option	-	discard								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>fortisandbox</i></td><td>Send original file to configured FortiSandbox.</td></tr><tr><td><i>quarantine</i></td><td>Send original file to quarantine.</td></tr><tr><td><i>discard</i></td><td>Original file will be discarded after content disarm.</td></tr></table>	Option	Description	<i>fortisandbox</i>	Send original file to configured FortiSandbox.	<i>quarantine</i>	Send original file to quarantine.	<i>discard</i>	Original file will be discarded after content disarm.			
Option	Description											
<i>fortisandbox</i>	Send original file to configured FortiSandbox.											
<i>quarantine</i>	Send original file to quarantine.											
<i>discard</i>	Original file will be discarded after content disarm.											
error-action	Action to be taken if CDR engine encounters an unrecoverable error.	option	-	log-only								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>block</i></td><td>Block file on CDR error.</td></tr><tr><td><i>log-only</i></td><td>Log CDR error, but allow file.</td></tr><tr><td><i>ignore</i></td><td>Do nothing on CDR error.</td></tr></table>	Option	Description	<i>block</i>	Block file on CDR error.	<i>log-only</i>	Log CDR error, but allow file.	<i>ignore</i>	Do nothing on CDR error.			
Option	Description											
<i>block</i>	Block file on CDR error.											
<i>log-only</i>	Log CDR error, but allow file.											
<i>ignore</i>	Do nothing on CDR error.											
office-macro	Enable/disable stripping of macros in Microsoft Office documents.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable this Content Disarm and Reconstruction feature.</td></tr><tr><td><i>enable</i></td><td>Enable this Content Disarm and Reconstruction feature.</td></tr></table>	Option	Description	<i>disable</i>	Disable this Content Disarm and Reconstruction feature.	<i>enable</i>	Enable this Content Disarm and Reconstruction feature.					
Option	Description											
<i>disable</i>	Disable this Content Disarm and Reconstruction feature.											
<i>enable</i>	Enable this Content Disarm and Reconstruction feature.											
office-hylink	Enable/disable stripping of hyperlinks in Microsoft Office documents.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable this Content Disarm and Reconstruction feature.</td></tr><tr><td><i>enable</i></td><td>Enable this Content Disarm and Reconstruction feature.</td></tr></table>	Option	Description	<i>disable</i>	Disable this Content Disarm and Reconstruction feature.	<i>enable</i>	Enable this Content Disarm and Reconstruction feature.					
Option	Description											
<i>disable</i>	Disable this Content Disarm and Reconstruction feature.											
<i>enable</i>	Enable this Content Disarm and Reconstruction feature.											
office-linked	Enable/disable stripping of linked objects in Microsoft Office documents.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable this Content Disarm and Reconstruction feature.</td></tr><tr><td><i>enable</i></td><td>Enable this Content Disarm and Reconstruction feature.</td></tr></table>	Option	Description	<i>disable</i>	Disable this Content Disarm and Reconstruction feature.	<i>enable</i>	Enable this Content Disarm and Reconstruction feature.					
Option	Description											
<i>disable</i>	Disable this Content Disarm and Reconstruction feature.											
<i>enable</i>	Enable this Content Disarm and Reconstruction feature.											
office-embed	Enable/disable stripping of embedded objects in Microsoft Office documents.	option	-	enable								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable this Content Disarm and Reconstruction feature.		
	<i>enable</i>	Enable this Content Disarm and Reconstruction feature.		
office-dde	Enable/disable stripping of Dynamic Data Exchange events in Microsoft Office documents.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable this Content Disarm and Reconstruction feature.		
	<i>enable</i>	Enable this Content Disarm and Reconstruction feature.		
office-action	Enable/disable stripping of PowerPoint action events in Microsoft Office documents.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable this Content Disarm and Reconstruction feature.		
	<i>enable</i>	Enable this Content Disarm and Reconstruction feature.		
pdf-javacode	Enable/disable stripping of JavaScript code in PDF documents.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable this Content Disarm and Reconstruction feature.		
	<i>enable</i>	Enable this Content Disarm and Reconstruction feature.		
pdf-embedfile	Enable/disable stripping of embedded files in PDF documents.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable this Content Disarm and Reconstruction feature.		
	<i>enable</i>	Enable this Content Disarm and Reconstruction feature.		
pdf-hyperlink	Enable/disable stripping of hyperlinks from PDF documents.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable this Content Disarm and Reconstruction feature.		
	<i>enable</i>	Enable this Content Disarm and Reconstruction feature.		

Parameter	Description	Type	Size	Default						
pdf-act-gotor	Enable/disable stripping of PDF document actions that access other PDF documents.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable this Content Disarm and Reconstruction feature.</td></tr><tr><td>enable</td><td>Enable this Content Disarm and Reconstruction feature.</td></tr></table>	Option	Description	disable	Disable this Content Disarm and Reconstruction feature.	enable	Enable this Content Disarm and Reconstruction feature.			
Option	Description									
disable	Disable this Content Disarm and Reconstruction feature.									
enable	Enable this Content Disarm and Reconstruction feature.									
pdf-act-launch	Enable/disable stripping of PDF document actions that launch other applications.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable this Content Disarm and Reconstruction feature.</td></tr><tr><td>enable</td><td>Enable this Content Disarm and Reconstruction feature.</td></tr></table>	Option	Description	disable	Disable this Content Disarm and Reconstruction feature.	enable	Enable this Content Disarm and Reconstruction feature.			
Option	Description									
disable	Disable this Content Disarm and Reconstruction feature.									
enable	Enable this Content Disarm and Reconstruction feature.									
pdf-act-sound	Enable/disable stripping of PDF document actions that play a sound.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable this Content Disarm and Reconstruction feature.</td></tr><tr><td>enable</td><td>Enable this Content Disarm and Reconstruction feature.</td></tr></table>	Option	Description	disable	Disable this Content Disarm and Reconstruction feature.	enable	Enable this Content Disarm and Reconstruction feature.			
Option	Description									
disable	Disable this Content Disarm and Reconstruction feature.									
enable	Enable this Content Disarm and Reconstruction feature.									
pdf-act-movie	Enable/disable stripping of PDF document actions that play a movie.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable this Content Disarm and Reconstruction feature.</td></tr><tr><td>enable</td><td>Enable this Content Disarm and Reconstruction feature.</td></tr></table>	Option	Description	disable	Disable this Content Disarm and Reconstruction feature.	enable	Enable this Content Disarm and Reconstruction feature.			
Option	Description									
disable	Disable this Content Disarm and Reconstruction feature.									
enable	Enable this Content Disarm and Reconstruction feature.									
pdf-act-java	Enable/disable stripping of PDF document actions that execute JavaScript code.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable this Content Disarm and Reconstruction feature.</td></tr><tr><td>enable</td><td>Enable this Content Disarm and Reconstruction feature.</td></tr></table>	Option	Description	disable	Disable this Content Disarm and Reconstruction feature.	enable	Enable this Content Disarm and Reconstruction feature.			
Option	Description									
disable	Disable this Content Disarm and Reconstruction feature.									
enable	Enable this Content Disarm and Reconstruction feature.									
pdf-act-form	Enable/disable stripping of PDF document actions that submit data to other targets.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable this Content Disarm and Reconstruction feature.</td></tr><tr><td>enable</td><td>Enable this Content Disarm and Reconstruction feature.</td></tr></table>	Option	Description	disable	Disable this Content Disarm and Reconstruction feature.	enable	Enable this Content Disarm and Reconstruction feature.			
Option	Description									
disable	Disable this Content Disarm and Reconstruction feature.									
enable	Enable this Content Disarm and Reconstruction feature.									

Parameter	Description	Type	Size	Default
cover-page	Enable/disable inserting a cover page into the disarmed document.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable this Content Disarm and Reconstruction feature.		
	<i>enable</i>	Enable this Content Disarm and Reconstruction feature.		
detect-only	Enable/disable only detect disarmable files, do not alter content.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable this Content Disarm and Reconstruction feature.		
	<i>enable</i>	Enable this Content Disarm and Reconstruction feature.		

config antivirus quarantine

Configure quarantine options.

```

config antivirus quarantine
  Description: Configure quarantine options.
  set agelimit {integer}
  set maxfilesize {integer}
  set quarantine-quota {integer}
  set drop-infected {option1}, {option2}, ...
  set store-infected {option1}, {option2}, ...
  set drop-blocked {option1}, {option2}, ...
  set store-blocked {option1}, {option2}, ...
  set drop-machine-learning {option1}, {option2}, ...
  set store-machine-learning {option1}, {option2}, ...
  set lowspace [drop-new|ovrw-old]
  set destination [NULL|disk|...]
end

```

config antivirus quarantine

Parameter	Description	Type	Size	Default
agelimit	Age limit for quarantined files (0 - 479 hours, 0 means forever).	integer	Minimum value: 0 Maximum value: 479	0

Parameter	Description	Type	Size	Default																															
maxfilesize	Maximum file size to quarantine (0 - 500 Mbytes, 0 means unlimited).	integer	Minimum value: 0 Maximum value: 500	0																															
quarantine-quota	The amount of disk space to reserve for quarantining files (0 - 4294967295 Mbytes, depends on disk space).	integer	Minimum value: 0 Maximum value: 4294967295	0																															
drop-infected	Do not quarantine infected files found in sessions using the selected protocols. Dropped files are deleted instead of being quarantined.	option	-																																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>imap</td><td>IMAP.</td></tr><tr><td>smtp</td><td>SMTP.</td></tr><tr><td>pop3</td><td>POP3.</td></tr><tr><td>http</td><td>HTTP.</td></tr><tr><td>ftp</td><td>FTP.</td></tr><tr><td>nntp</td><td>NNTP.</td></tr><tr><td>imaps</td><td>IMAPS.</td></tr><tr><td>smtps</td><td>SMTPS.</td></tr><tr><td>pop3s</td><td>POP3S.</td></tr><tr><td>https</td><td>HTTPS.</td></tr><tr><td>ftps</td><td>FTPS.</td></tr><tr><td>mapi</td><td>MAPI.</td></tr><tr><td>cifs</td><td>CIFS.</td></tr><tr><td>ssh</td><td>SSH.</td></tr></table>		Option	Description	imap	IMAP.	smtp	SMTP.	pop3	POP3.	http	HTTP.	ftp	FTP.	nntp	NNTP.	imaps	IMAPS.	smtps	SMTPS.	pop3s	POP3S.	https	HTTPS.	ftps	FTPS.	mapi	MAPI.	cifs	CIFS.	ssh	SSH.			
	Option	Description																																	
	imap	IMAP.																																	
	smtp	SMTP.																																	
	pop3	POP3.																																	
	http	HTTP.																																	
	ftp	FTP.																																	
	nntp	NNTP.																																	
	imaps	IMAPS.																																	
	smtps	SMTPS.																																	
	pop3s	POP3S.																																	
	https	HTTPS.																																	
	ftps	FTPS.																																	
	mapi	MAPI.																																	
	cifs	CIFS.																																	
ssh	SSH.																																		
store-infected	Quarantine infected files found in sessions using the selected protocols.	option	-	imap smtp pop3 http ftp nntp imaps smtps pop3s https ftps mapi cifs ssh																															

Parameter	Description	Type	Size	Default																														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>imap</i></td><td>IMAP.</td></tr><tr><td><i>smtp</i></td><td>SMTP.</td></tr><tr><td><i>pop3</i></td><td>POP3.</td></tr><tr><td><i>http</i></td><td>HTTP.</td></tr><tr><td><i>ftp</i></td><td>FTP.</td></tr><tr><td><i>nntp</i></td><td>NNTP.</td></tr><tr><td><i>imaps</i></td><td>IMAPS.</td></tr><tr><td><i>smtps</i></td><td>SMTPS.</td></tr><tr><td><i>pop3s</i></td><td>POP3S.</td></tr><tr><td><i>https</i></td><td>HTTPS.</td></tr><tr><td><i>ftps</i></td><td>FTPS.</td></tr><tr><td><i>mapi</i></td><td>MAPI.</td></tr><tr><td><i>cifs</i></td><td>CIFS.</td></tr><tr><td><i>ssh</i></td><td>SSH.</td></tr></table>	Option	Description	<i>imap</i>	IMAP.	<i>smtp</i>	SMTP.	<i>pop3</i>	POP3.	<i>http</i>	HTTP.	<i>ftp</i>	FTP.	<i>nntp</i>	NNTP.	<i>imaps</i>	IMAPS.	<i>smtps</i>	SMTPS.	<i>pop3s</i>	POP3S.	<i>https</i>	HTTPS.	<i>ftps</i>	FTPS.	<i>mapi</i>	MAPI.	<i>cifs</i>	CIFS.	<i>ssh</i>	SSH.			
	Option	Description																																
	<i>imap</i>	IMAP.																																
	<i>smtp</i>	SMTP.																																
	<i>pop3</i>	POP3.																																
	<i>http</i>	HTTP.																																
	<i>ftp</i>	FTP.																																
	<i>nntp</i>	NNTP.																																
	<i>imaps</i>	IMAPS.																																
	<i>smtps</i>	SMTPS.																																
	<i>pop3s</i>	POP3S.																																
	<i>https</i>	HTTPS.																																
	<i>ftps</i>	FTPS.																																
	<i>mapi</i>	MAPI.																																
	<i>cifs</i>	CIFS.																																
<i>ssh</i>	SSH.																																	
drop-blocked	Do not quarantine dropped files found in sessions using the selected protocols. Dropped files are deleted instead of being quarantined.	option	-																															
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>imap</i></td><td>IMAP.</td></tr><tr><td><i>smtp</i></td><td>SMTP.</td></tr><tr><td><i>pop3</i></td><td>POP3.</td></tr><tr><td><i>http</i></td><td>HTTP.</td></tr><tr><td><i>ftp</i></td><td>FTP.</td></tr><tr><td><i>nntp</i></td><td>NNTP.</td></tr><tr><td><i>imaps</i></td><td>IMAPS.</td></tr><tr><td><i>smtps</i></td><td>SMTPS.</td></tr><tr><td><i>pop3s</i></td><td>POP3S.</td></tr><tr><td><i>ftps</i></td><td>FTPS.</td></tr><tr><td><i>mapi</i></td><td>MAPI.</td></tr></table>	Option	Description	<i>imap</i>	IMAP.	<i>smtp</i>	SMTP.	<i>pop3</i>	POP3.	<i>http</i>	HTTP.	<i>ftp</i>	FTP.	<i>nntp</i>	NNTP.	<i>imaps</i>	IMAPS.	<i>smtps</i>	SMTPS.	<i>pop3s</i>	POP3S.	<i>ftps</i>	FTPS.	<i>mapi</i>	MAPI.									
	Option	Description																																
	<i>imap</i>	IMAP.																																
	<i>smtp</i>	SMTP.																																
	<i>pop3</i>	POP3.																																
	<i>http</i>	HTTP.																																
	<i>ftp</i>	FTP.																																
	<i>nntp</i>	NNTP.																																
	<i>imaps</i>	IMAPS.																																
	<i>smtps</i>	SMTPS.																																
	<i>pop3s</i>	POP3S.																																
	<i>ftps</i>	FTPS.																																
	<i>mapi</i>	MAPI.																																

Parameter	Description	Type	Size	Default																												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>cifs</i></td><td>CIFS.</td></tr><tr><td><i>ssh</i></td><td>SSH.</td></tr></table>	Option	Description	<i>cifs</i>	CIFS.	<i>ssh</i>	SSH.																									
	Option	Description																														
	<i>cifs</i>	CIFS.																														
<i>ssh</i>	SSH.																															
store-blocked	Quarantine blocked files found in sessions using the selected protocols.	option	-	imap smtp pop3 http ftp nntp imaps smtps pop3s ftps mapi cifs ssh																												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>imap</i></td><td>IMAP.</td></tr><tr><td><i>smtp</i></td><td>SMTP.</td></tr><tr><td><i>pop3</i></td><td>POP3.</td></tr><tr><td><i>http</i></td><td>HTTP.</td></tr><tr><td><i>ftp</i></td><td>FTP.</td></tr><tr><td><i>nntp</i></td><td>NNTP.</td></tr><tr><td><i>imaps</i></td><td>IMAPS.</td></tr><tr><td><i>smtps</i></td><td>SMTPS.</td></tr><tr><td><i>pop3s</i></td><td>POP3S.</td></tr><tr><td><i>ftps</i></td><td>FTPS.</td></tr><tr><td><i>mapi</i></td><td>MAPI.</td></tr><tr><td><i>cifs</i></td><td>CIFS.</td></tr><tr><td><i>ssh</i></td><td>SSH.</td></tr></table>	Option	Description	<i>imap</i>	IMAP.	<i>smtp</i>	SMTP.	<i>pop3</i>	POP3.	<i>http</i>	HTTP.	<i>ftp</i>	FTP.	<i>nntp</i>	NNTP.	<i>imaps</i>	IMAPS.	<i>smtps</i>	SMTPS.	<i>pop3s</i>	POP3S.	<i>ftps</i>	FTPS.	<i>mapi</i>	MAPI.	<i>cifs</i>	CIFS.	<i>ssh</i>	SSH.			
	Option	Description																														
	<i>imap</i>	IMAP.																														
	<i>smtp</i>	SMTP.																														
	<i>pop3</i>	POP3.																														
	<i>http</i>	HTTP.																														
	<i>ftp</i>	FTP.																														
	<i>nntp</i>	NNTP.																														
	<i>imaps</i>	IMAPS.																														
	<i>smtps</i>	SMTPS.																														
	<i>pop3s</i>	POP3S.																														
	<i>ftps</i>	FTPS.																														
	<i>mapi</i>	MAPI.																														
<i>cifs</i>	CIFS.																															
<i>ssh</i>	SSH.																															
drop-machine-learning	Do not quarantine files detected by machine learning found in sessions using the selected protocols. Dropped files are deleted instead of being quarantined.	option	-																													
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>imap</i></td><td>IMAP.</td></tr><tr><td><i>smtp</i></td><td>SMTP.</td></tr></table>	Option	Description	<i>imap</i>	IMAP.	<i>smtp</i>	SMTP.																									
	Option	Description																														
	<i>imap</i>	IMAP.																														
<i>smtp</i>	SMTP.																															

Parameter	Description	Type	Size	Default																										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>pop3</i></td><td>POP3.</td></tr><tr><td><i>http</i></td><td>HTTP.</td></tr><tr><td><i>ftp</i></td><td>FTP.</td></tr><tr><td><i>nntp</i></td><td>NNTP.</td></tr><tr><td><i>imaps</i></td><td>IMAPS.</td></tr><tr><td><i>smtps</i></td><td>SMTPS.</td></tr><tr><td><i>pop3s</i></td><td>POP3S.</td></tr><tr><td><i>https</i></td><td>HTTPS.</td></tr><tr><td><i>ftps</i></td><td>FTPS.</td></tr><tr><td><i>mapi</i></td><td>MAPI.</td></tr><tr><td><i>cifs</i></td><td>CIFS.</td></tr><tr><td><i>ssh</i></td><td>SSH.</td></tr></table>	Option	Description	<i>pop3</i>	POP3.	<i>http</i>	HTTP.	<i>ftp</i>	FTP.	<i>nntp</i>	NNTP.	<i>imaps</i>	IMAPS.	<i>smtps</i>	SMTPS.	<i>pop3s</i>	POP3S.	<i>https</i>	HTTPS.	<i>ftps</i>	FTPS.	<i>mapi</i>	MAPI.	<i>cifs</i>	CIFS.	<i>ssh</i>	SSH.			
	Option	Description																												
	<i>pop3</i>	POP3.																												
	<i>http</i>	HTTP.																												
	<i>ftp</i>	FTP.																												
	<i>nntp</i>	NNTP.																												
	<i>imaps</i>	IMAPS.																												
	<i>smtps</i>	SMTPS.																												
	<i>pop3s</i>	POP3S.																												
	<i>https</i>	HTTPS.																												
	<i>ftps</i>	FTPS.																												
	<i>mapi</i>	MAPI.																												
	<i>cifs</i>	CIFS.																												
	<i>ssh</i>	SSH.																												
store-machine-learning	Quarantine files detected by machine learning found in sessions using the selected protocols.	option	-	imap smtp pop3 http ftp nntp imaps smtps pop3s https ftps mapi cifs ssh																										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>imap</i></td><td>IMAP.</td></tr><tr><td><i>smtp</i></td><td>SMTP.</td></tr><tr><td><i>pop3</i></td><td>POP3.</td></tr><tr><td><i>http</i></td><td>HTTP.</td></tr><tr><td><i>ftp</i></td><td>FTP.</td></tr><tr><td><i>nntp</i></td><td>NNTP.</td></tr><tr><td><i>imaps</i></td><td>IMAPS.</td></tr><tr><td><i>smtps</i></td><td>SMTPS.</td></tr><tr><td><i>pop3s</i></td><td>POP3S.</td></tr></table>	Option	Description	<i>imap</i>	IMAP.	<i>smtp</i>	SMTP.	<i>pop3</i>	POP3.	<i>http</i>	HTTP.	<i>ftp</i>	FTP.	<i>nntp</i>	NNTP.	<i>imaps</i>	IMAPS.	<i>smtps</i>	SMTPS.	<i>pop3s</i>	POP3S.									
	Option	Description																												
	<i>imap</i>	IMAP.																												
	<i>smtp</i>	SMTP.																												
	<i>pop3</i>	POP3.																												
	<i>http</i>	HTTP.																												
	<i>ftp</i>	FTP.																												
	<i>nntp</i>	NNTP.																												
	<i>imaps</i>	IMAPS.																												
	<i>smtps</i>	SMTPS.																												
<i>pop3s</i>	POP3S.																													

Parameter	Description	Type	Size	Default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>https</i></td><td>HTTPS.</td></tr><tr><td><i>ftps</i></td><td>FTPS.</td></tr><tr><td><i>mapi</i></td><td>MAPI.</td></tr><tr><td><i>cifs</i></td><td>CIFS.</td></tr><tr><td><i>ssh</i></td><td>SSH.</td></tr></table>	Option	Description	<i>https</i>	HTTPS.	<i>ftps</i>	FTPS.	<i>mapi</i>	MAPI.	<i>cifs</i>	CIFS.	<i>ssh</i>	SSH.			
	Option	Description														
	<i>https</i>	HTTPS.														
	<i>ftps</i>	FTPS.														
	<i>mapi</i>	MAPI.														
	<i>cifs</i>	CIFS.														
<i>ssh</i>	SSH.															
lowspace	Select the method for handling additional files when running low on disk space.	option	-	ovrw-old												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>drop-new</i></td><td>Drop (delete) the most recently quarantined files.</td></tr><tr><td><i>ovrw-old</i></td><td>Overwrite the oldest quarantined files. That is, the files that are closest to being deleted from the quarantine.</td></tr></table>	Option	Description	<i>drop-new</i>	Drop (delete) the most recently quarantined files.	<i>ovrw-old</i>	Overwrite the oldest quarantined files. That is, the files that are closest to being deleted from the quarantine.									
	Option	Description														
	<i>drop-new</i>	Drop (delete) the most recently quarantined files.														
<i>ovrw-old</i>	Overwrite the oldest quarantined files. That is, the files that are closest to being deleted from the quarantine.															
destination	Choose whether to quarantine files to the FortiProxy disk or to FortiAnalyzer or to delete them instead of quarantining them.	option	-	disk												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>NULL</i></td><td>Files that would be quarantined are deleted.</td></tr><tr><td><i>disk</i></td><td>Quarantine files to the FortiProxy hard disk.</td></tr><tr><td><i>FortiAnalyzer</i></td><td>FortiAnalyzer</td></tr></table>	Option	Description	<i>NULL</i>	Files that would be quarantined are deleted.	<i>disk</i>	Quarantine files to the FortiProxy hard disk.	<i>FortiAnalyzer</i>	FortiAnalyzer							
	Option	Description														
	<i>NULL</i>	Files that would be quarantined are deleted.														
	<i>disk</i>	Quarantine files to the FortiProxy hard disk.														
<i>FortiAnalyzer</i>	FortiAnalyzer															

config antivirus settings

Configure AntiVirus settings.

```
config antivirus settings
  Description: Configure AntiVirus settings.
  set machine-learning-detection [enable|monitor|...]
  set use-extreme-db [enable|disable]
  set grayware [enable|disable]
  set override-timeout {integer}
  set cache-infected-result [enable|disable]
end
```

config antivirus settings

Parameter	Description	Type	Size	Default								
machine-learning-detection	Use machine learning based malware detection.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable machine learning based malware detection.</td></tr><tr><td><i>monitor</i></td><td>Enable machine learning based malware detection for monitoring only.</td></tr><tr><td><i>disable</i></td><td>Disable machine learning based malware detection.</td></tr></table>	Option	Description	<i>enable</i>	Enable machine learning based malware detection.	<i>monitor</i>	Enable machine learning based malware detection for monitoring only.	<i>disable</i>	Disable machine learning based malware detection.			
Option	Description											
<i>enable</i>	Enable machine learning based malware detection.											
<i>monitor</i>	Enable machine learning based malware detection for monitoring only.											
<i>disable</i>	Disable machine learning based malware detection.											
use-extreme-db	Enable/disable the use of Extreme AVDB.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable extreme AVDB.</td></tr><tr><td><i>disable</i></td><td>Disable extreme AVDB.</td></tr></table>	Option	Description	<i>enable</i>	Enable extreme AVDB.	<i>disable</i>	Disable extreme AVDB.					
Option	Description											
<i>enable</i>	Enable extreme AVDB.											
<i>disable</i>	Disable extreme AVDB.											
grayware	Enable/disable grayware detection when an AntiVirus profile is applied to traffic.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable grayware detection.</td></tr><tr><td><i>disable</i></td><td>Disable grayware detection.</td></tr></table>	Option	Description	<i>enable</i>	Enable grayware detection.	<i>disable</i>	Disable grayware detection.					
Option	Description											
<i>enable</i>	Enable grayware detection.											
<i>disable</i>	Disable grayware detection.											
override-timeout	Override the large file scan timeout value in seconds (30 - 3600). Zero is the default value and is used to disable this command. When disabled, the daemon adjusts the large file scan timeout based on the file size.	integer	Minimum value: 30 Maximum value: 3600	0								
cache-infected-result	Enable/disable cache of infected scan results (default = enable).	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable cache of infected scan results.</td></tr><tr><td><i>disable</i></td><td>Disable cache of infected scan results.</td></tr></table>	Option	Description	<i>enable</i>	Enable cache of infected scan results.	<i>disable</i>	Disable cache of infected scan results.					
Option	Description											
<i>enable</i>	Enable cache of infected scan results.											
<i>disable</i>	Disable cache of infected scan results.											

application

This section includes syntax for the following commands:

- [config application custom on page 113](#)
- [config application group on page 114](#)
- [config application list on page 115](#)
- [config application name on page 124](#)
- [config application rule-settings on page 126](#)

config application custom

Configure custom application signatures.

```
config application custom
  Description: Configure custom application signatures.
  edit <tag>
    set id {integer}
    set comment {string}
    set signature {var-string}
    set category {integer}
    set protocol {user}
    set technology {user}
    set behavior {user}
    set vendor {user}
  next
end
```

config application custom

Parameter	Description	Type	Size	Default
tag	Signature tag.	string	Maximum length: 63	
id	Custom application category ID (use ? to view available options).	integer	Minimum value: 0 Maximum value: 4294967295	0
comment	Comment.	string	Maximum length: 63	

Parameter	Description	Type	Size	Default
signature	The text that makes up the actual custom application signature.	var-string	Maximum length: 4095	
category	Custom application category ID (use ? to view available options).	integer	Minimum value: 0 Maximum value: 4294967295	0
protocol	Custom application signature protocol.	user	Not Specified	
technology	Custom application signature technology.	user	Not Specified	
behavior	Custom application signature behavior.	user	Not Specified	
vendor	Custom application signature vendor.	user	Not Specified	

config application group

Configure firewall application groups.

```

config application group
  Description: Configure firewall application groups.
  edit <name>
    set comment {var-string}
    set type [application|filter]
    set application <id1>, <id2>, ...
    set category <id1>, <id2>, ...
    set risk <level1>, <level2>, ...
    set protocols {user}
    set vendor {user}
    set technology {user}
    set behavior {user}
    set popularity {option1}, {option2}, ...
  next
end

```

config application group

Parameter	Description	Type	Size	Default
name	Application group name.	string	Maximum length: 63	
comment	Comments.	var-string	Maximum length: 255	
type	Application group type.	option	-	application

Parameter	Description	Type	Size	Default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>application</i></td><td>Application ID.</td></tr><tr><td><i>filter</i></td><td>Application filter.</td></tr></table>	Option	Description	<i>application</i>	Application ID.	<i>filter</i>	Application filter.									
	Option	Description														
	<i>application</i>	Application ID.														
<i>filter</i>	Application filter.															
application <id>	Application ID list. Application IDs.	integer	Minimum value: 0 Maximum value: 4294967295													
category <id>	Application category ID list. Category IDs.	integer	Minimum value: 0 Maximum value: 4294967295													
risk <level>	Risk, or impact, of allowing traffic from this application to occur (1 - 5; Low, Elevated, Medium, High, and Critical). Risk, or impact, of allowing traffic from this application to occur (1 - 5; Low, Elevated, Medium, High, and Critical).	integer	Minimum value: 0 Maximum value: 4294967295													
protocols	Application protocol filter.	user	Not Specified	all												
vendor	Application vendor filter.	user	Not Specified	all												
technology	Application technology filter.	user	Not Specified	all												
behavior	Application behavior filter.	user	Not Specified	all												
popularity	Application popularity filter (1 - 5, from least to most popular).	option	-	1 2 3 4 5												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>1</td><td>Popularity level 1.</td></tr><tr><td>2</td><td>Popularity level 2.</td></tr><tr><td>3</td><td>Popularity level 3.</td></tr><tr><td>4</td><td>Popularity level 4.</td></tr><tr><td>5</td><td>Popularity level 5.</td></tr></table>	Option	Description	1	Popularity level 1.	2	Popularity level 2.	3	Popularity level 3.	4	Popularity level 4.	5	Popularity level 5.			
	Option	Description														
	1	Popularity level 1.														
	2	Popularity level 2.														
	3	Popularity level 3.														
	4	Popularity level 4.														
5	Popularity level 5.															

config application list

Configure application control lists.

```

config application list
    Description: Configure application control lists.
    edit <name>
        set comment {var-string}
        set replacemsg-group {string}
        set extended-log [enable|disable]
        set other-application-action [pass|block]
        set app-replacemsg [disable|enable]
        set other-application-log [disable|enable]
        set enforce-default-app-port [disable|enable]
        set force-inclusion-ssl-di-sigs [disable|enable]
        set unknown-application-action [pass|block]
        set unknown-application-log [disable|enable]
        set p2p-block-list {option1}, {option2}, ...
        set deep-app-inspection [disable|enable]
        set options {option1}, {option2}, ...
    config entries
        Description: Application list entries.
        edit <id>
            set risk <level1>, <level2>, ...
            set category <id1>, <id2>, ...
            set application <id1>, <id2>, ...
            set protocols {user}
            set vendor {user}
            set technology {user}
            set behavior {user}
            set popularity {option1}, {option2}, ...
            set exclusion <id1>, <id2>, ...
        config parameters
            Description: Application parameters.
            edit <id>
                config members
                    Description: Parameter tuple members.
                    edit <id>
                        set name {string}
                        set value {string}
                    next
                end
            next
        end
        set action [pass|block|...]
        set log [disable|enable]
        set log-packet [disable|enable]
        set rate-count {integer}
        set rate-duration {integer}
        set rate-mode [periodical|continuous]
        set rate-track [none|src-ip|...]
        set session-ttl {integer}
        set shaper {string}
        set quarantine [none|attacker]
        set quarantine-expiry {user}
        set quarantine-log [disable|enable]

```

```

        next
    end
    set control-default-network-services [disable|enable]
    config default-network-services
        Description: Default network service entries.
        edit <id>
            set port {integer}
            set services {option1}, {option2}, ...
            set violation-action [pass|monitor|...]
        next
    end
next
end

```

config application list

Parameter	Description	Type	Size	Default						
name	List name.	string	Maximum length: 35							
comment	Comments.	var-string	Maximum length: 255							
replacemsg-group	Replacement message group.	string	Maximum length: 35							
extended-log	Enable/disable extended logging.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
other-application-action	Action for other applications.	option	-	pass						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>pass</i></td><td>Allow sessions matching an application in this application list.</td></tr><tr><td><i>block</i></td><td>Block sessions matching an application in this application list.</td></tr></table>	Option	Description	<i>pass</i>	Allow sessions matching an application in this application list.	<i>block</i>	Block sessions matching an application in this application list.			
Option	Description									
<i>pass</i>	Allow sessions matching an application in this application list.									
<i>block</i>	Block sessions matching an application in this application list.									
app-replacemsg	Enable/disable replacement messages for blocked applications.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable replacement messages for blocked applications.</td></tr><tr><td><i>enable</i></td><td>Enable replacement messages for blocked applications.</td></tr></table>	Option	Description	<i>disable</i>	Disable replacement messages for blocked applications.	<i>enable</i>	Enable replacement messages for blocked applications.			
Option	Description									
<i>disable</i>	Disable replacement messages for blocked applications.									
<i>enable</i>	Enable replacement messages for blocked applications.									

Parameter	Description	Type	Size	Default						
other-application-log	Enable/disable logging for other applications.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable logging for other applications.</td></tr><tr><td><i>enable</i></td><td>Enable logging for other applications.</td></tr></table>	Option	Description	<i>disable</i>	Disable logging for other applications.	<i>enable</i>	Enable logging for other applications.			
Option	Description									
<i>disable</i>	Disable logging for other applications.									
<i>enable</i>	Enable logging for other applications.									
enforce-default-app-port	Enable/disable default application port enforcement for allowed applications.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable default application port enforcement.</td></tr><tr><td><i>enable</i></td><td>Enable default application port enforcement.</td></tr></table>	Option	Description	<i>disable</i>	Disable default application port enforcement.	<i>enable</i>	Enable default application port enforcement.			
Option	Description									
<i>disable</i>	Disable default application port enforcement.									
<i>enable</i>	Enable default application port enforcement.									
force-inclusion-ssl-di-sigs	Enable/disable forced inclusion of SSL deep inspection signatures.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable forced inclusion of signatures which normally require SSL deep inspection.</td></tr><tr><td><i>enable</i></td><td>Enable forced inclusion of signatures which normally require SSL deep inspection.</td></tr></table>	Option	Description	<i>disable</i>	Disable forced inclusion of signatures which normally require SSL deep inspection.	<i>enable</i>	Enable forced inclusion of signatures which normally require SSL deep inspection.			
Option	Description									
<i>disable</i>	Disable forced inclusion of signatures which normally require SSL deep inspection.									
<i>enable</i>	Enable forced inclusion of signatures which normally require SSL deep inspection.									
unknown-application-action	Pass or block traffic from unknown applications.	option	-	pass						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>pass</i></td><td>Pass or allow unknown applications.</td></tr><tr><td><i>block</i></td><td>Drop or block unknown applications.</td></tr></table>	Option	Description	<i>pass</i>	Pass or allow unknown applications.	<i>block</i>	Drop or block unknown applications.			
Option	Description									
<i>pass</i>	Pass or allow unknown applications.									
<i>block</i>	Drop or block unknown applications.									
unknown-application-log	Enable/disable logging for unknown applications.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable logging for unknown applications.</td></tr><tr><td><i>enable</i></td><td>Enable logging for unknown applications.</td></tr></table>	Option	Description	<i>disable</i>	Disable logging for unknown applications.	<i>enable</i>	Enable logging for unknown applications.			
Option	Description									
<i>disable</i>	Disable logging for unknown applications.									
<i>enable</i>	Enable logging for unknown applications.									

Parameter	Description	Type	Size	Default										
p2p-block-list	P2P applications to be block listed.	option	-											
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>skype</td><td>Skype.</td></tr><tr><td>edonkey</td><td>Edonkey.</td></tr><tr><td>bittorrent</td><td>Bit torrent.</td></tr></table>	Option	Description	skype	Skype.	edonkey	Edonkey.	bittorrent	Bit torrent.					
Option	Description													
skype	Skype.													
edonkey	Edonkey.													
bittorrent	Bit torrent.													
deep-app-inspection	Enable/disable deep application inspection.	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable deep application inspection.</td></tr><tr><td>enable</td><td>Enable deep application inspection.</td></tr></table>	Option	Description	disable	Disable deep application inspection.	enable	Enable deep application inspection.							
Option	Description													
disable	Disable deep application inspection.													
enable	Enable deep application inspection.													
options	Basic application protocol signatures allowed by default.	option	-	allow-dns										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>allow-dns</td><td>Allow DNS.</td></tr><tr><td>allow-icmp</td><td>Allow ICMP.</td></tr><tr><td>allow-http</td><td>Allow generic HTTP web browsing.</td></tr><tr><td>allow-ssl</td><td>Allow generic SSL communication.</td></tr></table>	Option	Description	allow-dns	Allow DNS.	allow-icmp	Allow ICMP.	allow-http	Allow generic HTTP web browsing.	allow-ssl	Allow generic SSL communication.			
Option	Description													
allow-dns	Allow DNS.													
allow-icmp	Allow ICMP.													
allow-http	Allow generic HTTP web browsing.													
allow-ssl	Allow generic SSL communication.													
control-default-network-services	Enable/disable enforcement of protocols over selected ports.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable protocol enforcement over selected ports.</td></tr><tr><td>enable</td><td>Enable protocol enforcement over selected ports.</td></tr></table>	Option	Description	disable	Disable protocol enforcement over selected ports.	enable	Enable protocol enforcement over selected ports.							
Option	Description													
disable	Disable protocol enforcement over selected ports.													
enable	Enable protocol enforcement over selected ports.													

config entries

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

Parameter	Description	Type	Size	Default												
risk <level>	Risk, or impact, of allowing traffic from this application to occur (1 - 5; Low, Elevated, Medium, High, and Critical). Risk, or impact, of allowing traffic from this application to occur (1 - 5; Low, Elevated, Medium, High, and Critical).	integer	Minimum value: 0 Maximum value: 4294967295													
category <id>	Category ID list. Application category ID.	integer	Minimum value: 0 Maximum value: 4294967295													
application <id>	ID of allowed applications. Application IDs.	integer	Minimum value: 0 Maximum value: 4294967295													
protocols	Application protocol filter.	user	Not Specified	all												
vendor	Application vendor filter.	user	Not Specified	all												
technology	Application technology filter.	user	Not Specified	all												
behavior	Application behavior filter.	user	Not Specified	all												
popularity	Application popularity filter (1 - 5, from least to most popular).	option	-	1 2 3 4 5												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>1</td><td>Popularity level 1.</td></tr><tr><td>2</td><td>Popularity level 2.</td></tr><tr><td>3</td><td>Popularity level 3.</td></tr><tr><td>4</td><td>Popularity level 4.</td></tr><tr><td>5</td><td>Popularity level 5.</td></tr></table>				Option	Description	1	Popularity level 1.	2	Popularity level 2.	3	Popularity level 3.	4	Popularity level 4.	5	Popularity level 5.
Option	Description															
1	Popularity level 1.															
2	Popularity level 2.															
3	Popularity level 3.															
4	Popularity level 4.															
5	Popularity level 5.															
exclusion <id>	ID of excluded applications. Excluded application IDs.	integer	Minimum value: 0 Maximum value: 4294967295													
action	Pass or block traffic, or reset connection for traffic from this application.	option	-	block												

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>pass</i>	Pass or allow matching traffic.		
	<i>block</i>	Block or drop matching traffic.		
	<i>reset</i>	Reset sessions for matching traffic.		
log	Enable/disable logging for this application list.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable logging.		
	<i>enable</i>	Enable logging.		
log-packet	Enable/disable packet logging.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable packet logging.		
	<i>enable</i>	Enable packet logging.		
rate-count	Count of the rate.	integer	Minimum value: 0 Maximum value: 65535	0
rate-duration	Duration (sec) of the rate.	integer	Minimum value: 1 Maximum value: 65535	60
rate-mode	Rate limit mode.	option	-	continuous
	Option	Description		
	<i>periodical</i>	Allow configured number of packets every rate-duration.		
	<i>continuous</i>	Block packets once the rate is reached.		
rate-track	Track the packet protocol field.	option	-	none
	Option	Description		
	<i>none</i>	none		
	<i>src-ip</i>	Source IP.		
	<i>dest-ip</i>	Destination IP.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>dhcp-client-mac</i>	DHCP client.		
	<i>dns-domain</i>	DNS domain.		
session-ttl	Session TTL (0 = default).	integer	Minimum value: 0 Maximum value: 4294967295	0
shaper	Traffic shaper.	string	Maximum length: 35	
quarantine	Quarantine method.	option	-	none
	Option	Description		
	<i>none</i>	Quarantine is disabled.		
	<i>attacker</i>	Block all traffic sent from attacker's IP address. The attacker's IP address is also added to the banned user list. The target's address is not affected.		
quarantine-expiry	Duration of quarantine. (Format ###d###h###m, minimum 1m, maximum 364d23h59m, default = 5m). Requires quarantine set to attacker.	user	Not Specified	5m
quarantine-log	Enable/disable quarantine logging.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable quarantine logging.		
	<i>enable</i>	Enable quarantine logging.		

config parameters

Parameter	Description	Type	Size	Default
id	Parameter tuple ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

config members

Parameter	Description	Type	Size	Default
id	Parameter.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Parameter name.	string	Maximum length: 31	
value	Parameter value.	string	Maximum length: 199	

config default-network-services

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
port	Port number.	integer	Minimum value: 0 Maximum value: 65535	0
services	Network protocols.	option	-	
	Option	Description		
	http	HTTP.		
	ssh	SSH.		
	telnet	TELNET.		
	ftp	FTP.		
	dns	DNS.		
	smtp	SMTP.		
	pop3	POP3.		
	imap	IMAP.		
	snmp	SNMP.		
	nntp	NNTP.		
	https	HTTPS.		

Parameter	Description	Type	Size	Default
violation-action	Action for protocols not in the allowlist for selected port.	option	-	block
	Option	Description		
	<i>pass</i>	Allow protocols not in the allowlist for selected port.		
	<i>monitor</i>	Monitor protocols not in the allowlist for selected port.		
	<i>block</i>	Block protocols not in the allowlist for selected port.		

config application name

Configure application signatures.

```

config application name
  Description: Configure application signatures.
  edit <name>
    set id {integer}
    set category {integer}
    set popularity {integer}
    set risk {integer}
    set weight {integer}
    set protocol {user}
    set technology {user}
    set behavior {user}
    set vendor {user}
  config parameters
    Description: Application parameters.
    edit <name>
      set default value {string}
    next
  end
config metadata
  Description: Meta data.
  edit <id>
    set metaid {integer}
    set valueid {integer}
  next
end
next
end

```

config application name

Parameter	Description	Type	Size	Default
name	Application name.	string	Maximum length: 63	
id	Application ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Application category ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
popularity	Application popularity.	integer	Minimum value: 0 Maximum value: 255	0
risk	Application risk.	integer	Minimum value: 0 Maximum value: 255	0
weight	Application weight.	integer	Minimum value: 0 Maximum value: 255	0
protocol	Application protocol.	user	Not Specified	
technology	Application technology.	user	Not Specified	
behavior	Application behavior.	user	Not Specified	
vendor	Application vendor.	user	Not Specified	

config parameters

Parameter	Description	Type	Size	Default
name	Parameter name.	string	Maximum length: 31	
default value	Parameter default value.	string	Maximum length: 199	

config metadata

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
metaid	Meta ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
valueid	Value ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

config application rule-settings

Configure application rule settings.

```
config application rule-settings
    Description: Configure application rule settings.
    edit <id>
    next
end
```

config application rule-settings

Parameter	Description	Type	Size	Default
id	Rule ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

authentication

This section includes syntax for the following commands:

- [config authentication rule on page 127](#)
- [config authentication scheme on page 130](#)
- [config authentication setting on page 132](#)

config authentication rule

Configure Authentication Rules.

```
config authentication rule
  Description: Configure Authentication Rules.
  edit <name>
    set status [enable|disable]
    set protocol [http|ftp|...]
    set web-proxy {string}
    set srcintf <name1>, <name2>, ...
    set srcaddr <name1>, <name2>, ...
    set dstaddr <name1>, <name2>, ...
    set srcaddr6 <name1>, <name2>, ...
    set dstaddr6 <name1>, <name2>, ...
    set ip-based [enable|disable]
    set active-auth-method {string}
    set sso-auth-method {string}
    set web-auth-cookie [enable|disable]
    set cors-stateful [enable|disable]
    set cors-depth {integer}
    set transaction-based [enable|disable]
    set web-portal [enable|disable]
    set comments {var-string}
    set form-auth-fallback [enable|disable]
  next
end
```

config authentication rule

Parameter	Description	Type	Size	Default
name	Authentication rule name.	string	Maximum length: 35	
status	Enable/disable this authentication rule.	option	-	enable

Parameter	Description	Type	Size	Default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable this authentication rule.</td></tr><tr><td><i>disable</i></td><td>Disable this authentication rule.</td></tr></table>	Option	Description	<i>enable</i>	Enable this authentication rule.	<i>disable</i>	Disable this authentication rule.							
	Option	Description												
	<i>enable</i>	Enable this authentication rule.												
<i>disable</i>	Disable this authentication rule.													
protocol	Authentication is required for the selected protocol (default = HTTP).	option	-	http										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>http</i></td><td>HTTP traffic is matched and authentication is required.</td></tr><tr><td><i>ftp</i></td><td>FTP traffic is matched and authentication is required.</td></tr><tr><td><i>socks</i></td><td>SOCKS traffic is matched and authentication is required.</td></tr><tr><td><i>ssh</i></td><td>SSH traffic is matched and authentication is required.</td></tr></table>	Option	Description	<i>http</i>	HTTP traffic is matched and authentication is required.	<i>ftp</i>	FTP traffic is matched and authentication is required.	<i>socks</i>	SOCKS traffic is matched and authentication is required.	<i>ssh</i>	SSH traffic is matched and authentication is required.			
	Option	Description												
	<i>http</i>	HTTP traffic is matched and authentication is required.												
	<i>ftp</i>	FTP traffic is matched and authentication is required.												
	<i>socks</i>	SOCKS traffic is matched and authentication is required.												
<i>ssh</i>	SSH traffic is matched and authentication is required.													
web-proxy	Web-Proxy profile.	string	Maximum length: 35											
srcintf <name>	Incoming (ingress) interface. Interface name.	string	Maximum length: 79											
srcaddr <name>	Authentication is required for the selected IPv4 source address. Address name.	string	Maximum length: 79											
dstaddr <name>	Select an IPv4 destination address from available options. Required for web proxy authentication. Address name.	string	Maximum length: 79											
srcaddr6 <name>	Authentication is required for the selected IPv6 source address. Address name.	string	Maximum length: 79											
dstaddr6 <name>	Select an IPv6 destination address from available options. Required for web proxy authentication. Address name.	string	Maximum length: 79											
ip-based	Enable/disable IP-based authentication. When enabled, previously authenticated users from the same IP address will be exempted.	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable IP-based authentication.</td></tr></table>	Option	Description	<i>enable</i>	Enable IP-based authentication.									
	Option	Description												
<i>enable</i>	Enable IP-based authentication.													

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable IP-based authentication.		
active-auth-method	Select an active authentication method.	string	Maximum length: 35	
sso-auth-method	Select a single-sign on (SSO) authentication method.	string	Maximum length: 35	
web-auth-cookie	Enable/disable Web authentication cookies (default = disable).	option	-	disable
	Option	Description		
	<i>enable</i>	Enable Web authentication cookie.		
	<i>disable</i>	Disable Web authentication cookie.		
cors-stateful	Enable/disable allowance of CORS access (default = disable).	option	-	disable
	Option	Description		
	<i>enable</i>	Enable allowance of CORS access		
	<i>disable</i>	Disable allowance of CORS access		
cors-depth	Depth to allow CORS access (default = 3).	integer	Minimum value: 1 Maximum value: 8	3
transaction-based	Enable/disable transaction based authentication (default = disable).	option	-	disable
	Option	Description		
	<i>enable</i>	Enable transaction based authentication.		
	<i>disable</i>	Disable transaction based authentication.		
web-portal	Enable/disable web portal for proxy transparent policy (default = enable).	option	-	enable
	Option	Description		
	<i>enable</i>	Enable web-portal.		
	<i>disable</i>	Disable web-portal.		

Parameter	Description	Type	Size	Default						
comments	Comment.	var-string	Maximum length: 1023							
form-auth-fallback	Enable/disable to use FORM authentication if needed.(default = disable).	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable Form Authentication Fallback</td></tr><tr><td><i>disable</i></td><td>Disable Form Authentication Fallback</td></tr></table>				Option	Description	<i>enable</i>	Enable Form Authentication Fallback	<i>disable</i>	Disable Form Authentication Fallback
Option	Description									
<i>enable</i>	Enable Form Authentication Fallback									
<i>disable</i>	Disable Form Authentication Fallback									

config authentication scheme

Configure Authentication Schemes.

```

config authentication scheme
  Description: Configure Authentication Schemes.
  edit <name>
    set method {option1}, {option2}, ...
    set auth-user-header {string}
    set negotiate-ntlm [enable|disable]
    set kerberos-keytab {string}
    set domain-controller {string}
    set saml-server {string}
    set saml-timeout {integer}
    set fsso-agent-for-ntlm {string}
    set require-tfa [enable|disable]
    set fsso-guest [enable|disable]
    set user-cert [enable|disable]
    set search-all-ldap-databases [enable|disable]
    set user-database <name1>, <name2>, ...
    set ssh-ca {string}
  next
end

```

config authentication scheme

Parameter	Description	Type	Size	Default
name	Authentication scheme name.	string	Maximum length: 35	
method	Authentication methods (default = basic).	option	-	

Parameter	Description	Type	Size	Default																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ntlm</i></td><td>NTLM authentication.</td></tr><tr><td><i>basic</i></td><td>Basic HTTP authentication.</td></tr><tr><td><i>digest</i></td><td>Digest HTTP authentication.</td></tr><tr><td><i>form</i></td><td>Form-based HTTP authentication.</td></tr><tr><td><i>negotiate</i></td><td>Negotiate authentication.</td></tr><tr><td><i>fsso</i></td><td>Fortinet Single Sign-On (FSSO) authentication.</td></tr><tr><td><i>rsso</i></td><td>RADIUS Single Sign-On (RSSO) authentication.</td></tr><tr><td><i>ssh-publickey</i></td><td>Public key based SSH authentication.</td></tr><tr><td><i>cert</i></td><td>Client certificate authentication.</td></tr><tr><td><i>saml</i></td><td>SAML authentication.</td></tr><tr><td><i>x-auth-user</i></td><td>User from custom HTTP header (default = x-authenticated-user).</td></tr></table>	Option	Description	<i>ntlm</i>	NTLM authentication.	<i>basic</i>	Basic HTTP authentication.	<i>digest</i>	Digest HTTP authentication.	<i>form</i>	Form-based HTTP authentication.	<i>negotiate</i>	Negotiate authentication.	<i>fsso</i>	Fortinet Single Sign-On (FSSO) authentication.	<i>rsso</i>	RADIUS Single Sign-On (RSSO) authentication.	<i>ssh-publickey</i>	Public key based SSH authentication.	<i>cert</i>	Client certificate authentication.	<i>saml</i>	SAML authentication.	<i>x-auth-user</i>	User from custom HTTP header (default = x-authenticated-user).			
	Option	Description																										
	<i>ntlm</i>	NTLM authentication.																										
	<i>basic</i>	Basic HTTP authentication.																										
	<i>digest</i>	Digest HTTP authentication.																										
	<i>form</i>	Form-based HTTP authentication.																										
	<i>negotiate</i>	Negotiate authentication.																										
	<i>fsso</i>	Fortinet Single Sign-On (FSSO) authentication.																										
	<i>rsso</i>	RADIUS Single Sign-On (RSSO) authentication.																										
	<i>ssh-publickey</i>	Public key based SSH authentication.																										
	<i>cert</i>	Client certificate authentication.																										
	<i>saml</i>	SAML authentication.																										
<i>x-auth-user</i>	User from custom HTTP header (default = x-authenticated-user).																											
auth-user-header	Override HTTP header used for authenticated user.	string	Maximum length: 255																									
negotiate-ntlm	Enable/disable negotiate authentication for NTLM (default = disable).	option	-	enable																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable negotiate authentication for NTLM.</td></tr><tr><td><i>disable</i></td><td>Disable negotiate authentication for NTLM.</td></tr></table>	Option	Description	<i>enable</i>	Enable negotiate authentication for NTLM.	<i>disable</i>	Disable negotiate authentication for NTLM.																					
	Option	Description																										
	<i>enable</i>	Enable negotiate authentication for NTLM.																										
<i>disable</i>	Disable negotiate authentication for NTLM.																											
kerberos-keytab	Kerberos keytab setting.	string	Maximum length: 35																									
domain-controller	Domain controller setting.	string	Maximum length: 35																									
saml-server	SAML configuration.	string	Maximum length: 35																									
saml-timeout	SAML authentication timeout in seconds.	integer	Minimum value: 30 Maximum value: 1200	120																								
fsso-agent-for-ntlm	FSSO agent to use for NTLM authentication.	string	Maximum length: 35																									
require-tfa	Enable/disable two-factor authentication (default = disable).	option	-	disable																								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable two-factor authentication.		
	<i>disable</i>	Disable two-factor authentication.		
fsso-guest	Enable/disable user fsso-guest authentication (default = disable).	option	-	disable
	Option	Description		
	<i>enable</i>	Enable user fsso-guest authentication.		
	<i>disable</i>	Disable user fsso-guest authentication.		
user-cert	Enable/disable authentication with user certificate (default = disable).	option	-	disable
	Option	Description		
	<i>enable</i>	Enable client certificate field authentication.		
	<i>disable</i>	Disable client certificate field authentication.		
search-all-ldap-databases	Enable/disable searching all LDAP databases to find groups.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable searching for groups in all LDAP databases.		
	<i>disable</i>	Disable searching for groups in all LDAP databases.		
user-database <name>	Authentication server to contain user information; "local" (default) or "123" (for LDAP). Authentication server name.	string	Maximum length: 79	
ssh-ca	SSH CA name.	string	Maximum length: 35	

config authentication setting

Configure authentication setting.

```
config authentication setting
  Description: Configure authentication setting.
  set active-auth-scheme {string}
  set sso-auth-scheme {string}
  set update-time {user}
```

```

set persistent-cookie [enable|disable]
set ip-auth-cookie [enable|disable]
set cookie-max-age {integer}
set cookie-refresh-div {integer}
set captive-portal-type [fqdn|ip]
set captive-portal-ip {ipv4-address-any}
set captive-portal-ip6 {ipv6-address}
set captive-portal {string}
set captive-portal6 {string}
set cert-auth [enable|disable]
set cert-captive-portal {string}
set cert-captive-portal-ip {ipv4-address-any}
set cert-captive-portal-port {integer}
set captive-portal-port {integer}
set auth-https [enable|disable]
set captive-portal-ssl-port {integer}
set user-cert-ca <name1>, <name2>, ...
set dev-range <name1>, <name2>, ...
set log-auth-request [enable|disable]
end

```

config authentication setting

Parameter	Description	Type	Size	Default
active-auth-scheme	Active authentication method (scheme name).	string	Maximum length: 35	
sso-auth-scheme	Single-Sign-On authentication method (scheme name).	string	Maximum length: 35	
update-time	Time of the last update.	user	Not Specified	
persistent-cookie	Enable/disable persistent cookie on web portal authentication (default = enable).	option	-	enable
	Option		Description	
	enable		Enable persistent cookie.	
	disable		Disable persistent cookie.	
ip-auth-cookie	Enable/disable persistent cookie on IP based web portal authentication (default = disable).	option	-	disable
	Option		Description	
	enable		Enable persistent cookie for IP-based authentication.	
	disable		Disable persistent cookie for IP-based authentication.	

Parameter	Description	Type	Size	Default
cookie-max-age	Persistent web portal cookie maximum age in minutes (30 - 10080 (1 week), default = 480 (8 hours)).	integer	Minimum value: 30 Maximum value: 10080	480
cookie-refresh-div	Refresh rate divider of persistent web portal cookie (default = 2). Refresh value = cookie-max-age/cookie-refresh-div.	integer	Minimum value: 2 Maximum value: 4	2
captive-portal-type	Captive portal type.	option	-	fqdn
	Option	Description		
	fqdn	Use FQDN for captive portal.		
	ip	Use an IP address for captive portal.		
captive-portal-ip	Captive portal IP address.	ipv4-address-any	Not Specified	0.0.0.0
captive-portal-ip6	Captive portal IPv6 address.	ipv6-address	Not Specified	::
captive-portal	Captive portal host name.	string	Maximum length: 255	
captive-portal6	IPv6 captive portal host name.	string	Maximum length: 255	
cert-auth	Enable/disable redirecting certificate authentication to HTTPS portal.	option	-	disable
	Option	Description		
	enable	Enable setting.		
	disable	Disable setting.		
cert-captive-portal	Certificate captive portal host name.	string	Maximum length: 255	
cert-captive-portal-ip	Certificate captive portal IP address.	ipv4-address-any	Not Specified	0.0.0.0

Parameter	Description	Type	Size	Default
cert-captive-portal-port	Certificate captive portal port number (1 - 65535, default = 7832).	integer	Minimum value: 1 Maximum value: 65535	7832
captive-portal-port	Captive portal port number (1 - 65535, default = 7830).	integer	Minimum value: 1 Maximum value: 65535	7830
auth-https	Enable/disable redirecting HTTP user authentication to HTTPS.	option	-	enable
	Option	Description		
	enable	Enable setting.		
	disable	Disable setting.		
captive-portal-ssl-port	Captive portal SSL port number (1 - 65535, default = 7831).	integer	Minimum value: 1 Maximum value: 65535	7831
user-cert-ca <name>	CA certificate used for client certificate verification. CA certificate list.	string	Maximum length: 79	
dev-range <name>	Address range for the IP based device query. Address name.	string	Maximum length: 79	
log-auth-request	Enable/disable to log authentication request.	option	-	disable
	Option	Description		
	enable	Enable setting.		
	disable	Disable setting.		

automation

This section includes syntax for the following commands:

- [config automation setting on page 136](#)

config automation setting

Automation setting configuration.

```
config automation setting
  Description: Automation setting configuration.
  set max-concurrent-stitches {integer}
  set fabric-sync [enable|disable]
end
```

config automation setting

Parameter	Description	Type	Size	Default						
max-concurrent-stitches	Maximum number of automation stitches that are allowed to run concurrently.	integer	Minimum value: 32 Maximum value: 1024	512						
fabric-sync	Enable/disable synchronization of automation settings with security fabric.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Synchronize automation setting with security fabric.</td></tr><tr><td><i>disable</i></td><td>Do not synchronize automation setting with security fabric.</td></tr></table>				Option	Description	<i>enable</i>	Synchronize automation setting with security fabric.	<i>disable</i>	Do not synchronize automation setting with security fabric.
Option	Description									
<i>enable</i>	Synchronize automation setting with security fabric.									
<i>disable</i>	Do not synchronize automation setting with security fabric.									

casb

This section includes syntax for the following commands:

- [config casb profile on page 137](#)
- [config casb saas-application on page 140](#)
- [config casb user-activity on page 141](#)

config casb profile

Configure CASB profile.

```
config casb profile
  Description: Configure CASB profile.
  edit <name>
    set comment {var-string}
    config saas-application
      Description: CASB profile SaaS application.
      edit <name>
        set status [enable|disable]
        set safe-search [enable|disable]
        set safe-search-control <name1>, <name2>, ...
        set tenant-control [enable|disable]
        set tenant-control-tenants <name1>, <name2>, ...
        set domain-control [enable|disable]
        set domain-control-domains <name1>, <name2>, ...
        set log [enable|disable]
        config access-rule
          Description: CASB profile access rule.
          edit <name>
            set bypass {option1}, {option2}, ...
            set action [monitor|bypass|...]
          next
        end
      config custom-control
        Description: CASB profile custom control.
        edit <name>
          config option
            Description: CASB custom control option.
            edit <name>
              set user-input <value1>, <value2>, ...
            next
          end
        next
      end
    next
  end
next
```

```
end
next
end
```

config casb profile

Parameter	Description	Type	Size	Default
name	CASB profile name.	string	Maximum length: 35	
comment	Comment.	var-string	Maximum length: 255	

config saas-application

Parameter	Description	Type	Size	Default						
name	CASB profile SaaS application name.	string	Maximum length: 79							
status	Enable/disable setting.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
safe-search	Enable/disable safe search.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
safe-search-control <name>	CASB profile safe search control. Safe search control name.	string	Maximum length: 79							
tenant-control	Enable/disable tenant control.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									

Parameter	Description	Type	Size	Default						
tenant-control-tenants <name>	CASB profile tenant control tenants. Tenant control tenants name.	string	Maximum length: 79							
domain-control	Enable/disable domain control.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
domain-control-domains <name>	CASB profile domain control domains. Domain control domain name.	string	Maximum length: 79							
log	Enable/disable log settings.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable log setting.</td></tr><tr><td><i>disable</i></td><td>Disable log setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable log setting.	<i>disable</i>	Disable log setting.			
Option	Description									
<i>enable</i>	Enable log setting.									
<i>disable</i>	Disable log setting.									

config access-rule

Parameter	Description	Type	Size	Default												
name	CASB access rule activity name.	string	Maximum length: 79													
bypass	CASB bypass options.	option	-													
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>av</td><td>Exempt from AV scanning.</td></tr><tr><td>dlp</td><td>Exempt from data leak prevention (DLP).</td></tr><tr><td>web-filter</td><td>Exempt from web filter.</td></tr><tr><td>file-filter</td><td>Exempt from file filter.</td></tr><tr><td>video-filter</td><td>Exempt from video filter.</td></tr></table>				Option	Description	av	Exempt from AV scanning.	dlp	Exempt from data leak prevention (DLP).	web-filter	Exempt from web filter.	file-filter	Exempt from file filter.	video-filter	Exempt from video filter.
	Option	Description														
	av	Exempt from AV scanning.														
	dlp	Exempt from data leak prevention (DLP).														
	web-filter	Exempt from web filter.														
	file-filter	Exempt from file filter.														
video-filter	Exempt from video filter.															
action	CASB access rule action.	option	-	monitor												

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>monitor</i>	Log when log is enabled.		
	<i>bypass</i>	Apply bypass options.		
	<i>block</i>	Block the request.		

config custom-control

Parameter	Description	Type	Size	Default
name	CASB custom control user activity name.	string	Maximum length: 79	

config option

Parameter	Description	Type	Size	Default
name	CASB custom control option name.	string	Maximum length: 79	
user-input <value>	CASB custom control user input. user input value.	string	Maximum length: 79	

config casb saas-application

Configure CASB SaaS application.

```

config casb saas-application
  Description: Configure CASB SaaS application.
  edit <name>
    set uuid {string}
    set status [enable|disable]
    set type [built-in|customized]
    set casb-name {string}
    set description {string}
    set domains <domain1>, <domain2>, ...
  next
end

```

config casb saas-application

Parameter	Description	Type	Size	Default						
name	SaaS application name.	string	Maximum length: 79							
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	string	Maximum length: 36							
status	Enable/disable setting.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
type	SaaS application type.	option	-	customized						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>built-in</i></td><td>Built-in SaaS application.</td></tr><tr><td><i>customized</i></td><td>User customized SaaS application.</td></tr></table>	Option	Description	<i>built-in</i>	Built-in SaaS application.	<i>customized</i>	User customized SaaS application.			
Option	Description									
<i>built-in</i>	Built-in SaaS application.									
<i>customized</i>	User customized SaaS application.									
casb-name	SaaS application signature name.	string	Maximum length: 79							
description	SaaS application description.	string	Maximum length: 63							
domains <domain>	SaaS application domain list. Domain list separated by space.	string	Maximum length: 127							

config casb user-activity

Configure CASB user activity.

```
config casb user-activity
  Description: Configure CASB user activity.
  edit <name>
    set uuid {string}
    set status [enable|disable]
    set description {string}
    set type [built-in|customized]
    set casb-name {string}
    set application {string}
    set category [activity-control|tenant-control|...]
    set match-strategy [and|or]
    config match
```

```

Description: CASB user activity match rules.
edit <id>
    set strategy [and|or]
    config rules
        Description: CASB user activity rules.
        edit <id>
            set type [domains|host|...]
            set domains <domain1>, <domain2>, ...
            set methods <method1>, <method2>, ...
            set match-pattern [simple|substr|...]
            set match-value {string}
            set header-name {string}
            set case-sensitive [enable|disable]
            set negate [enable|disable]
        next
    end
next
end
config control-options
    Description: CASB control options.
    edit <name>
        set status [enable|disable]
        config operations
            Description: CASB control option operations.
            edit <name>
                set target [header|path]
                set action [append|prepend|...]
                set direction {option}
                set header-name {string}
                set search-pattern [simple|substr|...]
                set search-key {string}
                set case-sensitive [enable|disable]
                set value-from-input [enable|disable]
                set values <value1>, <value2>, ...
            next
        end
    next
end
next
end
end

```

config casb user-activity

Parameter	Description	Type	Size	Default
name	CASB user activity name.	string	Maximum length: 79	

Parameter	Description	Type	Size	Default												
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	string	Maximum length: 36													
status	CASB user activity status.	option	-	enable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.									
Option	Description															
<i>enable</i>	Enable setting.															
<i>disable</i>	Disable setting.															
description	CASB user activity description.	string	Maximum length: 63													
type	CASB user activity type.	option	-	customized												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>built-in</i></td><td>Built-in CASB user-activity.</td></tr><tr><td><i>customized</i></td><td>User customized CASB user-activity.</td></tr></table>	Option	Description	<i>built-in</i>	Built-in CASB user-activity.	<i>customized</i>	User customized CASB user-activity.									
Option	Description															
<i>built-in</i>	Built-in CASB user-activity.															
<i>customized</i>	User customized CASB user-activity.															
casb-name	CASB user activity signature name.	string	Maximum length: 79													
application	CASB SaaS application name.	string	Maximum length: 79													
category	CASB user activity category.	option	-	activity-control												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>activity-control</i></td><td>Activity control.</td></tr><tr><td><i>tenant-control</i></td><td>Tenant control.</td></tr><tr><td><i>domain-control</i></td><td>Domain control.</td></tr><tr><td><i>safe-search-control</i></td><td>Safe search control.</td></tr><tr><td><i>other</i></td><td>User customized category.</td></tr></table>	Option	Description	<i>activity-control</i>	Activity control.	<i>tenant-control</i>	Tenant control.	<i>domain-control</i>	Domain control.	<i>safe-search-control</i>	Safe search control.	<i>other</i>	User customized category.			
Option	Description															
<i>activity-control</i>	Activity control.															
<i>tenant-control</i>	Tenant control.															
<i>domain-control</i>	Domain control.															
<i>safe-search-control</i>	Safe search control.															
<i>other</i>	User customized category.															
match-strategy	CASB user activity match strategy.	option	-	or												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>and</i></td><td>Match user activity using a logical AND operator.</td></tr><tr><td><i>or</i></td><td>Match user activity using a logical OR operator.</td></tr></table>	Option	Description	<i>and</i>	Match user activity using a logical AND operator.	<i>or</i>	Match user activity using a logical OR operator.									
Option	Description															
<i>and</i>	Match user activity using a logical AND operator.															
<i>or</i>	Match user activity using a logical OR operator.															

config match

Parameter	Description	Type	Size	Default
id	CASB user activity match rules ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
strategy	CASB user activity rules strategy.	option	-	and
	Option	Description		
	<i>and</i>	Match user activity using a logical AND operator.		
	<i>or</i>	Match user activity using a logical OR operator.		

config rules

Parameter	Description	Type	Size	Default
id	CASB user activity rule ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
type	CASB user activity rule type.	option	-	host
	Option	Description		
	<i>domains</i>	Domains.		
	<i>host</i>	Host.		
	<i>path</i>	Path.		
	<i>header</i>	HTTP header.		
	<i>header-value</i>	HTTP header and value.		
	<i>method</i>	HTTP method.		
domains <domain>	CASB user activity domain list. Domain list separated by space.	string	Maximum length: 127	
methods <method>	CASB user activity method list. User activity method.	string	Maximum length: 79	
match-pattern	CASB user activity rule match pattern.	option	-	simple

Parameter	Description	Type	Size	Default
	Option Description			
	<i>simple</i>	Exact string match pattern.		
	<i>substr</i>	Sub-string pattern.		
	<i>regex</i>	Regular expression pattern.		
match-value	CASB user activity rule match value.	string	Maximum length: 1023	
header-name	CASB user activity rule header name.	string	Maximum length: 255	
case-sensitive	CASB user activity match case sensitive.	option	-	disable
	Option Description			
	<i>enable</i>	Enable value case sensitive match.		
	<i>disable</i>	Disable value case sensitive match.		
negate	Enable/disable what the matching strategy must not be.	option	-	disable
	Option Description			
	<i>enable</i>	Matching strategy is negated.		
	<i>disable</i>	Matching strategy is not negated.		

config control-options

Parameter	Description	Type	Size	Default
name	CASB control option name.	string	Maximum length: 79	
status	CASB control option status.	option	-	enable
	Option Description			
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

config operations

Parameter	Description	Type	Size	Default														
name	CASB control option operation name.	string	Maximum length: 79															
target	CASB operation target.	option	-	header														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>header</i></td><td>Header.</td></tr><tr><td><i>path</i></td><td>Path.</td></tr></table>	Option	Description	<i>header</i>	Header.	<i>path</i>	Path.											
Option	Description																	
<i>header</i>	Header.																	
<i>path</i>	Path.																	
action	CASB operation action.	option	-	append														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>append</i></td><td>Append the values after the target.</td></tr><tr><td><i>prepend</i></td><td>Prepend the values before the target.</td></tr><tr><td><i>replace</i></td><td>Replace the target by the value.</td></tr><tr><td><i>new</i></td><td>Create a new header regardless if existing header is found or not.</td></tr><tr><td><i>new-on-not-found</i></td><td>Create new header only if existing HTTP header is not found.</td></tr><tr><td><i>delete</i></td><td>Delete the target.</td></tr></table>	Option	Description	<i>append</i>	Append the values after the target.	<i>prepend</i>	Prepend the values before the target.	<i>replace</i>	Replace the target by the value.	<i>new</i>	Create a new header regardless if existing header is found or not.	<i>new-on-not-found</i>	Create new header only if existing HTTP header is not found.	<i>delete</i>	Delete the target.			
Option	Description																	
<i>append</i>	Append the values after the target.																	
<i>prepend</i>	Prepend the values before the target.																	
<i>replace</i>	Replace the target by the value.																	
<i>new</i>	Create a new header regardless if existing header is found or not.																	
<i>new-on-not-found</i>	Create new header only if existing HTTP header is not found.																	
<i>delete</i>	Delete the target.																	
direction	CASB operation direction.	option	-	request														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>request</i></td><td>Request.</td></tr></table>	Option	Description	<i>request</i>	Request.													
Option	Description																	
<i>request</i>	Request.																	
header-name	CASB operation header name to search.	string	Maximum length: 255															
search-pattern	CASB operation search pattern.	option	-	simple														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>simple</i></td><td>Exact string match pattern.</td></tr><tr><td><i>substr</i></td><td>Sub-string pattern.</td></tr><tr><td><i>regex</i></td><td>Regular expression pattern.</td></tr></table>	Option	Description	<i>simple</i>	Exact string match pattern.	<i>substr</i>	Sub-string pattern.	<i>regex</i>	Regular expression pattern.									
Option	Description																	
<i>simple</i>	Exact string match pattern.																	
<i>substr</i>	Sub-string pattern.																	
<i>regex</i>	Regular expression pattern.																	
search-key	CASB operation key to search.	string	Maximum length: 1023															

Parameter	Description	Type	Size	Default
case-sensitive	CASB operation search case sensitive.	option	-	disable
	Option Description			
	<i>enable</i>	Enable case sensitive search.		
	<i>disable</i>	Disable case sensitive search.		
value-from-input	Enable/disable value from user input.	option	-	disable
	Option Description			
	<i>enable</i>	Enable value from input.		
	<i>disable</i>	Disable value from input.		
values <value>	CASB operation new values. Operation value.	string	Maximum length: 79	

certificate

This section includes syntax for the following commands:

- [config certificate ca on page 148](#)
- [config certificate crl on page 150](#)
- [config certificate local on page 151](#)
- [config certificate remote on page 156](#)

config certificate ca

CA certificate.

```
config certificate ca
  Description: CA certificate.
  edit <name>
    set ca {user}
    set range [global|vdom]
    set source [factory|user|...]
    set ssl-inspection-trusted [enable|disable]
    set scep-url {string}
    set auto-update-days {integer}
    set auto-update-days-warning {integer}
    set source-ip {ipv4-address}
    set ca-identifier {string}
    set obsolete [disable|enable]
  next
end
```

config certificate ca

Parameter	Description	Type	Size	Default
name	Name.	string	Maximum length: 79	
ca	CA certificate as a PEM file.	user	Not Specified	
range	Either global or VDOM IP address range for the CA certificate.	option	-	global

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>global</i>	Global range.		
	<i>vdom</i>	VDOM IP address range.		
source	CA certificate source type.	option	-	user
	Option	Description		
	<i>factory</i>	Factory installed certificate.		
	<i>user</i>	User generated certificate.		
	<i>bundle</i>	Bundle file certificate.		
ssl-inspection-trusted	Enable/disable this CA as a trusted CA for SSL inspection.	option	-	enable
	Option	Description		
	<i>enable</i>	Trusted CA for SSL inspection.		
	<i>disable</i>	Untrusted CA for SSL inspection.		
scep-url	URL of the SCEP server.	string	Maximum length: 255	
auto-update-days	Number of days to wait before requesting an updated CA certificate (0 - 4294967295, 0 = disabled).	integer	Minimum value: 0 Maximum value: 4294967295	0
auto-update-days-warning	Number of days before an expiry-warning message is generated (0 - 4294967295, 0 = disabled).	integer	Minimum value: 0 Maximum value: 4294967295	0
source-ip	Source IP address for communications to the SCEP server.	ipv4-address	Not Specified	0.0.0.0
ca-identifier	CA identifier of the SCEP server.	string	Maximum length: 255	
obsolete	Enable/disable this CA as obsoleted.	option	-	disable
	Option	Description		
	<i>disable</i>	Alive.		
	<i>enable</i>	Obsolete.		

config certificate crl

Certificate Revocation List as a PEM file.

```
config certificate crl
  Description: Certificate Revocation List as a PEM file.
  edit <name>
    set crl {user}
    set range [global|vdom]
    set source [factory|user|...]
    set update-vdom {string}
    set ldap-server {string}
    set ldap-username {string}
    set ldap-password {password}
    set http-url {string}
    set scep-url {string}
    set scep-cert {string}
    set update-interval {integer}
    set source-ip {ipv4-address}
  next
end
```

config certificate crl

Parameter	Description	Type	Size	Default								
name	Name.	string	Maximum length: 35									
crl	Certificate Revocation List as a PEM file.	user	Not Specified									
range	Either global or VDOM IP address range for the certificate.	option	-	global								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>global</i></td><td>Global range.</td></tr><tr><td><i>vdom</i></td><td>VDOM IP address range.</td></tr></table>	Option	Description	<i>global</i>	Global range.	<i>vdom</i>	VDOM IP address range.					
Option	Description											
<i>global</i>	Global range.											
<i>vdom</i>	VDOM IP address range.											
source	Certificate source type.	option	-	user								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>factory</i></td><td>Factory installed certificate.</td></tr><tr><td><i>user</i></td><td>User generated certificate.</td></tr><tr><td><i>bundle</i></td><td>Bundle file certificate.</td></tr></table>	Option	Description	<i>factory</i>	Factory installed certificate.	<i>user</i>	User generated certificate.	<i>bundle</i>	Bundle file certificate.			
Option	Description											
<i>factory</i>	Factory installed certificate.											
<i>user</i>	User generated certificate.											
<i>bundle</i>	Bundle file certificate.											

Parameter	Description	Type	Size	Default
update-vdom	VDOM for CRL update.	string	Maximum length: 31	root
ldap-server	LDAP server name for CRL auto-update.	string	Maximum length: 35	
ldap-username	LDAP server user name.	string	Maximum length: 63	
ldap-password	LDAP server user password.	password	Not Specified	
http-url	HTTP server URL for CRL auto-update.	string	Maximum length: 255	
scep-url	SCEP server URL for CRL auto-update.	string	Maximum length: 255	
scep-cert	Local certificate for SCEP communication for CRL auto-update.	string	Maximum length: 35	Fortinet_CA_SSL
update-interval	Time in seconds before the FortiProxy checks for an updated CRL. Set to 0 to update only when it expires.	integer	Minimum value: 0 Maximum value: 4294967295	0
source-ip	Source IP address for communications to a HTTP or SCEP CA server.	ipv4-address	Not Specified	0.0.0.0

config certificate local

Local keys and certificates.

```

config certificate local
  Description: Local keys and certificates.
  edit <name>
    set type [normal|hsm]
    set password {password}
    set hsm-vendor [safenet|primus]
    set hsm-slot {string}
    set hsm-keytype [rsa|ec]
    set comments {string}
    set private-key {user}
    set certificate {user}
    set csr {user}
    set state {user}
    set scep-url {string}
    set range [global|vdom]
    set source [factory|user|...]

```

```

set auto-regenerate-days {integer}
set auto-regenerate-days-warning {integer}
set scep-password {password}
set ca-identifier {string}
set name-encoding [printable|utf8]
set source-ip {ipv4-address}
set ike-localid {string}
set ike-localid-type [asn1dn|fqdn]
set enroll-protocol [none|scep|...]
set private-key-retain [enable|disable]
set cmp-server {string}
set cmp-path {string}
set cmp-server-cert {string}
set cmp-regeneration-method [keyupdate|renewal]
set acme-ca-url {string}
set acme-domain {string}
set acme-email {string}
set acme-rsa-key-size {integer}
set acme-renew-window {integer}

next
end

```

config certificate local

Parameter	Description	Type	Size	Default
name	Name.	string	Maximum length: 35	
type	Type.	option	-	normal
	Option	Description		
	<i>normal</i>	Normal		
	<i>hsm</i>	HSM		
password	Password as a PEM file.	password	Not Specified	
hsm-vendor	HSM vendor.	option	-	safenet
	Option	Description		
	<i>safenet</i>	Safenet HSM.		
	<i>primus</i>	Securosys Primus HSM.		
hsm-slot	HSM slot to use with this certificate.	string	Maximum length: 35	

Parameter	Description	Type	Size	Default
hsm-keytype	HSM certificate key type.	option	-	rsa
	Option Description			
	<i>rsa</i>	RSA key type.		
	<i>ec</i>	EC key type.		
comments	Comment.	string	Maximum length: 511	
private-key	PEM format key encrypted with a password.	user	Not Specified	
certificate	PEM format certificate.	user	Not Specified	
csr	Certificate Signing Request.	user	Not Specified	
state	Certificate Signing Request State.	user	Not Specified	
scep-url	SCEP server URL.	string	Maximum length: 255	
range	Either a global or VDOM IP address range for the certificate.	option	-	global
	Option Description			
	<i>global</i>	Global range.		
	<i>vdom</i>	VDOM IP address range.		
source	Certificate source type.	option	-	user
	Option Description			
	<i>factory</i>	Factory installed certificate.		
	<i>user</i>	User generated certificate.		
	<i>bundle</i>	Bundle file certificate.		

Parameter	Description	Type	Size	Default
auto-regenerate-days	Number of days to wait before expiry of an updated local certificate is requested (0 = disabled).	integer	Minimum value: 0 Maximum value: 4294967295	0
auto-regenerate-days-warning	Number of days to wait before an expiry warning message is generated (0 = disabled).	integer	Minimum value: 0 Maximum value: 4294967295	0
scep-password	SCEP server challenge password for auto-regeneration.	password	Not Specified	
ca-identifier	CA identifier of the CA server for signing via SCEP.	string	Maximum length: 255	
name-encoding	Name encoding method for auto-regeneration.	option	-	printable
	Option		Description	
	<i>printable</i>		Printable encoding (default).	
	<i>utf8</i>		UTF-8 encoding.	
source-ip	Source IP address for communications to the SCEP server.	ipv4-address	Not Specified	0.0.0.0
ike-localid	Local ID the FortiProxy uses for authentication as a VPN client.	string	Maximum length: 63	
ike-localid-type	IKE local ID type.	option	-	asn1dn

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>asn1dn</i>	ASN.1 distinguished name.		
	<i>fqdn</i>	Fully qualified domain name.		
enroll-protocol	Certificate enrollment protocol.	option	-	none
	Option	Description		
	<i>none</i>	None (default).		
	<i>scep</i>	Simple Certificate Enrollment Protocol.		
	<i>cmpv2</i>	Certificate Management Protocol Version 2.		
	<i>acme2</i>	Automated Certificate Management Environment Version 2.		
private-key-retain	Enable/disable retention of private key during SCEP renewal (default = disable).	option	-	disable
	Option	Description		
	<i>enable</i>	Keep the existing private key during SCEP renewal.		
	<i>disable</i>	Generate a new private key during SCEP renewal.		
cmp-server	Address and port for CMP server (format = address:port).	string	Maximum length: 63	
cmp-path	Path location inside CMP server.	string	Maximum length: 255	
cmp-server-cert	CMP server certificate.	string	Maximum length: 79	
cmp-regeneration-method	CMP auto-regeneration method.	option	-	keyupate

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>keyupate</i>	Key Update.		
	<i>renewal</i>	Renewal.		
acme-ca-url	The URL for the ACME CA server (Let's Encrypt is the default provider).	string	Maximum length: 255	https://acme-v02.api.letsencrypt.org/directory
acme-domain	A valid domain that resolves to this FortiProxy unit.	string	Maximum length: 255	
acme-email	Contact email address that is required by some CAs like LetsEncrypt.	string	Maximum length: 255	
acme-rsa-key-size	Length of the RSA private key of the generated cert (Minimum 2048 bits).	integer	Minimum value: 2048 Maximum value: 4096	2048
acme-renew-window	Beginning of the renewal window (in days before certificate expiration, 30 by default).	integer	Minimum value: 1 Maximum value: 60	30

config certificate remote

Remote certificate as a PEM file.

```

config certificate remote
  Description: Remote certificate as a PEM file.
  edit <name>
    set remote {user}
    set range [global|vdom]
    set source [factory|user|...]
  next
end

```

config certificate remote

Parameter	Description	Type	Size	Default								
name	Name.	string	Maximum length: 35									
remote	Remote certificate.	user	Not Specified									
range	Either the global or VDOM IP address range for the remote certificate.	option	-	global								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>global</i></td><td>Global range.</td></tr><tr><td><i>vdom</i></td><td>VDOM IP address range.</td></tr></table>	Option	Description	<i>global</i>	Global range.	<i>vdom</i>	VDOM IP address range.					
Option	Description											
<i>global</i>	Global range.											
<i>vdom</i>	VDOM IP address range.											
source	Remote certificate source type.	option	-	user								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>factory</i></td><td>Factory installed certificate.</td></tr><tr><td><i>user</i></td><td>User generated certificate.</td></tr><tr><td><i>bundle</i></td><td>Bundle file certificate.</td></tr></table>	Option	Description	<i>factory</i>	Factory installed certificate.	<i>user</i>	User generated certificate.	<i>bundle</i>	Bundle file certificate.			
Option	Description											
<i>factory</i>	Factory installed certificate.											
<i>user</i>	User generated certificate.											
<i>bundle</i>	Bundle file certificate.											

dlp

This section includes syntax for the following commands:

- [config dlp data-type on page 158](#)
- [config dlp dictionary on page 160](#)
- [config dlp exact-data-match on page 162](#)
- [config dlp filepattern on page 163](#)
- [config dlp fp-doc-source on page 166](#)
- [config dlp profile on page 169](#)
- [config dlp sensitivity on page 174](#)
- [config dlp sensor on page 175](#)
- [config dlp settings on page 176](#)

config dlp data-type

Configure predefined data type used by DLP blocking.

```
config dlp data-type
  Description: Configure predefined data type used by DLP blocking.
  edit <name>
    set pattern {string}
    set verify {string}
    set verify2 {string}
    set match-around {string}
    set look-back {integer}
    set look-ahead {integer}
    set match-back {integer}
    set match-ahead {integer}
    set transform {string}
    set verify-transformed-pattern [enable|disable]
    set comment {var-string}
  next
end
```

config dlp data-type

Parameter	Description	Type	Size	Default
name	Name of table containing the data type.	string	Maximum length: 35	

Parameter	Description	Type	Size	Default						
pattern	Regular expression pattern string without look around.	string	Maximum length: 255							
verify	Regular expression pattern string used to verify the data type.	string	Maximum length: 255							
verify2	Extra regular expression pattern string used to verify the data type.	string	Maximum length: 255							
match-around	Dictionary to check whether it has a match around (Only support match-any and basic types, no repeat supported).	string	Maximum length: 35							
look-back	Number of characters required to save for verification (1 - 255, default = 1).	integer	Minimum value: 1 Maximum value: 255	1						
look-ahead	Number of characters to obtain in advance for verification (1 - 255, default = 1).	integer	Minimum value: 1 Maximum value: 255	1						
match-back	Number of characters in front for match-around (1 - 4096, default = 1).	integer	Minimum value: 1 Maximum value: 4096	1						
match-ahead	Number of characters behind for match-around (1 - 4096, default = 1).	integer	Minimum value: 1 Maximum value: 4096	1						
transform	Template to transform user input to a pattern using capture group from 'pattern'.	string	Maximum length: 255							
verify-transformed-pattern	Enable/disable verification for transformed pattern.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable verification for transformed pattern.</td></tr><tr><td><i>disable</i></td><td>Disable verification for transformed pattern.</td></tr></table>				Option	Description	<i>enable</i>	Enable verification for transformed pattern.	<i>disable</i>	Disable verification for transformed pattern.
Option	Description									
<i>enable</i>	Enable verification for transformed pattern.									
<i>disable</i>	Disable verification for transformed pattern.									
comment	Optional comments.	var-string	Maximum length: 255							

config dlp dictionary

Configure dictionaries used by DLP blocking.

```
config dlp dictionary
  Description: Configure dictionaries used by DLP blocking.
  edit <name>
    set uuid {uuid}
    set match-type [match-all|match-any]
    set match-around [enable|disable]
    set comment {var-string}
    config entries
      Description: DLP dictionary entries.
      edit <id>
        set type {string}
        set pattern {string}
        set ignore-case [enable|disable]
        set repeat [enable|disable]
        set status [enable|disable]
        set comment {var-string}
      next
    end
  next
end
```

config dlp dictionary

Parameter	Description	Type	Size	Default
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000
name	Name of table containing the dictionary.	string	Maximum length: 35	
match-type	Logical relation between entries (default = match-any).	option	-	match-any
	Option	Description		
	<i>match-all</i>	Match all entries.		
	<i>match-any</i>	Match any entries.		
match-around	Enable/disable match-around support.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable match-around support.		
	<i>disable</i>	Disable match-around support.		
comment	Optional comments.	var-string	Maximum length: 255	

config entries

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
type	Pattern type to match.	string	Maximum length: 35	
pattern	Pattern to match.	string	Maximum length: 255	
ignore-case	Enable/disable ignore case.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable ignore case.		
	<i>disable</i>	Disable ignore case.		
repeat	Enable/disable repeat match.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable repeat match.		
	<i>disable</i>	Disable repeat match.		
status	Enable/disable this pattern.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable this pattern.		
	<i>disable</i>	Disable this pattern.		
comment	Optional comments.	var-string	Maximum length: 255	

config dlp exact-data-match

Configure exact-data-match template used by DLP scan.

```
config dlp exact-data-match
  Description: Configure exact-data-match template used by DLP scan.
  edit <name>
    set optional {integer}
    set data {string}
    config columns
      Description: DLP exact-data-match column types.
      edit <index>
        set type {string}
        set optional [enable|disable]
      next
    end
  next
end
```

config dlp exact-data-match

Parameter	Description	Type	Size	Default
name	Name of table containing the exact-data-match template.	string	Maximum length: 35	
optional	Number of optional columns need to match.	integer	Minimum value: 0 Maximum value: 32	0
data	External resource for exact data match.	string	Maximum length: 35	

config columns

Parameter	Description	Type	Size	Default
index	Column index.	integer	Minimum value: 1 Maximum value: 32	0
type	Data-type for this column.	string	Maximum length: 35	
optional	Enable/disable optional match.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable optional match.		
	<i>disable</i>	Disable optional match.		

config dlp filepattern

Configure file patterns used by DLP blocking.

```
config dlp filepattern
  Description: Configure file patterns used by DLP blocking.
  edit <id>
    set name {string}
    set comment {var-string}
    config entries
      Description: Configure file patterns used by DLP blocking.
      edit <pattern>
        set filter-type [pattern|type]
        set file-type [7z|arj|...]
      next
    end
  next
end
```

config dlp filepattern

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Name of table containing the file pattern list.	string	Maximum length: 63	
comment	Optional comments.	var-string	Maximum length: 255	

config entries

Parameter	Description	Type	Size	Default
filter-type	Filter by file name pattern or by file type.	option	-	pattern
	Option	Description		
	<i>pattern</i>	Filter by file name pattern.		
	<i>type</i>	Filter by file type.		
pattern	Add a file name pattern.	string	Maximum length: 79	
file-type	Select a file type.	option	-	unknown
	Option	Description		
	<i>7z</i>	Match 7-zip files.		
	<i>arj</i>	Match arj compressed files.		
	<i>cab</i>	Match Windows cab files.		
	<i>lzh</i>	Match lzh compressed files.		
	<i>rar</i>	Match rar archives.		
	<i>tar</i>	Match tar files.		
	<i>zip</i>	Match zip files.		
	<i>bzip</i>	Match bzip files.		
	<i>gzip</i>	Match gzip files.		
	<i>bzip2</i>	Match bzip2 files.		
	<i>xz</i>	Match xz files.		
	<i>bat</i>	Match Windows batch files.		
	<i>uue</i>	Match uue files.		
	<i>mime</i>	Match mime files.		
	<i>base64</i>	Match base64 files.		
	<i>binhex</i>	Match binhex files.		
	<i>elf</i>	Match elf files.		
	<i>exe</i>	Match Windows executable files.		
	<i>hta</i>	Match hta files.		
	<i>html</i>	Match html files.		
	<i>jad</i>	Match jad files.		

Parameter	Description	Type	Size	Default

Option	Description
<i>class</i>	Match class files.
<i>cod</i>	Match cod files.
<i>javascript</i>	Match javascript files.
<i>msoffice</i>	Match MS-Office files. For example, doc, xls, ppt, and so on.
<i>msofficex</i>	Match MS-Office XML files. For example, docx, xlsx, pptx, and so on.
<i>fsg</i>	Match fsg files.
<i>upx</i>	Match upx files.
<i>petite</i>	Match petite files.
<i>aspack</i>	Match aspack files.
<i>sis</i>	Match sis files.
<i>hlp</i>	Match Windows help files.
<i>activemime</i>	Match activemime files.
<i>jpeg</i>	Match jpeg files.
<i>gif</i>	Match gif files.
<i>tiff</i>	Match tiff files.
<i>png</i>	Match png files.
<i>bmp</i>	Match bmp files.
<i>unknown</i>	Match unknown files.
<i>mpeg</i>	Match mpeg files.
<i>mov</i>	Match mov files.
<i>mp3</i>	Match mp3 files.
<i>wma</i>	Match wma files.
<i>wav</i>	Match wav files.
<i>pdf</i>	Match Acrobat PDF files.
<i>avi</i>	Match avi files.
<i>rm</i>	Match rm files.
<i>torrent</i>	Match torrent files.
<i>hibun</i>	Match special-file-23-support files.

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>msi</i>	Match Windows Installer msi files.		
	<i>mach-o</i>	Match Mach object files.		
	<i>dmg</i>	Match Apple disk image files.		
	<i>.net</i>	Match .NET files.		
	<i>xar</i>	Match xar archive files.		
	<i>chm</i>	Match Windows compiled HTML help files.		
	<i>iso</i>	Match ISO archive files.		
	<i>crx</i>	Match Chrome extension files.		
	<i>flac</i>	Match flac files.		

config dlp fp-doc-source

Create a DLP fingerprint database by allowing the FortiProxy to access a file server containing files from which to create fingerprints.

```
config dlp fp-doc-source
    Description: Create a DLP fingerprint database by allowing the FortiProxy to access a file
    server containing files from which to create fingerprints.
    edit <name>
        set server-type {option}
        set server {string}
        set period [none|daily|...]
        set vdom [mgmt|current]
        set scan-subdirectories [enable|disable]
        set scan-on-creation [enable|disable]
        set remove-deleted [enable|disable]
        set keep-modified [enable|disable]
        set username {string}
        set password {password}
        set file-path {string}
        set file-pattern {string}
        set sensitivity {string}
        set tod-hour {integer}
        set tod-min {integer}
        set weekday [sunday|monday|...]
        set date {integer}
    next
end
```

config dlp fp-doc-source

Parameter	Description	Type	Size	Default										
name	Name of the DLP fingerprint database.	string	Maximum length: 35											
server-type	Protocol used to communicate with the file server. Currently only Samba (SMB) servers are supported.	option	-	samba										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>samba</td><td>SAMBA server.</td></tr></table>				Option	Description	samba	SAMBA server.						
Option	Description													
samba	SAMBA server.													
server	IPv4 or IPv6 address of the server.	string	Maximum length: 35											
period	Frequency for which the FortiProxy checks the server for new or changed files.	option	-	none										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>none</td><td>Check the server when the FortiProxy starts up.</td></tr><tr><td>daily</td><td>Check the server once a day.</td></tr><tr><td>weekly</td><td>Check the server once a week.</td></tr><tr><td>monthly</td><td>Check the server once a month.</td></tr></table>				Option	Description	none	Check the server when the FortiProxy starts up.	daily	Check the server once a day.	weekly	Check the server once a week.	monthly	Check the server once a month.
Option	Description													
none	Check the server when the FortiProxy starts up.													
daily	Check the server once a day.													
weekly	Check the server once a week.													
monthly	Check the server once a month.													
vdom	Select the VDOM that can communicate with the file server.	option	-	mgmt										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>mgmt</td><td>Communicate with the file server through the management VDOM.</td></tr><tr><td>current</td><td>Communicate with the file server through the VDOM containing this DLP fingerprint database configuration.</td></tr></table>				Option	Description	mgmt	Communicate with the file server through the management VDOM.	current	Communicate with the file server through the VDOM containing this DLP fingerprint database configuration.				
Option	Description													
mgmt	Communicate with the file server through the management VDOM.													
current	Communicate with the file server through the VDOM containing this DLP fingerprint database configuration.													
scan-subdirectories	Enable/disable scanning subdirectories to find files to create fingerprints from.	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Scan subdirectories.</td></tr><tr><td>disable</td><td>Do not scan subdirectories.</td></tr></table>				Option	Description	enable	Scan subdirectories.	disable	Do not scan subdirectories.				
Option	Description													
enable	Scan subdirectories.													
disable	Do not scan subdirectories.													

Parameter	Description	Type	Size	Default
scan-on-creation	Enable to keep the fingerprint database up to date when a file is added or changed on the server.	option	-	enable
	Option	Description		
	<i>enable</i>	Keep the fingerprint database up to date when a file is added or changed on the server.		
	<i>disable</i>	Do not check for added or changed files on the server. Saves system resources.		
remove-deleted	Enable to keep the fingerprint database up to date when a file is deleted from the server.	option	-	enable
	Option	Description		
	<i>enable</i>	Keep the fingerprint database up to date when a file is deleted from the server.		
	<i>disable</i>	Do not check for deleted files on the server. Saves system resources.		
keep-modified	Enable so that when a file is changed on the server the FortiProxy keeps the old fingerprint and adds a new fingerprint to the database.	option	-	enable
	Option	Description		
	<i>enable</i>	Keep the old fingerprint and add a new fingerprint when a file is changed on the server.		
	<i>disable</i>	Replace the old fingerprint with the new fingerprint when a file is changed on the server.		
username	User name required to log into the file server.	string	Maximum length: 35	
password	Password required to log into the file server.	password	Not Specified	
file-path	Path on the server to the fingerprint files (max 119 characters).	string	Maximum length: 119	
file-pattern	Files matching this pattern on the server are fingerprinted. Optionally use the * and ? wildcards.	string	Maximum length: 35	*

Parameter	Description	Type	Size	Default
sensitivity	Select a sensitivity or threat level for matches with this fingerprint database. Add sensitivities using sensitivity.	string	Maximum length: 35	
tod-hour	Hour of the day on which to scan the server (0 - 23, default = 1).	integer	Minimum value: 0 Maximum value: 23	1
tod-min	Minute of the hour on which to scan the server (0 - 59).	integer	Minimum value: 0 Maximum value: 59	0
weekday	Day of the week on which to scan the server.	option	-	sunday
	Option		Description	
	sunday		Sunday	
	monday		Monday	
	tuesday		Tuesday	
	wednesday		Wednesday	
	thursday		Thursday	
	friday		Friday	
	saturday		Saturday	
date	Day of the month on which to scan the server (1 - 31).	integer	Minimum value: 1 Maximum value: 31	1

config dlp profile

Configure DLP profiles.

```

config dlp profile
  Description: Configure DLP profiles.
  edit <name>
    set comment {var-string}
    set feature-set [flow|proxy]
    set replacemsg-group {string}
    config rule
      Description: Set up DLP rules for this profile.
      edit <id>

```

```

        set name {string}
        set severity [info|low|...]
        set type [file|message]
        set proto {option1}, {option2}, ...
        set filter-by [sensor|mip|...]
        set file-size {integer}
        set sensitivity <name1>, <name2>, ...
        set match-percentage {integer}
        set file-type {integer}
        set sensor <name1>, <name2>, ...
        set label {string}
        set archive [disable|enable]
        set action [allow|log-only|...]
        set expiry {user}
    next
end
set dlp-log [enable|disable]
set nac-quar-log [enable|disable]
set full-archive-proto {option1}, {option2}, ...
set summary-proto {option1}, {option2}, ...
next
end

```

config dlp profile

Parameter	Description	Type	Size	Default						
name	Name of the DLP profile.	string	Maximum length: 35							
comment	Comment.	var-string	Maximum length: 255							
feature-set	Flow/proxy feature set.	option	-	proxy						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>flow</i></td><td>Flow feature set.</td></tr><tr><td><i>proxy</i></td><td>Proxy feature set.</td></tr></table>	Option	Description	<i>flow</i>	Flow feature set.	<i>proxy</i>	Proxy feature set.			
Option	Description									
<i>flow</i>	Flow feature set.									
<i>proxy</i>	Proxy feature set.									
replacemsg-group	Replacement message group used by this DLP profile.	string	Maximum length: 35							
dlp-log	Enable/disable DLP logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable DLP logging.</td></tr><tr><td><i>disable</i></td><td>Disable DLP logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable DLP logging.	<i>disable</i>	Disable DLP logging.			
Option	Description									
<i>enable</i>	Enable DLP logging.									
<i>disable</i>	Disable DLP logging.									

Parameter	Description	Type	Size	Default																						
nac-quar-log	Enable/disable NAC quarantine logging.	option	-	disable																						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable NAC quarantine logging.</td></tr><tr><td><i>disable</i></td><td>Disable NAC quarantine logging.</td></tr></table>				Option	Description	<i>enable</i>	Enable NAC quarantine logging.	<i>disable</i>	Disable NAC quarantine logging.																
	Option	Description																								
	<i>enable</i>	Enable NAC quarantine logging.																								
<i>disable</i>	Disable NAC quarantine logging.																									
full-archive-proto	Protocols to always content archive.	option	-																							
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>smtp</i></td><td>SMTP.</td></tr><tr><td><i>pop3</i></td><td>POP3.</td></tr><tr><td><i>imap</i></td><td>IMAP.</td></tr><tr><td><i>http-get</i></td><td>HTTP GET.</td></tr><tr><td><i>http-post</i></td><td>HTTP POST.</td></tr><tr><td><i>ftp</i></td><td>FTP.</td></tr><tr><td><i>nntp</i></td><td>NNTP.</td></tr><tr><td><i>mapi</i></td><td>MAPI.</td></tr><tr><td><i>ssh</i></td><td>SFTP and SCP.</td></tr><tr><td><i>cifs</i></td><td>CIFS.</td></tr></table>				Option	Description	<i>smtp</i>	SMTP.	<i>pop3</i>	POP3.	<i>imap</i>	IMAP.	<i>http-get</i>	HTTP GET.	<i>http-post</i>	HTTP POST.	<i>ftp</i>	FTP.	<i>nntp</i>	NNTP.	<i>mapi</i>	MAPI.	<i>ssh</i>	SFTP and SCP.	<i>cifs</i>	CIFS.
	Option	Description																								
	<i>smtp</i>	SMTP.																								
	<i>pop3</i>	POP3.																								
	<i>imap</i>	IMAP.																								
	<i>http-get</i>	HTTP GET.																								
	<i>http-post</i>	HTTP POST.																								
	<i>ftp</i>	FTP.																								
	<i>nntp</i>	NNTP.																								
	<i>mapi</i>	MAPI.																								
	<i>ssh</i>	SFTP and SCP.																								
<i>cifs</i>	CIFS.																									
summary-proto	Protocols to always log summary.	option	-																							
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>smtp</i></td><td>SMTP.</td></tr><tr><td><i>pop3</i></td><td>POP3.</td></tr><tr><td><i>imap</i></td><td>IMAP.</td></tr><tr><td><i>http-get</i></td><td>HTTP GET.</td></tr><tr><td><i>http-post</i></td><td>HTTP POST.</td></tr><tr><td><i>ftp</i></td><td>FTP.</td></tr><tr><td><i>nntp</i></td><td>NNTP.</td></tr><tr><td><i>mapi</i></td><td>MAPI.</td></tr><tr><td><i>ssh</i></td><td>SFTP and SCP.</td></tr><tr><td><i>cifs</i></td><td>CIFS.</td></tr></table>				Option	Description	<i>smtp</i>	SMTP.	<i>pop3</i>	POP3.	<i>imap</i>	IMAP.	<i>http-get</i>	HTTP GET.	<i>http-post</i>	HTTP POST.	<i>ftp</i>	FTP.	<i>nntp</i>	NNTP.	<i>mapi</i>	MAPI.	<i>ssh</i>	SFTP and SCP.	<i>cifs</i>	CIFS.
	Option	Description																								
	<i>smtp</i>	SMTP.																								
	<i>pop3</i>	POP3.																								
	<i>imap</i>	IMAP.																								
	<i>http-get</i>	HTTP GET.																								
	<i>http-post</i>	HTTP POST.																								
	<i>ftp</i>	FTP.																								
	<i>nntp</i>	NNTP.																								
	<i>mapi</i>	MAPI.																								
	<i>ssh</i>	SFTP and SCP.																								
<i>cifs</i>	CIFS.																									

config rule

Parameter	Description	Type	Size	Default																
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0																
name	Filter name.	string	Maximum length: 35																	
severity	Select the severity or threat level that matches this filter.	option	-	medium																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>info</td><td>Informational.</td></tr><tr><td>low</td><td>Low.</td></tr><tr><td>medium</td><td>Medium.</td></tr><tr><td>high</td><td>High.</td></tr><tr><td>critical</td><td>Critical.</td></tr></table>				Option	Description	info	Informational.	low	Low.	medium	Medium.	high	High.	critical	Critical.				
Option	Description																			
info	Informational.																			
low	Low.																			
medium	Medium.																			
high	High.																			
critical	Critical.																			
type	Select whether to check the content of messages (an email message) or files (downloaded files or email attachments).	option	-	file																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>file</td><td>Check the contents of downloaded or attached files.</td></tr><tr><td>message</td><td>Check the contents of email messages, web pages, etc.</td></tr></table>				Option	Description	file	Check the contents of downloaded or attached files.	message	Check the contents of email messages, web pages, etc.										
Option	Description																			
file	Check the contents of downloaded or attached files.																			
message	Check the contents of email messages, web pages, etc.																			
proto	Check messages or files over one or more of these protocols.	option	-																	
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>smtp</td><td>SMTP.</td></tr><tr><td>pop3</td><td>POP3.</td></tr><tr><td>imap</td><td>IMAP.</td></tr><tr><td>http-get</td><td>HTTP GET.</td></tr><tr><td>http-post</td><td>HTTP POST.</td></tr><tr><td>ftp</td><td>FTP.</td></tr><tr><td>nntp</td><td>NNTP.</td></tr></table>				Option	Description	smtp	SMTP.	pop3	POP3.	imap	IMAP.	http-get	HTTP GET.	http-post	HTTP POST.	ftp	FTP.	nntp	NNTP.
Option	Description																			
smtp	SMTP.																			
pop3	POP3.																			
imap	IMAP.																			
http-get	HTTP GET.																			
http-post	HTTP POST.																			
ftp	FTP.																			
nntp	NNTP.																			

Parameter	Description	Type	Size	Default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>mapi</i></td><td>MAPI.</td></tr><tr><td><i>ssh</i></td><td>SFTP and SCP.</td></tr><tr><td><i>cifs</i></td><td>CIFS.</td></tr></table>	Option	Description	<i>mapi</i>	MAPI.	<i>ssh</i>	SFTP and SCP.	<i>cifs</i>	CIFS.							
	Option	Description														
	<i>mapi</i>	MAPI.														
	<i>ssh</i>	SFTP and SCP.														
<i>cifs</i>	CIFS.															
filter-by	Select the type of content to match.	option	-	none												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>sensor</i></td><td>Use DLP sensors to match content.</td></tr><tr><td><i>mip</i></td><td>Use MIP label dictionary to match content.</td></tr><tr><td><i>fingerprint</i></td><td>Match against a fingerprint sensitivity.</td></tr><tr><td><i>encrypted</i></td><td>Look for encrypted files.</td></tr><tr><td><i>none</i></td><td>No content scan.</td></tr></table>	Option	Description	<i>sensor</i>	Use DLP sensors to match content.	<i>mip</i>	Use MIP label dictionary to match content.	<i>fingerprint</i>	Match against a fingerprint sensitivity.	<i>encrypted</i>	Look for encrypted files.	<i>none</i>	No content scan.			
	Option	Description														
	<i>sensor</i>	Use DLP sensors to match content.														
	<i>mip</i>	Use MIP label dictionary to match content.														
	<i>fingerprint</i>	Match against a fingerprint sensitivity.														
	<i>encrypted</i>	Look for encrypted files.														
<i>none</i>	No content scan.															
file-size	Match files this size or larger (0 - 4294967295 kbytes).	integer	Minimum value: 0 Maximum value: 4294967295	0												
sensitivity <name>	Select a DLP file pattern sensitivity to match. Select a DLP sensitivity.	string	Maximum length: 35													
match-percentage	Percentage of fingerprints in the fingerprint databases designated with the selected sensitivity to match.	integer	Minimum value: 1 Maximum value: 100	10												
file-type	Select the number of a DLP file pattern table to match.	integer	Minimum value: 0 Maximum value: 4294967295	0												
sensor <name>	Select DLP sensors. Address name.	string	Maximum length: 35													
label	MIP label dictionary.	string	Maximum length: 35													
archive	Enable/disable DLP archiving.	option	-	disable												

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	No DLP archiving.		
	<i>enable</i>	Enable full DLP archiving.		
action	Action to take with content that this DLP profile matches.	option	-	allow
	Option	Description		
	<i>allow</i>	Allow the content to pass through the FortiProxy and do not create a log message.		
	<i>log-only</i>	Allow the content to pass through the FortiProxy, but write a log message.		
	<i>block</i>	Block the content and write a log message.		
	<i>quarantine-ip</i>	Quarantine all traffic from the IP address and write a log message.		
expiry	Quarantine duration in days, hours, minutes (format = dddhhmm).	user	Not Specified	5m

config dlp sensitivity

Create self-explanatory DLP sensitivity levels to be used when setting sensitivity under config fp-doc-source.

```
config dlp sensitivity
    Description: Create self-explanatory DLP sensitivity levels to be used when setting
    sensitivity under config fp-doc-source.
    edit <name>
        next
    end
```

config dlp sensitivity

Parameter	Description	Type	Size	Default
name	DLP Sensitivity Levels.	string	Maximum length: 35	

config dlp sensor

Configure sensors used by DLP blocking.

```
config dlp sensor
  Description: Configure sensors used by DLP blocking.
  edit <name>
    set match-type [match-all|match-any|...]
    set eval {string}
    set comment {var-string}
    config entries
      Description: DLP sensor entries.
      edit <id>
        set dictionary {string}
        set count {integer}
        set status [enable|disable]
      next
    end
  next
end
```

config dlp sensor

Parameter	Description	Type	Size	Default								
name	Name of table containing the sensor.	string	Maximum length: 35									
match-type	Logical relation between entries (default = match-any).	option	-	match-any								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>match-all</i></td><td>Match all entries.</td></tr><tr><td><i>match-any</i></td><td>Match any entries.</td></tr><tr><td><i>match-eval</i></td><td>Match an expression evaluation.</td></tr></table>				Option	Description	<i>match-all</i>	Match all entries.	<i>match-any</i>	Match any entries.	<i>match-eval</i>	Match an expression evaluation.
	Option	Description										
	<i>match-all</i>	Match all entries.										
	<i>match-any</i>	Match any entries.										
<i>match-eval</i>	Match an expression evaluation.											
eval	Expression to evaluate.	string	Maximum length: 255									
comment	Optional comments.	var-string	Maximum length: 255									

config entries

Parameter	Description	Type	Size	Default						
id	ID.	integer	Minimum value: 1 Maximum value: 32	0						
dictionary	Select a DLP dictionary.	string	Maximum length: 35							
count	Count of dictionary matches to trigger sensor entry match (Dictionary might not be able to trigger more than once based on its 'repeat' option, 1 - 255, default = 1).	integer	Minimum value: 1 Maximum value: 255	1						
status	Enable/disable this entry.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable this entry.</td></tr><tr><td><i>disable</i></td><td>Disable this entry.</td></tr></table>				Option	Description	<i>enable</i>	Enable this entry.	<i>disable</i>	Disable this entry.
	Option	Description								
	<i>enable</i>	Enable this entry.								
<i>disable</i>	Disable this entry.									

config dlp settings

Designate logical storage for DLP fingerprint database.

```
config dlp settings
  Description: Designate logical storage for DLP fingerprint database.
  set storage-device {string}
  set size {integer}
  set db-mode [stop-adding|remove-modified-then-oldest|...]
  set cache-mem-percent {integer}
  set chunk-size {integer}
end
```

config dlp settings

Parameter	Description	Type	Size	Default
storage-device	Storage device name.	string	Maximum length: 35	

Parameter	Description	Type	Size	Default
size	Maximum total size of files within the storage (MB).	integer	Minimum value: 16 Maximum value: 4294967295	16
db-mode	Behavior when the maximum size is reached.	option	-	stop-adding
	Option	Description		
	<i>stop-adding</i>	Stop adding entries.		
	<i>remove-modified-then-oldest</i>	Remove modified chunks first, then oldest file entries.		
	<i>remove-oldest</i>	Remove the oldest files first.		
cache-mem-percent	Maximum percentage of available memory allocated to caching (1 - 15).	integer	Minimum value: 1 Maximum value: 15	2
chunk-size	Maximum fingerprint chunk size. Caution, changing this setting will flush the entire database.	integer	Minimum value: 100 Maximum value: 100000	2800

dnsfilter

This section includes syntax for the following commands:

- [config dnsfilter domain-filter](#) on page 178
- [config dnsfilter profile](#) on page 179

config dnsfilter domain-filter

Configure DNS domain filters.

```
config dnsfilter domain-filter
  Description: Configure DNS domain filters.
  edit <id>
    set name {string}
    set comment {var-string}
    config entries
      Description: DNS domain filter entries.
      edit <id>
        set domain {string}
        set type [simple|regex|...]
        set action [block|allow|...]
        set status [enable|disable]
      next
    end
  next
end
```

config dnsfilter domain-filter

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Name of table.	string	Maximum length: 63	
comment	Optional comments.	var-string	Maximum length: 255	

config entries

Parameter	Description	Type	Size	Default
id	Id.	integer	Minimum value: 0 Maximum value: 4294967295	0
domain	Domain entries to be filtered.	string	Maximum length: 511	
type	DNS domain filter type.	option	-	simple
	OptionDescription			
	simpleSimple domain string.			
	regexRegular expression domain string.			
	wildcardWildcard domain string.			
action	Action to take for domain filter matches.	option	-	block
	OptionDescription			
	blockBlock DNS requests matching the domain filter.			
	allowAllow DNS requests matching the domain filter without logging.			
	monitorAllow DNS requests matching the domain filter with logging.			
status	Enable/disable this domain filter.	option	-	enable
	OptionDescription			
	enableEnable this domain filter.			
	disableDisable this domain filter.			

config dnsfilter profile

Configure DNS domain filter profile.

```
config dnsfilter profile
  Description: Configure DNS domain filter profile.
  edit <name>
    set comment {var-string}
    config domain-filter
      Description: Domain filter settings.
      set domain-filter-table {integer}
    end
```

```

config ftgd-dns
  Description: FortiGuard DNS Filter settings.
  set options {option1}, {option2}, ...
  config filters
    Description: FortiGuard DNS domain filters.
    edit <id>
      set category {integer}
      set action [block|monitor]
      set log [enable|disable]
    next
  end
end
set log-all-domain [enable|disable]
set sdns-ftgd-err-log [enable|disable]
set sdns-domain-log [enable|disable]
set block-action [block|redirect|...]
set redirect-portal {ipv4-address}
set redirect-portal6 {ipv6-address}
set block-botnet [disable|enable]
set safe-search [disable|enable]
set youtube-restrict [strict|moderate]
set external-ip-blocklist <name1>, <name2>, ...
config dns-translation
  Description: DNS translation settings.
  edit <id>
    set addr-type [ipv4|ipv6]
    set src {ipv4-address}
    set dst {ipv4-address}
    set netmask {ipv4-netmask}
    set status [enable|disable]
    set src6 {ipv6-address}
    set dst6 {ipv6-address}
    set prefix {integer}
  next
end
set strip-ech [disable|enable]
next
end

```

config dnsfilter profile

Parameter	Description	Type	Size	Default
name	Profile name.	string	Maximum length: 35	
comment	Comment.	var-string	Maximum length: 255	

Parameter	Description	Type	Size	Default								
log-all-domain	Enable/disable logging of all domains visited (detailed DNS logging).	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable logging of all domains visited.</td></tr><tr><td><i>disable</i></td><td>Disable logging of all domains visited.</td></tr></table>	Option	Description	<i>enable</i>	Enable logging of all domains visited.	<i>disable</i>	Disable logging of all domains visited.					
Option	Description											
<i>enable</i>	Enable logging of all domains visited.											
<i>disable</i>	Disable logging of all domains visited.											
sdns-ftgd-err-log	Enable/disable FortiGuard SDNS rating error logging.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable FortiGuard SDNS rating error logging.</td></tr><tr><td><i>disable</i></td><td>Disable FortiGuard SDNS rating error logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable FortiGuard SDNS rating error logging.	<i>disable</i>	Disable FortiGuard SDNS rating error logging.					
Option	Description											
<i>enable</i>	Enable FortiGuard SDNS rating error logging.											
<i>disable</i>	Disable FortiGuard SDNS rating error logging.											
sdns-domain-log	Enable/disable domain filtering and botnet domain logging.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable domain filtering and botnet domain logging.</td></tr><tr><td><i>disable</i></td><td>Disable domain filtering and botnet domain logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable domain filtering and botnet domain logging.	<i>disable</i>	Disable domain filtering and botnet domain logging.					
Option	Description											
<i>enable</i>	Enable domain filtering and botnet domain logging.											
<i>disable</i>	Disable domain filtering and botnet domain logging.											
block-action	Action to take for blocked domains.	option	-	redirect								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>block</i></td><td>Return NXDOMAIN for blocked domains.</td></tr><tr><td><i>redirect</i></td><td>Redirect blocked domains to SDNS portal.</td></tr><tr><td><i>block-sevrfail</i></td><td>Return SERVFAIL for blocked domains.</td></tr></table>	Option	Description	<i>block</i>	Return NXDOMAIN for blocked domains.	<i>redirect</i>	Redirect blocked domains to SDNS portal.	<i>block-sevrfail</i>	Return SERVFAIL for blocked domains.			
Option	Description											
<i>block</i>	Return NXDOMAIN for blocked domains.											
<i>redirect</i>	Redirect blocked domains to SDNS portal.											
<i>block-sevrfail</i>	Return SERVFAIL for blocked domains.											
redirect-portal	IPv4 address of the SDNS redirect portal.	ipv4-address	Not Specified	0.0.0.0								
redirect-portal6	IPv6 address of the SDNS redirect portal.	ipv6-address	Not Specified	::								
block-botnet	Enable/disable blocking botnet C&C DNS lookups.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable blocking botnet C&C DNS lookups.</td></tr><tr><td><i>enable</i></td><td>Enable blocking botnet C&C DNS lookups.</td></tr></table>	Option	Description	<i>disable</i>	Disable blocking botnet C&C DNS lookups.	<i>enable</i>	Enable blocking botnet C&C DNS lookups.					
Option	Description											
<i>disable</i>	Disable blocking botnet C&C DNS lookups.											
<i>enable</i>	Enable blocking botnet C&C DNS lookups.											

Parameter	Description	Type	Size	Default						
safe-search	Enable/disable Google, Bing, YouTube, Qwant, DuckDuckGo safe search.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable Google, Bing, YouTube, Qwant, DuckDuckGo safe search.</td></tr><tr><td><i>enable</i></td><td>Enable Google, Bing, YouTube, Qwant, DuckDuckGo safe search.</td></tr></table>	Option	Description	<i>disable</i>	Disable Google, Bing, YouTube, Qwant, DuckDuckGo safe search.	<i>enable</i>	Enable Google, Bing, YouTube, Qwant, DuckDuckGo safe search.			
Option	Description									
<i>disable</i>	Disable Google, Bing, YouTube, Qwant, DuckDuckGo safe search.									
<i>enable</i>	Enable Google, Bing, YouTube, Qwant, DuckDuckGo safe search.									
youtube-restrict	Set safe search for YouTube restriction level.	option	-	strict						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>strict</i></td><td>Enable strict safe search for YouTube.</td></tr><tr><td><i>moderate</i></td><td>Enable moderate safe search for YouTube.</td></tr></table>	Option	Description	<i>strict</i>	Enable strict safe search for YouTube.	<i>moderate</i>	Enable moderate safe search for YouTube.			
Option	Description									
<i>strict</i>	Enable strict safe search for YouTube.									
<i>moderate</i>	Enable moderate safe search for YouTube.									
external-ip-blocklist <name>	One or more external IP block lists. External domain block list name.	string	Maximum length: 79							
strip-ech	Enable/disable removal of the encrypted client hello service parameter from supporting DNS RRs.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable removal of the encrypted client hello service parameter from supporting DNS RRs.</td></tr><tr><td><i>enable</i></td><td>Enable removal of the encrypted client hello service parameter from supporting DNS RRs.</td></tr></table>	Option	Description	<i>disable</i>	Disable removal of the encrypted client hello service parameter from supporting DNS RRs.	<i>enable</i>	Enable removal of the encrypted client hello service parameter from supporting DNS RRs.			
Option	Description									
<i>disable</i>	Disable removal of the encrypted client hello service parameter from supporting DNS RRs.									
<i>enable</i>	Enable removal of the encrypted client hello service parameter from supporting DNS RRs.									

config domain-filter

Parameter	Description	Type	Size	Default
domain-filter-table	DNS domain filter table ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

config ftgd-dns

Parameter	Description	Type	Size	Default
options	FortiGuard DNS filter options.	option	-	

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>error-allow</i>	Allow all domains when FortiGuard DNS servers fail.		
	<i>ftgd-disable</i>	Disable FortiGuard DNS domain rating.		

config filters

Parameter	Description	Type	Size	Default
id	ID number.	integer	Minimum value: 0 Maximum value: 255	0
category	Category number.	integer	Minimum value: 0 Maximum value: 255	0
action	Action to take for DNS requests matching the category.	option	-	monitor
	Option	Description		
	<i>block</i>	Block DNS requests matching the category.		
	<i>monitor</i>	Allow DNS requests matching the category and log the result.		
log	Enable/disable DNS filter logging for this DNS profile.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable DNS filter logging.		
	<i>disable</i>	Disable DNS filter logging.		

config dns-translation

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
addr-type	DNS translation type (IPv4 or IPv6).	option	-	ipv4

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ipv4</i></td><td>IPv4 address type.</td></tr><tr><td><i>ipv6</i></td><td>IPv6 address type.</td></tr></table>				Option	Description	<i>ipv4</i>	IPv4 address type.	<i>ipv6</i>	IPv6 address type.
	Option	Description								
	<i>ipv4</i>	IPv4 address type.								
<i>ipv6</i>	IPv6 address type.									
src	IPv4 address or subnet on the internal network to compare with the resolved address in DNS query replies. If the resolved address matches, the resolved address is substituted with dst.	ipv4-address	Not Specified	0.0.0.0						
dst	IPv4 address or subnet on the external network to substitute for the resolved address in DNS query replies. Can be single IP address or subnet on the external network, but number of addresses must equal number of mapped IP addresses in src.	ipv4-address	Not Specified	0.0.0.0						
netmask	If src and dst are subnets rather than single IP addresses, enter the netmask for both src and dst.	ipv4-netmask	Not Specified	255.255.255.255						
status	Enable/disable this DNS translation entry.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable this DNS translation.</td></tr><tr><td><i>disable</i></td><td>Disable this DNS translation.</td></tr></table>				Option	Description	<i>enable</i>	Enable this DNS translation.	<i>disable</i>	Disable this DNS translation.
	Option	Description								
	<i>enable</i>	Enable this DNS translation.								
<i>disable</i>	Disable this DNS translation.									
src6	IPv6 address or subnet on the internal network to compare with the resolved address in DNS query replies. If the resolved address matches, the resolved address is substituted with dst6.	ipv6-address	Not Specified	::						
dst6	IPv6 address or subnet on the external network to substitute for the resolved address in DNS query replies. Can be single IP address or subnet on the external network, but number of addresses must equal number of mapped IP addresses in src6.	ipv6-address	Not Specified	::						

Parameter	Description	Type	Size	Default
prefix	If src6 and dst6 are subnets rather than single IP addresses, enter the prefix for both src6 and dst6 (1 - 128, default = 128).	integer	Minimum value: 1 Maximum value: 128	128

emailfilter

This section includes syntax for the following commands:

- [config emailfilter block-allow-list on page 186](#)
- [config emailfilter bword on page 188](#)
- [config emailfilter dnsbl on page 190](#)
- [config emailfilter fortishield on page 192](#)
- [config emailfilter iptrust on page 192](#)
- [config emailfilter mheader on page 194](#)
- [config emailfilter options on page 195](#)
- [config emailfilter profile on page 196](#)

config emailfilter block-allow-list

Configure anti-spam block/allow list.

```
config emailfilter block-allow-list
  Description: Configure anti-spam block/allow list.
  edit <id>
    set name {string}
    set comment {var-string}
    config entries
      Description: Anti-spam block/allow entries.
      edit <id>
        set status [enable|disable]
        set type [ip|email-to|...]
        set action [reject|spam|...]
        set addr-type [ipv4|ipv6]
        set ip4-subnet {ipv4-classnet}
        set ip6-subnet {ipv6-network}
        set pattern-type [wildcard|regexp]
        set pattern {string}
      next
    end
  next
end
```

config emailfilter block-allow-list

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Name of table.	string	Maximum length: 63	
comment	Optional comments.	var-string	Maximum length: 255	

config entries

Parameter	Description	Type	Size	Default										
status	Enable/disable status.	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable status.</td></tr><tr><td><i>disable</i></td><td>Disable status.</td></tr></table>	Option	Description	<i>enable</i>	Enable status.	<i>disable</i>	Disable status.							
	Option	Description												
	<i>enable</i>	Enable status.												
<i>disable</i>	Disable status.													
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0										
type	Entry type.	option	-	ip										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ip</i></td><td>By IP address.</td></tr><tr><td><i>email-to</i></td><td>By email recipient.</td></tr><tr><td><i>email-from</i></td><td>By email sender.</td></tr><tr><td><i>subject</i></td><td>By email subject.</td></tr></table>	Option	Description	<i>ip</i>	By IP address.	<i>email-to</i>	By email recipient.	<i>email-from</i>	By email sender.	<i>subject</i>	By email subject.			
	Option	Description												
	<i>ip</i>	By IP address.												
	<i>email-to</i>	By email recipient.												
	<i>email-from</i>	By email sender.												
<i>subject</i>	By email subject.													
action	Reject, mark as spam or good email.	option	-	spam										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>reject</i></td><td>Reject the connection.</td></tr><tr><td><i>spam</i></td><td>Mark as spam email.</td></tr></table>	Option	Description	<i>reject</i>	Reject the connection.	<i>spam</i>	Mark as spam email.							
	Option	Description												
	<i>reject</i>	Reject the connection.												
<i>spam</i>	Mark as spam email.													

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>clear</i></td><td>Mark as good email.</td></tr></table>	Option	Description	<i>clear</i>	Mark as good email.					
	Option	Description								
	<i>clear</i>	Mark as good email.								
addr-type	IP address type.	option	-	ipv4						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ipv4</i></td><td>IPv4 Address type.</td></tr><tr><td><i>ipv6</i></td><td>IPv6 Address type.</td></tr></table>	Option	Description	<i>ipv4</i>	IPv4 Address type.	<i>ipv6</i>	IPv6 Address type.			
	Option	Description								
	<i>ipv4</i>	IPv4 Address type.								
<i>ipv6</i>	IPv6 Address type.									
ip4-subnet	IPv4 network address/subnet mask bits.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0						
ip6-subnet	IPv6 network address/subnet mask bits.	ipv6-network	Not Specified	::/128						
pattern-type	Wildcard pattern or regular expression.	option	-	wildcard						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>wildcard</i></td><td>Wildcard pattern.</td></tr><tr><td><i>regex</i></td><td>Perl regular expression.</td></tr></table>	Option	Description	<i>wildcard</i>	Wildcard pattern.	<i>regex</i>	Perl regular expression.			
	Option	Description								
	<i>wildcard</i>	Wildcard pattern.								
<i>regex</i>	Perl regular expression.									
pattern	Pattern to match.	string	Maximum length: 127							

config emailfilter bword

Configure AntiSpam banned word list.

```

config emailfilter bword
  Description: Configure AntiSpam banned word list.
  edit <id>
    set name {string}
    set comment {var-string}
    config entries
      Description: Spam filter banned word.
      edit <id>
        set status [enable|disable]
        set pattern {string}
        set pattern-type [wildcard|regex]
        set action [spam|clear]
        set where [subject|body|...]
        set language [western|simch|...]
        set score {integer}
      next
    end
  end

```

```
next
end
```

config emailfilter bword

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Name of table.	string	Maximum length: 63	
comment	Optional comments.	var-string	Maximum length: 255	

config entries

Parameter	Description	Type	Size	Default
status	Enable/disable status.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable status.		
	<i>disable</i>	Disable status.		
id	Banned word entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
pattern	Pattern for the banned word.	string	Maximum length: 127	
pattern-type	Wildcard pattern or regular expression.	option	-	wildcard
	Option	Description		
	<i>wildcard</i>	Wildcard pattern.		
	<i>regex</i>	Perl regular expression.		
action	Mark spam or good.	option	-	spam

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>spam</i>	Mark as spam email.		
	<i>clear</i>	Mark as good email.		
where	Component of the email to be scanned.	option	-	all
	Option	Description		
	<i>subject</i>	Banned word in email subject.		
	<i>body</i>	Banned word in email body.		
	<i>all</i>	Banned word in both subject and body.		
language	Language for the banned word.	option	-	western
	Option	Description		
	<i>western</i>	Western.		
	<i>simch</i>	Simplified Chinese.		
	<i>trach</i>	Traditional Chinese.		
	<i>japanese</i>	Japanese.		
	<i>korean</i>	Korean.		
	<i>french</i>	French.		
	<i>thai</i>	Thai.		
	<i>spanish</i>	Spanish.		
score	Score value.	integer	Minimum value: 1 Maximum value: 99999	10

config emailfilter dnsbl

Configure AntiSpam DNSBL/ORBL.

```

config emailfilter dnsbl
  Description: Configure AntiSpam DNSBL/ORBL.
  edit <id>
    set name {string}
    set comment {var-string}
    config entries
      Description: Spam filter DNSBL and ORBL server.
      edit <id>

```

```

        set status [enable|disable]
        set server {string}
        set action [reject|spam]
    next
end
next
end

```

config emailfilter dnsbl

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Name of table.	string	Maximum length: 63	
comment	Optional comments.	var-string	Maximum length: 255	

config entries

Parameter	Description	Type	Size	Default
status	Enable/disable status.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable status.		
	<i>disable</i>	Disable status.		
id	DNSBL/ORBL entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
server	DNSBL or ORBL server name.	string	Maximum length: 127	
action	Reject connection or mark as spam email.	option	-	spam
	Option	Description		
	<i>reject</i>	Reject the connection.		
	<i>spam</i>	Mark as spam email.		

config emailfilter fortishield

Configure FortiGuard - AntiSpam.

```
config emailfilter fortishield
  Description: Configure FortiGuard - AntiSpam.
  set spam-submit-srv {string}
  set spam-submit-force [enable|disable]
  set spam-submit-txt2htm [enable|disable]
end
```

config emailfilter fortishield

Parameter	Description	Type	Size	Default
spam-submit-srv	Hostname of the spam submission server.	string	Maximum length: 63	www.nospammer.net
spam-submit-force	Enable/disable force insertion of a new mime entity for the submission text.	option	-	enable
	Option Description			
	enable Enable setting.			
	disable Disable setting.			
spam-submit-txt2htm	Enable/disable conversion of text email to HTML email.	option	-	enable
	Option Description			
	enable Enable setting.			
	disable Disable setting.			

config emailfilter iptrust

Configure AntiSpam IP trust.

```
config emailfilter iptrust
  Description: Configure AntiSpam IP trust.
  edit <id>
    set name {string}
    set comment {var-string}
    config entries
      Description: Spam filter trusted IP addresses.
```



```

edit <id>
    set status [enable|disable]
    set addr-type [ipv4|ipv6]
    set ip4-subnet {ipv4-classnet}
    set ip6-subnet {ipv6-network}
next
end
next
end

```

config emailfilter iptrust

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Name of table.	string	Maximum length: 63	
comment	Optional comments.	var-string	Maximum length: 255	

config entries

Parameter	Description	Type	Size	Default						
status	Enable/disable status.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable status.</td></tr><tr><td>disable</td><td>Disable status.</td></tr></table>				Option	Description	enable	Enable status.	disable	Disable status.
	Option	Description								
	enable	Enable status.								
disable	Disable status.									
id	Trusted IP entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0						
addr-type	Type of address.	option	-	ipv4						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>ipv4</td><td>IPv4 Address type.</td></tr><tr><td>ipv6</td><td>IPv6 Address type.</td></tr></table>				Option	Description	ipv4	IPv4 Address type.	ipv6	IPv6 Address type.
	Option	Description								
	ipv4	IPv4 Address type.								
ipv6	IPv6 Address type.									

Parameter	Description	Type	Size	Default
ip4-subnet	IPv4 network address or network address/subnet mask bits.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0
ip6-subnet	IPv6 network address/subnet mask bits.	ipv6-network	Not Specified	::/128

config emailfilter mheader

Configure AntiSpam MIME header.

```

config emailfilter mheader
  Description: Configure AntiSpam MIME header.
  edit <id>
    set name {string}
    set comment {var-string}
    config entries
      Description: Spam filter mime header content.
      edit <id>
        set status [enable|disable]
        set fieldname {string}
        set fieldbody {string}
        set pattern-type [wildcard|regexp]
        set action [spam|clear]
      next
    end
  next
end

```

config emailfilter mheader

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Name of table.	string	Maximum length: 63	
comment	Optional comments.	var-string	Maximum length: 255	

config entries

Parameter	Description	Type	Size	Default						
status	Enable/disable status.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable status.</td></tr><tr><td><i>disable</i></td><td>Disable status.</td></tr></table>	Option	Description	<i>enable</i>	Enable status.	<i>disable</i>	Disable status.			
Option	Description									
<i>enable</i>	Enable status.									
<i>disable</i>	Disable status.									
id	Mime header entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0						
fieldname	Pattern for header field name.	string	Maximum length: 63							
fieldbody	Pattern for the header field body.	string	Maximum length: 127							
pattern-type	Wildcard pattern or regular expression.	option	-	wildcard						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>wildcard</i></td><td>Wildcard pattern.</td></tr><tr><td><i>regex</i></td><td>Perl regular expression.</td></tr></table>	Option	Description	<i>wildcard</i>	Wildcard pattern.	<i>regex</i>	Perl regular expression.			
Option	Description									
<i>wildcard</i>	Wildcard pattern.									
<i>regex</i>	Perl regular expression.									
action	Mark spam or good.	option	-	spam						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>spam</i></td><td>Mark as spam email.</td></tr><tr><td><i>clear</i></td><td>Mark as good email.</td></tr></table>	Option	Description	<i>spam</i>	Mark as spam email.	<i>clear</i>	Mark as good email.			
Option	Description									
<i>spam</i>	Mark as spam email.									
<i>clear</i>	Mark as good email.									

config emailfilter options

Configure AntiSpam options.

```
config emailfilter options
  Description: Configure AntiSpam options.
  set dns-timeout {integer}
end
```

config emailfilter options

Parameter	Description	Type	Size	Default
dns-timeout	DNS query time out (1 - 30 sec).	integer	Minimum value: 1 Maximum value: 30	7

config emailfilter profile

Configure Email Filter profiles.

```
config emailfilter profile
  Description: Configure Email Filter profiles.
  edit <name>
    set comment {var-string}
    set replacemsg-group {string}
    set spam-log [disable|enable]
    set spam-log-fortiguard-response [disable|enable]
    set spam-filtering [enable|disable]
    set external [enable|disable]
    set options {option1}, {option2}, ...
    config imap
      Description: IMAP.
      set log-all [disable|enable]
      set action [pass|tag]
      set tag-type {option1}, {option2}, ...
      set tag-msg {string}
    end
    config pop3
      Description: POP3.
      set log-all [disable|enable]
      set action [pass|tag]
      set tag-type {option1}, {option2}, ...
      set tag-msg {string}
    end
    config smtp
      Description: SMTP.
      set log-all [disable|enable]
      set action [pass|tag|...]
      set tag-type {option1}, {option2}, ...
      set tag-msg {string}
      set hdrip [disable|enable]
      set local-override [disable|enable]
    end
    config mapi
      Description: MAPI.
      set log-all [disable|enable]
```

```

        set action [pass|discard]
    end
    config msn-hotmail
        Description: MSN Hotmail.
        set log-all [disable|enable]
    end
    config yahoo-mail
        Description: Yahoo! Mail.
        set log-all [disable|enable]
    end
    config gmail
        Description: Gmail.
        set log-all [disable|enable]
    end
    config other-webmails
        Description: Other supported webmails.
        set log-all [disable|enable]
    end
    set spam-bword-threshold {integer}
    set spam-bword-table {integer}
    set spam-bal-table {integer}
    set spam-mheader-table {integer}
    set spam-rbl-table {integer}
    set spam-iptrust-table {integer}
next
end

```

config emailfilter profile

Parameter	Description	Type	Size	Default
name	Profile name.	string	Maximum length: 35	
comment	Comment.	var-string	Maximum length: 255	
replacemsg-group	Replacement message group.	string	Maximum length: 35	
spam-log	Enable/disable spam logging for email filtering.	option	-	enable
		Option	Description	
		<i>disable</i>	Disable spam logging for email filtering.	
		<i>enable</i>	Enable spam logging for email filtering.	

Parameter	Description	Type	Size	Default																								
spam-log-fortiguard-response	Enable/disable logging FortiGuard spam response.	option	-	disable																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable logging FortiGuard spam response.</td></tr><tr><td><i>enable</i></td><td>Enable logging FortiGuard spam response.</td></tr></table>	Option	Description	<i>disable</i>	Disable logging FortiGuard spam response.	<i>enable</i>	Enable logging FortiGuard spam response.																					
Option	Description																											
<i>disable</i>	Disable logging FortiGuard spam response.																											
<i>enable</i>	Enable logging FortiGuard spam response.																											
spam-filtering	Enable/disable spam filtering.	option	-	disable																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.																					
Option	Description																											
<i>enable</i>	Enable setting.																											
<i>disable</i>	Disable setting.																											
external	Enable/disable external Email inspection.	option	-	disable																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.																					
Option	Description																											
<i>enable</i>	Enable setting.																											
<i>disable</i>	Disable setting.																											
options	Options.	option	-																									
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>bannedword</i></td><td>Content block.</td></tr><tr><td><i>spambal</i></td><td>Block/allow list.</td></tr><tr><td><i>spamfsip</i></td><td>Email IP address FortiGuard AntiSpam block list check.</td></tr><tr><td><i>spamfssubmit</i></td><td>Add FortiGuard AntiSpam spam submission text.</td></tr><tr><td><i>spamfschksum</i></td><td>Email checksum FortiGuard AntiSpam check.</td></tr><tr><td><i>spamfsurl</i></td><td>Email content URL FortiGuard AntiSpam check.</td></tr><tr><td><i>spamhelodns</i></td><td>Email helo/ehlo domain DNS check.</td></tr><tr><td><i>spamraddrdns</i></td><td>Email return address DNS check.</td></tr><tr><td><i>spamrbl</i></td><td>Email DNSBL & ORBL check.</td></tr><tr><td><i>spamhdrcheck</i></td><td>Email mime header check.</td></tr><tr><td><i>spamfsphish</i></td><td>Email content phishing URL FortiGuard AntiSpam check.</td></tr></table>	Option	Description	<i>bannedword</i>	Content block.	<i>spambal</i>	Block/allow list.	<i>spamfsip</i>	Email IP address FortiGuard AntiSpam block list check.	<i>spamfssubmit</i>	Add FortiGuard AntiSpam spam submission text.	<i>spamfschksum</i>	Email checksum FortiGuard AntiSpam check.	<i>spamfsurl</i>	Email content URL FortiGuard AntiSpam check.	<i>spamhelodns</i>	Email helo/ehlo domain DNS check.	<i>spamraddrdns</i>	Email return address DNS check.	<i>spamrbl</i>	Email DNSBL & ORBL check.	<i>spamhdrcheck</i>	Email mime header check.	<i>spamfsphish</i>	Email content phishing URL FortiGuard AntiSpam check.			
Option	Description																											
<i>bannedword</i>	Content block.																											
<i>spambal</i>	Block/allow list.																											
<i>spamfsip</i>	Email IP address FortiGuard AntiSpam block list check.																											
<i>spamfssubmit</i>	Add FortiGuard AntiSpam spam submission text.																											
<i>spamfschksum</i>	Email checksum FortiGuard AntiSpam check.																											
<i>spamfsurl</i>	Email content URL FortiGuard AntiSpam check.																											
<i>spamhelodns</i>	Email helo/ehlo domain DNS check.																											
<i>spamraddrdns</i>	Email return address DNS check.																											
<i>spamrbl</i>	Email DNSBL & ORBL check.																											
<i>spamhdrcheck</i>	Email mime header check.																											
<i>spamfsphish</i>	Email content phishing URL FortiGuard AntiSpam check.																											

Parameter	Description	Type	Size	Default
spam-bword-threshold	Spam banned word threshold.	integer	Minimum value: 0 Maximum value: 2147483647	10
spam-bword-table	Anti-spam banned word table ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
spam-bal-table	Anti-spam block/allow list table ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
spam-mheader-table	Anti-spam MIME header table ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
spam-rbl-table	Anti-spam DNSBL table ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
spam-iptrust-table	Anti-spam IP trust table ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

config imap

Parameter	Description	Type	Size	Default
log-all	Enable/disable logging of all email traffic.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable logging of all email traffic.		
	<i>enable</i>	Enable logging of all email traffic.		
action	Action for spam email.	option	-	tag

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>pass</i>	Allow spam email to pass through.		
	<i>tag</i>	Tag spam email with configured text in subject or header.		
tag-type	Tag subject or header for spam email.	option	-	subject spaminfo
	Option	Description		
	<i>subject</i>	Prepend text to spam email subject.		
	<i>header</i>	Append a user defined mime header to spam email.		
	<i>spaminfo</i>	Append spam info to spam email header.		
tag-msg	Subject text or header added to spam email.	string	Maximum length: 63	Spam

config pop3

Parameter	Description	Type	Size	Default
log-all	Enable/disable logging of all email traffic.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable logging of all email traffic.		
	<i>enable</i>	Enable logging of all email traffic.		
action	Action for spam email.	option	-	tag
	Option	Description		
	<i>pass</i>	Allow spam email to pass through.		
	<i>tag</i>	Tag spam email with configured text in subject or header.		
tag-type	Tag subject or header for spam email.	option	-	subject spaminfo
	Option	Description		
	<i>subject</i>	Prepend text to spam email subject.		
	<i>header</i>	Append a user defined mime header to spam email.		
	<i>spaminfo</i>	Append spam info to spam email header.		
tag-msg	Subject text or header added to spam email.	string	Maximum length: 63	Spam

config smtp

Parameter	Description	Type	Size	Default								
log-all	Enable/disable logging of all email traffic.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable logging of all email traffic.</td></tr><tr><td><i>enable</i></td><td>Enable logging of all email traffic.</td></tr></table>	Option	Description	<i>disable</i>	Disable logging of all email traffic.	<i>enable</i>	Enable logging of all email traffic.					
Option	Description											
<i>disable</i>	Disable logging of all email traffic.											
<i>enable</i>	Enable logging of all email traffic.											
action	Action for spam email.	option	-	discard								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>pass</i></td><td>Allow spam email to pass through.</td></tr><tr><td><i>tag</i></td><td>Tag spam email with configured text in subject or header.</td></tr><tr><td><i>discard</i></td><td>Discard (block) spam email.</td></tr></table>	Option	Description	<i>pass</i>	Allow spam email to pass through.	<i>tag</i>	Tag spam email with configured text in subject or header.	<i>discard</i>	Discard (block) spam email.			
Option	Description											
<i>pass</i>	Allow spam email to pass through.											
<i>tag</i>	Tag spam email with configured text in subject or header.											
<i>discard</i>	Discard (block) spam email.											
tag-type	Tag subject or header for spam email.	option	-	subject spaminfo								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>subject</i></td><td>Prepend text to spam email subject.</td></tr><tr><td><i>header</i></td><td>Append a user defined mime header to spam email.</td></tr><tr><td><i>spaminfo</i></td><td>Append spam info to spam email header.</td></tr></table>	Option	Description	<i>subject</i>	Prepend text to spam email subject.	<i>header</i>	Append a user defined mime header to spam email.	<i>spaminfo</i>	Append spam info to spam email header.			
Option	Description											
<i>subject</i>	Prepend text to spam email subject.											
<i>header</i>	Append a user defined mime header to spam email.											
<i>spaminfo</i>	Append spam info to spam email header.											
tag-msg	Subject text or header added to spam email.	string	Maximum length: 63	Spam								
hdrip	Enable/disable SMTP email header IP checks for spamfsip, spamrbl, and spambal filters.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable SMTP email header IP checks for spamfsip, spamrbl, and spambal filters.</td></tr><tr><td><i>enable</i></td><td>Enable SMTP email header IP checks for spamfsip, spamrbl, and spambal filters.</td></tr></table>	Option	Description	<i>disable</i>	Disable SMTP email header IP checks for spamfsip, spamrbl, and spambal filters.	<i>enable</i>	Enable SMTP email header IP checks for spamfsip, spamrbl, and spambal filters.					
Option	Description											
<i>disable</i>	Disable SMTP email header IP checks for spamfsip, spamrbl, and spambal filters.											
<i>enable</i>	Enable SMTP email header IP checks for spamfsip, spamrbl, and spambal filters.											
local-override	Enable/disable local filter to override SMTP remote check result.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable local filter to override SMTP remote check result.</td></tr><tr><td><i>enable</i></td><td>Enable local filter to override SMTP remote check result.</td></tr></table>	Option	Description	<i>disable</i>	Disable local filter to override SMTP remote check result.	<i>enable</i>	Enable local filter to override SMTP remote check result.					
Option	Description											
<i>disable</i>	Disable local filter to override SMTP remote check result.											
<i>enable</i>	Enable local filter to override SMTP remote check result.											

config mapi

Parameter	Description	Type	Size	Default
log-all	Enable/disable logging of all email traffic.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable logging of all email traffic.		
	<i>enable</i>	Enable logging of all email traffic.		
action	Action for spam email.	option	-	pass
	Option	Description		
	<i>pass</i>	Allow spam email to pass through.		
	<i>discard</i>	Discard (block) spam email.		

config msn-hotmail

Parameter	Description	Type	Size	Default
log-all	Enable/disable logging of all email traffic.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable logging of all email traffic.		
	<i>enable</i>	Enable logging of all email traffic.		

config yahoo-mail

Parameter	Description	Type	Size	Default
log-all	Enable/disable logging of all email traffic.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable logging of all email traffic.		
	<i>enable</i>	Enable logging of all email traffic.		

config gmail

Parameter	Description	Type	Size	Default
log-all	Enable/disable logging of all email traffic.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable logging of all email traffic.		
	<i>enable</i>	Enable logging of all email traffic.		

config other-webmails

Parameter	Description	Type	Size	Default
log-all	Enable/disable logging of all email traffic.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable logging of all email traffic.		
	<i>enable</i>	Enable logging of all email traffic.		

endpoint-control

This section includes syntax for the following commands:

- [config endpoint-control fctems on page 204](#)

config endpoint-control fctems

Configure FortiClient Enterprise Management Server (EMS) entries.

```
config endpoint-control fctems
  Description: Configure FortiClient Enterprise Management Server (EMS) entries.
  edit <ems-id>
    set status [enable|disable]
    set name {string}
    set dirty-reason [none|mismatched-ems-sn]
    set fortinetone-cloud-authentication [enable|disable]
    set server {string}
    set https-port {integer}
    set serial-number {string}
    set tenant-id {string}
    set source-ip {ipv4-address-any}
    set pull-sysinfo [enable|disable]
    set pull-vulnerabilities [enable|disable]
    set pull-avatars [enable|disable]
    set pull-tags [enable|disable]
    set pull-malware-hash [enable|disable]
    set cloud-server-type [production|alpha|...]
    set capabilities {option1}, {option2}, ...
    set call-timeout {integer}
    set out-of-sync-threshold {integer}
    set websocket-override [disable|enable]
    set preserve-ssl-session [enable|disable]
    set interface-select-method [auto|specify]
    set interface {string}
    set trust-ca-cn [enable|disable]
  next
end
```

config endpoint-control fctems

Parameter	Description	Type	Size	Default
ems-id	EMS ID in order (1 - 7).	integer	Minimum value: 1 Maximum value: 7	0
status	Enable or disable this EMS configuration.	option	-	disable
	Option		Description	
	<i>enable</i>		Enable EMS configuration and operation.	
	<i>disable</i>		Disable EMS configuration and operation.	
name	FortiClient Enterprise Management Server (EMS) name.	string	Maximum length: 35	
dirty-reason	Dirty Reason for FortiClient EMS.	option	-	none
	Option		Description	
	<i>none</i>		FortiClient EMS entry not dirty.	
	<i>mismatched-ems-sn</i>		FortiClient EMS entry dirty because EMS SN is mismatched with configured SN.	
fortinetone-cloud-authentication	Enable/disable authentication of FortiClient EMS Cloud through FortiCloud account.	option	-	disable
	Option		Description	
	<i>enable</i>		Enable authentication of FortiClient EMS Cloud through the use of FortiCloud account.	
	<i>disable</i>		Disable authentication of FortiClient EMS Cloud through the use of FortiCloud account.	
server	FortiClient EMS FQDN or IPv4 address.	string	Maximum length: 255	
https-port	FortiClient EMS HTTPS access port number. (1 - 65535, default: 443).	integer	Minimum value: 1 Maximum value: 65535	443
serial-number	EMS Serial Number.	string	Maximum length: 16	

Parameter	Description	Type	Size	Default
tenant-id	EMS Tenant ID.	string	Maximum length: 32	
source-ip	REST API call source IP.	ipv4-address-any	Not Specified	0.0.0.0
pull-sysinfo	Enable/disable pulling SysInfo from EMS.	option	-	enable
	Option		Description	
	<i>enable</i>		Enable pulling FortiClient user SysInfo from EMS.	
	<i>disable</i>		Disable pulling FortiClient user SysInfo from EMS.	
pull-vulnerabilities	Enable/disable pulling vulnerabilities from EMS.	option	-	enable
	Option		Description	
	<i>enable</i>		Enable pulling client vulnerabilities from EMS.	
	<i>disable</i>		Disable pulling client vulnerabilities from EMS.	
pull-avatars	Enable/disable pulling avatars from EMS.	option	-	enable
	Option		Description	
	<i>enable</i>		Enable pulling FortiClient user avatars from EMS.	
	<i>disable</i>		Disable pulling FortiClient user avatars from EMS.	
pull-tags	Enable/disable pulling FortiClient user tags from EMS.	option	-	enable
	Option		Description	
	<i>enable</i>		Enable pulling FortiClient user tags from EMS.	
	<i>disable</i>		Disable pulling FortiClient user tags from EMS.	
pull-malware-hash	Enable/disable pulling FortiClient malware hash from EMS.	option	-	enable
	Option		Description	
	<i>enable</i>		Enable pulling FortiClient malware hash from EMS.	
	<i>disable</i>		Disable pulling FortiClient malware hash from EMS.	

Parameter	Description	Type	Size	Default																
cloud-server-type	Cloud server type.	option	-	production																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>production</i></td><td>Production FortiClient EMS Cloud Controller.</td></tr><tr><td><i>alpha</i></td><td>Alpha FortiClient EMS Cloud Controller.</td></tr><tr><td><i>beta</i></td><td>Beta FortiClient EMS Cloud Controller.</td></tr></table>	Option	Description	<i>production</i>	Production FortiClient EMS Cloud Controller.	<i>alpha</i>	Alpha FortiClient EMS Cloud Controller.	<i>beta</i>	Beta FortiClient EMS Cloud Controller.											
	Option	Description																		
	<i>production</i>	Production FortiClient EMS Cloud Controller.																		
	<i>alpha</i>	Alpha FortiClient EMS Cloud Controller.																		
<i>beta</i>	Beta FortiClient EMS Cloud Controller.																			
capabilities	List of EMS capabilities.	option	-																	
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>fabric-auth</i></td><td>Allow this FortiProxy unit to load the authentication page provided by EMS to authenticate itself with EMS.</td></tr><tr><td><i>silent-approval</i></td><td>Allow silent approval of non-root or FortiProxy HA clusters on EMS in the Security Fabric.</td></tr><tr><td><i>websocket</i></td><td>Enable/disable websockets for this FortiProxy unit. Override behavior using websocket-override.</td></tr><tr><td><i>websocket-malware</i></td><td>Allow this FortiGate unit to request malware hash notifications over websocket.</td></tr><tr><td><i>push-ca-certs</i></td><td>Enable/disable syncing deep inspection certificates with EMS.</td></tr><tr><td><i>common-tags-api</i></td><td>Can receive tag information from New Common Tags API from EMS.</td></tr><tr><td><i>tenant-id</i></td><td>Allow this FortiGate to retrieve Tenant-ID from EMS.</td></tr></table>	Option	Description	<i>fabric-auth</i>	Allow this FortiProxy unit to load the authentication page provided by EMS to authenticate itself with EMS.	<i>silent-approval</i>	Allow silent approval of non-root or FortiProxy HA clusters on EMS in the Security Fabric.	<i>websocket</i>	Enable/disable websockets for this FortiProxy unit. Override behavior using websocket-override.	<i>websocket-malware</i>	Allow this FortiGate unit to request malware hash notifications over websocket.	<i>push-ca-certs</i>	Enable/disable syncing deep inspection certificates with EMS.	<i>common-tags-api</i>	Can receive tag information from New Common Tags API from EMS.	<i>tenant-id</i>	Allow this FortiGate to retrieve Tenant-ID from EMS.			
	Option	Description																		
	<i>fabric-auth</i>	Allow this FortiProxy unit to load the authentication page provided by EMS to authenticate itself with EMS.																		
	<i>silent-approval</i>	Allow silent approval of non-root or FortiProxy HA clusters on EMS in the Security Fabric.																		
	<i>websocket</i>	Enable/disable websockets for this FortiProxy unit. Override behavior using websocket-override.																		
	<i>websocket-malware</i>	Allow this FortiGate unit to request malware hash notifications over websocket.																		
	<i>push-ca-certs</i>	Enable/disable syncing deep inspection certificates with EMS.																		
<i>common-tags-api</i>	Can receive tag information from New Common Tags API from EMS.																			
<i>tenant-id</i>	Allow this FortiGate to retrieve Tenant-ID from EMS.																			
call-timeout	FortiClient EMS call timeout in seconds (1 - 180 seconds, default = 30).	integer	Minimum value: 1 Maximum value: 180	30																
out-of-sync-threshold	Outdated resource threshold in seconds (10 - 3600, default = 180).	integer	Minimum value: 10 Maximum value: 3600	180																
websocket-override	Enable/disable override behavior for how this FortiProxy unit connects to EMS using a WebSocket connection.	option	-	disable																

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Do not override the WebSocket connection. Connect to WebSocket of this EMS server if it is capable (default).		
	<i>enable</i>	Override the WebSocket connection. Do not connect to WebSocket even if EMS is capable of a WebSocket connection.		
preserve-ssl-session	Enable/disable preservation of EMS SSL session connection. Warning, most users should not touch this setting.	option	-	disable
	Option	Description		
	<i>enable</i>	Allow preservation of EMS SSL session connection.		
	<i>disable</i>	Don't allow preservation of EMS SSL session connection.		
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto
	Option	Description		
	<i>auto</i>	Set outgoing interface automatically.		
	<i>specify</i>	Set outgoing interface manually.		
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	
trust-ca-cn	Enable/disable trust of the EMS certificate issuer(CA) and common name(CN) for certificate auto-renewal.	option	-	enable
	Option	Description		
	<i>enable</i>	Trust EMS certificate CA & CN to automatically renew certificate.		
	<i>disable</i>	Do not trust EMS certificate CA & CN to automatically renew certificate.		

file-filter

This section includes syntax for the following commands:

- [config file-filter profile on page 209](#)

config file-filter profile

Configure file-filter profiles.

```
config file-filter profile
  Description: Configure file-filter profiles.
  edit <name>
    set comment {var-string}
    set replacemsg-group {string}
    set log [disable|enable]
    set scan-archive-contents [disable|enable]
    config rules
      Description: File filter rules.
      edit <name>
        set comment {var-string}
        set protocol {option1}, {option2}, ...
        set action [log-only|block]
        set direction [incoming|outgoing|...]
        set password-protected [yes|any]
        set file-type <name1>, <name2>, ...
      next
    end
  next
end
```

config file-filter profile

Parameter	Description	Type	Size	Default
name	Profile name.	string	Maximum length: 35	
comment	Comment.	var-string	Maximum length: 255	
replacemsg-group	Replacement message group.	string	Maximum length: 35	
log	Enable/disable file-filter logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable logging.		
	<i>enable</i>	Enable logging.		
scan-archive-contents	Enable/disable archive contents scan.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable scanning archive contents.		
	<i>enable</i>	Enable scanning archive contents.		

config rules

Parameter	Description	Type	Size	Default
name	File-filter rule name.	string	Maximum length: 35	
comment	Comment.	var-string	Maximum length: 255	
protocol	Protocols to apply rule to.	option	-	http ftp smtp imap pop3 mapi cifs ssh
	Option	Description		
	<i>http</i>	Filter on HTTP.		
	<i>ftp</i>	Filter on FTP.		
	<i>smtp</i>	Filter on SMTP.		
	<i>imap</i>	Filter on IMAP.		
	<i>pop3</i>	Filter on POP3.		
	<i>mapi</i>	Filter on MAPI. (Proxy mode only.)		
	<i>cifs</i>	Filter on CIFS.		
	<i>ssh</i>	Filter on SFTP and SCP. (Proxy mode only.)		
action	Action taken for matched file.	option	-	log-only
	Option	Description		
	<i>log-only</i>	Allow the content and write a log message.		

Parameter	Description	Type	Size	Default								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>block</i></td><td>Block the content and write a log message.</td></tr></table>	Option	Description	<i>block</i>	Block the content and write a log message.							
	Option	Description										
<i>block</i>	Block the content and write a log message.											
direction	Traffic direction (HTTP, FTP, SSH, CIFS only).	option	-	any								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>incoming</i></td><td>Match files transmitted in the session's reply direction.</td></tr><tr><td><i>outgoing</i></td><td>Match files transmitted in the session's originating direction.</td></tr><tr><td><i>any</i></td><td>Match files transmitted in the session's originating and reply directions.</td></tr></table>	Option	Description	<i>incoming</i>	Match files transmitted in the session's reply direction.	<i>outgoing</i>	Match files transmitted in the session's originating direction.	<i>any</i>	Match files transmitted in the session's originating and reply directions.			
	Option	Description										
	<i>incoming</i>	Match files transmitted in the session's reply direction.										
	<i>outgoing</i>	Match files transmitted in the session's originating direction.										
<i>any</i>	Match files transmitted in the session's originating and reply directions.											
password-protected	Match password-protected files.	option	-	any								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>yes</i></td><td>Match only password-protected files.</td></tr><tr><td><i>any</i></td><td>Match any file.</td></tr></table>	Option	Description	<i>yes</i>	Match only password-protected files.	<i>any</i>	Match any file.					
	Option	Description										
	<i>yes</i>	Match only password-protected files.										
<i>any</i>	Match any file.											
file-type <name>	Select file type. File type name.	string	Maximum length: 39									

firewall

This section includes syntax for the following commands:

- [config firewall access-proxy-ssh-client-cert on page 250](#)
- [config firewall access-proxy-virtual-host on page 253](#)
- [config firewall access-proxy on page 213](#)
- [config firewall access-proxy6 on page 250](#)
- [config firewall address on page 254](#)
- [config firewall address6-template on page 263](#)
- [config firewall address6 on page 259](#)
- [config firewall addrgrp on page 265](#)
- [config firewall addrgrp6 on page 267](#)
- [config firewall auth-portal on page 268](#)
- [config firewall central-snat-map on page 269](#)
- [config firewall city on page 271](#)
- [config firewall country on page 271](#)
- [config firewall decrypted-traffic-mirror on page 272](#)
- [config firewall global on page 273](#)
- [config firewall identity-based-route on page 274](#)
- [config firewall internet-service-addition on page 277](#)
- [config firewall internet-service-append on page 278](#)
- [config firewall internet-service-botnet on page 279](#)
- [config firewall internet-service-custom-group on page 282](#)
- [config firewall internet-service-custom on page 280](#)
- [config firewall internet-service-definition on page 282](#)
- [config firewall internet-service-extension on page 284](#)
- [config firewall internet-service-group on page 288](#)
- [config firewall internet-service-ipbl-reason on page 289](#)
- [config firewall internet-service-ipbl-vendor on page 289](#)
- [config firewall internet-service-list on page 290](#)
- [config firewall internet-service-name on page 290](#)
- [config firewall internet-service-owner on page 291](#)
- [config firewall internet-service-reputation on page 292](#)
- [config firewall internet-service-sld on page 293](#)
- [config firewall internet-service-subapp on page 293](#)
- [config firewall internet-service on page 275](#)
- [config firewall ippool on page 294](#)
- [config firewall ippool6 on page 294](#)
- [config firewall network-service-dynamic on page 295](#)

-
- [config firewall policy on page 296](#)
 - [config firewall profile-group on page 310](#)
 - [config firewall profile-protocol-options on page 311](#)
 - [config firewall proxy-address on page 336](#)
 - [config firewall proxy-address6 on page 341](#)
 - [config firewall proxy-addrgrp on page 346](#)
 - [config firewall proxy-addrgrp6 on page 347](#)
 - [config firewall region on page 348](#)
 - [config firewall response-shaping-policy on page 349](#)
 - [config firewall schedule group on page 352](#)
 - [config firewall schedule onetime on page 352](#)
 - [config firewall schedule recurring on page 353](#)
 - [config firewall service category on page 355](#)
 - [config firewall service custom on page 355](#)
 - [config firewall service group on page 359](#)
 - [config firewall shaper per-ip-shaper on page 360](#)
 - [config firewall shaper traffic-shaper on page 362](#)
 - [config firewall shaping-policy on page 364](#)
 - [config firewall shaping-profile on page 368](#)
 - [config firewall sniffer on page 370](#)
 - [config firewall ssh host-key on page 371](#)
 - [config firewall ssh local-ca on page 373](#)
 - [config firewall ssh local-key on page 374](#)
 - [config firewall ssh setting on page 374](#)
 - [config firewall ssl-server on page 378](#)
 - [config firewall ssl-ssh-profile on page 381](#)
 - [config firewall ssl default-certificate on page 376](#)
 - [config firewall ssl keyring-list on page 376](#)
 - [config firewall ssl setting on page 377](#)
 - [config firewall traffic-class on page 413](#)
 - [config firewall ttl-policy on page 414](#)
 - [config firewall vendor-mac-summary on page 416](#)
 - [config firewall vendor-mac on page 415](#)
 - [config firewall vip on page 416](#)
 - [config firewall vipgrp on page 451](#)
 - [config firewall wildcard-fqdn custom on page 451](#)
 - [config firewall wildcard-fqdn group on page 452](#)

config firewall access-proxy

Configure IPv4 access proxy.

```

config firewall access-proxy
    Description: Configure IPv4 access proxy.
    edit <name>
        set vip {string}
        set client-cert [disable|enable]
        set user-agent-detect [disable|enable]
        set auth-portal [disable|enable]
        set auth-virtual-host {string}
        set empty-cert-action [accept|block|...]
        set log-blocked-traffic [enable|disable]
        set add-vhost-domain-to-dnsdb [enable|disable]
        set svr-pool-multiplex [enable|disable]
        set svr-pool-ttl {integer}
        set svr-pool-server-max-request {integer}
        set svr-pool-server-max-concurrent-request {integer}
        set decrypted-traffic-mirror {string}
    config api-gateway
        Description: Set IPv4 API Gateway.
        edit <id>
            set url-map {string}
            set service [http|https|...]
            set ldb-method [static|round-robin|...]
            set virtual-host {string}
            set url-map-type [sub-string|wildcard|...]
            set h2-support [enable|disable]
            set h3-support [enable|disable]
        config quic
            Description: QUIC setting.
            set max-idle-timeout {integer}
            set max-udp-payload-size {integer}
            set active-connection-id-limit {integer}
            set ack-delay-exponent {integer}
            set max-ack-delay {integer}
            set max-datagram-frame-size {integer}
            set active-migration [enable|disable]
            set grease-quic-bit [enable|disable]
        end
    config realservers
        Description: Select the real servers that this Access Proxy will distribute
traffic to.
        edit <id>
            set addr-type [ip|fqdn]
            set address {string}
            set ip {ipv4-address-any}
            set domain {string}
            set port {integer}
            set mappedport {user}
            set status [active|standby|...]
            set type [tcp-forwarding|ssh]
            set weight {integer}
            set http-host {string}
            set health-check [disable|enable]

```

```

        set health-check-proto [ping|http|...]
        set holddown-interval [enable|disable]
        set translate-host [enable|disable]
        set ssh-client-cert {string}
        set ssh-host-key-validation [disable|enable]
        set ssh-host-key <name1>, <name2>, ...
        set verify-cert [enable|disable]
    next
end
set application <name1>, <name2>, ...
set persistence [none|http-cookie]
set http-cookie-domain-from-host [disable|enable]
set http-cookie-domain {string}
set http-cookie-path {string}
set http-cookie-generation {integer}
set http-cookie-age {integer}
set http-cookie-share [disable|same-ip]
set https-cookie-secure [disable|enable]
set saml-server {string}
set saml-redirect [disable|enable]
set ssl-dh-bits [768|1024|...]
set ssl-algorithm [high|medium|...]
config ssl-cipher-suites
    Description: SSL/TLS cipher suites to offer to a server, ordered by priority.
    edit <priority>
        set cipher [TLS-AES-128-GCM-SHA256|TLS-AES-256-GCM-SHA384|...]
        set versions {option1}, {option2}, ...
    next
end
set ssl-min-version [tls-1.0|tls-1.1|...]
set ssl-max-version [tls-1.0|tls-1.1|...]
set ssl-renegotiation [enable|disable]
next
end
config api-gateway6
    Description: Set IPv6 API Gateway.
    edit <id>
        set url-map {string}
        set service [http|https|...]
        set ldb-method [static|round-robin|...]
        set virtual-host {string}
        set url-map-type [sub-string|wildcard|...]
        set h2-support [enable|disable]
        set h3-support [enable|disable]
        config quic
            Description: QUIC setting.
            set max-idle-timeout {integer}
            set max-udp-payload-size {integer}
            set active-connection-id-limit {integer}
            set ack-delay-exponent {integer}
            set max-ack-delay {integer}
            set max-datagram-frame-size {integer}
        end
    end
end

```

```

        set active-migration [enable|disable]
        set grease-quit-bit [enable|disable]
    end
    config realservers
        Description: Select the real servers that this Access Proxy will distribute
traffic to.
        edit <id>
            set addr-type [ip|fqdn]
            set address {string}
            set ip {ipv6-address}
            set domain {string}
            set port {integer}
            set mappedport {user}
            set status [active|standby|...]
            set type [tcp-forwarding|ssh]
            set weight {integer}
            set http-host {string}
            set health-check [disable|enable]
            set health-check-proto [ping|http|...]
            set holddown-interval [enable|disable]
            set translate-host [enable|disable]
            set ssh-client-cert {string}
            set ssh-host-key-validation [disable|enable]
            set ssh-host-key <name1>, <name2>, ...
            set verify-cert [enable|disable]
        next
    end
    set application <name1>, <name2>, ...
    set persistence [none|http-cookie]
    set http-cookie-domain-from-host [disable|enable]
    set http-cookie-domain {string}
    set http-cookie-path {string}
    set http-cookie-generation {integer}
    set http-cookie-age {integer}
    set http-cookie-share [disable|same-ip]
    set https-cookie-secure [disable|enable]
    set saml-server {string}
    set saml-redirect [disable|enable]
    set ssl-dh-bits [768|1024|...]
    set ssl-algorithm [high|medium|...]
    config ssl-cipher-suites
        Description: SSL/TLS cipher suites to offer to a server, ordered by priority.
        edit <priority>
            set cipher [TLS-AES-128-GCM-SHA256|TLS-AES-256-GCM-SHA384|...]
            set versions {option1}, {option2}, ...
        next
    end
    set ssl-min-version [tls-1.0|tls-1.1|...]
    set ssl-max-version [tls-1.0|tls-1.1|...]
    set ssl-renegotiation [enable|disable]
next
end

```



```
next
end
```

config firewall access-proxy

Parameter	Description	Type	Size	Default						
name	Access Proxy name.	string	Maximum length: 79							
vip	Virtual IP name.	string	Maximum length: 79							
client-cert	Enable/disable to request client certificate.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable client certificate request.</td></tr><tr><td><i>enable</i></td><td>Enable client certificate request.</td></tr></table>	Option	Description	<i>disable</i>	Disable client certificate request.	<i>enable</i>	Enable client certificate request.			
Option	Description									
<i>disable</i>	Disable client certificate request.									
<i>enable</i>	Enable client certificate request.									
user-agent-detect	Enable/disable to detect device type by HTTP user-agent if no client certificate provided.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable to detect unknown device by HTTP user-agent if no client certificate provided.</td></tr><tr><td><i>enable</i></td><td>Enable to detect unknown device by HTTP user-agent if no client certificate provided.</td></tr></table>	Option	Description	<i>disable</i>	Disable to detect unknown device by HTTP user-agent if no client certificate provided.	<i>enable</i>	Enable to detect unknown device by HTTP user-agent if no client certificate provided.			
Option	Description									
<i>disable</i>	Disable to detect unknown device by HTTP user-agent if no client certificate provided.									
<i>enable</i>	Enable to detect unknown device by HTTP user-agent if no client certificate provided.									
auth-portal	Enable/disable authentication portal.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable authentication portal.</td></tr><tr><td><i>enable</i></td><td>Enable authentication portal.</td></tr></table>	Option	Description	<i>disable</i>	Disable authentication portal.	<i>enable</i>	Enable authentication portal.			
Option	Description									
<i>disable</i>	Disable authentication portal.									
<i>enable</i>	Enable authentication portal.									
auth-virtual-host	Virtual host for authentication portal.	string	Maximum length: 79							
empty-cert-action	Action of an empty client certificate.	option	-	block						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>accept</i></td><td>Accept the SSL handshake if the client certificate is empty.</td></tr></table>	Option	Description	<i>accept</i>	Accept the SSL handshake if the client certificate is empty.					
Option	Description									
<i>accept</i>	Accept the SSL handshake if the client certificate is empty.									

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>block</i>	Block the SSL handshake if the client certificate is empty.		
	<i>accept-unmanageable</i>	Accept the SSL handshake only if the end-point is unmanageable.		
log-blocked-traffic	Enable/disable logging of blocked traffic.	option	-	enable
	Option	Description		
	<i>enable</i>	Log all traffic denied by this access proxy.		
	<i>disable</i>	Do not log all traffic denied by this access proxy.		
add-vhost-domain-to-dnsdb	Enable/disable adding vhost/domain to dnsdb for ztna dox tunnel.	option	-	disable
	Option	Description		
	<i>enable</i>	add dns entry for all vhosts used by access proxy.		
	<i>disable</i>	Do not add dns entry for all vhosts used by access proxy.		
svr-pool-multiplex	Enable/disable server pool multiplexing (default = disable). Share connected server in HTTP, HTTPS, and web-portal api-gateway.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable server pool multiplexing. Share connected server.		
	<i>disable</i>	Disable server pool multiplexing. Do not share connected server.		
svr-pool-ttl	Time-to-live in the server pool for idle connections to servers.	integer	Minimum value: 0 Maximum value: 2147483647	15
svr-pool-server-max-request	Maximum number of requests that servers in server pool handle before disconnecting (default = unlimited).	integer	Minimum value: 0 Maximum value: 2147483647	0

Parameter	Description	Type	Size	Default
svr-pool-server-max-concurrent-request	Maximum number of concurrent requests that servers in server pool could handle (default = unlimited).	integer	Minimum value: 0 Maximum value: 2147483647	0
decrypted-traffic-mirror	Decrypted traffic mirror.	string	Maximum length: 35	

config api-gateway

Parameter	Description	Type	Size	Default												
id	API Gateway ID.	integer	Minimum value: 0 Maximum value: 4294967295	0												
url-map	URL pattern to match.	string	Maximum length: 511	/												
service	Service.	option	-	https												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>http</td><td>HTTP.</td></tr><tr><td>https</td><td>HTTPS.</td></tr><tr><td>tcp-forwarding</td><td>TCP-FORWARDING.</td></tr><tr><td>samlsp</td><td>SAML-SP.</td></tr><tr><td>saas</td><td>SAAS.</td></tr></table>				Option	Description	http	HTTP.	https	HTTPS.	tcp-forwarding	TCP-FORWARDING.	samlsp	SAML-SP.	saas	SAAS.
	Option	Description														
	http	HTTP.														
	https	HTTPS.														
	tcp-forwarding	TCP-FORWARDING.														
	samlsp	SAML-SP.														
	saas	SAAS.														
ldb-method	Method used to distribute sessions to real servers.	option	-	static												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>static</td><td>Distribute to server based on source IP.</td></tr><tr><td>round-robin</td><td>Distribute to server based round robin order.</td></tr><tr><td>weighted</td><td>Distribute to server based on weight.</td></tr><tr><td>first-alive</td><td>Distribute to the first server that is alive.</td></tr><tr><td>http-host</td><td>Distribute to server based on host field in HTTP header.</td></tr></table>				Option	Description	static	Distribute to server based on source IP.	round-robin	Distribute to server based round robin order.	weighted	Distribute to server based on weight.	first-alive	Distribute to the first server that is alive.	http-host	Distribute to server based on host field in HTTP header.
	Option	Description														
	static	Distribute to server based on source IP.														
	round-robin	Distribute to server based round robin order.														
	weighted	Distribute to server based on weight.														
	first-alive	Distribute to the first server that is alive.														
http-host	Distribute to server based on host field in HTTP header.															

Parameter	Description	Type	Size	Default
virtual-host	Virtual host.	string	Maximum length: 79	
url-map-type	Type of url-map.	option	-	sub-string
	Option	Description		
	<i>sub-string</i>	Match the pattern if a string contains the sub-string.		
	<i>wildcard</i>	Match the pattern with wildcards.		
	<i>regex</i>	Match the pattern with a regular expression.		
h2-support	HTTP2 support, default=Enable.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable HTTP2 support.		
	<i>disable</i>	Disable HTTP2 support.		
h3-support	HTTP3/QUIC support, default=Disable.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable HTTP3/QUIC support.		
	<i>disable</i>	Disable HTTP3/QUIC support.		
application <name>	SaaS application controlled by this Access Proxy. SaaS application name.	string	Maximum length: 79	
persistence	Configure how to make sure that clients connect to the same server every time they make a request that is part of the same session.	option	-	none
	Option	Description		
	<i>none</i>	None.		
	<i>http-cookie</i>	HTTP cookie.		
http-cookie-domain-from-host	Enable/disable use of HTTP cookie domain from host field in HTTP.	option	-	disable

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable use of HTTP cookie domain from host field in HTTP (use http-cooke-domain setting).</td></tr><tr><td><i>enable</i></td><td>Enable use of HTTP cookie domain from host field in HTTP.</td></tr></table>	Option	Description	<i>disable</i>	Disable use of HTTP cookie domain from host field in HTTP (use http-cooke-domain setting).	<i>enable</i>	Enable use of HTTP cookie domain from host field in HTTP.			
	Option	Description								
	<i>disable</i>	Disable use of HTTP cookie domain from host field in HTTP (use http-cooke-domain setting).								
<i>enable</i>	Enable use of HTTP cookie domain from host field in HTTP.									
http-cookie-domain	Domain that HTTP cookie persistence should apply to.	string	Maximum length: 35							
http-cookie-path	Limit HTTP cookie persistence to the specified path.	string	Maximum length: 35							
http-cookie-generation	Generation of HTTP cookie to be accepted. Changing invalidates all existing cookies.	integer	Minimum value: 0 Maximum value: 4294967295	0						
http-cookie-age	Time in minutes that client web browsers should keep a cookie. Default is 60 minutes. 0 = no time limit.	integer	Minimum value: 0 Maximum value: 525600	60						
http-cookie-share	Control sharing of cookies across API Gateway. Use of same-ip means a cookie from one virtual server can be used by another. Disable stops cookie sharing.	option	-	same-ip						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Only allow HTTP cookie to match this API Gateway.</td></tr><tr><td><i>same-ip</i></td><td>Allow HTTP cookie to match any API Gateway with same IP.</td></tr></table>	Option	Description	<i>disable</i>	Only allow HTTP cookie to match this API Gateway.	<i>same-ip</i>	Allow HTTP cookie to match any API Gateway with same IP.			
	Option	Description								
	<i>disable</i>	Only allow HTTP cookie to match this API Gateway.								
<i>same-ip</i>	Allow HTTP cookie to match any API Gateway with same IP.									
https-cookie-secure	Enable/disable verification that inserted HTTPS cookies are secure.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not mark cookie as secure, allow sharing between an HTTP and HTTPS connection.</td></tr><tr><td><i>enable</i></td><td>Mark inserted cookie as secure, cookie can only be used for HTTPS a connection.</td></tr></table>	Option	Description	<i>disable</i>	Do not mark cookie as secure, allow sharing between an HTTP and HTTPS connection.	<i>enable</i>	Mark inserted cookie as secure, cookie can only be used for HTTPS a connection.			
	Option	Description								
	<i>disable</i>	Do not mark cookie as secure, allow sharing between an HTTP and HTTPS connection.								
<i>enable</i>	Mark inserted cookie as secure, cookie can only be used for HTTPS a connection.									
saml-server	SAML service provider configuration for VIP authentication.	string	Maximum length: 35							
saml-redirect	Enable/disable SAML redirection after successful authentication.	option	-	disable						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Do not support redirection after successful SAML authentication.		
	<i>enable</i>	Support redirection after successful SAML authentication.		
ssl-dh-bits	Number of bits to use in the Diffie-Hellman exchange for RSA encryption of SSL sessions.	option	-	2048
	Option	Description		
	<i>768</i>	768-bit Diffie-Hellman prime.		
	<i>1024</i>	1024-bit Diffie-Hellman prime.		
	<i>1536</i>	1536-bit Diffie-Hellman prime.		
	<i>2048</i>	2048-bit Diffie-Hellman prime.		
	<i>3072</i>	3072-bit Diffie-Hellman prime.		
	<i>4096</i>	4096-bit Diffie-Hellman prime.		
ssl-algorithm	Permitted encryption algorithms for the server side of SSL full mode sessions according to encryption strength.	option	-	high
	Option	Description		
	<i>high</i>	High encryption. Allow only AES and ChaCha.		
	<i>medium</i>	Medium encryption. Allow AES, ChaCha, 3DES, and RC4.		
	<i>low</i>	Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.		
ssl-min-version	Lowest SSL/TLS version acceptable from a server.	option	-	tls-1.1
	Option	Description		
	<i>tls-1.0</i>	TLS 1.0.		
	<i>tls-1.1</i>	TLS 1.1.		
	<i>tls-1.2</i>	TLS 1.2.		
	<i>tls-1.3</i>	TLS 1.3.		
ssl-max-version	Highest SSL/TLS version acceptable from a server.	option	-	tls-1.3

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>tls-1.0</i>	TLS 1.0.		
	<i>tls-1.1</i>	TLS 1.1.		
	<i>tls-1.2</i>	TLS 1.2.		
	<i>tls-1.3</i>	TLS 1.3.		
ssl-renegotiation	Enable/disable secure renegotiation to comply with RFC 5746.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable secure renegotiation.		
	<i>disable</i>	Disable secure renegotiation.		

config quic

Parameter	Description	Type	Size	Default
max-idle-timeout	Maximum idle timeout milliseconds (1 - 60000, default = 30000).	integer	Minimum value: 1 Maximum value: 60000	30000
max-udp-payload-size	Maximum UDP payload size in bytes (1200 - 1500, default = 1500).	integer	Minimum value: 1200 Maximum value: 1500	1500
active-connection-id-limit	Active connection ID limit (1 - 8, default = 2).	integer	Minimum value: 1 Maximum value: 8	2
ack-delay-exponent	ACK delay exponent (1 - 20, default = 3).	integer	Minimum value: 1 Maximum value: 20	3
max-ack-delay	Maximum ACK delay in milliseconds (1 - 16383, default = 25).	integer	Minimum value: 1 Maximum value: 16383	25

Parameter	Description	Type	Size	Default						
max-datagram-frame-size	Maximum datagram frame size in bytes (1 - 1500, default = 1500).	integer	Minimum value: 1 Maximum value: 1500	1500						
active-migration	Enable/disable active migration (default = disable).	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable active migration.</td></tr><tr><td><i>disable</i></td><td>Disable active migration.</td></tr></table>	Option	Description	<i>enable</i>	Enable active migration.	<i>disable</i>	Disable active migration.			
Option	Description									
<i>enable</i>	Enable active migration.									
<i>disable</i>	Disable active migration.									
grease-quic-bit	Enable/disable grease QUIC bit (default = enable).	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable grease QUIC bit.</td></tr><tr><td><i>disable</i></td><td>Disable grease QUIC bit.</td></tr></table>	Option	Description	<i>enable</i>	Enable grease QUIC bit.	<i>disable</i>	Disable grease QUIC bit.			
Option	Description									
<i>enable</i>	Enable grease QUIC bit.									
<i>disable</i>	Disable grease QUIC bit.									

config realservers

Parameter	Description	Type	Size	Default
id	Real server ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
addr-type	Type of address.	option	-	ip
	Option	Description		
	ip	Standard IPv4 address.		
	fqdn	Non-wildcard FQDN address object.		
address	Address or address group of the real server.	string	Maximum length: 79	
ip	IP address of the real server.	ipv4-address-any	Not Specified	0.0.0.0
domain	Wildcard domain name of the real server.	string	Maximum length: 255	

Parameter	Description	Type	Size	Default								
port	Port for communicating with the real server.	integer	Minimum value: 1 Maximum value: 65535	443								
mappedport	Port for communicating with the real server.	user	Not Specified									
status	Set the status of the real server to active so that it can accept traffic, or on standby or disabled so no traffic is sent.	option	-	active								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>active</td><td>Server status active.</td></tr><tr><td>standby</td><td>Server status standby.</td></tr><tr><td>disable</td><td>Server status disable.</td></tr></table>				Option	Description	active	Server status active.	standby	Server status standby.	disable	Server status disable.
Option	Description											
active	Server status active.											
standby	Server status standby.											
disable	Server status disable.											
type	TCP forwarding server type.	option	-	tcp-forwarding								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>tcp-forwarding</td><td>TCP forwarding.</td></tr><tr><td>ssh</td><td>SSH.</td></tr></table>				Option	Description	tcp-forwarding	TCP forwarding.	ssh	SSH.		
Option	Description											
tcp-forwarding	TCP forwarding.											
ssh	SSH.											
weight	Weight of the real server. If weighted load balancing is enabled, the server with the highest weight gets more connections.	integer	Minimum value: 1 Maximum value: 255	1								
http-host	HTTP server domain name in HTTP header.	string	Maximum length: 63									
health-check	Enable to check the responsiveness of the real server before forwarding traffic.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable per server health check.</td></tr><tr><td>enable</td><td>Enable per server health check.</td></tr></table>				Option	Description	disable	Disable per server health check.	enable	Enable per server health check.		
Option	Description											
disable	Disable per server health check.											
enable	Enable per server health check.											
health-check-proto	Protocol of the health check monitor to use when polling to determine server's connectivity status.	option	-	ping								

Parameter	Description	Type	Size	Default								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ping</i></td><td>Use PING to test the link with the server.</td></tr><tr><td><i>http</i></td><td>Use HTTP-GET to test the link with the server.</td></tr><tr><td><i>tcp-connect</i></td><td>Use a full TCP connection to test the link with the server.</td></tr></table>	Option	Description	<i>ping</i>	Use PING to test the link with the server.	<i>http</i>	Use HTTP-GET to test the link with the server.	<i>tcp-connect</i>	Use a full TCP connection to test the link with the server.			
Option	Description											
<i>ping</i>	Use PING to test the link with the server.											
<i>http</i>	Use HTTP-GET to test the link with the server.											
<i>tcp-connect</i>	Use a full TCP connection to test the link with the server.											
holddown-interval	Enable/disable holddown timer. Server will be considered active and reachable once the holddown period has expired (30 seconds).	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable per server holddown.</td></tr><tr><td><i>disable</i></td><td>Disable per server holddown.</td></tr></table>	Option	Description	<i>enable</i>	Enable per server holddown.	<i>disable</i>	Disable per server holddown.					
Option	Description											
<i>enable</i>	Enable per server holddown.											
<i>disable</i>	Disable per server holddown.											
translate-host	Enable/disable translation of hostname/IP from virtual server to real server.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable virtual hostname/IP translation.</td></tr><tr><td><i>disable</i></td><td>Disable virtual hostname/IP translation.</td></tr></table>	Option	Description	<i>enable</i>	Enable virtual hostname/IP translation.	<i>disable</i>	Disable virtual hostname/IP translation.					
Option	Description											
<i>enable</i>	Enable virtual hostname/IP translation.											
<i>disable</i>	Disable virtual hostname/IP translation.											
ssh-client-cert	Set access-proxy SSH client certificate profile.	string	Maximum length: 79									
ssh-host-key-validation	Enable/disable SSH real server host key validation.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable SSH real server host key validation.</td></tr><tr><td><i>enable</i></td><td>Enable SSH real server host key validation.</td></tr></table>	Option	Description	<i>disable</i>	Disable SSH real server host key validation.	<i>enable</i>	Enable SSH real server host key validation.					
Option	Description											
<i>disable</i>	Disable SSH real server host key validation.											
<i>enable</i>	Enable SSH real server host key validation.											
ssh-host-key <name>	One or more server host key. Server host key name.	string	Maximum length: 79									
verify-cert	Enable/disable certificate verification of the real server.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable certificate verification.</td></tr><tr><td><i>disable</i></td><td>Disable certificate verification.</td></tr></table>	Option	Description	<i>enable</i>	Enable certificate verification.	<i>disable</i>	Disable certificate verification.					
Option	Description											
<i>enable</i>	Enable certificate verification.											
<i>disable</i>	Disable certificate verification.											

config ssl-cipher-suites

Parameter	Description	Type	Size	Default																		
priority	SSL/TLS cipher suites priority.	integer	Minimum value: 0 Maximum value: 4294967295	0																		
cipher	Cipher suite name.	option	-																			
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>TLS-AES-128-GCM-SHA256</td><td>Cipher suite TLS-AES-128-GCM-SHA256.</td></tr><tr><td>TLS-AES-256-GCM-SHA384</td><td>Cipher suite TLS-AES-256-GCM-SHA384.</td></tr><tr><td>TLS-CHACHA20-POLY1305-SHA256</td><td>Cipher suite TLS-CHACHA20-POLY1305-SHA256.</td></tr><tr><td>TLS-ECDHE-RSA-WITH-CHACHA20-POLY1305-SHA256</td><td>Cipher suite TLS-ECDHE-RSA-WITH-CHACHA20-POLY1305-SHA256.</td></tr><tr><td>TLS-ECDHE-ECDSA-WITH-CHACHA20-POLY1305-SHA256</td><td>Cipher suite TLS-ECDHE-ECDSA-WITH-CHACHA20-POLY1305-SHA256.</td></tr><tr><td>TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256</td><td>Cipher suite TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256.</td></tr><tr><td>TLS-DHE-RSA-WITH-AES-128-CBC-SHA</td><td>Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA.</td></tr><tr><td>TLS-DHE-RSA-WITH-AES-256-CBC-SHA</td><td>Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA.</td></tr></table>	Option	Description	TLS-AES-128-GCM-SHA256	Cipher suite TLS-AES-128-GCM-SHA256.	TLS-AES-256-GCM-SHA384	Cipher suite TLS-AES-256-GCM-SHA384.	TLS-CHACHA20-POLY1305-SHA256	Cipher suite TLS-CHACHA20-POLY1305-SHA256.	TLS-ECDHE-RSA-WITH-CHACHA20-POLY1305-SHA256	Cipher suite TLS-ECDHE-RSA-WITH-CHACHA20-POLY1305-SHA256.	TLS-ECDHE-ECDSA-WITH-CHACHA20-POLY1305-SHA256	Cipher suite TLS-ECDHE-ECDSA-WITH-CHACHA20-POLY1305-SHA256.	TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256	Cipher suite TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256.	TLS-DHE-RSA-WITH-AES-128-CBC-SHA	Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA.	TLS-DHE-RSA-WITH-AES-256-CBC-SHA	Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA.			
Option	Description																					
TLS-AES-128-GCM-SHA256	Cipher suite TLS-AES-128-GCM-SHA256.																					
TLS-AES-256-GCM-SHA384	Cipher suite TLS-AES-256-GCM-SHA384.																					
TLS-CHACHA20-POLY1305-SHA256	Cipher suite TLS-CHACHA20-POLY1305-SHA256.																					
TLS-ECDHE-RSA-WITH-CHACHA20-POLY1305-SHA256	Cipher suite TLS-ECDHE-RSA-WITH-CHACHA20-POLY1305-SHA256.																					
TLS-ECDHE-ECDSA-WITH-CHACHA20-POLY1305-SHA256	Cipher suite TLS-ECDHE-ECDSA-WITH-CHACHA20-POLY1305-SHA256.																					
TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256	Cipher suite TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256.																					
TLS-DHE-RSA-WITH-AES-128-CBC-SHA	Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA.																					
TLS-DHE-RSA-WITH-AES-256-CBC-SHA	Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA.																					

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>TLS-DHE-RSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA256.		
	<i>TLS-DHE-RSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-GCM-SHA256.		
	<i>TLS-DHE-RSA-WITH-AES-256-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA256.		
	<i>TLS-DHE-RSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-DHE-RSA-WITH-AES-256-GCM-SHA384.		
	<i>TLS-DHE-DSS-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-AES-128-CBC-SHA.		
	<i>TLS-DHE-DSS-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-AES-256-CBC-SHA.		
	<i>TLS-DHE-DSS-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-AES-128-CBC-SHA256.		
	<i>TLS-DHE-DSS-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-AES-128-GCM-SHA256.		
	<i>TLS-DHE-DSS-WITH-AES-256-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-AES-256-CBC-SHA256.		
	<i>TLS-DHE-DSS-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-DHE-DSS-WITH-AES-256-GCM-SHA384.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA.		
	<i>TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA256.		
	<i>TLS-ECDHE-RSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-128-GCM-SHA256.		
	<i>TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA.		
	<i>TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA384.		
	<i>TLS-ECDHE-RSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-256-GCM-SHA384.		
	<i>TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA.		
	<i>TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA256.		
<i>TLS-ECDHE-ECDSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-GCM-SHA256.			

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA.		
	<i>TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA384.		
	<i>TLS-ECDHE-ECDSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-GCM-SHA384.		
	<i>TLS-RSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-AES-128-CBC-SHA.		
	<i>TLS-RSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-AES-256-CBC-SHA.		
	<i>TLS-RSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-AES-128-CBC-SHA256.		
	<i>TLS-RSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-RSA-WITH-AES-128-GCM-SHA256.		
	<i>TLS-RSA-WITH-AES-256-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-AES-256-CBC-SHA256.		
	<i>TLS-RSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-RSA-WITH-AES-256-GCM-SHA384.		
	<i>TLS-RSA-WITH-CAMELLIA-128-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-CAMELLIA-128-CBC-SHA.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>TLS-RSA-WITH-CAMELLIA-256-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-CAMELLIA-256-CBC-SHA.		
	<i>TLS-RSA-WITH-CAMELLIA-128-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-CAMELLIA-128-CBC-SHA256.		
	<i>TLS-RSA-WITH-CAMELLIA-256-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-CAMELLIA-256-CBC-SHA256.		
	<i>TLS-DHE-RSA-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-3DES-EDE-CBC-SHA.		
	<i>TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA.		
	<i>TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA</i>	Cipher suite TLS-DSS-RSA-WITH-CAMELLIA-128-CBC-SHA.		
	<i>TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA.		
	<i>TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA.		
<i>TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA256.			

Parameter	Description	Type	Size	Default																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-SEED-CBC-SHA</i></td><td>Cipher suite TLS-DHE-RSA-WITH-SEED-CBC-SHA.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-SEED-CBC-SHA</i></td><td>Cipher suite TLS-DHE-DSS-WITH-SEED-CBC-SHA.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-ARIA-128-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-RSA-WITH-ARIA-128-CBC-SHA256.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384</i></td><td>Cipher suite TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-ARIA-128-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-DSS-WITH-ARIA-128-CBC-SHA256.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-ARIA-256-CBC-SHA384</i></td><td>Cipher suite TLS-DHE-DSS-WITH-ARIA-256-CBC-SHA384.</td></tr></table>	Option	Description	<i>TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256.	<i>TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256.	<i>TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256.	<i>TLS-DHE-RSA-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-SEED-CBC-SHA.	<i>TLS-DHE-DSS-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-SEED-CBC-SHA.	<i>TLS-DHE-RSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-ARIA-128-CBC-SHA256.	<i>TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384.	<i>TLS-DHE-DSS-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-ARIA-128-CBC-SHA256.	<i>TLS-DHE-DSS-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-DHE-DSS-WITH-ARIA-256-CBC-SHA384.			
Option	Description																							
<i>TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256.																							
<i>TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256.																							
<i>TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256.																							
<i>TLS-DHE-RSA-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-SEED-CBC-SHA.																							
<i>TLS-DHE-DSS-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-SEED-CBC-SHA.																							
<i>TLS-DHE-RSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-ARIA-128-CBC-SHA256.																							
<i>TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384.																							
<i>TLS-DHE-DSS-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-ARIA-128-CBC-SHA256.																							
<i>TLS-DHE-DSS-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-DHE-DSS-WITH-ARIA-256-CBC-SHA384.																							

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>TLS-RSA-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-SEED-CBC-SHA.		
	<i>TLS-RSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-ARIA-128-CBC-SHA256.		
	<i>TLS-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-RSA-WITH-ARIA-256-CBC-SHA384.		
	<i>TLS-ECDHE-RSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-ARIA-128-CBC-SHA256.		
	<i>TLS-ECDHE-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-RSA-WITH-ARIA-256-CBC-SHA384.		
	<i>TLS-ECDHE-ECDSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-ARIA-128-CBC_SHA256.		
	<i>TLS-ECDHE-ECDSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-ARIA-256-CBC_SHA384.		
	<i>TLS-ECDHE-RSA-WITH-RC4-128-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-RC4-128-SHA.		
	<i>TLS-ECDHE-RSA-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-3DES-EDE-CBC-SHA.		
	<i>TLS-DHE-DSS-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-3DES-EDE-CBC-SHA.		

Parameter	Description	Type	Size	Default														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>TLS-RSA-WITH-3DES-EDE-CBC-SHA</i></td><td>Cipher suite TLS-RSA-WITH-3DES-EDE-CBC-SHA.</td></tr><tr><td><i>TLS-RSA-WITH-RC4-128-MD5</i></td><td>Cipher suite TLS-RSA-WITH-RC4-128-MD5.</td></tr><tr><td><i>TLS-RSA-WITH-RC4-128-SHA</i></td><td>Cipher suite TLS-RSA-WITH-RC4-128-SHA.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-DES-CBC-SHA</i></td><td>Cipher suite TLS-DHE-RSA-WITH-DES-CBC-SHA.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-DES-CBC-SHA</i></td><td>Cipher suite TLS-DHE-DSS-WITH-DES-CBC-SHA.</td></tr><tr><td><i>TLS-RSA-WITH-DES-CBC-SHA</i></td><td>Cipher suite TLS-RSA-WITH-DES-CBC-SHA.</td></tr></table>	Option	Description	<i>TLS-RSA-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-3DES-EDE-CBC-SHA.	<i>TLS-RSA-WITH-RC4-128-MD5</i>	Cipher suite TLS-RSA-WITH-RC4-128-MD5.	<i>TLS-RSA-WITH-RC4-128-SHA</i>	Cipher suite TLS-RSA-WITH-RC4-128-SHA.	<i>TLS-DHE-RSA-WITH-DES-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-DES-CBC-SHA.	<i>TLS-DHE-DSS-WITH-DES-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-DES-CBC-SHA.	<i>TLS-RSA-WITH-DES-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-DES-CBC-SHA.			
	Option	Description																
	<i>TLS-RSA-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-3DES-EDE-CBC-SHA.																
	<i>TLS-RSA-WITH-RC4-128-MD5</i>	Cipher suite TLS-RSA-WITH-RC4-128-MD5.																
	<i>TLS-RSA-WITH-RC4-128-SHA</i>	Cipher suite TLS-RSA-WITH-RC4-128-SHA.																
	<i>TLS-DHE-RSA-WITH-DES-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-DES-CBC-SHA.																
	<i>TLS-DHE-DSS-WITH-DES-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-DES-CBC-SHA.																
<i>TLS-RSA-WITH-DES-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-DES-CBC-SHA.																	
versions	SSL/TLS versions that the cipher suite can be used with.	option	-	tls-1.0 tls-1.1 tls-1.2 tls-1.3														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>tls-1.0</i></td><td>TLS 1.0.</td></tr><tr><td><i>tls-1.1</i></td><td>TLS 1.1.</td></tr><tr><td><i>tls-1.2</i></td><td>TLS 1.2.</td></tr><tr><td><i>tls-1.3</i></td><td>TLS 1.3.</td></tr></table>	Option	Description	<i>tls-1.0</i>	TLS 1.0.	<i>tls-1.1</i>	TLS 1.1.	<i>tls-1.2</i>	TLS 1.2.	<i>tls-1.3</i>	TLS 1.3.							
	Option	Description																
	<i>tls-1.0</i>	TLS 1.0.																
	<i>tls-1.1</i>	TLS 1.1.																
	<i>tls-1.2</i>	TLS 1.2.																
<i>tls-1.3</i>	TLS 1.3.																	

config api-gateway6

Parameter	Description	Type	Size	Default
id	API Gateway ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

Parameter	Description	Type	Size	Default												
url-map	URL pattern to match.	string	Maximum length: 511	/												
service	Service.	option	-	https												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>http</td><td>HTTP.</td></tr><tr><td>https</td><td>HTTPS.</td></tr><tr><td>tcp-forwarding</td><td>TCP-FORWARDING.</td></tr><tr><td>samlsp</td><td>SAML-SP.</td></tr><tr><td>saas</td><td>SAAS.</td></tr></table>	Option	Description	http	HTTP.	https	HTTPS.	tcp-forwarding	TCP-FORWARDING.	samlsp	SAML-SP.	saas	SAAS.			
Option	Description															
http	HTTP.															
https	HTTPS.															
tcp-forwarding	TCP-FORWARDING.															
samlsp	SAML-SP.															
saas	SAAS.															
ldb-method	Method used to distribute sessions to real servers.	option	-	static												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>static</td><td>Distribute to server based on source IP.</td></tr><tr><td>round-robin</td><td>Distribute to server based round robin order.</td></tr><tr><td>weighted</td><td>Distribute to server based on weight.</td></tr><tr><td>first-alive</td><td>Distribute to the first server that is alive.</td></tr><tr><td>http-host</td><td>Distribute to server based on host field in HTTP header.</td></tr></table>	Option	Description	static	Distribute to server based on source IP.	round-robin	Distribute to server based round robin order.	weighted	Distribute to server based on weight.	first-alive	Distribute to the first server that is alive.	http-host	Distribute to server based on host field in HTTP header.			
Option	Description															
static	Distribute to server based on source IP.															
round-robin	Distribute to server based round robin order.															
weighted	Distribute to server based on weight.															
first-alive	Distribute to the first server that is alive.															
http-host	Distribute to server based on host field in HTTP header.															
virtual-host	Virtual host.	string	Maximum length: 79													
url-map-type	Type of url-map.	option	-	sub-string												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>sub-string</td><td>Match the pattern if a string contains the sub-string.</td></tr><tr><td>wildcard</td><td>Match the pattern with wildcards.</td></tr><tr><td>regex</td><td>Match the pattern with a regular expression.</td></tr></table>	Option	Description	sub-string	Match the pattern if a string contains the sub-string.	wildcard	Match the pattern with wildcards.	regex	Match the pattern with a regular expression.							
Option	Description															
sub-string	Match the pattern if a string contains the sub-string.															
wildcard	Match the pattern with wildcards.															
regex	Match the pattern with a regular expression.															
h2-support	HTTP2 support, default=Enable.	option	-	enable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable HTTP2 support.</td></tr><tr><td>disable</td><td>Disable HTTP2 support.</td></tr></table>	Option	Description	enable	Enable HTTP2 support.	disable	Disable HTTP2 support.									
Option	Description															
enable	Enable HTTP2 support.															
disable	Disable HTTP2 support.															

Parameter	Description	Type	Size	Default
h3-support	HTTP3/QUIC support, default=Disable.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable HTTP3/QUIC support.		
	<i>disable</i>	Disable HTTP3/QUIC support.		
application <name>	SaaS application controlled by this Access Proxy. SaaS application name.	string	Maximum length: 79	
persistence	Configure how to make sure that clients connect to the same server every time they make a request that is part of the same session.	option	-	none
	Option	Description		
	<i>none</i>	None.		
	<i>http-cookie</i>	HTTP cookie.		
http-cookie-domain-from-host	Enable/disable use of HTTP cookie domain from host field in HTTP.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable use of HTTP cookie domain from host field in HTTP (use http-cooke-domain setting).		
	<i>enable</i>	Enable use of HTTP cookie domain from host field in HTTP.		
http-cookie-domain	Domain that HTTP cookie persistence should apply to.	string	Maximum length: 35	
http-cookie-path	Limit HTTP cookie persistence to the specified path.	string	Maximum length: 35	
http-cookie-generation	Generation of HTTP cookie to be accepted. Changing invalidates all existing cookies.	integer	Minimum value: 0 Maximum value: 4294967295	0
http-cookie-age	Time in minutes that client web browsers should keep a cookie. Default is 60 minutes. 0 = no time limit.	integer	Minimum value: 0 Maximum value: 525600	60

Parameter	Description	Type	Size	Default														
http-cookie-share	Control sharing of cookies across API Gateway. Use of same-ip means a cookie from one virtual server can be used by another. Disable stops cookie sharing.	option	-	same-ip														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Only allow HTTP cookie to match this API Gateway.</td></tr><tr><td>same-ip</td><td>Allow HTTP cookie to match any API Gateway with same IP.</td></tr></table>	Option	Description	disable	Only allow HTTP cookie to match this API Gateway.	same-ip	Allow HTTP cookie to match any API Gateway with same IP.											
Option	Description																	
disable	Only allow HTTP cookie to match this API Gateway.																	
same-ip	Allow HTTP cookie to match any API Gateway with same IP.																	
https-cookie-secure	Enable/disable verification that inserted HTTPS cookies are secure.	option	-	disable														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Do not mark cookie as secure, allow sharing between an HTTP and HTTPS connection.</td></tr><tr><td>enable</td><td>Mark inserted cookie as secure, cookie can only be used for HTTPS a connection.</td></tr></table>	Option	Description	disable	Do not mark cookie as secure, allow sharing between an HTTP and HTTPS connection.	enable	Mark inserted cookie as secure, cookie can only be used for HTTPS a connection.											
Option	Description																	
disable	Do not mark cookie as secure, allow sharing between an HTTP and HTTPS connection.																	
enable	Mark inserted cookie as secure, cookie can only be used for HTTPS a connection.																	
saml-server	SAML service provider configuration for VIP authentication.	string	Maximum length: 35															
saml-redirect	Enable/disable SAML redirection after successful authentication.	option	-	disable														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Do not support redirection after successful SAML authentication.</td></tr><tr><td>enable</td><td>Support redirection after successful SAML authentication.</td></tr></table>	Option	Description	disable	Do not support redirection after successful SAML authentication.	enable	Support redirection after successful SAML authentication.											
Option	Description																	
disable	Do not support redirection after successful SAML authentication.																	
enable	Support redirection after successful SAML authentication.																	
ssl-dh-bits	Number of bits to use in the Diffie-Hellman exchange for RSA encryption of SSL sessions.	option	-	2048														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>768</td><td>768-bit Diffie-Hellman prime.</td></tr><tr><td>1024</td><td>1024-bit Diffie-Hellman prime.</td></tr><tr><td>1536</td><td>1536-bit Diffie-Hellman prime.</td></tr><tr><td>2048</td><td>2048-bit Diffie-Hellman prime.</td></tr><tr><td>3072</td><td>3072-bit Diffie-Hellman prime.</td></tr><tr><td>4096</td><td>4096-bit Diffie-Hellman prime.</td></tr></table>	Option	Description	768	768-bit Diffie-Hellman prime.	1024	1024-bit Diffie-Hellman prime.	1536	1536-bit Diffie-Hellman prime.	2048	2048-bit Diffie-Hellman prime.	3072	3072-bit Diffie-Hellman prime.	4096	4096-bit Diffie-Hellman prime.			
Option	Description																	
768	768-bit Diffie-Hellman prime.																	
1024	1024-bit Diffie-Hellman prime.																	
1536	1536-bit Diffie-Hellman prime.																	
2048	2048-bit Diffie-Hellman prime.																	
3072	3072-bit Diffie-Hellman prime.																	
4096	4096-bit Diffie-Hellman prime.																	

Parameter	Description	Type	Size	Default										
ssl-algorithm	Permitted encryption algorithms for the server side of SSL full mode sessions according to encryption strength.	option	-	high										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>high</i></td><td>High encryption. Allow only AES and ChaCha.</td></tr><tr><td><i>medium</i></td><td>Medium encryption. Allow AES, ChaCha, 3DES, and RC4.</td></tr><tr><td><i>low</i></td><td>Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.</td></tr></table>	Option	Description	<i>high</i>	High encryption. Allow only AES and ChaCha.	<i>medium</i>	Medium encryption. Allow AES, ChaCha, 3DES, and RC4.	<i>low</i>	Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.					
Option	Description													
<i>high</i>	High encryption. Allow only AES and ChaCha.													
<i>medium</i>	Medium encryption. Allow AES, ChaCha, 3DES, and RC4.													
<i>low</i>	Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.													
ssl-min-version	Lowest SSL/TLS version acceptable from a server.	option	-	tls-1.1										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>tls-1.0</i></td><td>TLS 1.0.</td></tr><tr><td><i>tls-1.1</i></td><td>TLS 1.1.</td></tr><tr><td><i>tls-1.2</i></td><td>TLS 1.2.</td></tr><tr><td><i>tls-1.3</i></td><td>TLS 1.3.</td></tr></table>	Option	Description	<i>tls-1.0</i>	TLS 1.0.	<i>tls-1.1</i>	TLS 1.1.	<i>tls-1.2</i>	TLS 1.2.	<i>tls-1.3</i>	TLS 1.3.			
Option	Description													
<i>tls-1.0</i>	TLS 1.0.													
<i>tls-1.1</i>	TLS 1.1.													
<i>tls-1.2</i>	TLS 1.2.													
<i>tls-1.3</i>	TLS 1.3.													
ssl-max-version	Highest SSL/TLS version acceptable from a server.	option	-	tls-1.3										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>tls-1.0</i></td><td>TLS 1.0.</td></tr><tr><td><i>tls-1.1</i></td><td>TLS 1.1.</td></tr><tr><td><i>tls-1.2</i></td><td>TLS 1.2.</td></tr><tr><td><i>tls-1.3</i></td><td>TLS 1.3.</td></tr></table>	Option	Description	<i>tls-1.0</i>	TLS 1.0.	<i>tls-1.1</i>	TLS 1.1.	<i>tls-1.2</i>	TLS 1.2.	<i>tls-1.3</i>	TLS 1.3.			
Option	Description													
<i>tls-1.0</i>	TLS 1.0.													
<i>tls-1.1</i>	TLS 1.1.													
<i>tls-1.2</i>	TLS 1.2.													
<i>tls-1.3</i>	TLS 1.3.													
ssl-renegotiation	Enable/disable secure renegotiation to comply with RFC 5746.	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable secure renegotiation.</td></tr><tr><td><i>disable</i></td><td>Disable secure renegotiation.</td></tr></table>	Option	Description	<i>enable</i>	Enable secure renegotiation.	<i>disable</i>	Disable secure renegotiation.							
Option	Description													
<i>enable</i>	Enable secure renegotiation.													
<i>disable</i>	Disable secure renegotiation.													

config quic

Parameter	Description	Type	Size	Default						
max-idle-timeout	Maximum idle timeout milliseconds (1 - 60000, default = 30000).	integer	Minimum value: 1 Maximum value: 60000	30000						
max-udp-payload-size	Maximum UDP payload size in bytes (1200 - 1500, default = 1500).	integer	Minimum value: 1200 Maximum value: 1500	1500						
active-connection-id-limit	Active connection ID limit (1 - 8, default = 2).	integer	Minimum value: 1 Maximum value: 8	2						
ack-delay-exponent	ACK delay exponent (1 - 20, default = 3).	integer	Minimum value: 1 Maximum value: 20	3						
max-ack-delay	Maximum ACK delay in milliseconds (1 - 16383, default = 25).	integer	Minimum value: 1 Maximum value: 16383	25						
max-datagram-frame-size	Maximum datagram frame size in bytes (1 - 1500, default = 1500).	integer	Minimum value: 1 Maximum value: 1500	1500						
active-migration	Enable/disable active migration (default = disable).	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable active migration.</td></tr><tr><td><i>disable</i></td><td>Disable active migration.</td></tr></table>	Option	Description	<i>enable</i>	Enable active migration.	<i>disable</i>	Disable active migration.			
Option	Description									
<i>enable</i>	Enable active migration.									
<i>disable</i>	Disable active migration.									
grease-quic-bit	Enable/disable grease QUIC bit (default = enable).	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable grease QUIC bit.</td></tr><tr><td><i>disable</i></td><td>Disable grease QUIC bit.</td></tr></table>	Option	Description	<i>enable</i>	Enable grease QUIC bit.	<i>disable</i>	Disable grease QUIC bit.			
Option	Description									
<i>enable</i>	Enable grease QUIC bit.									
<i>disable</i>	Disable grease QUIC bit.									

config realservers

Parameter	Description	Type	Size	Default								
id	Real server ID.	integer	Minimum value: 0 Maximum value: 4294967295	0								
addr-type	Type of address.	option	-	ip								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ip</i></td><td>Standard IPv4 address.</td></tr><tr><td><i>fqdn</i></td><td>Non-wildcard FQDN address object.</td></tr></table>				Option	Description	<i>ip</i>	Standard IPv4 address.	<i>fqdn</i>	Non-wildcard FQDN address object.		
	Option	Description										
	<i>ip</i>	Standard IPv4 address.										
<i>fqdn</i>	Non-wildcard FQDN address object.											
address	Address or address group of the real server.	string	Maximum length: 79									
ip	IPv6 address of the real server.	ipv6-address	Not Specified	::								
domain	Wildcard domain name of the real server.	string	Maximum length: 255									
port	Port for communicating with the real server.	integer	Minimum value: 1 Maximum value: 65535	443								
mappedport	Port for communicating with the real server.	user	Not Specified									
status	Set the status of the real server to active so that it can accept traffic, or on standby or disabled so no traffic is sent.	option	-	active								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>active</i></td><td>Server status active.</td></tr><tr><td><i>standby</i></td><td>Server status standby.</td></tr><tr><td><i>disable</i></td><td>Server status disable.</td></tr></table>				Option	Description	<i>active</i>	Server status active.	<i>standby</i>	Server status standby.	<i>disable</i>	Server status disable.
	Option	Description										
	<i>active</i>	Server status active.										
	<i>standby</i>	Server status standby.										
<i>disable</i>	Server status disable.											
type	TCP forwarding server type.	option	-	tcp-forwarding								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>tcp-forwarding</i>	TCP forwarding.		
	<i>ssh</i>	SSH.		
weight	Weight of the real server. If weighted load balancing is enabled, the server with the highest weight gets more connections.	integer	Minimum value: 1 Maximum value: 255	1
http-host	HTTP server domain name in HTTP header.	string	Maximum length: 63	
health-check	Enable to check the responsiveness of the real server before forwarding traffic.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable per server health check.		
	<i>enable</i>	Enable per server health check.		
health-check-proto	Protocol of the health check monitor to use when polling to determine server's connectivity status.	option	-	ping
	Option	Description		
	<i>ping</i>	Use PING to test the link with the server.		
	<i>http</i>	Use HTTP-GET to test the link with the server.		
	<i>tcp-connect</i>	Use a full TCP connection to test the link with the server.		
holddown-interval	Enable/disable holddown timer. Server will be considered active and reachable once the holddown period has expired (30 seconds).	option	-	enable
	Option	Description		
	<i>enable</i>	Enable per server holddown.		
	<i>disable</i>	Disable per server holddown.		
translate-host	Enable/disable translation of hostname/IP from virtual server to real server.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable virtual hostname/IP translation.		
	<i>disable</i>	Disable virtual hostname/IP translation.		
ssh-client-cert	Set access-proxy SSH client certificate profile.	string	Maximum length: 79	
ssh-host-key-validation	Enable/disable SSH real server host key validation.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable SSH real server host key validation.		
	<i>enable</i>	Enable SSH real server host key validation.		
ssh-host-key <name>	One or more server host key. Server host key name.	string	Maximum length: 79	
verify-cert	Enable/disable certificate verification of the real server.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable certificate verification.		
	<i>disable</i>	Disable certificate verification.		

config ssl-cipher-suites

Parameter	Description	Type	Size	Default
priority	SSL/TLS cipher suites priority.	integer	Minimum value: 0 Maximum value: 4294967295	0
cipher	Cipher suite name.	option	-	
	Option	Description		
	<i>TLS-AES-128-GCM-SHA256</i>	Cipher suite TLS-AES-128-GCM-SHA256.		
	<i>TLS-AES-256-GCM-SHA384</i>	Cipher suite TLS-AES-256-GCM-SHA384.		

Parameter	Description	Type	Size	Default																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>TLS-CHACHA20-POLY1305-SHA256</i></td><td>Cipher suite TLS-CHACHA20-POLY1305-SHA256.</td></tr><tr><td><i>TLS-ECDHE-RSA-WITH-CHACHA20-POLY1305-SHA256</i></td><td>Cipher suite TLS-ECDHE-RSA-WITH-CHACHA20-POLY1305-SHA256.</td></tr><tr><td><i>TLS-ECDHE-ECDSA-WITH-CHACHA20-POLY1305-SHA256</i></td><td>Cipher suite TLS-ECDHE-ECDSA-WITH-CHACHA20-POLY1305-SHA256.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256</i></td><td>Cipher suite TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-AES-128-CBC-SHA</i></td><td>Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-AES-256-CBC-SHA</i></td><td>Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-AES-128-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA256.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-AES-128-GCM-SHA256</i></td><td>Cipher suite TLS-DHE-RSA-WITH-AES-128-GCM-SHA256.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-AES-256-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA256.</td></tr></table>	Option	Description	<i>TLS-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-CHACHA20-POLY1305-SHA256.	<i>TLS-ECDHE-RSA-WITH-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-CHACHA20-POLY1305-SHA256.	<i>TLS-ECDHE-ECDSA-WITH-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-CHACHA20-POLY1305-SHA256.	<i>TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256.	<i>TLS-DHE-RSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA.	<i>TLS-DHE-RSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA.	<i>TLS-DHE-RSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA256.	<i>TLS-DHE-RSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-GCM-SHA256.	<i>TLS-DHE-RSA-WITH-AES-256-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA256.			
Option	Description																							
<i>TLS-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-CHACHA20-POLY1305-SHA256.																							
<i>TLS-ECDHE-RSA-WITH-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-CHACHA20-POLY1305-SHA256.																							
<i>TLS-ECDHE-ECDSA-WITH-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-CHACHA20-POLY1305-SHA256.																							
<i>TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256.																							
<i>TLS-DHE-RSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA.																							
<i>TLS-DHE-RSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA.																							
<i>TLS-DHE-RSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA256.																							
<i>TLS-DHE-RSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-GCM-SHA256.																							
<i>TLS-DHE-RSA-WITH-AES-256-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA256.																							

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>TLS-DHE-RSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-DHE-RSA-WITH-AES-256-GCM-SHA384.		
	<i>TLS-DHE-DSS-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-AES-128-CBC-SHA.		
	<i>TLS-DHE-DSS-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-AES-256-CBC-SHA.		
	<i>TLS-DHE-DSS-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-AES-128-CBC-SHA256.		
	<i>TLS-DHE-DSS-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-AES-128-GCM-SHA256.		
	<i>TLS-DHE-DSS-WITH-AES-256-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-AES-256-CBC-SHA256.		
	<i>TLS-DHE-DSS-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-DHE-DSS-WITH-AES-256-GCM-SHA384.		
	<i>TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA.		
	<i>TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA256.		
	<i>TLS-ECDHE-RSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-128-GCM-SHA256.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA.		
	<i>TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA384.		
	<i>TLS-ECDHE-RSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-256-GCM-SHA384.		
	<i>TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA.		
	<i>TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA256.		
	<i>TLS-ECDHE-ECDSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-GCM-SHA256.		
	<i>TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA.		
	<i>TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA384.		
	<i>TLS-ECDHE-ECDSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-GCM-SHA384.		
	<i>TLS-RSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-AES-128-CBC-SHA.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>TLS-RSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-AES-256-CBC-SHA.		
	<i>TLS-RSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-AES-128-CBC-SHA256.		
	<i>TLS-RSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-RSA-WITH-AES-128-GCM-SHA256.		
	<i>TLS-RSA-WITH-AES-256-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-AES-256-CBC-SHA256.		
	<i>TLS-RSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-RSA-WITH-AES-256-GCM-SHA384.		
	<i>TLS-RSA-WITH-CAMELLIA-128-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-CAMELLIA-128-CBC-SHA.		
	<i>TLS-RSA-WITH-CAMELLIA-256-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-CAMELLIA-256-CBC-SHA.		
	<i>TLS-RSA-WITH-CAMELLIA-128-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-CAMELLIA-128-CBC-SHA256.		
	<i>TLS-RSA-WITH-CAMELLIA-256-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-CAMELLIA-256-CBC-SHA256.		

Parameter	Description	Type	Size	Default																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>TLS-DHE-RSA-WITH-3DES-EDE-CBC-SHA</td><td>Cipher suite TLS-DHE-RSA-WITH-3DES-EDE-CBC-SHA.</td></tr><tr><td>TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA</td><td>Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA.</td></tr><tr><td>TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA</td><td>Cipher suite TLS-DSS-RSA-WITH-CAMELLIA-128-CBC-SHA.</td></tr><tr><td>TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA</td><td>Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA.</td></tr><tr><td>TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA</td><td>Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA.</td></tr><tr><td>TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA256</td><td>Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA256.</td></tr><tr><td>TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256</td><td>Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256.</td></tr><tr><td>TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256</td><td>Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256.</td></tr><tr><td>TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256</td><td>Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256.</td></tr></table>	Option	Description	TLS-DHE-RSA-WITH-3DES-EDE-CBC-SHA	Cipher suite TLS-DHE-RSA-WITH-3DES-EDE-CBC-SHA.	TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA.	TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA	Cipher suite TLS-DSS-RSA-WITH-CAMELLIA-128-CBC-SHA.	TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA.	TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA.	TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA256	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA256.	TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256.	TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256.	TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256.			
Option	Description																							
TLS-DHE-RSA-WITH-3DES-EDE-CBC-SHA	Cipher suite TLS-DHE-RSA-WITH-3DES-EDE-CBC-SHA.																							
TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA.																							
TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA	Cipher suite TLS-DSS-RSA-WITH-CAMELLIA-128-CBC-SHA.																							
TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA.																							
TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA.																							
TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA256	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA256.																							
TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256.																							
TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256.																							
TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256.																							

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>TLS-DHE-RSA-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-SEED-CBC-SHA.		
	<i>TLS-DHE-DSS-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-SEED-CBC-SHA.		
	<i>TLS-DHE-RSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-ARIA-128-CBC-SHA256.		
	<i>TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384.		
	<i>TLS-DHE-DSS-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-ARIA-128-CBC-SHA256.		
	<i>TLS-DHE-DSS-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-DHE-DSS-WITH-ARIA-256-CBC-SHA384.		
	<i>TLS-RSA-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-SEED-CBC-SHA.		
	<i>TLS-RSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-ARIA-128-CBC-SHA256.		
	<i>TLS-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-RSA-WITH-ARIA-256-CBC-SHA384.		
	<i>TLS-ECDHE-RSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-ARIA-128-CBC-SHA256.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>TLS-ECDHE-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-RSA-WITH-ARIA-256-CBC-SHA384.		
	<i>TLS-ECDHE-ECDSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-ARIA-128-CBC-SHA256.		
	<i>TLS-ECDHE-ECDSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-ARIA-256-CBC-SHA384.		
	<i>TLS-ECDHE-RSA-WITH-RC4-128-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-RC4-128-SHA.		
	<i>TLS-ECDHE-RSA-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-3DES-EDE-CBC-SHA.		
	<i>TLS-DHE-DSS-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-3DES-EDE-CBC-SHA.		
	<i>TLS-RSA-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-3DES-EDE-CBC-SHA.		
	<i>TLS-RSA-WITH-RC4-128-MD5</i>	Cipher suite TLS-RSA-WITH-RC4-128-MD5.		
	<i>TLS-RSA-WITH-RC4-128-SHA</i>	Cipher suite TLS-RSA-WITH-RC4-128-SHA.		
	<i>TLS-DHE-RSA-WITH-DES-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-DES-CBC-SHA.		
	<i>TLS-DHE-DSS-WITH-DES-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-DES-CBC-SHA.		

Parameter	Description	Type	Size	Default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>TLS-RSA-WITH-DES-CBC-SHA</i></td><td>Cipher suite TLS-RSA-WITH-DES-CBC-SHA.</td></tr></table>	Option	Description	<i>TLS-RSA-WITH-DES-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-DES-CBC-SHA.									
Option	Description													
<i>TLS-RSA-WITH-DES-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-DES-CBC-SHA.													
versions	SSL/TLS versions that the cipher suite can be used with.	option	-	tls-1.0 tls-1.1 tls-1.2 tls-1.3										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>tls-1.0</i></td><td>TLS 1.0.</td></tr><tr><td><i>tls-1.1</i></td><td>TLS 1.1.</td></tr><tr><td><i>tls-1.2</i></td><td>TLS 1.2.</td></tr><tr><td><i>tls-1.3</i></td><td>TLS 1.3.</td></tr></table>	Option	Description	<i>tls-1.0</i>	TLS 1.0.	<i>tls-1.1</i>	TLS 1.1.	<i>tls-1.2</i>	TLS 1.2.	<i>tls-1.3</i>	TLS 1.3.			
Option	Description													
<i>tls-1.0</i>	TLS 1.0.													
<i>tls-1.1</i>	TLS 1.1.													
<i>tls-1.2</i>	TLS 1.2.													
<i>tls-1.3</i>	TLS 1.3.													

config firewall access-proxy6

Configure IPv6 access proxy.

```
config firewall access-proxy6
    Description: Configure IPv6 access proxy.
    edit <name>
        set vip {string}
    next
end
```

config firewall access-proxy6

Parameter	Description	Type	Size	Default
name	Access Proxy name.	string	Maximum length: 79	
vip	Virtual IP name.	string	Maximum length: 79	

config firewall access-proxy-ssh-client-cert

Configure Access Proxy SSH client certificate.

```

config firewall access-proxy-ssh-client-cert
    Description: Configure Access Proxy SSH client certificate.
    edit <name>
        set source-address [enable|disable]
        set permit-x11-forwarding [enable|disable]
        set permit-agent-forwarding [enable|disable]
        set permit-port-forwarding [enable|disable]
        set permit-pty [enable|disable]
        set permit-user-rc [enable|disable]
    config cert-extension
        Description: Configure certificate extension for user certificate.
        edit <name>
            set critical [no|yes]
            set type [fixed|user]
            set data {string}
        next
    end
    set auth-ca {string}
next
end

```

config firewall access-proxy-ssh-client-cert

Parameter	Description	Type	Size	Default						
name	SSH client certificate name.	string	Maximum length: 79							
source-address	Enable/disable appending source-address certificate critical option. This option ensure certificate only accepted from FortiGate source address.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
permit-x11-forwarding	Enable/disable appending permit-x11-forwarding certificate extension.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
permit-agent-forwarding	Enable/disable appending permit-agent-forwarding certificate extension.	option	-	enable						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
permit-port-forwarding	Enable/disable appending permit-port-forwarding certificate extension.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
permit-pty	Enable/disable appending permit-pty certificate extension.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
permit-user-rc	Enable/disable appending permit-user-rc certificate extension.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
auth-ca	Name of the SSH server public key authentication CA.	string	Maximum length: 79	

config cert-extension

Parameter	Description	Type	Size	Default
name	Name of certificate extension.	string	Maximum length: 127	
critical	Critical option.	option	-	no
	Option	Description		
	<i>no</i>	Certificate extension, server ignores the unsupported certificate extension.		
	<i>yes</i>	Critical option, server refuses to authorize if it cannot recognize the critical option.		

Parameter	Description	Type	Size	Default						
type	Type of certificate extension.	option	-	fixed						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>fixed</i></td><td>Fixed certificate extension entry.</td></tr><tr><td><i>user</i></td><td>Certificate extension entry filled with authenticated username.</td></tr></table>				Option	Description	<i>fixed</i>	Fixed certificate extension entry.	<i>user</i>	Certificate extension entry filled with authenticated username.
	Option	Description								
	<i>fixed</i>	Fixed certificate extension entry.								
<i>user</i>	Certificate extension entry filled with authenticated username.									
data	Data of certificate extension.	string	Maximum length: 127							

config firewall access-proxy-virtual-host

Configure Access Proxy virtual hosts.

```
config firewall access-proxy-virtual-host
  Description: Configure Access Proxy virtual hosts.
  edit <name>
    set ssl-certificate <name1>, <name2>, ...
    set host {string}
    set host-type [sub-string|wildcard]
    set replacemsg-group {string}
  next
end
```

config firewall access-proxy-virtual-host

Parameter	Description	Type	Size	Default
name	Virtual host name.	string	Maximum length: 79	
ssl-certificate <name>	SSL certificates for this host. Certificate list.	string	Maximum length: 79	
host	The host name.	string	Maximum length: 79	
host-type	Type of host pattern.	option	-	sub-string
	Option	Description		
	sub-string	Match the pattern if a string contains the sub-string.		
	wildcard	Match the pattern with wildcards.		
replacemsg-group	Access-proxy-virtual-host replacement message override group.	string	Maximum length: 35	

config firewall address

Configure IPv4 addresses.

```
config firewall address
  Description: Configure IPv4 addresses.
  edit <name>
    set uuid {uuid}
    set subnet {ipv4-classnet-any}
    set type [ipmask|iprange|...]
    set sub-type [sdn|fsso|...]
    set clearpass-spt [unknown|healthy|...]
    set start-ip {ipv4-address-any}
    set end-ip {ipv4-address-any}
    set fqdn {string}
    set country {string}
    set wildcard-fqdn {string}
    set pattern-start {integer}
    set pattern-end {integer}
    set cache-ttl {integer}
    set wildcard {ipv4-classnet-any}
    set sdn {string}
    set fsso-group <name1>, <name2>, ...
    set interface {string}
    set tenant {string}
    set organization {string}
    set epg-name {string}
    set subnet-name {string}
    set sdn-tag {string}
    set policy-group {string}
    set obj-tag {string}
    set obj-type [ip|mac]
    set tag-detection-level {string}
    set tag-type {string}
    set comment {var-string}
    set associated-interface {string}
    set color {integer}
    set filter {var-string}
    set sdn-addr-type [private|public|...]
    set node-ip-only [enable|disable]
    set obj-id {var-string}
  config list
    Description: IP address list.
    edit <ip>
      next
    end
  config tagging
    Description: Config object tagging.
    edit <name>
      set category {string}
      set tags <name1>, <name2>, ...
```

```

        next
    end
    set allow-routing [enable|disable]
    set fabric-object [enable|disable]
next
end

```

config firewall address

Parameter	Description	Type	Size	Default
name	Address name.	string	Maximum length: 79	
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000
subnet	IP address and subnet mask of address.	ipv4-classnet-any	Not Specified	0.0.0.0 0.0.0.0
type	Type of address.	option	-	ipmask
	OptionDescription			
	ipmask	Standard IPv4 address with subnet mask.		
	iprange	Range of IPv4 addresses between two specified addresses (inclusive).		
	fqdn	Fully Qualified Domain Name address.		
	fqdn-group	Fully Qualified Domain Name Group address.		
	geography	IP addresses from a specified country.		
	wildcard	Standard IPv4 using a wildcard subnet mask.		
	dynamic	Dynamic address object.		
	interface-subnet	IP and subnet of interface.		
sub-type	Sub-type of address.	option	-	sdn
	OptionDescription			
	sdn	SDN address.		
	fsso	FSSO address.		
	ems-tag	FortiClient EMS tag.		
	fortinac-tag	FortiNAC tag.		

Parameter	Description	Type	Size	Default														
clearpass-spt	SPT (System Posture Token) value.	option	-	unknown														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>unknown</i></td><td>UNKNOWN.</td></tr><tr><td><i>healthy</i></td><td>HEALTHY.</td></tr><tr><td><i>quarantine</i></td><td>QUARANTINE.</td></tr><tr><td><i>checkup</i></td><td>CHECKUP.</td></tr><tr><td><i>transient</i></td><td>TRANSIENT.</td></tr><tr><td><i>infected</i></td><td>INFECTED.</td></tr></table>	Option	Description	<i>unknown</i>	UNKNOWN.	<i>healthy</i>	HEALTHY.	<i>quarantine</i>	QUARANTINE.	<i>checkup</i>	CHECKUP.	<i>transient</i>	TRANSIENT.	<i>infected</i>	INFECTED.			
	Option	Description																
	<i>unknown</i>	UNKNOWN.																
	<i>healthy</i>	HEALTHY.																
	<i>quarantine</i>	QUARANTINE.																
	<i>checkup</i>	CHECKUP.																
	<i>transient</i>	TRANSIENT.																
<i>infected</i>	INFECTED.																	
start-ip	First IP address (inclusive) in the range for the address.	ipv4-address-any	Not Specified	0.0.0.0														
end-ip	Final IP address (inclusive) in the range for the address.	ipv4-address-any	Not Specified	0.0.0.0														
fqdn	Fully Qualified Domain Name address.	string	Maximum length: 255															
country	IP addresses associated to a specific country.	string	Maximum length: 2															
wildcard-fqdn	Fully Qualified Domain Name with wildcard characters.	string	Maximum length: 255															
pattern-start	Starting number of pattern for fqdn-group.	integer	Minimum value: 0 Maximum value: 65535	0														
pattern-end	Ending number of pattern for fqdn-group.	integer	Minimum value: 0 Maximum value: 65535	0														
cache-ttl	Defines the minimal TTL of individual IP addresses in FQDN cache measured in seconds.	integer	Minimum value: 0 Maximum value: 86400	0														

Parameter	Description	Type	Size	Default						
wildcard	IP address and wildcard netmask.	ipv4-classnet-any	Not Specified	0.0.0.0 0.0.0.0						
sdn	SDN.	string	Maximum length: 35							
fsso-group <name>	FSSO group(s). FSSO group name.	string	Maximum length: 511							
interface	Name of interface whose IP address is to be used.	string	Maximum length: 35							
tenant	Tenant.	string	Maximum length: 35							
organization	Organization domain name (Syntax: organization/domain).	string	Maximum length: 35							
epg-name	Endpoint group name.	string	Maximum length: 255							
subnet-name	Subnet name.	string	Maximum length: 255							
sdn-tag	SDN Tag.	string	Maximum length: 15							
policy-group	Policy group name.	string	Maximum length: 15							
obj-tag	Tag of dynamic address object.	string	Maximum length: 255							
obj-type	Object type.	option	-	ip						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ip</i></td><td>IP address.</td></tr><tr><td><i>mac</i></td><td>MAC address</td></tr></table>				Option	Description	<i>ip</i>	IP address.	<i>mac</i>	MAC address
Option	Description									
<i>ip</i>	IP address.									
<i>mac</i>	MAC address									
tag-detection-level	Tag detection level of dynamic address object.	string	Maximum length: 15							
tag-type	Tag type of dynamic address object.	string	Maximum length: 63							
comment	Comment.	var-string	Maximum length: 255							
associated-interface	Network interface associated with address.	string	Maximum length: 35							

Parameter	Description	Type	Size	Default								
color	Color of icon on the GUI.	integer	Minimum value: 0 Maximum value: 32	0								
filter	Match criteria filter.	var-string	Maximum length: 2047									
sdn-addr-type	Type of addresses to collect.	option	-	private								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>private</i></td><td>Collect private addresses only.</td></tr><tr><td><i>public</i></td><td>Collect public addresses only.</td></tr><tr><td><i>all</i></td><td>Collect both public and private addresses.</td></tr></table>	Option	Description	<i>private</i>	Collect private addresses only.	<i>public</i>	Collect public addresses only.	<i>all</i>	Collect both public and private addresses.			
Option	Description											
<i>private</i>	Collect private addresses only.											
<i>public</i>	Collect public addresses only.											
<i>all</i>	Collect both public and private addresses.											
node-ip-only	Enable/disable collection of node addresses only in Kubernetes.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable collection of node addresses only in Kubernetes.</td></tr><tr><td><i>disable</i></td><td>Disable collection of node addresses only in Kubernetes.</td></tr></table>	Option	Description	<i>enable</i>	Enable collection of node addresses only in Kubernetes.	<i>disable</i>	Disable collection of node addresses only in Kubernetes.					
Option	Description											
<i>enable</i>	Enable collection of node addresses only in Kubernetes.											
<i>disable</i>	Disable collection of node addresses only in Kubernetes.											
obj-id	Object ID for NSX.	var-string	Maximum length: 255									
allow-routing	Enable/disable use of this address in the static route configuration.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable use of this address in the static route configuration.</td></tr><tr><td><i>disable</i></td><td>Disable use of this address in the static route configuration.</td></tr></table>	Option	Description	<i>enable</i>	Enable use of this address in the static route configuration.	<i>disable</i>	Disable use of this address in the static route configuration.					
Option	Description											
<i>enable</i>	Enable use of this address in the static route configuration.											
<i>disable</i>	Disable use of this address in the static route configuration.											
fabric-object	Security Fabric global object setting.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Object is set as a security fabric-wide global object.</td></tr><tr><td><i>disable</i></td><td>Object is local to this security fabric member.</td></tr></table>	Option	Description	<i>enable</i>	Object is set as a security fabric-wide global object.	<i>disable</i>	Object is local to this security fabric member.					
Option	Description											
<i>enable</i>	Object is set as a security fabric-wide global object.											
<i>disable</i>	Object is local to this security fabric member.											

config list

Parameter	Description	Type	Size	Default
ip	IP.	string	Maximum length: 35	

config tagging

Parameter	Description	Type	Size	Default
name	Tagging entry name.	string	Maximum length: 63	
category	Tag category.	string	Maximum length: 63	
tags <name>	Tags. Tag name.	string	Maximum length: 79	

config firewall address6

Configure IPv6 firewall addresses.

```
config firewall address6
  Description: Configure IPv6 firewall addresses.
  edit <name>
    set uuid {uuid}
    set type [ipprefix|iprange|...]
    set sdn {string}
    set ip6 {ipv6-network}
    set start-ip {ipv6-address}
    set end-ip {ipv6-address}
    set fqdn {string}
    set country {string}
    set cache-ttl {integer}
    set color {integer}
    set obj-id {var-string}
    config list
      Description: IP address list.
      edit <ip>
        next
      end
    config tagging
      Description: Config object tagging.
      edit <name>
        set category {string}
        set tags <name1>, <name2>, ...
      next
    end
```

```

set comment {var-string}
set template {string}
config subnet-segment
  Description: IPv6 subnet segments.
  edit <name>
    set type [any|specific]
    set value {string}
  next
end
set host-type [any|specific]
set host {ipv6-address}
set tenant {string}
set epg-name {string}
set sdn-tag {string}
set fabric-object [enable|disable]
next
end

```

config firewall address6

Parameter	Description	Type	Size	Default														
name	Address name.	string	Maximum length: 79															
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000														
type	Type of IPv6 address object (default = ipprefix).	option	-	ipprefix														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ipprefix</i></td><td>Uses the IP prefix to define a range of IPv6 addresses.</td></tr><tr><td><i>iprange</i></td><td>Range of IPv6 addresses between two specified addresses (inclusive).</td></tr><tr><td><i>fqdn</i></td><td>Fully qualified domain name.</td></tr><tr><td><i>geography</i></td><td>IPv6 addresses from a specified country.</td></tr><tr><td><i>dynamic</i></td><td>Dynamic address object for SDN.</td></tr><tr><td><i>template</i></td><td>Template.</td></tr></table>				Option	Description	<i>ipprefix</i>	Uses the IP prefix to define a range of IPv6 addresses.	<i>iprange</i>	Range of IPv6 addresses between two specified addresses (inclusive).	<i>fqdn</i>	Fully qualified domain name.	<i>geography</i>	IPv6 addresses from a specified country.	<i>dynamic</i>	Dynamic address object for SDN.	<i>template</i>	Template.
Option	Description																	
<i>ipprefix</i>	Uses the IP prefix to define a range of IPv6 addresses.																	
<i>iprange</i>	Range of IPv6 addresses between two specified addresses (inclusive).																	
<i>fqdn</i>	Fully qualified domain name.																	
<i>geography</i>	IPv6 addresses from a specified country.																	
<i>dynamic</i>	Dynamic address object for SDN.																	
<i>template</i>	Template.																	
sdn	SDN.	string	Maximum length: 35															

Parameter	Description	Type	Size	Default						
ip6	IPv6 address prefix (format: xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx/xx).	ipv6-network	Not Specified	::/0						
start-ip	First IP address (inclusive) in the range for the address (format: xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx).	ipv6-address	Not Specified	::						
end-ip	Final IP address (inclusive) in the range for the address (format: xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx).	ipv6-address	Not Specified	::						
fqdn	Fully qualified domain name.	string	Maximum length: 255							
country	IPv6 addresses associated to a specific country.	string	Maximum length: 2							
cache-ttl	Minimal TTL of individual IPv6 addresses in FQDN cache.	integer	Minimum value: 0 Maximum value: 86400	0						
color	Integer value to determine the color of the icon in the GUI (range 1 to 32, default = 0, which sets the value to 1).	integer	Minimum value: 0 Maximum value: 32	0						
obj-id	Object ID for NSX.	var-string	Maximum length: 255							
comment	Comment.	var-string	Maximum length: 255							
template	IPv6 address template.	string	Maximum length: 63							
host-type	Host type.	option	-	any						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>any</td><td>Wildcard.</td></tr><tr><td>specific</td><td>Specific host address.</td></tr></table>				Option	Description	any	Wildcard.	specific	Specific host address.
	Option	Description								
	any	Wildcard.								
specific	Specific host address.									
host	Host Address.	ipv6-address	Not Specified	::						

Parameter	Description	Type	Size	Default						
tenant	Tenant.	string	Maximum length: 35							
epg-name	Endpoint group name.	string	Maximum length: 255							
sdn-tag	SDN Tag.	string	Maximum length: 15							
fabric-object	Security Fabric global object setting.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Object is set as a security fabric-wide global object.</td></tr><tr><td><i>disable</i></td><td>Object is local to this security fabric member.</td></tr></table>				Option	Description	<i>enable</i>	Object is set as a security fabric-wide global object.	<i>disable</i>	Object is local to this security fabric member.
Option	Description									
<i>enable</i>	Object is set as a security fabric-wide global object.									
<i>disable</i>	Object is local to this security fabric member.									

config list

Parameter	Description	Type	Size	Default
ip	IP.	string	Maximum length: 89	

config tagging

Parameter	Description	Type	Size	Default
name	Tagging entry name.	string	Maximum length: 63	
category	Tag category.	string	Maximum length: 63	
tags <name>	Tags. Tag name.	string	Maximum length: 79	

config subnet-segment

Parameter	Description	Type	Size	Default
name	Name.	string	Maximum length: 63	
type	Subnet segment type.	option	-	any

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>any</i>	Wildcard.		
	<i>specific</i>	Specific subnet segment address.		
value	Subnet segment value.	string	Maximum length: 35	

config firewall address6-template

Configure IPv6 address templates.

```

config firewall address6-template
  Description: Configure IPv6 address templates.
  edit <name>
    set ip6 {ipv6-network}
    set subnet-segment-count {integer}
    config subnet-segment
      Description: IPv6 subnet segments.
      edit <id>
        set name {string}
        set bits {integer}
        set exclusive [enable|disable]
        config values
          Description: Subnet segment values.
          edit <name>
            set value {string}
          next
        end
      next
    end
  set fabric-object [enable|disable]
next
end

```

config firewall address6-template

Parameter	Description	Type	Size	Default
name	IPv6 address template name.	string	Maximum length: 63	
ip6	IPv6 address prefix.	ipv6-network	Not Specified	::/0

Parameter	Description	Type	Size	Default						
subnet-segment-count	Number of IPv6 subnet segments.	integer	Minimum value: 1 Maximum value: 6	0						
fabric-object	Security Fabric global object setting.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Object is set as a security fabric-wide global object.</td></tr><tr><td><i>disable</i></td><td>Object is local to this security fabric member.</td></tr></table>				Option	Description	<i>enable</i>	Object is set as a security fabric-wide global object.	<i>disable</i>	Object is local to this security fabric member.
Option	Description									
<i>enable</i>	Object is set as a security fabric-wide global object.									
<i>disable</i>	Object is local to this security fabric member.									

config subnet-segment

Parameter	Description	Type	Size	Default						
id	Subnet segment ID.	integer	Minimum value: 0 Maximum value: 4294967295	0						
name	Subnet segment name.	string	Maximum length: 63							
bits	Number of bits.	integer	Minimum value: 1 Maximum value: 16	0						
exclusive	Enable/disable exclusive value.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable exclusive value.</td></tr><tr><td><i>disable</i></td><td>Disable exclusive value.</td></tr></table>				Option	Description	<i>enable</i>	Enable exclusive value.	<i>disable</i>	Disable exclusive value.
Option	Description									
<i>enable</i>	Enable exclusive value.									
<i>disable</i>	Disable exclusive value.									

config values

Parameter	Description	Type	Size	Default
name	Subnet segment value name.	string	Maximum length: 63	
value	Subnet segment value.	string	Maximum length: 35	

config firewall addrgrp

Configure IPv4 address groups.

```
config firewall addrgrp
  Description: Configure IPv4 address groups.
  edit <name>
    set type [default|folder]
    set category [default|ztna-ems-tag]
    set uuid {uuid}
    set member <name1>, <name2>, ...
    set comment {var-string}
    set exclude [enable|disable]
    set exclude-member <name1>, <name2>, ...
    set color {integer}
    config tagging
      Description: Config object tagging.
      edit <name>
        set category {string}
        set tags <name1>, <name2>, ...
      next
    end
    set allow-routing [enable|disable]
    set fabric-object [enable|disable]
  next
end
```

config firewall addrgrp

Parameter	Description	Type	Size	Default
name	Address group name.	string	Maximum length: 79	
type	Address group type.	option	-	default
	Option	Description		
	<i>default</i>	Default address group type (address may belong to multiple groups).		
	<i>folder</i>	Address folder group (members may not belong to any other group).		
category	Address group category.	option	-	default

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>default</i>	Default address group category (cannot be used as ztna-ems-tag in policy).		
	<i>ztna-ems-tag</i>	Members must be ztna-ems-tag group or ems-tag address, can be used as ztna-ems-tag in policy.		
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000
member <name>	Address objects contained within the group. Address name.	string	Maximum length: 79	
comment	Comment.	var-string	Maximum length: 255	
exclude	Enable/disable address exclusion.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable address exclusion.		
	<i>disable</i>	Disable address exclusion.		
exclude-member <name>	Address exclusion member. Address name.	string	Maximum length: 79	
color	Color of icon on the GUI.	integer	Minimum value: 0 Maximum value: 32	0
allow-routing	Enable/disable use of this group in the static route configuration.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable use of this group in the static route configuration.		
	<i>disable</i>	Disable use of this group in the static route configuration.		
fabric-object	Security Fabric global object setting.	option	-	disable
	Option	Description		
	<i>enable</i>	Object is set as a security fabric-wide global object.		
	<i>disable</i>	Object is local to this security fabric member.		

config tagging

Parameter	Description	Type	Size	Default
name	Tagging entry name.	string	Maximum length: 63	
category	Tag category.	string	Maximum length: 63	
tags <name>	Tags. Tag name.	string	Maximum length: 79	

config firewall addrgrp6

Configure IPv6 address groups.

```
config firewall addrgrp6
  Description: Configure IPv6 address groups.
  edit <name>
    set uuid {uuid}
    set color {integer}
    set comment {var-string}
    set member <name1>, <name2>, ...
    config tagging
      Description: Config object tagging.
      edit <name>
        set category {string}
        set tags <name1>, <name2>, ...
      next
    end
    set fabric-object [enable|disable]
  next
end
```

config firewall addrgrp6

Parameter	Description	Type	Size	Default
name	IPv6 address group name.	string	Maximum length: 79	
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000

Parameter	Description	Type	Size	Default						
color	Integer value to determine the color of the icon in the GUI (1 - 32, default = 0, which sets the value to 1).	integer	Minimum value: 0 Maximum value: 32	0						
comment	Comment.	var-string	Maximum length: 255							
member <name>	Address objects contained within the group. Address6/addrgrp6 name.	string	Maximum length: 79							
fabric-object	Security Fabric global object setting.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Object is set as a security fabric-wide global object.</td></tr><tr><td><i>disable</i></td><td>Object is local to this security fabric member.</td></tr></table>				Option	Description	<i>enable</i>	Object is set as a security fabric-wide global object.	<i>disable</i>	Object is local to this security fabric member.
Option	Description									
<i>enable</i>	Object is set as a security fabric-wide global object.									
<i>disable</i>	Object is local to this security fabric member.									

config tagging

Parameter	Description	Type	Size	Default
name	Tagging entry name.	string	Maximum length: 63	
category	Tag category.	string	Maximum length: 63	
tags <name>	Tags. Tag name.	string	Maximum length: 79	

config firewall auth-portal

Configure firewall authentication portals.

```

config firewall auth-portal
  Description: Configure firewall authentication portals.
  set groups <name1>, <name2>, ...
  set portal-addr {string}
  set portal-addr6 {string}
  set identity-based-route {string}
  set proxy-auth [enable|disable]
end

```

config firewall auth-portal

Parameter	Description	Type	Size	Default
groups <name>	Firewall user groups permitted to authenticate through this portal. Separate group names with spaces. Group name.	string	Maximum length: 79	
portal-addr	Address (or FQDN) of the authentication portal.	string	Maximum length: 63	
portal-addr6	IPv6 address (or FQDN) of authentication portal.	string	Maximum length: 63	
identity-based-route	Name of the identity-based route that applies to this portal.	string	Maximum length: 35	
proxy-auth	Enable/disable authentication by proxy daemon (default = disable).	option	-	disable

Option	Description
<i>enable</i>	Users are authenticated by proxy daemon.
<i>disable</i>	Users are not authenticated by proxy daemon.

config firewall central-snat-map

Configure central SNAT policies.

```
config firewall central-snat-map
  Description: Configure central SNAT policies.
  edit <policyid>
    set status [enable|disable]
    set action [bypass|masquerade|...]
    set ipv6 [enable|disable]
    set srcintf {string}
    set dstintf {string}
    set src-addr <name1>, <name2>, ...
    set src-addr6 <name1>, <name2>, ...
    set dst-addr <name1>, <name2>, ...
    set dst-addr6 <name1>, <name2>, ...
    set nat-ippool <name1>, <name2>, ...
    set nat-ippool6 <name1>, <name2>, ...
  next
end
```

config firewall central-snat-map

Parameter	Description	Type	Size	Default								
policyid	Policy ID.	integer	Minimum value: 0 Maximum value: 4294967295	0								
status	Enable/disable the active status of this policy.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable this policy.</td></tr><tr><td><i>disable</i></td><td>Disable this policy.</td></tr></table>	Option	Description	<i>enable</i>	Enable this policy.	<i>disable</i>	Disable this policy.					
	Option	Description										
	<i>enable</i>	Enable this policy.										
<i>disable</i>	Disable this policy.											
action	central SNAT action.	option	-	masquerade								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>bypass</i></td><td>Bypass and do not perform NAT.</td></tr><tr><td><i>masquerade</i></td><td>NAT using the primary IP of destination interface.</td></tr><tr><td><i>ippool</i></td><td>NAT using ip pool.</td></tr></table>	Option	Description	<i>bypass</i>	Bypass and do not perform NAT.	<i>masquerade</i>	NAT using the primary IP of destination interface.	<i>ippool</i>	NAT using ip pool.			
	Option	Description										
	<i>bypass</i>	Bypass and do not perform NAT.										
	<i>masquerade</i>	NAT using the primary IP of destination interface.										
<i>ippool</i>	NAT using ip pool.											
ipv6	Enable/disable IPv6.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable ipv6.</td></tr><tr><td><i>disable</i></td><td>Disable ipv6.</td></tr></table>	Option	Description	<i>enable</i>	Enable ipv6.	<i>disable</i>	Disable ipv6.					
	Option	Description										
	<i>enable</i>	Enable ipv6.										
<i>disable</i>	Disable ipv6.											
srcintf	Source interface name from available interfaces.	string	Maximum length: 35									
dstintf	Destination interface name from available interfaces.	string	Maximum length: 35									
src-addr <name>	IPv4 Original address. Address name.	string	Maximum length: 79									
src-addr6 <name>	IPv6 Original address. Address name.	string	Maximum length: 79									
dst-addr <name>	IPv4 Destination address. Address name.	string	Maximum length: 79									
dst-addr6 <name>	IPv6 Destination address. Address name.	string	Maximum length: 79									

Parameter	Description	Type	Size	Default
nat-ippool <name>	Name of the IP pools to be used to translate addresses from available IP Pools. IP pool name.	string	Maximum length: 79	
nat-ippool6 <name>	IPv6 pools to be used for source NAT. IP pool name.	string	Maximum length: 79	

config firewall city

Define city table.

```
config firewall city
    Description: Define city table.
    edit <id>
        set name {string}
    next
end
```

config firewall city

Parameter	Description	Type	Size	Default
id	City ID.	integer	Minimum value: 0 Maximum value: 65535	0
name	City name.	string	Maximum length: 63	

config firewall country

Define country table.

```
config firewall country
    Description: Define country table.
    edit <id>
        set name {string}
        set region <id1>, <id2>, ...
    next
end
```

config firewall country

Parameter	Description	Type	Size	Default
id	Country ID.	integer	Minimum value: 0 Maximum value: 65535	0
name	Country name.	string	Maximum length: 63	
region <id>	Region ID list. Region ID.	integer	Minimum value: 0 Maximum value: 65535	

config firewall decrypted-traffic-mirror

Configure decrypted traffic mirror.

```
config firewall decrypted-traffic-mirror
  Description: Configure decrypted traffic mirror.
  edit <name>
    set dstmac {mac-address}
    set traffic-type {option1}, {option2}, ...
    set traffic-source [client|server|...]
    set interface <name1>, <name2>, ...
  next
end
```

config firewall decrypted-traffic-mirror

Parameter	Description	Type	Size	Default
name	Name.	string	Maximum length: 35	
dstmac	Set destination MAC address for mirrored traffic.	mac-address	Not Specified	ff:ff:ff:ff:ff:ff
traffic-type	Types of decrypted traffic to be mirrored.	option	-	ssl

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>ssl</i>	Mirror decrypted SSL traffic.		
	<i>ssh</i>	Mirror decrypted SSH traffic.		
traffic-source	Source of decrypted traffic to be mirrored.	option	-	client
	Option	Description		
	<i>client</i>	Mirror client side decrypted traffic.		
	<i>server</i>	Mirror server side decrypted traffic.		
	<i>both</i>	Mirror both client and server side decrypted traffic.		
interface <name>	Decrypted traffic mirror interface. Decrypted traffic mirror interface.	string	Maximum length: 79	

config firewall global

Global firewall settings.

```
config firewall global
    Description: Global firewall settings.
    set banned-ip-persistence [disabled|permanent-only|...]
end
```

config firewall global

Parameter	Description	Type	Size	Default
banned-ip-persistence	Persistence of banned IPs across power cycling.	option	-	disabled
	Option	Description		
	<i>disabled</i>	No entries are kept across power cycling.		
	<i>permanent-only</i>	Only permanent IP bans are kept across power cycling.		
	<i>all</i>	All IP bans are kept across power cycling.		

config firewall identity-based-route

Configure identity based routing.

```
config firewall identity-based-route
  Description: Configure identity based routing.
  edit <name>
    set comments {string}
    config rule
      Description: Rule.
      edit <id>
        set gateway {ipv4-address}
        set device {string}
        set groups <name1>, <name2>, ...
      next
    end
  next
end
```

config firewall identity-based-route

Parameter	Description	Type	Size	Default
name	Name.	string	Maximum length: 35	
comments	Comments.	string	Maximum length: 127	

config rule

Parameter	Description	Type	Size	Default
id	Rule ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
gateway	IPv4 address of the gateway (Format: xxx.xxx.xxx.xxx , Default: 0.0.0.0).	ipv4-address	Not Specified	0.0.0.0
device	Outgoing interface for the rule.	string	Maximum length: 35	
groups <name>	Select one or more group(s) from available groups that are allowed to use this route. Separate group names with a space. Group name.	string	Maximum length: 79	

config firewall internet-service

Show Internet Service application.

```
config firewall internet-service
  Description: Show Internet Service application.
  edit <id>
    set name {string}
    set icon-id {integer}
    set direction [src|dst|...]
    set database [isdb|irdb]
    set ip-range-number {integer}
    set extra-ip-range-number {integer}
    set ip-number {integer}
    set ip6-range-number {integer}
    set extra-ip6-range-number {integer}
    set singularity {integer}
    set obsolete {integer}
  next
end
```

config firewall internet-service

Parameter	Description	Type	Size	Default
id	Internet Service ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Internet Service name.	string	Maximum length: 63	
icon-id	Icon ID of Internet Service.	integer	Minimum value: 0 Maximum value: 4294967295	0
direction	How this service may be used in a firewall policy (source, destination or both).	option	-	both
		Option	Description	
		<i>src</i>	As source in the firewall policy.	
		<i>dst</i>	As destination in the firewall policy.	
		<i>both</i>	Both directions in the firewall policy.	

Parameter	Description	Type	Size	Default						
database	Database name this Internet Service belongs to.	option	-	isdb						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>isdb</td><td>Internet Service Database.</td></tr><tr><td>irdb</td><td>Internet RRR Database.</td></tr></table>				Option	Description	isdb	Internet Service Database.	irdb	Internet RRR Database.
	Option	Description								
	isdb	Internet Service Database.								
irdb	Internet RRR Database.									
ip-range-number	Number of IPv4 ranges.	integer	Minimum value: 0 Maximum value: 4294967295	0						
extra-ip-range-number	Extra number of IPv4 ranges.	integer	Minimum value: 0 Maximum value: 4294967295	0						
ip-number	Total number of IPv4 addresses.	integer	Minimum value: 0 Maximum value: 4294967295	0						
ip6-range-number	Number of IPv6 ranges.	integer	Minimum value: 0 Maximum value: 4294967295	0						
extra-ip6-range-number	Extra number of IPv6 ranges.	integer	Minimum value: 0 Maximum value: 4294967295	0						
singularity	Singular level of the Internet Service.	integer	Minimum value: 0 Maximum value: 65535	0						
obsolete	Indicates whether the Internet Service can be used.	integer	Minimum value: 0 Maximum value: 255	0						

config firewall internet-service-addition

Configure Internet Services Addition.

```
config firewall internet-service-addition
  Description: Configure Internet Services Addition.
  edit <id>
    set comment {var-string}
    config entry
      Description: Entries added to the Internet Service addition database.
      edit <id>
        set addr-mode [ipv4|ipv6]
        set protocol {integer}
        config port-range
          Description: Port ranges in the custom entry.
          edit <id>
            set start-port {integer}
            set end-port {integer}
          next
        end
      next
    end
  next
end
```

config firewall internet-service-addition

Parameter	Description	Type	Size	Default
id	Internet Service ID in the Internet Service database.	integer	Minimum value: 0 Maximum value: 4294967295	0
comment	Comment.	var-string	Maximum length: 255	

config entry

Parameter	Description	Type	Size	Default
id	Entry ID(1-255).	integer	Minimum value: 0 Maximum value: 255	0
addr-mode	Address mode (IPv4 or IPv6).	option	-	ipv4

Parameter	Description	Type	Size	Default							
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ipv4</i></td><td>IPv4 mode.</td></tr><tr><td><i>ipv6</i></td><td>IPv6 mode.</td></tr></table>		Option	Description	<i>ipv4</i>	IPv4 mode.	<i>ipv6</i>	IPv6 mode.			
	Option	Description									
	<i>ipv4</i>	IPv4 mode.									
	<i>ipv6</i>	IPv6 mode.									
protocol	Integer value for the protocol type as defined by IANA (only TCP is supported).	integer	Minimum value: 6 Maximum value: 6	6							

config port-range

Parameter	Description	Type	Size	Default
id	Custom entry port range ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
start-port	Integer value for starting TCP/UDP/SCTP destination port in range (0 to 65535).	integer	Minimum value: 0 Maximum value: 65535	1
end-port	Integer value for ending TCP/UDP/SCTP destination port in range (0 to 65535).	integer	Minimum value: 0 Maximum value: 65535	65535

config firewall internet-service-append

Configure additional port mappings for Internet Services.

```

config firewall internet-service-append
    Description: Configure additional port mappings for Internet Services.
    set addr-mode [ipv4|ipv6|...]
    set match-port {integer}
    set append-port {integer}
end

```

config firewall internet-service-append

Parameter	Description	Type	Size	Default								
addr-mode	Address mode (IPv4 or IPv6).	option	-	ipv4								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>ipv4</td><td>IPv4 mode.</td></tr><tr><td>ipv6</td><td>IPv6 mode.</td></tr><tr><td>both</td><td>Both IPv4 and IPv6 mode.</td></tr></table>				Option	Description	ipv4	IPv4 mode.	ipv6	IPv6 mode.	both	Both IPv4 and IPv6 mode.
	Option	Description										
	ipv4	IPv4 mode.										
	ipv6	IPv6 mode.										
both	Both IPv4 and IPv6 mode.											
match-port	Matching TCP/UDP/SCTP destination port (0 to 65535, 0 means any port).	integer	Minimum value: 0 Maximum value: 65535	0								
append-port	Appending TCP/UDP/SCTP destination port (1 to 65535).	integer	Minimum value: 0 Maximum value: 65535	0								

config firewall internet-service-botnet

Show Internet Service botnet.

```
config firewall internet-service-botnet
  Description: Show Internet Service botnet.
  edit <id>
    set name {string}
  next
end
```

config firewall internet-service-botnet

Parameter	Description	Type	Size	Default
id	Internet Service Botnet ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Internet Service Botnet name.	string	Maximum length: 63	

config firewall internet-service-custom

Configure custom Internet Services.

```
config firewall internet-service-custom
  Description: Configure custom Internet Services.
  edit <name>
    set reputation {integer}
    set comment {var-string}
    config entry
      Description: Entries added to the Internet Service database and custom database.
      edit <id>
        set addr-mode [ipv4|ipv6]
        set protocol {integer}
        config port-range
          Description: Port ranges in the custom entry.
          edit <id>
            set start-port {integer}
            set end-port {integer}
          next
        end
        set dst <name1>, <name2>, ...
        set dst6 <name1>, <name2>, ...
      next
    end
  next
end
```

config firewall internet-service-custom

Parameter	Description	Type	Size	Default
name	Internet Service name.	string	Maximum length: 63	
reputation	Reputation level of the custom Internet Service.	integer	Minimum value: 0 Maximum value: 4294967295	3
comment	Comment.	var-string	Maximum length: 255	

config entry

Parameter	Description	Type	Size	Default
id	Entry ID(1-255).	integer	Minimum value: 0 Maximum value: 255	0
addr-mode	Address mode (IPv4 or IPv6).	option	-	ipv4
	Option	Description		
	ipv4	IPv4 mode.		
	ipv6	IPv6 mode.		
protocol	Integer value for the protocol type as defined by IANA (only TCP is supported).	integer	Minimum value: 6 Maximum value: 6	6
dst <name>	Destination address or address group name. Select the destination address or address group object from available options.	string	Maximum length: 79	
dst6 <name>	Destination address6 or address6 group name. Select the destination address6 or address group object from available options.	string	Maximum length: 79	

config port-range

Parameter	Description	Type	Size	Default
id	Custom entry port range ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
start-port	Integer value for starting TCP/UDP/SCTP destination port in range (0 to 65535).	integer	Minimum value: 0 Maximum value: 65535	1
end-port	Integer value for ending TCP/UDP/SCTP destination port in range (0 to 65535).	integer	Minimum value: 0 Maximum value: 65535	65535

config firewall internet-service-custom-group

Configure custom Internet Service group.

```
config firewall internet-service-custom-group
  Description: Configure custom Internet Service group.
  edit <name>
    set comment {var-string}
    set member <name1>, <name2>, ...
  next
end
```

config firewall internet-service-custom-group

Parameter	Description	Type	Size	Default
name	Custom Internet Service group name.	string	Maximum length: 63	
comment	Comment.	var-string	Maximum length: 255	
member <name>	Custom Internet Service group members. Group member name.	string	Maximum length: 79	

config firewall internet-service-definition

Configure Internet Service definition.

```
config firewall internet-service-definition
  Description: Configure Internet Service definition.
  edit <id>
    config entry
      Description: Protocol and port information in an Internet Service entry.
      edit <seq-num>
        set category-id {integer}
        set name {string}
        set protocol {integer}
        config port-range
          Description: Port ranges in the definition entry.
          edit <id>
            set start-port {integer}
            set end-port {integer}
          next
        end
      next
    end
  next
end
```

```
next
end
```

config firewall internet-service-definition

Parameter	Description	Type	Size	Default
id	Internet Service application list ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

config entry

Parameter	Description	Type	Size	Default
seq-num	Entry sequence number.	integer	Minimum value: 0 Maximum value: 4294967295	0
category-id	Internet Service category ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Internet Service name.	string	Maximum length: 63	
protocol	Integer value for the protocol type as defined by IANA (0 - 255).	integer	Minimum value: 0 Maximum value: 255	0

config port-range

Parameter	Description	Type	Size	Default
id	Custom entry port range ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

Parameter	Description	Type	Size	Default
start-port	Starting TCP/UDP/SCTP destination port (1 to 65535).	integer	Minimum value: 1 Maximum value: 65535	1
end-port	Ending TCP/UDP/SCTP destination port (1 to 65535).	integer	Minimum value: 1 Maximum value: 65535	65535

config firewall internet-service-extension

Configure Internet Services Extension.

```

config firewall internet-service-extension
    Description: Configure Internet Services Extension.
    edit <id>
        set comment {var-string}
        config entry
            Description: Entries added to the Internet Service extension database.
            edit <id>
                set addr-mode [ipv4|ipv6]
                set protocol {integer}
                config port-range
                    Description: Port ranges in the custom entry.
                    edit <id>
                        set start-port {integer}
                        set end-port {integer}
                    next
                next
            end
            set dst <name1>, <name2>, ...
            set dst6 <name1>, <name2>, ...
        next
    end
    config disable-entry
        Description: Disable entries in the Internet Service database.
        edit <id>
            set addr-mode [ipv4|ipv6]
            set protocol {integer}
            config port-range
                Description: Port ranges in the disable entry.
                edit <id>
                    set start-port {integer}
                    set end-port {integer}
                next
            end
            config ip-range
                Description: IPv4 ranges in the disable entry.

```

```

        edit <id>
            set start-ip {ipv4-address-any}
            set end-ip {ipv4-address-any}
        next
    end
    config ip6-range
        Description: IPv6 ranges in the disable entry.
        edit <id>
            set start-ip6 {ipv6-address}
            set end-ip6 {ipv6-address}
        next
    end
next
end
next
end

```

config firewall internet-service-extension

Parameter	Description	Type	Size	Default
id	Internet Service ID in the Internet Service database.	integer	Minimum value: 0 Maximum value: 4294967295	0
comment	Comment.	var-string	Maximum length: 255	

config entry

Parameter	Description	Type	Size	Default						
id	Entry ID(1-255).	integer	Minimum value: 0 Maximum value: 255	0						
addr-mode	Address mode (IPv4 or IPv6).	option	-	ipv4						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>ipv4</td><td>IPv4 mode.</td></tr><tr><td>ipv6</td><td>IPv6 mode.</td></tr></table>				Option	Description	ipv4	IPv4 mode.	ipv6	IPv6 mode.
Option	Description									
ipv4	IPv4 mode.									
ipv6	IPv6 mode.									

Parameter	Description	Type	Size	Default
protocol	Integer value for the protocol type as defined by IANA (only TCP is supported).	integer	Minimum value: 6 Maximum value: 6	6
dst <name>	Destination address or address group name. Select the destination address or address group object from available options.	string	Maximum length: 79	
dst6 <name>	Destination address6 or address6 group name. Select the destination address6 or address group object from available options.	string	Maximum length: 79	

config port-range

Parameter	Description	Type	Size	Default
id	Custom entry port range ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
start-port	Integer value for starting TCP/UDP/SCTP destination port in range (0 to 65535).	integer	Minimum value: 0 Maximum value: 65535	1
end-port	Integer value for ending TCP/UDP/SCTP destination port in range (0 to 65535).	integer	Minimum value: 0 Maximum value: 65535	65535

config disable-entry

Parameter	Description	Type	Size	Default				
id	Disable entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0				
addr-mode	Address mode (IPv4 or IPv6).	option	-	ipv4				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>ipv4</td><td>IPv4 mode.</td></tr></table>				Option	Description	ipv4	IPv4 mode.
Option	Description							
ipv4	IPv4 mode.							

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>ipv6</i>	IPv6 mode.		
protocol	Integer value for the protocol type as defined by IANA (0 - 255).	integer	Minimum value: 0 Maximum value: 255	0

config port-range

Parameter	Description	Type	Size	Default
id	Custom entry port range ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
start-port	Starting TCP/UDP/SCTP destination port (0 to 65535).	integer	Minimum value: 0 Maximum value: 65535	1
end-port	Ending TCP/UDP/SCTP destination port (0 to 65535).	integer	Minimum value: 0 Maximum value: 65535	65535

config ip-range

Parameter	Description	Type	Size	Default
id	Disable entry range ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
start-ip	Start IPv4 address.	ipv4-address-any	Not Specified	0.0.0.0
end-ip	End IPv4 address.	ipv4-address-any	Not Specified	0.0.0.0

config ip6-range

Parameter	Description	Type	Size	Default
id	Disable entry range ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
start-ip6	Start IPv6 address.	ipv6-address	Not Specified	::
end-ip6	End IPv6 address.	ipv6-address	Not Specified	::

config firewall internet-service-group

Configure group of Internet Service.

```
config firewall internet-service-group
  Description: Configure group of Internet Service.
  edit <name>
    set comment {var-string}
    set direction [source|destination|...]
    set member <name1>, <name2>, ...
  next
end
```

config firewall internet-service-group

Parameter	Description	Type	Size	Default
name	Internet Service group name.	string	Maximum length: 63	
comment	Comment.	var-string	Maximum length: 255	
direction	How this service may be used (source, destination or both).	option	-	both
		Option	Description	
		<i>source</i>	As source when applied.	
		<i>destination</i>	As destination when applied.	
		<i>both</i>	Both directions when applied.	

Parameter	Description	Type	Size	Default
member <name>	Internet Service group member. Internet Service name.	string	Maximum length: 79	

config firewall internet-service-ipbl-reason

IP block list reason.

```
config firewall internet-service-ipbl-reason
  Description: IP block list reason.
  edit <id>
    set name {string}
  next
end
```

config firewall internet-service-ipbl-reason

Parameter	Description	Type	Size	Default
id	IP block list reason ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	IP block list reason name.	string	Maximum length: 63	

config firewall internet-service-ipbl-vendor

IP block list vendor.

```
config firewall internet-service-ipbl-vendor
  Description: IP block list vendor.
  edit <id>
    set name {string}
  next
end
```

config firewall internet-service-ipbl-vendor

Parameter	Description	Type	Size	Default
id	IP block list vendor ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	IP block list vendor name.	string	Maximum length: 63	

config firewall internet-service-list

Internet Service list.

```
config firewall internet-service-list
  Description: Internet Service list.
  edit <id>
    set name {string}
  next
end
```

config firewall internet-service-list

Parameter	Description	Type	Size	Default
id	Internet Service category ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Internet Service category name.	string	Maximum length: 63	

config firewall internet-service-name

Define internet service names.

```
config firewall internet-service-name
  Description: Define internet service names.
  edit <name>
    set type [default|location]
```

```

        set internet-service-id {integer}
        set country-id {integer}
        set region-id {integer}
        set city-id {integer}
    next
end

```

config firewall internet-service-name

Parameter	Description	Type	Size	Default
name	Internet Service name.	string	Maximum length: 63	
type	Internet Service name type.	option	-	default
	Option	Description		
	<i>default</i>	Automatically generated Internet Service.		
	<i>location</i>	Geography location based Internet Service.		
internet-service-id	Internet Service ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
country-id	Country or Area ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
region-id	Region ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
city-id	City ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

config firewall internet-service-owner

Internet Service owner.

```
config firewall internet-service-owner
  Description: Internet Service owner.
  edit <id>
    set name {string}
  next
end
```

config firewall internet-service-owner

Parameter	Description	Type	Size	Default
id	Internet Service owner ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Internet Service owner name.	string	Maximum length: 63	

config firewall internet-service-reputation

Show Internet Service reputation.

```
config firewall internet-service-reputation
  Description: Show Internet Service reputation.
  edit <id>
    set description {string}
  next
end
```

config firewall internet-service-reputation

Parameter	Description	Type	Size	Default
id	Internet Service Reputation ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
description	Description.	string	Maximum length: 127	

config firewall internet-service-sld

Internet Service Second Level Domain.

```
config firewall internet-service-sld
  Description: Internet Service Second Level Domain.
  edit <id>
    set name {string}
  next
end
```

config firewall internet-service-sld

Parameter	Description	Type	Size	Default
id	Second Level Domain ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Second Level Domain name.	string	Maximum length: 63	

config firewall internet-service-subapp

Show Internet Service sub app ID.

```
config firewall internet-service-subapp
  Description: Show Internet Service sub app ID.
  edit <id>
    set sub-app <id1>, <id2>, ...
  next
end
```

config firewall internet-service-subapp

Parameter	Description	Type	Size	Default
id	Internet Service main ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

Parameter	Description	Type	Size	Default
sub-app <id>	Subapp number list. Subapp ID.	integer	Minimum value: 0 Maximum value: 4294967295	

config firewall ippool

Configure IPv4 IP pools.

```
config firewall ippool
  Description: Configure IPv4 IP pools.
  edit <name>
    set startip {ipv4-address-any}
    set endip {ipv4-address-any}
    set comments {var-string}
  next
end
```

config firewall ippool

Parameter	Description	Type	Size	Default
name	IP pool name.	string	Maximum length: 79	
startip	First IPv4 address (inclusive) in the range for the address pool (format xxx.xxx.xxx.xxx, Default: 0.0.0.0).	ipv4-address-any	Not Specified	0.0.0.0
endip	Final IPv4 address (inclusive) in the range for the address pool (format xxx.xxx.xxx.xxx, Default: 0.0.0.0).	ipv4-address-any	Not Specified	0.0.0.0
comments	Comment.	var-string	Maximum length: 255	

config firewall ippool6

Configure IPv6 IP pools.

```
config firewall ippool6
  Description: Configure IPv6 IP pools.
  edit <name>
    set startip {ipv6-address}
```

```

    set endip {ipv6-address}
    set comments {var-string}
    set nat46 [disable|enable]
    set add-nat46-route [disable|enable]
next
end

```

config firewall ippool6

Parameter	Description	Type	Size	Default						
name	IPv6 IP pool name.	string	Maximum length: 79							
startip	First IPv6 address (inclusive) in the range for the address pool (format = xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx, default = ::).	ipv6-address	Not Specified	::						
endip	Final IPv6 address (inclusive) in the range for the address pool (format = xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx, default = ::).	ipv6-address	Not Specified	::						
comments	Comment.	var-string	Maximum length: 255							
nat46	Enable/disable NAT46.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable NAT46.</td></tr><tr><td>enable</td><td>Enable NAT46.</td></tr></table>				Option	Description	disable	Disable NAT46.	enable	Enable NAT46.
Option	Description									
disable	Disable NAT46.									
enable	Enable NAT46.									
add-nat46-route	Enable/disable adding NAT46 route.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable adding NAT46 route.</td></tr><tr><td>enable</td><td>Enable adding NAT46 route.</td></tr></table>				Option	Description	disable	Disable adding NAT46 route.	enable	Enable adding NAT46 route.
Option	Description									
disable	Disable adding NAT46 route.									
enable	Enable adding NAT46 route.									

config firewall network-service-dynamic

Configure Dynamic Network Services.

```

config firewall network-service-dynamic
    Description: Configure Dynamic Network Services.

```

```

edit <name>
    set sdn {string}
    set comment {var-string}
    set filter {var-string}
next
end

```

config firewall network-service-dynamic

Parameter	Description	Type	Size	Default
name	Dynamic Network Service name.	string	Maximum length: 63	
sdn	SDN connector name.	string	Maximum length: 35	
comment	Comment.	var-string	Maximum length: 255	
filter	Match criteria filter.	var-string	Maximum length: 2047	

config firewall policy

Configure firewall policies.

```

config firewall policy
    Description: Configure firewall policies.
    edit <policyid>
        set type [explicit-web|explicit-web-connect|...]
        set status [enable|disable]
        set name {string}
        set uuid {uuid}
        set force-proxy [enable|disable]
        set implicit-proxy-detection [enable|disable]
        set dynamic-bypass [enable|disable]
        set srcintf <name1>, <name2>, ...
        set dstintf <name1>, <name2>, ...
        set ztna-device-ownership [enable|disable]
        set srcaddr <name1>, <name2>, ...
        set dstaddr <name1>, <name2>, ...
        set srcaddr6 <name1>, <name2>, ...
        set dstaddr6 <name1>, <name2>, ...
        set action [accept|deny|...]
        set schedule {string}
        set policy-expiry [enable|disable]
        set policy-expiry-date {datetime}
    end
end

```



```

set service <name1>, <name2>, ...
set explicit-web-proxy {string}
set transparent [enable|disable]
set access-proxy <name1>, <name2>, ...
set ztna-ems-tag <name1>, <name2>, ...
set ztna-tags-match-logic [or|and]
set device-ownership [enable|disable]
set pass-through [enable|disable]
set url-category <id1>, <id2>, ...
set url-risk <name1>, <name2>, ...
set internet-service [enable|disable]
set internet-service-name <name1>, <name2>, ...
set internet-service-group <name1>, <name2>, ...
set internet-service-custom <name1>, <name2>, ...
set internet-service6 [enable|disable]
set internet-service6-name <name1>, <name2>, ...
set internet-service6-group <name1>, <name2>, ...
set internet-service6-custom <name1>, <name2>, ...
set internet-service6-custom-group <name1>, <name2>, ...
set internet-service-custom-group <name1>, <name2>, ...
set utm-status [enable|disable]
set ztna-policy-redirect [enable|disable]
set webproxy-profile {string}
set logtraffic [all|utm|...]
set logtraffic-start [enable|disable]
set log-http-transaction [disable|enable]
set extended-log [enable|disable]
set wanopt [enable|disable]
set wanopt-detection [active|passive|...]
set wanopt-passive-opt [default|transparent|...]
set wanopt-profile {string}
set wanopt-peer {string}
set webcache [enable|disable]
set webcache-https [disable|enable]
set reverse-cache [disable|enable]
set http-tunnel-auth [enable|disable]
set ssh-policy-check [enable|disable]
set webproxy-forward-server {string}
set isolator-server {string}
set poolname <name1>, <name2>, ...
set groups <name1>, <name2>, ...
set users <name1>, <name2>, ...
set disclaimer [disable|domain|...]
set comments {var-string}
set redirect-url {var-string}
set custom-log-fields <field-id1>, <field-id2>, ...
set replacemsg-override-group {string}
set srcaddr-negate [enable|disable]
set dstaddr-negate [enable|disable]
set service-negate [enable|disable]
set internet-service-negate [enable|disable]
set internet-service6-negate [enable|disable]

```

```

set application <id1>, <id2>, ...
set app-category <id1>, <id2>, ...
set app-group <name1>, <name2>, ...
set https-sub-category [enable|disable]
set decrypted-traffic-mirror {string}
set max-session-per-user {integer}
set profile-type [single|group]
set profile-group {string}
set profile-protocol-options {string}
set ssl-ssh-profile {string}
set av-profile {string}
set ia-profile {string}
set webfilter-profile {string}
set dnsfilter-profile {string}
set emailfilter-profile {string}
set dlp-profile {string}
set file-filter-profile {string}
set ips-sensor {string}
set application-list {string}
set icap-profile {string}
set cifs-profile {string}
set videofilter-profile {string}
set isolator-profile {string}
set redirect-profile {string}
set ssh-filter-profile {string}
set casb-profile {string}
set detect-https-in-http-request [enable|disable]
next
end

```

config firewall policy

Parameter	Description	Type	Size	Default
policyid	Policy ID.	integer	Minimum value: 0 Maximum value: 4294967294	0
type	Type of policy.	option	-	transparent
	Option		Description	
	explicit-web		Explicit Web Proxy policy	
	explicit-web-connect		Explicit Web Proxy connection policy	
	transparent		Transparent firewall policy	
	transparent-connect		Transparent firewall connection policy	

Parameter	Description	Type	Size	Default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>explicit-ftp</i></td><td>Explicit FTP Proxy policy</td></tr><tr><td><i>ssh-tunnel</i></td><td>SSH Tunnel policy</td></tr><tr><td><i>ssh</i></td><td>SSH policy</td></tr><tr><td><i>access-proxy</i></td><td>Access Proxy</td></tr><tr><td><i>wanopt</i></td><td>WANopt Tunnel</td></tr></table>	Option	Description	<i>explicit-ftp</i>	Explicit FTP Proxy policy	<i>ssh-tunnel</i>	SSH Tunnel policy	<i>ssh</i>	SSH policy	<i>access-proxy</i>	Access Proxy	<i>wanopt</i>	WANopt Tunnel			
	Option	Description														
	<i>explicit-ftp</i>	Explicit FTP Proxy policy														
	<i>ssh-tunnel</i>	SSH Tunnel policy														
	<i>ssh</i>	SSH policy														
	<i>access-proxy</i>	Access Proxy														
	<i>wanopt</i>	WANopt Tunnel														
status	Enable or disable this policy.	option	-	enable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.									
	Option	Description														
	<i>enable</i>	Enable setting.														
<i>disable</i>	Disable setting.															
name	Policy name.	string	Maximum length: 35													
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000												
force-proxy	Force proxy.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Force all TCP transparent traffic to proxy.</td></tr><tr><td><i>disable</i></td><td>Do not force TCP transparent traffic to proxy.</td></tr></table>	Option	Description	<i>enable</i>	Force all TCP transparent traffic to proxy.	<i>disable</i>	Do not force TCP transparent traffic to proxy.									
	Option	Description														
	<i>enable</i>	Force all TCP transparent traffic to proxy.														
<i>disable</i>	Do not force TCP transparent traffic to proxy.															
implicit-proxy-detection	Implicit proxy detection.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable implicit proxy detection.</td></tr><tr><td><i>disable</i></td><td>Disable implicit proxy detection.</td></tr></table>	Option	Description	<i>enable</i>	Enable implicit proxy detection.	<i>disable</i>	Disable implicit proxy detection.									
	Option	Description														
	<i>enable</i>	Enable implicit proxy detection.														
<i>disable</i>	Disable implicit proxy detection.															
dynamic-bypass	Dynamic bypass.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable dynamic bypass to all HTTP traffic in this policy.</td></tr><tr><td><i>disable</i></td><td>Disable dynamic bypass to all HTTP traffic in this policy.</td></tr></table>	Option	Description	<i>enable</i>	Enable dynamic bypass to all HTTP traffic in this policy.	<i>disable</i>	Disable dynamic bypass to all HTTP traffic in this policy.									
	Option	Description														
	<i>enable</i>	Enable dynamic bypass to all HTTP traffic in this policy.														
<i>disable</i>	Disable dynamic bypass to all HTTP traffic in this policy.															

Parameter	Description	Type	Size	Default										
srcintf <name>	Incoming (ingress) interface. Interface name.	string	Maximum length: 79											
dstintf <name>	Outgoing (egress) interface. Interface name.	string	Maximum length: 79											
ztna-device-ownership	Enable/disable zero trust device ownership.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable ZTNA device ownership check.</td></tr><tr><td><i>disable</i></td><td>Disable ZTNA device ownership check.</td></tr></table>				Option	Description	<i>enable</i>	Enable ZTNA device ownership check.	<i>disable</i>	Disable ZTNA device ownership check.				
Option	Description													
<i>enable</i>	Enable ZTNA device ownership check.													
<i>disable</i>	Disable ZTNA device ownership check.													
srcaddr <name>	Source address and address group names. Address name.	string	Maximum length: 79											
dstaddr <name>	Destination address and address group names. Address name.	string	Maximum length: 79											
srcaddr6 <name>	IPv6 source address (web proxy and ftp proxy only). Address name.	string	Maximum length: 79											
dstaddr6 <name>	IPv6 destination address (web proxy and ftp proxy only). Address name.	string	Maximum length: 79											
action	Policy action (allow/deny).	option	-	deny										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>accept</i></td><td>Allows session that match the firewall policy.</td></tr><tr><td><i>deny</i></td><td>Blocks sessions that match the firewall policy.</td></tr><tr><td><i>redirect</i></td><td>Redirect sessions that match the firewall policy to a url.</td></tr><tr><td><i>isolate</i></td><td>Isolate sessions that match the firewall policy with isolator.</td></tr></table>				Option	Description	<i>accept</i>	Allows session that match the firewall policy.	<i>deny</i>	Blocks sessions that match the firewall policy.	<i>redirect</i>	Redirect sessions that match the firewall policy to a url.	<i>isolate</i>	Isolate sessions that match the firewall policy with isolator.
Option	Description													
<i>accept</i>	Allows session that match the firewall policy.													
<i>deny</i>	Blocks sessions that match the firewall policy.													
<i>redirect</i>	Redirect sessions that match the firewall policy to a url.													
<i>isolate</i>	Isolate sessions that match the firewall policy with isolator.													
schedule	Schedule name.	string	Maximum length: 35											
policy-expiry	Enable/disable policy expiry.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable policy expiry.</td></tr><tr><td><i>disable</i></td><td>Disable policy expiry.</td></tr></table>				Option	Description	<i>enable</i>	Enable policy expiry.	<i>disable</i>	Disable policy expiry.				
Option	Description													
<i>enable</i>	Enable policy expiry.													
<i>disable</i>	Disable policy expiry.													

Parameter	Description	Type	Size	Default						
policy-expiry-date	Policy expiry date (YYYY-MM-DD HH:MM:SS).	datetime	Not Specified	0000-00-00 00:00:00						
service <name>	Service and service group names. Service and service group names.	string	Maximum length: 79							
explicit-web-proxy	Explicit web proxy.	string	Maximum length: 35							
transparent	set webproxy to use original client address.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable using original client address for webproxy.</td></tr><tr><td><i>disable</i></td><td>Disable using original client address for webproxy.</td></tr></table>				Option	Description	<i>enable</i>	Enable using original client address for webproxy.	<i>disable</i>	Disable using original client address for webproxy.
Option	Description									
<i>enable</i>	Enable using original client address for webproxy.									
<i>disable</i>	Disable using original client address for webproxy.									
access-proxy <name>	Access Proxy. Access Proxy name.	string	Maximum length: 79							
ztna-ems-tag <name>	Source ztna-ems-tag names. Address name.	string	Maximum length: 79							
ztna-tags-match-logic	ZTNA tag matching logic.	option	-	or						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>or</i></td><td>Match ZTNA tags using a logical OR operator.</td></tr><tr><td><i>and</i></td><td>Match ZTNA tags using a logical AND operator.</td></tr></table>				Option	Description	<i>or</i>	Match ZTNA tags using a logical OR operator.	<i>and</i>	Match ZTNA tags using a logical AND operator.
Option	Description									
<i>or</i>	Match ZTNA tags using a logical OR operator.									
<i>and</i>	Match ZTNA tags using a logical AND operator.									
device-ownership	When enabled, the ownership enforcement will be done at policy level.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable device ownership.</td></tr><tr><td><i>disable</i></td><td>Disable device ownership.</td></tr></table>				Option	Description	<i>enable</i>	Enable device ownership.	<i>disable</i>	Disable device ownership.
Option	Description									
<i>enable</i>	Enable device ownership.									
<i>disable</i>	Disable device ownership.									
pass-through	Enable/disable policy matching pass through	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable policy matching pass through.</td></tr><tr><td><i>disable</i></td><td>Disable policy matching pass through.</td></tr></table>				Option	Description	<i>enable</i>	Enable policy matching pass through.	<i>disable</i>	Disable policy matching pass through.
Option	Description									
<i>enable</i>	Enable policy matching pass through.									
<i>disable</i>	Disable policy matching pass through.									

Parameter	Description	Type	Size	Default						
url-category <id>	URL category ID list. URL category ID.	integer	Minimum value: 0 Maximum value: 4294967295							
url-risk <name>	URL risk level name. Risk level name.	string	Maximum length: 79							
internet-service	Enable/disable use of Internet Services for this policy. If enabled, destination address and service are not used.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable use of Internet Services in policy.</td></tr><tr><td><i>disable</i></td><td>Disable use of Internet Services in policy.</td></tr></table>				Option	Description	<i>enable</i>	Enable use of Internet Services in policy.	<i>disable</i>	Disable use of Internet Services in policy.
Option	Description									
<i>enable</i>	Enable use of Internet Services in policy.									
<i>disable</i>	Disable use of Internet Services in policy.									
internet-service-name <name>	Internet Service name. Internet Service name.	string	Maximum length: 79							
internet-service-group <name>	Internet Service group name. Internet Service group name.	string	Maximum length: 79							
internet-service-custom <name>	Custom Internet Service Name. Custom Internet Service name.	string	Maximum length: 79							
internet-service6	Enable/disable use of IPv6 Internet Services for this policy. If enabled, destination address and service are not used.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable use of IPv6 Internet Services in policy.</td></tr><tr><td><i>disable</i></td><td>Disable use of IPv6 Internet Services in policy.</td></tr></table>				Option	Description	<i>enable</i>	Enable use of IPv6 Internet Services in policy.	<i>disable</i>	Disable use of IPv6 Internet Services in policy.
Option	Description									
<i>enable</i>	Enable use of IPv6 Internet Services in policy.									
<i>disable</i>	Disable use of IPv6 Internet Services in policy.									
internet-service6-name <name>	IPv6 Internet Service name. IPv6 Internet Service name.	string	Maximum length: 79							
internet-service6-group <name>	Internet Service group name. Internet Service group name.	string	Maximum length: 79							

Parameter	Description	Type	Size	Default								
internet-service6-custom <name>	Custom IPv6 Internet Service name. Custom Internet Service name.	string	Maximum length: 79									
internet-service6-custom-group <name>	Custom Internet Service6 group name. Custom Internet Service6 group name.	string	Maximum length: 79									
internet-service-custom-group <name>	Custom Internet Service group name. Custom Internet Service group name.	string	Maximum length: 79									
utm-status	Enable to add one or more security profiles (AV, IPS, etc.) to the firewall policy.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.					
Option	Description											
<i>enable</i>	Enable setting.											
<i>disable</i>	Disable setting.											
ztna-policy-redirect	Redirect ZTNA traffic to matching Access-Proxy proxy-policy.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable ZTNA proxy-policy redirect.</td></tr><tr><td><i>disable</i></td><td>Disable ZTNA proxy-policy redirect.</td></tr></table>	Option	Description	<i>enable</i>	Enable ZTNA proxy-policy redirect.	<i>disable</i>	Disable ZTNA proxy-policy redirect.					
Option	Description											
<i>enable</i>	Enable ZTNA proxy-policy redirect.											
<i>disable</i>	Disable ZTNA proxy-policy redirect.											
webproxy-profile	Web proxy profile using when none matched policy.	string	Maximum length: 63									
logtraffic	Enable or disable logging. Log all sessions or security profile sessions.	option	-	utm								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>all</i></td><td>Log all sessions accepted or denied by this policy.</td></tr><tr><td><i>utm</i></td><td>Log traffic that has a security profile applied to it.</td></tr><tr><td><i>disable</i></td><td>Disable all logging for this policy.</td></tr></table>	Option	Description	<i>all</i>	Log all sessions accepted or denied by this policy.	<i>utm</i>	Log traffic that has a security profile applied to it.	<i>disable</i>	Disable all logging for this policy.			
Option	Description											
<i>all</i>	Log all sessions accepted or denied by this policy.											
<i>utm</i>	Log traffic that has a security profile applied to it.											
<i>disable</i>	Disable all logging for this policy.											
logtraffic-start	Record logs when a session starts and ends.	option	-	disable								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
log-http-transaction	Enable/disable http transaction log.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable HTTP transaction log.		
	<i>enable</i>	Enable HTTP transaction log.		
extended-log	Enable/disable extended log for http transaction.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
wanopt	Enable/disable WAN optimization.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
wanopt-detection	WAN optimization auto-detection mode.	option	-	active
	Option	Description		
	<i>active</i>	Active WAN optimization peer auto-detection.		
	<i>passive</i>	Passive WAN optimization peer auto-detection.		
	<i>off</i>	Turn off WAN optimization peer auto-detection.		
wanopt-passive-opt	WAN optimization passive mode options. This option decides what IP address will be used to connect server.	option	-	default
	Option	Description		
	<i>default</i>	Allow client side WAN opt peer to decide.		

Parameter	Description	Type	Size	Default
	Option Description			
	<i>transparent</i>	Use address of client to connect to server.		
	<i>non-transparent</i>	Use local FortiProxy address to connect to server.		
wanopt-profile	WAN optimization profile.	string	Maximum length: 35	
wanopt-peer	WAN optimization peer.	string	Maximum length: 35	
webcache	Enable/disable web cache.	option	-	disable
	Option Description			
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
webcache-https	Enable/disable web cache for HTTPS.	option	-	disable
	Option Description			
	<i>disable</i>	Disable web cache for HTTPS.		
	<i>enable</i>	Enable web cache for HTTPS.		
reverse-cache	Enable/disable reverse cache servers.	option	-	disable
	Option Description			
	<i>disable</i>	Disable reverse cache.		
	<i>enable</i>	Enable reverse cache servers.		
http-tunnel-auth	Enable/disable HTTP tunnel authentication.	option	-	disable
	Option Description			
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
ssh-policy-check	Enable/disable SSH policy check.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable SSH policy check.		
	<i>disable</i>	Disable SSH policy check.		
webproxy-forward-server	Webproxy forward server name.	string	Maximum length: 63	
isolator-server	isolator server name.	string	Maximum length: 63	
poolname <name>	Name of IP pool object. IP pool name.	string	Maximum length: 79	
groups <name>	Names of user groups that can authenticate with this policy. Group name.	string	Maximum length: 79	
users <name>	Names of individual users that can authenticate with this policy. Names of individual users that can authenticate with this policy.	string	Maximum length: 79	
disclaimer	Web proxy disclaimer setting: by domain, policy, or user.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable disclaimer.		
	<i>domain</i>	Display disclaimer for domain		
	<i>policy</i>	Display disclaimer for policy		
	<i>user</i>	Display disclaimer for current user		
comments	Comment.	var-string	Maximum length: 1023	
redirect-url	Redirect URL for further web proxy processing.	var-string	Maximum length: 1023	
custom-log-fields <field-id>	Custom fields to append to log messages for this policy. Custom log field.	string	Maximum length: 35	

Parameter	Description	Type	Size	Default						
replacemsg-override-group	Override the default replacement message group for this policy.	string	Maximum length: 35							
srcaddr-negate	When enabled srcaddr specifies what the source address must NOT be.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable source address negate.</td></tr><tr><td><i>disable</i></td><td>Disable source address negate.</td></tr></table>	Option	Description	<i>enable</i>	Enable source address negate.	<i>disable</i>	Disable source address negate.			
Option	Description									
<i>enable</i>	Enable source address negate.									
<i>disable</i>	Disable source address negate.									
dstaddr-negate	When enabled dstaddr specifies what the destination address must NOT be.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable destination address negate.</td></tr><tr><td><i>disable</i></td><td>Disable destination address negate.</td></tr></table>	Option	Description	<i>enable</i>	Enable destination address negate.	<i>disable</i>	Disable destination address negate.			
Option	Description									
<i>enable</i>	Enable destination address negate.									
<i>disable</i>	Disable destination address negate.									
service-negate	When enabled service specifies what the service must NOT be.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable negated service match.</td></tr><tr><td><i>disable</i></td><td>Disable negated service match.</td></tr></table>	Option	Description	<i>enable</i>	Enable negated service match.	<i>disable</i>	Disable negated service match.			
Option	Description									
<i>enable</i>	Enable negated service match.									
<i>disable</i>	Disable negated service match.									
internet-service-negate	When enabled internet-service specifies what the service must NOT be.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable negated Internet Service match.</td></tr><tr><td><i>disable</i></td><td>Disable negated Internet Service match.</td></tr></table>	Option	Description	<i>enable</i>	Enable negated Internet Service match.	<i>disable</i>	Disable negated Internet Service match.			
Option	Description									
<i>enable</i>	Enable negated Internet Service match.									
<i>disable</i>	Disable negated Internet Service match.									
internet-service6-negate	When enabled internet-service6 specifies what the service must not be.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable negated IPv6 Internet Service match.</td></tr><tr><td><i>disable</i></td><td>Disable negated IPv6 Internet Service match.</td></tr></table>	Option	Description	<i>enable</i>	Enable negated IPv6 Internet Service match.	<i>disable</i>	Disable negated IPv6 Internet Service match.			
Option	Description									
<i>enable</i>	Enable negated IPv6 Internet Service match.									
<i>disable</i>	Disable negated IPv6 Internet Service match.									

Parameter	Description	Type	Size	Default						
application <id>	Application ID list. Application IDs.	integer	Minimum value: 0 Maximum value: 4294967295							
app-category <id>	Application category ID list. Category IDs.	integer	Minimum value: 0 Maximum value: 4294967295							
app-group <name>	One or more application group names. Application group name.	string	Maximum length: 79							
https-sub- category	Enable/disable HTTPS sub- category policy matching.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable HTTPS sub-category policy matching.</td></tr><tr><td><i>disable</i></td><td>Disable HTTPS sub-category policy matching.</td></tr></table>				Option	Description	<i>enable</i>	Enable HTTPS sub-category policy matching.	<i>disable</i>	Disable HTTPS sub-category policy matching.
Option	Description									
<i>enable</i>	Enable HTTPS sub-category policy matching.									
<i>disable</i>	Disable HTTPS sub-category policy matching.									
decrypted- traffic-mirror	Decrypted traffic mirror.	string	Maximum length: 35							
max-session- per-user	Max UTM sessions per user.	integer	Minimum value: 0 Maximum value: 4294967295	0						
profile-type	Determine whether the firewall policy allows security profile groups or single profiles only.	option	-	single						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>single</i></td><td>Do not allow security profile groups.</td></tr><tr><td><i>group</i></td><td>Allow security profile groups.</td></tr></table>				Option	Description	<i>single</i>	Do not allow security profile groups.	<i>group</i>	Allow security profile groups.
Option	Description									
<i>single</i>	Do not allow security profile groups.									
<i>group</i>	Allow security profile groups.									
profile-group	Name of profile group.	string	Maximum length: 35							
profile- protocol- options	Name of an existing Protocol options profile.	string	Maximum length: 35	default						

Parameter	Description	Type	Size	Default
ssl-ssh-profile	Name of an existing SSL SSH profile.	string	Maximum length: 35	no-inspection
av-profile	Name of an existing Antivirus profile.	string	Maximum length: 35	
ia-profile	Image analyzer profile.	string	Maximum length: 35	
webfilter-profile	Name of an existing Web filter profile.	string	Maximum length: 35	
dnsfilter-profile	Name of an existing DNS filter profile.	string	Maximum length: 35	
emailfilter-profile	Name of an existing email filter profile.	string	Maximum length: 35	
dlp-profile	Name of an existing DLP profile.	string	Maximum length: 35	
file-filter-profile	Name of an existing file-filter profile.	string	Maximum length: 35	
ips-sensor	Name of an existing IPS sensor.	string	Maximum length: 35	
application-list	Name of an existing Application list.	string	Maximum length: 35	
icap-profile	Name of an existing ICAP profile.	string	Maximum length: 35	
cifs-profile	Name of an existing CIFS profile.	string	Maximum length: 35	
videofilter-profile	Name of an existing VideoFilter profile.	string	Maximum length: 35	
isolator-profile	Name of an existing isolator profile.	string	Maximum length: 35	
redirect-profile	Name of an existing URL Redirect profile.	string	Maximum length: 35	
ssh-filter-profile	Name of an existing SSH filter profile.	string	Maximum length: 35	
casb-profile	Name of an existing CASB profile.	string	Maximum length: 35	
detect-https-in-http-request	Enable/disable detection of HTTPS in HTTP request.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable detection of HTTPS in HTTP request.		
	<i>disable</i>	Disable detection of HTTPS in HTTP request.		

config firewall profile-group

Configure profile groups.

```

config firewall profile-group
  Description: Configure profile groups.
  edit <name>
    set profile-protocol-options {string}
    set ssl-ssh-profile {string}
    set av-profile {string}
    set ia-profile {string}
    set webfilter-profile {string}
    set dnsfilter-profile {string}
    set emailfilter-profile {string}
    set dlp-profile {string}
    set file-filter-profile {string}
    set ips-sensor {string}
    set application-list {string}
    set icap-profile {string}
    set cifs-profile {string}
    set videofilter-profile {string}
    set isolator-profile {string}
    set redirect-profile {string}
    set ssh-filter-profile {string}
    set casb-profile {string}
  next
end

```

config firewall profile-group

Parameter	Description	Type	Size	Default
name	Profile group name.	string	Maximum length: 35	
profile-protocol-options	Name of an existing Protocol options profile.	string	Maximum length: 35	default

Parameter	Description	Type	Size	Default
ssl-ssh-profile	Name of an existing SSL SSH profile.	string	Maximum length: 35	certificate-inspection
av-profile	Name of an existing Antivirus profile.	string	Maximum length: 35	
ia-profile	Image analyzer profile.	string	Maximum length: 35	
webfilter-profile	Name of an existing Web filter profile.	string	Maximum length: 35	
dnsfilter-profile	Name of an existing DNS filter profile.	string	Maximum length: 35	
emailfilter-profile	Name of an existing email filter profile.	string	Maximum length: 35	
dlp-profile	Name of an existing DLP profile.	string	Maximum length: 35	
file-filter-profile	Name of an existing file-filter profile.	string	Maximum length: 35	
ips-sensor	Name of an existing IPS sensor.	string	Maximum length: 35	
application-list	Name of an existing Application list.	string	Maximum length: 35	
icap-profile	Name of an existing ICAP profile.	string	Maximum length: 35	
cifs-profile	Name of an existing CIFS profile.	string	Maximum length: 35	
videofilter-profile	Name of an existing VideoFilter profile.	string	Maximum length: 35	
isolator-profile	Name of an existing isolator profile.	string	Maximum length: 35	
redirect-profile	Name of an existing URL Redirect profile.	string	Maximum length: 35	
ssh-filter-profile	Name of an existing SSH filter profile.	string	Maximum length: 35	
casb-profile	Name of an existing CASB profile.	string	Maximum length: 35	

config firewall profile-protocol-options

Configure protocol options.

```

config firewall profile-protocol-options
    Description: Configure protocol options.
    edit <name>
        set comment {var-string}
        set replacemsg-group {string}
        set oversize-log [disable|enable]
        set switching-protocols-log [disable|enable]
    config proxy-redirect
        Description: Configure proxy redirection protocol options.
        set ports {integer}
        set status [enable|disable]
    end
    config http
        Description: Configure HTTP protocol options.
        set ports {integer}
        set status [enable|disable]
        set options {option1}, {option2}, ...
        set comfort-interval {integer}
        set comfort-amount {integer}
        set range-block [disable|enable]
        set strip-x-forwarded-for [disable|enable]
        set post-lang {option1}, {option2}, ...
        set streaming-content-bypass [enable|disable]
        set dns-protection [enable|disable]
        set switching-protocols [bypass|block]
        set unknown-http-version [reject|tunnel|...]
        set tunnel-non-http [enable|disable]
        set h2c [enable|disable]
        set unknown-content-encoding [block|inspect|...]
        set oversize-limit {integer}
        set uncompressed-oversize-limit {integer}
        set uncompressed-nest-limit {integer}
        set stream-based-uncompressed-limit {integer}
        set scan-bzip2 [enable|disable]
        set verify-dns-for-policy-matching [enable|disable]
        set block-page-status-code {integer}
        set retry-count {integer}
        set domain-fronting [allow|block|...]
        set tcp-window-type [auto-tuning|system|...]
        set tcp-window-minimum {integer}
        set tcp-window-maximum {integer}
        set tcp-window-size {integer}
        set ssl-offloaded [no|yes]
        set address-ip-rating [enable|disable]
        set encrypted-file [pass|inspect|...]
        set encrypted-file-log [enable|disable]
    end
    config ftp
        Description: Configure FTP protocol options.
        set ports {integer}
        set status [enable|disable]
        set options {option1}, {option2}, ...

```



```

    set comfort-interval {integer}
    set comfort-amount {integer}
    set oversize-limit {integer}
    set uncompressed-oversize-limit {integer}
    set uncompressed-nest-limit {integer}
    set stream-based-uncompressed-limit {integer}
    set scan-bzip2 [enable|disable]
    set tcp-window-type [auto-tuning|system|...]
    set tcp-window-minimum {integer}
    set tcp-window-maximum {integer}
    set tcp-window-size {integer}
    set ssl-offloaded [no|yes]
    set explicit-ftp-tls [enable|disable]
end
config imap
    Description: Configure IMAP protocol options.
    set ports {integer}
    set status [enable|disable]
    set options {option1}, {option2}, ...
    set oversize-limit {integer}
    set uncompressed-oversize-limit {integer}
    set uncompressed-nest-limit {integer}
    set scan-bzip2 [enable|disable]
    set ssl-offloaded [no|yes]
    set address-ip-rating [enable|disable]
end
config mapi
    Description: Configure MAPI protocol options.
    set ports {integer}
    set status [enable|disable]
    set options {option1}, {option2}, ...
    set oversize-limit {integer}
    set uncompressed-oversize-limit {integer}
    set uncompressed-nest-limit {integer}
    set scan-bzip2 [enable|disable]
end
config pop3
    Description: Configure POP3 protocol options.
    set ports {integer}
    set status [enable|disable]
    set options {option1}, {option2}, ...
    set oversize-limit {integer}
    set uncompressed-oversize-limit {integer}
    set uncompressed-nest-limit {integer}
    set scan-bzip2 [enable|disable]
    set ssl-offloaded [no|yes]
end
config smtp
    Description: Configure SMTP protocol options.
    set ports {integer}
    set status [enable|disable]
    set options {option1}, {option2}, ...

```

```

    set oversize-limit {integer}
    set uncompressed-oversize-limit {integer}
    set uncompressed-nest-limit {integer}
    set scan-bzip2 [enable|disable]
    set server-busy [enable|disable]
    set ssl-offloaded [no|yes]
end
config nntp
    Description: Configure NNTP protocol options.
    set ports {integer}
    set status [enable|disable]
    set options {option1}, {option2}, ...
    set oversize-limit {integer}
    set uncompressed-oversize-limit {integer}
    set uncompressed-nest-limit {integer}
    set scan-bzip2 [enable|disable]
end
config ssh
    Description: Configure SFTP and SCP protocol options.
    set options {option1}, {option2}, ...
    set comfort-interval {integer}
    set comfort-amount {integer}
    set oversize-limit {integer}
    set uncompressed-oversize-limit {integer}
    set uncompressed-nest-limit {integer}
    set stream-based-uncompressed-limit {integer}
    set scan-bzip2 [enable|disable]
    set tcp-window-type [auto-tuning|system|...]
    set tcp-window-minimum {integer}
    set tcp-window-maximum {integer}
    set tcp-window-size {integer}
    set ssl-offloaded [no|yes]
end
config dns
    Description: Configure DNS protocol options.
    set ports {integer}
    set status [enable|disable]
end
config cifs
    Description: Configure CIFS protocol options.
    set ports {integer}
    set status [enable|disable]
    set options {option1}, {option2}, ...
    set oversize-limit {integer}
    set uncompressed-oversize-limit {integer}
    set uncompressed-nest-limit {integer}
    set scan-bzip2 [enable|disable]
    set tcp-window-type [auto-tuning|system|...]
    set tcp-window-minimum {integer}
    set tcp-window-maximum {integer}
    set tcp-window-size {integer}
    set server-credential-type [none|credential-replication|...]

```

```

        set domain-controller {string}
        config server-keytab
            Description: Server keytab.
            edit <principal>
                set keytab {string}
            next
        end
    end
end
config mail-signature
    Description: Configure Mail signature.
    set status [disable|enable]
    set signature {string}
end
set rpc-over-http [enable|disable]
next
end

```

config firewall profile-protocol-options

Parameter	Description	Type	Size	Default						
name	Name.	string	Maximum length: 35							
comment	Optional comments.	var-string	Maximum length: 255							
replacemsg-group	Name of the replacement message group to be used.	string	Maximum length: 35							
oversize-log	Enable/disable logging for antivirus oversize file blocking.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable logging for antivirus oversize file blocking.</td></tr><tr><td><i>enable</i></td><td>Enable logging for antivirus oversize file blocking.</td></tr></table>				Option	Description	<i>disable</i>	Disable logging for antivirus oversize file blocking.	<i>enable</i>	Enable logging for antivirus oversize file blocking.
Option	Description									
<i>disable</i>	Disable logging for antivirus oversize file blocking.									
<i>enable</i>	Enable logging for antivirus oversize file blocking.									
switching-protocols-log	Enable/disable logging for HTTP/HTTPS switching protocols.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable logging for HTTP/HTTPS switching protocols.</td></tr><tr><td><i>enable</i></td><td>Enable logging for HTTP/HTTPS switching protocols.</td></tr></table>				Option	Description	<i>disable</i>	Disable logging for HTTP/HTTPS switching protocols.	<i>enable</i>	Enable logging for HTTP/HTTPS switching protocols.
Option	Description									
<i>disable</i>	Disable logging for HTTP/HTTPS switching protocols.									
<i>enable</i>	Enable logging for HTTP/HTTPS switching protocols.									
rpc-over-http	Enable/disable inspection of RPC over HTTP.	option	-	disable						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable inspection of RPC over HTTP.		
	<i>disable</i>	Disable inspection of RPC over HTTP.		

config proxy-redirect

Parameter	Description	Type	Size	Default
ports	Ports to inspect all for content (1 - 65535).	integer	Minimum value: 1 Maximum value: 65535	
status	Enable/disable the active status of scanning for this protocol.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

config http

Parameter	Description	Type	Size	Default
ports	Ports to scan for content (1 - 65535, default = 80).	integer	Minimum value: 1 Maximum value: 65535	
status	Enable/disable the active status of scanning for this protocol.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
options	One or more options that can be applied to the session.	option	-	
	Option	Description		
	<i>clientcomfort</i>	Prevent client timeout.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>servercomfort</i>	Prevent server timeout.		
	<i>oversize</i>	Block oversized file.		
	<i>chunkedbypass</i>	Bypass chunked transfer encoded sites.		
comfort-interval	Interval between successive transmissions of data for client comforting (seconds).	integer	Minimum value: 1 Maximum value: 900	10
comfort-amount	Number of bytes to send in each transmission for client comforting (bytes).	integer	Minimum value: 1 Maximum value: 65535	1
range-block	Enable/disable blocking of partial downloads.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable range header blocking (allow partial file downloads)		
	<i>enable</i>	Enable range header blocking (treat all partial file downloads as full file download)		
strip-x-forwarded-for	Enable/disable stripping of HTTP X-Forwarded-For header.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable changing of HTTP X-Forwarded-For header.		
	<i>enable</i>	Enable replacement of X-Forwarded-For value with 1.1.1.1.		
post-lang	ID codes for character sets to be used to convert to UTF-8 for banned words and DLP on HTTP posts (maximum of 5 character sets).	option	-	
	Option	Description		
	<i>jisx0201</i>	Japanese Industrial Standard 0201.		
	<i>jisx0208</i>	Japanese Industrial Standard 0208.		
	<i>jisx0212</i>	Japanese Industrial Standard 0212.		
	<i>gb2312</i>	Guojia Biaozhun 2312 (simplified Chinese).		

Parameter	Description	Type	Size	Default																																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ksc5601-ex</i></td><td>Wansung Korean standard 5601.</td></tr><tr><td><i>euc-jp</i></td><td>Extended Unicode Japanese.</td></tr><tr><td><i>sjis</i></td><td>Shift Japanese Industrial Standard.</td></tr><tr><td><i>iso2022-jp</i></td><td>ISO 2022 Japanese.</td></tr><tr><td><i>iso2022-jp-1</i></td><td>ISO 2022-1 Japanese.</td></tr><tr><td><i>iso2022-jp-2</i></td><td>ISO 2022-2 Japanese.</td></tr><tr><td><i>euc-cn</i></td><td>Extended Unicode Chinese.</td></tr><tr><td><i>ces-gbk</i></td><td>Extended GB2312 (simplified Chinese).</td></tr><tr><td><i>hz</i></td><td>Hanzi simplified Chinese.</td></tr><tr><td><i>ces-big5</i></td><td>Big-5 traditional Chinese.</td></tr><tr><td><i>euc-kr</i></td><td>Extended Unicode Korean.</td></tr><tr><td><i>iso2022-jp-3</i></td><td>ISO 2022-3 Japanese.</td></tr><tr><td><i>iso8859-1</i></td><td>ISO 8859 Part 1 (Western European).</td></tr><tr><td><i>tis620</i></td><td>Thai Industrial Standard 620.</td></tr><tr><td><i>cp874</i></td><td>Code Page 874 (Thai).</td></tr><tr><td><i>cp1252</i></td><td>Code Page 1252 (Western European Latin).</td></tr><tr><td><i>cp1251</i></td><td>Code Page 1251 (Cyrillic).</td></tr></table>	Option	Description	<i>ksc5601-ex</i>	Wansung Korean standard 5601.	<i>euc-jp</i>	Extended Unicode Japanese.	<i>sjis</i>	Shift Japanese Industrial Standard.	<i>iso2022-jp</i>	ISO 2022 Japanese.	<i>iso2022-jp-1</i>	ISO 2022-1 Japanese.	<i>iso2022-jp-2</i>	ISO 2022-2 Japanese.	<i>euc-cn</i>	Extended Unicode Chinese.	<i>ces-gbk</i>	Extended GB2312 (simplified Chinese).	<i>hz</i>	Hanzi simplified Chinese.	<i>ces-big5</i>	Big-5 traditional Chinese.	<i>euc-kr</i>	Extended Unicode Korean.	<i>iso2022-jp-3</i>	ISO 2022-3 Japanese.	<i>iso8859-1</i>	ISO 8859 Part 1 (Western European).	<i>tis620</i>	Thai Industrial Standard 620.	<i>cp874</i>	Code Page 874 (Thai).	<i>cp1252</i>	Code Page 1252 (Western European Latin).	<i>cp1251</i>	Code Page 1251 (Cyrillic).			
	Option	Description																																						
	<i>ksc5601-ex</i>	Wansung Korean standard 5601.																																						
	<i>euc-jp</i>	Extended Unicode Japanese.																																						
	<i>sjis</i>	Shift Japanese Industrial Standard.																																						
	<i>iso2022-jp</i>	ISO 2022 Japanese.																																						
	<i>iso2022-jp-1</i>	ISO 2022-1 Japanese.																																						
	<i>iso2022-jp-2</i>	ISO 2022-2 Japanese.																																						
	<i>euc-cn</i>	Extended Unicode Chinese.																																						
	<i>ces-gbk</i>	Extended GB2312 (simplified Chinese).																																						
	<i>hz</i>	Hanzi simplified Chinese.																																						
	<i>ces-big5</i>	Big-5 traditional Chinese.																																						
	<i>euc-kr</i>	Extended Unicode Korean.																																						
	<i>iso2022-jp-3</i>	ISO 2022-3 Japanese.																																						
	<i>iso8859-1</i>	ISO 8859 Part 1 (Western European).																																						
	<i>tis620</i>	Thai Industrial Standard 620.																																						
	<i>cp874</i>	Code Page 874 (Thai).																																						
	<i>cp1252</i>	Code Page 1252 (Western European Latin).																																						
<i>cp1251</i>	Code Page 1251 (Cyrillic).																																							
streaming-content-bypass	Enable/disable bypassing of streaming content from buffering.	option	-	enable																																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable bypassing of streaming content from buffering</td></tr><tr><td><i>disable</i></td><td>Disable bypassing of streaming content from buffering</td></tr></table>	Option	Description	<i>enable</i>	Enable bypassing of streaming content from buffering	<i>disable</i>	Disable bypassing of streaming content from buffering																																	
	Option	Description																																						
	<i>enable</i>	Enable bypassing of streaming content from buffering																																						
<i>disable</i>	Disable bypassing of streaming content from buffering																																							
dns-protection	Enable/disable DNS protection for HTTP/HTTPS traffic.	option	-	disable																																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.																																	
	Option	Description																																						
	<i>enable</i>	Enable setting.																																						
<i>disable</i>	Disable setting.																																							

Parameter	Description	Type	Size	Default								
switching-protocols	Bypass from scanning, or block a connection that attempts to switch protocol.	option	-	bypass								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>bypass</td><td>Bypass connections when switching protocols.</td></tr><tr><td>block</td><td>Block connections when switching protocols.</td></tr></table>	Option	Description	bypass	Bypass connections when switching protocols.	block	Block connections when switching protocols.					
Option	Description											
bypass	Bypass connections when switching protocols.											
block	Block connections when switching protocols.											
unknown-http-version	How to handle HTTP sessions that do not comply with HTTP 0.9, 1.0, or 1.1.	option	-	reject								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>reject</td><td>Reject or tear down HTTP sessions that do not use HTTP 0.9, 1.0, or 1.1.</td></tr><tr><td>tunnel</td><td>Pass HTTP traffic that does not use HTTP 0.9, 1.0, or 1.1 without applying HTTP protocol optimization, byte-caching, or web caching. TCP protocol optimization is applied.</td></tr><tr><td>best-effort</td><td>Assume all HTTP sessions comply with HTTP 0.9, 1.0, or 1.1. If a session uses a different HTTP version, it may not parse correctly and the connection may be lost.</td></tr></table>	Option	Description	reject	Reject or tear down HTTP sessions that do not use HTTP 0.9, 1.0, or 1.1.	tunnel	Pass HTTP traffic that does not use HTTP 0.9, 1.0, or 1.1 without applying HTTP protocol optimization, byte-caching, or web caching. TCP protocol optimization is applied.	best-effort	Assume all HTTP sessions comply with HTTP 0.9, 1.0, or 1.1. If a session uses a different HTTP version, it may not parse correctly and the connection may be lost.			
Option	Description											
reject	Reject or tear down HTTP sessions that do not use HTTP 0.9, 1.0, or 1.1.											
tunnel	Pass HTTP traffic that does not use HTTP 0.9, 1.0, or 1.1 without applying HTTP protocol optimization, byte-caching, or web caching. TCP protocol optimization is applied.											
best-effort	Assume all HTTP sessions comply with HTTP 0.9, 1.0, or 1.1. If a session uses a different HTTP version, it may not parse correctly and the connection may be lost.											
tunnel-non-http	Configure how to process non-HTTP traffic when a profile configured for HTTP traffic accepts a non-HTTP session. Can occur if an application sends non-HTTP traffic using an HTTP destination port.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Pass non-HTTP sessions through the tunnel without applying protocol optimization, byte-caching, or web caching. TCP protocol optimization is applied.</td></tr><tr><td>disable</td><td>Drop or tear down non-HTTP sessions accepted by the profile.</td></tr></table>	Option	Description	enable	Pass non-HTTP sessions through the tunnel without applying protocol optimization, byte-caching, or web caching. TCP protocol optimization is applied.	disable	Drop or tear down non-HTTP sessions accepted by the profile.					
Option	Description											
enable	Pass non-HTTP sessions through the tunnel without applying protocol optimization, byte-caching, or web caching. TCP protocol optimization is applied.											
disable	Drop or tear down non-HTTP sessions accepted by the profile.											
h2c	Enable/disable h2c HTTP connection upgrade.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Allow h2c HTTP connection upgrades. h2c tunnels do not support content scan.</td></tr></table>	Option	Description	enable	Allow h2c HTTP connection upgrades. h2c tunnels do not support content scan.							
Option	Description											
enable	Allow h2c HTTP connection upgrades. h2c tunnels do not support content scan.											

Parameter	Description	Type	Size	Default								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not allow h2c HTTP connection upgrades.</td></tr></table>	Option	Description	<i>disable</i>	Do not allow h2c HTTP connection upgrades.							
	Option	Description										
<i>disable</i>	Do not allow h2c HTTP connection upgrades.											
unknown-content-encoding	Configure the action the FortiGate unit will take on unknown content-encoding.	option	-	block								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>block</i></td><td>Block HTTP session when unknown content-encoding is detected.</td></tr><tr><td><i>inspect</i></td><td>Scan HTTP traffic as plain-text when unknown content-encoding is detected.</td></tr><tr><td><i>bypass</i></td><td>Bypass scan when unknown content-encoding is detected.</td></tr></table>	Option	Description	<i>block</i>	Block HTTP session when unknown content-encoding is detected.	<i>inspect</i>	Scan HTTP traffic as plain-text when unknown content-encoding is detected.	<i>bypass</i>	Bypass scan when unknown content-encoding is detected.			
	Option	Description										
	<i>block</i>	Block HTTP session when unknown content-encoding is detected.										
	<i>inspect</i>	Scan HTTP traffic as plain-text when unknown content-encoding is detected.										
<i>bypass</i>	Bypass scan when unknown content-encoding is detected.											
oversize-limit	Maximum in-memory file size that can be scanned (MB).	integer	Minimum value: 1 Maximum value: 4095	10								
uncompressed-oversize-limit	Maximum in-memory uncompressed file size that can be scanned.	integer	Minimum value: 1 Maximum value: 4095	10								
uncompressed-nest-limit	Maximum nested levels of compression that can be uncompressed and scanned (2 - 100, default = 12).	integer	Minimum value: 2 Maximum value: 100	12								
stream-based-uncompressed-limit	Maximum stream-based uncompressed data size that will be scanned in megabytes. Stream-based uncompression used only under certain conditions (unlimited = 0, default = 0).	integer	Minimum value: 0 Maximum value: 4294967295	0								
scan-bzip2	Enable/disable scanning of BZip2 compressed files.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.					
	Option	Description										
	<i>enable</i>	Enable setting.										
<i>disable</i>	Disable setting.											
verify-dns-for-policy-matching	Enable/disable verify DNS for policy matching.	option	-	enable								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
block-page-status-code	Code number returned for blocked HTTP pages (non-FortiGuard only) (100 - 599, default = 403).	integer	Minimum value: 100 Maximum value: 599	403
retry-count	Number of attempts to retry HTTP connection (0 - 100, default = 0).	integer	Minimum value: 0 Maximum value: 100	0
domain-fronting	Configure HTTP domain fronting (default = block).	option	-	block
	Option	Description		
	<i>allow</i>	Allow domain fronting.		
	<i>block</i>	Block and log domain fronting.		
	<i>monitor</i>	Allow and log domain fronting.		
tcp-window-type	TCP window type to use for this protocol.	option	-	auto-tuning
	Option	Description		
	<i>auto-tuning</i>	Allow system to auto-tune TCP window size (default).		
	<i>system</i>	Use system default TCP window size for this protocol.		
	<i>static</i>	Manually specify TCP window size.		
	<i>dynamic</i>	Vary TCP window size based on available memory and within limits of tcp-window-minimum and tcp-window-maximum.		
tcp-window-minimum	Minimum dynamic TCP window size.	integer	Minimum value: 65536 Maximum value: 1048576	131072

Parameter	Description	Type	Size	Default								
tcp-window-maximum	Maximum dynamic TCP window size.	integer	Minimum value: 1048576 Maximum value: 33554432	8388608								
tcp-window-size	Set TCP static window size.	integer	Minimum value: 65536 Maximum value: 33554432	262144								
ssl-offloaded	SSL decryption and encryption performed by an external device.	option	-	no								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>no</td><td>SSL decryption and encryption performed by FortiProxy when deep-inspection is enabled.</td></tr><tr><td>yes</td><td>SSL decryption and encryption performed by an external device.</td></tr></table>	Option	Description	no	SSL decryption and encryption performed by FortiProxy when deep-inspection is enabled.	yes	SSL decryption and encryption performed by an external device.					
Option	Description											
no	SSL decryption and encryption performed by FortiProxy when deep-inspection is enabled.											
yes	SSL decryption and encryption performed by an external device.											
address-ip-rating	Enable/disable IP based URL rating.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable setting.</td></tr><tr><td>disable</td><td>Disable setting.</td></tr></table>	Option	Description	enable	Enable setting.	disable	Disable setting.					
Option	Description											
enable	Enable setting.											
disable	Disable setting.											
encrypted-file	Encrypted file action (default = pass).	option	-	pass								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>pass</td><td>Pass encrypted files without content scan.</td></tr><tr><td>inspect</td><td>Request password to decrypt and scan encrypted file. Files failed to decrypt will be blocked.</td></tr><tr><td>block</td><td>Block encrypted files.</td></tr></table>	Option	Description	pass	Pass encrypted files without content scan.	inspect	Request password to decrypt and scan encrypted file. Files failed to decrypt will be blocked.	block	Block encrypted files.			
Option	Description											
pass	Pass encrypted files without content scan.											
inspect	Request password to decrypt and scan encrypted file. Files failed to decrypt will be blocked.											
block	Block encrypted files.											
encrypted-file-log	Enable/disable Log encrypted file.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable setting.</td></tr><tr><td>disable</td><td>Disable setting.</td></tr></table>	Option	Description	enable	Enable setting.	disable	Disable setting.					
Option	Description											
enable	Enable setting.											
disable	Disable setting.											

config ftp

Parameter	Description	Type	Size	Default												
ports	Ports to scan for content (1 - 65535, default = 21).	integer	Minimum value: 1 Maximum value: 65535													
status	Enable/disable the active status of scanning for this protocol.	option	-	enable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>				Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.						
	Option	Description														
	<i>enable</i>	Enable setting.														
<i>disable</i>	Disable setting.															
options	One or more options that can be applied to the session.	option	-													
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>clientcomfort</i></td><td>Prevent client timeout.</td></tr><tr><td><i>oversize</i></td><td>Block oversized file.</td></tr><tr><td><i>splice</i></td><td>Enable splice mode.</td></tr><tr><td><i>bypass-rest-command</i></td><td>Bypass REST command.</td></tr><tr><td><i>bypass-mode-command</i></td><td>Bypass MODE command.</td></tr></table>				Option	Description	<i>clientcomfort</i>	Prevent client timeout.	<i>oversize</i>	Block oversized file.	<i>splice</i>	Enable splice mode.	<i>bypass-rest-command</i>	Bypass REST command.	<i>bypass-mode-command</i>	Bypass MODE command.
	Option	Description														
	<i>clientcomfort</i>	Prevent client timeout.														
	<i>oversize</i>	Block oversized file.														
	<i>splice</i>	Enable splice mode.														
	<i>bypass-rest-command</i>	Bypass REST command.														
<i>bypass-mode-command</i>	Bypass MODE command.															
comfort-interval	Interval between successive transmissions of data for client comforting (seconds).	integer	Minimum value: 1 Maximum value: 900	10												
comfort-amount	Number of bytes to send in each transmission for client comforting (bytes).	integer	Minimum value: 1 Maximum value: 65535	1												
oversize-limit	Maximum in-memory file size that can be scanned (MB).	integer	Minimum value: 1 Maximum value: 4095	10												
uncompressed-oversize-limit	Maximum in-memory uncompressed file size that can be scanned.	integer	Minimum value: 1 Maximum value: 4095	10												

Parameter	Description	Type	Size	Default											
uncompressed-nest-limit	Maximum nested levels of compression that can be uncompressed and scanned (2 - 100, default = 12).	integer	Minimum value: 2 Maximum value: 100	12											
stream-based-uncompressed-limit	Maximum stream-based uncompressed data size that will be scanned in megabytes. Stream-based uncompression used only under certain conditions (unlimited = 0, default = 0).	integer	Minimum value: 0 Maximum value: 4294967295	0											
scan-bzip2	Enable/disable scanning of BZip2 compressed files.	option	-	enable											
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>		Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.							
	Option	Description													
	<i>enable</i>	Enable setting.													
<i>disable</i>	Disable setting.														
tcp-window-type	TCP window type to use for this protocol.	option	-	auto-tuning											
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto-tuning</i></td><td>Allow system to auto-tune TCP window size (default).</td></tr><tr><td><i>system</i></td><td>Use system default TCP window size for this protocol.</td></tr><tr><td><i>static</i></td><td>Manually specify TCP window size.</td></tr><tr><td><i>dynamic</i></td><td>Vary TCP window size based on available memory and within limits of tcp-window-minimum and tcp-window-maximum.</td></tr></table>		Option	Description	<i>auto-tuning</i>	Allow system to auto-tune TCP window size (default).	<i>system</i>	Use system default TCP window size for this protocol.	<i>static</i>	Manually specify TCP window size.	<i>dynamic</i>	Vary TCP window size based on available memory and within limits of tcp-window-minimum and tcp-window-maximum.			
	Option	Description													
	<i>auto-tuning</i>	Allow system to auto-tune TCP window size (default).													
	<i>system</i>	Use system default TCP window size for this protocol.													
	<i>static</i>	Manually specify TCP window size.													
<i>dynamic</i>	Vary TCP window size based on available memory and within limits of tcp-window-minimum and tcp-window-maximum.														
tcp-window-minimum	Minimum dynamic TCP window size.	integer	Minimum value: 65536 Maximum value: 1048576	131072											
tcp-window-maximum	Maximum dynamic TCP window size.	integer	Minimum value: 1048576 Maximum value: 33554432	8388608											

Parameter	Description	Type	Size	Default						
tcp-window-size	Set TCP static window size.	integer	Minimum value: 65536 Maximum value: 33554432	262144						
ssl-offloaded	SSL decryption and encryption performed by an external device.	option	-	no						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>no</td><td>SSL decryption and encryption performed by FortiProxy when deep-inspection is enabled.</td></tr><tr><td>yes</td><td>SSL decryption and encryption performed by an external device.</td></tr></table>	Option	Description	no	SSL decryption and encryption performed by FortiProxy when deep-inspection is enabled.	yes	SSL decryption and encryption performed by an external device.			
Option	Description									
no	SSL decryption and encryption performed by FortiProxy when deep-inspection is enabled.									
yes	SSL decryption and encryption performed by an external device.									
explicit-ftp-tls	Enable/disable deep inspection of FTP control session over STARTTLS.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable setting.</td></tr><tr><td>disable</td><td>Disable setting.</td></tr></table>	Option	Description	enable	Enable setting.	disable	Disable setting.			
Option	Description									
enable	Enable setting.									
disable	Disable setting.									

config imap

Parameter	Description	Type	Size	Default
ports	Ports to scan for content (1 - 65535, default = 143).	integer	Minimum value: 1 Maximum value: 65535	
status	Enable/disable the active status of scanning for this protocol.	option	-	enable
	Option	Description		
	enable	Enable setting.		
	disable	Disable setting.		
options	One or more options that can be applied to the session.	option	-	

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>fragmail</i>	Pass fragmented email.		
	<i>oversize</i>	Block oversized email.		
oversize-limit	Maximum in-memory file size that can be scanned (MB).	integer	Minimum value: 1 Maximum value: 4095	10
uncompressed-oversize-limit	Maximum in-memory uncompressed file size that can be scanned.	integer	Minimum value: 1 Maximum value: 4095	10
uncompressed-nest-limit	Maximum nested levels of compression that can be uncompressed and scanned (2 - 100, default = 12).	integer	Minimum value: 2 Maximum value: 100	12
scan-bzip2	Enable/disable scanning of BZip2 compressed files.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
ssl-offloaded	SSL decryption and encryption performed by an external device.	option	-	no
	Option	Description		
	<i>no</i>	SSL decryption and encryption performed by FortiProxy when deep-inspection is enabled.		
	<i>yes</i>	SSL decryption and encryption performed by an external device.		
address-ip-rating	Enable/disable IP based URL rating.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

config mapi

Parameter	Description	Type	Size	Default
ports	Ports to scan for content (1 - 65535, default = 135).	integer	Minimum value: 1 Maximum value: 65535	
status	Enable/disable the active status of scanning for this protocol.	option	-	enable
	Option Description			
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
options	One or more options that can be applied to the session.	option	-	
	Option Description			
	<i>fragmail</i>	Pass fragmented email.		
	<i>oversize</i>	Block oversized email.		
oversize-limit	Maximum in-memory file size that can be scanned (MB).	integer	Minimum value: 1 Maximum value: 4095	10
uncompressed-oversize-limit	Maximum in-memory uncompressed file size that can be scanned.	integer	Minimum value: 1 Maximum value: 4095	10
uncompressed-nest-limit	Maximum nested levels of compression that can be uncompressed and scanned (2 - 100, default = 12).	integer	Minimum value: 2 Maximum value: 100	12
scan-bzip2	Enable/disable scanning of BZip2 compressed files.	option	-	enable
	Option Description			
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

config pop3

Parameter	Description	Type	Size	Default
ports	Ports to scan for content (1 - 65535, default = 110).	integer	Minimum value: 1 Maximum value: 65535	
status	Enable/disable the active status of scanning for this protocol.	option	-	enable
	Option Description			
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
options	One or more options that can be applied to the session.	option	-	
	Option Description			
	<i>fragmail</i>	Pass fragmented email.		
	<i>oversize</i>	Block oversized email.		
oversize-limit	Maximum in-memory file size that can be scanned (MB).	integer	Minimum value: 1 Maximum value: 4095	10
uncompressed-oversize-limit	Maximum in-memory uncompressed file size that can be scanned.	integer	Minimum value: 1 Maximum value: 4095	10
uncompressed-nest-limit	Maximum nested levels of compression that can be uncompressed and scanned (2 - 100, default = 12).	integer	Minimum value: 2 Maximum value: 100	12
scan-bzip2	Enable/disable scanning of BZip2 compressed files.	option	-	enable
	Option Description			
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

Parameter	Description	Type	Size	Default
ssl-offloaded	SSL decryption and encryption performed by an external device.	option	-	no
	Option Description			
	<i>no</i>	SSL decryption and encryption performed by FortiProxy when deep-inspection is enabled.		
	<i>yes</i>	SSL decryption and encryption performed by an external device.		

config smtp

Parameter	Description	Type	Size	Default
ports	Ports to scan for content (1 - 65535, default = 25).	integer	Minimum value: 1 Maximum value: 65535	
status	Enable/disable the active status of scanning for this protocol.	option	-	enable
	Option Description			
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
options	One or more options that can be applied to the session.	option	-	
	Option Description			
	<i>fragmail</i>	Pass fragmented email.		
	<i>oversize</i>	Block oversized email.		
	<i>splice</i>	Enable splice mode.		
oversize-limit	Maximum in-memory file size that can be scanned (MB).	integer	Minimum value: 1 Maximum value: 4095	10
uncompressed-oversize-limit	Maximum in-memory uncompressed file size that can be scanned.	integer	Minimum value: 1 Maximum value: 4095	10

Parameter	Description	Type	Size	Default						
uncompressed-nest-limit	Maximum nested levels of compression that can be uncompressed and scanned (2 - 100, default = 12).	integer	Minimum value: 2 Maximum value: 100	12						
scan-bzip2	Enable/disable scanning of BZip2 compressed files.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
server-busy	Enable/disable SMTP server busy when server not available.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
ssl-offloaded	SSL decryption and encryption performed by an external device.	option	-	no						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>no</i></td><td>SSL decryption and encryption performed by FortiProxy when deep-inspection is enabled.</td></tr><tr><td><i>yes</i></td><td>SSL decryption and encryption performed by an external device.</td></tr></table>	Option	Description	<i>no</i>	SSL decryption and encryption performed by FortiProxy when deep-inspection is enabled.	<i>yes</i>	SSL decryption and encryption performed by an external device.			
Option	Description									
<i>no</i>	SSL decryption and encryption performed by FortiProxy when deep-inspection is enabled.									
<i>yes</i>	SSL decryption and encryption performed by an external device.									

config nntp

Parameter	Description	Type	Size	Default						
ports	Ports to scan for content (1 - 65535, default = 119).	integer	Minimum value: 1 Maximum value: 65535							
status	Enable/disable the active status of scanning for this protocol.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>				Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									

Parameter	Description	Type	Size	Default						
options	One or more options that can be applied to the session.	option	-							
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>oversize</i></td><td>Block oversized file.</td></tr><tr><td><i>splice</i></td><td>Enable splice mode.</td></tr></table>				Option	Description	<i>oversize</i>	Block oversized file.	<i>splice</i>	Enable splice mode.
	Option	Description								
	<i>oversize</i>	Block oversized file.								
<i>splice</i>	Enable splice mode.									
oversize-limit	Maximum in-memory file size that can be scanned (MB).	integer	Minimum value: 1 Maximum value: 4095	10						
uncompressed-oversize-limit	Maximum in-memory uncompressed file size that can be scanned.	integer	Minimum value: 1 Maximum value: 4095	10						
uncompressed-nest-limit	Maximum nested levels of compression that can be uncompressed and scanned (2 - 100, default = 12).	integer	Minimum value: 2 Maximum value: 100	12						
scan-bzip2	Enable/disable scanning of BZip2 compressed files.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>				Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.
	Option	Description								
	<i>enable</i>	Enable setting.								
<i>disable</i>	Disable setting.									

config ssh

Parameter	Description	Type	Size	Default								
options	One or more options that can be applied to the session.	option	-									
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>oversize</i></td><td>Block oversized file.</td></tr><tr><td><i>clientcomfort</i></td><td>Prevent client timeout.</td></tr><tr><td><i>servercomfort</i></td><td>Prevent server timeout.</td></tr></table>	Option	Description	<i>oversize</i>	Block oversized file.	<i>clientcomfort</i>	Prevent client timeout.	<i>servercomfort</i>	Prevent server timeout.			
Option	Description											
<i>oversize</i>	Block oversized file.											
<i>clientcomfort</i>	Prevent client timeout.											
<i>servercomfort</i>	Prevent server timeout.											

Parameter	Description	Type	Size	Default								
comfort-interval	Interval between successive transmissions of data for client comforting (seconds).	integer	Minimum value: 1 Maximum value: 900	10								
comfort-amount	Number of bytes to send in each transmission for client comforting (bytes).	integer	Minimum value: 1 Maximum value: 65535	1								
oversize-limit	Maximum in-memory file size that can be scanned (MB).	integer	Minimum value: 1 Maximum value: 4095	10								
uncompressed-oversize-limit	Maximum in-memory uncompressed file size that can be scanned.	integer	Minimum value: 1 Maximum value: 4095	10								
uncompressed-nest-limit	Maximum nested levels of compression that can be uncompressed and scanned (2 - 100, default = 12).	integer	Minimum value: 2 Maximum value: 100	12								
stream-based-uncompressed-limit	Maximum stream-based uncompressed data size that will be scanned in megabytes. Stream-based uncompression used only under certain conditions (unlimited = 0, default = 0).	integer	Minimum value: 0 Maximum value: 4294967295	0								
scan-bzip2	Enable/disable scanning of BZip2 compressed files.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable setting.</td></tr><tr><td>disable</td><td>Disable setting.</td></tr></table>				Option	Description	enable	Enable setting.	disable	Disable setting.		
Option	Description											
enable	Enable setting.											
disable	Disable setting.											
tcp-window-type	TCP window type to use for this protocol.	option	-	auto-tuning								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>auto-tuning</td><td>Allow system to auto-tune TCP window size (default).</td></tr><tr><td>system</td><td>Use system default TCP window size for this protocol.</td></tr><tr><td>static</td><td>Manually specify TCP window size.</td></tr></table>				Option	Description	auto-tuning	Allow system to auto-tune TCP window size (default).	system	Use system default TCP window size for this protocol.	static	Manually specify TCP window size.
Option	Description											
auto-tuning	Allow system to auto-tune TCP window size (default).											
system	Use system default TCP window size for this protocol.											
static	Manually specify TCP window size.											

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>dynamic</i></td><td>Vary TCP window size based on available memory and within limits of tcp-window-minimum and tcp-window-maximum.</td></tr></table>	Option	Description	<i>dynamic</i>	Vary TCP window size based on available memory and within limits of tcp-window-minimum and tcp-window-maximum.					
	Option	Description								
<i>dynamic</i>	Vary TCP window size based on available memory and within limits of tcp-window-minimum and tcp-window-maximum.									
tcp-window-minimum	Minimum dynamic TCP window size.	integer	Minimum value: 65536 Maximum value: 1048576	131072						
tcp-window-maximum	Maximum dynamic TCP window size.	integer	Minimum value: 1048576 Maximum value: 33554432	8388608						
tcp-window-size	Set TCP static window size.	integer	Minimum value: 65536 Maximum value: 33554432	262144						
ssl-offloaded	SSL decryption and encryption performed by an external device.	option	-	no						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>no</i></td><td>SSL decryption and encryption performed by FortiProxy when deep-inspection is enabled.</td></tr><tr><td><i>yes</i></td><td>SSL decryption and encryption performed by an external device.</td></tr></table>	Option	Description	<i>no</i>	SSL decryption and encryption performed by FortiProxy when deep-inspection is enabled.	<i>yes</i>	SSL decryption and encryption performed by an external device.			
	Option	Description								
<i>no</i>	SSL decryption and encryption performed by FortiProxy when deep-inspection is enabled.									
<i>yes</i>	SSL decryption and encryption performed by an external device.									

config dns

Parameter	Description	Type	Size	Default
ports	Ports to scan for content (1 - 65535, default = 53).	integer	Minimum value: 1 Maximum value: 65535	
status	Enable/disable the active status of scanning for this protocol.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

config cifs

Parameter	Description	Type	Size	Default
ports	Ports to scan for content (1 - 65535, default = 445).	integer	Minimum value: 1 Maximum value: 65535	
status	Enable/disable the active status of scanning for this protocol.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
options	One or more options that can be applied to the session.	option	-	
	Option	Description		
	<i>oversize</i>	Block oversized file.		
oversize-limit	Maximum in-memory file size that can be scanned (MB).	integer	Minimum value: 1 Maximum value: 4095	10
uncompressed-oversize-limit	Maximum in-memory uncompressed file size that can be scanned.	integer	Minimum value: 1 Maximum value: 4095	10
uncompressed-nest-limit	Maximum nested levels of compression that can be uncompressed and scanned (2 - 100, default = 12).	integer	Minimum value: 2 Maximum value: 100	12
scan-bzip2	Enable/disable scanning of BZip2 compressed files.	option	-	enable

Parameter	Description	Type	Size	Default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.							
	Option	Description												
	<i>enable</i>	Enable setting.												
<i>disable</i>	Disable setting.													
tcp-window-type	TCP window type to use for this protocol.	option	-	auto-tuning										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto-tuning</i></td><td>Allow system to auto-tune TCP window size (default).</td></tr><tr><td><i>system</i></td><td>Use system default TCP window size for this protocol.</td></tr><tr><td><i>static</i></td><td>Manually specify TCP window size.</td></tr><tr><td><i>dynamic</i></td><td>Vary TCP window size based on available memory and within limits of tcp-window-minimum and tcp-window-maximum.</td></tr></table>	Option	Description	<i>auto-tuning</i>	Allow system to auto-tune TCP window size (default).	<i>system</i>	Use system default TCP window size for this protocol.	<i>static</i>	Manually specify TCP window size.	<i>dynamic</i>	Vary TCP window size based on available memory and within limits of tcp-window-minimum and tcp-window-maximum.			
	Option	Description												
	<i>auto-tuning</i>	Allow system to auto-tune TCP window size (default).												
	<i>system</i>	Use system default TCP window size for this protocol.												
	<i>static</i>	Manually specify TCP window size.												
<i>dynamic</i>	Vary TCP window size based on available memory and within limits of tcp-window-minimum and tcp-window-maximum.													
tcp-window-minimum	Minimum dynamic TCP window size.	integer	Minimum value: 65536 Maximum value: 1048576	131072										
tcp-window-maximum	Maximum dynamic TCP window size.	integer	Minimum value: 1048576 Maximum value: 33554432	8388608										
tcp-window-size	Set TCP static window size.	integer	Minimum value: 65536 Maximum value: 33554432	262144										
server-credential-type	CIFS server credential type.	option	-	none										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>none</i></td><td>Credential derivation not set.</td></tr><tr><td><i>credential-replication</i></td><td>Credential derived using Replication account on Domain Controller.</td></tr></table>	Option	Description	<i>none</i>	Credential derivation not set.	<i>credential-replication</i>	Credential derived using Replication account on Domain Controller.							
	Option	Description												
	<i>none</i>	Credential derivation not set.												
<i>credential-replication</i>	Credential derived using Replication account on Domain Controller.													

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>credential-keytab</i>	Credential derived using server keytab.		
domain-controller	Domain for which to decrypt CIFS traffic.	string	Maximum length: 63	

config server-keytab

Parameter	Description	Type	Size	Default
principal	Service principal. For example, host/cifsserver.example.com@example.com.	string	Maximum length: 511	
keytab	Base64 encoded keytab file containing credential of the server.	string	Maximum length: 8191	

config mail-signature

Parameter	Description	Type	Size	Default
status	Enable/disable adding an email signature to SMTP email messages as they pass through the FortiProxy.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable mail signature.		
	<i>enable</i>	Enable mail signature.		
signature	Email signature to be added to outgoing email (if the signature contains spaces, enclose with quotation marks).	string	Maximum length: 1023	

config firewall proxy-address

Configure web proxy address.

```
config firewall proxy-address
  Description: Configure web proxy address.
  edit <name>
    set uuid {uuid}
    set type [host-regex|url|...]
    set host {string}
```



```

set host-regex {string}
set path {string}
set query {string}
set referrer [enable|disable]
set post-arg [enable|disable]
set category <id1>, <id2>, ...
set url-list {string}
set method {option1}, {option2}, ...
set ua {option1}, {option2}, ...
set ua-min-ver {string}
set ua-max-ver {string}
set header-name {string}
set header {string}
set case-sensitivity [disable|enable]
config header-group
    Description: HTTP header group.
    edit <id>
        set header-name {string}
        set header {string}
        set case-sensitivity [disable|enable]
    next
end
set color {integer}
config tagging
    Description: Config object tagging.
    edit <name>
        set category {string}
        set tags <name1>, <name2>, ...
    next
end
set comment {var-string}
set application <name1>, <name2>, ...
next
end

```

config firewall proxy-address

Parameter	Description	Type	Size	Default
name	Address name.	string	Maximum length: 79	
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000
type	Proxy address type.	option	-	url

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>host-regex</i>	Host regular expression.		
	<i>url</i>	HTTP URL.		
	<i>category</i>	FortiGuard URL catgeory.		
	<i>url-list</i>	HTTP URL list from external resource or Web filter URL list.		
	<i>method</i>	HTTP request method.		
	<i>ua</i>	HTTP request user agent.		
	<i>header</i>	HTTP request header.		
	<i>src-advanced</i>	HTTP advanced source criteria.		
	<i>dst-advanced</i>	HTTP advanced destination criteria.		
	<i>saas</i>	SaaS application.		
	<i>response-header</i>	HTTP response header.		
	host	Address object for the host.	string	Maximum length: 79
host-regex	Host name as a regular expression.	string	Maximum length: 255	
path	URL path as a regular expression.	string	Maximum length: 255	
query	Match the query part of the URL as a regular expression.	string	Maximum length: 255	
referrer	Enable/disable use of referrer field in the HTTP header to match the address.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
post-arg	Enable/disable use of body in the HTTP POST to match the query.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

Parameter	Description	Type	Size	Default																		
category <id>	FortiGuard category ID. FortiGuard category ID.	integer	Minimum value: 0 Maximum value: 4294967295																			
url-list	External or Web filter URL list.	string	Maximum length: 35																			
method	HTTP request methods to be used.	option	-																			
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>get</i></td><td>GET method.</td></tr><tr><td><i>post</i></td><td>POST method.</td></tr><tr><td><i>put</i></td><td>PUT method.</td></tr><tr><td><i>head</i></td><td>HEAD method.</td></tr><tr><td><i>connect</i></td><td>CONNECT method.</td></tr><tr><td><i>trace</i></td><td>TRACE method.</td></tr><tr><td><i>options</i></td><td>OPTIONS method.</td></tr><tr><td><i>delete</i></td><td>DELETE method.</td></tr></table>	Option	Description	<i>get</i>	GET method.	<i>post</i>	POST method.	<i>put</i>	PUT method.	<i>head</i>	HEAD method.	<i>connect</i>	CONNECT method.	<i>trace</i>	TRACE method.	<i>options</i>	OPTIONS method.	<i>delete</i>	DELETE method.			
Option	Description																					
<i>get</i>	GET method.																					
<i>post</i>	POST method.																					
<i>put</i>	PUT method.																					
<i>head</i>	HEAD method.																					
<i>connect</i>	CONNECT method.																					
<i>trace</i>	TRACE method.																					
<i>options</i>	OPTIONS method.																					
<i>delete</i>	DELETE method.																					
ua	Names of browsers to be used as user agent.	option	-																			
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>chrome</i></td><td>Google Chrome.</td></tr><tr><td><i>ms</i></td><td>Microsoft Internet Explorer or EDGE.</td></tr><tr><td><i>firefox</i></td><td>Mozilla Firefox.</td></tr><tr><td><i>safari</i></td><td>Apple Safari.</td></tr><tr><td><i>ie</i></td><td>Microsoft Internet Explorer.</td></tr><tr><td><i>edge</i></td><td>Microsoft Edge.</td></tr><tr><td><i>other</i></td><td>Other browsers.</td></tr></table>	Option	Description	<i>chrome</i>	Google Chrome.	<i>ms</i>	Microsoft Internet Explorer or EDGE.	<i>firefox</i>	Mozilla Firefox.	<i>safari</i>	Apple Safari.	<i>ie</i>	Microsoft Internet Explorer.	<i>edge</i>	Microsoft Edge.	<i>other</i>	Other browsers.					
Option	Description																					
<i>chrome</i>	Google Chrome.																					
<i>ms</i>	Microsoft Internet Explorer or EDGE.																					
<i>firefox</i>	Mozilla Firefox.																					
<i>safari</i>	Apple Safari.																					
<i>ie</i>	Microsoft Internet Explorer.																					
<i>edge</i>	Microsoft Edge.																					
<i>other</i>	Other browsers.																					
ua-min-ver	Minimum version of the user agent specified in dotted notation. For example, use 90.0.1 with the ua field set to "chrome" to require Google Chrome's minimum version must be 90.0.1.	string	Maximum length: 63																			

Parameter	Description	Type	Size	Default
ua-max-ver	Maximum version of the user agent specified in dotted notation. For example, use 120 with the ua field set to "chrome" to require Google Chrome's maximum version must be 120.	string	Maximum length: 63	
header-name	Name of HTTP header.	string	Maximum length: 79	
header	HTTP header name as a regular expression.	string	Maximum length: 255	
case-sensitivity	Enable to make the pattern case sensitive.	option	-	disable
	Option		Description	
	<i>disable</i>		Case insensitive in pattern.	
	<i>enable</i>		Case sensitive in pattern.	
color	Integer value to determine the color of the icon in the GUI (1 - 32, default = 0, which sets value to 1).	integer	Minimum value: 0 Maximum value: 32	0
comment	Optional comments.	var-string	Maximum length: 255	
application <name>	SaaS application. SaaS application name.	string	Maximum length: 79	

config header-group

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
header-name	HTTP header.	string	Maximum length: 79	
header	HTTP header regular expression.	string	Maximum length: 255	
case-sensitivity	Case sensitivity in pattern.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Case insensitive in pattern.		
	<i>enable</i>	Case sensitive in pattern.		

config tagging

Parameter	Description	Type	Size	Default
name	Tagging entry name.	string	Maximum length: 63	
category	Tag category.	string	Maximum length: 63	
tags <name>	Tags. Tag name.	string	Maximum length: 79	

config firewall proxy-address6

Configure web proxy address6.

```

config firewall proxy-address6
  Description: Configure web proxy address6.
  edit <name>
    set uuid {uuid}
    set type [host-regex|url|...]
    set host {string}
    set host-regex {string}
    set path {string}
    set query {string}
    set referrer [enable|disable]
    set post-arg [enable|disable]
    set category <id1>, <id2>, ...
    set url-list {string}
    set method {option1}, {option2}, ...
    set ua {option1}, {option2}, ...
    set ua-min-ver {string}
    set ua-max-ver {string}
    set header-name {string}
    set header {string}
    set case-sensitivity [disable|enable]
  config header-group
    Description: HTTP header group.
    edit <id>
      set header-name {string}
      set header {string}

```

```

        set case-sensitivity [disable|enable]
    next
end
set color {integer}
config tagging
    Description: Config object tagging.
    edit <name>
        set category {string}
        set tags <name1>, <name2>, ...
    next
end
set comment {var-string}
set application <name1>, <name2>, ...
next
end

```

config firewall proxy-address6

Parameter	Description	Type	Size	Default																								
name	Address6 name.	string	Maximum length: 79																									
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000																								
type	Proxy address6 type.	option	-	url																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>host-regex</td><td>Host regular expression.</td></tr><tr><td>url</td><td>HTTP URL.</td></tr><tr><td>category</td><td>FortiGuard URL category.</td></tr><tr><td>url-list</td><td>HTTP URL list from external resource or Web filter URL list.</td></tr><tr><td>method</td><td>HTTP request method.</td></tr><tr><td>ua</td><td>HTTP request user agent.</td></tr><tr><td>header</td><td>HTTP request header.</td></tr><tr><td>src-advanced</td><td>HTTP advanced source criteria.</td></tr><tr><td>dst-advanced</td><td>HTTP advanced destination criteria.</td></tr><tr><td>saas</td><td>SaaS application.</td></tr><tr><td>response-header</td><td>HTTP response header.</td></tr></table>				Option	Description	host-regex	Host regular expression.	url	HTTP URL.	category	FortiGuard URL category.	url-list	HTTP URL list from external resource or Web filter URL list.	method	HTTP request method.	ua	HTTP request user agent.	header	HTTP request header.	src-advanced	HTTP advanced source criteria.	dst-advanced	HTTP advanced destination criteria.	saas	SaaS application.	response-header	HTTP response header.
Option	Description																											
host-regex	Host regular expression.																											
url	HTTP URL.																											
category	FortiGuard URL category.																											
url-list	HTTP URL list from external resource or Web filter URL list.																											
method	HTTP request method.																											
ua	HTTP request user agent.																											
header	HTTP request header.																											
src-advanced	HTTP advanced source criteria.																											
dst-advanced	HTTP advanced destination criteria.																											
saas	SaaS application.																											
response-header	HTTP response header.																											

Parameter	Description	Type	Size	Default												
host	Address6 object for the host.	string	Maximum length: 79													
host-regex	Host name as a regular expression.	string	Maximum length: 255													
path	URL path as a regular expression.	string	Maximum length: 255													
query	Match the query part of the URL as a regular expression.	string	Maximum length: 255													
referrer	Enable/disable use of referrer field in the HTTP header to match the address.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>				Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.						
Option	Description															
<i>enable</i>	Enable setting.															
<i>disable</i>	Disable setting.															
post-arg	Enable/disable use of body in the HTTP POST to match the query.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>				Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.						
Option	Description															
<i>enable</i>	Enable setting.															
<i>disable</i>	Disable setting.															
category <id>	FortiGuard category ID. FortiGuard category ID.	integer	Minimum value: 0 Maximum value: 4294967295													
url-list	External or Web filter URL list.	string	Maximum length: 35													
method	HTTP request methods to be used.	option	-													
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>get</i></td><td>GET method.</td></tr><tr><td><i>post</i></td><td>POST method.</td></tr><tr><td><i>put</i></td><td>PUT method.</td></tr><tr><td><i>head</i></td><td>HEAD method.</td></tr><tr><td><i>connect</i></td><td>CONNECT method.</td></tr></table>				Option	Description	<i>get</i>	GET method.	<i>post</i>	POST method.	<i>put</i>	PUT method.	<i>head</i>	HEAD method.	<i>connect</i>	CONNECT method.
Option	Description															
<i>get</i>	GET method.															
<i>post</i>	POST method.															
<i>put</i>	PUT method.															
<i>head</i>	HEAD method.															
<i>connect</i>	CONNECT method.															

Parameter	Description	Type	Size	Default																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>trace</i></td><td>TRACE method.</td></tr><tr><td><i>options</i></td><td>OPTIONS method.</td></tr><tr><td><i>delete</i></td><td>DELETE method.</td></tr></table>	Option	Description	<i>trace</i>	TRACE method.	<i>options</i>	OPTIONS method.	<i>delete</i>	DELETE method.											
	Option	Description																		
	<i>trace</i>	TRACE method.																		
	<i>options</i>	OPTIONS method.																		
	<i>delete</i>	DELETE method.																		
ua	Names of browsers to be used as user agent.	option	-																	
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>chrome</i></td><td>Google Chrome.</td></tr><tr><td><i>ms</i></td><td>Microsoft Internet Explorer or EDGE.</td></tr><tr><td><i>firefox</i></td><td>Mozilla Firefox.</td></tr><tr><td><i>safari</i></td><td>Apple Safari.</td></tr><tr><td><i>ie</i></td><td>Microsoft Internet Explorer.</td></tr><tr><td><i>edge</i></td><td>Microsoft Edge.</td></tr><tr><td><i>other</i></td><td>Other browsers.</td></tr></table>	Option	Description	<i>chrome</i>	Google Chrome.	<i>ms</i>	Microsoft Internet Explorer or EDGE.	<i>firefox</i>	Mozilla Firefox.	<i>safari</i>	Apple Safari.	<i>ie</i>	Microsoft Internet Explorer.	<i>edge</i>	Microsoft Edge.	<i>other</i>	Other browsers.			
	Option	Description																		
	<i>chrome</i>	Google Chrome.																		
	<i>ms</i>	Microsoft Internet Explorer or EDGE.																		
	<i>firefox</i>	Mozilla Firefox.																		
	<i>safari</i>	Apple Safari.																		
	<i>ie</i>	Microsoft Internet Explorer.																		
	<i>edge</i>	Microsoft Edge.																		
<i>other</i>	Other browsers.																			
ua-min-ver	Minimum version of the user agent specified in dotted notation. For example, use 90.0.1 with the ua field set to "chrome" to require Google Chrome's minimum version must be 90.0.1.	string	Maximum length: 63																	
ua-max-ver	Maximum version of the user agent specified in dotted notation. For example, use 120 with the ua field set to "chrome" to require Google Chrome's maximum version must be 120.	string	Maximum length: 63																	
header-name	Name of HTTP header.	string	Maximum length: 79																	
header	HTTP header name as a regular expression.	string	Maximum length: 255																	
case-sensitivity	Enable to make the pattern case sensitive.	option	-	disable																

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Case insensitive in pattern.		
	<i>enable</i>	Case sensitive in pattern.		
color	Integer value to determine the color of the icon in the GUI (1 - 32, default = 0, which sets value to 1).	integer	Minimum value: 0 Maximum value: 32	0
comment	Optional comments.	var-string	Maximum length: 255	
application <name>	SaaS application. SaaS application name.	string	Maximum length: 79	

config header-group

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
header-name	HTTP header.	string	Maximum length: 79	
header	HTTP header regular expression.	string	Maximum length: 255	
case-sensitivity	Case sensitivity in pattern.	option	-	disable
	Option	Description		
	disable	Case insensitive in pattern.		
	enable	Case sensitive in pattern.		

config tagging

Parameter	Description	Type	Size	Default
name	Tagging entry name.	string	Maximum length: 63	

Parameter	Description	Type	Size	Default
category	Tag category.	string	Maximum length: 63	
tags <name>	Tags. Tag name.	string	Maximum length: 79	

config firewall proxy-addrgrp

Configure web proxy address group.

```
config firewall proxy-addrgrp
  Description: Configure web proxy address group.
  edit <name>
    set type [src|dst]
    set uuid {uuid}
    set member <name1>, <name2>, ...
    set color {integer}
    config tagging
      Description: Config object tagging.
      edit <name>
        set category {string}
        set tags <name1>, <name2>, ...
      next
    end
    set comment {var-string}
  next
end
```

config firewall proxy-addrgrp

Parameter	Description	Type	Size	Default						
name	Address group name.	string	Maximum length: 79							
type	Source or destination address group type.	option	-	src						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>src</td><td>Source group.</td></tr><tr><td>dst</td><td>Destination group.</td></tr></table>				Option	Description	src	Source group.	dst	Destination group.
	Option	Description								
	src	Source group.								
dst	Destination group.									
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000						

Parameter	Description	Type	Size	Default
member <name>	Members of address group. Address name.	string	Maximum length: 79	
color	Integer value to determine the color of the icon in the GUI (1 - 32, default = 0, which sets value to 1).	integer	Minimum value: 0 Maximum value: 32	0
comment	Optional comments.	var- string	Maximum length: 255	

config tagging

Parameter	Description	Type	Size	Default
name	Tagging entry name.	string	Maximum length: 63	
category	Tag category.	string	Maximum length: 63	
tags <name>	Tags. Tag name.	string	Maximum length: 79	

config firewall proxy-addrgrp6

Configure web proxy address group6.

```

config firewall proxy-addrgrp6
  Description: Configure web proxy address group6.
  edit <name>
    set type [src|dst]
    set uuid {uuid}
    set member <name1>, <name2>, ...
    set color {integer}
    config tagging
      Description: Config object tagging.
      edit <name>
        set category {string}
        set tags <name1>, <name2>, ...
      next
    end
    set comment {var-string}
  next
end

```

config firewall proxy-addrgrp6

Parameter	Description	Type	Size	Default
name	Address group6.	string	Maximum length: 79	
type	Source or destination address group6 type.	option	-	src
	Option	Description		
	src	Source group.		
	dst	Destination group.		
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000
member <name>	Members of address group6. Address name.	string	Maximum length: 79	
color	Integer value to determine the color of the icon in the GUI (1 - 32, default = 0, which sets value to 1).	integer	Minimum value: 0 Maximum value: 32	0
comment	Optional comments.	var-string	Maximum length: 255	

config tagging

Parameter	Description	Type	Size	Default
name	Tagging entry name.	string	Maximum length: 63	
category	Tag category.	string	Maximum length: 63	
tags <name>	Tags. Tag name.	string	Maximum length: 79	

config firewall region

Define region table.

```
config firewall region
    Description: Define region table.
```

```

edit <id>
    set name {string}
    set city <id1>, <id2>, ...
next
end

```

config firewall region

Parameter	Description	Type	Size	Default
id	Region ID.	integer	Minimum value: 0 Maximum value: 65535	0
name	Region name.	string	Maximum length: 63	
city <id>	City ID list. City ID.	integer	Minimum value: 0 Maximum value: 65535	

config firewall response-shaping-policy

Configure HTTP response matching shaping policies.

```

config firewall response-shaping-policy
    Description: Configure HTTP response matching shaping policies.
    edit <id>
        set uuid {uuid}
        set name {string}
        set schedule {string}
        set comment {var-string}
        set status [enable|disable]
        set ip-version [4|6]
        set srcaddr <name1>, <name2>, ...
        set dstaddr <name1>, <name2>, ...
        set dstaddr6 <name1>, <name2>, ...
        set traffic-shaper {string}
        set traffic-shaper-reverse {string}
        set per-ip-shaper {string}
        set class-id {integer}
        set class-id-reverse {integer}
        set diffserv-forward [enable|disable]
        set diffservcode-forward {user}
    
```

```

set diffserv-reverse [enable|disable]
set diffservcode-rev {user}
set matched-shaping-policies {integer}
next
end

```

config firewall response-shaping-policy

Parameter	Description	Type	Size	Default
id	Response shaping policy ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000
name	Response shaping policy name.	string	Maximum length: 35	
schedule	Schedule name.	string	Maximum length: 35	always
comment	Comments.	var-string	Maximum length: 255	
status	Enable/disable response traffic shaping policy.	option	-	enable
	Option		Description	
	<i>enable</i>		Enable traffic shaping policy.	
	<i>disable</i>		Disable traffic shaping policy.	
ip-version	IP version.	option	-	4
	Option		Description	
	4		Use IPv4 addressing for Configuration Method.	
	6		Use IPv6 addressing for Configuration Method.	
srcaddr <name>	Source address. Address name.	string	Maximum length: 79	
dstaddr <name>	Destination address. Address name.	string	Maximum length: 79	

Parameter	Description	Type	Size	Default						
dstaddr6 <name>	IPv6 destination address. Address name.	string	Maximum length: 79							
traffic-shaper	Forward traffic shaper.	string	Maximum length: 35							
traffic-shaper- reverse	Reverse traffic shaper.	string	Maximum length: 35							
per-ip-shaper	Per IP shaper.	string	Maximum length: 35							
class-id	Forward class id.	integer	Minimum value: 2 Maximum value: 31	0						
class-id- reverse	Reverse class id.	integer	Minimum value: 2 Maximum value: 31	0						
diffserv- forward	Enable/disable forward (original) traffic DiffServ.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>				Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
diffservcode- forward	Forward (original) traffic DiffServ code point value.	user	Not Specified							
diffserv- reverse	Enable/disable reverse (reply) traffic DiffServ.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>				Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
diffservcode- rev	Reverse (reply) traffic DiffServ code point value.	user	Not Specified							
matched- shaping- policies	Matched shaping policies.	integer	Minimum value: 0 Maximum value: 4294967295							

config firewall schedule group

Schedule group configuration.

```
config firewall schedule group
  Description: Schedule group configuration.
  edit <name>
    set member <name1>, <name2>, ...
    set color {integer}
    set fabric-object [enable|disable]
  next
end
```

config firewall schedule group

Parameter	Description	Type	Size	Default
name	Schedule group name.	string	Maximum length: 31	
member <name>	Schedules added to the schedule group. Schedule name.	string	Maximum length: 79	
color	Color of icon on the GUI.	integer	Minimum value: 0 Maximum value: 32	0
fabric-object	Security Fabric global object setting.	option	-	disable
		Option	Description	
		<i>enable</i>	Object is set as a security fabric-wide global object.	
		<i>disable</i>	Object is local to this security fabric member.	

config firewall schedule onetime

Onetime schedule configuration.

```
config firewall schedule onetime
  Description: Onetime schedule configuration.
  edit <name>
    set start {user}
    set start-utc {user}
    set end {user}
    set end-utc {user}
```



```

        set color {integer}
        set expiration-days {integer}
        set fabric-object [enable|disable]
    next
end

```

config firewall schedule onetime

Parameter	Description	Type	Size	Default
name	Onetime schedule name.	string	Maximum length: 31	
start	Schedule start date and time, format hh:mm yyyy/mm/dd.	user	Not Specified	
start-utc	Schedule start date and time, in epoch format.	user	Not Specified	
end	Schedule end date and time, format hh:mm yyyy/mm/dd.	user	Not Specified	
end-utc	Schedule end date and time, in epoch format.	user	Not Specified	
color	Color of icon on the GUI.	integer	Minimum value: 0 Maximum value: 32	0
expiration-days	Write an event log message this many days before the schedule expires.	integer	Minimum value: 0 Maximum value: 100	3
fabric-object	Security Fabric global object setting.	option	-	disable
		Option	Description	
		<i>enable</i>	Object is set as a security fabric-wide global object.	
		<i>disable</i>	Object is local to this security fabric member.	

config firewall schedule recurring

Recurring schedule configuration.

```

config firewall schedule recurring
    Description: Recurring schedule configuration.
    edit <name>
        set start {user}
    end
end

```

```

    set end {user}
    set day {option1}, {option2}, ...
    set color {integer}
    set fabric-object [enable|disable]
  next
end

```

config firewall schedule recurring

Parameter	Description	Type	Size	Default
name	Recurring schedule name.	string	Maximum length: 31	
start	Time of day to start the schedule, format hh:mm.	user	Not Specified	
end	Time of day to end the schedule, format hh:mm.	user	Not Specified	
day	One or more days of the week on which the schedule is valid. Separate the names of the days with a space.	option	-	none
	Option		Description	
	sunday		Sunday.	
	monday		Monday.	
	tuesday		Tuesday.	
	wednesday		Wednesday.	
	thursday		Thursday.	
	friday		Friday.	
	saturday		Saturday.	
	none		None.	
color	Color of icon on the GUI.	integer	Minimum value: 0 Maximum value: 32	0
fabric-object	Security Fabric global object setting.	option	-	disable
	Option		Description	
	enable		Object is set as a security fabric-wide global object.	
	disable		Object is local to this security fabric member.	

config firewall service category

Configure service categories.

```
config firewall service category
  Description: Configure service categories.
  edit <name>
    set comment {var-string}
    set fabric-object [enable|disable]
  next
end
```

config firewall service category

Parameter	Description	Type	Size	Default
name	Service category name.	string	Maximum length: 63	
comment	Comment.	var-string	Maximum length: 255	
fabric-object	Security Fabric global object setting.	option	-	disable
		Option	Description	
		<i>enable</i>	Object is set as a security fabric-wide global object.	
		<i>disable</i>	Object is local to this security fabric member.	

config firewall service custom

Configure custom services.

```
config firewall service custom
  Description: Configure custom services.
  edit <name>
    set proxy [enable|disable]
    set category {string}
    set protocol [TCP/UDP/SCTP/ICMP|...]
    set iprange {user}
    set fqdn {string}
    set protocol-number {integer}
    set icmptype {integer}
    set icmpcode {integer}
    set tcp-portrange {user}
    set udp-portrange {user}
```

```

set sctp-portrange {user}
set tcp-halfclose-timer {integer}
set tcp-halfopen-timer {integer}
set tcp-timewait-timer {integer}
set tcp-rst-timer {integer}
set udp-idle-timer {integer}
set session-ttl {user}
set check-reset-range [disable|strict|...]
set comment {var-string}
set color {integer}
set app-service-type [disable|app-id|...]
set app-category <id1>, <id2>, ...
set application <id1>, <id2>, ...
set fabric-object [enable|disable]
next
end

```

config firewall service custom

Parameter	Description	Type	Size	Default
name	Custom service name.	string	Maximum length: 79	
proxy	Enable/disable web proxy service.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
category	Service category.	string	Maximum length: 63	
protocol	Protocol type based on IANA numbers.	option	-	TCP/UDP/SCTP
	Option	Description		
	<i>TCP/UDP/SCTP</i>	TCP, UDP and SCTP.		
	<i>ICMP</i>	ICMP.		
	<i>ICMP6</i>	ICMP6.		
	<i>IP</i>	IP.		
	<i>HTTP</i>	HTTP - for web proxy.		
	<i>FTP</i>	FTP - for web proxy.		
	<i>CONNECT</i>	Connect - for web proxy.		

Parameter	Description	Type	Size	Default
	Option	Description		
	SOCKS-TCP	Socks TCP - for web proxy.		
	SOCKS-UDP	Socks UDP - for web proxy.		
	ALL	All - for web proxy.		
iprange	Start and end of the IP range associated with service.	user	Not Specified	
fqdn	Fully qualified domain name.	string	Maximum length: 255	
protocol-number	IP protocol number.	integer	Minimum value: 0 Maximum value: 254	0
icmptype	ICMP type.	integer	Minimum value: 0 Maximum value: 4294967295	
icmpcode	ICMP code.	integer	Minimum value: 0 Maximum value: 255	
tcp-portrange	Multiple TCP port ranges.	user	Not Specified	
udp-portrange	Multiple UDP port ranges.	user	Not Specified	
sctp-portrange	Multiple SCTP port ranges.	user	Not Specified	
tcp-halfclose-timer	Wait time to close a TCP session waiting for an unanswered FIN packet (1 - 86400 sec, 0 = default).	integer	Minimum value: 0 Maximum value: 86400	0
tcp-halfopen-timer	Wait time to close a TCP session waiting for an unanswered open session packet (1 - 86400 sec, 0 = default).	integer	Minimum value: 0 Maximum value: 86400	0

Parameter	Description	Type	Size	Default								
tcp-timewait-timer	Set the length of the TCP TIME-WAIT state in seconds (1 - 300 sec, 0 = default).	integer	Minimum value: 0 Maximum value: 300	0								
tcp-rst-timer	Set the length of the TCP CLOSE state in seconds (5 - 300 sec, 0 = default).	integer	Minimum value: 5 Maximum value: 300	0								
udp-idle-timer	Number of seconds before an idle UDP connection times out (0 - 86400 sec, 0 = default).	integer	Minimum value: 0 Maximum value: 86400	0								
session-ttl	Session TTL (300 - 2764800, 0 = default).	user	Not Specified									
check-reset-range	Configure the type of ICMP error message verification.	option	-	default								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable RST range check.</td></tr><tr><td><i>strict</i></td><td>Check RST range strictly.</td></tr><tr><td><i>default</i></td><td>Using system default setting.</td></tr></table>				Option	Description	<i>disable</i>	Disable RST range check.	<i>strict</i>	Check RST range strictly.	<i>default</i>	Using system default setting.
	Option	Description										
	<i>disable</i>	Disable RST range check.										
	<i>strict</i>	Check RST range strictly.										
<i>default</i>	Using system default setting.											
comment	Comment.	var-string	Maximum length: 255									
color	Color of icon on the GUI.	integer	Minimum value: 0 Maximum value: 32	0								
app-service-type	Application service type.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable application type.</td></tr><tr><td><i>app-id</i></td><td>Application ID.</td></tr><tr><td><i>app-category</i></td><td>Applicatin category.</td></tr></table>				Option	Description	<i>disable</i>	Disable application type.	<i>app-id</i>	Application ID.	<i>app-category</i>	Applicatin category.
	Option	Description										
	<i>disable</i>	Disable application type.										
	<i>app-id</i>	Application ID.										
<i>app-category</i>	Applicatin category.											
app-category <id>	Application category ID. Application category id.	integer	Minimum value: 0 Maximum value: 4294967295									

Parameter	Description	Type	Size	Default
application <id>	Application ID. Application id.	integer	Minimum value: 0 Maximum value: 4294967295	
fabric-object	Security Fabric global object setting.	option	-	disable
		Option	Description	
		<i>enable</i>	Object is set as a security fabric-wide global object.	
		<i>disable</i>	Object is local to this security fabric member.	

config firewall service group

Configure service groups.

```
config firewall service group
  Description: Configure service groups.
  edit <name>
    set proxy [enable|disable]
    set member <name1>, <name2>, ...
    set comment {var-string}
    set color {integer}
    set fabric-object [enable|disable]
  next
end
```

config firewall service group

Parameter	Description	Type	Size	Default
name	Service group name.	string	Maximum length: 79	
proxy	Enable/disable web proxy service group.	option	-	disable
		Option	Description	
		<i>enable</i>	Enable setting.	
		<i>disable</i>	Disable setting.	
member <name>	Service objects contained within the group. Service or service group name.	string	Maximum length: 79	

Parameter	Description	Type	Size	Default
comment	Comment.	var-string	Maximum length: 255	
color	Color of icon on the GUI.	integer	Minimum value: 0 Maximum value: 32	0
fabric-object	Security Fabric global object setting.	option	-	disable
	Option	Description		
	<i>enable</i>	Object is set as a security fabric-wide global object.		
	<i>disable</i>	Object is local to this security fabric member.		

config firewall shaper per-ip-shaper

Configure per-IP traffic shaper.

```

config firewall shaper per-ip-shaper
  Description: Configure per-IP traffic shaper.
  edit <name>
    set max-bandwidth {integer}
    set bandwidth-unit [kbps|mbps|...]
    set max-concurrent-session {integer}
    set max-concurrent-tcp-session {integer}
    set max-concurrent-udp-session {integer}
    set diffserv-forward [enable|disable]
    set diffserv-reverse [enable|disable]
    set diffservcode-forward {user}
    set diffservcode-rev {user}
  next
end

```

config firewall shaper per-ip-shaper

Parameter	Description	Type	Size	Default
name	Traffic shaper name.	string	Maximum length: 35	

Parameter	Description	Type	Size	Default								
max-bandwidth	Upper bandwidth limit enforced by this shaper (0 - 80000000). 0 means no limit. Units depend on the bandwidth-unit setting.	integer	Minimum value: 0 Maximum value: 80000000	0								
bandwidth-unit	Unit of measurement for maximum bandwidth for this shaper (Kbps, Mbps or Gbps).	option	-	kbps								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>kbps</i></td><td>Kilobits per second.</td></tr><tr><td><i>mbps</i></td><td>Megabits per second.</td></tr><tr><td><i>gbps</i></td><td>Gigabits per second.</td></tr></table>	Option	Description	<i>kbps</i>	Kilobits per second.	<i>mbps</i>	Megabits per second.	<i>gbps</i>	Gigabits per second.			
Option	Description											
<i>kbps</i>	Kilobits per second.											
<i>mbps</i>	Megabits per second.											
<i>gbps</i>	Gigabits per second.											
max-concurrent-session	Maximum number of concurrent sessions allowed by this shaper (0 - 2097000). 0 means no limit.	integer	Minimum value: 0 Maximum value: 2097000	0								
max-concurrent-tcp-session	Maximum number of concurrent TCP sessions allowed by this shaper (0 - 2097000). 0 means no limit.	integer	Minimum value: 0 Maximum value: 2097000	0								
max-concurrent-udp-session	Maximum number of concurrent UDP sessions allowed by this shaper (0 - 2097000). 0 means no limit.	integer	Minimum value: 0 Maximum value: 2097000	0								
diffserv-forward	Enable/disable changing the Forward (original) DiffServ setting applied to traffic accepted by this shaper.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting forward (original) traffic DiffServ.</td></tr><tr><td><i>disable</i></td><td>Disable setting forward (original) traffic DiffServ.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting forward (original) traffic DiffServ.	<i>disable</i>	Disable setting forward (original) traffic DiffServ.					
Option	Description											
<i>enable</i>	Enable setting forward (original) traffic DiffServ.											
<i>disable</i>	Disable setting forward (original) traffic DiffServ.											
diffserv-reverse	Enable/disable changing the Reverse (reply) DiffServ setting applied to traffic accepted by this shaper.	option	-	disable								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable setting reverse (reply) traffic DiffServ.		
	<i>disable</i>	Disable setting reverse (reply) traffic DiffServ.		
diffservcode-forward	Forward (original) DiffServ setting to be applied to traffic accepted by this shaper.	user	Not Specified	
diffservcode-rev	Reverse (reply) DiffServ setting to be applied to traffic accepted by this shaper.	user	Not Specified	

config firewall shaper traffic-shaper

Configure shared traffic shaper.

```
config firewall shaper traffic-shaper
  Description: Configure shared traffic shaper.
  edit <name>
    set guaranteed-bandwidth {integer}
    set maximum-bandwidth {integer}
    set bandwidth-unit [kbps|mbps|...]
    set priority [low|medium|...]
    set per-policy [disable|enable]
    set diffserv [enable|disable]
    set diffservcode {user}
    set dscp-marking-method [multi-stage|static]
    set exceed-bandwidth {integer}
    set exceed-dscp {user}
    set maximum-dscp {user}
    set overhead {integer}
  next
end
```

config firewall shaper traffic-shaper

Parameter	Description	Type	Size	Default
name	Traffic shaper name.	string	Maximum length: 35	
guaranteed-bandwidth	Amount of bandwidth guaranteed for this shaper (0 - 80000000). Units depend on the bandwidth-unit setting.	integer	Minimum value: 0 Maximum value: 80000000	0

Parameter	Description	Type	Size	Default								
maximum-bandwidth	Upper bandwidth limit enforced by this shaper (0 - 800000000). 0 means no limit. Units depend on the bandwidth-unit setting.	integer	Minimum value: 0 Maximum value: 800000000	0								
bandwidth-unit	Unit of measurement for guaranteed and maximum bandwidth for this shaper (Kbps, Mbps or Gbps).	option	-	kbps								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>kbps</i></td><td>Kilobits per second.</td></tr><tr><td><i>mbps</i></td><td>Megabits per second.</td></tr><tr><td><i>gbps</i></td><td>Gigabits per second.</td></tr></table>	Option	Description	<i>kbps</i>	Kilobits per second.	<i>mbps</i>	Megabits per second.	<i>gbps</i>	Gigabits per second.			
Option	Description											
<i>kbps</i>	Kilobits per second.											
<i>mbps</i>	Megabits per second.											
<i>gbps</i>	Gigabits per second.											
priority	Higher priority traffic is more likely to be forwarded without delays and without compromising the guaranteed bandwidth.	option	-	high								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>low</i></td><td>Low priority.</td></tr><tr><td><i>medium</i></td><td>Medium priority.</td></tr><tr><td><i>high</i></td><td>High priority.</td></tr></table>	Option	Description	<i>low</i>	Low priority.	<i>medium</i>	Medium priority.	<i>high</i>	High priority.			
Option	Description											
<i>low</i>	Low priority.											
<i>medium</i>	Medium priority.											
<i>high</i>	High priority.											
per-policy	Enable/disable applying a separate shaper for each policy. For example, if enabled the guaranteed bandwidth is applied separately for each policy.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>All referring policies share one traffic shaper.</td></tr><tr><td><i>enable</i></td><td>Each referring policy has its own traffic shaper.</td></tr></table>	Option	Description	<i>disable</i>	All referring policies share one traffic shaper.	<i>enable</i>	Each referring policy has its own traffic shaper.					
Option	Description											
<i>disable</i>	All referring policies share one traffic shaper.											
<i>enable</i>	Each referring policy has its own traffic shaper.											
diffserv	Enable/disable changing the DiffServ setting applied to traffic accepted by this shaper.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting traffic DiffServ.</td></tr><tr><td><i>disable</i></td><td>Disable setting traffic DiffServ.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting traffic DiffServ.	<i>disable</i>	Disable setting traffic DiffServ.					
Option	Description											
<i>enable</i>	Enable setting traffic DiffServ.											
<i>disable</i>	Disable setting traffic DiffServ.											

Parameter	Description	Type	Size	Default						
diffservcode	DiffServ setting to be applied to traffic accepted by this shaper.	user	Not Specified							
dscp-marking-method	Select DSCP marking method.	option	-	static						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>multi-stage</i></td><td>Multistage marking.</td></tr><tr><td><i>static</i></td><td>Static marking.</td></tr></table>	Option	Description	<i>multi-stage</i>	Multistage marking.	<i>static</i>	Static marking.			
Option	Description									
<i>multi-stage</i>	Multistage marking.									
<i>static</i>	Static marking.									
exceed-bandwidth	Exceed bandwidth used for DSCP multi-stage marking. Units depend on the bandwidth-unit setting.	integer	Minimum value: 0 Maximum value: 80000000	0						
exceed-dscp	DSCP mark for traffic in guaranteed-bandwidth and exceed-bandwidth.	user	Not Specified							
maximum-dscp	DSCP mark for traffic in exceed-bandwidth and maximum-bandwidth.	user	Not Specified							
overhead	Per-packet size overhead used in rate computations.	integer	Minimum value: 0 Maximum value: 100	0						

config firewall shaping-policy

Configure shaping policies.

```
config firewall shaping-policy
  Description: Configure shaping policies.
  edit <id>
    set uuid {uuid}
    set name {string}
    set comment {var-string}
    set status [enable|disable]
    set ip-version [4|6]
    set service-type [service|internet-service]
    set srcaddr <name1>, <name2>, ...
    set dstaddr <name1>, <name2>, ...
    set srcaddr6 <name1>, <name2>, ...
    set dstaddr6 <name1>, <name2>, ...
    set service <name1>, <name2>, ...
    set internet-service-name <name1>, <name2>, ...
    set internet-service-group <name1>, <name2>, ...
    set internet-service-custom <name1>, <name2>, ...
```

```

set internet-service-custom-group <name1>, <name2>, ...
set schedule {string}
set http-response-match [enable|disable]
set users <name1>, <name2>, ...
set groups <name1>, <name2>, ...
set application <id1>, <id2>, ...
set app-category <id1>, <id2>, ...
set app-group <name1>, <name2>, ...
set dstintf <name1>, <name2>, ...
set traffic-shaper {string}
set traffic-shaper-reverse {string}
set per-ip-shaper {string}
set class-id {integer}
set class-id-reverse {integer}
set diffserv-forward [enable|disable]
set diffservcode-forward {user}
set diffserv-reverse [enable|disable]
set diffservcode-rev {user}
next
end

```

config firewall shaping-policy

Parameter	Description	Type	Size	Default						
id	Shaping policy ID.	integer	Minimum value: 0 Maximum value: 4294967295	0						
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000						
name	Shaping policy name.	string	Maximum length: 35							
comment	Comments.	var-string	Maximum length: 255							
status	Enable/disable traffic shaping policy.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable traffic shaping policy.</td></tr><tr><td><i>disable</i></td><td>Disable traffic shaping policy.</td></tr></table>				Option	Description	<i>enable</i>	Enable traffic shaping policy.	<i>disable</i>	Disable traffic shaping policy.
	Option	Description								
	<i>enable</i>	Enable traffic shaping policy.								
<i>disable</i>	Disable traffic shaping policy.									
ip-version	IP version.	option	-	4						

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>4</td><td>Use IPv4 addressing for Configuration Method.</td></tr><tr><td>6</td><td>Use IPv6 addressing for Configuration Method.</td></tr></table>	Option	Description	4	Use IPv4 addressing for Configuration Method.	6	Use IPv6 addressing for Configuration Method.			
	Option	Description								
	4	Use IPv4 addressing for Configuration Method.								
6	Use IPv6 addressing for Configuration Method.									
service-type	Select service-type: service / internet-service.	option	-	service						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>service</td><td>Firewall services.</td></tr><tr><td>internet-service</td><td>Internet-services.</td></tr></table>	Option	Description	service	Firewall services.	internet-service	Internet-services.			
	Option	Description								
	service	Firewall services.								
internet-service	Internet-services.									
srcaddr <name>	Source address. Address name.	string	Maximum length: 79							
dstaddr <name>	Destination address. Address name.	string	Maximum length: 79							
srcaddr6 <name>	IPv6 source address. Address name.	string	Maximum length: 79							
dstaddr6 <name>	IPv6 destination address. Address name.	string	Maximum length: 79							
service <name>	Service name. Service name.	string	Maximum length: 79							
internet-service-name <name>	Internet Service ID. Internet Service name.	string	Maximum length: 79							
internet-service-group <name>	Internet Service group name. Internet Service group name.	string	Maximum length: 79							
internet-service-custom <name>	Custom Internet Service name. Custom Internet Service name.	string	Maximum length: 79							
internet-service-custom-group <name>	Custom Internet Service group name. Custom Internet Service group name.	string	Maximum length: 79							
schedule	Schedule name.	string	Maximum length: 35	always						

Parameter	Description	Type	Size	Default
http-response-match	Enable/disable matching http response shaping policies.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable matching HTTP response shaping policies.		
	<i>disable</i>	Disable matching HTTP response shaping policies.		
users <name>	User name. User name.	string	Maximum length: 79	
groups <name>	User authentication groups. Group name.	string	Maximum length: 79	
application <id>	IDs of one or more applications that this shaper applies application control traffic shaping to. Application IDs.	integer	Minimum value: 0 Maximum value: 4294967295	
app-category <id>	IDs of one or more application categories that this shaper applies application control traffic shaping to. Category IDs.	integer	Minimum value: 0 Maximum value: 4294967295	
app-group <name>	One or more application group names. Application group name.	string	Maximum length: 79	
dstintf <name>	Destination interface list. Interface name.	string	Maximum length: 79	
traffic-shaper	Forward traffic shaper.	string	Maximum length: 35	
traffic-shaper-reverse	Reverse traffic shaper.	string	Maximum length: 35	
per-ip-shaper	Per IP shaper.	string	Maximum length: 35	
class-id	Forward class id.	integer	Minimum value: 2 Maximum value: 31	0

Parameter	Description	Type	Size	Default
class-id-reverse	Reverse class id.	integer	Minimum value: 2 Maximum value: 31	0
diffserv-forward	Enable/disable forward (original) traffic DiffServ.	option	-	disable
	Option		Description	
	<i>enable</i>		Enable setting.	
	<i>disable</i>		Disable setting.	
diffservcode-forward	Forward (original) traffic DiffServ code point value.	user	Not Specified	
diffserv-reverse	Enable/disable reverse (reply) traffic DiffServ.	option	-	disable
	Option		Description	
	<i>enable</i>		Enable setting.	
	<i>disable</i>		Disable setting.	
diffservcode-rev	Reverse (reply) traffic DiffServ code point value.	user	Not Specified	

config firewall shaping-profile

Configure shaping profiles.

```

config firewall shaping-profile
  Description: Configure shaping profiles.
  edit <profile-name>
    set comment {var-string}
    set default-class {integer}
    config classes
      Description: Define shaping classes of this shaping profile
      edit <name>
        set class-id {integer}
        set priority [top|critical|...]
        set guaranteed-bandwidth {integer}
        set maximum-bandwidth {integer}
      next
    end
  next
end

```


config firewall shaping-profile

Parameter	Description	Type	Size	Default
profile-name	Shaping profile name.	string	Maximum length: 35	
comment	Comment.	var-string	Maximum length: 1023	
default-class	Default class ID to handle unclassified packets.	integer	Minimum value: 2 Maximum value: 32	2

config classes

Parameter	Description	Type	Size	Default
name	Class Name.	string	Maximum length: 35	
class-id	Class ID.	integer	Minimum value: 2 Maximum value: 32	0
priority	Priority.	option	-	top
	Option	Description		
	<i>top</i>	Top priority.		
	<i>critical</i>	Critical priority.		
	<i>high</i>	High priority.		
	<i>medium</i>	Medium priority.		
	<i>low</i>	Low priority.		
guaranteed-bandwidth	Guaranteed bandwidth in percentage.	integer	Minimum value: 0 Maximum value: 100	0
maximum-bandwidth	Maximum bandwidth in percentage.	integer	Minimum value: 1 Maximum value: 100	1

config firewall sniffer

Configure sniffer.

```
config firewall sniffer
  Description: Configure sniffer.
  edit <id>
    set uuid {uuid}
    set status [enable|disable]
    set logtraffic [all|utm|...]
    set non-ip [enable|disable]
    set interface {string}
    set host {string}
    set port {string}
    set protocol {string}
    set vlan {string}
  next
end
```

config firewall sniffer

Parameter	Description	Type	Size	Default						
id	Sniffer ID (0 - 9999).	integer	Minimum value: 0 Maximum value: 9999	0						
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000						
status	Enable/disable the active status of the sniffer.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable sniffer status.</td></tr><tr><td><i>disable</i></td><td>Disable sniffer status.</td></tr></table>				Option	Description	<i>enable</i>	Enable sniffer status.	<i>disable</i>	Disable sniffer status.
Option	Description									
<i>enable</i>	Enable sniffer status.									
<i>disable</i>	Disable sniffer status.									
logtraffic	Either log all sessions, only sessions that have a security profile applied, or disable all logging for this policy.	option	-	utm						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>all</i></td><td>Log all sessions accepted or denied by this policy.</td></tr></table>				Option	Description	<i>all</i>	Log all sessions accepted or denied by this policy.		
Option	Description									
<i>all</i>	Log all sessions accepted or denied by this policy.									

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>utm</i>	Log traffic that has a security profile applied to it.		
	<i>disable</i>	Disable all logging for this policy.		
non-ip	Enable/disable sniffing non-IP packets.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable sniffer for non-IP packets.		
	<i>disable</i>	Disable sniffer for non-IP packets.		
interface	Interface name that traffic sniffing will take place on.	string	Maximum length: 35	
host	Hosts to filter for in sniffer traffic (Format examples: 1.1.1.1, 2.2.2.0/24, 3.3.3.3/255.255.255.0, 4.4.4.0-4.4.4.240).	string	Maximum length: 63	
port	Ports to sniff (Format examples: 10, :20, 30:40, 50-, 100-200).	string	Maximum length: 63	
protocol	Integer value for the protocol type as defined by IANA (0 - 255).	string	Maximum length: 63	
vlan	List of VLANs to sniff.	string	Maximum length: 63	

config firewall ssh host-key

SSH proxy host public keys.

```

config firewall ssh host-key
  Description: SSH proxy host public keys.
  edit <name>
    set status [trusted|revoked]
    set type [RSA|DSA|...]
    set nid [256|384|...]
    set usage [transparent-proxy|access-proxy]
    set ip {ipv4-address-any}
    set port {integer}
    set hostname {string}
    set public-key {var-string}
  next
end

```

config firewall ssh host-key

Parameter	Description	Type	Size	Default																		
name	SSH public key name.	string	Maximum length: 35																			
status	Set the trust status of the public key.	option	-	trusted																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>trusted</i></td><td>The public key is trusted.</td></tr><tr><td><i>revoked</i></td><td>The public key is revoked.</td></tr></table>	Option	Description	<i>trusted</i>	The public key is trusted.	<i>revoked</i>	The public key is revoked.															
Option	Description																					
<i>trusted</i>	The public key is trusted.																					
<i>revoked</i>	The public key is revoked.																					
type	Set the type of the public key.	option	-	RSA																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>RSA</i></td><td>The type of the public key is RSA.</td></tr><tr><td><i>DSA</i></td><td>The type of the public key is DSA.</td></tr><tr><td><i>ECDSA</i></td><td>The type of the public key is ECDSA.</td></tr><tr><td><i>ED25519</i></td><td>The type of the public key is ED25519.</td></tr><tr><td><i>RSA-CA</i></td><td>The type of the public key is from RSA CA.</td></tr><tr><td><i>DSA-CA</i></td><td>The type of the public key is from DSA CA.</td></tr><tr><td><i>ECDSA-CA</i></td><td>The type of the public key is from ECDSA CA.</td></tr><tr><td><i>ED25519-CA</i></td><td>The type of the public key is from ED25519 CA.</td></tr></table>	Option	Description	<i>RSA</i>	The type of the public key is RSA.	<i>DSA</i>	The type of the public key is DSA.	<i>ECDSA</i>	The type of the public key is ECDSA.	<i>ED25519</i>	The type of the public key is ED25519.	<i>RSA-CA</i>	The type of the public key is from RSA CA.	<i>DSA-CA</i>	The type of the public key is from DSA CA.	<i>ECDSA-CA</i>	The type of the public key is from ECDSA CA.	<i>ED25519-CA</i>	The type of the public key is from ED25519 CA.			
Option	Description																					
<i>RSA</i>	The type of the public key is RSA.																					
<i>DSA</i>	The type of the public key is DSA.																					
<i>ECDSA</i>	The type of the public key is ECDSA.																					
<i>ED25519</i>	The type of the public key is ED25519.																					
<i>RSA-CA</i>	The type of the public key is from RSA CA.																					
<i>DSA-CA</i>	The type of the public key is from DSA CA.																					
<i>ECDSA-CA</i>	The type of the public key is from ECDSA CA.																					
<i>ED25519-CA</i>	The type of the public key is from ED25519 CA.																					
nid	Set the nid of the ECDSA key.	option	-	256																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>256</i></td><td>The NID is ecdsa-sha2-nistp256.</td></tr><tr><td><i>384</i></td><td>The NID is ecdsa-sha2-nistp384.</td></tr><tr><td><i>521</i></td><td>The NID is ecdsa-sha2-nistp521.</td></tr></table>	Option	Description	<i>256</i>	The NID is ecdsa-sha2-nistp256.	<i>384</i>	The NID is ecdsa-sha2-nistp384.	<i>521</i>	The NID is ecdsa-sha2-nistp521.													
Option	Description																					
<i>256</i>	The NID is ecdsa-sha2-nistp256.																					
<i>384</i>	The NID is ecdsa-sha2-nistp384.																					
<i>521</i>	The NID is ecdsa-sha2-nistp521.																					
usage	Usage for this public key.	option	-	transparent-proxy																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>transparent-proxy</i></td><td>Transparent proxy uses this public key to validate server.</td></tr><tr><td><i>access-proxy</i></td><td>Access proxy uses this public key to validate server.</td></tr></table>	Option	Description	<i>transparent-proxy</i>	Transparent proxy uses this public key to validate server.	<i>access-proxy</i>	Access proxy uses this public key to validate server.															
Option	Description																					
<i>transparent-proxy</i>	Transparent proxy uses this public key to validate server.																					
<i>access-proxy</i>	Access proxy uses this public key to validate server.																					

Parameter	Description	Type	Size	Default
ip	IP address of the SSH server.	ipv4-address-any	Not Specified	0.0.0.0
port	Port of the SSH server.	integer	Minimum value: 0 Maximum value: 4294967295	22
hostname	Hostname of the SSH server to match SSH certificate principals.	string	Maximum length: 255	
public-key	SSH public key.	var-string	Maximum length: 32768	

config firewall ssh local-ca

SSH proxy local CA.

```
config firewall ssh local-ca
  Description: SSH proxy local CA.
  edit <name>
    set password {password}
    set private-key {user}
    set public-key {user}
    set source [built-in|user]
  next
end
```

config firewall ssh local-ca

Parameter	Description	Type	Size	Default
name	SSH proxy local CA name.	string	Maximum length: 35	
password	Password for SSH private key.	password	Not Specified	
private-key	SSH proxy private key, encrypted with a password.	user	Not Specified	
public-key	SSH proxy public key.	user	Not Specified	
source	SSH proxy local CA source type.	option	-	user

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>built-in</i>	Built-in SSH proxy local keys.		
	<i>user</i>	User imported SSH proxy local keys.		

config firewall ssh local-key

SSH proxy local keys.

```
config firewall ssh local-key
  Description: SSH proxy local keys.
  edit <name>
    set password {password}
    set private-key {user}
    set public-key {user}
    set source [built-in|user]
  next
end
```

config firewall ssh local-key

Parameter	Description	Type	Size	Default
name	SSH proxy local key name.	string	Maximum length: 35	
password	Password for SSH private key.	password	Not Specified	
private-key	SSH proxy private key, encrypted with a password.	user	Not Specified	
public-key	SSH proxy public key.	user	Not Specified	
source	SSH proxy local key source type.	option	-	user
	Option	Description		
	<i>built-in</i>	Built-in SSH proxy local keys.		
	<i>user</i>	User imported SSH proxy local keys.		

config firewall ssh setting

SSH proxy settings.

```

config firewall ssh setting
    Description: SSH proxy settings.
    set caname {string}
    set untrusted-caname {string}
    set hostkey-rsa2048 {string}
    set hostkey-dsa1024 {string}
    set hostkey-ecdsa256 {string}
    set hostkey-ecdsa384 {string}
    set hostkey-ecdsa521 {string}
    set hostkey-ed25519 {string}
    set host-trusted-checking [enable|disable]
end

```

config firewall ssh setting

Parameter	Description	Type	Size	Default
caname	CA certificate used by SSH Inspection.	string	Maximum length: 35	
untrusted-caname	Untrusted CA certificate used by SSH Inspection.	string	Maximum length: 35	
hostkey-rsa2048	RSA certificate used by SSH proxy.	string	Maximum length: 35	
hostkey-dsa1024	DSA certificate used by SSH proxy.	string	Maximum length: 35	
hostkey-ecdsa256	ECDSA nid256 certificate used by SSH proxy.	string	Maximum length: 35	
hostkey-ecdsa384	ECDSA nid384 certificate used by SSH proxy.	string	Maximum length: 35	
hostkey-ecdsa521	ECDSA nid384 certificate used by SSH proxy.	string	Maximum length: 35	
hostkey-ed25519	ED25519 hostkey used by SSH proxy.	string	Maximum length: 35	
host-trusted-checking	Enable/disable host trusted checking.	option	-	enable
		Option	Description	
		<i>enable</i>	Enable host key trusted checking.	
		<i>disable</i>	Disable host key trusted checking.	

config firewall ssl default-certificate

SSL default certificate.

```
config firewall ssl default-certificate
  Description: SSL default certificate.
  set default-ca {string}
  set default-untrusted-ca {string}
  set default-server-cert {string}
end
```

config firewall ssl default-certificate

Parameter	Description	Type	Size	Default
default-ca	Default CA certificate used by SSL inspection.	string	Maximum length: 35	Fortinet_CA_SSL
default-untrusted-ca	Default CA certificate used by SSL inspection.	string	Maximum length: 35	Fortinet_CA_Untrusted
default-server-cert	Default server certificate used by SSL inspection.	string	Maximum length: 35	Fortinet_Factory

config firewall ssl keyring-list

SSL keyring list.

```
config firewall ssl keyring-list
  Description: SSL keyring list.
  edit <name>
    set uuid {uuid}
  next
end
```

config firewall ssl keyring-list

Parameter	Description	Type	Size	Default
name	Keyring list name.	string	Maximum length: 35	
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000

config firewall ssl setting

SSL proxy settings.

```
config firewall ssl setting
  Description: SSL proxy settings.
  set proxy-connect-timeout {integer}
  set ssl-dh-bits [768|1024|...]
  set ssl-send-empty-frags [enable|disable]
  set no-matching-cipher-action [bypass|drop]
  set cert-cache-capacity {integer}
  set cert-cache-timeout {integer}
  set session-cache-capacity {integer}
  set session-cache-timeout {integer}
  set abbreviate-handshake [enable|disable]
end
```

config firewall ssl setting

Parameter	Description	Type	Size	Default
proxy-connect-timeout	Time limit to make an internal connection to the appropriate proxy process (1 - 60 sec, default = 30).	integer	Minimum value: 1 Maximum value: 60	30
ssl-dh-bits	Bit-size of Diffie-Hellman (DH) prime used in DHE-RSA negotiation (default = 2048).	option	-	2048
	Option Description			
	768	768-bit Diffie-Hellman prime.		
	1024	1024-bit Diffie-Hellman prime.		
	1536	1536-bit Diffie-Hellman prime.		
	2048	2048-bit Diffie-Hellman prime.		
ssl-send-empty-frags	Enable/disable sending empty fragments to avoid attack on CBC IV (for SSL 3.0 and TLS 1.0 only).	option	-	enable
	Option Description			
	enable	Send empty fragments.		
	disable	Do not send empty fragments.		
no-matching-cipher-action	Bypass or drop the connection when no matching cipher is found.	option	-	bypass

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>bypass</i>	Bypass connection.		
	<i>drop</i>	Drop connection.		
cert-cache-capacity	Maximum capacity of the host certificate cache (0 - 500, default = 200).	integer	Minimum value: 0 Maximum value: 500	200
cert-cache-timeout	Time limit to keep certificate cache (1 - 120 min, default = 10).	integer	Minimum value: 1 Maximum value: 120	10
session-cache-capacity	Capacity of the SSL session cache (-- Obsolete--) (1 - 1000, default = 500).	integer	Minimum value: 0 Maximum value: 1000	500
session-cache-timeout	Time limit to keep SSL session state (1 - 60 min, default = 20).	integer	Minimum value: 1 Maximum value: 60	20
abbreviate-handshake	Enable/disable use of SSL abbreviated handshake.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable use of SSL abbreviated handshake.		
	<i>disable</i>	Disable use of SSL abbreviated handshake.		

config firewall ssl-server

Configure SSL servers.

```
config firewall ssl-server
  Description: Configure SSL servers.
  edit <name>
    set ip {ipv4-address-any}
    set port {integer}
    set ssl-mode [half|full]
    set add-header-x-forwarded-proto [enable|disable]
    set mapped-port {integer}
    set ssl-cert <name1>, <name2>, ...
    set ssl-dh-bits [768|1024|...]
    set ssl-algorithm [high|medium|...]
```

```

set ssl-client-renegotiation [allow|deny|...]
set ssl-min-version [tls-1.0|tls-1.1|...]
set ssl-max-version [tls-1.0|tls-1.1|...]
set ssl-send-empty-frags [enable|disable]
set url-rewrite [enable|disable]
next
end

```

config firewall ssl-server

Parameter	Description	Type	Size	Default						
name	Server name.	string	Maximum length: 35							
ip	IPv4 address of the SSL server.	ipv4-address-any	Not Specified	0.0.0.0						
port	Server service port (1 - 65535, default = 443).	integer	Minimum value: 1 Maximum value: 65535	443						
ssl-mode	SSL/TLS mode for encryption and decryption of traffic.	option	-	full						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>half</td><td>Client to FortiProxy SSL.</td></tr><tr><td>full</td><td>Client to FortiProxy and FortiProxy to Server SSL.</td></tr></table>				Option	Description	half	Client to FortiProxy SSL.	full	Client to FortiProxy and FortiProxy to Server SSL.
Option	Description									
half	Client to FortiProxy SSL.									
full	Client to FortiProxy and FortiProxy to Server SSL.									
add-header-x-forwarded-proto	Enable/disable adding an X-Forwarded-Proto header to forwarded requests.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Add X-Forwarded-Proto header.</td></tr><tr><td>disable</td><td>Do not add X-Forwarded-Proto header.</td></tr></table>				Option	Description	enable	Add X-Forwarded-Proto header.	disable	Do not add X-Forwarded-Proto header.
Option	Description									
enable	Add X-Forwarded-Proto header.									
disable	Do not add X-Forwarded-Proto header.									
mapped-port	Mapped server service port (1 - 65535, default = 80).	integer	Minimum value: 1 Maximum value: 65535	80						

Parameter	Description	Type	Size	Default										
ssl-cert <name>	List of certificate names to use for SSL connections to this server. (default = "Fortinet_SSL"). Certificate list.	string	Maximum length: 79											
ssl-dh-bits	Bit-size of Diffie-Hellman (DH) prime used in DHE-RSA negotiation (default = 2048).	option	-	2048										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>768</td><td>768-bit Diffie-Hellman prime.</td></tr><tr><td>1024</td><td>1024-bit Diffie-Hellman prime.</td></tr><tr><td>1536</td><td>1536-bit Diffie-Hellman prime.</td></tr><tr><td>2048</td><td>2048-bit Diffie-Hellman prime.</td></tr></table>	Option	Description	768	768-bit Diffie-Hellman prime.	1024	1024-bit Diffie-Hellman prime.	1536	1536-bit Diffie-Hellman prime.	2048	2048-bit Diffie-Hellman prime.			
Option	Description													
768	768-bit Diffie-Hellman prime.													
1024	1024-bit Diffie-Hellman prime.													
1536	1536-bit Diffie-Hellman prime.													
2048	2048-bit Diffie-Hellman prime.													
ssl-algorithm	Relative strength of encryption algorithms accepted in negotiation.	option	-	high										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>high</td><td>High encryption. Allow only AES and ChaCha</td></tr><tr><td>medium</td><td>Medium encryption. Allow AES, ChaCha, 3DES, and RC4.</td></tr><tr><td>low</td><td>Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.</td></tr></table>	Option	Description	high	High encryption. Allow only AES and ChaCha	medium	Medium encryption. Allow AES, ChaCha, 3DES, and RC4.	low	Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.					
Option	Description													
high	High encryption. Allow only AES and ChaCha													
medium	Medium encryption. Allow AES, ChaCha, 3DES, and RC4.													
low	Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.													
ssl-client-renegotiation	Allow or block client renegotiation by server.	option	-	allow										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>allow</td><td>Allow a SSL client to renegotiate.</td></tr><tr><td>deny</td><td>Abort any SSL connection that attempts to renegotiate.</td></tr><tr><td>secure</td><td>Reject any SSL connection that does not offer a RFC 5746 Secure Renegotiation Indication.</td></tr></table>	Option	Description	allow	Allow a SSL client to renegotiate.	deny	Abort any SSL connection that attempts to renegotiate.	secure	Reject any SSL connection that does not offer a RFC 5746 Secure Renegotiation Indication.					
Option	Description													
allow	Allow a SSL client to renegotiate.													
deny	Abort any SSL connection that attempts to renegotiate.													
secure	Reject any SSL connection that does not offer a RFC 5746 Secure Renegotiation Indication.													
ssl-min-version	Lowest SSL/TLS version to negotiate.	option	-	tls-1.1										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>tls-1.0</td><td>TLS 1.0.</td></tr><tr><td>tls-1.1</td><td>TLS 1.1.</td></tr><tr><td>tls-1.2</td><td>TLS 1.2.</td></tr><tr><td>tls-1.3</td><td>TLS 1.3.</td></tr></table>	Option	Description	tls-1.0	TLS 1.0.	tls-1.1	TLS 1.1.	tls-1.2	TLS 1.2.	tls-1.3	TLS 1.3.			
Option	Description													
tls-1.0	TLS 1.0.													
tls-1.1	TLS 1.1.													
tls-1.2	TLS 1.2.													
tls-1.3	TLS 1.3.													

Parameter	Description	Type	Size	Default
ssl-max-version	Highest SSL/TLS version to negotiate.	option	-	tls-1.3
	Option	Description		
	<i>tls-1.0</i>	TLS 1.0.		
	<i>tls-1.1</i>	TLS 1.1.		
	<i>tls-1.2</i>	TLS 1.2.		
	<i>tls-1.3</i>	TLS 1.3.		
ssl-send-empty-frags	Enable/disable sending empty fragments to avoid attack on CBC IV.	option	-	enable
	Option	Description		
	<i>enable</i>	Send empty fragments.		
	<i>disable</i>	Do not send empty fragments.		
url-rewrite	Enable/disable rewriting the URL.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

config firewall ssl-ssh-profile

Configure SSL/SSH protocol options.

```
config firewall ssl-ssh-profile
  Description: Configure SSL/SSH protocol options.
  edit <name>
    set comment {var-string}
    config ssl
      Description: Configure SSL options.
      set inspect-all [disable|certificate-inspection|...]
      set client-certificate [bypass|inspect|...]
      set unsupported-ssl-version [allow|block]
      set unsupported-ssl-cipher [allow|block]
      set unsupported-ssl-negotiation [allow|block]
      set expired-server-cert [allow|block|...]
      set revoked-server-cert [allow|block|...]
      set untrusted-server-cert [allow|block|...]
      set cert-validation-timeout [allow|block|...]
      set cert-validation-failure [allow|block|...]
      set sni-server-cert-check [enable|strict|...]
```

```

    set cert-probe-failure [allow|block]
    set encrypted-client-hello [allow|block]
    set min-allowed-ssl-version [ssl-3.0|tls-1.0|...]
end
config https
    Description: Configure HTTPS options.
    set ports {integer}
    set status [disable|certificate-inspection|...]
    set quic [inspect|bypass|...]
    set proxy-after-tcp-handshake [enable|disable]
    set client-certificate [bypass|inspect|...]
    set unsupported-ssl-version [allow|block]
    set unsupported-ssl-cipher [allow|block]
    set unsupported-ssl-negotiation [allow|block]
    set expired-server-cert [allow|block|...]
    set revoked-server-cert [allow|block|...]
    set untrusted-server-cert [allow|block|...]
    set cert-validation-timeout [allow|block|...]
    set cert-validation-failure [allow|block|...]
    set sni-server-cert-check [enable|strict|...]
    set cert-probe-failure [allow|block]
    set encrypted-client-hello [allow|block]
    set min-allowed-ssl-version [ssl-3.0|tls-1.0|...]
end
config ftps
    Description: Configure FTPS options.
    set ports {integer}
    set status [disable|deep-inspection]
    set client-certificate [bypass|inspect|...]
    set unsupported-ssl-version [allow|block]
    set unsupported-ssl-cipher [allow|block]
    set unsupported-ssl-negotiation [allow|block]
    set expired-server-cert [allow|block|...]
    set revoked-server-cert [allow|block|...]
    set untrusted-server-cert [allow|block|...]
    set cert-validation-timeout [allow|block|...]
    set cert-validation-failure [allow|block|...]
    set sni-server-cert-check [enable|strict|...]
    set min-allowed-ssl-version [ssl-3.0|tls-1.0|...]
end
config imaps
    Description: Configure IMAPS options.
    set ports {integer}
    set status [disable|deep-inspection]
    set proxy-after-tcp-handshake [enable|disable]
    set client-certificate [bypass|inspect|...]
    set unsupported-ssl-version [allow|block]
    set unsupported-ssl-cipher [allow|block]
    set unsupported-ssl-negotiation [allow|block]
    set expired-server-cert [allow|block|...]
    set revoked-server-cert [allow|block|...]
    set untrusted-server-cert [allow|block|...]

```

```

        set cert-validation-timeout [allow|block|...]
        set cert-validation-failure [allow|block|...]
        set sni-server-cert-check [enable|strict|...]
    end
    config pop3s
        Description: Configure POP3S options.
        set ports {integer}
        set status [disable|deep-inspection]
        set proxy-after-tcp-handshake [enable|disable]
        set client-certificate [bypass|inspect|...]
        set unsupported-ssl-version [allow|block]
        set unsupported-ssl-cipher [allow|block]
        set unsupported-ssl-negotiation [allow|block]
        set expired-server-cert [allow|block|...]
        set revoked-server-cert [allow|block|...]
        set untrusted-server-cert [allow|block|...]
        set cert-validation-timeout [allow|block|...]
        set cert-validation-failure [allow|block|...]
        set sni-server-cert-check [enable|strict|...]
    end
    config smtps
        Description: Configure SMTPS options.
        set ports {integer}
        set status [disable|deep-inspection]
        set proxy-after-tcp-handshake [enable|disable]
        set client-certificate [bypass|inspect|...]
        set unsupported-ssl-version [allow|block]
        set unsupported-ssl-cipher [allow|block]
        set unsupported-ssl-negotiation [allow|block]
        set expired-server-cert [allow|block|...]
        set revoked-server-cert [allow|block|...]
        set untrusted-server-cert [allow|block|...]
        set cert-validation-timeout [allow|block|...]
        set cert-validation-failure [allow|block|...]
        set sni-server-cert-check [enable|strict|...]
    end
    config ssh
        Description: Configure SSH options.
        set ports {integer}
        set status [disable|deep-inspection]
        set proxy-after-tcp-handshake [enable|disable]
        set unsupported-version [bypass|block]
        set ssh-tun-policy-check [disable|enable]
        set ssh-algorithm [compatible|high-encryption]
    end
    config dot
        Description: Configure DNS over TLS options.
        set status [disable|deep-inspection]
        set quic [inspect|bypass|...]
        set proxy-after-tcp-handshake [enable|disable]
        set client-certificate [bypass|inspect|...]
        set unsupported-ssl-version [allow|block]

```

```

    set unsupported-ssl-cipher [allow|block]
    set unsupported-ssl-negotiation [allow|block]
    set expired-server-cert [allow|block|...]
    set revoked-server-cert [allow|block|...]
    set untrusted-server-cert [allow|block|...]
    set cert-validation-timeout [allow|block|...]
    set cert-validation-failure [allow|block|...]
    set sni-server-cert-check [enable|strict|...]
end
config ssl-client-certificate
    Description: Configure SSL client certificate setting.
    set status [do-not-offer|keyring-list|...]
    set keyring-list {string}
    set caname {string}
    set cert {string}
end
config ssl-exempt
    Description: Servers to exempt from SSL inspection.
    edit <id>
        set type [fortiguard-category|address|...]
        set fortiguard-category {integer}
        set address {string}
        set address6 {string}
        set wildcard-fqdn {string}
        set regex {string}
        set finger-print-category [unknown|firefox|...]
    next
end
config ech-outer-sni
    Description: ClientHelloOuter SNIs to be blocked.
    edit <name>
        set sni {string}
    next
end
set allowlist [enable|disable]
set block-blocklisted-certificates [disable|enable]
set server-cert-mode [re-sign|replace]
set use-ssl-server [disable|enable]
set caname {string}
set untrusted-caname {string}
set server-cert <name1>, <name2>, ...
config ssl-server
    Description: SSL server settings used for client certificate request.
    edit <id>
        set ip {ipv4-address-any}
        set https-client-certificate [bypass|inspect|...]
        set smtps-client-certificate [bypass|inspect|...]
        set pop3s-client-certificate [bypass|inspect|...]
        set imaps-client-certificate [bypass|inspect|...]
        set ftps-client-certificate [bypass|inspect|...]
        set ssl-other-client-certificate [bypass|inspect|...]
    next

```



```

end
set ssl-exemption-ip-rating [enable|disable]
set ssl-exemption-log [disable|enable]
set ssl-anomaly-log [disable|enable]
set ssl-negotiation-log [disable|enable]
set ssl-server-cert-log [disable|enable]
set ssl-handshake-log [disable|enable]
set rpc-over-https [enable|disable]
set mapi-over-https [enable|disable]
set supported-alpn [http1-1|http2|...]
next
end

```

config firewall ssl-ssh-profile

Parameter	Description	Type	Size	Default						
name	Name.	string	Maximum length: 35							
comment	Optional comments.	var-string	Maximum length: 255							
allowlist	Enable/disable exempting servers by FortiGuard allowlist.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
block-blocklisted-certificates	Enable/disable blocking SSL-based botnet communication by FortiGuard certificate blocklist.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable FortiGuard certificate blocklist.</td></tr><tr><td><i>enable</i></td><td>Enable FortiGuard certificate blocklist.</td></tr></table>	Option	Description	<i>disable</i>	Disable FortiGuard certificate blocklist.	<i>enable</i>	Enable FortiGuard certificate blocklist.			
Option	Description									
<i>disable</i>	Disable FortiGuard certificate blocklist.									
<i>enable</i>	Enable FortiGuard certificate blocklist.									
server-cert-mode	Re-sign or replace the server's certificate.	option	-	re-sign						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>re-sign</i></td><td>Multiple clients connecting to multiple servers.</td></tr><tr><td><i>replace</i></td><td>Protect an SSL server.</td></tr></table>	Option	Description	<i>re-sign</i>	Multiple clients connecting to multiple servers.	<i>replace</i>	Protect an SSL server.			
Option	Description									
<i>re-sign</i>	Multiple clients connecting to multiple servers.									
<i>replace</i>	Protect an SSL server.									

Parameter	Description	Type	Size	Default						
use-ssl-server	Enable/disable the use of SSL server table for SSL offloading.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Don't use SSL server configuration.</td></tr><tr><td><i>enable</i></td><td>Use SSL server configuration.</td></tr></table>	Option	Description	<i>disable</i>	Don't use SSL server configuration.	<i>enable</i>	Use SSL server configuration.			
Option	Description									
<i>disable</i>	Don't use SSL server configuration.									
<i>enable</i>	Use SSL server configuration.									
caname	CA certificate used by SSL Inspection.	string	Maximum length: 35	default-ca						
untrusted-caname	Untrusted CA certificate used by SSL Inspection.	string	Maximum length: 35	default-untrusted-ca						
server-cert <name>	Certificate used by SSL Inspection to replace server certificate. Certificate list.	string	Maximum length: 79							
ssl-exemption-ip-rating	Enable/disable IP based URL rating.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable IP based URL rating.</td></tr><tr><td><i>disable</i></td><td>Disable IP based URL rating.</td></tr></table>	Option	Description	<i>enable</i>	Enable IP based URL rating.	<i>disable</i>	Disable IP based URL rating.			
Option	Description									
<i>enable</i>	Enable IP based URL rating.									
<i>disable</i>	Disable IP based URL rating.									
ssl-exemption-log	Enable/disable logging SSL exemptions.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable logging SSL exemptions.</td></tr><tr><td><i>enable</i></td><td>Enable logging SSL exemptions.</td></tr></table>	Option	Description	<i>disable</i>	Disable logging SSL exemptions.	<i>enable</i>	Enable logging SSL exemptions.			
Option	Description									
<i>disable</i>	Disable logging SSL exemptions.									
<i>enable</i>	Enable logging SSL exemptions.									
ssl-anomaly-log	Enable/disable logging of SSL anomalies.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable logging of SSL anomalies.</td></tr><tr><td><i>enable</i></td><td>Enable logging of SSL anomalies.</td></tr></table>	Option	Description	<i>disable</i>	Disable logging of SSL anomalies.	<i>enable</i>	Enable logging of SSL anomalies.			
Option	Description									
<i>disable</i>	Disable logging of SSL anomalies.									
<i>enable</i>	Enable logging of SSL anomalies.									
ssl-negotiation-log	Enable/disable logging SSL negotiation.	option	-	disable						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable logging SSL negotiation.		
	<i>enable</i>	Enable logging SSL negotiation.		
ssl-server-cert-log	Enable/disable logging of server certificate information.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable logging server certificate.		
	<i>enable</i>	Enable logging server certificate.		
ssl-handshake-log	Enable/disable logging of TLS handshakes.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable logging TLS handshakes.		
	<i>enable</i>	Enable logging TLS handshakes.		
rpc-over-https	Enable/disable inspection of RPC over HTTPS.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable inspection of RPC over HTTPS.		
	<i>disable</i>	Disable inspection of RPC over HTTPS.		
mapi-over-https	Enable/disable inspection of MAPI over HTTPS.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable inspection of MAPI over HTTPS.		
	<i>disable</i>	Disable inspection of MAPI over HTTPS.		
supported-alpn	Configure ALPN option.	option	-	all
	Option	Description		
	<i>http1-1</i>	Enable all ALPN including HTTP1.1 except HTTP2 and SPDY.		
	<i>http2</i>	Enable all ALPN including HTTP2 except HTTP1.1 and SPDY.		
	<i>all</i>	Allow all ALPN extensions except SPDY.		
	<i>none</i>	Do not use ALPN.		

config ssl

Parameter	Description	Type	Size	Default										
inspect-all	Level of SSL inspection.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr><tr><td><i>certificate-inspection</i></td><td>Inspect SSL handshake only.</td></tr><tr><td><i>deep-inspection</i></td><td>Full SSL inspection.</td></tr></table>	Option	Description	<i>disable</i>	Disable.	<i>certificate-inspection</i>	Inspect SSL handshake only.	<i>deep-inspection</i>	Full SSL inspection.					
Option	Description													
<i>disable</i>	Disable.													
<i>certificate-inspection</i>	Inspect SSL handshake only.													
<i>deep-inspection</i>	Full SSL inspection.													
client-certificate	Action based on received client certificate.	option	-	bypass										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>bypass</i></td><td>Bypass the session.</td></tr><tr><td><i>inspect</i></td><td>Inspect the session.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>bypass-on-cert-req</i></td><td>Bypass on certificate request.</td></tr></table>	Option	Description	<i>bypass</i>	Bypass the session.	<i>inspect</i>	Inspect the session.	<i>block</i>	Block the session.	<i>bypass-on-cert-req</i>	Bypass on certificate request.			
Option	Description													
<i>bypass</i>	Bypass the session.													
<i>inspect</i>	Inspect the session.													
<i>block</i>	Block the session.													
<i>bypass-on-cert-req</i>	Bypass on certificate request.													
unsupported-ssl-version	Action based on the SSL version used being unsupported.	option	-	block										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Bypass the session when the version is not supported.</td></tr><tr><td><i>block</i></td><td>Block the session when the version is not supported.</td></tr></table>	Option	Description	<i>allow</i>	Bypass the session when the version is not supported.	<i>block</i>	Block the session when the version is not supported.							
Option	Description													
<i>allow</i>	Bypass the session when the version is not supported.													
<i>block</i>	Block the session when the version is not supported.													
unsupported-ssl-cipher	Action based on the SSL cipher used being unsupported.	option	-	allow										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Bypass the session when the cipher is not supported.</td></tr><tr><td><i>block</i></td><td>Block the session when the cipher is not supported.</td></tr></table>	Option	Description	<i>allow</i>	Bypass the session when the cipher is not supported.	<i>block</i>	Block the session when the cipher is not supported.							
Option	Description													
<i>allow</i>	Bypass the session when the cipher is not supported.													
<i>block</i>	Block the session when the cipher is not supported.													
unsupported-ssl-negotiation	Action based on the SSL negotiation used being unsupported.	option	-	allow										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Bypass the session when the negotiation is not supported.</td></tr><tr><td><i>block</i></td><td>Block the session when the negotiation is not supported.</td></tr></table>	Option	Description	<i>allow</i>	Bypass the session when the negotiation is not supported.	<i>block</i>	Block the session when the negotiation is not supported.							
Option	Description													
<i>allow</i>	Bypass the session when the negotiation is not supported.													
<i>block</i>	Block the session when the negotiation is not supported.													

Parameter	Description	Type	Size	Default								
expired-server-cert	Action based on server certificate is expired.	option	-	block								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the server certificate.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>ignore</i></td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	<i>allow</i>	Allow the server certificate.	<i>block</i>	Block the session.	<i>ignore</i>	Re-sign the server certificate as trusted.			
Option	Description											
<i>allow</i>	Allow the server certificate.											
<i>block</i>	Block the session.											
<i>ignore</i>	Re-sign the server certificate as trusted.											
revoked-server-cert	Action based on server certificate is revoked.	option	-	block								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the server certificate.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>ignore</i></td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	<i>allow</i>	Allow the server certificate.	<i>block</i>	Block the session.	<i>ignore</i>	Re-sign the server certificate as trusted.			
Option	Description											
<i>allow</i>	Allow the server certificate.											
<i>block</i>	Block the session.											
<i>ignore</i>	Re-sign the server certificate as trusted.											
untrusted-server-cert	Action based on server certificate is not issued by a trusted CA.	option	-	allow								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the server certificate.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>ignore</i></td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	<i>allow</i>	Allow the server certificate.	<i>block</i>	Block the session.	<i>ignore</i>	Re-sign the server certificate as trusted.			
Option	Description											
<i>allow</i>	Allow the server certificate.											
<i>block</i>	Block the session.											
<i>ignore</i>	Re-sign the server certificate as trusted.											
cert-validation-timeout	Action based on certificate validation timeout.	option	-	allow								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the server certificate.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>ignore</i></td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	<i>allow</i>	Allow the server certificate.	<i>block</i>	Block the session.	<i>ignore</i>	Re-sign the server certificate as trusted.			
Option	Description											
<i>allow</i>	Allow the server certificate.											
<i>block</i>	Block the session.											
<i>ignore</i>	Re-sign the server certificate as trusted.											
cert-validation-failure	Action based on certificate validation failure.	option	-	block								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the server certificate.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>ignore</i></td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	<i>allow</i>	Allow the server certificate.	<i>block</i>	Block the session.	<i>ignore</i>	Re-sign the server certificate as trusted.			
Option	Description											
<i>allow</i>	Allow the server certificate.											
<i>block</i>	Block the session.											
<i>ignore</i>	Re-sign the server certificate as trusted.											

Parameter	Description	Type	Size	Default												
sni-server-cert-check	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.	option	-	enable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, use the CN in the server certificate to do URL filtering.</td></tr><tr><td><i>strict</i></td><td>Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, close the connection.</td></tr><tr><td><i>disable</i></td><td>Do not check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.</td></tr></table>	Option	Description	<i>enable</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, use the CN in the server certificate to do URL filtering.	<i>strict</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, close the connection.	<i>disable</i>	Do not check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.							
Option	Description															
<i>enable</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, use the CN in the server certificate to do URL filtering.															
<i>strict</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, close the connection.															
<i>disable</i>	Do not check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.															
cert-probe-failure	Action based on certificate probe failure.	option	-	block												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Bypass the session when unable to retrieve server's certificate for inspection.</td></tr><tr><td><i>block</i></td><td>Block the session when unable to retrieve server's certificate for inspection.</td></tr></table>	Option	Description	<i>allow</i>	Bypass the session when unable to retrieve server's certificate for inspection.	<i>block</i>	Block the session when unable to retrieve server's certificate for inspection.									
Option	Description															
<i>allow</i>	Bypass the session when unable to retrieve server's certificate for inspection.															
<i>block</i>	Block the session when unable to retrieve server's certificate for inspection.															
encrypted-client-hello	Block/allow session based on existence of encrypted-client-hello.	option	-	block												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Pass the session when encrypted-client-hello exists.</td></tr><tr><td><i>block</i></td><td>Block the session when encrypted-client-hello exists.</td></tr></table>	Option	Description	<i>allow</i>	Pass the session when encrypted-client-hello exists.	<i>block</i>	Block the session when encrypted-client-hello exists.									
Option	Description															
<i>allow</i>	Pass the session when encrypted-client-hello exists.															
<i>block</i>	Block the session when encrypted-client-hello exists.															
min-allowed-ssl-version	Minimum SSL version to be allowed.	option	-	tls-1.1												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ssl-3.0</i></td><td>SSL 3.0.</td></tr><tr><td><i>tls-1.0</i></td><td>TLS 1.0.</td></tr><tr><td><i>tls-1.1</i></td><td>TLS 1.1.</td></tr><tr><td><i>tls-1.2</i></td><td>TLS 1.2.</td></tr><tr><td><i>tls-1.3</i></td><td>TLS 1.3.</td></tr></table>	Option	Description	<i>ssl-3.0</i>	SSL 3.0.	<i>tls-1.0</i>	TLS 1.0.	<i>tls-1.1</i>	TLS 1.1.	<i>tls-1.2</i>	TLS 1.2.	<i>tls-1.3</i>	TLS 1.3.			
Option	Description															
<i>ssl-3.0</i>	SSL 3.0.															
<i>tls-1.0</i>	TLS 1.0.															
<i>tls-1.1</i>	TLS 1.1.															
<i>tls-1.2</i>	TLS 1.2.															
<i>tls-1.3</i>	TLS 1.3.															

config https

Parameter	Description	Type	Size	Default								
ports	Ports to use for scanning (1 - 65535, default = 443).	integer	Minimum value: 1 Maximum value: 65535									
status	Configure protocol inspection status.	option	-	deep-inspection								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr><tr><td><i>certificate-inspection</i></td><td>Inspect SSL handshake only.</td></tr><tr><td><i>deep-inspection</i></td><td>Full SSL inspection.</td></tr></table>	Option	Description	<i>disable</i>	Disable.	<i>certificate-inspection</i>	Inspect SSL handshake only.	<i>deep-inspection</i>	Full SSL inspection.			
Option	Description											
<i>disable</i>	Disable.											
<i>certificate-inspection</i>	Inspect SSL handshake only.											
<i>deep-inspection</i>	Full SSL inspection.											
quic	QUIC inspection status (default = inspect).	option	-	inspect								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>inspect</i></td><td>Inspect QUIC traffic.</td></tr><tr><td><i>bypass</i></td><td>Bypass QUIC traffic.</td></tr><tr><td><i>block</i></td><td>Block QUIC traffic.</td></tr></table>	Option	Description	<i>inspect</i>	Inspect QUIC traffic.	<i>bypass</i>	Bypass QUIC traffic.	<i>block</i>	Block QUIC traffic.			
Option	Description											
<i>inspect</i>	Inspect QUIC traffic.											
<i>bypass</i>	Bypass QUIC traffic.											
<i>block</i>	Block QUIC traffic.											
proxy-after-tcp-handshake	Proxy traffic after the TCP 3-way handshake has been established (not before).	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.					
Option	Description											
<i>enable</i>	Enable setting.											
<i>disable</i>	Disable setting.											
client-certificate	Action based on received client certificate.	option	-	bypass								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>bypass</i></td><td>Bypass the session.</td></tr><tr><td><i>inspect</i></td><td>Inspect the session.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr></table>	Option	Description	<i>bypass</i>	Bypass the session.	<i>inspect</i>	Inspect the session.	<i>block</i>	Block the session.			
Option	Description											
<i>bypass</i>	Bypass the session.											
<i>inspect</i>	Inspect the session.											
<i>block</i>	Block the session.											

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>bypass-on-cert-req</i>	Bypass on certificate request.		
unsupported-ssl-version	Action based on the SSL version used being unsupported.	option	-	block
	Option	Description		
	<i>allow</i>	Bypass the session when the version is not supported.		
	<i>block</i>	Block the session when the version is not supported.		
unsupported-ssl-cipher	Action based on the SSL cipher used being unsupported.	option	-	allow
	Option	Description		
	<i>allow</i>	Bypass the session when the cipher is not supported.		
	<i>block</i>	Block the session when the cipher is not supported.		
unsupported-ssl-negotiation	Action based on the SSL negotiation used being unsupported.	option	-	allow
	Option	Description		
	<i>allow</i>	Bypass the session when the negotiation is not supported.		
	<i>block</i>	Block the session when the negotiation is not supported.		
expired-server-cert	Action based on server certificate is expired.	option	-	block
	Option	Description		
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
revoked-server-cert	Action based on server certificate is revoked.	option	-	block
	Option	Description		
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		

Parameter	Description	Type	Size	Default								
untrusted-server-cert	Action based on server certificate is not issued by a trusted CA.	option	-	allow								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the server certificate.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>ignore</i></td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	<i>allow</i>	Allow the server certificate.	<i>block</i>	Block the session.	<i>ignore</i>	Re-sign the server certificate as trusted.			
Option	Description											
<i>allow</i>	Allow the server certificate.											
<i>block</i>	Block the session.											
<i>ignore</i>	Re-sign the server certificate as trusted.											
cert-validation-timeout	Action based on certificate validation timeout.	option	-	allow								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the server certificate.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>ignore</i></td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	<i>allow</i>	Allow the server certificate.	<i>block</i>	Block the session.	<i>ignore</i>	Re-sign the server certificate as trusted.			
Option	Description											
<i>allow</i>	Allow the server certificate.											
<i>block</i>	Block the session.											
<i>ignore</i>	Re-sign the server certificate as trusted.											
cert-validation-failure	Action based on certificate validation failure.	option	-	block								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the server certificate.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>ignore</i></td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	<i>allow</i>	Allow the server certificate.	<i>block</i>	Block the session.	<i>ignore</i>	Re-sign the server certificate as trusted.			
Option	Description											
<i>allow</i>	Allow the server certificate.											
<i>block</i>	Block the session.											
<i>ignore</i>	Re-sign the server certificate as trusted.											
sni-server-cert-check	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, use the CN in the server certificate to do URL filtering.</td></tr><tr><td><i>strict</i></td><td>Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, close the connection.</td></tr><tr><td><i>disable</i></td><td>Do not check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.</td></tr></table>	Option	Description	<i>enable</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, use the CN in the server certificate to do URL filtering.	<i>strict</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, close the connection.	<i>disable</i>	Do not check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.			
Option	Description											
<i>enable</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, use the CN in the server certificate to do URL filtering.											
<i>strict</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, close the connection.											
<i>disable</i>	Do not check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.											
cert-probe-failure	Action based on certificate probe failure.	option	-	block								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>allow</i>	Bypass the session when unable to retrieve server's certificate for inspection.		
	<i>block</i>	Block the session when unable to retrieve server's certificate for inspection.		
encrypted-client-hello	Block/allow session based on existence of encrypted-client-hello.	option	-	block
	Option	Description		
	<i>allow</i>	Pass the session when encrypted-client-hello exists.		
	<i>block</i>	Block the session when encrypted-client-hello exists.		
min-allowed-ssl-version	Minimum SSL version to be allowed.	option	-	tls-1.1
	Option	Description		
	<i>ssl-3.0</i>	SSL 3.0.		
	<i>tls-1.0</i>	TLS 1.0.		
	<i>tls-1.1</i>	TLS 1.1.		
	<i>tls-1.2</i>	TLS 1.2.		
	<i>tls-1.3</i>	TLS 1.3.		

config ftps

Parameter	Description	Type	Size	Default
ports	Ports to use for scanning (1 - 65535, default = 443).	integer	Minimum value: 1 Maximum value: 65535	
status	Configure protocol inspection status.	option	-	deep-inspection
	Option	Description		
	disable	Disable.		
	deep-inspection	Full SSL inspection.		

Parameter	Description	Type	Size	Default										
client-certificate	Action based on received client certificate.	option	-	bypass										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>bypass</td><td>Bypass the session.</td></tr><tr><td>inspect</td><td>Inspect the session.</td></tr><tr><td>block</td><td>Block the session.</td></tr><tr><td>bypass-on-cert-req</td><td>Bypass on certificate request.</td></tr></table>	Option	Description	bypass	Bypass the session.	inspect	Inspect the session.	block	Block the session.	bypass-on-cert-req	Bypass on certificate request.			
Option	Description													
bypass	Bypass the session.													
inspect	Inspect the session.													
block	Block the session.													
bypass-on-cert-req	Bypass on certificate request.													
unsupported-ssl-version	Action based on the SSL version used being unsupported.	option	-	block										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>allow</td><td>Bypass the session when the version is not supported.</td></tr><tr><td>block</td><td>Block the session when the version is not supported.</td></tr></table>	Option	Description	allow	Bypass the session when the version is not supported.	block	Block the session when the version is not supported.							
Option	Description													
allow	Bypass the session when the version is not supported.													
block	Block the session when the version is not supported.													
unsupported-ssl-cipher	Action based on the SSL cipher used being unsupported.	option	-	allow										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>allow</td><td>Bypass the session when the cipher is not supported.</td></tr><tr><td>block</td><td>Block the session when the cipher is not supported.</td></tr></table>	Option	Description	allow	Bypass the session when the cipher is not supported.	block	Block the session when the cipher is not supported.							
Option	Description													
allow	Bypass the session when the cipher is not supported.													
block	Block the session when the cipher is not supported.													
unsupported-ssl-negotiation	Action based on the SSL negotiation used being unsupported.	option	-	allow										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>allow</td><td>Bypass the session when the negotiation is not supported.</td></tr><tr><td>block</td><td>Block the session when the negotiation is not supported.</td></tr></table>	Option	Description	allow	Bypass the session when the negotiation is not supported.	block	Block the session when the negotiation is not supported.							
Option	Description													
allow	Bypass the session when the negotiation is not supported.													
block	Block the session when the negotiation is not supported.													
expired-server-cert	Action based on server certificate is expired.	option	-	block										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>allow</td><td>Allow the server certificate.</td></tr><tr><td>block</td><td>Block the session.</td></tr><tr><td>ignore</td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	allow	Allow the server certificate.	block	Block the session.	ignore	Re-sign the server certificate as trusted.					
Option	Description													
allow	Allow the server certificate.													
block	Block the session.													
ignore	Re-sign the server certificate as trusted.													

Parameter	Description	Type	Size	Default								
revoked-server-cert	Action based on server certificate is revoked.	option	-	block								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the server certificate.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>ignore</i></td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	<i>allow</i>	Allow the server certificate.	<i>block</i>	Block the session.	<i>ignore</i>	Re-sign the server certificate as trusted.			
Option	Description											
<i>allow</i>	Allow the server certificate.											
<i>block</i>	Block the session.											
<i>ignore</i>	Re-sign the server certificate as trusted.											
untrusted-server-cert	Action based on server certificate is not issued by a trusted CA.	option	-	allow								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the server certificate.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>ignore</i></td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	<i>allow</i>	Allow the server certificate.	<i>block</i>	Block the session.	<i>ignore</i>	Re-sign the server certificate as trusted.			
Option	Description											
<i>allow</i>	Allow the server certificate.											
<i>block</i>	Block the session.											
<i>ignore</i>	Re-sign the server certificate as trusted.											
cert-validation-timeout	Action based on certificate validation timeout.	option	-	allow								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the server certificate.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>ignore</i></td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	<i>allow</i>	Allow the server certificate.	<i>block</i>	Block the session.	<i>ignore</i>	Re-sign the server certificate as trusted.			
Option	Description											
<i>allow</i>	Allow the server certificate.											
<i>block</i>	Block the session.											
<i>ignore</i>	Re-sign the server certificate as trusted.											
cert-validation-failure	Action based on certificate validation failure.	option	-	block								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the server certificate.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>ignore</i></td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	<i>allow</i>	Allow the server certificate.	<i>block</i>	Block the session.	<i>ignore</i>	Re-sign the server certificate as trusted.			
Option	Description											
<i>allow</i>	Allow the server certificate.											
<i>block</i>	Block the session.											
<i>ignore</i>	Re-sign the server certificate as trusted.											
sni-server-cert-check	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.	option	-	enable								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, use the CN in the server certificate to do URL filtering.		
	<i>strict</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, close the connection.		
	<i>disable</i>	Do not check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.		
min-allowed-ssl-version	Minimum SSL version to be allowed.	option	-	tls-1.1
	Option	Description		
	<i>ssl-3.0</i>	SSL 3.0.		
	<i>tls-1.0</i>	TLS 1.0.		
	<i>tls-1.1</i>	TLS 1.1.		
	<i>tls-1.2</i>	TLS 1.2.		
	<i>tls-1.3</i>	TLS 1.3.		

config imaps

Parameter	Description	Type	Size	Default
ports	Ports to use for scanning (1 - 65535, default = 443).	integer	Minimum value: 1 Maximum value: 65535	
status	Configure protocol inspection status.	option	-	deep-inspection
	Option	Description		
	disable	Disable.		
	deep-inspection	Full SSL inspection.		
proxy-after-tcp-handshake	Proxy traffic after the TCP 3-way handshake has been established (not before).	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
client-certificate	Action based on received client certificate.	option	-	inspect
	Option	Description		
	<i>bypass</i>	Bypass the session.		
	<i>inspect</i>	Inspect the session.		
	<i>block</i>	Block the session.		
	<i>bypass-on-cert-req</i>	Bypass on certificate request.		
unsupported-ssl-version	Action based on the SSL version used being unsupported.	option	-	block
	Option	Description		
	<i>allow</i>	Bypass the session when the version is not supported.		
	<i>block</i>	Block the session when the version is not supported.		
unsupported-ssl-cipher	Action based on the SSL cipher used being unsupported.	option	-	allow
	Option	Description		
	<i>allow</i>	Bypass the session when the cipher is not supported.		
	<i>block</i>	Block the session when the cipher is not supported.		
unsupported-ssl-negotiation	Action based on the SSL negotiation used being unsupported.	option	-	allow
	Option	Description		
	<i>allow</i>	Bypass the session when the negotiation is not supported.		
	<i>block</i>	Block the session when the negotiation is not supported.		
expired-server-cert	Action based on server certificate is expired.	option	-	block

Parameter	Description	Type	Size	Default
	Option Description			
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
revoked-server-cert	Action based on server certificate is revoked.	option	-	block
	Option Description			
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
untrusted-server-cert	Action based on server certificate is not issued by a trusted CA.	option	-	allow
	Option Description			
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
cert-validation-timeout	Action based on certificate validation timeout.	option	-	allow
	Option Description			
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
cert-validation-failure	Action based on certificate validation failure.	option	-	block
	Option Description			
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
sni-server-cert-check	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.	option	-	enable

Parameter	Description	Type	Size	Default
	Option Description			
	<i>enable</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, use the CN in the server certificate to do URL filtering.		
	<i>strict</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, close the connection.		
	<i>disable</i>	Do not check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.		

config pop3s

Parameter	Description	Type	Size	Default
ports	Ports to use for scanning (1 - 65535, default = 443).	integer	Minimum value: 1 Maximum value: 65535	
status	Configure protocol inspection status.	option	-	deep-inspection
	Option Description			
	<i>disable</i>	Disable.		
	<i>deep-inspection</i>	Full SSL inspection.		
proxy-after-tcp-handshake	Proxy traffic after the TCP 3-way handshake has been established (not before).	option	-	disable
	Option Description			
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
client-certificate	Action based on received client certificate.	option	-	inspect
	Option Description			
	<i>bypass</i>	Bypass the session.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>inspect</i>	Inspect the session.		
	<i>block</i>	Block the session.		
	<i>bypass-on-cert-req</i>	Bypass on certificate request.		
unsupported-ssl-version	Action based on the SSL version used being unsupported.	option	-	block
	Option	Description		
	<i>allow</i>	Bypass the session when the version is not supported.		
	<i>block</i>	Block the session when the version is not supported.		
unsupported-ssl-cipher	Action based on the SSL cipher used being unsupported.	option	-	allow
	Option	Description		
	<i>allow</i>	Bypass the session when the cipher is not supported.		
	<i>block</i>	Block the session when the cipher is not supported.		
unsupported-ssl-negotiation	Action based on the SSL negotiation used being unsupported.	option	-	allow
	Option	Description		
	<i>allow</i>	Bypass the session when the negotiation is not supported.		
	<i>block</i>	Block the session when the negotiation is not supported.		
expired-server-cert	Action based on server certificate is expired.	option	-	block
	Option	Description		
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
revoked-server-cert	Action based on server certificate is revoked.	option	-	block

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
untrusted-server-cert	Action based on server certificate is not issued by a trusted CA.	option	-	allow
	Option	Description		
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
cert-validation-timeout	Action based on certificate validation timeout.	option	-	allow
	Option	Description		
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
cert-validation-failure	Action based on certificate validation failure.	option	-	block
	Option	Description		
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
sni-server-cert-check	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.	option	-	enable
	Option	Description		
	<i>enable</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, use the CN in the server certificate to do URL filtering.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>strict</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, close the connection.		
	<i>disable</i>	Do not check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.		

config smtps

Parameter	Description	Type	Size	Default
ports	Ports to use for scanning (1 - 65535, default = 443).	integer	Minimum value: 1 Maximum value: 65535	
status	Configure protocol inspection status.	option	-	deep-inspection
	Option	Description		
	<i>disable</i>	Disable.		
	<i>deep-inspection</i>	Full SSL inspection.		
proxy-after-tcp-handshake	Proxy traffic after the TCP 3-way handshake has been established (not before).	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
client-certificate	Action based on received client certificate.	option	-	inspect
	Option	Description		
	<i>bypass</i>	Bypass the session.		
	<i>inspect</i>	Inspect the session.		
	<i>block</i>	Block the session.		
	<i>bypass-on-cert-req</i>	Bypass on certificate request.		

Parameter	Description	Type	Size	Default								
unsupported-ssl-version	Action based on the SSL version used being unsupported.	option	-	block								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Bypass the session when the version is not supported.</td></tr><tr><td><i>block</i></td><td>Block the session when the version is not supported.</td></tr></table>	Option	Description	<i>allow</i>	Bypass the session when the version is not supported.	<i>block</i>	Block the session when the version is not supported.					
Option	Description											
<i>allow</i>	Bypass the session when the version is not supported.											
<i>block</i>	Block the session when the version is not supported.											
unsupported-ssl-cipher	Action based on the SSL cipher used being unsupported.	option	-	allow								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Bypass the session when the cipher is not supported.</td></tr><tr><td><i>block</i></td><td>Block the session when the cipher is not supported.</td></tr></table>	Option	Description	<i>allow</i>	Bypass the session when the cipher is not supported.	<i>block</i>	Block the session when the cipher is not supported.					
Option	Description											
<i>allow</i>	Bypass the session when the cipher is not supported.											
<i>block</i>	Block the session when the cipher is not supported.											
unsupported-ssl-negotiation	Action based on the SSL negotiation used being unsupported.	option	-	allow								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Bypass the session when the negotiation is not supported.</td></tr><tr><td><i>block</i></td><td>Block the session when the negotiation is not supported.</td></tr></table>	Option	Description	<i>allow</i>	Bypass the session when the negotiation is not supported.	<i>block</i>	Block the session when the negotiation is not supported.					
Option	Description											
<i>allow</i>	Bypass the session when the negotiation is not supported.											
<i>block</i>	Block the session when the negotiation is not supported.											
expired-server-cert	Action based on server certificate is expired.	option	-	block								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the server certificate.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>ignore</i></td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	<i>allow</i>	Allow the server certificate.	<i>block</i>	Block the session.	<i>ignore</i>	Re-sign the server certificate as trusted.			
Option	Description											
<i>allow</i>	Allow the server certificate.											
<i>block</i>	Block the session.											
<i>ignore</i>	Re-sign the server certificate as trusted.											
revoked-server-cert	Action based on server certificate is revoked.	option	-	block								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the server certificate.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>ignore</i></td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	<i>allow</i>	Allow the server certificate.	<i>block</i>	Block the session.	<i>ignore</i>	Re-sign the server certificate as trusted.			
Option	Description											
<i>allow</i>	Allow the server certificate.											
<i>block</i>	Block the session.											
<i>ignore</i>	Re-sign the server certificate as trusted.											
untrusted-server-cert	Action based on server certificate is not issued by a trusted CA.	option	-	allow								

Parameter	Description	Type	Size	Default
	Option Description			
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
cert-validation-timeout	Action based on certificate validation timeout.	option	-	allow
	Option Description			
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
cert-validation-failure	Action based on certificate validation failure.	option	-	block
	Option Description			
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
sni-server-cert-check	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.	option	-	enable
	Option Description			
	<i>enable</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, use the CN in the server certificate to do URL filtering.		
	<i>strict</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, close the connection.		
	<i>disable</i>	Do not check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.		

config ssh

Parameter	Description	Type	Size	Default						
ports	Ports to use for scanning (1 - 65535, default = 443).	integer	Minimum value: 1 Maximum value: 65535							
status	Configure protocol inspection status.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr><tr><td><i>deep-inspection</i></td><td>Full SSL inspection.</td></tr></table>	Option	Description	<i>disable</i>	Disable.	<i>deep-inspection</i>	Full SSL inspection.			
Option	Description									
<i>disable</i>	Disable.									
<i>deep-inspection</i>	Full SSL inspection.									
proxy-after-tcp-handshake	Proxy traffic after the TCP 3-way handshake has been established (not before).	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
unsupported-version	Action based on SSH version being unsupported.	option	-	bypass						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>bypass</i></td><td>Bypass the session.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr></table>	Option	Description	<i>bypass</i>	Bypass the session.	<i>block</i>	Block the session.			
Option	Description									
<i>bypass</i>	Bypass the session.									
<i>block</i>	Block the session.									
ssh-tun-policy-check	Enable/disable SSH tunnel policy check.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable SSH tunnel policy check.</td></tr><tr><td><i>enable</i></td><td>Enable SSH tunnel policy check.</td></tr></table>	Option	Description	<i>disable</i>	Disable SSH tunnel policy check.	<i>enable</i>	Enable SSH tunnel policy check.			
Option	Description									
<i>disable</i>	Disable SSH tunnel policy check.									
<i>enable</i>	Enable SSH tunnel policy check.									
ssh-algorithm	Relative strength of encryption algorithms accepted during negotiation.	option	-	compatible						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>compatible</i></td><td>Allow a broader set of encryption algorithms for best compatibility.</td></tr></table>	Option	Description	<i>compatible</i>	Allow a broader set of encryption algorithms for best compatibility.					
Option	Description									
<i>compatible</i>	Allow a broader set of encryption algorithms for best compatibility.									

Parameter	Description	Type	Size	Default
	Option Description <i>high-encryption</i> Allow only AES-CTR, AES-GCM ciphers and high encryption algorithms.			

config dot

Parameter	Description	Type	Size	Default
status	Configure protocol inspection status.	option	-	disable
	Option Description <i>disable</i> Disable. <i>deep-inspection</i> Full SSL inspection.			
quic	QUIC inspection status (default = inspect).	option	-	inspect
	Option Description <i>inspect</i> Inspect QUIC traffic. <i>bypass</i> Bypass QUIC traffic. <i>block</i> Block QUIC traffic.			
proxy-after-tcp-handshake	Proxy traffic after the TCP 3-way handshake has been established (not before).	option	-	disable
	Option Description <i>enable</i> Enable setting. <i>disable</i> Disable setting.			
client-certificate	Action based on received client certificate.	option	-	bypass
	Option Description <i>bypass</i> Bypass the session. <i>inspect</i> Inspect the session. <i>block</i> Block the session. <i>bypass-on-cert-req</i> Bypass on certificate request.			

Parameter	Description	Type	Size	Default								
unsupported-ssl-version	Action based on the SSL version used being unsupported.	option	-	block								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Bypass the session when the version is not supported.</td></tr><tr><td><i>block</i></td><td>Block the session when the version is not supported.</td></tr></table>	Option	Description	<i>allow</i>	Bypass the session when the version is not supported.	<i>block</i>	Block the session when the version is not supported.					
Option	Description											
<i>allow</i>	Bypass the session when the version is not supported.											
<i>block</i>	Block the session when the version is not supported.											
unsupported-ssl-cipher	Action based on the SSL cipher used being unsupported.	option	-	allow								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Bypass the session when the cipher is not supported.</td></tr><tr><td><i>block</i></td><td>Block the session when the cipher is not supported.</td></tr></table>	Option	Description	<i>allow</i>	Bypass the session when the cipher is not supported.	<i>block</i>	Block the session when the cipher is not supported.					
Option	Description											
<i>allow</i>	Bypass the session when the cipher is not supported.											
<i>block</i>	Block the session when the cipher is not supported.											
unsupported-ssl-negotiation	Action based on the SSL negotiation used being unsupported.	option	-	allow								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Bypass the session when the negotiation is not supported.</td></tr><tr><td><i>block</i></td><td>Block the session when the negotiation is not supported.</td></tr></table>	Option	Description	<i>allow</i>	Bypass the session when the negotiation is not supported.	<i>block</i>	Block the session when the negotiation is not supported.					
Option	Description											
<i>allow</i>	Bypass the session when the negotiation is not supported.											
<i>block</i>	Block the session when the negotiation is not supported.											
expired-server-cert	Action based on server certificate is expired.	option	-	block								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the server certificate.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>ignore</i></td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	<i>allow</i>	Allow the server certificate.	<i>block</i>	Block the session.	<i>ignore</i>	Re-sign the server certificate as trusted.			
Option	Description											
<i>allow</i>	Allow the server certificate.											
<i>block</i>	Block the session.											
<i>ignore</i>	Re-sign the server certificate as trusted.											
revoked-server-cert	Action based on server certificate is revoked.	option	-	block								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the server certificate.</td></tr><tr><td><i>block</i></td><td>Block the session.</td></tr><tr><td><i>ignore</i></td><td>Re-sign the server certificate as trusted.</td></tr></table>	Option	Description	<i>allow</i>	Allow the server certificate.	<i>block</i>	Block the session.	<i>ignore</i>	Re-sign the server certificate as trusted.			
Option	Description											
<i>allow</i>	Allow the server certificate.											
<i>block</i>	Block the session.											
<i>ignore</i>	Re-sign the server certificate as trusted.											
untrusted-server-cert	Action based on server certificate is not issued by a trusted CA.	option	-	allow								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
cert-validation-timeout	Action based on certificate validation timeout.	option	-	allow
	Option	Description		
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
cert-validation-failure	Action based on certificate validation failure.	option	-	block
	Option	Description		
	<i>allow</i>	Allow the server certificate.		
	<i>block</i>	Block the session.		
	<i>ignore</i>	Re-sign the server certificate as trusted.		
sni-server-cert-check	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.	option	-	enable
	Option	Description		
	<i>enable</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, use the CN in the server certificate to do URL filtering.		
	<i>strict</i>	Check the SNI in the client hello message with the CN or SAN fields in the returned server certificate. If mismatched, close the connection.		
	<i>disable</i>	Do not check the SNI in the client hello message with the CN or SAN fields in the returned server certificate.		

config ssl-client-certificate

Parameter	Description	Type	Size	Default
status	Configure SSL client certificate status.	option	-	do-not-offer
	Option	Description		
	<i>do-not-offer</i>	Do not offer SSL client certificate.		
	<i>keyring-list</i>	For authenticated users, offer matching SSL client certificate from keyring list.		
	<i>ca-sign</i>	For authenticated users, offer SSL client certificate signed by configured CA.		
	<i>static</i>	Offer static SSL client certificate.		
keyring-list	Keyring list used to find client certificate.	string	Maximum length: 35	
caname	CA certificate used to sign client certificate.	string	Maximum length: 35	Fortinet_CA_SSL
cert	Client certificate.	string	Maximum length: 35	

config ssl-exempt

Parameter	Description	Type	Size	Default
id	ID number.	integer	Minimum value: 0 Maximum value: 512	0
type	Type of address object (IPv4 or IPv6) or FortiGuard category.	option	-	fortiguard-category
	Option	Description		
	<i>fortiguard-category</i>	FortiGuard category.		
	<i>address</i>	Firewall IPv4 address.		
	<i>address6</i>	Firewall IPv6 address.		
	<i>wildcard-fqdn</i>	Fully Qualified Domain Name with wildcard characters.		
	<i>regex</i>	Regular expression FQDN.		
	<i>finger-print</i>	TLS finger print.		

Parameter	Description	Type	Size	Default																				
fortiguard-category	FortiGuard category ID.	integer	Minimum value: 0 Maximum value: 255	0																				
address	IPv4 address object.	string	Maximum length: 79																					
address6	IPv6 address object.	string	Maximum length: 79																					
wildcard-fqdn	Exempt servers by wildcard FQDN.	string	Maximum length: 79																					
regex	Exempt servers by regular expression.	string	Maximum length: 255																					
finger-print-category	Finger print platform.	option	-	android																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>unknown</td><td>Unknown clients.</td></tr><tr><td>firefox</td><td>Firefox.</td></tr><tr><td>chrome</td><td>Chrome.</td></tr><tr><td>safari</td><td>Safari.</td></tr><tr><td>edge</td><td>Edge.</td></tr><tr><td>ie</td><td>Internet Explorer.</td></tr><tr><td>android</td><td>Android applications.</td></tr><tr><td>ios</td><td>iOS applications.</td></tr><tr><td>windows</td><td>Windows applications.</td></tr></table>				Option	Description	unknown	Unknown clients.	firefox	Firefox.	chrome	Chrome.	safari	Safari.	edge	Edge.	ie	Internet Explorer.	android	Android applications.	ios	iOS applications.	windows	Windows applications.
Option	Description																							
unknown	Unknown clients.																							
firefox	Firefox.																							
chrome	Chrome.																							
safari	Safari.																							
edge	Edge.																							
ie	Internet Explorer.																							
android	Android applications.																							
ios	iOS applications.																							
windows	Windows applications.																							

config ech-outer-sni

Parameter	Description	Type	Size	Default
name	ClientHelloOuter SNI name.	string	Maximum length: 79	
sni	ClientHelloOuter SNI to be blocked.	string	Maximum length: 255	

config ssl-server

Parameter	Description	Type	Size	Default								
id	SSL server ID.	integer	Minimum value: 0 Maximum value: 4294967295	0								
ip	IPv4 address of the SSL server.	ipv4-address-any	Not Specified	0.0.0.0								
https-client-certificate	Action based on received client certificate during the HTTPS handshake.	option	-	bypass								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>bypass</td><td>Bypass the session.</td></tr><tr><td>inspect</td><td>Inspect the session.</td></tr><tr><td>block</td><td>Block the session.</td></tr></table>	Option	Description	bypass	Bypass the session.	inspect	Inspect the session.	block	Block the session.			
Option	Description											
bypass	Bypass the session.											
inspect	Inspect the session.											
block	Block the session.											
smtps-client-certificate	Action based on received client certificate during the SMTPS handshake.	option	-	bypass								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>bypass</td><td>Bypass the session.</td></tr><tr><td>inspect</td><td>Inspect the session.</td></tr><tr><td>block</td><td>Block the session.</td></tr></table>	Option	Description	bypass	Bypass the session.	inspect	Inspect the session.	block	Block the session.			
Option	Description											
bypass	Bypass the session.											
inspect	Inspect the session.											
block	Block the session.											
pop3s-client-certificate	Action based on received client certificate during the POP3S handshake.	option	-	bypass								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>bypass</td><td>Bypass the session.</td></tr><tr><td>inspect</td><td>Inspect the session.</td></tr><tr><td>block</td><td>Block the session.</td></tr></table>	Option	Description	bypass	Bypass the session.	inspect	Inspect the session.	block	Block the session.			
Option	Description											
bypass	Bypass the session.											
inspect	Inspect the session.											
block	Block the session.											
imaps-client-certificate	Action based on received client certificate during the IMAPS handshake.	option	-	bypass								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>bypass</i>	Bypass the session.		
	<i>inspect</i>	Inspect the session.		
	<i>block</i>	Block the session.		
ftps-client-certificate	Action based on received client certificate during the FTPS handshake.	option	-	bypass
	Option	Description		
	<i>bypass</i>	Bypass the session.		
	<i>inspect</i>	Inspect the session.		
	<i>block</i>	Block the session.		
ssl-other-client-certificate	Action based on received client certificate during an SSL protocol handshake.	option	-	bypass
	Option	Description		
	<i>bypass</i>	Bypass the session.		
	<i>inspect</i>	Inspect the session.		
	<i>block</i>	Block the session.		

config firewall traffic-class

Configure names for shaping classes.

```

config firewall traffic-class
    Description: Configure names for shaping classes.
    edit <class-id>
        set class-name {string}
    next
end

```

config firewall traffic-class

Parameter	Description	Type	Size	Default
class-id	Class ID to be named.	integer	Minimum value: 2 Maximum value: 31	0
class-name	Define the name for this class-id.	string	Maximum length: 35	

config firewall ttl-policy

Configure TTL policies.

```
config firewall ttl-policy
  Description: Configure TTL policies.
  edit <id>
    set status [enable|disable]
    set action [accept|deny]
    set srcintf {string}
    set srcaddr <name1>, <name2>, ...
    set service <name1>, <name2>, ...
    set schedule {string}
    set ttl {user}
  next
end
```

config firewall ttl-policy

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
status	Enable/disable this TTL policy.	option	-	enable
	Option	Description		
	enable	Enable this TTL policy.		
	disable	Disable this TTL policy.		

Parameter	Description	Type	Size	Default						
action	Action to be performed on traffic matching this policy (default = deny).	option	-	deny						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>accept</i></td><td>Allow traffic matching this policy.</td></tr><tr><td><i>deny</i></td><td>Deny or block traffic matching this policy.</td></tr></table>				Option	Description	<i>accept</i>	Allow traffic matching this policy.	<i>deny</i>	Deny or block traffic matching this policy.
	Option	Description								
	<i>accept</i>	Allow traffic matching this policy.								
<i>deny</i>	Deny or block traffic matching this policy.									
srcintf	Source interface name from available interfaces.	string	Maximum length: 35							
srcaddr <name>	Source address object(s) from available options. Separate multiple names with a space. Address name.	string	Maximum length: 79							
service <name>	Service object(s) from available options. Separate multiple names with a space. Service name.	string	Maximum length: 79							
schedule	Schedule object from available options.	string	Maximum length: 35							
ttl	Value/range to match against the packet's Time to Live value (format: ttl[- ttl_high], 1 - 255).	user	Not Specified							

config firewall vendor-mac

Show vendor and the MAC address they have.

```
config firewall vendor-mac
  Description: Show vendor and the MAC address they have.
  edit <id>
    set name {string}
    set mac-number {integer}
    set obsolete {integer}
  next
end
```

config firewall vendor-mac

Parameter	Description	Type	Size	Default
id	Vendor ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Vendor name.	string	Maximum length: 63	
mac-number	Total number of MAC addresses.	integer	Minimum value: 0 Maximum value: 4294967295	0
obsolete	Indicates whether the Vendor ID can be used.	integer	Minimum value: 0 Maximum value: 255	0

config firewall vendor-mac-summary

Vendor MAC database summary.

```
config firewall vendor-mac-summary
  Description: Vendor MAC database summary.
end
```

config firewall vip

Configure virtual IP for IPv4.

```
config firewall vip
  Description: Configure virtual IP for IPv4.
  edit <name>
    set id {integer}
    set uuid {uuid}
    set comment {var-string}
    set type [static-nat|server-load-balance|...]
    set server-type [http|https|...]
    set ldb-method [static|round-robin|...]
    set extip {user}
    set h2-support [enable|disable]
```



```

set h3-support [enable|disable]
config quic
    Description: QUIC setting.
    set max-idle-timeout {integer}
    set max-udp-payload-size {integer}
    set active-connection-id-limit {integer}
    set ack-delay-exponent {integer}
    set max-ack-delay {integer}
    set max-datagram-frame-size {integer}
    set active-migration [enable|disable]
    set grease-quic-bit [enable|disable]
end
set mappedip <range1>, <range2>, ...
set extintf {string}
set arp-reply [disable|enable]
set http-redirect [enable|disable]
set persistence [none|http-cookie|...]
set portforward [disable|enable]
set status [disable|enable]
set protocol [tcp|udp|...]
set extport {user}
set mappedport {user}
set gratuitous-arp-interval {integer}
config realservers
    Description: Select the real servers that this server load balancing VIP will
distribute traffic to.
    edit <id>
        set type [ip|address]
        set address {string}
        set ip {user}
        set port {integer}
        set status [active|standby|...]
        set weight {integer}
        set holddown-interval {integer}
        set healthcheck [disable|enable]
        set health-check-proto [ping|http]
        set http-host {string}
        set translate-host [enable|disable]
        set max-connections {integer}
        set client-ip {user}
        set verify-cert [enable|disable]
    next
end
set http-cookie-domain-from-host [disable|enable]
set http-cookie-domain {string}
set http-cookie-path {string}
set http-cookie-generation {integer}
set http-cookie-age {integer}
set http-cookie-share [disable|same-ip]
set https-cookie-secure [disable|enable]
set http-multiplex [enable|disable]
set http-multiplex-ttl {integer}

```

```

set http-multiplex-max-request {integer}
set http-multiplex-max-concurrent-request {integer}
set http-ip-header [enable|disable]
set http-ip-header-name {string}
set outlook-web-access [disable|enable]
set weblogic-server [disable|enable]
set websphere-server [disable|enable]
set ssl-mode [half|full]
set ssl-certificate <name1>, <name2>, ...
set ssl-dh-bits [768|1024|...]
set ssl-algorithm [high|medium|...]
config ssl-cipher-suites
    Description: SSL/TLS cipher suites acceptable from a client, ordered by priority.
    edit <priority>
        set cipher [TLS-AES-128-GCM-SHA256|TLS-AES-256-GCM-SHA384|...]
        set versions {option1}, {option2}, ...
    next
end
set ssl-server-algorithm [high|medium|...]
config ssl-server-cipher-suites
    Description: SSL/TLS cipher suites to offer to a server, ordered by priority.
    edit <priority>
        set cipher [TLS-AES-128-GCM-SHA256|TLS-AES-256-GCM-SHA384|...]
        set versions {option1}, {option2}, ...
    next
end
set ssl-pfs [require|deny|...]
set ssl-min-version [ssl-3.0|tls-1.0|...]
set ssl-max-version [ssl-3.0|tls-1.0|...]
set ssl-server-min-version [ssl-3.0|tls-1.0|...]
set ssl-server-max-version [ssl-3.0|tls-1.0|...]
set ssl-accept-ffdhe-groups [enable|disable]
set ssl-send-empty-frags [enable|disable]
set ssl-client-fallback [disable|enable]
set ssl-client-renegotiation [allow|deny|...]
set ssl-client-session-state-type [disable|time|...]
set ssl-client-session-state-timeout {integer}
set ssl-client-session-state-max {integer}
set ssl-client-rekey-count {integer}
set ssl-server-renegotiation [enable|disable]
set ssl-server-session-state-type [disable|time|...]
set ssl-server-session-state-timeout {integer}
set ssl-server-session-state-max {integer}
set ssl-http-location-conversion [enable|disable]
set ssl-http-match-host [enable|disable]
set ssl-hpkp [disable|enable|...]
set ssl-hpkp-primary {string}
set ssl-hpkp-backup {string}
set ssl-hpkp-age {integer}
set ssl-hpkp-report-uri {var-string}
set ssl-hpkp-include-subdomains [disable|enable]
set ssl-hsts [disable|enable]

```

```

        set ssl-hsts-age {integer}
        set ssl-hsts-include-subdomains [disable|enable]
        set max-embryonic-connections {integer}
        set color {integer}
    next
end

```

config firewall vip

Parameter	Description	Type	Size	Default
name	Virtual IP name.	string	Maximum length: 79	
id	Custom defined ID.	integer	Minimum value: 0 Maximum value: 65535	0
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000
comment	Comment.	var-string	Maximum length: 255	
type	Configure between a static NAT and access proxy VIP.	option	-	static-nat
	Option		Description	
	<i>static-nat</i>		Static NAT.	
	<i>server-load-balance</i>		Server load balance.	
	<i>access-proxy</i>		Access proxy.	
server-type	Protocol to be load balanced by the virtual server (also called the server load balance virtual IP).	option	-	
	Option		Description	
	<i>http</i>		HTTP.	
	<i>https</i>		HTTPS.	
	<i>imaps</i>		IMAPS.	
	<i>pop3s</i>		POP3S.	

Parameter	Description	Type	Size	Default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>smtps</i></td><td>SMTPS.</td></tr><tr><td><i>ssl</i></td><td>SSL.</td></tr><tr><td><i>tcp</i></td><td>TCP.</td></tr><tr><td><i>udp</i></td><td>UDP.</td></tr><tr><td><i>ip</i></td><td>IP.</td></tr></table>	Option	Description	<i>smtps</i>	SMTPS.	<i>ssl</i>	SSL.	<i>tcp</i>	TCP.	<i>udp</i>	UDP.	<i>ip</i>	IP.			
	Option	Description														
	<i>smtps</i>	SMTPS.														
	<i>ssl</i>	SSL.														
	<i>tcp</i>	TCP.														
	<i>udp</i>	UDP.														
	<i>ip</i>	IP.														
ldb-method	Method used to distribute sessions to real servers.	option	-	static												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>static</i></td><td>Distribute to server based on source IP.</td></tr><tr><td><i>round-robin</i></td><td>Distribute to server based round robin order.</td></tr><tr><td><i>weighted</i></td><td>Distribute to server based on weight.</td></tr><tr><td><i>first-alive</i></td><td>Distribute to the first server that is alive.</td></tr><tr><td><i>http-host</i></td><td>Distribute to server based on host field in HTTP header.</td></tr></table>	Option	Description	<i>static</i>	Distribute to server based on source IP.	<i>round-robin</i>	Distribute to server based round robin order.	<i>weighted</i>	Distribute to server based on weight.	<i>first-alive</i>	Distribute to the first server that is alive.	<i>http-host</i>	Distribute to server based on host field in HTTP header.			
	Option	Description														
	<i>static</i>	Distribute to server based on source IP.														
	<i>round-robin</i>	Distribute to server based round robin order.														
	<i>weighted</i>	Distribute to server based on weight.														
	<i>first-alive</i>	Distribute to the first server that is alive.														
<i>http-host</i>	Distribute to server based on host field in HTTP header.															
extip	IP address or address range on the external interface that you want to map to an address or address range on the destination network.	user	Not Specified													
h2-support	Enable/disable HTTP2 support (default = enable).	option	-	enable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable HTTP2 support.</td></tr><tr><td><i>disable</i></td><td>Disable HTTP2 support.</td></tr></table>	Option	Description	<i>enable</i>	Enable HTTP2 support.	<i>disable</i>	Disable HTTP2 support.									
	Option	Description														
	<i>enable</i>	Enable HTTP2 support.														
<i>disable</i>	Disable HTTP2 support.															
h3-support	Enable/disable HTTP3/QUIC support (default = disable).	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable HTTP3/QUIC support.</td></tr><tr><td><i>disable</i></td><td>Disable HTTP3/QUIC support.</td></tr></table>	Option	Description	<i>enable</i>	Enable HTTP3/QUIC support.	<i>disable</i>	Disable HTTP3/QUIC support.									
	Option	Description														
	<i>enable</i>	Enable HTTP3/QUIC support.														
<i>disable</i>	Disable HTTP3/QUIC support.															

Parameter	Description	Type	Size	Default								
mappedip <range>	IP address or address range on the destination network to which the external IP address is mapped. Mapped IP range.	string	Maximum length: 79									
extintf	Interface connected to the source network that receives the packets that will be forwarded to the destination network.	string	Maximum length: 35									
arp-reply	Enable to respond to ARP requests for this virtual IP address. Enabled by default.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable ARP reply.</td></tr><tr><td><i>enable</i></td><td>Enable ARP reply.</td></tr></table>				Option	Description	<i>disable</i>	Disable ARP reply.	<i>enable</i>	Enable ARP reply.		
Option	Description											
<i>disable</i>	Disable ARP reply.											
<i>enable</i>	Enable ARP reply.											
http-redirect	Enable/disable redirection of HTTP to HTTPS.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable redirection of HTTP to HTTPS.</td></tr><tr><td><i>disable</i></td><td>Disable redirection of HTTP to HTTPS.</td></tr></table>				Option	Description	<i>enable</i>	Enable redirection of HTTP to HTTPS.	<i>disable</i>	Disable redirection of HTTP to HTTPS.		
Option	Description											
<i>enable</i>	Enable redirection of HTTP to HTTPS.											
<i>disable</i>	Disable redirection of HTTP to HTTPS.											
persistence	Configure how to make sure that clients connect to the same server every time they make a request that is part of the same session.	option	-	none								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>none</i></td><td>None.</td></tr><tr><td><i>http-cookie</i></td><td>HTTP cookie.</td></tr><tr><td><i>ssl-session-id</i></td><td>SSL session ID.</td></tr></table>				Option	Description	<i>none</i>	None.	<i>http-cookie</i>	HTTP cookie.	<i>ssl-session-id</i>	SSL session ID.
Option	Description											
<i>none</i>	None.											
<i>http-cookie</i>	HTTP cookie.											
<i>ssl-session-id</i>	SSL session ID.											
portforward	Enable/disable port forwarding.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable port forward.</td></tr><tr><td><i>enable</i></td><td>Enable port forward.</td></tr></table>				Option	Description	<i>disable</i>	Disable port forward.	<i>enable</i>	Enable port forward.		
Option	Description											
<i>disable</i>	Disable port forward.											
<i>enable</i>	Enable port forward.											

Parameter	Description	Type	Size	Default
status	Enable/disable VIP.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable the VIP.		
	<i>enable</i>	Enable the VIP.		
protocol	Protocol to use when forwarding packets.	option	-	tcp
	Option	Description		
	<i>tcp</i>	TCP.		
	<i>udp</i>	UDP.		
	<i>sctp</i>	SCTP.		
	<i>icmp</i>	ICMP.		
extport	Incoming port number range that you want to map to a port number range on the destination network.	user	Not Specified	
mappedport	Port number range on the destination network to which the external port number range is mapped.	user	Not Specified	
gratuitous-arp-interval	Enable to have the VIP send gratuitous ARPs. 0=disabled. Set from 5 up to 8640000 seconds to enable.	integer	Minimum value: 5 Maximum value: 8640000	0
http-cookie-domain-from-host	Enable/disable use of HTTP cookie domain from host field in HTTP.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable use of HTTP cookie domain from host field in HTTP (use http-cooke-domain setting).		
	<i>enable</i>	Enable use of HTTP cookie domain from host field in HTTP.		
http-cookie-domain	Domain that HTTP cookie persistence should apply to.	string	Maximum length: 35	
http-cookie-path	Limit HTTP cookie persistence to the specified path.	string	Maximum length: 35	

Parameter	Description	Type	Size	Default
http-cookie-generation	Generation of HTTP cookie to be accepted. Changing invalidates all existing cookies.	integer	Minimum value: 0 Maximum value: 4294967295	0
http-cookie-age	Time in minutes that client web browsers should keep a cookie. Default is 60 minutes. 0 = no time limit.	integer	Minimum value: 0 Maximum value: 525600	60
http-cookie-share	Control sharing of cookies across virtual servers. Use of same-ip means a cookie from one virtual server can be used by another. Disable stops cookie sharing.	option	-	same-ip
	Option		Description	
	<i>disable</i>		Only allow HTTP cookie to match this virtual server.	
	<i>same-ip</i>		Allow HTTP cookie to match any virtual server with same IP.	
https-cookie-secure	Enable/disable verification that inserted HTTPS cookies are secure.	option	-	disable
	Option		Description	
	<i>disable</i>		Do not mark cookie as secure, allow sharing between an HTTP and HTTPS connection.	
	<i>enable</i>		Mark inserted cookie as secure, cookie can only be used for HTTPS a connection.	
http-multiplex	Enable/disable HTTP multiplexing.	option	-	disable
	Option		Description	
	<i>enable</i>		Enable HTTP session multiplexing.	
	<i>disable</i>		Disable HTTP session multiplexing.	
http-multiplex-ttl	Time-to-live for idle connections to servers.	integer	Minimum value: 0 Maximum value: 2147483647	15

Parameter	Description	Type	Size	Default						
http-multiplex-max-request	Maximum number of requests that a multiplex server can handle before disconnecting sessions (default = unlimited).	integer	Minimum value: 0 Maximum value: 2147483647	0						
http-multiplex-max-concurrent-request	Maximum number of concurrent requests that a multiplex server can handle (default = unlimited).	integer	Minimum value: 0 Maximum value: 2147483647	0						
http-ip-header	For HTTP multiplexing, enable to add the original client IP address in the XForwarded-For HTTP header.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable adding HTTP header.</td></tr><tr><td><i>disable</i></td><td>Disable adding HTTP header.</td></tr></table>				Option	Description	<i>enable</i>	Enable adding HTTP header.	<i>disable</i>	Disable adding HTTP header.
Option	Description									
<i>enable</i>	Enable adding HTTP header.									
<i>disable</i>	Disable adding HTTP header.									
http-ip-header-name	For HTTP multiplexing, enter a custom HTTPS header name. The original client IP address is added to this header. If empty, X-Forwarded-For is used.	string	Maximum length: 35							
outlook-web-access	Enable to add the Front-End-Https header for Microsoft Outlook Web Access.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable Outlook Web Access support.</td></tr><tr><td><i>enable</i></td><td>Enable Outlook Web Access support.</td></tr></table>				Option	Description	<i>disable</i>	Disable Outlook Web Access support.	<i>enable</i>	Enable Outlook Web Access support.
Option	Description									
<i>disable</i>	Disable Outlook Web Access support.									
<i>enable</i>	Enable Outlook Web Access support.									
weblogic-server	Enable to add an HTTP header to indicate SSL offloading for a WebLogic server.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not add HTTP header indicating SSL offload for WebLogic server.</td></tr><tr><td><i>enable</i></td><td>Add HTTP header indicating SSL offload for WebLogic server.</td></tr></table>				Option	Description	<i>disable</i>	Do not add HTTP header indicating SSL offload for WebLogic server.	<i>enable</i>	Add HTTP header indicating SSL offload for WebLogic server.
Option	Description									
<i>disable</i>	Do not add HTTP header indicating SSL offload for WebLogic server.									
<i>enable</i>	Add HTTP header indicating SSL offload for WebLogic server.									

Parameter	Description	Type	Size	Default														
websphere-server	Enable to add an HTTP header to indicate SSL offloading for a WebSphere server.	option	-	disable														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not add HTTP header indicating SSL offload for WebSphere server.</td></tr><tr><td><i>enable</i></td><td>Add HTTP header indicating SSL offload for WebSphere server.</td></tr></table>	Option	Description	<i>disable</i>	Do not add HTTP header indicating SSL offload for WebSphere server.	<i>enable</i>	Add HTTP header indicating SSL offload for WebSphere server.											
Option	Description																	
<i>disable</i>	Do not add HTTP header indicating SSL offload for WebSphere server.																	
<i>enable</i>	Add HTTP header indicating SSL offload for WebSphere server.																	
ssl-mode	Apply SSL offloading between the client and the FortiProxy (half) or from the client to the FortiProxy and from the FortiProxy to the server (full).	option	-	half														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>half</i></td><td>Client to FortiProxy SSL.</td></tr><tr><td><i>full</i></td><td>Client to FortiProxy and FortiProxy to Server SSL.</td></tr></table>	Option	Description	<i>half</i>	Client to FortiProxy SSL.	<i>full</i>	Client to FortiProxy and FortiProxy to Server SSL.											
Option	Description																	
<i>half</i>	Client to FortiProxy SSL.																	
<i>full</i>	Client to FortiProxy and FortiProxy to Server SSL.																	
ssl-certificate <name>	Name of the certificate to use for SSL handshake. Certificate list.	string	Maximum length: 79															
ssl-dh-bits	Number of bits to use in the Diffie-Hellman exchange for RSA encryption of SSL sessions.	option	-	2048														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>768</i></td><td>768-bit Diffie-Hellman prime.</td></tr><tr><td><i>1024</i></td><td>1024-bit Diffie-Hellman prime.</td></tr><tr><td><i>1536</i></td><td>1536-bit Diffie-Hellman prime.</td></tr><tr><td><i>2048</i></td><td>2048-bit Diffie-Hellman prime.</td></tr><tr><td><i>3072</i></td><td>3072-bit Diffie-Hellman prime.</td></tr><tr><td><i>4096</i></td><td>4096-bit Diffie-Hellman prime.</td></tr></table>	Option	Description	<i>768</i>	768-bit Diffie-Hellman prime.	<i>1024</i>	1024-bit Diffie-Hellman prime.	<i>1536</i>	1536-bit Diffie-Hellman prime.	<i>2048</i>	2048-bit Diffie-Hellman prime.	<i>3072</i>	3072-bit Diffie-Hellman prime.	<i>4096</i>	4096-bit Diffie-Hellman prime.			
Option	Description																	
<i>768</i>	768-bit Diffie-Hellman prime.																	
<i>1024</i>	1024-bit Diffie-Hellman prime.																	
<i>1536</i>	1536-bit Diffie-Hellman prime.																	
<i>2048</i>	2048-bit Diffie-Hellman prime.																	
<i>3072</i>	3072-bit Diffie-Hellman prime.																	
<i>4096</i>	4096-bit Diffie-Hellman prime.																	
ssl-algorithm	Permitted encryption algorithms for SSL sessions according to encryption strength.	option	-	high														

Parameter	Description	Type	Size	Default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>high</i></td><td>High encryption. Allow only AES and ChaCha.</td></tr><tr><td><i>medium</i></td><td>Medium encryption. Allow AES, ChaCha, 3DES, and RC4.</td></tr><tr><td><i>low</i></td><td>Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.</td></tr><tr><td><i>custom</i></td><td>Custom encryption. Use config ssl-cipher-suites to select the cipher suites that are allowed.</td></tr></table>	Option	Description	<i>high</i>	High encryption. Allow only AES and ChaCha.	<i>medium</i>	Medium encryption. Allow AES, ChaCha, 3DES, and RC4.	<i>low</i>	Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.	<i>custom</i>	Custom encryption. Use config ssl-cipher-suites to select the cipher suites that are allowed.					
	Option	Description														
	<i>high</i>	High encryption. Allow only AES and ChaCha.														
	<i>medium</i>	Medium encryption. Allow AES, ChaCha, 3DES, and RC4.														
	<i>low</i>	Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.														
<i>custom</i>	Custom encryption. Use config ssl-cipher-suites to select the cipher suites that are allowed.															
ssl-server-algorithm	Permitted encryption algorithms for the server side of SSL full mode sessions according to encryption strength.	option	-	client												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>high</i></td><td>High encryption. Allow only AES and ChaCha.</td></tr><tr><td><i>medium</i></td><td>Medium encryption. Allow AES, ChaCha, 3DES, and RC4.</td></tr><tr><td><i>low</i></td><td>Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.</td></tr><tr><td><i>custom</i></td><td>Custom encryption. Use ssl-server-cipher-suites to select the cipher suites that are allowed.</td></tr><tr><td><i>client</i></td><td>Use the same encryption algorithms for both client and server sessions.</td></tr></table>	Option	Description	<i>high</i>	High encryption. Allow only AES and ChaCha.	<i>medium</i>	Medium encryption. Allow AES, ChaCha, 3DES, and RC4.	<i>low</i>	Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.	<i>custom</i>	Custom encryption. Use ssl-server-cipher-suites to select the cipher suites that are allowed.	<i>client</i>	Use the same encryption algorithms for both client and server sessions.			
	Option	Description														
	<i>high</i>	High encryption. Allow only AES and ChaCha.														
	<i>medium</i>	Medium encryption. Allow AES, ChaCha, 3DES, and RC4.														
	<i>low</i>	Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.														
<i>custom</i>	Custom encryption. Use ssl-server-cipher-suites to select the cipher suites that are allowed.															
<i>client</i>	Use the same encryption algorithms for both client and server sessions.															
ssl-pfs	Select the cipher suites that can be used for SSL perfect forward secrecy (PFS). Applies to both client and server sessions.	option	-	require												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>require</i></td><td>Allow only Diffie-Hellman cipher-suites, so PFS is applied.</td></tr><tr><td><i>deny</i></td><td>Allow only non-Diffie-Hellman cipher-suites, so PFS is not applied.</td></tr><tr><td><i>allow</i></td><td>Allow use of any cipher suite so PFS may or may not be used depending on the cipher suite selected.</td></tr></table>	Option	Description	<i>require</i>	Allow only Diffie-Hellman cipher-suites, so PFS is applied.	<i>deny</i>	Allow only non-Diffie-Hellman cipher-suites, so PFS is not applied.	<i>allow</i>	Allow use of any cipher suite so PFS may or may not be used depending on the cipher suite selected.							
	Option	Description														
	<i>require</i>	Allow only Diffie-Hellman cipher-suites, so PFS is applied.														
<i>deny</i>	Allow only non-Diffie-Hellman cipher-suites, so PFS is not applied.															
<i>allow</i>	Allow use of any cipher suite so PFS may or may not be used depending on the cipher suite selected.															
ssl-min-version	Lowest SSL/TLS version acceptable from a client.	option	-	tls-1.1												

Parameter	Description	Type	Size	Default														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ssl-3.0</i></td><td>SSL 3.0.</td></tr><tr><td><i>tls-1.0</i></td><td>TLS 1.0.</td></tr><tr><td><i>tls-1.1</i></td><td>TLS 1.1.</td></tr><tr><td><i>tls-1.2</i></td><td>TLS 1.2.</td></tr><tr><td><i>tls-1.3</i></td><td>TLS 1.3.</td></tr></table>	Option	Description	<i>ssl-3.0</i>	SSL 3.0.	<i>tls-1.0</i>	TLS 1.0.	<i>tls-1.1</i>	TLS 1.1.	<i>tls-1.2</i>	TLS 1.2.	<i>tls-1.3</i>	TLS 1.3.					
	Option	Description																
	<i>ssl-3.0</i>	SSL 3.0.																
	<i>tls-1.0</i>	TLS 1.0.																
	<i>tls-1.1</i>	TLS 1.1.																
	<i>tls-1.2</i>	TLS 1.2.																
	<i>tls-1.3</i>	TLS 1.3.																
ssl-max-version	Highest SSL/TLS version acceptable from a client.	option	-	tls-1.3														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ssl-3.0</i></td><td>SSL 3.0.</td></tr><tr><td><i>tls-1.0</i></td><td>TLS 1.0.</td></tr><tr><td><i>tls-1.1</i></td><td>TLS 1.1.</td></tr><tr><td><i>tls-1.2</i></td><td>TLS 1.2.</td></tr><tr><td><i>tls-1.3</i></td><td>TLS 1.3.</td></tr></table>	Option	Description	<i>ssl-3.0</i>	SSL 3.0.	<i>tls-1.0</i>	TLS 1.0.	<i>tls-1.1</i>	TLS 1.1.	<i>tls-1.2</i>	TLS 1.2.	<i>tls-1.3</i>	TLS 1.3.					
	Option	Description																
	<i>ssl-3.0</i>	SSL 3.0.																
	<i>tls-1.0</i>	TLS 1.0.																
	<i>tls-1.1</i>	TLS 1.1.																
	<i>tls-1.2</i>	TLS 1.2.																
	<i>tls-1.3</i>	TLS 1.3.																
ssl-server-min-version	Lowest SSL/TLS version acceptable from a server. Use the client setting by default.	option	-	client														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ssl-3.0</i></td><td>SSL 3.0.</td></tr><tr><td><i>tls-1.0</i></td><td>TLS 1.0.</td></tr><tr><td><i>tls-1.1</i></td><td>TLS 1.1.</td></tr><tr><td><i>tls-1.2</i></td><td>TLS 1.2.</td></tr><tr><td><i>tls-1.3</i></td><td>TLS 1.3.</td></tr><tr><td><i>client</i></td><td>Use same value as client configuration.</td></tr></table>	Option	Description	<i>ssl-3.0</i>	SSL 3.0.	<i>tls-1.0</i>	TLS 1.0.	<i>tls-1.1</i>	TLS 1.1.	<i>tls-1.2</i>	TLS 1.2.	<i>tls-1.3</i>	TLS 1.3.	<i>client</i>	Use same value as client configuration.			
	Option	Description																
	<i>ssl-3.0</i>	SSL 3.0.																
	<i>tls-1.0</i>	TLS 1.0.																
	<i>tls-1.1</i>	TLS 1.1.																
	<i>tls-1.2</i>	TLS 1.2.																
	<i>tls-1.3</i>	TLS 1.3.																
<i>client</i>	Use same value as client configuration.																	
ssl-server-max-version	Highest SSL/TLS version acceptable from a server. Use the client setting by default.	option	-	client														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ssl-3.0</i></td><td>SSL 3.0.</td></tr><tr><td><i>tls-1.0</i></td><td>TLS 1.0.</td></tr></table>	Option	Description	<i>ssl-3.0</i>	SSL 3.0.	<i>tls-1.0</i>	TLS 1.0.											
	Option	Description																
	<i>ssl-3.0</i>	SSL 3.0.																
<i>tls-1.0</i>	TLS 1.0.																	

Parameter	Description	Type	Size	Default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>tls-1.1</i></td><td>TLS 1.1.</td></tr><tr><td><i>tls-1.2</i></td><td>TLS 1.2.</td></tr><tr><td><i>tls-1.3</i></td><td>TLS 1.3.</td></tr><tr><td><i>client</i></td><td>Use same value as client configuration.</td></tr></table>	Option	Description	<i>tls-1.1</i>	TLS 1.1.	<i>tls-1.2</i>	TLS 1.2.	<i>tls-1.3</i>	TLS 1.3.	<i>client</i>	Use same value as client configuration.			
	Option	Description												
	<i>tls-1.1</i>	TLS 1.1.												
	<i>tls-1.2</i>	TLS 1.2.												
	<i>tls-1.3</i>	TLS 1.3.												
<i>client</i>	Use same value as client configuration.													
ssl-accept-ffdhe-groups	Enable/disable FFDHE cipher suite for SSL key exchange.	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Accept FFDHE groups.</td></tr><tr><td><i>disable</i></td><td>Do not accept FFDHE groups.</td></tr></table>	Option	Description	<i>enable</i>	Accept FFDHE groups.	<i>disable</i>	Do not accept FFDHE groups.							
	Option	Description												
	<i>enable</i>	Accept FFDHE groups.												
<i>disable</i>	Do not accept FFDHE groups.													
ssl-send-empty-frags	Enable/disable sending empty fragments to avoid CBC IV attacks (SSL 3.0 & TLS 1.0 only). May need to be disabled for compatibility with older systems.	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Send empty fragments.</td></tr><tr><td><i>disable</i></td><td>Do not send empty fragments.</td></tr></table>	Option	Description	<i>enable</i>	Send empty fragments.	<i>disable</i>	Do not send empty fragments.							
	Option	Description												
	<i>enable</i>	Send empty fragments.												
<i>disable</i>	Do not send empty fragments.													
ssl-client-fallback	Enable/disable support for preventing Downgrade Attacks on client connections (RFC 7507).	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr><tr><td><i>enable</i></td><td>Enable.</td></tr></table>	Option	Description	<i>disable</i>	Disable.	<i>enable</i>	Enable.							
	Option	Description												
	<i>disable</i>	Disable.												
<i>enable</i>	Enable.													
ssl-client-renegotiation	Allow, deny, or require secure renegotiation of client sessions to comply with RFC 5746.	option	-	secure										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow a SSL client to renegotiate.</td></tr><tr><td><i>deny</i></td><td>Abort any client initiated SSL re-negotiation attempt.</td></tr></table>	Option	Description	<i>allow</i>	Allow a SSL client to renegotiate.	<i>deny</i>	Abort any client initiated SSL re-negotiation attempt.							
	Option	Description												
	<i>allow</i>	Allow a SSL client to renegotiate.												
<i>deny</i>	Abort any client initiated SSL re-negotiation attempt.													

Parameter	Description	Type	Size	Default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>secure</i></td><td>Abort any client initiated SSL re-negotiation attempt that does not use RFC 5746 Secure Renegotiation.</td></tr></table>	Option	Description	<i>secure</i>	Abort any client initiated SSL re-negotiation attempt that does not use RFC 5746 Secure Renegotiation.									
	Option	Description												
<i>secure</i>	Abort any client initiated SSL re-negotiation attempt that does not use RFC 5746 Secure Renegotiation.													
ssl-client-session-state-type	How to expire SSL sessions for the segment of the SSL connection between the client and the FortiProxy.	option	-	both										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not keep session states.</td></tr><tr><td><i>time</i></td><td>Expire session states after this many minutes.</td></tr><tr><td><i>count</i></td><td>Expire session states when this maximum is reached.</td></tr><tr><td><i>both</i></td><td>Expire session states based on time or count, whichever occurs first.</td></tr></table>	Option	Description	<i>disable</i>	Do not keep session states.	<i>time</i>	Expire session states after this many minutes.	<i>count</i>	Expire session states when this maximum is reached.	<i>both</i>	Expire session states based on time or count, whichever occurs first.			
	Option	Description												
	<i>disable</i>	Do not keep session states.												
	<i>time</i>	Expire session states after this many minutes.												
	<i>count</i>	Expire session states when this maximum is reached.												
<i>both</i>	Expire session states based on time or count, whichever occurs first.													
ssl-client-session-state-timeout	Number of minutes to keep client to FortiProxy SSL session state.	integer	Minimum value: 1 Maximum value: 14400	30										
ssl-client-session-state-max	Maximum number of client to FortiProxy SSL session states to keep.	integer	Minimum value: 1 Maximum value: 10000	1000										
ssl-client-rekey-count	Maximum length of data in MB before triggering a client rekey (0 = disable).	integer	Minimum value: 200 Maximum value: 1048576	0										
ssl-server-renegotiation	Enable/disable secure renegotiation to comply with RFC 5746.	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable secure renegotiation.</td></tr><tr><td><i>disable</i></td><td>Disable secure renegotiation.</td></tr></table>	Option	Description	<i>enable</i>	Enable secure renegotiation.	<i>disable</i>	Disable secure renegotiation.							
	Option	Description												
	<i>enable</i>	Enable secure renegotiation.												
<i>disable</i>	Disable secure renegotiation.													
ssl-server-session-state-type	How to expire SSL sessions for the segment of the SSL connection between the server and the FortiProxy.	option	-	both										

Parameter	Description	Type	Size	Default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not keep session states.</td></tr><tr><td><i>time</i></td><td>Expire session states after this many minutes.</td></tr><tr><td><i>count</i></td><td>Expire session states when this maximum is reached.</td></tr><tr><td><i>both</i></td><td>Expire session states based on time or count, whichever occurs first.</td></tr></table>	Option	Description	<i>disable</i>	Do not keep session states.	<i>time</i>	Expire session states after this many minutes.	<i>count</i>	Expire session states when this maximum is reached.	<i>both</i>	Expire session states based on time or count, whichever occurs first.			
	Option	Description												
	<i>disable</i>	Do not keep session states.												
	<i>time</i>	Expire session states after this many minutes.												
	<i>count</i>	Expire session states when this maximum is reached.												
<i>both</i>	Expire session states based on time or count, whichever occurs first.													
ssl-server-session-state-timeout	Number of minutes to keep FortiProxy to Server SSL session state.	integer	Minimum value: 1 Maximum value: 14400	60										
ssl-server-session-state-max	Maximum number of FortiProxy to Server SSL session states to keep.	integer	Minimum value: 1 Maximum value: 10000	100										
ssl-http-location-conversion	Enable to replace HTTP with HTTPS in the reply's Location HTTP header field.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable HTTP location conversion.</td></tr><tr><td><i>disable</i></td><td>Disable HTTP location conversion.</td></tr></table>	Option	Description	<i>enable</i>	Enable HTTP location conversion.	<i>disable</i>	Disable HTTP location conversion.							
	Option	Description												
	<i>enable</i>	Enable HTTP location conversion.												
<i>disable</i>	Disable HTTP location conversion.													
ssl-http-match-host	Enable/disable HTTP host matching for location conversion.	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Match HTTP host in response header.</td></tr><tr><td><i>disable</i></td><td>Do not match HTTP host.</td></tr></table>	Option	Description	<i>enable</i>	Match HTTP host in response header.	<i>disable</i>	Do not match HTTP host.							
	Option	Description												
	<i>enable</i>	Match HTTP host in response header.												
<i>disable</i>	Do not match HTTP host.													
ssl-hpkp	Enable/disable including HPKP header in response.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not add a HPKP header to each HTTP response.</td></tr><tr><td><i>enable</i></td><td>Add a HPKP header to each a HTTP response.</td></tr><tr><td><i>report-only</i></td><td>Add a HPKP Report-Only header to each HTTP response.</td></tr></table>	Option	Description	<i>disable</i>	Do not add a HPKP header to each HTTP response.	<i>enable</i>	Add a HPKP header to each a HTTP response.	<i>report-only</i>	Add a HPKP Report-Only header to each HTTP response.					
	Option	Description												
	<i>disable</i>	Do not add a HPKP header to each HTTP response.												
	<i>enable</i>	Add a HPKP header to each a HTTP response.												
<i>report-only</i>	Add a HPKP Report-Only header to each HTTP response.													

Parameter	Description	Type	Size	Default						
ssl-hpkp-primary	Certificate to generate primary HPKP pin from.	string	Maximum length: 79							
ssl-hpkp-backup	Certificate to generate backup HPKP pin from.	string	Maximum length: 79							
ssl-hpkp-age	Number of seconds the client should honor the HPKP setting.	integer	Minimum value: 60 Maximum value: 157680000	5184000						
ssl-hpkp-report-uri	URL to report HPKP violations to.	var-string	Maximum length: 255							
ssl-hpkp-include-subdomains	Indicate that HPKP header applies to all subdomains.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>HPKP header does not apply to subdomains.</td></tr><tr><td>enable</td><td>HPKP header applies to subdomains.</td></tr></table>				Option	Description	disable	HPKP header does not apply to subdomains.	enable	HPKP header applies to subdomains.
Option	Description									
disable	HPKP header does not apply to subdomains.									
enable	HPKP header applies to subdomains.									
ssl-hsts	Enable/disable including HSTS header in response.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Do not add a HSTS header to each a HTTP response.</td></tr><tr><td>enable</td><td>Add a HSTS header to each HTTP response.</td></tr></table>				Option	Description	disable	Do not add a HSTS header to each a HTTP response.	enable	Add a HSTS header to each HTTP response.
Option	Description									
disable	Do not add a HSTS header to each a HTTP response.									
enable	Add a HSTS header to each HTTP response.									
ssl-hsts-age	Number of seconds the client should honor the HSTS setting.	integer	Minimum value: 60 Maximum value: 157680000	5184000						
ssl-hsts-include-subdomains	Indicate that HSTS header applies to all subdomains.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>HSTS header does not apply to subdomains.</td></tr><tr><td>enable</td><td>HSTS header applies to subdomains.</td></tr></table>				Option	Description	disable	HSTS header does not apply to subdomains.	enable	HSTS header applies to subdomains.
Option	Description									
disable	HSTS header does not apply to subdomains.									
enable	HSTS header applies to subdomains.									

Parameter	Description	Type	Size	Default
max-embryonic-connections	Maximum number of incomplete connections.	integer	Minimum value: 0 Maximum value: 100000	1000
color	Color of icon on the GUI.	integer	Minimum value: 0 Maximum value: 32	0

config quic

Parameter	Description	Type	Size	Default
max-idle-timeout	Maximum idle timeout milliseconds (1 - 60000, default = 30000).	integer	Minimum value: 1 Maximum value: 60000	30000
max-udp-payload-size	Maximum UDP payload size in bytes (1200 - 1500, default = 1500).	integer	Minimum value: 1200 Maximum value: 1500	1500
active-connection-id-limit	Active connection ID limit (1 - 8, default = 2).	integer	Minimum value: 1 Maximum value: 8	2
ack-delay-exponent	ACK delay exponent (1 - 20, default = 3).	integer	Minimum value: 1 Maximum value: 20	3
max-ack-delay	Maximum ACK delay in milliseconds (1 - 16383, default = 25).	integer	Minimum value: 1 Maximum value: 16383	25
max-datagram-frame-size	Maximum datagram frame size in bytes (1 - 1500, default = 1500).	integer	Minimum value: 1 Maximum value: 1500	1500
active-migration	Enable/disable active migration (default = disable).	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable active migration.		
	<i>disable</i>	Disable active migration.		
grease-quic-bit	Enable/disable grease QUIC bit (default = enable).	option	-	enable
	Option	Description		
	<i>enable</i>	Enable grease QUIC bit.		
	<i>disable</i>	Disable grease QUIC bit.		

config realservers

Parameter	Description	Type	Size	Default
id	Real server ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
type	Type of address.	option	-	ip
	Option	Description		
	<i>ip</i>	Standard IPv4 address.		
	<i>address</i>	Dynamic address object.		
address	Dynamic address of the real server.	string	Maximum length: 79	
ip	IP address of the real server.	user	Not Specified	
port	Port for communicating with the real server. Required if port forwarding is enabled.	integer	Minimum value: 1 Maximum value: 65535	0
status	Set the status of the real server to active so that it can accept traffic, or on standby or disabled so no traffic is sent.	option	-	active
	Option	Description		
	<i>active</i>	Server status active.		

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>standby</i></td><td>Server status standby.</td></tr><tr><td><i>disable</i></td><td>Server status disable.</td></tr></table>	Option	Description	<i>standby</i>	Server status standby.	<i>disable</i>	Server status disable.			
	Option	Description								
	<i>standby</i>	Server status standby.								
<i>disable</i>	Server status disable.									
weight	Weight of the real server. If weighted load balancing is enabled, the server with the highest weight gets more connections.	integer	Minimum value: 1 Maximum value: 255	1						
holddown-interval	Time in seconds that the health check monitor continues to monitor and unresponsive server that should be active.	integer	Minimum value: 30 Maximum value: 65535	300						
healthcheck	Enable to check the responsiveness of the real server before forwarding traffic.	option	-							
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable per server health check.</td></tr><tr><td><i>enable</i></td><td>Enable per server health check.</td></tr></table>	Option	Description	<i>disable</i>	Disable per server health check.	<i>enable</i>	Enable per server health check.			
	Option	Description								
	<i>disable</i>	Disable per server health check.								
<i>enable</i>	Enable per server health check.									
health-check- proto	Protocol of the health check monitor to use when polling to determine server's connectivity status.	option	-	ping						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ping</i></td><td>Use PING to test the link with the server.</td></tr><tr><td><i>http</i></td><td>Use HTTP-GET to test the link with the server.</td></tr></table>	Option	Description	<i>ping</i>	Use PING to test the link with the server.	<i>http</i>	Use HTTP-GET to test the link with the server.			
	Option	Description								
	<i>ping</i>	Use PING to test the link with the server.								
<i>http</i>	Use HTTP-GET to test the link with the server.									
http-host	HTTP server domain name in HTTP header.	string	Maximum length: 63							
translate-host	Enable/disable translation of hostname/IP from virtual server to real server.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable virtual hostname/IP translation.</td></tr><tr><td><i>disable</i></td><td>Disable virtual hostname/IP translation.</td></tr></table>	Option	Description	<i>enable</i>	Enable virtual hostname/IP translation.	<i>disable</i>	Disable virtual hostname/IP translation.			
	Option	Description								
	<i>enable</i>	Enable virtual hostname/IP translation.								
<i>disable</i>	Disable virtual hostname/IP translation.									
max-connections	Max number of active connections that can be directed to the real server. When reached, sessions are sent to other real servers.	integer	Minimum value: 0 Maximum value: 2147483647	0						

Parameter	Description	Type	Size	Default
client-ip	Only clients in this IP range can connect to this real server.	user	Not Specified	
verify-cert	Enable/disable certificate verification of the real server.	option	-	disable
		Option	Description	
		<i>enable</i>	Enable certificate verification.	
		<i>disable</i>	Disable certificate verification.	

config ssl-cipher-suites

Parameter	Description	Type	Size	Default
priority	SSL/TLS cipher suites priority.	integer	Minimum value: 0 Maximum value: 4294967295	0
cipher	Cipher suite name.	option	-	
		Option	Description	
		<i>TLS-AES-128-GCM-SHA256</i>	Cipher suite TLS-AES-128-GCM-SHA256.	
		<i>TLS-AES-256-GCM-SHA384</i>	Cipher suite TLS-AES-256-GCM-SHA384.	
		<i>TLS-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-CHACHA20-POLY1305-SHA256.	
		<i>TLS-ECDHE-RSA-WITH-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-CHACHA20-POLY1305-SHA256.	
		<i>TLS-ECDHE-ECDSA-WITH-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-CHACHA20-POLY1305-SHA256.	

Parameter	Description	Type	Size	Default																						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256</i></td><td>Cipher suite TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-AES-128-CBC-SHA</i></td><td>Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-AES-256-CBC-SHA</i></td><td>Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-AES-128-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA256.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-AES-128-GCM-SHA256</i></td><td>Cipher suite TLS-DHE-RSA-WITH-AES-128-GCM-SHA256.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-AES-256-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA256.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-AES-256-GCM-SHA384</i></td><td>Cipher suite TLS-DHE-RSA-WITH-AES-256-GCM-SHA384.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-AES-128-CBC-SHA</i></td><td>Cipher suite TLS-DHE-DSS-WITH-AES-128-CBC-SHA.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-AES-256-CBC-SHA</i></td><td>Cipher suite TLS-DHE-DSS-WITH-AES-256-CBC-SHA.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-AES-128-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-DSS-WITH-AES-128-CBC-SHA256.</td></tr></table>	Option	Description	<i>TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256.	<i>TLS-DHE-RSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA.	<i>TLS-DHE-RSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA.	<i>TLS-DHE-RSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA256.	<i>TLS-DHE-RSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-GCM-SHA256.	<i>TLS-DHE-RSA-WITH-AES-256-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA256.	<i>TLS-DHE-RSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-DHE-RSA-WITH-AES-256-GCM-SHA384.	<i>TLS-DHE-DSS-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-AES-128-CBC-SHA.	<i>TLS-DHE-DSS-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-AES-256-CBC-SHA.	<i>TLS-DHE-DSS-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-AES-128-CBC-SHA256.			
Option	Description																									
<i>TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256.																									
<i>TLS-DHE-RSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA.																									
<i>TLS-DHE-RSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA.																									
<i>TLS-DHE-RSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA256.																									
<i>TLS-DHE-RSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-GCM-SHA256.																									
<i>TLS-DHE-RSA-WITH-AES-256-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA256.																									
<i>TLS-DHE-RSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-DHE-RSA-WITH-AES-256-GCM-SHA384.																									
<i>TLS-DHE-DSS-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-AES-128-CBC-SHA.																									
<i>TLS-DHE-DSS-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-AES-256-CBC-SHA.																									
<i>TLS-DHE-DSS-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-AES-128-CBC-SHA256.																									

Parameter	Description	Type	Size	Default
	Option	Description		
	TLS-DHE-DSS-WITH-AES-128-GCM-SHA256	Cipher suite TLS-DHE-DSS-WITH-AES-128-GCM-SHA256.		
	TLS-DHE-DSS-WITH-AES-256-CBC-SHA256	Cipher suite TLS-DHE-DSS-WITH-AES-256-CBC-SHA256.		
	TLS-DHE-DSS-WITH-AES-256-GCM-SHA384	Cipher suite TLS-DHE-DSS-WITH-AES-256-GCM-SHA384.		
	TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA	Cipher suite TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA.		
	TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA256	Cipher suite TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA256.		
	TLS-ECDHE-RSA-WITH-AES-128-GCM-SHA256	Cipher suite TLS-ECDHE-RSA-WITH-AES-128-GCM-SHA256.		
	TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA	Cipher suite TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA.		
	TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA384	Cipher suite TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA384.		
TLS-ECDHE-RSA-WITH-AES-256-GCM-SHA384	Cipher suite TLS-ECDHE-RSA-WITH-AES-256-GCM-SHA384.			

Parameter	Description	Type	Size	Default																						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA</i></td><td>Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA.</td></tr><tr><td><i>TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA256</i></td><td>Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA256.</td></tr><tr><td><i>TLS-ECDHE-ECDSA-WITH-AES-128-GCM-SHA256</i></td><td>Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-GCM-SHA256.</td></tr><tr><td><i>TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA</i></td><td>Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA.</td></tr><tr><td><i>TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA384</i></td><td>Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA384.</td></tr><tr><td><i>TLS-ECDHE-ECDSA-WITH-AES-256-GCM-SHA384</i></td><td>Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-GCM-SHA384.</td></tr><tr><td><i>TLS-RSA-WITH-AES-128-CBC-SHA</i></td><td>Cipher suite TLS-RSA-WITH-AES-128-CBC-SHA.</td></tr><tr><td><i>TLS-RSA-WITH-AES-256-CBC-SHA</i></td><td>Cipher suite TLS-RSA-WITH-AES-256-CBC-SHA.</td></tr><tr><td><i>TLS-RSA-WITH-AES-128-CBC-SHA256</i></td><td>Cipher suite TLS-RSA-WITH-AES-128-CBC-SHA256.</td></tr><tr><td><i>TLS-RSA-WITH-AES-128-GCM-SHA256</i></td><td>Cipher suite TLS-RSA-WITH-AES-128-GCM-SHA256.</td></tr></table>	Option	Description	<i>TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA.	<i>TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA256.	<i>TLS-ECDHE-ECDSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-GCM-SHA256.	<i>TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA.	<i>TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA384.	<i>TLS-ECDHE-ECDSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-GCM-SHA384.	<i>TLS-RSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-AES-128-CBC-SHA.	<i>TLS-RSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-AES-256-CBC-SHA.	<i>TLS-RSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-AES-128-CBC-SHA256.	<i>TLS-RSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-RSA-WITH-AES-128-GCM-SHA256.			
Option	Description																									
<i>TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA.																									
<i>TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA256.																									
<i>TLS-ECDHE-ECDSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-GCM-SHA256.																									
<i>TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA.																									
<i>TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA384.																									
<i>TLS-ECDHE-ECDSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-GCM-SHA384.																									
<i>TLS-RSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-AES-128-CBC-SHA.																									
<i>TLS-RSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-AES-256-CBC-SHA.																									
<i>TLS-RSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-AES-128-CBC-SHA256.																									
<i>TLS-RSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-RSA-WITH-AES-128-GCM-SHA256.																									

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>TLS-RSA-WITH-AES-256-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-AES-256-CBC-SHA256.		
	<i>TLS-RSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-RSA-WITH-AES-256-GCM-SHA384.		
	<i>TLS-RSA-WITH-CAMELLIA-128-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-CAMELLIA-128-CBC-SHA.		
	<i>TLS-RSA-WITH-CAMELLIA-256-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-CAMELLIA-256-CBC-SHA.		
	<i>TLS-RSA-WITH-CAMELLIA-128-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-CAMELLIA-128-CBC-SHA256.		
	<i>TLS-RSA-WITH-CAMELLIA-256-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-CAMELLIA-256-CBC-SHA256.		
	<i>TLS-DHE-RSA-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-3DES-EDE-CBC-SHA.		
	<i>TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA.		
	<i>TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA</i>	Cipher suite TLS-DSS-RSA-WITH-CAMELLIA-128-CBC-SHA.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA.		
	<i>TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA.		
	<i>TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA256.		
	<i>TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256.		
	<i>TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256.		
	<i>TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256.		
	<i>TLS-DHE-RSA-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-SEED-CBC-SHA.		
	<i>TLS-DHE-DSS-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-SEED-CBC-SHA.		
	<i>TLS-DHE-RSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-ARIA-128-CBC-SHA256.		

Parameter	Description	Type	Size	Default																						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384</i></td><td>Cipher suite TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-ARIA-128-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-DSS-WITH-ARIA-128-CBC-SHA256.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-ARIA-256-CBC-SHA384</i></td><td>Cipher suite TLS-DHE-DSS-WITH-ARIA-256-CBC-SHA384.</td></tr><tr><td><i>TLS-RSA-WITH-SEED-CBC-SHA</i></td><td>Cipher suite TLS-RSA-WITH-SEED-CBC-SHA.</td></tr><tr><td><i>TLS-RSA-WITH-ARIA-128-CBC-SHA256</i></td><td>Cipher suite TLS-RSA-WITH-ARIA-128-CBC-SHA256.</td></tr><tr><td><i>TLS-RSA-WITH-ARIA-256-CBC-SHA384</i></td><td>Cipher suite TLS-RSA-WITH-ARIA-256-CBC-SHA384.</td></tr><tr><td><i>TLS-ECDHE-RSA-WITH-ARIA-128-CBC-SHA256</i></td><td>Cipher suite TLS-ECDHE-RSA-WITH-ARIA-128-CBC-SHA256.</td></tr><tr><td><i>TLS-ECDHE-RSA-WITH-ARIA-256-CBC-SHA384</i></td><td>Cipher suite TLS-ECDHE-RSA-WITH-ARIA-256-CBC-SHA384.</td></tr><tr><td><i>TLS-ECDHE-ECDSA-WITH-ARIA-128-CBC-SHA256</i></td><td>Cipher suite TLS-ECDHE-ECDSA-WITH-ARIA-128-CBC_SHA256.</td></tr><tr><td><i>TLS-ECDHE-ECDSA-WITH-ARIA-256-CBC-SHA384</i></td><td>Cipher suite TLS-ECDHE-ECDSA-WITH-ARIA-256-CBC_SHA384.</td></tr></table>	Option	Description	<i>TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384.	<i>TLS-DHE-DSS-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-ARIA-128-CBC-SHA256.	<i>TLS-DHE-DSS-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-DHE-DSS-WITH-ARIA-256-CBC-SHA384.	<i>TLS-RSA-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-SEED-CBC-SHA.	<i>TLS-RSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-ARIA-128-CBC-SHA256.	<i>TLS-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-RSA-WITH-ARIA-256-CBC-SHA384.	<i>TLS-ECDHE-RSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-ARIA-128-CBC-SHA256.	<i>TLS-ECDHE-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-RSA-WITH-ARIA-256-CBC-SHA384.	<i>TLS-ECDHE-ECDSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-ARIA-128-CBC_SHA256.	<i>TLS-ECDHE-ECDSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-ARIA-256-CBC_SHA384.			
Option	Description																									
<i>TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384.																									
<i>TLS-DHE-DSS-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-ARIA-128-CBC-SHA256.																									
<i>TLS-DHE-DSS-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-DHE-DSS-WITH-ARIA-256-CBC-SHA384.																									
<i>TLS-RSA-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-SEED-CBC-SHA.																									
<i>TLS-RSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-ARIA-128-CBC-SHA256.																									
<i>TLS-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-RSA-WITH-ARIA-256-CBC-SHA384.																									
<i>TLS-ECDHE-RSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-ARIA-128-CBC-SHA256.																									
<i>TLS-ECDHE-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-RSA-WITH-ARIA-256-CBC-SHA384.																									
<i>TLS-ECDHE-ECDSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-ARIA-128-CBC_SHA256.																									
<i>TLS-ECDHE-ECDSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-ARIA-256-CBC_SHA384.																									

Parameter	Description	Type	Size	Default																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>TLS-ECDHE-RSA-WITH-RC4-128-SHA</i></td><td>Cipher suite TLS-ECDHE-RSA-WITH-RC4-128-SHA.</td></tr><tr><td><i>TLS-ECDHE-RSA-WITH-3DES-EDE-CBC-SHA</i></td><td>Cipher suite TLS-ECDHE-RSA-WITH-3DES-EDE-CBC-SHA.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-3DES-EDE-CBC-SHA</i></td><td>Cipher suite TLS-DHE-DSS-WITH-3DES-EDE-CBC-SHA.</td></tr><tr><td><i>TLS-RSA-WITH-3DES-EDE-CBC-SHA</i></td><td>Cipher suite TLS-RSA-WITH-3DES-EDE-CBC-SHA.</td></tr><tr><td><i>TLS-RSA-WITH-RC4-128-MD5</i></td><td>Cipher suite TLS-RSA-WITH-RC4-128-MD5.</td></tr><tr><td><i>TLS-RSA-WITH-RC4-128-SHA</i></td><td>Cipher suite TLS-RSA-WITH-RC4-128-SHA.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-DES-CBC-SHA</i></td><td>Cipher suite TLS-DHE-RSA-WITH-DES-CBC-SHA.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-DES-CBC-SHA</i></td><td>Cipher suite TLS-DHE-DSS-WITH-DES-CBC-SHA.</td></tr><tr><td><i>TLS-RSA-WITH-DES-CBC-SHA</i></td><td>Cipher suite TLS-RSA-WITH-DES-CBC-SHA.</td></tr></table>	Option	Description	<i>TLS-ECDHE-RSA-WITH-RC4-128-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-RC4-128-SHA.	<i>TLS-ECDHE-RSA-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-3DES-EDE-CBC-SHA.	<i>TLS-DHE-DSS-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-3DES-EDE-CBC-SHA.	<i>TLS-RSA-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-3DES-EDE-CBC-SHA.	<i>TLS-RSA-WITH-RC4-128-MD5</i>	Cipher suite TLS-RSA-WITH-RC4-128-MD5.	<i>TLS-RSA-WITH-RC4-128-SHA</i>	Cipher suite TLS-RSA-WITH-RC4-128-SHA.	<i>TLS-DHE-RSA-WITH-DES-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-DES-CBC-SHA.	<i>TLS-DHE-DSS-WITH-DES-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-DES-CBC-SHA.	<i>TLS-RSA-WITH-DES-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-DES-CBC-SHA.			
	Option	Description																						
	<i>TLS-ECDHE-RSA-WITH-RC4-128-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-RC4-128-SHA.																						
	<i>TLS-ECDHE-RSA-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-3DES-EDE-CBC-SHA.																						
	<i>TLS-DHE-DSS-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-3DES-EDE-CBC-SHA.																						
	<i>TLS-RSA-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-3DES-EDE-CBC-SHA.																						
	<i>TLS-RSA-WITH-RC4-128-MD5</i>	Cipher suite TLS-RSA-WITH-RC4-128-MD5.																						
	<i>TLS-RSA-WITH-RC4-128-SHA</i>	Cipher suite TLS-RSA-WITH-RC4-128-SHA.																						
	<i>TLS-DHE-RSA-WITH-DES-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-DES-CBC-SHA.																						
<i>TLS-DHE-DSS-WITH-DES-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-DES-CBC-SHA.																							
<i>TLS-RSA-WITH-DES-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-DES-CBC-SHA.																							
versions	SSL/TLS versions that the cipher suite can be used with.	option	-	ssl-3.0 tls-1.0 tls-1.1 tls-1.2 tls-1.3																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ssl-3.0</i></td><td>SSL 3.0.</td></tr><tr><td><i>tls-1.0</i></td><td>TLS 1.0.</td></tr><tr><td><i>tls-1.1</i></td><td>TLS 1.1.</td></tr></table>	Option	Description	<i>ssl-3.0</i>	SSL 3.0.	<i>tls-1.0</i>	TLS 1.0.	<i>tls-1.1</i>	TLS 1.1.															
	Option	Description																						
	<i>ssl-3.0</i>	SSL 3.0.																						
	<i>tls-1.0</i>	TLS 1.0.																						
<i>tls-1.1</i>	TLS 1.1.																							

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>tls-1.2</i>	TLS 1.2.		
	<i>tls-1.3</i>	TLS 1.3.		

config ssl-server-cipher-suites

Parameter	Description	Type	Size	Default
priority	SSL/TLS cipher suites priority.	integer	Minimum value: 0 Maximum value: 4294967295	0
cipher	Cipher suite name.	option	-	
	Option	Description		
	<i>TLS-AES-128-GCM-SHA256</i>	Cipher suite TLS-AES-128-GCM-SHA256.		
	<i>TLS-AES-256-GCM-SHA384</i>	Cipher suite TLS-AES-256-GCM-SHA384.		
	<i>TLS-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-CHACHA20-POLY1305-SHA256.		
	<i>TLS-ECDHE-RSA-WITH-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-CHACHA20-POLY1305-SHA256.		
	<i>TLS-ECDHE-ECDSA-WITH-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-CHACHA20-POLY1305-SHA256.		
	<i>TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-CHACHA20-POLY1305-SHA256.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>TLS-DHE-RSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA.		
	<i>TLS-DHE-RSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA.		
	<i>TLS-DHE-RSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-CBC-SHA256.		
	<i>TLS-DHE-RSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-128-GCM-SHA256.		
	<i>TLS-DHE-RSA-WITH-AES-256-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-AES-256-CBC-SHA256.		
	<i>TLS-DHE-RSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-DHE-RSA-WITH-AES-256-GCM-SHA384.		
	<i>TLS-DHE-DSS-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-AES-128-CBC-SHA.		
	<i>TLS-DHE-DSS-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-AES-256-CBC-SHA.		
	<i>TLS-DHE-DSS-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-AES-128-CBC-SHA256.		
	<i>TLS-DHE-DSS-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-AES-128-GCM-SHA256.		

Parameter	Description	Type	Size	Default																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>TLS-DHE-DSS-WITH-AES-256-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-DSS-WITH-AES-256-CBC-SHA256.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-AES-256-GCM-SHA384</i></td><td>Cipher suite TLS-DHE-DSS-WITH-AES-256-GCM-SHA384.</td></tr><tr><td><i>TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA</i></td><td>Cipher suite TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA.</td></tr><tr><td><i>TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA256</i></td><td>Cipher suite TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA256.</td></tr><tr><td><i>TLS-ECDHE-RSA-WITH-AES-128-GCM-SHA256</i></td><td>Cipher suite TLS-ECDHE-RSA-WITH-AES-128-GCM-SHA256.</td></tr><tr><td><i>TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA</i></td><td>Cipher suite TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA.</td></tr><tr><td><i>TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA384</i></td><td>Cipher suite TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA384.</td></tr><tr><td><i>TLS-ECDHE-RSA-WITH-AES-256-GCM-SHA384</i></td><td>Cipher suite TLS-ECDHE-RSA-WITH-AES-256-GCM-SHA384.</td></tr><tr><td><i>TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA</i></td><td>Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA.</td></tr></table>	Option	Description	<i>TLS-DHE-DSS-WITH-AES-256-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-AES-256-CBC-SHA256.	<i>TLS-DHE-DSS-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-DHE-DSS-WITH-AES-256-GCM-SHA384.	<i>TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA.	<i>TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA256.	<i>TLS-ECDHE-RSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-128-GCM-SHA256.	<i>TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA.	<i>TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA384.	<i>TLS-ECDHE-RSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-256-GCM-SHA384.	<i>TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA.			
Option	Description																							
<i>TLS-DHE-DSS-WITH-AES-256-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-AES-256-CBC-SHA256.																							
<i>TLS-DHE-DSS-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-DHE-DSS-WITH-AES-256-GCM-SHA384.																							
<i>TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA.																							
<i>TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-128-CBC-SHA256.																							
<i>TLS-ECDHE-RSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-128-GCM-SHA256.																							
<i>TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA.																							
<i>TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-256-CBC-SHA384.																							
<i>TLS-ECDHE-RSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-ECDHE-RSA-WITH-AES-256-GCM-SHA384.																							
<i>TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA.																							

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-CBC-SHA256.		
	<i>TLS-ECDHE-ECDSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-128-GCM-SHA256.		
	<i>TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA.		
	<i>TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-CBC-SHA384.		
	<i>TLS-ECDHE-ECDSA-WITH-AES-256-GCM-SHA384</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-AES-256-GCM-SHA384.		
	<i>TLS-RSA-WITH-AES-128-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-AES-128-CBC-SHA.		
	<i>TLS-RSA-WITH-AES-256-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-AES-256-CBC-SHA.		
	<i>TLS-RSA-WITH-AES-128-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-AES-128-CBC-SHA256.		
	<i>TLS-RSA-WITH-AES-128-GCM-SHA256</i>	Cipher suite TLS-RSA-WITH-AES-128-GCM-SHA256.		
	<i>TLS-RSA-WITH-AES-256-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-AES-256-CBC-SHA256.		

Parameter	Description	Type	Size	Default
	Option	Description		
	TLS-RSA-WITH-AES-256-GCM-SHA384	Cipher suite TLS-RSA-WITH-AES-256-GCM-SHA384.		
	TLS-RSA-WITH-CAMELLIA-128-CBC-SHA	Cipher suite TLS-RSA-WITH-CAMELLIA-128-CBC-SHA.		
	TLS-RSA-WITH-CAMELLIA-256-CBC-SHA	Cipher suite TLS-RSA-WITH-CAMELLIA-256-CBC-SHA.		
	TLS-RSA-WITH-CAMELLIA-128-CBC-SHA256	Cipher suite TLS-RSA-WITH-CAMELLIA-128-CBC-SHA256.		
	TLS-RSA-WITH-CAMELLIA-256-CBC-SHA256	Cipher suite TLS-RSA-WITH-CAMELLIA-256-CBC-SHA256.		
	TLS-DHE-RSA-WITH-3DES-EDE-CBC-SHA	Cipher suite TLS-DHE-RSA-WITH-3DES-EDE-CBC-SHA.		
	TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA.		
	TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA	Cipher suite TLS-DSS-RSA-WITH-CAMELLIA-128-CBC-SHA.		
	TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA.		

Parameter	Description	Type	Size	Default																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA</i></td><td>Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA256.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-SEED-CBC-SHA</i></td><td>Cipher suite TLS-DHE-RSA-WITH-SEED-CBC-SHA.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-SEED-CBC-SHA</i></td><td>Cipher suite TLS-DHE-DSS-WITH-SEED-CBC-SHA.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-ARIA-128-CBC-SHA256</i></td><td>Cipher suite TLS-DHE-RSA-WITH-ARIA-128-CBC-SHA256.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384</i></td><td>Cipher suite TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384.</td></tr></table>	Option	Description	<i>TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA.	<i>TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA256.	<i>TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256.	<i>TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256.	<i>TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256.	<i>TLS-DHE-RSA-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-SEED-CBC-SHA.	<i>TLS-DHE-DSS-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-SEED-CBC-SHA.	<i>TLS-DHE-RSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-ARIA-128-CBC-SHA256.	<i>TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384.			
Option	Description																							
<i>TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA.																							
<i>TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-128-CBC-SHA256.																							
<i>TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-128-CBC-SHA256.																							
<i>TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-CAMELLIA-256-CBC-SHA256.																							
<i>TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-CAMELLIA-256-CBC-SHA256.																							
<i>TLS-DHE-RSA-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-SEED-CBC-SHA.																							
<i>TLS-DHE-DSS-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-SEED-CBC-SHA.																							
<i>TLS-DHE-RSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-RSA-WITH-ARIA-128-CBC-SHA256.																							
<i>TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-DHE-RSA-WITH-ARIA-256-CBC-SHA384.																							

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>TLS-DHE-DSS-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-DHE-DSS-WITH-ARIA-128-CBC-SHA256.		
	<i>TLS-DHE-DSS-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-DHE-DSS-WITH-ARIA-256-CBC-SHA384.		
	<i>TLS-RSA-WITH-SEED-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-SEED-CBC-SHA.		
	<i>TLS-RSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-RSA-WITH-ARIA-128-CBC-SHA256.		
	<i>TLS-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-RSA-WITH-ARIA-256-CBC-SHA384.		
	<i>TLS-ECDHE-RSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-RSA-WITH-ARIA-128-CBC-SHA256.		
	<i>TLS-ECDHE-RSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-RSA-WITH-ARIA-256-CBC-SHA384.		
	<i>TLS-ECDHE-ECDSA-WITH-ARIA-128-CBC-SHA256</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-ARIA-128-CBC_SHA256.		
	<i>TLS-ECDHE-ECDSA-WITH-ARIA-256-CBC-SHA384</i>	Cipher suite TLS-ECDHE-ECDSA-WITH-ARIA-256-CBC_SHA384.		
	<i>TLS-ECDHE-RSA-WITH-RC4-128-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-RC4-128-SHA.		

Parameter	Description	Type	Size	Default																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>TLS-ECDHE-RSA-WITH-3DES-EDE-CBC-SHA</i></td><td>Cipher suite TLS-ECDHE-RSA-WITH-3DES-EDE-CBC-SHA.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-3DES-EDE-CBC-SHA</i></td><td>Cipher suite TLS-DHE-DSS-WITH-3DES-EDE-CBC-SHA.</td></tr><tr><td><i>TLS-RSA-WITH-3DES-EDE-CBC-SHA</i></td><td>Cipher suite TLS-RSA-WITH-3DES-EDE-CBC-SHA.</td></tr><tr><td><i>TLS-RSA-WITH-RC4-128-MD5</i></td><td>Cipher suite TLS-RSA-WITH-RC4-128-MD5.</td></tr><tr><td><i>TLS-RSA-WITH-RC4-128-SHA</i></td><td>Cipher suite TLS-RSA-WITH-RC4-128-SHA.</td></tr><tr><td><i>TLS-DHE-RSA-WITH-DES-CBC-SHA</i></td><td>Cipher suite TLS-DHE-RSA-WITH-DES-CBC-SHA.</td></tr><tr><td><i>TLS-DHE-DSS-WITH-DES-CBC-SHA</i></td><td>Cipher suite TLS-DHE-DSS-WITH-DES-CBC-SHA.</td></tr><tr><td><i>TLS-RSA-WITH-DES-CBC-SHA</i></td><td>Cipher suite TLS-RSA-WITH-DES-CBC-SHA.</td></tr></table>	Option	Description	<i>TLS-ECDHE-RSA-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-3DES-EDE-CBC-SHA.	<i>TLS-DHE-DSS-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-3DES-EDE-CBC-SHA.	<i>TLS-RSA-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-3DES-EDE-CBC-SHA.	<i>TLS-RSA-WITH-RC4-128-MD5</i>	Cipher suite TLS-RSA-WITH-RC4-128-MD5.	<i>TLS-RSA-WITH-RC4-128-SHA</i>	Cipher suite TLS-RSA-WITH-RC4-128-SHA.	<i>TLS-DHE-RSA-WITH-DES-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-DES-CBC-SHA.	<i>TLS-DHE-DSS-WITH-DES-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-DES-CBC-SHA.	<i>TLS-RSA-WITH-DES-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-DES-CBC-SHA.			
	Option	Description																				
	<i>TLS-ECDHE-RSA-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-ECDHE-RSA-WITH-3DES-EDE-CBC-SHA.																				
	<i>TLS-DHE-DSS-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-3DES-EDE-CBC-SHA.																				
	<i>TLS-RSA-WITH-3DES-EDE-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-3DES-EDE-CBC-SHA.																				
	<i>TLS-RSA-WITH-RC4-128-MD5</i>	Cipher suite TLS-RSA-WITH-RC4-128-MD5.																				
	<i>TLS-RSA-WITH-RC4-128-SHA</i>	Cipher suite TLS-RSA-WITH-RC4-128-SHA.																				
	<i>TLS-DHE-RSA-WITH-DES-CBC-SHA</i>	Cipher suite TLS-DHE-RSA-WITH-DES-CBC-SHA.																				
	<i>TLS-DHE-DSS-WITH-DES-CBC-SHA</i>	Cipher suite TLS-DHE-DSS-WITH-DES-CBC-SHA.																				
<i>TLS-RSA-WITH-DES-CBC-SHA</i>	Cipher suite TLS-RSA-WITH-DES-CBC-SHA.																					
versions	SSL/TLS versions that the cipher suite can be used with.	option	-	ssl-3.0 tls-1.0 tls-1.1 tls-1.2 tls-1.3																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ssl-3.0</i></td><td>SSL 3.0.</td></tr><tr><td><i>tls-1.0</i></td><td>TLS 1.0.</td></tr><tr><td><i>tls-1.1</i></td><td>TLS 1.1.</td></tr><tr><td><i>tls-1.2</i></td><td>TLS 1.2.</td></tr><tr><td><i>tls-1.3</i></td><td>TLS 1.3.</td></tr></table>	Option	Description	<i>ssl-3.0</i>	SSL 3.0.	<i>tls-1.0</i>	TLS 1.0.	<i>tls-1.1</i>	TLS 1.1.	<i>tls-1.2</i>	TLS 1.2.	<i>tls-1.3</i>	TLS 1.3.									
	Option	Description																				
	<i>ssl-3.0</i>	SSL 3.0.																				
	<i>tls-1.0</i>	TLS 1.0.																				
	<i>tls-1.1</i>	TLS 1.1.																				
	<i>tls-1.2</i>	TLS 1.2.																				
<i>tls-1.3</i>	TLS 1.3.																					

config firewall vipgrp

Configure IPv4 virtual IP groups.

```
config firewall vipgrp
  Description: Configure IPv4 virtual IP groups.
  edit <name>
    set uuid {uuid}
    set interface {string}
    set color {integer}
    set comments {var-string}
    set member <name1>, <name2>, ...
  next
end
```

config firewall vipgrp

Parameter	Description	Type	Size	Default
name	VIP group name.	string	Maximum length: 79	
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000
interface	Interface.	string	Maximum length: 35	
color	Integer value to determine the color of the icon in the GUI (range 1 to 32, default = 0, which sets the value to 1).	integer	Minimum value: 0 Maximum value: 32	0
comments	Comment.	var-string	Maximum length: 255	
member <name>	Member VIP objects of the group (Separate multiple objects with a space). VIP name.	string	Maximum length: 79	

config firewall wildcard-fqdn custom

Config global/VDOM Wildcard FQDN address.

```
config firewall wildcard-fqdn custom
  Description: Config global/VDOM Wildcard FQDN address.
```

```

edit <name>
    set uuid {uuid}
    set wildcard-fqdn {string}
    set color {integer}
    set comment {var-string}
next
end

```

config firewall wildcard-fqdn custom

Parameter	Description	Type	Size	Default
name	Address name.	string	Maximum length: 79	
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000
wildcard-fqdn	Wildcard FQDN.	string	Maximum length: 255	
color	GUI icon color.	integer	Minimum value: 0 Maximum value: 32	0
comment	Comment.	var-string	Maximum length: 255	

config firewall wildcard-fqdn group

Config global Wildcard FQDN address groups.

```

config firewall wildcard-fqdn group
    Description: Config global Wildcard FQDN address groups.
    edit <name>
        set uuid {uuid}
        set member <name1>, <name2>, ...
        set color {integer}
        set comment {var-string}
    next
end

```

config firewall wildcard-fqdn group

Parameter	Description	Type	Size	Default
name	Address group name.	string	Maximum length: 79	
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000
member <name>	Address group members. Address name.	string	Maximum length: 79	
color	GUI icon color.	integer	Minimum value: 0 Maximum value: 32	0
comment	Comment.	var-string	Maximum length: 255	

ftp-proxy

This section includes syntax for the following commands:

- [config ftp-proxy explicit on page 454](#)

config ftp-proxy explicit

Configure explicit FTP proxy settings.

```
config ftp-proxy explicit
  Description: Configure explicit FTP proxy settings.
  set status [enable|disable]
  set incoming-port {user}
  set incoming-ip {ipv4-address-any}
  set outgoing-ip {ipv4-address-any}
  set sec-default-action [accept|deny]
  set server-data-mode [client|passive]
  set active-src-port [default|server]
  set ipv6-status [enable|disable]
  set incoming-ip6 {ipv6-address}
  set ssl [enable|disable]
  set ssl-cert <name1>, <name2>, ...
  set ssl-dh-bits [768|1024|...]
  set ssl-algorithm [high|medium|...]
end
```

config ftp-proxy explicit

Parameter	Description	Type	Size	Default
status	Enable/disable the explicit FTP proxy.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable the explicit FTP proxy.		
	<i>disable</i>	Disable the explicit FTP proxy.		
incoming-port	Accept incoming FTP requests on one or more ports.	user	Not Specified	
incoming-ip	Accept incoming FTP requests from this IP address. An interface must have this IP address.	ipv4-address-any	Not Specified	0.0.0.0

Parameter	Description	Type	Size	Default						
outgoing-ip	Outgoing FTP requests will leave from this IP address. An interface must have this IP address.	ipv4-address-any	Not Specified							
sec-default-action	Accept or deny explicit FTP proxy sessions when no FTP proxy firewall policy exists.	option	-	deny						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>accept</td><td>Accept requests. All explicit FTP proxy traffic is accepted whether there is an explicit FTP proxy policy or not</td></tr><tr><td>deny</td><td>Deny requests unless there is a matching explicit FTP proxy policy.</td></tr></table>	Option	Description	accept	Accept requests. All explicit FTP proxy traffic is accepted whether there is an explicit FTP proxy policy or not	deny	Deny requests unless there is a matching explicit FTP proxy policy.			
Option	Description									
accept	Accept requests. All explicit FTP proxy traffic is accepted whether there is an explicit FTP proxy policy or not									
deny	Deny requests unless there is a matching explicit FTP proxy policy.									
server-data-mode	Determine mode of data session on FTP server side.	option	-	client						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>client</td><td>Use the same transmission mode for client and server data sessions.</td></tr><tr><td>passive</td><td>Use passive mode on server data session.</td></tr></table>	Option	Description	client	Use the same transmission mode for client and server data sessions.	passive	Use passive mode on server data session.			
Option	Description									
client	Use the same transmission mode for client and server data sessions.									
passive	Use passive mode on server data session.									
active-src-port	Determine port for data session to connect FTP client in active mode.	option	-	default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>default</td><td>Use the incoming port - 1 to connect client data session in active mode.</td></tr><tr><td>server</td><td>Use the same port as FTP server source port to connect client data session in active mode.</td></tr></table>	Option	Description	default	Use the incoming port - 1 to connect client data session in active mode.	server	Use the same port as FTP server source port to connect client data session in active mode.			
Option	Description									
default	Use the incoming port - 1 to connect client data session in active mode.									
server	Use the same port as FTP server source port to connect client data session in active mode.									
ipv6-status	Enable/disable allowing an IPv6 ftp proxy destination in policies and all IPv6 related entries in this command.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable allowing an IPv6 ftp proxy destination.</td></tr><tr><td>disable</td><td>Disable allowing an IPv6 ftp proxy destination.</td></tr></table>	Option	Description	enable	Enable allowing an IPv6 ftp proxy destination.	disable	Disable allowing an IPv6 ftp proxy destination.			
Option	Description									
enable	Enable allowing an IPv6 ftp proxy destination.									
disable	Disable allowing an IPv6 ftp proxy destination.									
incoming-ip6	Restrict the explicit ftp proxy to only accept sessions from this IPv6 address. An interface must have this IPv6 address.	ipv6-address	Not Specified	::						
ssl	Enable/disable the explicit FTPS proxy.	option	-	disable						

Parameter	Description	Type	Size	Default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable the explicit FTPS proxy.</td></tr><tr><td><i>disable</i></td><td>Disable the explicit FTPS proxy.</td></tr></table>	Option	Description	<i>enable</i>	Enable the explicit FTPS proxy.	<i>disable</i>	Disable the explicit FTPS proxy.							
	Option	Description												
	<i>enable</i>	Enable the explicit FTPS proxy.												
<i>disable</i>	Disable the explicit FTPS proxy.													
ssl-cert <name>	List of certificate names to use for SSL connections to this server. Certificate list.	string	Maximum length: 79											
ssl-dh-bits	Bit-size of Diffie-Hellman (DH) prime used in DHE-RSA negotiation (default = 2048).	option	-	2048										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>768</i></td><td>768-bit Diffie-Hellman prime.</td></tr><tr><td><i>1024</i></td><td>1024-bit Diffie-Hellman prime.</td></tr><tr><td><i>1536</i></td><td>1536-bit Diffie-Hellman prime.</td></tr><tr><td><i>2048</i></td><td>2048-bit Diffie-Hellman prime.</td></tr></table>	Option	Description	<i>768</i>	768-bit Diffie-Hellman prime.	<i>1024</i>	1024-bit Diffie-Hellman prime.	<i>1536</i>	1536-bit Diffie-Hellman prime.	<i>2048</i>	2048-bit Diffie-Hellman prime.			
	Option	Description												
	<i>768</i>	768-bit Diffie-Hellman prime.												
	<i>1024</i>	1024-bit Diffie-Hellman prime.												
	<i>1536</i>	1536-bit Diffie-Hellman prime.												
<i>2048</i>	2048-bit Diffie-Hellman prime.													
ssl-algorithm	Relative strength of encryption algorithms accepted in negotiation.	option	-	high										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>high</i></td><td>High encryption. Allow only AES and ChaCha</td></tr><tr><td><i>medium</i></td><td>Medium encryption. Allow AES, ChaCha, 3DES, and RC4.</td></tr><tr><td><i>low</i></td><td>Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.</td></tr></table>	Option	Description	<i>high</i>	High encryption. Allow only AES and ChaCha	<i>medium</i>	Medium encryption. Allow AES, ChaCha, 3DES, and RC4.	<i>low</i>	Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.					
	Option	Description												
	<i>high</i>	High encryption. Allow only AES and ChaCha												
	<i>medium</i>	Medium encryption. Allow AES, ChaCha, 3DES, and RC4.												
<i>low</i>	Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.													

hardware

This section includes syntax for the following commands:

- [config hardware cpu on page 457](#)
- [config hardware memory on page 457](#)
- [config hardware nic on page 457](#)
- [config hardware status on page 458](#)

config hardware cpu

Display detailed information for all installed CPU(s).

```
config hardware cpu
    Description: Display detailed information for all installed CPU(s).
end
```

config hardware memory

Display system memory information.

```
config hardware memory
    Description: Display system memory information.
end
```

config hardware nic

Display NIC information.

```
config hardware nic
    Description: Display NIC information.
    set <nic> {string}
end
```

config hardware nic

Parameter	Description	Type	Size	Default
<nic>	NIC name.	string	Maximum length: -	

config hardware status

Hardware status.

```
config hardware status
    Description: Hardware status.
end
```

icap

This section includes syntax for the following commands:

- [config icap local-server on page 459](#)
- [config icap profile on page 462](#)
- [config icap remote-server-group on page 472](#)
- [config icap remote-server on page 471](#)

config icap local-server

Configure ICAP local server.

```
config icap local-server
  Description: Configure ICAP local server.
  edit <icap-server-id>
    set status [disable|enable]
    set secure-connection [disable|enable]
    set status-ipv6 [disable|enable]
    set icap-incoming-port {integer}
    set icap-incoming-ssl-port {integer}
    set interface {string}
    set incoming-ip {ipv4-address-any}
    set incoming-ipv6 {ipv6-address}
    set ssl-cert <name1>, <name2>, ...
    set strict-scheme-check [disable|enable]
    set message-preview [disable|enable]
    set srcaddr {string}
    set timeout {integer}
  config icap-service
    Description: Set up services for local ICAP server.
    edit <service-id>
      set name {string}
      set dlp-profile {string}
      set av-profile {string}
      set webfilter-profile {string}
      set image-analyzer-profile {string}
      set profile-protocol-options {string}
      set extension-headers {option1}, {option2}, ...
    next
  end
next
end
```

config icap local-server

Parameter	Description	Type	Size	Default						
icap-server-id	ICAP local server id.	integer	Minimum value: 0 Maximum value: 65535	0						
status	Enable/disable status for icap server network profile.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable the status for ipv4 in network-profile.</td></tr><tr><td>enable</td><td>Enable the status for ipv4 in network-profile.</td></tr></table>	Option	Description	disable	Disable the status for ipv4 in network-profile.	enable	Enable the status for ipv4 in network-profile.			
Option	Description									
disable	Disable the status for ipv4 in network-profile.									
enable	Enable the status for ipv4 in network-profile.									
secure-connection	Enable/disable status for secured icap server network profile.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable the status for ipv4 ssl in network-profile.</td></tr><tr><td>enable</td><td>Enable the status for ipv4 ssl in network-profile.</td></tr></table>	Option	Description	disable	Disable the status for ipv4 ssl in network-profile.	enable	Enable the status for ipv4 ssl in network-profile.			
Option	Description									
disable	Disable the status for ipv4 ssl in network-profile.									
enable	Enable the status for ipv4 ssl in network-profile.									
status-ipv6	Enable/disable status for icap server service ipv6.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable the status for ipv6 in network-profile.</td></tr><tr><td>enable</td><td>Enable the status for ipv6 in network-profile.</td></tr></table>	Option	Description	disable	Disable the status for ipv6 in network-profile.	enable	Enable the status for ipv6 in network-profile.			
Option	Description									
disable	Disable the status for ipv6 in network-profile.									
enable	Enable the status for ipv6 in network-profile.									
icap-incoming-port	Accept incoming ICAP requests on a port (0 - 65535, default = 1344).	integer	Minimum value: 1 Maximum value: 65535	1344						
icap-incoming-ssl-port	Accept incoming secured ICAP requests on a port (0 - 65535, default = 11344).	integer	Minimum value: 1 Maximum value: 65535	11344						
interface	Interface name	string	Maximum length: 15							

Parameter	Description	Type	Size	Default						
incoming-ip	Restrict the ICAP server to only accept sessions from this IP address. An interface must have this IP address.	ipv4-address-any	Not Specified	0.0.0.0						
incoming-ipv6	Restrict the ICAP server to only accept sessions from this IPv6 address. An interface must have this IPv6 address.	ipv6-address	Not Specified	::						
ssl-cert <name>	SSL certificate for SSL interception. Certificate list.	string	Maximum length: 79							
strict-scheme-check	Enable/disable strict check of scheme.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable strict check of scheme.</td></tr><tr><td><i>enable</i></td><td>Enable strict check of scheme.</td></tr></table>				Option	Description	<i>disable</i>	Disable strict check of scheme.	<i>enable</i>	Enable strict check of scheme.
Option	Description									
<i>disable</i>	Disable strict check of scheme.									
<i>enable</i>	Enable strict check of scheme.									
message-preview	Enable/disable message preview support. Max preview data length is 4096 bytes.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable message preview support.</td></tr><tr><td><i>enable</i></td><td>Enable message preview support.</td></tr></table>				Option	Description	<i>disable</i>	Disable message preview support.	<i>enable</i>	Enable message preview support.
Option	Description									
<i>disable</i>	Disable message preview support.									
<i>enable</i>	Enable message preview support.									
srcaddr	Source address name.	string	Maximum length: 79							
timeout	ICAP server idle timeout in seconds.	integer	Minimum value: 30 Maximum value: 3600	300						

config icap-service

Parameter	Description	Type	Size	Default
service-id	ID of the ICAP server service.	integer	Minimum value: 0 Maximum value: 65535	0
name	Name of ICAP service profile.	string	Maximum length: 35	

Parameter	Description	Type	Size	Default								
dlp-profile	Name of an existing DLP profile.	string	Maximum length: 35									
av-profile	Name of an existing Antivirus profile.	string	Maximum length: 35									
webfilter-profile	Name of an existing Web filter profile.	string	Maximum length: 35									
image-analyzer-profile	Name of an existing Image analyzer profile.	string	Maximum length: 35									
profile-protocol-options	Name of an existing Protocol options profile.	string	Maximum length: 35	default								
extension-headers	Configure the extension headers of icap server response.	option	-									
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>X-Virus-id</i></td><td>Enable X-Virus-ID ICAP extension header.</td></tr><tr><td><i>X-Infection-Found</i></td><td>Enable X-Infection-Found ICAP extension header.</td></tr><tr><td><i>X-Violation-Found</i></td><td>Enable X-Violation-Found ICAP extension header.</td></tr></table>				Option	Description	<i>X-Virus-id</i>	Enable X-Virus-ID ICAP extension header.	<i>X-Infection-Found</i>	Enable X-Infection-Found ICAP extension header.	<i>X-Violation-Found</i>	Enable X-Violation-Found ICAP extension header.
Option	Description											
<i>X-Virus-id</i>	Enable X-Virus-ID ICAP extension header.											
<i>X-Infection-Found</i>	Enable X-Infection-Found ICAP extension header.											
<i>X-Violation-Found</i>	Enable X-Violation-Found ICAP extension header.											

config icap profile

Configure ICAP profiles.

```

config icap profile
  Description: Configure ICAP profiles.
  edit <name>
    set replacemsg-group {string}
    set comment {var-string}
    set request [disable|enable]
    set response [disable|enable]
    set file-transfer {option1}, {option2}, ...
    set streaming-content-bypass [disable|enable]
    set ocr_only [disable|enable]
    set 204-size-limit {integer}
    set 204-response [disable|enable]
    set preview [disable|enable]
    set preview-data-length {integer}
    set request-server {string}
    set response-server {string}
  
```

```

set file-transfer-server {string}
set request-failure [error|bypass]
set response-failure [error|bypass]
set file-transfer-failure [error|bypass]
set request-path {string}
set response-path {string}
set file-transfer-path {string}
set methods {option1}, {option2}, ...
set response-req-hdr [disable|enable]
set respmod-default-action [forward|bypass]
set icap-block-log [disable|enable]
set chunk-encap [disable|enable]
set extension-feature {option1}, {option2}, ...
set scan-progress-interval {integer}
set timeout {integer}
set scan-size-limit {integer}
set scan-oversize-log [disable|enable]
config icap-headers
    Description: Configure ICAP forwarded request headers.
    edit <id>
        set name {string}
        set source [content|http-header|...]
        set content {string}
        set http-header {string}
        set session-info-type [client-ip|user|...]
        set base64-encoding [disable|enable]
    next
end
config respmod-forward-rules
    Description: ICAP response mode forward rules.
    edit <name>
        set host {string}
        config header-group
            Description: HTTP header group.
            edit <id>
                set header-name {string}
                set header {string}
                set case-sensitivity [disable|enable]
            next
        end
        set action [forward|bypass]
        set http-resp-status-code <code1>, <code2>, ...
    next
end
next
end

```

config icap profile

Parameter	Description	Type	Size	Default						
replacemsg-group	Replacement message group.	string	Maximum length: 35							
name	ICAP profile name.	string	Maximum length: 35							
comment	Comment.	var-string	Maximum length: 255							
request	Enable/disable whether an HTTP request is passed to an ICAP server.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable HTTP request passing to ICAP server.</td></tr><tr><td><i>enable</i></td><td>Enable HTTP request passing to ICAP server.</td></tr></table>	Option	Description	<i>disable</i>	Disable HTTP request passing to ICAP server.	<i>enable</i>	Enable HTTP request passing to ICAP server.			
Option	Description									
<i>disable</i>	Disable HTTP request passing to ICAP server.									
<i>enable</i>	Enable HTTP request passing to ICAP server.									
response	Enable/disable whether an HTTP response is passed to an ICAP server.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable HTTP response passing to ICAP server.</td></tr><tr><td><i>enable</i></td><td>Enable HTTP response passing to ICAP server.</td></tr></table>	Option	Description	<i>disable</i>	Disable HTTP response passing to ICAP server.	<i>enable</i>	Enable HTTP response passing to ICAP server.			
Option	Description									
<i>disable</i>	Disable HTTP response passing to ICAP server.									
<i>enable</i>	Enable HTTP response passing to ICAP server.									
file-transfer	Configure the file transfer protocols to pass transferred files to an ICAP server as REQMOD.	option	-							
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ssh</i></td><td>Forward file transfer with SSH protocol to ICAP server for further processing.</td></tr><tr><td><i>ftp</i></td><td>Forward file transfer with FTP protocol to ICAP server for further processing.</td></tr></table>	Option	Description	<i>ssh</i>	Forward file transfer with SSH protocol to ICAP server for further processing.	<i>ftp</i>	Forward file transfer with FTP protocol to ICAP server for further processing.			
Option	Description									
<i>ssh</i>	Forward file transfer with SSH protocol to ICAP server for further processing.									
<i>ftp</i>	Forward file transfer with FTP protocol to ICAP server for further processing.									
streaming-content-bypass	Enable/disable bypassing of ICAP server for streaming content.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable bypassing of ICAP server for streaming content.</td></tr><tr><td><i>enable</i></td><td>Enable bypassing of ICAP server for streaming content.</td></tr></table>	Option	Description	<i>disable</i>	Disable bypassing of ICAP server for streaming content.	<i>enable</i>	Enable bypassing of ICAP server for streaming content.			
Option	Description									
<i>disable</i>	Disable bypassing of ICAP server for streaming content.									
<i>enable</i>	Enable bypassing of ICAP server for streaming content.									

Parameter	Description	Type	Size	Default						
ocr_only	Enable/disable only passing OCR scan request to ICAP server.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable only passing OCR scan request to ICAP server.</td></tr><tr><td><i>enable</i></td><td>Enable only passing OCR scan request to ICAP server.</td></tr></table>	Option	Description	<i>disable</i>	Disable only passing OCR scan request to ICAP server.	<i>enable</i>	Enable only passing OCR scan request to ICAP server.			
Option	Description									
<i>disable</i>	Disable only passing OCR scan request to ICAP server.									
<i>enable</i>	Enable only passing OCR scan request to ICAP server.									
204-size-limit	Allow 204 size limit to be saved by ICAP client. (default = 1 MB)	integer	Minimum value: 1 Maximum value: 10	1						
204-response	Enable/disable allowance of 204 response from ICAP server.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable allowance of 204 response from ICAP server.</td></tr><tr><td><i>enable</i></td><td>Enable allowance of 204 response from ICAP server.</td></tr></table>	Option	Description	<i>disable</i>	Disable allowance of 204 response from ICAP server.	<i>enable</i>	Enable allowance of 204 response from ICAP server.			
Option	Description									
<i>disable</i>	Disable allowance of 204 response from ICAP server.									
<i>enable</i>	Enable allowance of 204 response from ICAP server.									
preview	Enable/disable preview of data to ICAP server.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable preview of data to ICAP server.</td></tr><tr><td><i>enable</i></td><td>Enable preview of data to ICAP server.</td></tr></table>	Option	Description	<i>disable</i>	Disable preview of data to ICAP server.	<i>enable</i>	Enable preview of data to ICAP server.			
Option	Description									
<i>disable</i>	Disable preview of data to ICAP server.									
<i>enable</i>	Enable preview of data to ICAP server.									
preview-data-length	Preview data length to be sent to ICAP server.	integer	Minimum value: 0 Maximum value: 4096	0						
request-server	ICAP server to use for an HTTP request.	string	Maximum length: 63							
response-server	ICAP server to use for an HTTP response.	string	Maximum length: 63							
file-transfer-server	ICAP server to use for a file transfer.	string	Maximum length: 63							
request-failure	Action to take if the ICAP server cannot be contacted when processing an HTTP request.	option	-	error						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>error</i>	Error.		
	<i>bypass</i>	Bypass.		
response-failure	Action to take if the ICAP server cannot be contacted when processing an HTTP response.	option	-	error
	Option	Description		
	<i>error</i>	Error.		
	<i>bypass</i>	Bypass.		
file-transfer-failure	Action to take if the ICAP server cannot be contacted when processing a file transfer.	option	-	error
	Option	Description		
	<i>error</i>	Error.		
	<i>bypass</i>	Bypass.		
request-path	Path component of the ICAP URI that identifies the HTTP request processing service.	string	Maximum length: 127	
response-path	Path component of the ICAP URI that identifies the HTTP response processing service.	string	Maximum length: 127	
file-transfer-path	Path component of the ICAP URI that identifies the file transfer processing service.	string	Maximum length: 127	
methods	The allowed HTTP methods that will be sent to ICAP server for further processing.	option	-	delete get head options post put trace connect other
	Option	Description		
	<i>delete</i>	Forward HTTP request or response with DELETE method to ICAP server for further processing.		

Parameter	Description	Type	Size	Default																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>get</i></td><td>Forward HTTP request or response with GET method to ICAP server for further processing.</td></tr><tr><td><i>head</i></td><td>Forward HTTP request or response with HEAD method to ICAP server for further processing.</td></tr><tr><td><i>options</i></td><td>Forward HTTP request or response with OPTIONS method to ICAP server for further processing.</td></tr><tr><td><i>post</i></td><td>Forward HTTP request or response with POST method to ICAP server for further processing.</td></tr><tr><td><i>put</i></td><td>Forward HTTP request or response with PUT method to ICAP server for further processing.</td></tr><tr><td><i>trace</i></td><td>Forward HTTP request or response with TRACE method to ICAP server for further processing.</td></tr><tr><td><i>connect</i></td><td>Forward HTTP request or response with CONNECT method to ICAP server for further processing.</td></tr><tr><td><i>other</i></td><td>Forward HTTP request or response with All other methods to ICAP server for further processing.</td></tr></table>	Option	Description	<i>get</i>	Forward HTTP request or response with GET method to ICAP server for further processing.	<i>head</i>	Forward HTTP request or response with HEAD method to ICAP server for further processing.	<i>options</i>	Forward HTTP request or response with OPTIONS method to ICAP server for further processing.	<i>post</i>	Forward HTTP request or response with POST method to ICAP server for further processing.	<i>put</i>	Forward HTTP request or response with PUT method to ICAP server for further processing.	<i>trace</i>	Forward HTTP request or response with TRACE method to ICAP server for further processing.	<i>connect</i>	Forward HTTP request or response with CONNECT method to ICAP server for further processing.	<i>other</i>	Forward HTTP request or response with All other methods to ICAP server for further processing.			
	Option	Description																				
	<i>get</i>	Forward HTTP request or response with GET method to ICAP server for further processing.																				
	<i>head</i>	Forward HTTP request or response with HEAD method to ICAP server for further processing.																				
	<i>options</i>	Forward HTTP request or response with OPTIONS method to ICAP server for further processing.																				
	<i>post</i>	Forward HTTP request or response with POST method to ICAP server for further processing.																				
	<i>put</i>	Forward HTTP request or response with PUT method to ICAP server for further processing.																				
	<i>trace</i>	Forward HTTP request or response with TRACE method to ICAP server for further processing.																				
<i>connect</i>	Forward HTTP request or response with CONNECT method to ICAP server for further processing.																					
<i>other</i>	Forward HTTP request or response with All other methods to ICAP server for further processing.																					
response-req-hdr	Enable/disable addition of req-hdr for ICAP response modification (respmod) processing.	option	-	enable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not add req-hdr for response modification (respmod) processing.</td></tr><tr><td><i>enable</i></td><td>Add req-hdr for response modification (respmod) processing.</td></tr></table>	Option	Description	<i>disable</i>	Do not add req-hdr for response modification (respmod) processing.	<i>enable</i>	Add req-hdr for response modification (respmod) processing.															
	Option	Description																				
	<i>disable</i>	Do not add req-hdr for response modification (respmod) processing.																				
<i>enable</i>	Add req-hdr for response modification (respmod) processing.																					
respmod-default-action	Default action to ICAP response modification (respmod) processing.	option	-	forward																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>forward</i></td><td>Forward response to ICAP server unless a rule specifies not to.</td></tr><tr><td><i>bypass</i></td><td>Don't forward request to ICAP server unless a rule specifies to forward the request.</td></tr></table>	Option	Description	<i>forward</i>	Forward response to ICAP server unless a rule specifies not to.	<i>bypass</i>	Don't forward request to ICAP server unless a rule specifies to forward the request.															
	Option	Description																				
	<i>forward</i>	Forward response to ICAP server unless a rule specifies not to.																				
<i>bypass</i>	Don't forward request to ICAP server unless a rule specifies to forward the request.																					
icap-block-log	Enable/disable UTM log when infection found (default = disable).	option	-	disable																		

Parameter	Description	Type	Size	Default
	Option Description			
	<i>disable</i>	Disable UTM log when infection found.		
	<i>enable</i>	Enable UTM log when infection found.		
chunk-encap	Enable/disable chunked encapsulation (default = disable).	option	-	disable
	Option Description			
	<i>disable</i>	Do not encapsulate chunked data.		
	<i>enable</i>	Encapsulate chunked data into a new chunk.		
extension-feature	Enable/disable ICAP extension features.	option	-	
	Option Description			
	<i>scan-progress</i>	Support X-Scan-Progress-Interval ICAP header.		
scan-progress-interval	Scan progress interval value.	integer	Minimum value: 5 Maximum value: 30	10
timeout	Time (in seconds) that ICAP client waits for the response from ICAP server.	integer	Minimum value: 30 Maximum value: 3600	30
scan-size-limit	ICAP server scan size limit for an single request. (0 - 4096 MB, default = 0 MB means unlimited)	integer	Minimum value: 0 Maximum value: 4096	0
scan-oversize-log	Enable/disable scan oversize log (default = enable).	option	-	enable
	Option Description			
	<i>disable</i>	Disable scan oversize log.		
	<i>enable</i>	Enable scan oversize log.		

config icap-headers

Parameter	Description	Type	Size	Default
id	HTTP forwarded header ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	HTTP forwarded header name.	string	Maximum length: 79	
source	HTTP append header source.	option	-	content
	Option	Description		
	content	Create ICAP header from content.		
	http-header	Create ICAP header from HTTP header.		
	session	Create ICAP header from session info.		
content	HTTP header content.	string	Maximum length: 255	
http-header	HTTP header-field name.	string	Maximum length: 79	
session-info-type	Session info type.	option	-	client-ip
	Option	Description		
	client-ip	Client ip address.		
	user	Authentication user name.		
	upn	Authentication user principal name.		
	domain	User domain name.		
	local-grp	Firewall group name.		
	remote-grp	Group name from authentication server.		
	proxy-name	Proxy realm name.		
	auth-user-uri	Authenticated user uri.		
	auth-group-uri	Authenticated group uri.		
base64-encoding	Enable/disable use of base64 encoding of HTTP content.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable use of base64 encoding of HTTP content.		
	<i>enable</i>	Enable use of base64 encoding of HTTP content.		

config respmod-forward-rules

Parameter	Description	Type	Size	Default
name	Address name.	string	Maximum length: 63	
host	Address object for the host.	string	Maximum length: 79	
action	Action to be taken for ICAP server.	option	-	forward
	Option	Description		
	<i>forward</i>	Forward request to ICAP server when this rule is matched.		
	<i>bypass</i>	Don't forward request to ICAP server when this rule is matched.		
http-resp-status-code <code>	HTTP response status code. HTTP response status code.	integer	Minimum value: 100 Maximum value: 599	

config header-group

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
header-name	HTTP header.	string	Maximum length: 79	
header	HTTP header regular expression.	string	Maximum length: 255	
case-sensitivity	Enable/disable case sensitivity when matching header.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Ignore case when matching header.		
	<i>enable</i>	Do not ignore case when matching header.		

config icap remote-server

Configure ICAP servers.

```

config icap remote-server
    Description: Configure ICAP servers.
    edit <name>
        set addr-type [ip4|ip6|...]
        set ip-address {ipv4-address-any}
        set ip6-address {ipv6-address}
        set fqdn {string}
        set secure [disable|enable]
        set port {integer}
        set max-connections {integer}
        set ssl-cert {string}
        set healthcheck [disable|enable]
        set healthcheck-service {string}
    next
end

```

config icap remote-server

Parameter	Description	Type	Size	Default
name	Server name.	string	Maximum length: 63	
addr-type	Address type of the remote ICAP server: IPv4, IPv6 or FQDN.	option	-	ip4
	Option	Description		
	<i>ip4</i>	Use an IPv4 address for the remote ICAP server.		
	<i>ip6</i>	Use an IPv6 address for the remote ICAP server.		
	<i>fqdn</i>	Use the FQDN for the remote ICAP server.		
ip-address	IPv4 address of the ICAP server.	ipv4-address-any	Not Specified	0.0.0.0

Parameter	Description	Type	Size	Default						
ip6-address	IPv6 address of the ICAP server.	ipv6-address	Not Specified	::						
fqdn	ICAP remote server Fully Qualified Domain Name (FQDN).	string	Maximum length: 255							
secure	Enable/disable secure connection to ICAP server.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable connection to secure ICAP server.</td></tr><tr><td><i>enable</i></td><td>Enable connection to secure ICAP server.</td></tr></table>				Option	Description	<i>disable</i>	Disable connection to secure ICAP server.	<i>enable</i>	Enable connection to secure ICAP server.
Option	Description									
<i>disable</i>	Disable connection to secure ICAP server.									
<i>enable</i>	Enable connection to secure ICAP server.									
port	ICAP server port.	integer	Minimum value: 1 Maximum value: 65535	1344						
max-connections	Maximum number of concurrent connections to ICAP server (unlimited = 0, default = 100). Must not be less than wad-worker-count.	integer	Minimum value: 0 Maximum value: 4294967295	100						
ssl-cert	CA certificate name.	string	Maximum length: 79							
healthcheck	Enable/disable ICAP remote server health checking. Attempts to connect to the remote ICAP server to verify that the server is operating normally.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable health checking.</td></tr><tr><td><i>enable</i></td><td>Enable health checking.</td></tr></table>				Option	Description	<i>disable</i>	Disable health checking.	<i>enable</i>	Enable health checking.
Option	Description									
<i>disable</i>	Disable health checking.									
<i>enable</i>	Enable health checking.									
healthcheck-service	ICAP Service name to use for health checks.	string	Maximum length: 127							

config icap remote-server-group

Configure an ICAP remote server group consisting of multiple forward servers. Supports failover and load balancing.

```
config icap remote-server-group
    Description: Configure an ICAP remote server group consisting of multiple forward servers.
    Supports failover and load balancing.
```



```

edit <name>
    set ldb-method [weighted|least-session|...]
    config server-list
        Description: Add ICAP remote servers to a list to form a server group. Optionally
assign weights to each server.
        edit <name>
            set weight {integer}
        next
    end
next
end

```

config icap remote-server-group

Parameter	Description	Type	Size	Default								
name	Configure an ICAP remote server group consisting one or multiple forward servers. Supports failover and load balancing.	string	Maximum length: 63									
ldb-method	Load balance method.	option	-	weighted								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>weighted</i></td><td>Load balance traffic to forward servers based on assigned weights.</td></tr><tr><td><i>least-session</i></td><td>Send new sessions to the server with lowest session count.</td></tr><tr><td><i>active-passive</i></td><td>Send new sessions to active server with high weight.</td></tr></table>				Option	Description	<i>weighted</i>	Load balance traffic to forward servers based on assigned weights.	<i>least-session</i>	Send new sessions to the server with lowest session count.	<i>active-passive</i>	Send new sessions to active server with high weight.
Option	Description											
<i>weighted</i>	Load balance traffic to forward servers based on assigned weights.											
<i>least-session</i>	Send new sessions to the server with lowest session count.											
<i>active-passive</i>	Send new sessions to active server with high weight.											

config server-list

Parameter	Description	Type	Size	Default
name	ICAP remote server name.	string	Maximum length: 63	
weight	Optionally assign a weight of the forwarding server for weighted load balancing (1 - 100, default = 10).	integer	Minimum value: 1 Maximum value: 100	10

image-analyzer

This section includes syntax for the following commands:

- [config image-analyzer profile on page 474](#)

config image-analyzer profile

Configure image analyzer profiles

```
config image-analyzer profile
  Description: Configure image analyzer profiles
  edit <name>
    set comment {var-string}
    set alcohol-block-strictness-level {integer}
    set alcohol-status [allow|deny|...]
    set drugs-block-strictness-level {integer}
    set drugs-status [allow|deny|...]
    set extremism-block-strictness-level {integer}
    set extremism-status [allow|deny|...]
    set gambling-block-strictness-level {integer}
    set gambling-status [allow|deny|...]
    set gore-block-strictness-level {integer}
    set gore-status [allow|deny|...]
    set porn-block-strictness-level {integer}
    set porn-status [allow|deny|...]
    set swim_underwear-block-strictness-level {integer}
    set swim_underwear-status [allow|deny|...]
    set weapons-block-strictness-level {integer}
    set weapons-status [allow|deny|...]
    set image-skip-size {integer}
    set image-skip-width {integer}
    set image-skip-height {integer}
    set log-option [all|violation]
    set source-url [enable|disable]
    set blocked-img-cache [enable|disable]
    set rating-err-action [block|pass]
    set replace-image {string}
    set optical-character-recognition [enable|disable]
    set ocr-activation-threshold {integer}
  next
end
```

config image-analyzer profile

Parameter	Description	Type	Size	Default								
name	Profile name.	string	Maximum length: 35									
comment	Comment.	var-string	Maximum length: 255									
alcohol-block-strictness-level	Higher value means an image is more likely to be blocked(0 - 100, 0 = allow all images, 100 = block all images).	integer	Minimum value: 0 Maximum value: 100	30								
alcohol-status	Allow/deny/monitor the category image.	option	-	deny								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the category image.</td></tr><tr><td><i>deny</i></td><td>Deny the category image.</td></tr><tr><td><i>monitor</i></td><td>Monitor the category image.</td></tr></table>	Option	Description	<i>allow</i>	Allow the category image.	<i>deny</i>	Deny the category image.	<i>monitor</i>	Monitor the category image.			
Option	Description											
<i>allow</i>	Allow the category image.											
<i>deny</i>	Deny the category image.											
<i>monitor</i>	Monitor the category image.											
drugs-block-strictness-level	Higher value means an image is more likely to be blocked(0 - 100, 0 = allow all images, 100 = block all images).	integer	Minimum value: 0 Maximum value: 100	30								
drugs-status	Allow/deny/monitor the category image.	option	-	deny								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the category image.</td></tr><tr><td><i>deny</i></td><td>Deny the category image.</td></tr><tr><td><i>monitor</i></td><td>Monitor the category image.</td></tr></table>	Option	Description	<i>allow</i>	Allow the category image.	<i>deny</i>	Deny the category image.	<i>monitor</i>	Monitor the category image.			
Option	Description											
<i>allow</i>	Allow the category image.											
<i>deny</i>	Deny the category image.											
<i>monitor</i>	Monitor the category image.											
extremism-block-strictness-level	Higher value means an image is more likely to be blocked(0 - 100, 0 = allow all images, 100 = block all images).	integer	Minimum value: 0 Maximum value: 100	30								
extremism-status	Allow/deny/monitor the category image.	option	-	deny								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow the category image.</td></tr><tr><td><i>deny</i></td><td>Deny the category image.</td></tr><tr><td><i>monitor</i></td><td>Monitor the category image.</td></tr></table>	Option	Description	<i>allow</i>	Allow the category image.	<i>deny</i>	Deny the category image.	<i>monitor</i>	Monitor the category image.			
Option	Description											
<i>allow</i>	Allow the category image.											
<i>deny</i>	Deny the category image.											
<i>monitor</i>	Monitor the category image.											

Parameter	Description	Type	Size	Default
gambling-block-strictness-level	Higher value means an image is more likely to be blocked(0 - 100, 0 = allow all images, 100 = block all images).	integer	Minimum value: 0 Maximum value: 100	30
gambling-status	Allow/deny/monitor the category image.	option	-	deny
	Option	Description		
	<i>allow</i>	Allow the category image.		
	<i>deny</i>	Deny the category image.		
	<i>monitor</i>	Monitor the category image.		
gore-block-strictness-level	Higher value means an image is more likely to be blocked(0 - 100, 0 = allow all images, 100 = block all images).	integer	Minimum value: 0 Maximum value: 100	30
gore-status	Allow/deny/monitor the category image.	option	-	deny
	Option	Description		
	<i>allow</i>	Allow the category image.		
	<i>deny</i>	Deny the category image.		
	<i>monitor</i>	Monitor the category image.		
porn-block-strictness-level	Higher value means an image is more likely to be blocked(0 - 100, 0 = allow all images, 100 = block all images).	integer	Minimum value: 0 Maximum value: 100	30
porn-status	Allow/deny/monitor the category image.	option	-	deny
	Option	Description		
	<i>allow</i>	Allow the category image.		
	<i>deny</i>	Deny the category image.		
	<i>monitor</i>	Monitor the category image.		
swim_underwear-block-strictness-level	Higher value means an image is more likely to be blocked(0 - 100, 0 = allow all images, 100 = block all images).	integer	Minimum value: 0 Maximum value: 100	30

Parameter	Description	Type	Size	Default
swim_underwear-status	Allow/deny/monitor the category image.	option	-	deny
	Option Description			
	<i>allow</i>	Allow the category image.		
	<i>deny</i>	Deny the category image.		
	<i>monitor</i>	Monitor the category image.		
weapons-block-strictness-level	Higher value means an image is more likely to be blocked(0 - 100, 0 = allow all images, 100 = block all images).	integer	Minimum value: 0 Maximum value: 100	30
weapons-status	Allow/deny/monitor the category image.	option	-	deny
	Option Description			
	<i>allow</i>	Allow the category image.		
	<i>deny</i>	Deny the category image.		
	<i>monitor</i>	Monitor the category image.		
image-skip-size	Image skip rating size(0-2048k).	integer	Minimum value: 0 Maximum value: 2048	1
image-skip-width	Image skip rating width(min. 5 pixel).	integer	Minimum value: 5 Maximum value: 2147483647	30
image-skip-height	Image skip rating height(min. 5 pixel).	integer	Minimum value: 5 Maximum value: 2147483647	30
log-option	Log option for the inspected image result.	option	-	violation
	Option Description			
	<i>all</i>	Log all image result.		
	<i>violation</i>	Log only violation image result.		

Parameter	Description	Type	Size	Default						
source-url	Enable/disable source url in the image search result.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable source url in image search.</td></tr><tr><td><i>disable</i></td><td>Disable source url in image search.</td></tr></table>	Option	Description	<i>enable</i>	Enable source url in image search.	<i>disable</i>	Disable source url in image search.			
Option	Description									
<i>enable</i>	Enable source url in image search.									
<i>disable</i>	Disable source url in image search.									
blocked-img-cache	Enable/disable saving blocked images in ram disk.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable caching.</td></tr><tr><td><i>disable</i></td><td>Disable caching.</td></tr></table>	Option	Description	<i>enable</i>	Enable caching.	<i>disable</i>	Disable caching.			
Option	Description									
<i>enable</i>	Enable caching.									
<i>disable</i>	Disable caching.									
rating-err-action	Actions when image rating error.	option	-	pass						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>block</i></td><td>Block.</td></tr><tr><td><i>pass</i></td><td>Pass.</td></tr></table>	Option	Description	<i>block</i>	Block.	<i>pass</i>	Pass.			
Option	Description									
<i>block</i>	Block.									
<i>pass</i>	Pass.									
replace-image	Specify replacement image.	string	Maximum length: 35							
optical-character-recognition	Enable/disable optical character recognition.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable optical character recognition.</td></tr><tr><td><i>disable</i></td><td>Disable optical character recognition.</td></tr></table>	Option	Description	<i>enable</i>	Enable optical character recognition.	<i>disable</i>	Disable optical character recognition.			
Option	Description									
<i>enable</i>	Enable optical character recognition.									
<i>disable</i>	Disable optical character recognition.									
ocr-activation-threshold	Threshold to activate optical character recognition(0 - 100, 0 = bypass all images without DLP, 100 = process all images with DLP).	integer	Minimum value: 0 Maximum value: 100	30						

ips

This section includes syntax for the following commands:

- [config ips custom on page 479](#)
- [config ips decoder on page 481](#)
- [config ips global on page 481](#)
- [config ips rule-settings on page 487](#)
- [config ips rule on page 485](#)
- [config ips sensor on page 487](#)
- [config ips session on page 493](#)
- [config ips settings on page 493](#)
- [config ips view-map on page 494](#)

config ips custom

Configure IPS custom signature.

```
config ips custom
  Description: Configure IPS custom signature.
  edit <tag>
    set signature {var-string}
    set rule-id {integer}
    set severity {user}
    set location {user}
    set os {user}
    set application {user}
    set protocol {user}
    set status [disable|enable]
    set log [disable|enable]
    set log-packet [disable|enable]
    set action [pass|block]
    set comment {string}
  next
end
```

config ips custom

Parameter	Description	Type	Size	Default
tag	Signature tag.	string	Maximum length: 63	

Parameter	Description	Type	Size	Default						
signature	Custom signature enclosed in single quotes.	var-string	Maximum length: 4095							
rule-id	Signature ID.	integer	Minimum value: 0 Maximum value: 4294967295	0						
severity	Relative severity of the signature, from info to critical. Log messages generated by the signature include the severity.	user	Not Specified							
location	Protect client or server traffic.	user	Not Specified							
os	Operating system(s) that the signature protects. Blank for all operating systems.	user	Not Specified							
application	Applications to be protected. Blank for all applications.	user	Not Specified							
protocol	Protocol(s) that the signature scans. Blank for all protocols.	user	Not Specified							
status	Enable/disable this signature.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable status.</td></tr><tr><td><i>enable</i></td><td>Enable status.</td></tr></table>				Option	Description	<i>disable</i>	Disable status.	<i>enable</i>	Enable status.
Option	Description									
<i>disable</i>	Disable status.									
<i>enable</i>	Enable status.									
log	Enable/disable logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable logging.</td></tr><tr><td><i>enable</i></td><td>Enable logging.</td></tr></table>				Option	Description	<i>disable</i>	Disable logging.	<i>enable</i>	Enable logging.
Option	Description									
<i>disable</i>	Disable logging.									
<i>enable</i>	Enable logging.									
log-packet	Enable/disable packet logging.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable packet logging.</td></tr><tr><td><i>enable</i></td><td>Enable packet logging.</td></tr></table>				Option	Description	<i>disable</i>	Disable packet logging.	<i>enable</i>	Enable packet logging.
Option	Description									
<i>disable</i>	Disable packet logging.									
<i>enable</i>	Enable packet logging.									
action	Default action (pass or block) for this signature.	option	-	pass						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>pass</i>	Pass or allow matching traffic.		
	<i>block</i>	Block or drop matching traffic.		
comment	Comment.	string	Maximum length: 63	

config ips decoder

Configure IPS decoder.

```

config ips decoder
  Description: Configure IPS decoder.
  edit <name>
    config parameter
      Description: IPS group parameters.
      edit <name>
        set value {string}
      next
    end
  next
end

```

config ips decoder

Parameter	Description	Type	Size	Default
name	Decoder name.	string	Maximum length: 63	

config parameter

Parameter	Description	Type	Size	Default
name	Parameter name.	string	Maximum length: 31	
value	Parameter value.	string	Maximum length: 199	

config ips global

Configure IPS global parameter.

```

config ips global
    Description: Configure IPS global parameter.
    set fail-open [enable|disable]
    set database [regular|extended]
    set traffic-submit [enable|disable]
    set anomaly-mode [periodical|continuous]
    set session-limit-mode [accurate|heuristic]
    set socket-size {integer}
    set engine-count {integer}
    set sync-session-ttl [enable|disable]
    set deep-app-insp-timeout {integer}
    set deep-app-insp-db-limit {integer}
    set exclude-signatures [none|industrial]
    set packet-log-queue-depth {integer}
    config tls-active-probe
        Description: TLS active probe configuration.
        set interface-select-method [auto|sdwan|...]
        set interface {string}
        set vdom {string}
        set source-ip {ipv4-address}
        set source-ip6 {ipv6-address}
    end
end

```

config ips global

Parameter	Description	Type	Size	Default						
fail-open	Enable to allow traffic if the IPS buffer is full. Default is disable and IPS traffic is blocked when the IPS buffer is full.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable IPS fail open.</td></tr><tr><td><i>disable</i></td><td>Disable IPS fail open.</td></tr></table>	Option	Description	<i>enable</i>	Enable IPS fail open.	<i>disable</i>	Disable IPS fail open.			
Option	Description									
<i>enable</i>	Enable IPS fail open.									
<i>disable</i>	Disable IPS fail open.									
database	Regular or extended IPS database. Regular protects against the latest common and in-the-wild attacks. Extended includes protection from legacy attacks.	option	-	extended						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>regular</i></td><td>IPS regular database package.</td></tr><tr><td><i>extended</i></td><td>IPS extended database package.</td></tr></table>	Option	Description	<i>regular</i>	IPS regular database package.	<i>extended</i>	IPS extended database package.			
Option	Description									
<i>regular</i>	IPS regular database package.									
<i>extended</i>	IPS extended database package.									
traffic-submit	Enable/disable submitting attack data found by this FortiProxy to FortiGuard.	option	-	disable						

Parameter	Description	Type	Size	Default
	Option Description			
	<i>enable</i>	Enable traffic submit.		
	<i>disable</i>	Disable traffic submit.		
anomaly-mode	Global blocking mode for rate-based anomalies.	option	-	continuous
	Option Description			
	<i>periodical</i>	After an anomaly is detected, allow the number of packets per second according to the anomaly configuration.		
	<i>continuous</i>	Block packets once an anomaly is detected. Overrides individual anomaly settings.		
session-limit-mode	Method of counting concurrent sessions used by session limit anomalies. Choose between greater accuracy (accurate) or improved performance (heuristics).	option	-	heuristic
	Option Description			
	<i>accurate</i>	Accurately count concurrent sessions, demands more resources.		
	<i>heuristic</i>	Use heuristics to estimate the number of concurrent sessions. Acceptable in most cases.		
socket-size	IPS socket buffer size. Max and default value depend on available memory. Can be changed to tune performance.	integer	Minimum value: 0 Maximum value: 128	64
engine-count	Number of IPS engines running. If set to the default value of 0, FortiProxy sets the number to optimize performance depending on the number of CPU cores.	integer	Minimum value: 0 Maximum value: 255	0
sync-session-ttl	Enable/disable use of kernel session TTL for IPS sessions.	option	-	enable
	Option Description			
	<i>enable</i>	Enable use of kernel session TTL for IPS sessions.		
	<i>disable</i>	Disable use of kernel session TTL for IPS sessions.		

Parameter	Description	Type	Size	Default						
deep-app-insp-timeout	Timeout for Deep application inspection (1 - 2147483647 sec., 0 = use recommended setting).	integer	Minimum value: 0 Maximum value: 2147483647	0						
deep-app-insp-db-limit	Limit on number of entries in deep application inspection database (1 - 2147483647, use recommended setting = 0).	integer	Minimum value: 0 Maximum value: 2147483647	0						
exclude-signatures	Excluded signatures.	option	-	industrial						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>none</i></td><td>No signatures excluded.</td></tr><tr><td><i>industrial</i></td><td>Exclude industrial signatures.</td></tr></table>				Option	Description	<i>none</i>	No signatures excluded.	<i>industrial</i>	Exclude industrial signatures.
Option	Description									
<i>none</i>	No signatures excluded.									
<i>industrial</i>	Exclude industrial signatures.									
packet-log-queue-depth	Packet/pcap log queue depth per IPS engine.	integer	Minimum value: 128 Maximum value: 4096	128						

config tls-active-probe

Parameter	Description	Type	Size	Default
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto
	Option	Description		
	<i>auto</i>	Set outgoing interface automatically.		
	<i>sdwan</i>	Set outgoing interface by SD-WAN or policy routing rules.		
	<i>specify</i>	Set outgoing interface manually.		
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	
vdom	Virtual domain name for TLS active probe.	string	Maximum length: 31	
source-ip	Source IP address used for TLS active probe.	ipv4-address	Not Specified	0.0.0.0
source-ip6	Source IPv6 address used for TLS active probe.	ipv6-address	Not Specified	::

config ips rule

Configure IPS rules.

```
config ips rule
  Description: Configure IPS rules.
  edit <name>
    set log [disable|enable]
    set log-packet [disable|enable]
    set action [pass|block]
    set group {string}
    set severity {user}
    set location {user}
    set os {user}
    set application {user}
    set service {user}
    set rule-id {integer}
    set rev {integer}
    set date {integer}
    config metadata
      Description: Meta data.
      edit <id>
        set metaid {integer}
        set valueid {integer}
      next
    end
  next
end
```

config ips rule

Parameter	Description	Type	Size	Default
name	Rule name.	string	Maximum length: 63	
log	Enable/disable logging.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable logging.		
	<i>enable</i>	Enable logging.		
log-packet	Enable/disable packet logging.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable packet logging.		
	<i>enable</i>	Enable packet logging.		

Parameter	Description	Type	Size	Default						
action	Action.	option	-	pass						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>pass</i></td><td>Pass or allow matching traffic.</td></tr><tr><td><i>block</i></td><td>Block or drop matching traffic.</td></tr></table>				Option	Description	<i>pass</i>	Pass or allow matching traffic.	<i>block</i>	Block or drop matching traffic.
	Option	Description								
	<i>pass</i>	Pass or allow matching traffic.								
<i>block</i>	Block or drop matching traffic.									
group	Group.	string	Maximum length: 63							
severity	Severity.	user	Not Specified							
location	Vulnerable location.	user	Not Specified							
os	Vulnerable operation systems.	user	Not Specified							
application	Vulnerable applications.	user	Not Specified							
service	Vulnerable service.	user	Not Specified							
rule-id	Rule ID.	integer	Minimum value: 0 Maximum value: 4294967295	0						
rev	Revision.	integer	Minimum value: 0 Maximum value: 4294967295	0						
date	Date.	integer	Minimum value: 0 Maximum value: 4294967295	0						

config metadata

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

Parameter	Description	Type	Size	Default
metaid	Meta ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
valueid	Value ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

config ips rule-settings

Configure IPS rule setting.

```
config ips rule-settings
    Description: Configure IPS rule setting.
    edit <id>
        next
    end
```

config ips rule-settings

Parameter	Description	Type	Size	Default
id	Rule ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

config ips sensor

Configure IPS sensor.

```
config ips sensor
    Description: Configure IPS sensor.
    edit <name>
        set comment {var-string}
        set replacemsg-group {string}
        set block-malicious-url [disable|enable]
        set scan-botnet-connections [disable|block|...]
        set extended-log [enable|disable]
```

```

config entries
    Description: IPS sensor filter.
    edit <id>
        set rule <id1>, <id2>, ...
        set location {user}
        set severity {user}
        set protocol {user}
        set os {user}
        set application {user}
        set default-action [all|pass|...]
        set default-status [all|enable|...]
        set cve <cve-entry1>, <cve-entry2>, ...
        set vuln-type <id1>, <id2>, ...
        set last-modified {user}
        set status [disable|enable|...]
        set log [disable|enable]
        set log-packet [disable|enable]
        set log-attack-context [disable|enable]
        set action [pass|block|...]
        set rate-count {integer}
        set rate-duration {integer}
        set rate-mode [periodical|continuous]
        set rate-track [none|src-ip|...]
        config exempt-ip
            Description: Traffic from selected source or destination IP addresses is
exempt from this signature.
            edit <id>
                set src-ip {ipv4-classnet}
                set dst-ip {ipv4-classnet}
            next
        end
        set quarantine [none|attacker]
        set quarantine-expiry {user}
        set quarantine-log [disable|enable]
    next
end
next
end

```

config ips sensor

Parameter	Description	Type	Size	Default
name	Sensor name.	string	Maximum length: 35	
comment	Comment.	var-string	Maximum length: 255	

Parameter	Description	Type	Size	Default								
replacemsg-group	Replacement message group.	string	Maximum length: 35									
block-malicious-url	Enable/disable malicious URL blocking.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable malicious URL blocking.</td></tr><tr><td><i>enable</i></td><td>Enable malicious URL blocking.</td></tr></table>	Option	Description	<i>disable</i>	Disable malicious URL blocking.	<i>enable</i>	Enable malicious URL blocking.					
Option	Description											
<i>disable</i>	Disable malicious URL blocking.											
<i>enable</i>	Enable malicious URL blocking.											
scan-botnet-connections	Block or monitor connections to Botnet servers, or disable Botnet scanning.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not scan connections to botnet servers.</td></tr><tr><td><i>block</i></td><td>Block connections to botnet servers.</td></tr><tr><td><i>monitor</i></td><td>Log connections to botnet servers.</td></tr></table>	Option	Description	<i>disable</i>	Do not scan connections to botnet servers.	<i>block</i>	Block connections to botnet servers.	<i>monitor</i>	Log connections to botnet servers.			
Option	Description											
<i>disable</i>	Do not scan connections to botnet servers.											
<i>block</i>	Block connections to botnet servers.											
<i>monitor</i>	Log connections to botnet servers.											
extended-log	Enable/disable extended logging.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.					
Option	Description											
<i>enable</i>	Enable setting.											
<i>disable</i>	Disable setting.											

config entries

Parameter	Description	Type	Size	Default
id	Rule ID in IPS database (0 - 4294967295).	integer	Minimum value: 0 Maximum value: 4294967295	0
rule <id>	Identifies the predefined or custom IPS signatures to add to the sensor. Rule IPS.	integer	Minimum value: 0 Maximum value: 4294967295	
location	Protect client or server traffic.	user	Not Specified	all

Parameter	Description	Type	Size	Default								
severity	Relative severity of the signature, from info to critical. Log messages generated by the signature include the severity.	user	Not Specified	all								
protocol	Protocols to be examined. Use all for every protocol and other for unlisted protocols.	user	Not Specified	all								
os	Operating systems to be protected. Use all for every operating system and other for unlisted operating systems.	user	Not Specified	all								
application	Operating systems to be protected. Use all for every application and other for unlisted application.	user	Not Specified	all								
default-action	Signature default action filter.	option	-	all								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>all</td><td>Selects signatures with any default action.</td></tr><tr><td>pass</td><td>Selects signatures with default action 'pass'.</td></tr><tr><td>block</td><td>Selects signatures with default action 'block'.</td></tr></table>	Option	Description	all	Selects signatures with any default action.	pass	Selects signatures with default action 'pass'.	block	Selects signatures with default action 'block'.			
Option	Description											
all	Selects signatures with any default action.											
pass	Selects signatures with default action 'pass'.											
block	Selects signatures with default action 'block'.											
default-status	Signature default status filter.	option	-	all								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>all</td><td>Selects signatures with any default status.</td></tr><tr><td>enable</td><td>Selects signatures enabled by default.</td></tr><tr><td>disable</td><td>Selects signatures disabled by default.</td></tr></table>	Option	Description	all	Selects signatures with any default status.	enable	Selects signatures enabled by default.	disable	Selects signatures disabled by default.			
Option	Description											
all	Selects signatures with any default status.											
enable	Selects signatures enabled by default.											
disable	Selects signatures disabled by default.											
cve <cve-entry>	List of CVE IDs of the signatures to add to the sensor. CVE IDs or CVE wildcards.	string	Maximum length: 19									
vuln-type <id>	List of signature vulnerability types to filter by. Vulnerability type ID.	integer	Minimum value: 0 Maximum value: 4294967295									
last-modified	Filter by signature last modified date. Formats: before <date>, after <date>, between <start-date> <end-date>.	user	Not Specified									

Parameter	Description	Type	Size	Default
status	Status of the signatures included in filter. Only those filters with a status to enable are used.	option	-	default
	Option	Description		
	<i>disable</i>	Disable status of selected rules.		
	<i>enable</i>	Enable status of selected rules.		
log	Enable/disable logging of signatures included in filter.	option	-	enable
log-packet	Enable/disable packet logging. Enable to save the packet that triggers the filter. You can download the packets in pcap format for diagnostic use.	option	-	disable
log-attack-context	Enable/disable logging of attack context: URL buffer, header buffer, body buffer, packet buffer.	option	-	disable
action	Action taken with traffic in which signatures are detected.	option	-	default

Parameter	Description	Type	Size	Default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Pass or drop matching traffic, depending on the default action of the signature.</td></tr></table>	Option	Description	<i>default</i>	Pass or drop matching traffic, depending on the default action of the signature.											
	Option	Description														
	<i>default</i>	Pass or drop matching traffic, depending on the default action of the signature.														
rate-count	Count of the rate.	integer	Minimum value: 0 Maximum value: 65535	0												
rate-duration	Duration (sec) of the rate.	integer	Minimum value: 1 Maximum value: 65535	60												
rate-mode	Rate limit mode.	option	-	continuous												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>periodical</i></td><td>Allow configured number of packets every rate-duration.</td></tr><tr><td><i>continuous</i></td><td>Block packets once the rate is reached.</td></tr></table>	Option	Description	<i>periodical</i>	Allow configured number of packets every rate-duration.	<i>continuous</i>	Block packets once the rate is reached.									
	Option	Description														
	<i>periodical</i>	Allow configured number of packets every rate-duration.														
<i>continuous</i>	Block packets once the rate is reached.															
rate-track	Track the packet protocol field.	option	-	none												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>none</i></td><td>none</td></tr><tr><td><i>src-ip</i></td><td>Source IP.</td></tr><tr><td><i>dest-ip</i></td><td>Destination IP.</td></tr><tr><td><i>dhcp-client-mac</i></td><td>DHCP client.</td></tr><tr><td><i>dns-domain</i></td><td>DNS domain.</td></tr></table>	Option	Description	<i>none</i>	none	<i>src-ip</i>	Source IP.	<i>dest-ip</i>	Destination IP.	<i>dhcp-client-mac</i>	DHCP client.	<i>dns-domain</i>	DNS domain.			
	Option	Description														
	<i>none</i>	none														
	<i>src-ip</i>	Source IP.														
	<i>dest-ip</i>	Destination IP.														
	<i>dhcp-client-mac</i>	DHCP client.														
<i>dns-domain</i>	DNS domain.															
quarantine	Quarantine method.	option	-	none												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>none</i></td><td>Quarantine is disabled.</td></tr><tr><td><i>attacker</i></td><td>Block all traffic sent from attacker's IP address. The attacker's IP address is also added to the banned user list. The target's address is not affected.</td></tr></table>	Option	Description	<i>none</i>	Quarantine is disabled.	<i>attacker</i>	Block all traffic sent from attacker's IP address. The attacker's IP address is also added to the banned user list. The target's address is not affected.									
	Option	Description														
	<i>none</i>	Quarantine is disabled.														
<i>attacker</i>	Block all traffic sent from attacker's IP address. The attacker's IP address is also added to the banned user list. The target's address is not affected.															
quarantine-expiry	Duration of quarantine. (Format ###d##h##m, minimum 1m, maximum 364d23h59m, default = 5m). Requires quarantine set to attacker.	user	Not Specified	5m												

Parameter	Description	Type	Size	Default
quarantine-log	Enable/disable quarantine logging.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable quarantine logging.		
	<i>enable</i>	Enable quarantine logging.		

config exempt-ip

Parameter	Description	Type	Size	Default
id	Exempt IP ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
src-ip	Source IP address and netmask (applies to packet matching the signature).	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0
dst-ip	Destination IP address and netmask (applies to packet matching the signature).	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0

config ips session

Session status.

```
config ips session
    Description: Session status.
end
```

config ips settings

Configure IPS VDOM parameter.

```
config ips settings
    Description: Configure IPS VDOM parameter.
    set packet-log-history {integer}
    set packet-log-post-attack {integer}
    set packet-log-memory {integer}
    set ips-packet-quota {integer}
    set proxy-inline-ips [disable|enable]
end
```

config ips settings

Parameter	Description	Type	Size	Default						
packet-log-history	Number of packets to capture before and including the one in which the IPS signature is detected (1 - 255).	integer	Minimum value: 1 Maximum value: 255	1						
packet-log-post-attack	Number of packets to log after the IPS signature is detected (0 - 255).	integer	Minimum value: 0 Maximum value: 255	0						
packet-log-memory	Maximum memory can be used by packet log (64 - 8192 kB).	integer	Minimum value: 64 Maximum value: 8192	256						
ips-packet-quota	Maximum amount of disk space in MB for logged packets when logging to disk. Range depends on disk size.	integer	Minimum value: 0 Maximum value: 4294967295	0						
proxy-inline-ips	Enable/disable firewall policy inline IPS support.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not allow inline IPS in firewall policy.</td></tr><tr><td><i>enable</i></td><td>Allow inline IPS in firewall policy.</td></tr></table>				Option	Description	<i>disable</i>	Do not allow inline IPS in firewall policy.	<i>enable</i>	Allow inline IPS in firewall policy.
Option	Description									
<i>disable</i>	Do not allow inline IPS in firewall policy.									
<i>enable</i>	Allow inline IPS in firewall policy.									

config ips view-map

Configure IPS view-map.

```
config ips view-map
  Description: Configure IPS view-map.
  edit <id>
    set vdom-id {integer}
    set policy-id {integer}
    set id-policy-id {integer}
    set which {option}
  next
end
```

config ips view-map

Parameter	Description	Type	Size	Default
id	View ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
vdom-id	VDOM ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
policy-id	Policy ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
id-policy-id	ID-based policy ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
which	Policy.	option	-	firewall
		Option	Description	
		<i>firewall</i>	Firewall policy.	

ipsec

This section includes syntax for the following commands:

- [config ipsec tunnel on page 496](#)

config ipsec tunnel

IPsec tunnel.

```
config ipsec tunnel
    Description: IPsec tunnel.
end
```


isolator

This section includes syntax for the following commands:

- [config isolator profile on page 497](#)
- [config isolator setting on page 498](#)

config isolator profile

Configure isolator profiles.

```
config isolator profile
  Description: Configure isolator profiles.
  edit <name>
    set comments {var-string}
    set disclaimer {string}
    config entries
      Description: Isolator profile entries.
      edit <id>
        set proxy-address {string}
        set action [isolate|freeze|...]
        set status [enable|disable]
      next
    end
  next
end
```

config isolator profile

Parameter	Description	Type	Size	Default
name	Profile name.	string	Maximum length: 35	
comments	Comment.	var-string	Maximum length: 255	
disclaimer	A customized replacement message page for installer.	string	Maximum length: 35	

config entries

Parameter	Description	Type	Size	Default										
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0										
proxy-address	Choose the proxy-address for this isolator profile entry.	string	Maximum length: 79											
action	Choose the action for this isolator entry.	option	-	isolate										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>isolate</i></td><td>Open the website in an isolator instead of the client.</td></tr><tr><td><i>freeze</i></td><td>Freeze the website. The user is able to unfreeze and get access to the website when they accept the risk.</td></tr><tr><td><i>block</i></td><td>Block the traffic to the website.</td></tr><tr><td><i>allow</i></td><td>Bypass the traffic to the website.</td></tr></table>				Option	Description	<i>isolate</i>	Open the website in an isolator instead of the client.	<i>freeze</i>	Freeze the website. The user is able to unfreeze and get access to the website when they accept the risk.	<i>block</i>	Block the traffic to the website.	<i>allow</i>	Bypass the traffic to the website.
	Option	Description												
	<i>isolate</i>	Open the website in an isolator instead of the client.												
	<i>freeze</i>	Freeze the website. The user is able to unfreeze and get access to the website when they accept the risk.												
	<i>block</i>	Block the traffic to the website.												
<i>allow</i>	Bypass the traffic to the website.													
status	Enable/disable this isolator entry.													
	option													
	-													
	enable													
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable this entry.</td></tr><tr><td><i>disable</i></td><td>Disable this entry.</td></tr></table>				Option	Description	<i>enable</i>	Enable this entry.	<i>disable</i>	Disable this entry.				
	Option	Description												
	<i>enable</i>	Enable this entry.												
<i>disable</i>	Disable this entry.													

config isolator setting

Configure isolator setting.

```
config isolator setting
  Description: Configure isolator setting.
  set default-isolator-profile {string}
  set defective-session [use-default-profile|pass|...]
  set unmatched-session [use-default-profile|pass|...]
end
```

config isolator setting

Parameter	Description	Type	Size	Default
default-isolator-profile	Name of an existing isolator profile. This profile is used when no policy is matched.	string	Maximum length: 35	
defective-session	Choose the way to handle rating requests for sessions with missing information.	option	-	pass
	Option	Description		
	<i>use-default-profile</i>	Use default isolator profile to handle the session.		
	<i>pass</i>	Return bypass response to the rating request of the session.		
	<i>block</i>	Return block response to the rating request of the session.		
unmatched-session	Choose the way to handle rating requests for sessions that are unable to match any policy.	option	-	pass
	Option	Description		
	<i>use-default-profile</i>	Use default isolator profile to handle the session.		
	<i>pass</i>	Return bypass response to the rating request of the session.		
	<i>block</i>	Return block response to the rating request of the session.		

log

This section includes syntax for the following commands:

- [config log custom-field on page 501](#)
- [config log disk filter on page 502](#)
- [config log disk setting on page 505](#)
- [config log eventfilter on page 511](#)
- [config log fortianalyzer-cloud filter on page 563](#)
- [config log fortianalyzer-cloud override-filter on page 567](#)
- [config log fortianalyzer-cloud override-setting on page 570](#)
- [config log fortianalyzer-cloud setting on page 571](#)
- [config log fortianalyzer2 filter on page 531](#)
- [config log fortianalyzer2 override-filter on page 534](#)
- [config log fortianalyzer2 override-setting on page 538](#)
- [config log fortianalyzer2 setting on page 543](#)
- [config log fortianalyzer3 filter on page 547](#)
- [config log fortianalyzer3 override-filter on page 551](#)
- [config log fortianalyzer3 override-setting on page 554](#)
- [config log fortianalyzer3 setting on page 559](#)
- [config log fortianalyzer filter on page 515](#)
- [config log fortianalyzer override-filter on page 518](#)
- [config log fortianalyzer override-setting on page 522](#)
- [config log fortianalyzer setting on page 526](#)
- [config log fortiguard filter on page 574](#)
- [config log fortiguard override-filter on page 578](#)
- [config log fortiguard override-setting on page 581](#)
- [config log fortiguard setting on page 583](#)
- [config log gui-display on page 585](#)
- [config log memory filter on page 586](#)
- [config log memory global-setting on page 590](#)
- [config log memory setting on page 590](#)
- [config log null-device filter on page 591](#)
- [config log null-device setting on page 594](#)
- [config log setting on page 595](#)
- [config log syslogd2 filter on page 616](#)
- [config log syslogd2 override-filter on page 620](#)
- [config log syslogd2 override-setting on page 623](#)
- [config log syslogd2 setting on page 628](#)
- [config log syslogd3 filter on page 633](#)

- [config log syslogd3 override-filter on page 637](#)
- [config log syslogd3 override-setting on page 640](#)
- [config log syslogd3 setting on page 645](#)
- [config log syslogd4 filter on page 650](#)
- [config log syslogd4 override-filter on page 654](#)
- [config log syslogd4 override-setting on page 657](#)
- [config log syslogd4 setting on page 662](#)
- [config log syslogd filter on page 599](#)
- [config log syslogd override-filter on page 603](#)
- [config log syslogd override-setting on page 606](#)
- [config log syslogd setting on page 611](#)
- [config log tacacs+accounting2 filter on page 669](#)
- [config log tacacs+accounting2 setting on page 670](#)
- [config log tacacs+accounting3 filter on page 671](#)
- [config log tacacs+accounting3 setting on page 672](#)
- [config log tacacs+accounting filter on page 667](#)
- [config log tacacs+accounting setting on page 668](#)
- [config log threat-weight on page 673](#)
- [config log webtrends filter on page 685](#)
- [config log webtrends setting on page 688](#)

config log custom-field

Configure custom log fields.

```
config log custom-field
    Description: Configure custom log fields.
    edit <id>
        set name {string}
        set value {string}
    next
end
```

config log custom-field

Parameter	Description	Type	Size	Default
id	Field ID string.	string	Maximum length: 35	
name	Field name (max: 15 characters).	string	Maximum length: 15	
value	Field value (max: 15 characters).	string	Maximum length: 15	

config log disk filter

Configure filters for local disk logging. Use these filters to determine the log messages to record according to severity and type.

```
config log disk filter
    Description: Configure filters for local disk logging. Use these filters to determine the log
    messages to record according to severity and type.
    set severity [emergency|alert|...]
    set forward-traffic [enable|disable]
    set local-traffic [enable|disable]
    set multicast-traffic [enable|disable]
    set sniffer-traffic [enable|disable]
    set ztna-traffic [enable|disable]
    set http-transaction [enable|disable]
    set anomaly [enable|disable]
    set voip [enable|disable]
    set dlp-archive [enable|disable]
    config free-style
        Description: Free style filters.
        edit <id>
            set category [traffic|event|...]
            set filter {string}
            set filter-type [include|exclude]
        next
    end
end
```

config log disk filter

Parameter	Description	Type	Size	Default
severity	Log to disk every message above and including this severity level.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		

Parameter	Description	Type	Size	Default						
forward-traffic	Enable/disable forward traffic logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable forward traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable forward traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable forward traffic logging.	<i>disable</i>	Disable forward traffic logging.			
Option	Description									
<i>enable</i>	Enable forward traffic logging.									
<i>disable</i>	Disable forward traffic logging.									
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable local in or out traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable local in or out traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable local in or out traffic logging.	<i>disable</i>	Disable local in or out traffic logging.			
Option	Description									
<i>enable</i>	Enable local in or out traffic logging.									
<i>disable</i>	Disable local in or out traffic logging.									
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable multicast traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable multicast traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable multicast traffic logging.	<i>disable</i>	Disable multicast traffic logging.			
Option	Description									
<i>enable</i>	Enable multicast traffic logging.									
<i>disable</i>	Disable multicast traffic logging.									
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable sniffer traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable sniffer traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable sniffer traffic logging.	<i>disable</i>	Disable sniffer traffic logging.			
Option	Description									
<i>enable</i>	Enable sniffer traffic logging.									
<i>disable</i>	Disable sniffer traffic logging.									
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable ztna traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable ztna traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable ztna traffic logging.	<i>disable</i>	Disable ztna traffic logging.			
Option	Description									
<i>enable</i>	Enable ztna traffic logging.									
<i>disable</i>	Disable ztna traffic logging.									
http-transaction	Enable/disable log http-transaction messages.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable http transaction logging.</td></tr><tr><td><i>disable</i></td><td>Disable http transaction logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable http transaction logging.	<i>disable</i>	Disable http transaction logging.			
Option	Description									
<i>enable</i>	Enable http transaction logging.									
<i>disable</i>	Disable http transaction logging.									
anomaly	Enable/disable anomaly logging.	option	-	enable						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		
dlp-archive	Enable/disable DLP archive logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable DLP archive logging.		
	<i>disable</i>	Disable DLP archive logging.		

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	<i>traffic</i>	Traffic log.		
	<i>event</i>	Event log.		
	<i>virus</i>	Antivirus log.		
	<i>webfilter</i>	Web filter log.		
	<i>attack</i>	Attack log.		
	<i>spam</i>	Antispam log.		
	<i>anomaly</i>	Anomaly log.		
	<i>voip</i>	VoIP log.		
	<i>dlp</i>	DLP log.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>app-ctrl</i>	Application control log.		
	<i>waf</i>	Web application firewall log.		
	<i>dns</i>	DNS detail log.		
	<i>ssh</i>	SSH log.		
	<i>ssl</i>	SSL log.		
	<i>file-filter</i>	File filter log.		
	<i>icap</i>	ICAP log.		
filter	Free style filter string.	string	Maximum length: 1023	
filter-type	Include/exclude logs that match the filter.	option	-	include
	Option	Description		
	<i>include</i>	Include logs that match the filter.		
	<i>exclude</i>	Exclude logs that match the filter.		

config log disk setting

Settings for local disk logging.

```

config log disk setting
    Description: Settings for local disk logging.
    set status [enable|disable]
    set ips-archive [enable|disable]
    set max-log-file-size {integer}
    set max-policy-packet-capture-size {integer}
    set roll-schedule [daily|weekly]
    set roll-day {option1}, {option2}, ...
    set roll-time {user}
    set diskfull [overwrite|nolog]
    set log-quota {integer}
    set dlp-archive-quota {integer}
    set report-quota {integer}
    set maximum-log-age {integer}
    set upload [enable|disable]
    set upload-destination {option}
    set uploadip {ipv4-address}
    set uploadport {integer}
    set source-ip {ipv4-address}
    set uploaduser {string}

```

```

set uploadpass {password}
set uploadaddr {string}
set uploadtype {option1}, {option2}, ...
set uploadsched [disable|enable]
set uploadtime {user}
set upload-delete-files [enable|disable]
set upload-ssl-conn [default|high|...]
set full-first-warning-threshold {integer}
set full-second-warning-threshold {integer}
set full-final-warning-threshold {integer}
set interface-select-method [auto|specify]
set interface {string}
end

```

config log disk setting

Parameter	Description	Type	Size	Default						
status	Enable/disable local disk logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Log to local disk.</td></tr><tr><td><i>disable</i></td><td>Do not log to local disk.</td></tr></table>				Option	Description	<i>enable</i>	Log to local disk.	<i>disable</i>	Do not log to local disk.
	Option	Description								
	<i>enable</i>	Log to local disk.								
<i>disable</i>	Do not log to local disk.									
ips-archive	Enable/disable IPS packet archiving to the local disk.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable IPS packet archiving.</td></tr><tr><td><i>disable</i></td><td>Disable IPS packet archiving.</td></tr></table>				Option	Description	<i>enable</i>	Enable IPS packet archiving.	<i>disable</i>	Disable IPS packet archiving.
	Option	Description								
	<i>enable</i>	Enable IPS packet archiving.								
<i>disable</i>	Disable IPS packet archiving.									
max-log-file-size	Maximum log file size before rolling (1 - 100 Mbytes).	integer	Minimum value: 1 Maximum value: 100	20						
max-policy-packet-capture-size	Maximum size of policy sniffer in MB (0 means unlimited).	integer	Minimum value: 0 Maximum value: 4294967295	100						
roll-schedule	Frequency to check log file for rolling.	option	-	daily						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>daily</i>	Check the log file once a day.		
	<i>weekly</i>	Check the log file once a week.		
roll-day	Day of week on which to roll log file.	option	-	sunday
	Option	Description		
	<i>sunday</i>	Sunday		
	<i>monday</i>	Monday		
	<i>tuesday</i>	Tuesday		
	<i>wednesday</i>	Wednesday		
	<i>thursday</i>	Thursday		
	<i>friday</i>	Friday		
	<i>saturday</i>	Saturday		
roll-time	Time of day to roll the log file (hh:mm).	user	Not Specified	
diskfull	Action to take when disk is full. The system can overwrite the oldest log messages or stop logging when the disk is full (default = overwrite).	option	-	overwrite
	Option	Description		
	<i>overwrite</i>	Overwrite the oldest logs when the log disk is full.		
	<i>nolog</i>	Stop logging when the log disk is full.		
log-quota	Disk log quota (MB).	integer	Minimum value: 0 Maximum value: 4294967295	0
dlp-archive-quota	DLP archive quota (MB).	integer	Minimum value: 0 Maximum value: 4294967295	0

Parameter	Description	Type	Size	Default
report-quota	Report db quota (MB).	integer	Minimum value: 0 Maximum value: 4294967295	0
maximum-log-age	Delete log files older than (days).	integer	Minimum value: 0 Maximum value: 3650	7
upload	Enable/disable uploading log files when they are rolled.	option	-	disable
	Option	Description		
	enable	Enable uploading log files when they are rolled.		
	disable	Disable uploading log files when they are rolled.		
upload-destination	The type of server to upload log files to. Only FTP is currently supported.	option	-	ftp-server
	Option	Description		
	ftp-server	Upload rolled log files to an FTP server.		
uploadip	IP address of the FTP server to upload log files to.	ipv4-address	Not Specified	0.0.0.0
uploadport	TCP port to use for communicating with the FTP server (default = 21).	integer	Minimum value: 0 Maximum value: 65535	21
source-ip	Source IP address to use for uploading disk log files.	ipv4-address	Not Specified	0.0.0.0
uploaduser	Username required to log into the FTP server to upload disk log files.	string	Maximum length: 35	
uploadpass	Password required to log into the FTP server to upload disk log files.	password	Not Specified	
uploaddir	The remote directory on the FTP server to upload log files to.	string	Maximum length: 63	

Parameter	Description	Type	Size	Default																																				
uploadtype	Types of log files to upload. Separate multiple entries with a space.	option	-	traffic event virus webfilter IPS emailfilter dlp-archive anomaly voip dlp app-ctrl waf dns ssh ssl																																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>traffic</td><td>Upload traffic log.</td></tr><tr><td>event</td><td>Upload event log.</td></tr><tr><td>virus</td><td>Upload anti-virus log.</td></tr><tr><td>webfilter</td><td>Upload web filter log.</td></tr><tr><td>IPS</td><td>Upload IPS log.</td></tr><tr><td>emailfilter</td><td>Upload spam filter log.</td></tr><tr><td>dlp-archive</td><td>Upload DLP archive.</td></tr><tr><td>anomaly</td><td>Upload anomaly log.</td></tr><tr><td>voip</td><td>Upload VoIP log.</td></tr><tr><td>dlp</td><td>Upload DLP log.</td></tr><tr><td>app-ctrl</td><td>Upload application control log.</td></tr><tr><td>waf</td><td>Upload web application firewall log.</td></tr><tr><td>dns</td><td>Upload DNS log.</td></tr><tr><td>ssh</td><td>Upload SSH log.</td></tr><tr><td>ssl</td><td>Upload SSL log.</td></tr><tr><td>file-filter</td><td>Upload file-filter log.</td></tr><tr><td>icap</td><td>Upload ICAP log.</td></tr></table>	Option	Description	traffic	Upload traffic log.	event	Upload event log.	virus	Upload anti-virus log.	webfilter	Upload web filter log.	IPS	Upload IPS log.	emailfilter	Upload spam filter log.	dlp-archive	Upload DLP archive.	anomaly	Upload anomaly log.	voip	Upload VoIP log.	dlp	Upload DLP log.	app-ctrl	Upload application control log.	waf	Upload web application firewall log.	dns	Upload DNS log.	ssh	Upload SSH log.	ssl	Upload SSL log.	file-filter	Upload file-filter log.	icap	Upload ICAP log.			
	Option	Description																																						
	traffic	Upload traffic log.																																						
	event	Upload event log.																																						
	virus	Upload anti-virus log.																																						
	webfilter	Upload web filter log.																																						
	IPS	Upload IPS log.																																						
	emailfilter	Upload spam filter log.																																						
	dlp-archive	Upload DLP archive.																																						
	anomaly	Upload anomaly log.																																						
	voip	Upload VoIP log.																																						
	dlp	Upload DLP log.																																						
	app-ctrl	Upload application control log.																																						
	waf	Upload web application firewall log.																																						
	dns	Upload DNS log.																																						
	ssh	Upload SSH log.																																						
	ssl	Upload SSL log.																																						
file-filter	Upload file-filter log.																																							
icap	Upload ICAP log.																																							
uploadsched	Set the schedule for uploading log files to the FTP server (default = disable = upload when rolling).	option	-	disable																																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Upload when rolling.</td></tr><tr><td>enable</td><td>Scheduled upload.</td></tr></table>	Option	Description	disable	Upload when rolling.	enable	Scheduled upload.																																	
	Option	Description																																						
	disable	Upload when rolling.																																						
enable	Scheduled upload.																																							

Parameter	Description	Type	Size	Default										
uploadtime	Time of day at which log files are uploaded if uploadsched is enabled (hh:mm or hh).	user	Not Specified											
upload-delete-files	Delete log files after uploading (default = enable).	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Delete log files after uploading.</td></tr><tr><td>disable</td><td>Do not delete log files after uploading.</td></tr></table>	Option	Description	enable	Delete log files after uploading.	disable	Do not delete log files after uploading.							
Option	Description													
enable	Delete log files after uploading.													
disable	Do not delete log files after uploading.													
upload-ssl-conn	Enable/disable encrypted FTPS communication to upload log files.	option	-	default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>default</td><td>FTPS with high and medium encryption algorithms.</td></tr><tr><td>high</td><td>FTPS with high encryption algorithms.</td></tr><tr><td>low</td><td>FTPS with low encryption algorithms.</td></tr><tr><td>disable</td><td>Disable FTPS communication.</td></tr></table>	Option	Description	default	FTPS with high and medium encryption algorithms.	high	FTPS with high encryption algorithms.	low	FTPS with low encryption algorithms.	disable	Disable FTPS communication.			
Option	Description													
default	FTPS with high and medium encryption algorithms.													
high	FTPS with high encryption algorithms.													
low	FTPS with low encryption algorithms.													
disable	Disable FTPS communication.													
full-first-warning-threshold	Log full first warning threshold as a percent (1 - 98, default = 75).	integer	Minimum value: 1 Maximum value: 98	75										
full-second-warning-threshold	Log full second warning threshold as a percent (2 - 99, default = 90).	integer	Minimum value: 2 Maximum value: 99	90										
full-final-warning-threshold	Log full final warning threshold as a percent (3 - 100, default = 95).	integer	Minimum value: 3 Maximum value: 100	95										
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>auto</td><td>Set outgoing interface automatically.</td></tr><tr><td>specify</td><td>Set outgoing interface manually.</td></tr></table>	Option	Description	auto	Set outgoing interface automatically.	specify	Set outgoing interface manually.							
Option	Description													
auto	Set outgoing interface automatically.													
specify	Set outgoing interface manually.													
interface	Specify outgoing interface to reach server.	string	Maximum length: 15											

config log eventfilter

Configure log event filters.

```
config log eventfilter
  Description: Configure log event filters.
  set event [enable|disable]
  set system [enable|disable]
  set vpn [enable|disable]
  set user [enable|disable]
  set router [enable|disable]
  set wireless-activity [enable|disable]
  set wan-opt [enable|disable]
  set endpoint [enable|disable]
  set ha [enable|disable]
  set security-rating [enable|disable]
  set fortixtender [enable|disable]
  set connector [enable|disable]
  set sdwan [enable|disable]
  set cifs [enable|disable]
  set switch-controller [enable|disable]
  set wcs [enable|disable]
  set wdb [enable|disable]
  set aggd [enable|disable]
  set crwl [enable|disable]
  set rest-api [enable|disable]
  set webproxy [enable|disable]
  set iptables [enable|disable]
end
```

config log eventfilter

Parameter	Description	Type	Size	Default
event	Enable/disable event logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable event logging.		
	<i>disable</i>	Disable event logging.		
system	Enable/disable system event logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable system event logging.		
	<i>disable</i>	Disable system event logging.		

Parameter	Description	Type	Size	Default						
vpn	Enable/disable VPN event logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable VPN event logging.</td></tr><tr><td><i>disable</i></td><td>Disable VPN event logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable VPN event logging.	<i>disable</i>	Disable VPN event logging.			
Option	Description									
<i>enable</i>	Enable VPN event logging.									
<i>disable</i>	Disable VPN event logging.									
user	Enable/disable user authentication event logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable user authentication event logging.</td></tr><tr><td><i>disable</i></td><td>Disable user authentication event logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable user authentication event logging.	<i>disable</i>	Disable user authentication event logging.			
Option	Description									
<i>enable</i>	Enable user authentication event logging.									
<i>disable</i>	Disable user authentication event logging.									
router	Enable/disable router event logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable router event logging.</td></tr><tr><td><i>disable</i></td><td>Disable router event logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable router event logging.	<i>disable</i>	Disable router event logging.			
Option	Description									
<i>enable</i>	Enable router event logging.									
<i>disable</i>	Disable router event logging.									
wireless-activity	Enable/disable wireless event logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable wireless event logging.</td></tr><tr><td><i>disable</i></td><td>Disable wireless event logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable wireless event logging.	<i>disable</i>	Disable wireless event logging.			
Option	Description									
<i>enable</i>	Enable wireless event logging.									
<i>disable</i>	Disable wireless event logging.									
wan-opt	Enable/disable WAN optimization event logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable WAN optimization event logging.</td></tr><tr><td><i>disable</i></td><td>Disable WAN optimization event logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable WAN optimization event logging.	<i>disable</i>	Disable WAN optimization event logging.			
Option	Description									
<i>enable</i>	Enable WAN optimization event logging.									
<i>disable</i>	Disable WAN optimization event logging.									
endpoint	Enable/disable endpoint event logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable endpoint event logging.</td></tr><tr><td><i>disable</i></td><td>Disable endpoint event logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable endpoint event logging.	<i>disable</i>	Disable endpoint event logging.			
Option	Description									
<i>enable</i>	Enable endpoint event logging.									
<i>disable</i>	Disable endpoint event logging.									
ha	Enable/disable ha event logging.	option	-	enable						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable ha event logging.		
	<i>disable</i>	Disable ha event logging.		
security-rating	Enable/disable Security Rating result logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable Security Fabric audit result logging.		
	<i>disable</i>	Disable Security Fabric audit result logging.		
fortiextender	Enable/disable FortiExtender logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable Forti-Extender logging.		
	<i>disable</i>	Disable Forti-Extender logging.		
connector	Enable/disable SDN connector logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable SDN connector logging.		
	<i>disable</i>	Disable SDN connector logging.		
sdwan	Enable/disable SD-WAN logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable SD-WAN logging.		
	<i>disable</i>	Disable SD-WAN logging.		
cifs	Enable/disable CIFS logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable CIFS logging.		
	<i>disable</i>	Disable CIFS logging.		
switch-controller	Enable/disable Switch-Controller logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable Switch-Controller logging.		
	<i>disable</i>	Disable Switch-Controller logging.		

Parameter	Description	Type	Size	Default						
wcs	Enable/disable log for wcs events.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable Switch-Controller logging.</td></tr><tr><td><i>disable</i></td><td>Disable Switch-Controller logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable Switch-Controller logging.	<i>disable</i>	Disable Switch-Controller logging.			
Option	Description									
<i>enable</i>	Enable Switch-Controller logging.									
<i>disable</i>	Disable Switch-Controller logging.									
wdb	Enable/disable log for wdb events.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable Switch-Controller logging.</td></tr><tr><td><i>disable</i></td><td>Disable Switch-Controller logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable Switch-Controller logging.	<i>disable</i>	Disable Switch-Controller logging.			
Option	Description									
<i>enable</i>	Enable Switch-Controller logging.									
<i>disable</i>	Disable Switch-Controller logging.									
aggd	Enable/disable log for aggd events.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable Switch-Controller logging.</td></tr><tr><td><i>disable</i></td><td>Disable Switch-Controller logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable Switch-Controller logging.	<i>disable</i>	Disable Switch-Controller logging.			
Option	Description									
<i>enable</i>	Enable Switch-Controller logging.									
<i>disable</i>	Disable Switch-Controller logging.									
crwl	Enable/disable log for crwl events.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable Switch-Controller logging.</td></tr><tr><td><i>disable</i></td><td>Disable Switch-Controller logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable Switch-Controller logging.	<i>disable</i>	Disable Switch-Controller logging.			
Option	Description									
<i>enable</i>	Enable Switch-Controller logging.									
<i>disable</i>	Disable Switch-Controller logging.									
rest-api	Enable/disable REST API logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable REST API logging.</td></tr><tr><td><i>disable</i></td><td>Disable REST API logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable REST API logging.	<i>disable</i>	Disable REST API logging.			
Option	Description									
<i>enable</i>	Enable REST API logging.									
<i>disable</i>	Disable REST API logging.									
webproxy	Enable/disable web proxy event logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable Web Proxy event logging.</td></tr><tr><td><i>disable</i></td><td>Disable Web Proxy event logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable Web Proxy event logging.	<i>disable</i>	Disable Web Proxy event logging.			
Option	Description									
<i>enable</i>	Enable Web Proxy event logging.									
<i>disable</i>	Disable Web Proxy event logging.									
iptables	Enable/disable iptables event logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable iptables event logging.</td></tr><tr><td><i>disable</i></td><td>Disable iptables event logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable iptables event logging.	<i>disable</i>	Disable iptables event logging.			
Option	Description									
<i>enable</i>	Enable iptables event logging.									
<i>disable</i>	Disable iptables event logging.									

config log fortianalyzer filter

Filters for FortiAnalyzer.

```
config log fortianalyzer filter
  Description: Filters for FortiAnalyzer.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]
  set sniffer-traffic [enable|disable]
  set ztna-traffic [enable|disable]
  set http-transaction [enable|disable]
  set anomaly [enable|disable]
  set voip [enable|disable]
  set dlp-archive [enable|disable]
  config free-style
    Description: Free style filters.
    edit <id>
      set category [traffic|event|...]
      set filter {string}
      set filter-type [include|exclude]
    next
  end
end
```

config log fortianalyzer filter

Parameter	Description	Type	Size	Default
severity	Lowest severity level to log.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		
forward-traffic	Enable/disable forward traffic logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable multicast traffic logging.		
	<i>disable</i>	Disable multicast traffic logging.		
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable sniffer traffic logging.		
	<i>disable</i>	Disable sniffer traffic logging.		
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		
dlp-archive	Enable/disable DLP archive logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable DLP archive logging.		
	<i>disable</i>	Disable DLP archive logging.		

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	<i>traffic</i>	Traffic log.		
	<i>event</i>	Event log.		
	<i>virus</i>	Antivirus log.		
	<i>webfilter</i>	Web filter log.		
	<i>attack</i>	Attack log.		
	<i>spam</i>	Antispam log.		
	<i>anomaly</i>	Anomaly log.		
	<i>voip</i>	VoIP log.		
	<i>dlp</i>	DLP log.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>app-ctrl</i>	Application control log.		
	<i>waf</i>	Web application firewall log.		
	<i>dns</i>	DNS detail log.		
	<i>ssh</i>	SSH log.		
	<i>ssl</i>	SSL log.		
	<i>file-filter</i>	File filter log.		
	<i>icap</i>	ICAP log.		
filter	Free style filter string.	string	Maximum length: 1023	
filter-type	Include/exclude logs that match the filter.	option	-	include
	Option	Description		
	<i>include</i>	Include logs that match the filter.		
	<i>exclude</i>	Exclude logs that match the filter.		

config log fortianalyzer override-filter

Override filters for FortiAnalyzer.

```

config log fortianalyzer override-filter
    Description: Override filters for FortiAnalyzer.
    set severity [emergency|alert|...]
    set forward-traffic [enable|disable]
    set local-traffic [enable|disable]
    set multicast-traffic [enable|disable]
    set sniffer-traffic [enable|disable]
    set ztna-traffic [enable|disable]
    set http-transaction [enable|disable]
    set anomaly [enable|disable]
    set voip [enable|disable]
    set dlp-archive [enable|disable]
    config free-style
        Description: Free style filters.
        edit <id>
            set category [traffic|event|...]
            set filter {string}
            set filter-type [include|exclude]
        next
    next

```

```
end
end
```

config log fortianalyzer override-filter

Parameter	Description	Type	Size	Default
severity	Lowest severity level to log.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		
forward-traffic	Enable/disable forward traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable multicast traffic logging.		
	<i>disable</i>	Disable multicast traffic logging.		
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable sniffer traffic logging.		
	<i>disable</i>	Disable sniffer traffic logging.		
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		
dlp-archive	Enable/disable DLP archive logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable DLP archive logging.		
	<i>disable</i>	Disable DLP archive logging.		

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option Description			
	traffic	Traffic log.		
	event	Event log.		
	virus	Antivirus log.		
	webfilter	Web filter log.		
	attack	Attack log.		
	spam	Antispam log.		
	anomaly	Anomaly log.		
	voip	VoIP log.		
	dlp	DLP log.		
	app-ctrl	Application control log.		
	waf	Web application firewall log.		
	dns	DNS detail log.		
	ssh	SSH log.		
	ssl	SSL log.		
	file-filter	File filter log.		
	icap	ICAP log.		
filter	Free style filter string.	string	Maximum length: 1023	
filter-type	Include/exclude logs that match the filter.	option	-	include
	Option Description			
	include	Include logs that match the filter.		
	exclude	Exclude logs that match the filter.		

config log fortianalyzer override-setting

Override FortiAnalyzer settings.

```
config log fortianalyzer override-setting
  Description: Override FortiAnalyzer settings.
  set use-management-vdom [enable|disable]
  set status [enable|disable]
  set ips-archive [enable|disable]
  set server {string}
  set alt-server {string}
  set fallback-to-primary [enable|disable]
  set certificate-verification [enable|disable]
  set serial <name1>, <name2>, ...
  set server-cert-ca {string}
  set preshared-key {string}
  set access-config [enable|disable]
  set hmac-algorithm [sha256|sha1]
  set enc-algorithm [high-medium|high|...]
  set ssl-min-proto-version [default|SSLv3|...]
  set conn-timeout {integer}
  set monitor-keepalive-period {integer}
  set monitor-failure-retry-period {integer}
  set certificate {string}
  set source-ip {string}
  set upload-option [store-and-upload|realtime|...]
  set upload-interval [daily|weekly|...]
  set upload-day {user}
  set upload-time {user}
  set reliable [enable|disable]
  set priority [default|low]
  set max-log-rate {integer}
  set interface-select-method [auto|specify]
  set interface {string}
end
```

config log fortianalyzer override-setting

Parameter	Description	Type	Size	Default
use-management-vdom	Enable/disable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.		

Parameter	Description	Type	Size	Default
	Option Description			
	<i>disable</i>	Disable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.		
status	Enable/disable logging to FortiAnalyzer.	option	-	disable
	Option Description			
	<i>enable</i>	Enable logging to FortiAnalyzer.		
	<i>disable</i>	Disable logging to FortiAnalyzer.		
ips-archive	Enable/disable IPS packet archive logging.	option	-	enable
	Option Description			
	<i>enable</i>	Enable IPS packet archive logging.		
	<i>disable</i>	Disable IPS packet archive logging.		
server	The remote FortiAnalyzer.	string	Maximum length: 127	
alt-server	Alternate FortiAnalyzer.	string	Maximum length: 127	
fallback-to-primary	Enable/disable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.	option	-	enable
	Option Description			
	<i>enable</i>	Enable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.		
	<i>disable</i>	Disable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.		
certificate-verification	Enable/disable identity verification of FortiAnalyzer by use of certificate.	option	-	enable
	Option Description			
	<i>enable</i>	Enable identity verification of FortiAnalyzer by use of certificate.		
	<i>disable</i>	Disable identity verification of FortiAnalyzer by use of certificate.		
serial <name>	Serial numbers of the FortiAnalyzer. Serial Number.	string	Maximum length: 79	

Parameter	Description	Type	Size	Default														
server-cert-ca	Mandatory CA on FortiGate in certificate chain of server.	string	Maximum length: 79															
preshared-key	Preshared-key used for auto-authorization on FortiAnalyzer.	string	Maximum length: 63															
access-config	Enable/disable FortiAnalyzer access to configuration and data.	option	-	enable														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable FortiAnalyzer access to configuration and data.</td></tr><tr><td><i>disable</i></td><td>Disable FortiAnalyzer access to configuration and data.</td></tr></table>	Option	Description	<i>enable</i>	Enable FortiAnalyzer access to configuration and data.	<i>disable</i>	Disable FortiAnalyzer access to configuration and data.											
Option	Description																	
<i>enable</i>	Enable FortiAnalyzer access to configuration and data.																	
<i>disable</i>	Disable FortiAnalyzer access to configuration and data.																	
hmac-algorithm	OFTP login hash algorithm.	option	-	sha256														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>sha256</i></td><td>Use SHA256 as HMAC algorithm.</td></tr><tr><td><i>sha1</i></td><td>Step down to SHA1 as the HMAC algorithm.</td></tr></table>	Option	Description	<i>sha256</i>	Use SHA256 as HMAC algorithm.	<i>sha1</i>	Step down to SHA1 as the HMAC algorithm.											
Option	Description																	
<i>sha256</i>	Use SHA256 as HMAC algorithm.																	
<i>sha1</i>	Step down to SHA1 as the HMAC algorithm.																	
enc-algorithm	Configure the level of SSL protection for secure communication with FortiAnalyzer.	option	-	high														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>high-medium</i></td><td>Encrypt logs using high and medium encryption algorithms.</td></tr><tr><td><i>high</i></td><td>Encrypt logs using high encryption algorithms.</td></tr><tr><td><i>low</i></td><td>Encrypt logs using all encryption algorithms.</td></tr></table>	Option	Description	<i>high-medium</i>	Encrypt logs using high and medium encryption algorithms.	<i>high</i>	Encrypt logs using high encryption algorithms.	<i>low</i>	Encrypt logs using all encryption algorithms.									
Option	Description																	
<i>high-medium</i>	Encrypt logs using high and medium encryption algorithms.																	
<i>high</i>	Encrypt logs using high encryption algorithms.																	
<i>low</i>	Encrypt logs using all encryption algorithms.																	
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Follow system global setting.</td></tr><tr><td><i>SSLv3</i></td><td>SSLv3.</td></tr><tr><td><i>TLSv1</i></td><td>TLSv1.</td></tr><tr><td><i>TLSv1-1</i></td><td>TLSv1.1.</td></tr><tr><td><i>TLSv1-2</i></td><td>TLSv1.2.</td></tr><tr><td><i>TLSv1-3</i></td><td>TLSv1.3.</td></tr></table>	Option	Description	<i>default</i>	Follow system global setting.	<i>SSLv3</i>	SSLv3.	<i>TLSv1</i>	TLSv1.	<i>TLSv1-1</i>	TLSv1.1.	<i>TLSv1-2</i>	TLSv1.2.	<i>TLSv1-3</i>	TLSv1.3.			
Option	Description																	
<i>default</i>	Follow system global setting.																	
<i>SSLv3</i>	SSLv3.																	
<i>TLSv1</i>	TLSv1.																	
<i>TLSv1-1</i>	TLSv1.1.																	
<i>TLSv1-2</i>	TLSv1.2.																	
<i>TLSv1-3</i>	TLSv1.3.																	

Parameter	Description	Type	Size	Default										
conn-timeout	FortiAnalyzer connection time-out in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 3600	10										
monitor-keepalive-period	Time between OFTP keepalives in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 120	5										
monitor-failure-retry-period	Time between FortiAnalyzer connection retries in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 86400	5										
certificate	Certificate used to communicate with FortiAnalyzer.	string	Maximum length: 35											
source-ip	Source IPv4 or IPv6 address used to communicate with FortiAnalyzer.	string	Maximum length: 63											
upload-option	Enable/disable logging to hard disk and then uploading to FortiAnalyzer.	option	-	5-minute										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>store-and-upload</td><td>Log to hard disk and then upload to FortiAnalyzer.</td></tr><tr><td>realtime</td><td>Log directly to FortiAnalyzer in real time.</td></tr><tr><td>1-minute</td><td>Log directly to FortiAnalyzer at least every 1 minute.</td></tr><tr><td>5-minute</td><td>Log directly to FortiAnalyzer at least every 5 minutes.</td></tr></table>				Option	Description	store-and-upload	Log to hard disk and then upload to FortiAnalyzer.	realtime	Log directly to FortiAnalyzer in real time.	1-minute	Log directly to FortiAnalyzer at least every 1 minute.	5-minute	Log directly to FortiAnalyzer at least every 5 minutes.
Option	Description													
store-and-upload	Log to hard disk and then upload to FortiAnalyzer.													
realtime	Log directly to FortiAnalyzer in real time.													
1-minute	Log directly to FortiAnalyzer at least every 1 minute.													
5-minute	Log directly to FortiAnalyzer at least every 5 minutes.													
upload-interval	Frequency to upload log files to FortiAnalyzer.	option	-	daily										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>daily</td><td>Upload log files to FortiAnalyzer once a day.</td></tr><tr><td>weekly</td><td>Upload log files to FortiAnalyzer once a week.</td></tr><tr><td>monthly</td><td>Upload log files to FortiAnalyzer once a month.</td></tr></table>				Option	Description	daily	Upload log files to FortiAnalyzer once a day.	weekly	Upload log files to FortiAnalyzer once a week.	monthly	Upload log files to FortiAnalyzer once a month.		
Option	Description													
daily	Upload log files to FortiAnalyzer once a day.													
weekly	Upload log files to FortiAnalyzer once a week.													
monthly	Upload log files to FortiAnalyzer once a month.													
upload-day	Day of week (month) to upload logs.	user	Not Specified											
upload-time	Time to upload logs (hh:mm).	user	Not Specified											

Parameter	Description	Type	Size	Default
reliable	Enable/disable reliable logging to FortiAnalyzer.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable reliable logging to FortiAnalyzer.		
	<i>disable</i>	Disable reliable logging to FortiAnalyzer.		
priority	Set log transmission priority.	option	-	default
	Option	Description		
	<i>default</i>	Set FortiAnalyzer log transmission priority to default.		
	<i>low</i>	Set FortiAnalyzer log transmission priority to low.		
max-log-rate	FortiAnalyzer maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto
	Option	Description		
	<i>auto</i>	Set outgoing interface automatically.		
	<i>specify</i>	Set outgoing interface manually.		
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	

config log fortianalyzer setting

Global FortiAnalyzer settings.

```

config log fortianalyzer setting
  Description: Global FortiAnalyzer settings.
  set status [enable|disable]
  set ips-archive [enable|disable]
  set server {string}
  set alt-server {string}
  set fallback-to-primary [enable|disable]
  set certificate-verification [enable|disable]
  set serial <name1>, <name2>, ...
  set server-cert-ca {string}
  set preshared-key {string}

```

```

set access-config [enable|disable]
set hmac-algorithm [sha256|sha1]
set enc-algorithm [high-medium|high|...]
set ssl-min-protocol-version [default|SSLv3|...]
set conn-timeout {integer}
set monitor-keepalive-period {integer}
set monitor-failure-retry-period {integer}
set certificate {string}
set source-ip {string}
set upload-option [store-and-upload|realtime|...]
set upload-interval [daily|weekly|...]
set upload-day {user}
set upload-time {user}
set reliable [enable|disable]
set priority [default|low]
set max-log-rate {integer}
set interface-select-method [auto|specify]
set interface {string}
end

```

config log fortianalyzer setting

Parameter	Description	Type	Size	Default
status	Enable/disable logging to FortiAnalyzer.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable logging to FortiAnalyzer.		
	<i>disable</i>	Disable logging to FortiAnalyzer.		
ips-archive	Enable/disable IPS packet archive logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable IPS packet archive logging.		
	<i>disable</i>	Disable IPS packet archive logging.		
server	The remote FortiAnalyzer.	string	Maximum length: 127	
alt-server	Alternate FortiAnalyzer.	string	Maximum length: 127	
fallback-to-primary	Enable/disable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.		
	<i>disable</i>	Disable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.		
certificate-verification	Enable/disable identity verification of FortiAnalyzer by use of certificate.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable identity verification of FortiAnalyzer by use of certificate.		
	<i>disable</i>	Disable identity verification of FortiAnalyzer by use of certificate.		
serial <name>	Serial numbers of the FortiAnalyzer. Serial Number.	string	Maximum length: 79	
server-cert-ca	Mandatory CA on FortiGate in certificate chain of server.	string	Maximum length: 79	
preshared-key	Preshared-key used for auto-authorization on FortiAnalyzer.	string	Maximum length: 63	
access-config	Enable/disable FortiAnalyzer access to configuration and data.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable FortiAnalyzer access to configuration and data.		
	<i>disable</i>	Disable FortiAnalyzer access to configuration and data.		
hmac-algorithm	OFTP login hash algorithm.	option	-	sha256
	Option	Description		
	<i>sha256</i>	Use SHA 256 as HMAC algorithm.		
	<i>sha1</i>	Step down to SHA1 as the HMAC algorithm.		
enc-algorithm	Configure the level of SSL protection for secure communication with FortiAnalyzer.	option	-	high
	Option	Description		
	<i>high-medium</i>	Encrypt logs using high and medium encryption algorithms.		
	<i>high</i>	Encrypt logs using high encryption algorithms.		

Parameter	Description	Type	Size	Default														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>low</i></td><td>Encrypt logs using all encryption algorithms.</td></tr></table>	Option	Description	<i>low</i>	Encrypt logs using all encryption algorithms.													
	Option	Description																
<i>low</i>	Encrypt logs using all encryption algorithms.																	
ssl-min-proto-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Follow system global setting.</td></tr><tr><td><i>SSLv3</i></td><td>SSLv3.</td></tr><tr><td><i>TLSv1</i></td><td>TLSv1.</td></tr><tr><td><i>TLSv1-1</i></td><td>TLSv1.1.</td></tr><tr><td><i>TLSv1-2</i></td><td>TLSv1.2.</td></tr><tr><td><i>TLSv1-3</i></td><td>TLSv1.3.</td></tr></table>	Option	Description	<i>default</i>	Follow system global setting.	<i>SSLv3</i>	SSLv3.	<i>TLSv1</i>	TLSv1.	<i>TLSv1-1</i>	TLSv1.1.	<i>TLSv1-2</i>	TLSv1.2.	<i>TLSv1-3</i>	TLSv1.3.			
	Option	Description																
	<i>default</i>	Follow system global setting.																
	<i>SSLv3</i>	SSLv3.																
	<i>TLSv1</i>	TLSv1.																
	<i>TLSv1-1</i>	TLSv1.1.																
	<i>TLSv1-2</i>	TLSv1.2.																
<i>TLSv1-3</i>	TLSv1.3.																	
conn-timeout	FortiAnalyzer connection time-out in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 3600	10														
monitor-keepalive-period	Time between OFTP keepalives in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 120	5														
monitor-failure-retry-period	Time between FortiAnalyzer connection retries in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 86400	5														
certificate	Certificate used to communicate with FortiAnalyzer.	string	Maximum length: 35															
source-ip	Source IPv4 or IPv6 address used to communicate with FortiAnalyzer.	string	Maximum length: 63															
upload-option	Enable/disable logging to hard disk and then uploading to FortiAnalyzer.	option	-	5-minute														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>store-and-upload</i></td><td>Log to hard disk and then upload to FortiAnalyzer.</td></tr></table>	Option	Description	<i>store-and-upload</i>	Log to hard disk and then upload to FortiAnalyzer.													
	Option	Description																
<i>store-and-upload</i>	Log to hard disk and then upload to FortiAnalyzer.																	

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>realtime</i>	Log directly to FortiAnalyzer in real time.		
	<i>1-minute</i>	Log directly to FortiAnalyzer at least every 1 minute.		
	<i>5-minute</i>	Log directly to FortiAnalyzer at least every 5 minutes.		
upload-interval	Frequency to upload log files to FortiAnalyzer.	option	-	daily
	Option	Description		
	<i>daily</i>	Upload log files to FortiAnalyzer once a day.		
	<i>weekly</i>	Upload log files to FortiAnalyzer once a week.		
	<i>monthly</i>	Upload log files to FortiAnalyzer once a month.		
upload-day	Day of week (month) to upload logs.	user	Not Specified	
upload-time	Time to upload logs (hh:mm).	user	Not Specified	
reliable	Enable/disable reliable logging to FortiAnalyzer.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable reliable logging to FortiAnalyzer.		
	<i>disable</i>	Disable reliable logging to FortiAnalyzer.		
priority	Set log transmission priority.	option	-	default
	Option	Description		
	<i>default</i>	Set FortiAnalyzer log transmission priority to default.		
	<i>low</i>	Set FortiAnalyzer log transmission priority to low.		
max-log-rate	FortiAnalyzer maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>auto</i>	Set outgoing interface automatically.		
	<i>specify</i>	Set outgoing interface manually.		
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	

config log fortianalyzer2 filter

Filters for FortiAnalyzer.

```

config log fortianalyzer2 filter
  Description: Filters for FortiAnalyzer.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]
  set sniffer-traffic [enable|disable]
  set ztna-traffic [enable|disable]
  set http-transaction [enable|disable]
  set anomaly [enable|disable]
  set voip [enable|disable]
  set dlp-archive [enable|disable]
  config free-style
    Description: Free style filters.
    edit <id>
      set category [traffic|event|...]
      set filter {string}
      set filter-type [include|exclude]
    next
  end
end

```

config log fortianalyzer2 filter

Parameter	Description	Type	Size	Default
severity	Log every message above and including this severity level.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		

Parameter	Description	Type	Size	Default																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>alert</i></td><td>Alert level.</td></tr><tr><td><i>critical</i></td><td>Critical level.</td></tr><tr><td><i>error</i></td><td>Error level.</td></tr><tr><td><i>warning</i></td><td>Warning level.</td></tr><tr><td><i>notification</i></td><td>Notification level.</td></tr><tr><td><i>information</i></td><td>Information level.</td></tr><tr><td><i>debug</i></td><td>Debug level.</td></tr></table>	Option	Description	<i>alert</i>	Alert level.	<i>critical</i>	Critical level.	<i>error</i>	Error level.	<i>warning</i>	Warning level.	<i>notification</i>	Notification level.	<i>information</i>	Information level.	<i>debug</i>	Debug level.			
	Option	Description																		
	<i>alert</i>	Alert level.																		
	<i>critical</i>	Critical level.																		
	<i>error</i>	Error level.																		
	<i>warning</i>	Warning level.																		
	<i>notification</i>	Notification level.																		
	<i>information</i>	Information level.																		
<i>debug</i>	Debug level.																			
forward-traffic	Enable/disable forward traffic logging.	option	-	enable																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable forward traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable forward traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable forward traffic logging.	<i>disable</i>	Disable forward traffic logging.													
	Option	Description																		
	<i>enable</i>	Enable forward traffic logging.																		
<i>disable</i>	Disable forward traffic logging.																			
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable local in or out traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable local in or out traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable local in or out traffic logging.	<i>disable</i>	Disable local in or out traffic logging.													
	Option	Description																		
	<i>enable</i>	Enable local in or out traffic logging.																		
<i>disable</i>	Disable local in or out traffic logging.																			
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable multicast traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable multicast traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable multicast traffic logging.	<i>disable</i>	Disable multicast traffic logging.													
	Option	Description																		
	<i>enable</i>	Enable multicast traffic logging.																		
<i>disable</i>	Disable multicast traffic logging.																			
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable sniffer traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable sniffer traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable sniffer traffic logging.	<i>disable</i>	Disable sniffer traffic logging.													
	Option	Description																		
	<i>enable</i>	Enable sniffer traffic logging.																		
<i>disable</i>	Disable sniffer traffic logging.																			
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable																

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		
dlp-archive	Enable/disable DLP archive logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable DLP archive logging.		
	<i>disable</i>	Disable DLP archive logging.		

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic

Parameter	Description	Type	Size	Default																																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>traffic</i></td><td>Traffic log.</td></tr><tr><td><i>event</i></td><td>Event log.</td></tr><tr><td><i>virus</i></td><td>Antivirus log.</td></tr><tr><td><i>webfilter</i></td><td>Web filter log.</td></tr><tr><td><i>attack</i></td><td>Attack log.</td></tr><tr><td><i>spam</i></td><td>Antispam log.</td></tr><tr><td><i>anomaly</i></td><td>Anomaly log.</td></tr><tr><td><i>voip</i></td><td>VoIP log.</td></tr><tr><td><i>dlp</i></td><td>DLP log.</td></tr><tr><td><i>app-ctrl</i></td><td>Application control log.</td></tr><tr><td><i>waf</i></td><td>Web application firewall log.</td></tr><tr><td><i>dns</i></td><td>DNS detail log.</td></tr><tr><td><i>ssh</i></td><td>SSH log.</td></tr><tr><td><i>ssl</i></td><td>SSL log.</td></tr><tr><td><i>file-filter</i></td><td>File filter log.</td></tr><tr><td><i>icap</i></td><td>ICAP log.</td></tr></table>	Option	Description	<i>traffic</i>	Traffic log.	<i>event</i>	Event log.	<i>virus</i>	Antivirus log.	<i>webfilter</i>	Web filter log.	<i>attack</i>	Attack log.	<i>spam</i>	Antispam log.	<i>anomaly</i>	Anomaly log.	<i>voip</i>	VoIP log.	<i>dlp</i>	DLP log.	<i>app-ctrl</i>	Application control log.	<i>waf</i>	Web application firewall log.	<i>dns</i>	DNS detail log.	<i>ssh</i>	SSH log.	<i>ssl</i>	SSL log.	<i>file-filter</i>	File filter log.	<i>icap</i>	ICAP log.			
	Option	Description																																				
	<i>traffic</i>	Traffic log.																																				
	<i>event</i>	Event log.																																				
	<i>virus</i>	Antivirus log.																																				
	<i>webfilter</i>	Web filter log.																																				
	<i>attack</i>	Attack log.																																				
	<i>spam</i>	Antispam log.																																				
	<i>anomaly</i>	Anomaly log.																																				
	<i>voip</i>	VoIP log.																																				
	<i>dlp</i>	DLP log.																																				
	<i>app-ctrl</i>	Application control log.																																				
	<i>waf</i>	Web application firewall log.																																				
	<i>dns</i>	DNS detail log.																																				
	<i>ssh</i>	SSH log.																																				
	<i>ssl</i>	SSL log.																																				
	<i>file-filter</i>	File filter log.																																				
<i>icap</i>	ICAP log.																																					
filter	Free style filter string.	string	Maximum length: 1023																																			
filter-type	Include/exclude logs that match the filter.	option	-	include																																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>include</i></td><td>Include logs that match the filter.</td></tr><tr><td><i>exclude</i></td><td>Exclude logs that match the filter.</td></tr></table>	Option	Description	<i>include</i>	Include logs that match the filter.	<i>exclude</i>	Exclude logs that match the filter.																															
	Option	Description																																				
	<i>include</i>	Include logs that match the filter.																																				
<i>exclude</i>	Exclude logs that match the filter.																																					

config log fortianalyzer2 override-filter

Override filters for FortiAnalyzer.

```

config log fortianalyzer2 override-filter
  Description: Override filters for FortiAnalyzer.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]

```

```

set sniffer-traffic [enable|disable]
set ztna-traffic [enable|disable]
set http-transaction [enable|disable]
set anomaly [enable|disable]
set voip [enable|disable]
set dlp-archive [enable|disable]
config free-style
    Description: Free style filters.
    edit <id>
        set category [traffic|event|...]
        set filter {string}
        set filter-type [include|exclude]
    next
end
end

```

config log fortianalyzer2 override-filter

Parameter	Description	Type	Size	Default
severity	Log every message above and including this severity level.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		
forward-traffic	Enable/disable forward traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable multicast traffic logging.		
	<i>disable</i>	Disable multicast traffic logging.		
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable sniffer traffic logging.		
	<i>disable</i>	Disable sniffer traffic logging.		
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		
dlp-archive	Enable/disable DLP archive logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable DLP archive logging.		
	<i>disable</i>	Disable DLP archive logging.		

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	<i>traffic</i>	Traffic log.		
	<i>event</i>	Event log.		
	<i>virus</i>	Antivirus log.		
	<i>webfilter</i>	Web filter log.		
	<i>attack</i>	Attack log.		
	<i>spam</i>	Antispam log.		
	<i>anomaly</i>	Anomaly log.		
	<i>voip</i>	VoIP log.		
	<i>dlp</i>	DLP log.		
	<i>app-ctrl</i>	Application control log.		
	<i>waf</i>	Web application firewall log.		
	<i>dns</i>	DNS detail log.		
	<i>ssh</i>	SSH log.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>ssl</i>	SSL log.		
	<i>file-filter</i>	File filter log.		
	<i>icap</i>	ICAP log.		
filter	Free style filter string.	string	Maximum length: 1023	
filter-type	Include/exclude logs that match the filter.	option	-	include
	Option	Description		
	<i>include</i>	Include logs that match the filter.		
	<i>exclude</i>	Exclude logs that match the filter.		

config log fortianalyzer2 override-setting

Override FortiAnalyzer settings.

```
config log fortianalyzer2 override-setting
  Description: Override FortiAnalyzer settings.
  set use-management-vdom [enable|disable]
  set status [enable|disable]
  set ips-archive [enable|disable]
  set server {string}
  set alt-server {string}
  set fallback-to-primary [enable|disable]
  set certificate-verification [enable|disable]
  set serial <name1>, <name2>, ...
  set server-cert-ca {string}
  set preshared-key {string}
  set access-config [enable|disable]
  set hmac-algorithm [sha256|sha1]
  set enc-algorithm [high-medium|high|...]
  set ssl-min-proto-version [default|SSLv3|...]
  set conn-timeout {integer}
  set monitor-keepalive-period {integer}
  set monitor-failure-retry-period {integer}
  set certificate {string}
  set source-ip {string}
  set upload-option [store-and-upload|realtime|...]
  set upload-interval [daily|weekly|...]
  set upload-day {user}
  set upload-time {user}
  set reliable [enable|disable]
  set priority [default|low]
```

```

set max-log-rate {integer}
set interface-select-method [auto|specify]
set interface {string}
end

```

config log fortianalyzer2 override-setting

Parameter	Description	Type	Size	Default						
use-management-vdom	Enable/disable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.</td></tr><tr><td><i>disable</i></td><td>Disable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.</td></tr></table>	Option	Description	<i>enable</i>	Enable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.	<i>disable</i>	Disable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.			
Option	Description									
<i>enable</i>	Enable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.									
<i>disable</i>	Disable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.									
status	Enable/disable logging to FortiAnalyzer.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable logging to FortiAnalyzer.</td></tr><tr><td><i>disable</i></td><td>Disable logging to FortiAnalyzer.</td></tr></table>	Option	Description	<i>enable</i>	Enable logging to FortiAnalyzer.	<i>disable</i>	Disable logging to FortiAnalyzer.			
Option	Description									
<i>enable</i>	Enable logging to FortiAnalyzer.									
<i>disable</i>	Disable logging to FortiAnalyzer.									
ips-archive	Enable/disable IPS packet archive logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable IPS packet archive logging.</td></tr><tr><td><i>disable</i></td><td>Disable IPS packet archive logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable IPS packet archive logging.	<i>disable</i>	Disable IPS packet archive logging.			
Option	Description									
<i>enable</i>	Enable IPS packet archive logging.									
<i>disable</i>	Disable IPS packet archive logging.									
server	The remote FortiAnalyzer.	string	Maximum length: 127							
alt-server	Alternate FortiAnalyzer.	string	Maximum length: 127							
fallback-to-primary	Enable/disable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.</td></tr></table>	Option	Description	<i>enable</i>	Enable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.					
Option	Description									
<i>enable</i>	Enable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.									

Parameter	Description	Type	Size	Default								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.</td></tr></table>	Option	Description	<i>disable</i>	Disable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.							
	Option	Description										
	<i>disable</i>	Disable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.										
certificate-verification	Enable/disable identity verification of FortiAnalyzer by use of certificate.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable identity verification of FortiAnalyzer by use of certificate.</td></tr><tr><td><i>disable</i></td><td>Disable identity verification of FortiAnalyzer by use of certificate.</td></tr></table>	Option	Description	<i>enable</i>	Enable identity verification of FortiAnalyzer by use of certificate.	<i>disable</i>	Disable identity verification of FortiAnalyzer by use of certificate.					
	Option	Description										
	<i>enable</i>	Enable identity verification of FortiAnalyzer by use of certificate.										
<i>disable</i>	Disable identity verification of FortiAnalyzer by use of certificate.											
serial <name>	Serial numbers of the FortiAnalyzer. Serial Number.	string	Maximum length: 79									
server-cert-ca	Mandatory CA on FortiGate in certificate chain of server.	string	Maximum length: 79									
preshared-key	Preshared-key used for auto-authorization on FortiAnalyzer.	string	Maximum length: 63									
access-config	Enable/disable FortiAnalyzer access to configuration and data.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable FortiAnalyzer access to configuration and data.</td></tr><tr><td><i>disable</i></td><td>Disable FortiAnalyzer access to configuration and data.</td></tr></table>	Option	Description	<i>enable</i>	Enable FortiAnalyzer access to configuration and data.	<i>disable</i>	Disable FortiAnalyzer access to configuration and data.					
	Option	Description										
	<i>enable</i>	Enable FortiAnalyzer access to configuration and data.										
<i>disable</i>	Disable FortiAnalyzer access to configuration and data.											
hmac-algorithm	OFTP login hash algorithm.	option	-	sha256								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>sha256</i></td><td>Use SHA256 as HMAC algorithm.</td></tr><tr><td><i>sha1</i></td><td>Step down to SHA1 as the HMAC algorithm.</td></tr></table>	Option	Description	<i>sha256</i>	Use SHA256 as HMAC algorithm.	<i>sha1</i>	Step down to SHA1 as the HMAC algorithm.					
	Option	Description										
	<i>sha256</i>	Use SHA256 as HMAC algorithm.										
<i>sha1</i>	Step down to SHA1 as the HMAC algorithm.											
enc-algorithm	Configure the level of SSL protection for secure communication with FortiAnalyzer.	option	-	high								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>high-medium</i></td><td>Encrypt logs using high and medium encryption algorithms.</td></tr><tr><td><i>high</i></td><td>Encrypt logs using high encryption algorithms.</td></tr><tr><td><i>low</i></td><td>Encrypt logs using all encryption algorithms.</td></tr></table>	Option	Description	<i>high-medium</i>	Encrypt logs using high and medium encryption algorithms.	<i>high</i>	Encrypt logs using high encryption algorithms.	<i>low</i>	Encrypt logs using all encryption algorithms.			
	Option	Description										
	<i>high-medium</i>	Encrypt logs using high and medium encryption algorithms.										
<i>high</i>	Encrypt logs using high encryption algorithms.											
<i>low</i>	Encrypt logs using all encryption algorithms.											

Parameter	Description	Type	Size	Default														
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>default</td><td>Follow system global setting.</td></tr><tr><td>SSLv3</td><td>SSLv3.</td></tr><tr><td>TLSv1</td><td>TLSv1.</td></tr><tr><td>TLSv1-1</td><td>TLSv1.1.</td></tr><tr><td>TLSv1-2</td><td>TLSv1.2.</td></tr><tr><td>TLSv1-3</td><td>TLSv1.3.</td></tr></table>	Option	Description	default	Follow system global setting.	SSLv3	SSLv3.	TLSv1	TLSv1.	TLSv1-1	TLSv1.1.	TLSv1-2	TLSv1.2.	TLSv1-3	TLSv1.3.			
	Option	Description																
	default	Follow system global setting.																
	SSLv3	SSLv3.																
	TLSv1	TLSv1.																
	TLSv1-1	TLSv1.1.																
	TLSv1-2	TLSv1.2.																
TLSv1-3	TLSv1.3.																	
conn-timeout	FortiAnalyzer connection time-out in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 3600	10														
monitor-keepalive-period	Time between OFTP keepalives in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 120	5														
monitor-failure-retry-period	Time between FortiAnalyzer connection retries in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 86400	5														
certificate	Certificate used to communicate with FortiAnalyzer.	string	Maximum length: 35															
source-ip	Source IPv4 or IPv6 address used to communicate with FortiAnalyzer.	string	Maximum length: 63															
upload-option	Enable/disable logging to hard disk and then uploading to FortiAnalyzer.	option	-	5-minute														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>store-and-upload</td><td>Log to hard disk and then upload to FortiAnalyzer.</td></tr><tr><td>realtime</td><td>Log directly to FortiAnalyzer in real time.</td></tr><tr><td>1-minute</td><td>Log directly to FortiAnalyzer at least every 1 minute.</td></tr><tr><td>5-minute</td><td>Log directly to FortiAnalyzer at least every 5 minutes.</td></tr></table>	Option	Description	store-and-upload	Log to hard disk and then upload to FortiAnalyzer.	realtime	Log directly to FortiAnalyzer in real time.	1-minute	Log directly to FortiAnalyzer at least every 1 minute.	5-minute	Log directly to FortiAnalyzer at least every 5 minutes.							
	Option	Description																
	store-and-upload	Log to hard disk and then upload to FortiAnalyzer.																
	realtime	Log directly to FortiAnalyzer in real time.																
	1-minute	Log directly to FortiAnalyzer at least every 1 minute.																
5-minute	Log directly to FortiAnalyzer at least every 5 minutes.																	

Parameter	Description	Type	Size	Default								
upload-interval	Frequency to upload log files to FortiAnalyzer.	option	-	daily								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>daily</i></td><td>Upload log files to FortiAnalyzer once a day.</td></tr><tr><td><i>weekly</i></td><td>Upload log files to FortiAnalyzer once a week.</td></tr><tr><td><i>monthly</i></td><td>Upload log files to FortiAnalyzer once a month.</td></tr></table>	Option	Description	<i>daily</i>	Upload log files to FortiAnalyzer once a day.	<i>weekly</i>	Upload log files to FortiAnalyzer once a week.	<i>monthly</i>	Upload log files to FortiAnalyzer once a month.			
Option	Description											
<i>daily</i>	Upload log files to FortiAnalyzer once a day.											
<i>weekly</i>	Upload log files to FortiAnalyzer once a week.											
<i>monthly</i>	Upload log files to FortiAnalyzer once a month.											
upload-day	Day of week (month) to upload logs.	user	Not Specified									
upload-time	Time to upload logs (hh:mm).	user	Not Specified									
reliable	Enable/disable reliable logging to FortiAnalyzer.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable reliable logging to FortiAnalyzer.</td></tr><tr><td><i>disable</i></td><td>Disable reliable logging to FortiAnalyzer.</td></tr></table>	Option	Description	<i>enable</i>	Enable reliable logging to FortiAnalyzer.	<i>disable</i>	Disable reliable logging to FortiAnalyzer.					
Option	Description											
<i>enable</i>	Enable reliable logging to FortiAnalyzer.											
<i>disable</i>	Disable reliable logging to FortiAnalyzer.											
priority	Set log transmission priority.	option	-	default								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Set FortiAnalyzer log transmission priority to default.</td></tr><tr><td><i>low</i></td><td>Set FortiAnalyzer log transmission priority to low.</td></tr></table>	Option	Description	<i>default</i>	Set FortiAnalyzer log transmission priority to default.	<i>low</i>	Set FortiAnalyzer log transmission priority to low.					
Option	Description											
<i>default</i>	Set FortiAnalyzer log transmission priority to default.											
<i>low</i>	Set FortiAnalyzer log transmission priority to low.											
max-log-rate	FortiAnalyzer maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0								
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Set outgoing interface automatically.</td></tr><tr><td><i>specify</i></td><td>Set outgoing interface manually.</td></tr></table>	Option	Description	<i>auto</i>	Set outgoing interface automatically.	<i>specify</i>	Set outgoing interface manually.					
Option	Description											
<i>auto</i>	Set outgoing interface automatically.											
<i>specify</i>	Set outgoing interface manually.											
interface	Specify outgoing interface to reach server.	string	Maximum length: 15									

config log fortianalyzer2 setting

Global FortiAnalyzer settings.

```
config log fortianalyzer2 setting
  Description: Global FortiAnalyzer settings.
  set status [enable|disable]
  set ips-archive [enable|disable]
  set server {string}
  set alt-server {string}
  set fallback-to-primary [enable|disable]
  set certificate-verification [enable|disable]
  set serial <name1>, <name2>, ...
  set server-cert-ca {string}
  set preshared-key {string}
  set access-config [enable|disable]
  set hmac-algorithm [sha256|sha1]
  set enc-algorithm [high-medium|high|...]
  set ssl-min-proto-version [default|SSLv3|...]
  set conn-timeout {integer}
  set monitor-keepalive-period {integer}
  set monitor-failure-retry-period {integer}
  set certificate {string}
  set source-ip {string}
  set upload-option [store-and-upload|realtime|...]
  set upload-interval [daily|weekly|...]
  set upload-day {user}
  set upload-time {user}
  set reliable [enable|disable]
  set priority [default|low]
  set max-log-rate {integer}
  set interface-select-method [auto|specify]
  set interface {string}
end
```

config log fortianalyzer2 setting

Parameter	Description	Type	Size	Default
status	Enable/disable logging to FortiAnalyzer.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable logging to FortiAnalyzer.		
	<i>disable</i>	Disable logging to FortiAnalyzer.		
ips-archive	Enable/disable IPS packet archive logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable IPS packet archive logging.		
	<i>disable</i>	Disable IPS packet archive logging.		
server	The remote FortiAnalyzer.	string	Maximum length: 127	
alt-server	Alternate FortiAnalyzer.	string	Maximum length: 127	
fallback-to-primary	Enable/disable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.		
	<i>disable</i>	Disable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.		
certificate-verification	Enable/disable identity verification of FortiAnalyzer by use of certificate.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable identity verification of FortiAnalyzer by use of certificate.		
	<i>disable</i>	Disable identity verification of FortiAnalyzer by use of certificate.		
serial <name>	Serial numbers of the FortiAnalyzer. Serial Number.	string	Maximum length: 79	
server-cert-ca	Mandatory CA on FortiGate in certificate chain of server.	string	Maximum length: 79	
preshared-key	Preshared-key used for auto-authorization on FortiAnalyzer.	string	Maximum length: 63	
access-config	Enable/disable FortiAnalyzer access to configuration and data.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable FortiAnalyzer access to configuration and data.		
	<i>disable</i>	Disable FortiAnalyzer access to configuration and data.		
hmac-algorithm	OFTP login hash algorithm.	option	-	sha256

Parameter	Description	Type	Size	Default														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>sha256</td><td>Use SHA256 as HMAC algorithm.</td></tr><tr><td>sha1</td><td>Step down to SHA1 as the HMAC algorithm.</td></tr></table>	Option	Description	sha256	Use SHA256 as HMAC algorithm.	sha1	Step down to SHA1 as the HMAC algorithm.											
	Option	Description																
	sha256	Use SHA256 as HMAC algorithm.																
sha1	Step down to SHA1 as the HMAC algorithm.																	
enc-algorithm	Configure the level of SSL protection for secure communication with FortiAnalyzer.	option	-	high														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>high-medium</td><td>Encrypt logs using high and medium encryption algorithms.</td></tr><tr><td>high</td><td>Encrypt logs using high encryption algorithms.</td></tr><tr><td>low</td><td>Encrypt logs using all encryption algorithms.</td></tr></table>	Option	Description	high-medium	Encrypt logs using high and medium encryption algorithms.	high	Encrypt logs using high encryption algorithms.	low	Encrypt logs using all encryption algorithms.									
	Option	Description																
	high-medium	Encrypt logs using high and medium encryption algorithms.																
	high	Encrypt logs using high encryption algorithms.																
low	Encrypt logs using all encryption algorithms.																	
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>default</td><td>Follow system global setting.</td></tr><tr><td>SSLv3</td><td>SSLv3.</td></tr><tr><td>TLSv1</td><td>TLSv1.</td></tr><tr><td>TLSv1-1</td><td>TLSv1.1.</td></tr><tr><td>TLSv1-2</td><td>TLSv1.2.</td></tr><tr><td>TLSv1-3</td><td>TLSv1.3.</td></tr></table>	Option	Description	default	Follow system global setting.	SSLv3	SSLv3.	TLSv1	TLSv1.	TLSv1-1	TLSv1.1.	TLSv1-2	TLSv1.2.	TLSv1-3	TLSv1.3.			
	Option	Description																
	default	Follow system global setting.																
	SSLv3	SSLv3.																
	TLSv1	TLSv1.																
	TLSv1-1	TLSv1.1.																
	TLSv1-2	TLSv1.2.																
TLSv1-3	TLSv1.3.																	
conn-timeout	FortiAnalyzer connection time-out in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 3600	10														
monitor-keepalive-period	Time between OFTP keepalives in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 120	5														
monitor-failure-retry-period	Time between FortiAnalyzer connection retries in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 86400	5														

Parameter	Description	Type	Size	Default										
certificate	Certificate used to communicate with FortiAnalyzer.	string	Maximum length: 35											
source-ip	Source IPv4 or IPv6 address used to communicate with FortiAnalyzer.	string	Maximum length: 63											
upload-option	Enable/disable logging to hard disk and then uploading to FortiAnalyzer.	option	-	5-minute										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>store-and-upload</td><td>Log to hard disk and then upload to FortiAnalyzer.</td></tr><tr><td>realtime</td><td>Log directly to FortiAnalyzer in real time.</td></tr><tr><td>1-minute</td><td>Log directly to FortiAnalyzer at least every 1 minute.</td></tr><tr><td>5-minute</td><td>Log directly to FortiAnalyzer at least every 5 minutes.</td></tr></table>	Option	Description	store-and-upload	Log to hard disk and then upload to FortiAnalyzer.	realtime	Log directly to FortiAnalyzer in real time.	1-minute	Log directly to FortiAnalyzer at least every 1 minute.	5-minute	Log directly to FortiAnalyzer at least every 5 minutes.			
Option	Description													
store-and-upload	Log to hard disk and then upload to FortiAnalyzer.													
realtime	Log directly to FortiAnalyzer in real time.													
1-minute	Log directly to FortiAnalyzer at least every 1 minute.													
5-minute	Log directly to FortiAnalyzer at least every 5 minutes.													
upload-interval	Frequency to upload log files to FortiAnalyzer.	option	-	daily										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>daily</td><td>Upload log files to FortiAnalyzer once a day.</td></tr><tr><td>weekly</td><td>Upload log files to FortiAnalyzer once a week.</td></tr><tr><td>monthly</td><td>Upload log files to FortiAnalyzer once a month.</td></tr></table>	Option	Description	daily	Upload log files to FortiAnalyzer once a day.	weekly	Upload log files to FortiAnalyzer once a week.	monthly	Upload log files to FortiAnalyzer once a month.					
Option	Description													
daily	Upload log files to FortiAnalyzer once a day.													
weekly	Upload log files to FortiAnalyzer once a week.													
monthly	Upload log files to FortiAnalyzer once a month.													
upload-day	Day of week (month) to upload logs.	user	Not Specified											
upload-time	Time to upload logs (hh:mm).	user	Not Specified											
reliable	Enable/disable reliable logging to FortiAnalyzer.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable reliable logging to FortiAnalyzer.</td></tr><tr><td>disable</td><td>Disable reliable logging to FortiAnalyzer.</td></tr></table>	Option	Description	enable	Enable reliable logging to FortiAnalyzer.	disable	Disable reliable logging to FortiAnalyzer.							
Option	Description													
enable	Enable reliable logging to FortiAnalyzer.													
disable	Disable reliable logging to FortiAnalyzer.													
priority	Set log transmission priority.	option	-	default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>default</td><td>Set FortiAnalyzer log transmission priority to default.</td></tr><tr><td>low</td><td>Set FortiAnalyzer log transmission priority to low.</td></tr></table>	Option	Description	default	Set FortiAnalyzer log transmission priority to default.	low	Set FortiAnalyzer log transmission priority to low.							
Option	Description													
default	Set FortiAnalyzer log transmission priority to default.													
low	Set FortiAnalyzer log transmission priority to low.													

Parameter	Description	Type	Size	Default						
max-log-rate	FortiAnalyzer maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0						
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Set outgoing interface automatically.</td></tr><tr><td><i>specify</i></td><td>Set outgoing interface manually.</td></tr></table>				Option	Description	<i>auto</i>	Set outgoing interface automatically.	<i>specify</i>	Set outgoing interface manually.
Option	Description									
<i>auto</i>	Set outgoing interface automatically.									
<i>specify</i>	Set outgoing interface manually.									
interface	Specify outgoing interface to reach server.	string	Maximum length: 15							

config log fortianalyzer3 filter

Filters for FortiAnalyzer.

```

config log fortianalyzer3 filter
  Description: Filters for FortiAnalyzer.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]
  set sniffer-traffic [enable|disable]
  set ztna-traffic [enable|disable]
  set http-transaction [enable|disable]
  set anomaly [enable|disable]
  set voip [enable|disable]
  set dlp-archive [enable|disable]
  config free-style
    Description: Free style filters.
    edit <id>
      set category [traffic|event|...]
      set filter {string}
      set filter-type [include|exclude]
    next
  end
end
end

```

config log fortianalyzer3 filter

Parameter	Description	Type	Size	Default
severity	Lowest severity level to log.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		
forward-traffic	Enable/disable forward traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable multicast traffic logging.		
	<i>disable</i>	Disable multicast traffic logging.		
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable sniffer traffic logging.		
	<i>disable</i>	Disable sniffer traffic logging.		
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		
dlp-archive	Enable/disable DLP archive logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable DLP archive logging.		
	<i>disable</i>	Disable DLP archive logging.		

config free-style

Parameter	Description	Type	Size	Default																																		
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0																																		
category	Log category.	option	-	traffic																																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>traffic</td><td>Traffic log.</td></tr><tr><td>event</td><td>Event log.</td></tr><tr><td>virus</td><td>Antivirus log.</td></tr><tr><td>webfilter</td><td>Web filter log.</td></tr><tr><td>attack</td><td>Attack log.</td></tr><tr><td>spam</td><td>Antispam log.</td></tr><tr><td>anomaly</td><td>Anomaly log.</td></tr><tr><td>voip</td><td>VoIP log.</td></tr><tr><td>dlp</td><td>DLP log.</td></tr><tr><td>app-ctrl</td><td>Application control log.</td></tr><tr><td>waf</td><td>Web application firewall log.</td></tr><tr><td>dns</td><td>DNS detail log.</td></tr><tr><td>ssh</td><td>SSH log.</td></tr><tr><td>ssl</td><td>SSL log.</td></tr><tr><td>file-filter</td><td>File filter log.</td></tr><tr><td>icap</td><td>ICAP log.</td></tr></table>	Option	Description	traffic	Traffic log.	event	Event log.	virus	Antivirus log.	webfilter	Web filter log.	attack	Attack log.	spam	Antispam log.	anomaly	Anomaly log.	voip	VoIP log.	dlp	DLP log.	app-ctrl	Application control log.	waf	Web application firewall log.	dns	DNS detail log.	ssh	SSH log.	ssl	SSL log.	file-filter	File filter log.	icap	ICAP log.			
	Option	Description																																				
	traffic	Traffic log.																																				
	event	Event log.																																				
	virus	Antivirus log.																																				
	webfilter	Web filter log.																																				
	attack	Attack log.																																				
	spam	Antispam log.																																				
	anomaly	Anomaly log.																																				
	voip	VoIP log.																																				
	dlp	DLP log.																																				
	app-ctrl	Application control log.																																				
	waf	Web application firewall log.																																				
	dns	DNS detail log.																																				
	ssh	SSH log.																																				
	ssl	SSL log.																																				
	file-filter	File filter log.																																				
icap	ICAP log.																																					
filter	Free style filter string.	string	Maximum length: 1023																																			
filter-type	Include/exclude logs that match the filter.	option	-	include																																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>include</td><td>Include logs that match the filter.</td></tr><tr><td>exclude</td><td>Exclude logs that match the filter.</td></tr></table>	Option	Description	include	Include logs that match the filter.	exclude	Exclude logs that match the filter.																															
	Option	Description																																				
	include	Include logs that match the filter.																																				
exclude	Exclude logs that match the filter.																																					

config log fortianalyzer3 override-filter

Override filters for FortiAnalyzer.

```
config log fortianalyzer3 override-filter
  Description: Override filters for FortiAnalyzer.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]
  set sniffer-traffic [enable|disable]
  set ztna-traffic [enable|disable]
  set http-transaction [enable|disable]
  set anomaly [enable|disable]
  set voip [enable|disable]
  set dlp-archive [enable|disable]
  config free-style
    Description: Free style filters.
    edit <id>
      set category [traffic|event|...]
      set filter {string}
      set filter-type [include|exclude]
    next
  end
end
```

config log fortianalyzer3 override-filter

Parameter	Description	Type	Size	Default																		
severity	Lowest severity level to log.	option	-	information																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>emergency</i></td><td>Emergency level.</td></tr><tr><td><i>alert</i></td><td>Alert level.</td></tr><tr><td><i>critical</i></td><td>Critical level.</td></tr><tr><td><i>error</i></td><td>Error level.</td></tr><tr><td><i>warning</i></td><td>Warning level.</td></tr><tr><td><i>notification</i></td><td>Notification level.</td></tr><tr><td><i>information</i></td><td>Information level.</td></tr><tr><td><i>debug</i></td><td>Debug level.</td></tr></table>	Option	Description	<i>emergency</i>	Emergency level.	<i>alert</i>	Alert level.	<i>critical</i>	Critical level.	<i>error</i>	Error level.	<i>warning</i>	Warning level.	<i>notification</i>	Notification level.	<i>information</i>	Information level.	<i>debug</i>	Debug level.			
	Option	Description																				
	<i>emergency</i>	Emergency level.																				
	<i>alert</i>	Alert level.																				
	<i>critical</i>	Critical level.																				
	<i>error</i>	Error level.																				
	<i>warning</i>	Warning level.																				
	<i>notification</i>	Notification level.																				
	<i>information</i>	Information level.																				
<i>debug</i>	Debug level.																					
forward-traffic	Enable/disable forward traffic logging.	option	-	enable																		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable multicast traffic logging.		
	<i>disable</i>	Disable multicast traffic logging.		
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable sniffer traffic logging.		
	<i>disable</i>	Disable sniffer traffic logging.		
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		
dlp-archive	Enable/disable DLP archive logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable DLP archive logging.		
	<i>disable</i>	Disable DLP archive logging.		

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	<i>traffic</i>	Traffic log.		
	<i>event</i>	Event log.		
	<i>virus</i>	Antivirus log.		
	<i>webfilter</i>	Web filter log.		
	<i>attack</i>	Attack log.		
	<i>spam</i>	Antispam log.		
	<i>anomaly</i>	Anomaly log.		
	<i>voip</i>	VoIP log.		
	<i>dlp</i>	DLP log.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>app-ctrl</i>	Application control log.		
	<i>waf</i>	Web application firewall log.		
	<i>dns</i>	DNS detail log.		
	<i>ssh</i>	SSH log.		
	<i>ssl</i>	SSL log.		
	<i>file-filter</i>	File filter log.		
	<i>icap</i>	ICAP log.		
filter	Free style filter string.	string	Maximum length: 1023	
filter-type	Include/exclude logs that match the filter.	option	-	include
	Option	Description		
	<i>include</i>	Include logs that match the filter.		
	<i>exclude</i>	Exclude logs that match the filter.		

config log fortianalyzer3 override-setting

Override FortiAnalyzer settings.

```
config log fortianalyzer3 override-setting
  Description: Override FortiAnalyzer settings.
  set use-management-vdom [enable|disable]
  set status [enable|disable]
  set ips-archive [enable|disable]
  set server {string}
  set alt-server {string}
  set fallback-to-primary [enable|disable]
  set certificate-verification [enable|disable]
  set serial <name1>, <name2>, ...
  set server-cert-ca {string}
  set preshared-key {string}
  set access-config [enable|disable]
  set hmac-algorithm [sha256|sha1]
  set enc-algorithm [high-medium|high|...]
  set ssl-min-proto-version [default|SSLv3|...]
  set conn-timeout {integer}
  set monitor-keepalive-period {integer}
  set monitor-failure-retry-period {integer}
  set certificate {string}
```

```

set source-ip {string}
set upload-option [store-and-upload|realtime|...]
set upload-interval [daily|weekly|...]
set upload-day {user}
set upload-time {user}
set reliable [enable|disable]
set priority [default|low]
set max-log-rate {integer}
set interface-select-method [auto|specify]
set interface {string}
end

```

config log fortianalyzer3 override-setting

Parameter	Description	Type	Size	Default						
use-management-vdom	Enable/disable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.</td></tr><tr><td><i>disable</i></td><td>Disable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.</td></tr></table>	Option	Description	<i>enable</i>	Enable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.	<i>disable</i>	Disable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.			
Option	Description									
<i>enable</i>	Enable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.									
<i>disable</i>	Disable use of management VDOM IP address as source IP for logs sent to FortiAnalyzer.									
status	Enable/disable logging to FortiAnalyzer.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable logging to FortiAnalyzer.</td></tr><tr><td><i>disable</i></td><td>Disable logging to FortiAnalyzer.</td></tr></table>	Option	Description	<i>enable</i>	Enable logging to FortiAnalyzer.	<i>disable</i>	Disable logging to FortiAnalyzer.			
Option	Description									
<i>enable</i>	Enable logging to FortiAnalyzer.									
<i>disable</i>	Disable logging to FortiAnalyzer.									
ips-archive	Enable/disable IPS packet archive logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable IPS packet archive logging.</td></tr><tr><td><i>disable</i></td><td>Disable IPS packet archive logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable IPS packet archive logging.	<i>disable</i>	Disable IPS packet archive logging.			
Option	Description									
<i>enable</i>	Enable IPS packet archive logging.									
<i>disable</i>	Disable IPS packet archive logging.									
server	The remote FortiAnalyzer.	string	Maximum length: 127							
alt-server	Alternate FortiAnalyzer.	string	Maximum length: 127							

Parameter	Description	Type	Size	Default
fallback-to-primary	Enable/disable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.		
	<i>disable</i>	Disable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.		
certificate-verification	Enable/disable identity verification of FortiAnalyzer by use of certificate.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable identity verification of FortiAnalyzer by use of certificate.		
	<i>disable</i>	Disable identity verification of FortiAnalyzer by use of certificate.		
serial <name>	Serial numbers of the FortiAnalyzer. Serial Number.	string	Maximum length: 79	
server-cert-ca	Mandatory CA on FortiGate in certificate chain of server.	string	Maximum length: 79	
preshared-key	Preshared-key used for auto-authorization on FortiAnalyzer.	string	Maximum length: 63	
access-config	Enable/disable FortiAnalyzer access to configuration and data.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable FortiAnalyzer access to configuration and data.		
	<i>disable</i>	Disable FortiAnalyzer access to configuration and data.		
hmac-algorithm	OFTP login hash algorithm.	option	-	sha256
	Option	Description		
	<i>sha256</i>	Use SHA256 as HMAC algorithm.		
	<i>sha1</i>	Step down to SHA1 as the HMAC algorithm.		
enc-algorithm	Configure the level of SSL protection for secure communication with FortiAnalyzer.	option	-	high

Parameter	Description	Type	Size	Default														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>high-medium</i></td><td>Encrypt logs using high and medium encryption algorithms.</td></tr><tr><td><i>high</i></td><td>Encrypt logs using high encryption algorithms.</td></tr><tr><td><i>low</i></td><td>Encrypt logs using all encryption algorithms.</td></tr></table>	Option	Description	<i>high-medium</i>	Encrypt logs using high and medium encryption algorithms.	<i>high</i>	Encrypt logs using high encryption algorithms.	<i>low</i>	Encrypt logs using all encryption algorithms.									
	Option	Description																
	<i>high-medium</i>	Encrypt logs using high and medium encryption algorithms.																
	<i>high</i>	Encrypt logs using high encryption algorithms.																
<i>low</i>	Encrypt logs using all encryption algorithms.																	
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Follow system global setting.</td></tr><tr><td><i>SSLv3</i></td><td>SSLv3.</td></tr><tr><td><i>TLSv1</i></td><td>TLSv1.</td></tr><tr><td><i>TLSv1-1</i></td><td>TLSv1.1.</td></tr><tr><td><i>TLSv1-2</i></td><td>TLSv1.2.</td></tr><tr><td><i>TLSv1-3</i></td><td>TLSv1.3.</td></tr></table>	Option	Description	<i>default</i>	Follow system global setting.	<i>SSLv3</i>	SSLv3.	<i>TLSv1</i>	TLSv1.	<i>TLSv1-1</i>	TLSv1.1.	<i>TLSv1-2</i>	TLSv1.2.	<i>TLSv1-3</i>	TLSv1.3.			
	Option	Description																
	<i>default</i>	Follow system global setting.																
	<i>SSLv3</i>	SSLv3.																
	<i>TLSv1</i>	TLSv1.																
	<i>TLSv1-1</i>	TLSv1.1.																
	<i>TLSv1-2</i>	TLSv1.2.																
<i>TLSv1-3</i>	TLSv1.3.																	
conn-timeout	FortiAnalyzer connection time-out in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 3600	10														
monitor-keepalive-period	Time between OFTP keepalives in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 120	5														
monitor-failure-retry-period	Time between FortiAnalyzer connection retries in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 86400	5														
certificate	Certificate used to communicate with FortiAnalyzer.	string	Maximum length: 35															
source-ip	Source IPv4 or IPv6 address used to communicate with FortiAnalyzer.	string	Maximum length: 63															
upload-option	Enable/disable logging to hard disk and then uploading to FortiAnalyzer.	option	-	5-minute														

Parameter	Description	Type	Size	Default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>store-and-upload</i></td><td>Log to hard disk and then upload to FortiAnalyzer.</td></tr><tr><td><i>realtime</i></td><td>Log directly to FortiAnalyzer in real time.</td></tr><tr><td><i>1-minute</i></td><td>Log directly to FortiAnalyzer at least every 1 minute.</td></tr><tr><td><i>5-minute</i></td><td>Log directly to FortiAnalyzer at least every 5 minutes.</td></tr></table>	Option	Description	<i>store-and-upload</i>	Log to hard disk and then upload to FortiAnalyzer.	<i>realtime</i>	Log directly to FortiAnalyzer in real time.	<i>1-minute</i>	Log directly to FortiAnalyzer at least every 1 minute.	<i>5-minute</i>	Log directly to FortiAnalyzer at least every 5 minutes.			
	Option	Description												
	<i>store-and-upload</i>	Log to hard disk and then upload to FortiAnalyzer.												
	<i>realtime</i>	Log directly to FortiAnalyzer in real time.												
	<i>1-minute</i>	Log directly to FortiAnalyzer at least every 1 minute.												
<i>5-minute</i>	Log directly to FortiAnalyzer at least every 5 minutes.													
upload-interval	Frequency to upload log files to FortiAnalyzer.	option	-	daily										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>daily</i></td><td>Upload log files to FortiAnalyzer once a day.</td></tr><tr><td><i>weekly</i></td><td>Upload log files to FortiAnalyzer once a week.</td></tr><tr><td><i>monthly</i></td><td>Upload log files to FortiAnalyzer once a month.</td></tr></table>	Option	Description	<i>daily</i>	Upload log files to FortiAnalyzer once a day.	<i>weekly</i>	Upload log files to FortiAnalyzer once a week.	<i>monthly</i>	Upload log files to FortiAnalyzer once a month.					
	Option	Description												
	<i>daily</i>	Upload log files to FortiAnalyzer once a day.												
	<i>weekly</i>	Upload log files to FortiAnalyzer once a week.												
<i>monthly</i>	Upload log files to FortiAnalyzer once a month.													
upload-day	Day of week (month) to upload logs.	user	Not Specified											
upload-time	Time to upload logs (hh:mm).	user	Not Specified											
reliable	Enable/disable reliable logging to FortiAnalyzer.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable reliable logging to FortiAnalyzer.</td></tr><tr><td><i>disable</i></td><td>Disable reliable logging to FortiAnalyzer.</td></tr></table>	Option	Description	<i>enable</i>	Enable reliable logging to FortiAnalyzer.	<i>disable</i>	Disable reliable logging to FortiAnalyzer.							
	Option	Description												
	<i>enable</i>	Enable reliable logging to FortiAnalyzer.												
<i>disable</i>	Disable reliable logging to FortiAnalyzer.													
priority	Set log transmission priority.	option	-	default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Set FortiAnalyzer log transmission priority to default.</td></tr><tr><td><i>low</i></td><td>Set FortiAnalyzer log transmission priority to low.</td></tr></table>	Option	Description	<i>default</i>	Set FortiAnalyzer log transmission priority to default.	<i>low</i>	Set FortiAnalyzer log transmission priority to low.							
	Option	Description												
	<i>default</i>	Set FortiAnalyzer log transmission priority to default.												
<i>low</i>	Set FortiAnalyzer log transmission priority to low.													
max-log-rate	FortiAnalyzer maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0										
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto										

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>auto</i>	Set outgoing interface automatically.		
	<i>specify</i>	Set outgoing interface manually.		
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	

config log fortianalyzer3 setting

Global FortiAnalyzer settings.

```

config log fortianalyzer3 setting
  Description: Global FortiAnalyzer settings.
  set status [enable|disable]
  set ips-archive [enable|disable]
  set server {string}
  set alt-server {string}
  set fallback-to-primary [enable|disable]
  set certificate-verification [enable|disable]
  set serial <name1>, <name2>, ...
  set server-cert-ca {string}
  set preshared-key {string}
  set access-config [enable|disable]
  set hmac-algorithm [sha256|sha1]
  set enc-algorithm [high-medium|high|...]
  set ssl-min-proto-version [default|SSLv3|...]
  set conn-timeout {integer}
  set monitor-keepalive-period {integer}
  set monitor-failure-retry-period {integer}
  set certificate {string}
  set source-ip {string}
  set upload-option [store-and-upload|realtime|...]
  set upload-interval [daily|weekly|...]
  set upload-day {user}
  set upload-time {user}
  set reliable [enable|disable]
  set priority [default|low]
  set max-log-rate {integer}
  set interface-select-method [auto|specify]
  set interface {string}
end

```

config log fortianalyzer3 setting

Parameter	Description	Type	Size	Default
status	Enable/disable logging to FortiAnalyzer.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable logging to FortiAnalyzer.		
	<i>disable</i>	Disable logging to FortiAnalyzer.		
ips-archive	Enable/disable IPS packet archive logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable IPS packet archive logging.		
	<i>disable</i>	Disable IPS packet archive logging.		
server	The remote FortiAnalyzer.	string	Maximum length: 127	
alt-server	Alternate FortiAnalyzer.	string	Maximum length: 127	
fallback-to-primary	Enable/disable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.		
	<i>disable</i>	Disable this FortiGate unit to fallback to the primary FortiAnalyzer when it is available.		
certificate-verification	Enable/disable identity verification of FortiAnalyzer by use of certificate.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable identity verification of FortiAnalyzer by use of certificate.		
	<i>disable</i>	Disable identity verification of FortiAnalyzer by use of certificate.		
serial <name>	Serial numbers of the FortiAnalyzer. Serial Number.	string	Maximum length: 79	
server-cert-ca	Mandatory CA on FortiGate in certificate chain of server.	string	Maximum length: 79	
preshared-key	Preshared-key used for auto-authorization on FortiAnalyzer.	string	Maximum length: 63	

Parameter	Description	Type	Size	Default														
access-config	Enable/disable FortiAnalyzer access to configuration and data.	option	-	enable														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable FortiAnalyzer access to configuration and data.</td></tr><tr><td>disable</td><td>Disable FortiAnalyzer access to configuration and data.</td></tr></table>	Option	Description	enable	Enable FortiAnalyzer access to configuration and data.	disable	Disable FortiAnalyzer access to configuration and data.											
Option	Description																	
enable	Enable FortiAnalyzer access to configuration and data.																	
disable	Disable FortiAnalyzer access to configuration and data.																	
hmac-algorithm	OFTP login hash algorithm.	option	-	sha256														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>sha256</td><td>Use SHA256 as HMAC algorithm.</td></tr><tr><td>sha1</td><td>Step down to SHA1 as the HMAC algorithm.</td></tr></table>	Option	Description	sha256	Use SHA256 as HMAC algorithm.	sha1	Step down to SHA1 as the HMAC algorithm.											
Option	Description																	
sha256	Use SHA256 as HMAC algorithm.																	
sha1	Step down to SHA1 as the HMAC algorithm.																	
enc-algorithm	Configure the level of SSL protection for secure communication with FortiAnalyzer.	option	-	high														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>high-medium</td><td>Encrypt logs using high and medium encryption algorithms.</td></tr><tr><td>high</td><td>Encrypt logs using high encryption algorithms.</td></tr><tr><td>low</td><td>Encrypt logs using all encryption algorithms.</td></tr></table>	Option	Description	high-medium	Encrypt logs using high and medium encryption algorithms.	high	Encrypt logs using high encryption algorithms.	low	Encrypt logs using all encryption algorithms.									
Option	Description																	
high-medium	Encrypt logs using high and medium encryption algorithms.																	
high	Encrypt logs using high encryption algorithms.																	
low	Encrypt logs using all encryption algorithms.																	
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>default</td><td>Follow system global setting.</td></tr><tr><td>SSLv3</td><td>SSLv3.</td></tr><tr><td>TLSv1</td><td>TLSv1.</td></tr><tr><td>TLSv1-1</td><td>TLSv1.1.</td></tr><tr><td>TLSv1-2</td><td>TLSv1.2.</td></tr><tr><td>TLSv1-3</td><td>TLSv1.3.</td></tr></table>	Option	Description	default	Follow system global setting.	SSLv3	SSLv3.	TLSv1	TLSv1.	TLSv1-1	TLSv1.1.	TLSv1-2	TLSv1.2.	TLSv1-3	TLSv1.3.			
Option	Description																	
default	Follow system global setting.																	
SSLv3	SSLv3.																	
TLSv1	TLSv1.																	
TLSv1-1	TLSv1.1.																	
TLSv1-2	TLSv1.2.																	
TLSv1-3	TLSv1.3.																	
conn-timeout	FortiAnalyzer connection time-out in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 3600	10														

Parameter	Description	Type	Size	Default										
monitor-keepalive-period	Time between OFTP keepalives in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 120	5										
monitor-failure-retry-period	Time between FortiAnalyzer connection retries in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 86400	5										
certificate	Certificate used to communicate with FortiAnalyzer.	string	Maximum length: 35											
source-ip	Source IPv4 or IPv6 address used to communicate with FortiAnalyzer.	string	Maximum length: 63											
upload-option	Enable/disable logging to hard disk and then uploading to FortiAnalyzer.	option	-	5-minute										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>store-and-upload</td><td>Log to hard disk and then upload to FortiAnalyzer.</td></tr><tr><td>realtime</td><td>Log directly to FortiAnalyzer in real time.</td></tr><tr><td>1-minute</td><td>Log directly to FortiAnalyzer at least every 1 minute.</td></tr><tr><td>5-minute</td><td>Log directly to FortiAnalyzer at least every 5 minutes.</td></tr></table>				Option	Description	store-and-upload	Log to hard disk and then upload to FortiAnalyzer.	realtime	Log directly to FortiAnalyzer in real time.	1-minute	Log directly to FortiAnalyzer at least every 1 minute.	5-minute	Log directly to FortiAnalyzer at least every 5 minutes.
Option	Description													
store-and-upload	Log to hard disk and then upload to FortiAnalyzer.													
realtime	Log directly to FortiAnalyzer in real time.													
1-minute	Log directly to FortiAnalyzer at least every 1 minute.													
5-minute	Log directly to FortiAnalyzer at least every 5 minutes.													
upload-interval	Frequency to upload log files to FortiAnalyzer.	option	-	daily										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>daily</td><td>Upload log files to FortiAnalyzer once a day.</td></tr><tr><td>weekly</td><td>Upload log files to FortiAnalyzer once a week.</td></tr><tr><td>monthly</td><td>Upload log files to FortiAnalyzer once a month.</td></tr></table>				Option	Description	daily	Upload log files to FortiAnalyzer once a day.	weekly	Upload log files to FortiAnalyzer once a week.	monthly	Upload log files to FortiAnalyzer once a month.		
Option	Description													
daily	Upload log files to FortiAnalyzer once a day.													
weekly	Upload log files to FortiAnalyzer once a week.													
monthly	Upload log files to FortiAnalyzer once a month.													
upload-day	Day of week (month) to upload logs.	user	Not Specified											
upload-time	Time to upload logs (hh:mm).	user	Not Specified											
reliable	Enable/disable reliable logging to FortiAnalyzer.	option	-	disable										

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable reliable logging to FortiAnalyzer.		
	<i>disable</i>	Disable reliable logging to FortiAnalyzer.		
priority	Set log transmission priority.	option	-	default
	Option	Description		
	<i>default</i>	Set FortiAnalyzer log transmission priority to default.		
	<i>low</i>	Set FortiAnalyzer log transmission priority to low.		
max-log-rate	FortiAnalyzer maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto
	Option	Description		
	<i>auto</i>	Set outgoing interface automatically.		
	<i>specify</i>	Set outgoing interface manually.		
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	

config log fortianalyzer-cloud filter

Filters for FortiAnalyzer Cloud.

```

config log fortianalyzer-cloud filter
  Description: Filters for FortiAnalyzer Cloud.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]
  set sniffer-traffic [enable|disable]
  set ztna-traffic [enable|disable]
  set http-transaction [enable|disable]
  set anomaly [enable|disable]
  set voip [enable|disable]
  set dlp-archive [enable|disable]
config free-style

```

```

Description: Free style filters.
edit <id>
    set category [traffic|event|...]
    set filter {string}
    set filter-type [include|exclude]
next
end
end

```

config log fortianalyzer-cloud filter

Parameter	Description	Type	Size	Default
severity	Lowest severity level to log.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		
forward-traffic	Enable/disable forward traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable multicast traffic logging.		
	<i>disable</i>	Disable multicast traffic logging.		
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable sniffer traffic logging.		
	<i>disable</i>	Disable sniffer traffic logging.		
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		
dlp-archive	Enable/disable DLP archive logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable DLP archive logging.		
	<i>disable</i>	Disable DLP archive logging.		

config free-style

Parameter	Description	Type	Size	Default																																		
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0																																		
category	Log category.	option	-	traffic																																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>traffic</td><td>Traffic log.</td></tr><tr><td>event</td><td>Event log.</td></tr><tr><td>virus</td><td>Antivirus log.</td></tr><tr><td>webfilter</td><td>Web filter log.</td></tr><tr><td>attack</td><td>Attack log.</td></tr><tr><td>spam</td><td>Antispam log.</td></tr><tr><td>anomaly</td><td>Anomaly log.</td></tr><tr><td>voip</td><td>VoIP log.</td></tr><tr><td>dlp</td><td>DLP log.</td></tr><tr><td>app-ctrl</td><td>Application control log.</td></tr><tr><td>waf</td><td>Web application firewall log.</td></tr><tr><td>dns</td><td>DNS detail log.</td></tr><tr><td>ssh</td><td>SSH log.</td></tr><tr><td>ssl</td><td>SSL log.</td></tr><tr><td>file-filter</td><td>File filter log.</td></tr><tr><td>icap</td><td>ICAP log.</td></tr></table>	Option	Description	traffic	Traffic log.	event	Event log.	virus	Antivirus log.	webfilter	Web filter log.	attack	Attack log.	spam	Antispam log.	anomaly	Anomaly log.	voip	VoIP log.	dlp	DLP log.	app-ctrl	Application control log.	waf	Web application firewall log.	dns	DNS detail log.	ssh	SSH log.	ssl	SSL log.	file-filter	File filter log.	icap	ICAP log.			
	Option	Description																																				
	traffic	Traffic log.																																				
	event	Event log.																																				
	virus	Antivirus log.																																				
	webfilter	Web filter log.																																				
	attack	Attack log.																																				
	spam	Antispam log.																																				
	anomaly	Anomaly log.																																				
	voip	VoIP log.																																				
	dlp	DLP log.																																				
	app-ctrl	Application control log.																																				
	waf	Web application firewall log.																																				
	dns	DNS detail log.																																				
	ssh	SSH log.																																				
	ssl	SSL log.																																				
	file-filter	File filter log.																																				
icap	ICAP log.																																					
filter	Free style filter string.	string	Maximum length: 1023																																			
filter-type	Include/exclude logs that match the filter.	option	-	include																																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>include</td><td>Include logs that match the filter.</td></tr><tr><td>exclude</td><td>Exclude logs that match the filter.</td></tr></table>	Option	Description	include	Include logs that match the filter.	exclude	Exclude logs that match the filter.																															
	Option	Description																																				
	include	Include logs that match the filter.																																				
exclude	Exclude logs that match the filter.																																					

config log fortianalyzer-cloud override-filter

Override filters for FortiAnalyzer Cloud.

```
config log fortianalyzer-cloud override-filter
  Description: Override filters for FortiAnalyzer Cloud.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]
  set sniffer-traffic [enable|disable]
  set ztna-traffic [enable|disable]
  set http-transaction [enable|disable]
  set anomaly [enable|disable]
  set voip [enable|disable]
  set dlp-archive [enable|disable]
  config free-style
    Description: Free style filters.
    edit <id>
      set category [traffic|event|...]
      set filter {string}
      set filter-type [include|exclude]
    next
  end
end
```

config log fortianalyzer-cloud override-filter

Parameter	Description	Type	Size	Default
severity	Lowest severity level to log.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		
forward-traffic	Enable/disable forward traffic logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable multicast traffic logging.		
	<i>disable</i>	Disable multicast traffic logging.		
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable sniffer traffic logging.		
	<i>disable</i>	Disable sniffer traffic logging.		
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		
dlp-archive	Enable/disable DLP archive logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable DLP archive logging.		
	<i>disable</i>	Disable DLP archive logging.		

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	<i>traffic</i>	Traffic log.		
	<i>event</i>	Event log.		
	<i>virus</i>	Antivirus log.		
	<i>webfilter</i>	Web filter log.		
	<i>attack</i>	Attack log.		
	<i>spam</i>	Antispam log.		
	<i>anomaly</i>	Anomaly log.		
	<i>voip</i>	VoIP log.		
	<i>dlp</i>	DLP log.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>app-ctrl</i>	Application control log.		
	<i>waf</i>	Web application firewall log.		
	<i>dns</i>	DNS detail log.		
	<i>ssh</i>	SSH log.		
	<i>ssl</i>	SSL log.		
	<i>file-filter</i>	File filter log.		
	<i>icap</i>	ICAP log.		
filter	Free style filter string.	string	Maximum length: 1023	
filter-type	Include/exclude logs that match the filter.	option	-	include
	Option	Description		
	<i>include</i>	Include logs that match the filter.		
	<i>exclude</i>	Exclude logs that match the filter.		

config log fortianalyzer-cloud override-setting

Override FortiAnalyzer Cloud settings.

```
config log fortianalyzer-cloud override-setting
    Description: Override FortiAnalyzer Cloud settings.
    set status [enable|disable]
end
```

config log fortianalyzer-cloud override-setting

Parameter	Description	Type	Size	Default						
status	Enable/disable logging to FortiAnalyzer.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable logging to FortiAnalyzer.</td></tr><tr><td><i>disable</i></td><td>Disable logging to FortiAnalyzer.</td></tr></table>				Option	Description	<i>enable</i>	Enable logging to FortiAnalyzer.	<i>disable</i>	Disable logging to FortiAnalyzer.
Option	Description									
<i>enable</i>	Enable logging to FortiAnalyzer.									
<i>disable</i>	Disable logging to FortiAnalyzer.									

config log fortianalyzer-cloud setting

Global FortiAnalyzer Cloud settings.

```
config log fortianalyzer-cloud setting
  Description: Global FortiAnalyzer Cloud settings.
  set status [enable|disable]
  set ips-archive [enable|disable]
  set certificate-verification [enable|disable]
  set serial <name1>, <name2>, ...
  set preshared-key {string}
  set access-config [enable|disable]
  set hmac-algorithm [sha256|sha1]
  set enc-algorithm [high-medium|high|...]
  set ssl-min-proto-version [default|SSLv3|...]
  set conn-timeout {integer}
  set monitor-keepalive-period {integer}
  set monitor-failure-retry-period {integer}
  set certificate {string}
  set source-ip {string}
  set upload-option [store-and-upload|realtime|...]
  set upload-interval [daily|weekly|...]
  set upload-day {user}
  set upload-time {user}
  set priority [default|low]
  set max-log-rate {integer}
  set interface-select-method [auto|specify]
  set interface {string}
end
```

config log fortianalyzer-cloud setting

Parameter	Description	Type	Size	Default
status	Enable/disable logging to FortiAnalyzer.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable logging to FortiAnalyzer.		
	<i>disable</i>	Disable logging to FortiAnalyzer.		
ips-archive	Enable/disable IPS packet archive logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable IPS packet archive logging.		
	<i>disable</i>	Disable IPS packet archive logging.		

Parameter	Description	Type	Size	Default								
certificate-verification	Enable/disable identity verification of FortiAnalyzer by use of certificate.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable identity verification of FortiAnalyzer by use of certificate.</td></tr><tr><td><i>disable</i></td><td>Disable identity verification of FortiAnalyzer by use of certificate.</td></tr></table>	Option	Description	<i>enable</i>	Enable identity verification of FortiAnalyzer by use of certificate.	<i>disable</i>	Disable identity verification of FortiAnalyzer by use of certificate.					
Option	Description											
<i>enable</i>	Enable identity verification of FortiAnalyzer by use of certificate.											
<i>disable</i>	Disable identity verification of FortiAnalyzer by use of certificate.											
serial <name>	Serial numbers of the FortiAnalyzer. Serial Number.	string	Maximum length: 79									
preshared-key	Preshared-key used for auto-authorization on FortiAnalyzer.	string	Maximum length: 63									
access-config	Enable/disable FortiAnalyzer access to configuration and data.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable FortiAnalyzer access to configuration and data.</td></tr><tr><td><i>disable</i></td><td>Disable FortiAnalyzer access to configuration and data.</td></tr></table>	Option	Description	<i>enable</i>	Enable FortiAnalyzer access to configuration and data.	<i>disable</i>	Disable FortiAnalyzer access to configuration and data.					
Option	Description											
<i>enable</i>	Enable FortiAnalyzer access to configuration and data.											
<i>disable</i>	Disable FortiAnalyzer access to configuration and data.											
hmac-algorithm	OFTP login hash algorithm.	option	-	sha256								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>sha256</i></td><td>Use SHA256 as HMAC algorithm.</td></tr><tr><td><i>sha1</i></td><td>Step down to SHA1 as the HMAC algorithm.</td></tr></table>	Option	Description	<i>sha256</i>	Use SHA256 as HMAC algorithm.	<i>sha1</i>	Step down to SHA1 as the HMAC algorithm.					
Option	Description											
<i>sha256</i>	Use SHA256 as HMAC algorithm.											
<i>sha1</i>	Step down to SHA1 as the HMAC algorithm.											
enc-algorithm	Configure the level of SSL protection for secure communication with FortiAnalyzer.	option	-	high								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>high-medium</i></td><td>Encrypt logs using high and medium encryption algorithms.</td></tr><tr><td><i>high</i></td><td>Encrypt logs using high encryption algorithms.</td></tr><tr><td><i>low</i></td><td>Encrypt logs using all encryption algorithms.</td></tr></table>	Option	Description	<i>high-medium</i>	Encrypt logs using high and medium encryption algorithms.	<i>high</i>	Encrypt logs using high encryption algorithms.	<i>low</i>	Encrypt logs using all encryption algorithms.			
Option	Description											
<i>high-medium</i>	Encrypt logs using high and medium encryption algorithms.											
<i>high</i>	Encrypt logs using high encryption algorithms.											
<i>low</i>	Encrypt logs using all encryption algorithms.											
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Follow system global setting.</td></tr></table>	Option	Description	<i>default</i>	Follow system global setting.							
Option	Description											
<i>default</i>	Follow system global setting.											

Parameter	Description	Type	Size	Default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>SSLv3</td><td>SSLv3.</td></tr><tr><td>TLSv1</td><td>TLSv1.</td></tr><tr><td>TLSv1-1</td><td>TLSv1.1.</td></tr><tr><td>TLSv1-2</td><td>TLSv1.2.</td></tr><tr><td>TLSv1-3</td><td>TLSv1.3.</td></tr></table>	Option	Description	SSLv3	SSLv3.	TLSv1	TLSv1.	TLSv1-1	TLSv1.1.	TLSv1-2	TLSv1.2.	TLSv1-3	TLSv1.3.			
	Option	Description														
	SSLv3	SSLv3.														
	TLSv1	TLSv1.														
	TLSv1-1	TLSv1.1.														
	TLSv1-2	TLSv1.2.														
TLSv1-3	TLSv1.3.															
conn-timeout	FortiAnalyzer connection time-out in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 3600	10												
monitor-keepalive-period	Time between OFTP keepalives in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 120	5												
monitor-failure-retry-period	Time between FortiAnalyzer connection retries in seconds (for status and log buffer).	integer	Minimum value: 1 Maximum value: 86400	5												
certificate	Certificate used to communicate with FortiAnalyzer.	string	Maximum length: 35													
source-ip	Source IPv4 or IPv6 address used to communicate with FortiAnalyzer.	string	Maximum length: 63													
upload-option	Enable/disable logging to hard disk and then uploading to FortiAnalyzer.	option	-	5-minute												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>store-and-upload</td><td>Log to hard disk and then upload to FortiAnalyzer.</td></tr><tr><td>realtime</td><td>Log directly to FortiAnalyzer in real time.</td></tr><tr><td>1-minute</td><td>Log directly to FortiAnalyzer at least every 1 minute.</td></tr><tr><td>5-minute</td><td>Log directly to FortiAnalyzer at least every 5 minutes.</td></tr></table>	Option	Description	store-and-upload	Log to hard disk and then upload to FortiAnalyzer.	realtime	Log directly to FortiAnalyzer in real time.	1-minute	Log directly to FortiAnalyzer at least every 1 minute.	5-minute	Log directly to FortiAnalyzer at least every 5 minutes.					
	Option	Description														
	store-and-upload	Log to hard disk and then upload to FortiAnalyzer.														
	realtime	Log directly to FortiAnalyzer in real time.														
	1-minute	Log directly to FortiAnalyzer at least every 1 minute.														
5-minute	Log directly to FortiAnalyzer at least every 5 minutes.															
upload-interval	Frequency to upload log files to FortiAnalyzer.	option	-	daily												

Parameter	Description	Type	Size	Default								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>daily</i></td><td>Upload log files to FortiAnalyzer once a day.</td></tr><tr><td><i>weekly</i></td><td>Upload log files to FortiAnalyzer once a week.</td></tr><tr><td><i>monthly</i></td><td>Upload log files to FortiAnalyzer once a month.</td></tr></table>	Option	Description	<i>daily</i>	Upload log files to FortiAnalyzer once a day.	<i>weekly</i>	Upload log files to FortiAnalyzer once a week.	<i>monthly</i>	Upload log files to FortiAnalyzer once a month.			
	Option	Description										
	<i>daily</i>	Upload log files to FortiAnalyzer once a day.										
	<i>weekly</i>	Upload log files to FortiAnalyzer once a week.										
<i>monthly</i>	Upload log files to FortiAnalyzer once a month.											
upload-day	Day of week (month) to upload logs.	user	Not Specified									
upload-time	Time to upload logs (hh:mm).	user	Not Specified									
priority	Set log transmission priority.	option	-	default								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Set FortiAnalyzer log transmission priority to default.</td></tr><tr><td><i>low</i></td><td>Set FortiAnalyzer log transmission priority to low.</td></tr></table>	Option	Description	<i>default</i>	Set FortiAnalyzer log transmission priority to default.	<i>low</i>	Set FortiAnalyzer log transmission priority to low.					
	Option	Description										
	<i>default</i>	Set FortiAnalyzer log transmission priority to default.										
<i>low</i>	Set FortiAnalyzer log transmission priority to low.											
max-log-rate	FortiAnalyzer maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0								
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Set outgoing interface automatically.</td></tr><tr><td><i>specify</i></td><td>Set outgoing interface manually.</td></tr></table>	Option	Description	<i>auto</i>	Set outgoing interface automatically.	<i>specify</i>	Set outgoing interface manually.					
	Option	Description										
	<i>auto</i>	Set outgoing interface automatically.										
<i>specify</i>	Set outgoing interface manually.											
interface	Specify outgoing interface to reach server.	string	Maximum length: 15									

config log fortiguard filter

Filters for FortiCloud.

```
config log fortiguard filter
  Description: Filters for FortiCloud.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]
```

```

set sniffer-traffic [enable|disable]
set ztna-traffic [enable|disable]
set http-transaction [enable|disable]
set anomaly [enable|disable]
set voip [enable|disable]
config free-style
    Description: Free style filters.
    edit <id>
        set category [traffic|event|...]
        set filter {string}
        set filter-type [include|exclude]
    next
end
end

```

config log fortiguard filter

Parameter	Description	Type	Size	Default
severity	Lowest severity level to log.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		
forward-traffic	Enable/disable forward traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		

Parameter	Description	Type	Size	Default						
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable multicast traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable multicast traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable multicast traffic logging.	<i>disable</i>	Disable multicast traffic logging.			
Option	Description									
<i>enable</i>	Enable multicast traffic logging.									
<i>disable</i>	Disable multicast traffic logging.									
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable sniffer traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable sniffer traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable sniffer traffic logging.	<i>disable</i>	Disable sniffer traffic logging.			
Option	Description									
<i>enable</i>	Enable sniffer traffic logging.									
<i>disable</i>	Disable sniffer traffic logging.									
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable ztna traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable ztna traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable ztna traffic logging.	<i>disable</i>	Disable ztna traffic logging.			
Option	Description									
<i>enable</i>	Enable ztna traffic logging.									
<i>disable</i>	Disable ztna traffic logging.									
http-transaction	Enable/disable log http-transaction messages.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable http transaction logging.</td></tr><tr><td><i>disable</i></td><td>Disable http transaction logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable http transaction logging.	<i>disable</i>	Disable http transaction logging.			
Option	Description									
<i>enable</i>	Enable http transaction logging.									
<i>disable</i>	Disable http transaction logging.									
anomaly	Enable/disable anomaly logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable anomaly logging.</td></tr><tr><td><i>disable</i></td><td>Disable anomaly logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable anomaly logging.	<i>disable</i>	Disable anomaly logging.			
Option	Description									
<i>enable</i>	Enable anomaly logging.									
<i>disable</i>	Disable anomaly logging.									
voip	Enable/disable VoIP logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable VoIP logging.</td></tr><tr><td><i>disable</i></td><td>Disable VoIP logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable VoIP logging.	<i>disable</i>	Disable VoIP logging.			
Option	Description									
<i>enable</i>	Enable VoIP logging.									
<i>disable</i>	Disable VoIP logging.									

config free-style

Parameter	Description	Type	Size	Default																																		
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0																																		
category	Log category.	option	-	traffic																																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>traffic</td><td>Traffic log.</td></tr><tr><td>event</td><td>Event log.</td></tr><tr><td>virus</td><td>Antivirus log.</td></tr><tr><td>webfilter</td><td>Web filter log.</td></tr><tr><td>attack</td><td>Attack log.</td></tr><tr><td>spam</td><td>Antispam log.</td></tr><tr><td>anomaly</td><td>Anomaly log.</td></tr><tr><td>voip</td><td>VoIP log.</td></tr><tr><td>dlp</td><td>DLP log.</td></tr><tr><td>app-ctrl</td><td>Application control log.</td></tr><tr><td>waf</td><td>Web application firewall log.</td></tr><tr><td>dns</td><td>DNS detail log.</td></tr><tr><td>ssh</td><td>SSH log.</td></tr><tr><td>ssl</td><td>SSL log.</td></tr><tr><td>file-filter</td><td>File filter log.</td></tr><tr><td>icap</td><td>ICAP log.</td></tr></table>	Option	Description	traffic	Traffic log.	event	Event log.	virus	Antivirus log.	webfilter	Web filter log.	attack	Attack log.	spam	Antispam log.	anomaly	Anomaly log.	voip	VoIP log.	dlp	DLP log.	app-ctrl	Application control log.	waf	Web application firewall log.	dns	DNS detail log.	ssh	SSH log.	ssl	SSL log.	file-filter	File filter log.	icap	ICAP log.			
	Option	Description																																				
	traffic	Traffic log.																																				
	event	Event log.																																				
	virus	Antivirus log.																																				
	webfilter	Web filter log.																																				
	attack	Attack log.																																				
	spam	Antispam log.																																				
	anomaly	Anomaly log.																																				
	voip	VoIP log.																																				
	dlp	DLP log.																																				
	app-ctrl	Application control log.																																				
	waf	Web application firewall log.																																				
	dns	DNS detail log.																																				
	ssh	SSH log.																																				
	ssl	SSL log.																																				
	file-filter	File filter log.																																				
icap	ICAP log.																																					
filter	Free style filter string.	string	Maximum length: 1023																																			
filter-type	Include/exclude logs that match the filter.	option	-	include																																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>include</td><td>Include logs that match the filter.</td></tr><tr><td>exclude</td><td>Exclude logs that match the filter.</td></tr></table>	Option	Description	include	Include logs that match the filter.	exclude	Exclude logs that match the filter.																															
	Option	Description																																				
	include	Include logs that match the filter.																																				
exclude	Exclude logs that match the filter.																																					

config log fortiguard override-filter

Override filters for FortiCloud.

```
config log fortiguard override-filter
  Description: Override filters for FortiCloud.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]
  set sniffer-traffic [enable|disable]
  set ztna-traffic [enable|disable]
  set http-transaction [enable|disable]
  set anomaly [enable|disable]
  set voip [enable|disable]
  config free-style
    Description: Free style filters.
    edit <id>
      set category [traffic|event|...]
      set filter {string}
      set filter-type [include|exclude]
    next
  end
end
```

config log fortiguard override-filter

Parameter	Description	Type	Size	Default
severity	Lowest severity level to log.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		
forward-traffic	Enable/disable forward traffic logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable multicast traffic logging.		
	<i>disable</i>	Disable multicast traffic logging.		
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable sniffer traffic logging.		
	<i>disable</i>	Disable sniffer traffic logging.		
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	<i>traffic</i>	Traffic log.		
	<i>event</i>	Event log.		
	<i>virus</i>	Antivirus log.		
	<i>webfilter</i>	Web filter log.		
	<i>attack</i>	Attack log.		
	<i>spam</i>	Antispam log.		
	<i>anomaly</i>	Anomaly log.		
	<i>voip</i>	VoIP log.		
	<i>dlp</i>	DLP log.		
	<i>app-ctrl</i>	Application control log.		
	<i>waf</i>	Web application firewall log.		
	<i>dns</i>	DNS detail log.		
	<i>ssh</i>	SSH log.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>ssl</i>	SSL log.		
	<i>file-filter</i>	File filter log.		
	<i>icap</i>	ICAP log.		
filter	Free style filter string.	string	Maximum length: 1023	
filter-type	Include/exclude logs that match the filter.	option	-	include
	Option	Description		
	<i>include</i>	Include logs that match the filter.		
	<i>exclude</i>	Exclude logs that match the filter.		

config log fortiguard override-setting

Override global FortiCloud logging settings for this VDOM.

```
config log fortiguard override-setting
  Description: Override global FortiCloud logging settings for this VDOM.
  set override [enable|disable]
  set status [enable|disable]
  set upload-option [store-and-upload|realtime|...]
  set upload-interval [daily|weekly|...]
  set upload-day {user}
  set upload-time {user}
  set priority [default|low]
  set max-log-rate {integer}
  set access-config [enable|disable]
end
```

config log fortiguard override-setting

Parameter	Description	Type	Size	Default						
override	Overriding FortiCloud settings for this VDOM or use global settings.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Override FortiCloud logging settings.</td></tr><tr><td><i>disable</i></td><td>Use global FortiCloud logging settings.</td></tr></table>				Option	Description	<i>enable</i>	Override FortiCloud logging settings.	<i>disable</i>	Use global FortiCloud logging settings.
Option	Description									
<i>enable</i>	Override FortiCloud logging settings.									
<i>disable</i>	Use global FortiCloud logging settings.									

Parameter	Description	Type	Size	Default										
status	Enable/disable logging to FortiCloud.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable logging to FortiCloud.</td></tr><tr><td><i>disable</i></td><td>Disable logging to FortiCloud.</td></tr></table>	Option	Description	<i>enable</i>	Enable logging to FortiCloud.	<i>disable</i>	Disable logging to FortiCloud.							
Option	Description													
<i>enable</i>	Enable logging to FortiCloud.													
<i>disable</i>	Disable logging to FortiCloud.													
upload-option	Configure how log messages are sent to FortiCloud.	option	-	5-minute										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>store-and-upload</i></td><td>Log to the hard disk and then upload logs to FortiCloud.</td></tr><tr><td><i>realtime</i></td><td>Log directly to FortiCloud in real time.</td></tr><tr><td><i>1-minute</i></td><td>Log directly to FortiCloud at 1-minute intervals.</td></tr><tr><td><i>5-minute</i></td><td>Log directly to FortiCloud at 5-minute intervals.</td></tr></table>	Option	Description	<i>store-and-upload</i>	Log to the hard disk and then upload logs to FortiCloud.	<i>realtime</i>	Log directly to FortiCloud in real time.	<i>1-minute</i>	Log directly to FortiCloud at 1-minute intervals.	<i>5-minute</i>	Log directly to FortiCloud at 5-minute intervals.			
Option	Description													
<i>store-and-upload</i>	Log to the hard disk and then upload logs to FortiCloud.													
<i>realtime</i>	Log directly to FortiCloud in real time.													
<i>1-minute</i>	Log directly to FortiCloud at 1-minute intervals.													
<i>5-minute</i>	Log directly to FortiCloud at 5-minute intervals.													
upload-interval	Frequency of uploading log files to FortiCloud.	option	-	daily										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>daily</i></td><td>Upload log files to FortiCloud once a day.</td></tr><tr><td><i>weekly</i></td><td>Upload log files to FortiCloud once a week.</td></tr><tr><td><i>monthly</i></td><td>Upload log files to FortiCloud once a month.</td></tr></table>	Option	Description	<i>daily</i>	Upload log files to FortiCloud once a day.	<i>weekly</i>	Upload log files to FortiCloud once a week.	<i>monthly</i>	Upload log files to FortiCloud once a month.					
Option	Description													
<i>daily</i>	Upload log files to FortiCloud once a day.													
<i>weekly</i>	Upload log files to FortiCloud once a week.													
<i>monthly</i>	Upload log files to FortiCloud once a month.													
upload-day	Day of week to roll logs.	user	Not Specified											
upload-time	Time of day to roll logs (hh:mm).	user	Not Specified											
priority	Set log transmission priority.	option	-	default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Set FortiCloud log transmission priority to default.</td></tr><tr><td><i>low</i></td><td>Set FortiCloud log transmission priority to low.</td></tr></table>	Option	Description	<i>default</i>	Set FortiCloud log transmission priority to default.	<i>low</i>	Set FortiCloud log transmission priority to low.							
Option	Description													
<i>default</i>	Set FortiCloud log transmission priority to default.													
<i>low</i>	Set FortiCloud log transmission priority to low.													
max-log-rate	FortiCloud maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0										

Parameter	Description	Type	Size	Default
access-config	Enable/disable FortiCloud access to configuration and data.	option	-	enable
	Option Description			
	<i>enable</i>	Enable FortiCloud access to configuration and data.		
	<i>disable</i>	Disable FortiCloud access to configuration and data.		

config log fortiguard setting

Configure logging to FortiCloud.

```

config log fortiguard setting
  Description: Configure logging to FortiCloud.
  set status [enable|disable]
  set upload-option [store-and-upload|realtime|...]
  set upload-interval [daily|weekly|...]
  set upload-day {user}
  set upload-time {user}
  set priority [default|low]
  set max-log-rate {integer}
  set access-config [enable|disable]
  set enc-algorithm [high-medium|high|...]
  set ssl-min-proto-version [default|SSLv3|...]
  set conn-timeout {integer}
  set source-ip {ipv4-address}
  set interface-select-method [auto|specify]
  set interface {string}
end

```

config log fortiguard setting

Parameter	Description	Type	Size	Default
status	Enable/disable logging to FortiCloud.	option	-	disable
	Option Description			
	<i>enable</i>	Enable logging to FortiCloud.		
	<i>disable</i>	Disable logging to FortiCloud.		
upload-option	Configure how log messages are sent to FortiCloud.	option	-	5-minute

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>store-and-upload</i>	Log to the hard disk and then upload logs to FortiCloud.		
	<i>realtime</i>	Log directly to FortiCloud in real time.		
	<i>1-minute</i>	Log directly to FortiCloud at 1-minute intervals.		
	<i>5-minute</i>	Log directly to FortiCloud at 5-minute intervals.		
upload-interval	Frequency of uploading log files to FortiCloud.	option	-	daily
	Option	Description		
	<i>daily</i>	Upload log files to FortiCloud once a day.		
	<i>weekly</i>	Upload log files to FortiCloud once a week.		
	<i>monthly</i>	Upload log files to FortiCloud once a month.		
upload-day	Day of week to roll logs.	user	Not Specified	
upload-time	Time of day to roll logs (hh:mm).	user	Not Specified	
priority	Set log transmission priority.	option	-	default
	Option	Description		
	<i>default</i>	Set FortiCloud log transmission priority to default.		
	<i>low</i>	Set FortiCloud log transmission priority to low.		
max-log-rate	FortiCloud maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0
access-config	Enable/disable FortiCloud access to configuration and data.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable FortiCloud access to configuration and data.		
	<i>disable</i>	Disable FortiCloud access to configuration and data.		
enc-algorithm	Configure the level of SSL protection for secure communication with FortiCloud.	option	-	high

Parameter	Description	Type	Size	Default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>high-medium</i></td><td>Encrypt logs using high and medium encryption.</td></tr><tr><td><i>high</i></td><td>Encrypt logs using high encryption.</td></tr><tr><td><i>low</i></td><td>Encrypt logs using low encryption.</td></tr></table>	Option	Description	<i>high-medium</i>	Encrypt logs using high and medium encryption.	<i>high</i>	Encrypt logs using high encryption.	<i>low</i>	Encrypt logs using low encryption.							
	Option	Description														
	<i>high-medium</i>	Encrypt logs using high and medium encryption.														
	<i>high</i>	Encrypt logs using high encryption.														
<i>low</i>	Encrypt logs using low encryption.															
ssl-min- proto- version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Follow system global setting.</td></tr><tr><td><i>SSLv3</i></td><td>SSLv3.</td></tr><tr><td><i>TLSv1</i></td><td>TLSv1.</td></tr><tr><td><i>TLSv1-1</i></td><td>TLSv1.1.</td></tr><tr><td><i>TLSv1-2</i></td><td>TLSv1.2.</td></tr></table>	Option	Description	<i>default</i>	Follow system global setting.	<i>SSLv3</i>	SSLv3.	<i>TLSv1</i>	TLSv1.	<i>TLSv1-1</i>	TLSv1.1.	<i>TLSv1-2</i>	TLSv1.2.			
	Option	Description														
	<i>default</i>	Follow system global setting.														
	<i>SSLv3</i>	SSLv3.														
	<i>TLSv1</i>	TLSv1.														
	<i>TLSv1-1</i>	TLSv1.1.														
<i>TLSv1-2</i>	TLSv1.2.															
conn- timeout	FortiProxy Cloud connection timeout in seconds.	integer	Minimum value: 1 Maximum value: 3600	10												
source-ip	Source IP address used to connect FortiCloud.	ipv4- address	Not Specified	0.0.0.0												
interface- select- method	Specify how to select outgoing interface to reach server.	option	-	auto												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Set outgoing interface automatically.</td></tr><tr><td><i>specify</i></td><td>Set outgoing interface manually.</td></tr></table>	Option	Description	<i>auto</i>	Set outgoing interface automatically.	<i>specify</i>	Set outgoing interface manually.									
	Option	Description														
	<i>auto</i>	Set outgoing interface automatically.														
<i>specify</i>	Set outgoing interface manually.															
interface	Specify outgoing interface to reach server.	string	Maximum length: 15													

config log gui-display

Configure how log messages are displayed on the GUI.

```
config log gui-display
  Description: Configure how log messages are displayed on the GUI.
```

```

set resolve-hosts [enable|disable]
set resolve-apps [enable|disable]
set fortiview-unscanned-apps [enable|disable]
end

```

config log gui-display

Parameter	Description	Type	Size	Default						
resolve-hosts	Enable/disable resolving IP addresses to hostname in log messages on the GUI using reverse DNS lookup.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable resolving IP addresses to hostnames.</td></tr><tr><td><i>disable</i></td><td>Disable resolving IP addresses to hostnames.</td></tr></table>	Option	Description	<i>enable</i>	Enable resolving IP addresses to hostnames.	<i>disable</i>	Disable resolving IP addresses to hostnames.			
Option	Description									
<i>enable</i>	Enable resolving IP addresses to hostnames.									
<i>disable</i>	Disable resolving IP addresses to hostnames.									
resolve-apps	Resolve unknown applications on the GUI using Fortinet's remote application database.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable unknown applications on the GUI.</td></tr><tr><td><i>disable</i></td><td>Disable unknown applications on the GUI.</td></tr></table>	Option	Description	<i>enable</i>	Enable unknown applications on the GUI.	<i>disable</i>	Disable unknown applications on the GUI.			
Option	Description									
<i>enable</i>	Enable unknown applications on the GUI.									
<i>disable</i>	Disable unknown applications on the GUI.									
fortiview-unscanned-apps	Enable/disable showing unscanned traffic in FortiView application charts.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable showing unscanned traffic.</td></tr><tr><td><i>disable</i></td><td>Disable showing unscanned traffic.</td></tr></table>	Option	Description	<i>enable</i>	Enable showing unscanned traffic.	<i>disable</i>	Disable showing unscanned traffic.			
Option	Description									
<i>enable</i>	Enable showing unscanned traffic.									
<i>disable</i>	Disable showing unscanned traffic.									

config log memory filter

Filters for memory buffer.

```

config log memory filter
  Description: Filters for memory buffer.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]
  set sniffer-traffic [enable|disable]
  set ztna-traffic [enable|disable]

```

```

set http-transaction [enable|disable]
set anomaly [enable|disable]
set voip [enable|disable]
config free-style
    Description: Free style filters.
    edit <id>
        set category [traffic|event|...]
        set filter {string}
        set filter-type [include|exclude]
    next
end
end

```

config log memory filter

Parameter	Description	Type	Size	Default																		
severity	Log every message above and including this severity level.	option	-	information																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>emergency</i></td><td>Emergency level.</td></tr><tr><td><i>alert</i></td><td>Alert level.</td></tr><tr><td><i>critical</i></td><td>Critical level.</td></tr><tr><td><i>error</i></td><td>Error level.</td></tr><tr><td><i>warning</i></td><td>Warning level.</td></tr><tr><td><i>notification</i></td><td>Notification level.</td></tr><tr><td><i>information</i></td><td>Information level.</td></tr><tr><td><i>debug</i></td><td>Debug level.</td></tr></table>	Option	Description	<i>emergency</i>	Emergency level.	<i>alert</i>	Alert level.	<i>critical</i>	Critical level.	<i>error</i>	Error level.	<i>warning</i>	Warning level.	<i>notification</i>	Notification level.	<i>information</i>	Information level.	<i>debug</i>	Debug level.			
	Option	Description																				
	<i>emergency</i>	Emergency level.																				
	<i>alert</i>	Alert level.																				
	<i>critical</i>	Critical level.																				
	<i>error</i>	Error level.																				
	<i>warning</i>	Warning level.																				
	<i>notification</i>	Notification level.																				
	<i>information</i>	Information level.																				
<i>debug</i>	Debug level.																					
forward-traffic	Enable/disable forward traffic logging.	option	-	enable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable forward traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable forward traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable forward traffic logging.	<i>disable</i>	Disable forward traffic logging.															
	Option	Description																				
	<i>enable</i>	Enable forward traffic logging.																				
<i>disable</i>	Disable forward traffic logging.																					
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable local in or out traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable local in or out traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable local in or out traffic logging.	<i>disable</i>	Disable local in or out traffic logging.															
	Option	Description																				
	<i>enable</i>	Enable local in or out traffic logging.																				
<i>disable</i>	Disable local in or out traffic logging.																					

Parameter	Description	Type	Size	Default						
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable multicast traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable multicast traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable multicast traffic logging.	<i>disable</i>	Disable multicast traffic logging.			
Option	Description									
<i>enable</i>	Enable multicast traffic logging.									
<i>disable</i>	Disable multicast traffic logging.									
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable sniffer traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable sniffer traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable sniffer traffic logging.	<i>disable</i>	Disable sniffer traffic logging.			
Option	Description									
<i>enable</i>	Enable sniffer traffic logging.									
<i>disable</i>	Disable sniffer traffic logging.									
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable ztna traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable ztna traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable ztna traffic logging.	<i>disable</i>	Disable ztna traffic logging.			
Option	Description									
<i>enable</i>	Enable ztna traffic logging.									
<i>disable</i>	Disable ztna traffic logging.									
http-transaction	Enable/disable log http-transaction messages.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable http transaction logging.</td></tr><tr><td><i>disable</i></td><td>Disable http transaction logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable http transaction logging.	<i>disable</i>	Disable http transaction logging.			
Option	Description									
<i>enable</i>	Enable http transaction logging.									
<i>disable</i>	Disable http transaction logging.									
anomaly	Enable/disable anomaly logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable anomaly logging.</td></tr><tr><td><i>disable</i></td><td>Disable anomaly logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable anomaly logging.	<i>disable</i>	Disable anomaly logging.			
Option	Description									
<i>enable</i>	Enable anomaly logging.									
<i>disable</i>	Disable anomaly logging.									
voip	Enable/disable VoIP logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable VoIP logging.</td></tr><tr><td><i>disable</i></td><td>Disable VoIP logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable VoIP logging.	<i>disable</i>	Disable VoIP logging.			
Option	Description									
<i>enable</i>	Enable VoIP logging.									
<i>disable</i>	Disable VoIP logging.									

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option Description			
	traffic	Traffic log.		
	event	Event log.		
	virus	Antivirus log.		
	webfilter	Web filter log.		
	attack	Attack log.		
	spam	Antispam log.		
	anomaly	Anomaly log.		
	voip	VoIP log.		
	dlp	DLP log.		
	app-ctrl	Application control log.		
	waf	Web application firewall log.		
	dns	DNS detail log.		
	ssh	SSH log.		
	ssl	SSL log.		
	file-filter	File filter log.		
	icap	ICAP log.		
filter	Free style filter string.	string	Maximum length: 1023	
filter-type	Include/exclude logs that match the filter.	option	-	include
	Option Description			
	include	Include logs that match the filter.		
	exclude	Exclude logs that match the filter.		

config log memory global-setting

Global settings for memory logging.

```
config log memory global-setting
  Description: Global settings for memory logging.
  set max-size {integer}
  set full-first-warning-threshold {integer}
  set full-second-warning-threshold {integer}
  set full-final-warning-threshold {integer}
end
```

config log memory global-setting

Parameter	Description	Type	Size	Default
max-size	Maximum amount of memory that can be used for memory logging in bytes.	integer	Minimum value: 0 Maximum value: 4294967295	41308815
full-first-warning-threshold	Log full first warning threshold as a percent (1 - 98, default = 75).	integer	Minimum value: 1 Maximum value: 98	75
full-second-warning-threshold	Log full second warning threshold as a percent (2 - 99, default = 90).	integer	Minimum value: 2 Maximum value: 99	90
full-final-warning-threshold	Log full final warning threshold as a percent (3 - 100, default = 95).	integer	Minimum value: 3 Maximum value: 100	95

config log memory setting

Settings for memory buffer.

```
config log memory setting
  Description: Settings for memory buffer.
  set status [enable|disable]
end
```

config log memory setting

Parameter	Description	Type	Size	Default
status	Enable/disable logging to the FortiProxy's memory.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable logging to memory.		
	<i>disable</i>	Disable logging to memory.		

config log null-device filter

Filters for null device logging.

```
config log null-device filter
  Description: Filters for null device logging.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]
  set sniffer-traffic [enable|disable]
  set ztna-traffic [enable|disable]
  set http-transaction [enable|disable]
  set anomaly [enable|disable]
  set voip [enable|disable]
  config free-style
    Description: Free style filters.
    edit <id>
      set category [traffic|event|...]
      set filter {string}
      set filter-type [include|exclude]
    next
  end
end
```

config log null-device filter

Parameter	Description	Type	Size	Default
severity	Lowest severity level to log.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		

Parameter	Description	Type	Size	Default																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>alert</i></td><td>Alert level.</td></tr><tr><td><i>critical</i></td><td>Critical level.</td></tr><tr><td><i>error</i></td><td>Error level.</td></tr><tr><td><i>warning</i></td><td>Warning level.</td></tr><tr><td><i>notification</i></td><td>Notification level.</td></tr><tr><td><i>information</i></td><td>Information level.</td></tr><tr><td><i>debug</i></td><td>Debug level.</td></tr></table>	Option	Description	<i>alert</i>	Alert level.	<i>critical</i>	Critical level.	<i>error</i>	Error level.	<i>warning</i>	Warning level.	<i>notification</i>	Notification level.	<i>information</i>	Information level.	<i>debug</i>	Debug level.			
	Option	Description																		
	<i>alert</i>	Alert level.																		
	<i>critical</i>	Critical level.																		
	<i>error</i>	Error level.																		
	<i>warning</i>	Warning level.																		
	<i>notification</i>	Notification level.																		
	<i>information</i>	Information level.																		
<i>debug</i>	Debug level.																			
forward-traffic	Enable/disable forward traffic logging.	option	-	enable																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable forward traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable forward traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable forward traffic logging.	<i>disable</i>	Disable forward traffic logging.													
	Option	Description																		
	<i>enable</i>	Enable forward traffic logging.																		
<i>disable</i>	Disable forward traffic logging.																			
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable local in or out traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable local in or out traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable local in or out traffic logging.	<i>disable</i>	Disable local in or out traffic logging.													
	Option	Description																		
	<i>enable</i>	Enable local in or out traffic logging.																		
<i>disable</i>	Disable local in or out traffic logging.																			
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable multicast traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable multicast traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable multicast traffic logging.	<i>disable</i>	Disable multicast traffic logging.													
	Option	Description																		
	<i>enable</i>	Enable multicast traffic logging.																		
<i>disable</i>	Disable multicast traffic logging.																			
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable sniffer traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable sniffer traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable sniffer traffic logging.	<i>disable</i>	Disable sniffer traffic logging.													
	Option	Description																		
	<i>enable</i>	Enable sniffer traffic logging.																		
<i>disable</i>	Disable sniffer traffic logging.																			
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable																

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	<i>traffic</i>	Traffic log.		
	<i>event</i>	Event log.		
	<i>virus</i>	Antivirus log.		
	<i>webfilter</i>	Web filter log.		

Parameter	Description	Type	Size	Default																										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>attack</i></td><td>Attack log.</td></tr><tr><td><i>spam</i></td><td>Antispam log.</td></tr><tr><td><i>anomaly</i></td><td>Anomaly log.</td></tr><tr><td><i>voip</i></td><td>VoIP log.</td></tr><tr><td><i>dlp</i></td><td>DLP log.</td></tr><tr><td><i>app-ctrl</i></td><td>Application control log.</td></tr><tr><td><i>waf</i></td><td>Web application firewall log.</td></tr><tr><td><i>dns</i></td><td>DNS detail log.</td></tr><tr><td><i>ssh</i></td><td>SSH log.</td></tr><tr><td><i>ssl</i></td><td>SSL log.</td></tr><tr><td><i>file-filter</i></td><td>File filter log.</td></tr><tr><td><i>icap</i></td><td>ICAP log.</td></tr></table>	Option	Description	<i>attack</i>	Attack log.	<i>spam</i>	Antispam log.	<i>anomaly</i>	Anomaly log.	<i>voip</i>	VoIP log.	<i>dlp</i>	DLP log.	<i>app-ctrl</i>	Application control log.	<i>waf</i>	Web application firewall log.	<i>dns</i>	DNS detail log.	<i>ssh</i>	SSH log.	<i>ssl</i>	SSL log.	<i>file-filter</i>	File filter log.	<i>icap</i>	ICAP log.			
	Option	Description																												
	<i>attack</i>	Attack log.																												
	<i>spam</i>	Antispam log.																												
	<i>anomaly</i>	Anomaly log.																												
	<i>voip</i>	VoIP log.																												
	<i>dlp</i>	DLP log.																												
	<i>app-ctrl</i>	Application control log.																												
	<i>waf</i>	Web application firewall log.																												
	<i>dns</i>	DNS detail log.																												
	<i>ssh</i>	SSH log.																												
	<i>ssl</i>	SSL log.																												
	<i>file-filter</i>	File filter log.																												
<i>icap</i>	ICAP log.																													
filter	Free style filter string.	string	Maximum length: 1023																											
filter-type	Include/exclude logs that match the filter.	option	-	include																										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>include</i></td><td>Include logs that match the filter.</td></tr><tr><td><i>exclude</i></td><td>Exclude logs that match the filter.</td></tr></table>	Option	Description	<i>include</i>	Include logs that match the filter.	<i>exclude</i>	Exclude logs that match the filter.																							
	Option	Description																												
	<i>include</i>	Include logs that match the filter.																												
<i>exclude</i>	Exclude logs that match the filter.																													

config log null-device setting

Settings for null device logging.

```
config log null-device setting
    Description: Settings for null device logging.
    set status [enable|disable]
end
```

config log null-device setting

Parameter	Description	Type	Size	Default
status	Enable/disable statistics collection for when no external logging destination, such as FortiAnalyzer, is present (data is not saved).	option	-	disable
		Option	Description	
		<i>enable</i>	Enable statistics collection for when no external logging destination, such as FortiAnalyzer, is present (data is not saved).	
		<i>disable</i>	Disable statistics collection for when no external logging destination, such as FortiAnalyzer, is present (data is not saved).	

config log setting

Configure general log settings.

```
config log setting
  Description: Configure general log settings.
  set resolve-ip [enable|disable]
  set resolve-port [enable|disable]
  set log-user-in-upper [enable|disable]
  set fwpolicy-implicit-log [enable|disable]
  set fwpolicy6-implicit-log [enable|disable]
  set log-invalid-packet [enable|disable]
  set local-in-allow [enable|disable]
  set local-in-deny-unicast [enable|disable]
  set local-in-deny-broadcast [enable|disable]
  set local-out [enable|disable]
  set local-out-ioc-detection [enable|disable]
  set daemon-log [enable|disable]
  set neighbor-event [enable|disable]
  set brief-traffic-format [enable|disable]
  set user-anonymize [enable|disable]
  set expolicy-implicit-log [enable|disable]
  set log-policy-comment [enable|disable]
  set faz-override [enable|disable]
  set syslog-override [enable|disable]
  set rest-api-set [enable|disable]
  set rest-api-get [enable|disable]
  set custom-log-fields <field-id1>, <field-id2>, ...
  set anonymization-hash {string}
end
```

config log setting

Parameter	Description	Type	Size	Default						
resolve-ip	Enable/disable adding resolved domain names to traffic logs if possible.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable adding resolved domain names to traffic logs.</td></tr><tr><td><i>disable</i></td><td>Disable adding resolved domain names to traffic logs.</td></tr></table>	Option	Description	<i>enable</i>	Enable adding resolved domain names to traffic logs.	<i>disable</i>	Disable adding resolved domain names to traffic logs.			
Option	Description									
<i>enable</i>	Enable adding resolved domain names to traffic logs.									
<i>disable</i>	Disable adding resolved domain names to traffic logs.									
resolve-port	Enable/disable adding resolved service names to traffic logs.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable adding resolved service names to traffic logs.</td></tr><tr><td><i>disable</i></td><td>Disable adding resolved service names to traffic logs.</td></tr></table>	Option	Description	<i>enable</i>	Enable adding resolved service names to traffic logs.	<i>disable</i>	Disable adding resolved service names to traffic logs.			
Option	Description									
<i>enable</i>	Enable adding resolved service names to traffic logs.									
<i>disable</i>	Disable adding resolved service names to traffic logs.									
log-user-in-upper	Enable/disable logs with user-in-upper.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable logs with user-in-upper.</td></tr><tr><td><i>disable</i></td><td>Disable logs with user-in-upper.</td></tr></table>	Option	Description	<i>enable</i>	Enable logs with user-in-upper.	<i>disable</i>	Disable logs with user-in-upper.			
Option	Description									
<i>enable</i>	Enable logs with user-in-upper.									
<i>disable</i>	Disable logs with user-in-upper.									
fwpolicy-implicit-log	Enable/disable implicit firewall policy logging.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable implicit firewall policy logging.</td></tr><tr><td><i>disable</i></td><td>Disable implicit firewall policy logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable implicit firewall policy logging.	<i>disable</i>	Disable implicit firewall policy logging.			
Option	Description									
<i>enable</i>	Enable implicit firewall policy logging.									
<i>disable</i>	Disable implicit firewall policy logging.									
fwpolicy6-implicit-log	Enable/disable implicit firewall policy6 logging.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable implicit firewall policy6 logging.</td></tr><tr><td><i>disable</i></td><td>Disable implicit firewall policy6 logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable implicit firewall policy6 logging.	<i>disable</i>	Disable implicit firewall policy6 logging.			
Option	Description									
<i>enable</i>	Enable implicit firewall policy6 logging.									
<i>disable</i>	Disable implicit firewall policy6 logging.									
log-invalid-packet	Enable/disable invalid packet traffic logging.	option	-	disable						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable invalid packet traffic logging.		
	<i>disable</i>	Disable invalid packet traffic logging.		
local-in-allow	Enable/disable local-in-allow logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable local-in-allow logging.		
	<i>disable</i>	Disable local-in-allow logging.		
local-in-deny-unicast	Enable/disable local-in-deny-unicast logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable local-in-deny-unicast logging.		
	<i>disable</i>	Disable local-in-deny-unicast logging.		
local-in-deny-broadcast	Enable/disable local-in-deny-broadcast logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable local-in-deny-broadcast logging.		
	<i>disable</i>	Disable local-in-deny-broadcast logging.		
local-out	Enable/disable local-out logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local-out logging.		
	<i>disable</i>	Disable local-out logging.		
local-out-ioc-detection	Enable/disable local-out traffic IoC detection. Requires local-out to be enabled.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local-out traffic IoC detection. Requires local-out to be enabled.		
	<i>disable</i>	Disable local-out traffic IoC detection.		
daemon-log	Enable/disable daemon logging.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable daemon logging.		
	<i>disable</i>	Disable daemon logging.		
neighbor-event	Enable/disable neighbor event logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable neighbor event logging.		
	<i>disable</i>	Disable neighbor event logging.		
brief-traffic-format	Enable/disable brief format traffic logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable brief format traffic logging.		
	<i>disable</i>	Disable brief format traffic logging.		
user-anonymize	Enable/disable anonymizing user names in log messages.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable anonymizing user names in log messages.		
	<i>disable</i>	Disable anonymizing user names in log messages.		
expolicy-implicit-log	Enable/disable explicit proxy firewall implicit policy logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable explicit proxy firewall implicit policy logging.		
	<i>disable</i>	Disable explicit proxy firewall implicit policy logging.		
log-policy-comment	Enable/disable inserting policy comments into traffic logs.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable inserting policy comments into traffic logs.		
	<i>disable</i>	Disable inserting policy comments into traffic logs.		
faz-override	Enable/disable override FortiAnalyzer settings.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable override FortiAnalyzer settings.		
	<i>disable</i>	Disable override FortiAnalyzer settings.		
syslog-override	Enable/disable override Syslog settings.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable override Syslog settings.		
	<i>disable</i>	Disable override Syslog settings.		
rest-api-set	Enable/disable REST API POST/PUT/DELETE request logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable POST/PUT/DELETE REST API logging.		
	<i>disable</i>	Disable POST/PUT/DELETE REST API logging.		
rest-api-get	Enable/disable REST API GET request logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable GET REST API logging.		
	<i>disable</i>	Disable GET REST API logging.		
custom-log-fields <field-id>	Custom fields to append to all log messages. Custom log field.	string	Maximum length: 35	
anonymization-hash	User name anonymization hash salt.	string	Maximum length: 32	

config log syslogd filter

Filters for remote system server.

```
config log syslogd filter
  Description: Filters for remote system server.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]
  set sniffer-traffic [enable|disable]
  set ztna-traffic [enable|disable]
```

```

set http-transaction [enable|disable]
set anomaly [enable|disable]
set voip [enable|disable]
config free-style
    Description: Free style filters.
    edit <id>
        set category [traffic|event|...]
        set filter {string}
        set filter-type [include|exclude]
    next
end
end

```

config log syslogd filter

Parameter	Description	Type	Size	Default
severity	Lowest severity level to log.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		
forward-traffic	Enable/disable forward traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		

Parameter	Description	Type	Size	Default						
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable multicast traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable multicast traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable multicast traffic logging.	<i>disable</i>	Disable multicast traffic logging.			
Option	Description									
<i>enable</i>	Enable multicast traffic logging.									
<i>disable</i>	Disable multicast traffic logging.									
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable sniffer traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable sniffer traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable sniffer traffic logging.	<i>disable</i>	Disable sniffer traffic logging.			
Option	Description									
<i>enable</i>	Enable sniffer traffic logging.									
<i>disable</i>	Disable sniffer traffic logging.									
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable ztna traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable ztna traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable ztna traffic logging.	<i>disable</i>	Disable ztna traffic logging.			
Option	Description									
<i>enable</i>	Enable ztna traffic logging.									
<i>disable</i>	Disable ztna traffic logging.									
http-transaction	Enable/disable log http-transaction messages.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable http transaction logging.</td></tr><tr><td><i>disable</i></td><td>Disable http transaction logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable http transaction logging.	<i>disable</i>	Disable http transaction logging.			
Option	Description									
<i>enable</i>	Enable http transaction logging.									
<i>disable</i>	Disable http transaction logging.									
anomaly	Enable/disable anomaly logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable anomaly logging.</td></tr><tr><td><i>disable</i></td><td>Disable anomaly logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable anomaly logging.	<i>disable</i>	Disable anomaly logging.			
Option	Description									
<i>enable</i>	Enable anomaly logging.									
<i>disable</i>	Disable anomaly logging.									
voip	Enable/disable VoIP logging.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable VoIP logging.</td></tr><tr><td><i>disable</i></td><td>Disable VoIP logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable VoIP logging.	<i>disable</i>	Disable VoIP logging.			
Option	Description									
<i>enable</i>	Enable VoIP logging.									
<i>disable</i>	Disable VoIP logging.									

config free-style

Parameter	Description	Type	Size	Default																																		
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0																																		
category	Log category.	option	-	traffic																																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>traffic</td><td>Traffic log.</td></tr><tr><td>event</td><td>Event log.</td></tr><tr><td>virus</td><td>Antivirus log.</td></tr><tr><td>webfilter</td><td>Web filter log.</td></tr><tr><td>attack</td><td>Attack log.</td></tr><tr><td>spam</td><td>Antispam log.</td></tr><tr><td>anomaly</td><td>Anomaly log.</td></tr><tr><td>voip</td><td>VoIP log.</td></tr><tr><td>dlp</td><td>DLP log.</td></tr><tr><td>app-ctrl</td><td>Application control log.</td></tr><tr><td>waf</td><td>Web application firewall log.</td></tr><tr><td>dns</td><td>DNS detail log.</td></tr><tr><td>ssh</td><td>SSH log.</td></tr><tr><td>ssl</td><td>SSL log.</td></tr><tr><td>file-filter</td><td>File filter log.</td></tr><tr><td>icap</td><td>ICAP log.</td></tr></table>	Option	Description	traffic	Traffic log.	event	Event log.	virus	Antivirus log.	webfilter	Web filter log.	attack	Attack log.	spam	Antispam log.	anomaly	Anomaly log.	voip	VoIP log.	dlp	DLP log.	app-ctrl	Application control log.	waf	Web application firewall log.	dns	DNS detail log.	ssh	SSH log.	ssl	SSL log.	file-filter	File filter log.	icap	ICAP log.			
	Option	Description																																				
	traffic	Traffic log.																																				
	event	Event log.																																				
	virus	Antivirus log.																																				
	webfilter	Web filter log.																																				
	attack	Attack log.																																				
	spam	Antispam log.																																				
	anomaly	Anomaly log.																																				
	voip	VoIP log.																																				
	dlp	DLP log.																																				
	app-ctrl	Application control log.																																				
	waf	Web application firewall log.																																				
	dns	DNS detail log.																																				
	ssh	SSH log.																																				
	ssl	SSL log.																																				
	file-filter	File filter log.																																				
icap	ICAP log.																																					
filter	Free style filter string.	string	Maximum length: 1023																																			
filter-type	Include/exclude logs that match the filter.	option	-	include																																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>include</td><td>Include logs that match the filter.</td></tr><tr><td>exclude</td><td>Exclude logs that match the filter.</td></tr></table>	Option	Description	include	Include logs that match the filter.	exclude	Exclude logs that match the filter.																															
	Option	Description																																				
	include	Include logs that match the filter.																																				
exclude	Exclude logs that match the filter.																																					

config log syslogd override-filter

Override filters for remote system server.

```
config log syslogd override-filter
  Description: Override filters for remote system server.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]
  set sniffer-traffic [enable|disable]
  set ztna-traffic [enable|disable]
  set http-transaction [enable|disable]
  set anomaly [enable|disable]
  set voip [enable|disable]
  config free-style
    Description: Free style filters.
    edit <id>
      set category [traffic|event|...]
      set filter {string}
      set filter-type [include|exclude]
    next
  end
end
```

config log syslogd override-filter

Parameter	Description	Type	Size	Default
severity	Lowest severity level to log.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		
forward-traffic	Enable/disable forward traffic logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable multicast traffic logging.		
	<i>disable</i>	Disable multicast traffic logging.		
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable sniffer traffic logging.		
	<i>disable</i>	Disable sniffer traffic logging.		
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	<i>traffic</i>	Traffic log.		
	<i>event</i>	Event log.		
	<i>virus</i>	Antivirus log.		
	<i>webfilter</i>	Web filter log.		
	<i>attack</i>	Attack log.		
	<i>spam</i>	Antispam log.		
	<i>anomaly</i>	Anomaly log.		
	<i>voip</i>	VoIP log.		
	<i>dlp</i>	DLP log.		
	<i>app-ctrl</i>	Application control log.		
	<i>waf</i>	Web application firewall log.		
	<i>dns</i>	DNS detail log.		
	<i>ssh</i>	SSH log.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>ssl</i>	SSL log.		
	<i>file-filter</i>	File filter log.		
	<i>icap</i>	ICAP log.		
filter	Free style filter string.	string	Maximum length: 1023	
filter-type	Include/exclude logs that match the filter.	option	-	include
	Option	Description		
	<i>include</i>	Include logs that match the filter.		
	<i>exclude</i>	Exclude logs that match the filter.		

config log syslogd override-setting

Override settings for remote syslog server.

```

config log syslogd override-setting
    Description: Override settings for remote syslog server.
    set status [enable|disable]
    set server {string}
    set mode [udp|legacy-reliable|...]
    set port {integer}
    set facility [kernel|user|...]
    set source-ip {string}
    set format [default|csv|...]
    set priority [default|low]
    set max-log-rate {integer}
    set enc-algorithm [high-medium|high|...]
    set ssl-min-proto-version [default|SSLv3|...]
    set certificate {string}
    config custom-field-name
        Description: Custom field name for CEF format logging.
        edit <id>
            set name {string}
            set custom {string}
        next
    end
    set interface-select-method [auto|specify]
    set interface {string}
    config log-templates
        Description: Custom log templates.
        edit <id>
            set category [traffic|event|...]

```

```

        set empty-value-indicator {string}
        set template {string}
    next
end
end

```

config log syslogd override-setting

Parameter	Description	Type	Size	Default												
status	Enable/disable remote syslog logging.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Log to remote syslog server.</td></tr><tr><td><i>disable</i></td><td>Do not log to remote syslog server.</td></tr></table>	Option	Description	<i>enable</i>	Log to remote syslog server.	<i>disable</i>	Do not log to remote syslog server.									
Option	Description															
<i>enable</i>	Log to remote syslog server.															
<i>disable</i>	Do not log to remote syslog server.															
server	Address of remote syslog server.	string	Maximum length: 127													
mode	Remote syslog logging over UDP/Reliable TCP.	option	-	udp												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>udp</i></td><td>Enable syslogging over UDP.</td></tr><tr><td><i>legacy-reliable</i></td><td>Enable legacy reliable syslogging by RFC3195 (Reliable Delivery for Syslog).</td></tr><tr><td><i>reliable</i></td><td>Enable reliable syslogging by RFC6587 (Transmission of Syslog Messages over TCP).</td></tr></table>	Option	Description	<i>udp</i>	Enable syslogging over UDP.	<i>legacy-reliable</i>	Enable legacy reliable syslogging by RFC3195 (Reliable Delivery for Syslog).	<i>reliable</i>	Enable reliable syslogging by RFC6587 (Transmission of Syslog Messages over TCP).							
Option	Description															
<i>udp</i>	Enable syslogging over UDP.															
<i>legacy-reliable</i>	Enable legacy reliable syslogging by RFC3195 (Reliable Delivery for Syslog).															
<i>reliable</i>	Enable reliable syslogging by RFC6587 (Transmission of Syslog Messages over TCP).															
port	Server listen port.	integer	Minimum value: 0 Maximum value: 65535	514												
facility	Remote syslog facility.	option	-	local7												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>kernel</i></td><td>Kernel messages.</td></tr><tr><td><i>user</i></td><td>Random user-level messages.</td></tr><tr><td><i>mail</i></td><td>Mail system.</td></tr><tr><td><i>daemon</i></td><td>System daemons.</td></tr><tr><td><i>auth</i></td><td>Security/authorization messages.</td></tr></table>	Option	Description	<i>kernel</i>	Kernel messages.	<i>user</i>	Random user-level messages.	<i>mail</i>	Mail system.	<i>daemon</i>	System daemons.	<i>auth</i>	Security/authorization messages.			
Option	Description															
<i>kernel</i>	Kernel messages.															
<i>user</i>	Random user-level messages.															
<i>mail</i>	Mail system.															
<i>daemon</i>	System daemons.															
<i>auth</i>	Security/authorization messages.															

Parameter	Description	Type	Size	Default																																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>syslog</i></td><td>Messages generated internally by syslog.</td></tr><tr><td><i>lpr</i></td><td>Line printer subsystem.</td></tr><tr><td><i>news</i></td><td>Network news subsystem.</td></tr><tr><td><i>uucp</i></td><td>Network news subsystem.</td></tr><tr><td><i>cron</i></td><td>Clock daemon.</td></tr><tr><td><i>authpriv</i></td><td>Security/authorization messages (private).</td></tr><tr><td><i>ftp</i></td><td>FTP daemon.</td></tr><tr><td><i>ntp</i></td><td>NTP daemon.</td></tr><tr><td><i>audit</i></td><td>Log audit.</td></tr><tr><td><i>alert</i></td><td>Log alert.</td></tr><tr><td><i>clock</i></td><td>Clock daemon.</td></tr><tr><td><i>local0</i></td><td>Reserved for local use.</td></tr><tr><td><i>local1</i></td><td>Reserved for local use.</td></tr><tr><td><i>local2</i></td><td>Reserved for local use.</td></tr><tr><td><i>local3</i></td><td>Reserved for local use.</td></tr><tr><td><i>local4</i></td><td>Reserved for local use.</td></tr><tr><td><i>local5</i></td><td>Reserved for local use.</td></tr><tr><td><i>local6</i></td><td>Reserved for local use.</td></tr><tr><td><i>local7</i></td><td>Reserved for local use.</td></tr></table>	Option	Description	<i>syslog</i>	Messages generated internally by syslog.	<i>lpr</i>	Line printer subsystem.	<i>news</i>	Network news subsystem.	<i>uucp</i>	Network news subsystem.	<i>cron</i>	Clock daemon.	<i>authpriv</i>	Security/authorization messages (private).	<i>ftp</i>	FTP daemon.	<i>ntp</i>	NTP daemon.	<i>audit</i>	Log audit.	<i>alert</i>	Log alert.	<i>clock</i>	Clock daemon.	<i>local0</i>	Reserved for local use.	<i>local1</i>	Reserved for local use.	<i>local2</i>	Reserved for local use.	<i>local3</i>	Reserved for local use.	<i>local4</i>	Reserved for local use.	<i>local5</i>	Reserved for local use.	<i>local6</i>	Reserved for local use.	<i>local7</i>	Reserved for local use.			
	Option	Description																																										
	<i>syslog</i>	Messages generated internally by syslog.																																										
	<i>lpr</i>	Line printer subsystem.																																										
	<i>news</i>	Network news subsystem.																																										
	<i>uucp</i>	Network news subsystem.																																										
	<i>cron</i>	Clock daemon.																																										
	<i>authpriv</i>	Security/authorization messages (private).																																										
	<i>ftp</i>	FTP daemon.																																										
	<i>ntp</i>	NTP daemon.																																										
	<i>audit</i>	Log audit.																																										
	<i>alert</i>	Log alert.																																										
	<i>clock</i>	Clock daemon.																																										
	<i>local0</i>	Reserved for local use.																																										
	<i>local1</i>	Reserved for local use.																																										
	<i>local2</i>	Reserved for local use.																																										
	<i>local3</i>	Reserved for local use.																																										
	<i>local4</i>	Reserved for local use.																																										
	<i>local5</i>	Reserved for local use.																																										
	<i>local6</i>	Reserved for local use.																																										
<i>local7</i>	Reserved for local use.																																											
source-ip	Source IP address of syslog.	string	Maximum length: 63																																									
format	Log format.	option	-	default																																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Syslog format.</td></tr><tr><td><i>csv</i></td><td>CSV (Comma Separated Values) format.</td></tr><tr><td><i>cef</i></td><td>CEF (Common Event Format) format.</td></tr><tr><td><i>rfc5424</i></td><td>Syslog RFC5424 format.</td></tr><tr><td><i>json</i></td><td>JSON (JavaScript Object Notation) format.</td></tr><tr><td><i>custom</i></td><td>Custom format.</td></tr></table>	Option	Description	<i>default</i>	Syslog format.	<i>csv</i>	CSV (Comma Separated Values) format.	<i>cef</i>	CEF (Common Event Format) format.	<i>rfc5424</i>	Syslog RFC5424 format.	<i>json</i>	JSON (JavaScript Object Notation) format.	<i>custom</i>	Custom format.																													
	Option	Description																																										
	<i>default</i>	Syslog format.																																										
	<i>csv</i>	CSV (Comma Separated Values) format.																																										
	<i>cef</i>	CEF (Common Event Format) format.																																										
	<i>rfc5424</i>	Syslog RFC5424 format.																																										
	<i>json</i>	JSON (JavaScript Object Notation) format.																																										
<i>custom</i>	Custom format.																																											

Parameter	Description	Type	Size	Default												
priority	Set log transmission priority.	option	-	default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>default</td><td>Set Syslog transmission priority to default.</td></tr><tr><td>low</td><td>Set Syslog transmission priority to low.</td></tr></table>	Option	Description	default	Set Syslog transmission priority to default.	low	Set Syslog transmission priority to low.									
Option	Description															
default	Set Syslog transmission priority to default.															
low	Set Syslog transmission priority to low.															
max-log-rate	Syslog maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0												
enc-algorithm	Enable/disable reliable syslogging with TLS encryption.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>high-medium</td><td>SSL communication with high and medium encryption algorithms.</td></tr><tr><td>high</td><td>SSL communication with high encryption algorithms.</td></tr><tr><td>low</td><td>SSL communication with low encryption algorithms.</td></tr><tr><td>disable</td><td>Disable SSL communication.</td></tr></table>	Option	Description	high-medium	SSL communication with high and medium encryption algorithms.	high	SSL communication with high encryption algorithms.	low	SSL communication with low encryption algorithms.	disable	Disable SSL communication.					
Option	Description															
high-medium	SSL communication with high and medium encryption algorithms.															
high	SSL communication with high encryption algorithms.															
low	SSL communication with low encryption algorithms.															
disable	Disable SSL communication.															
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>default</td><td>Follow system global setting.</td></tr><tr><td>SSLv3</td><td>SSLv3.</td></tr><tr><td>TLSv1</td><td>TLSv1.</td></tr><tr><td>TLSv1-1</td><td>TLSv1.1.</td></tr><tr><td>TLSv1-2</td><td>TLSv1.2.</td></tr></table>	Option	Description	default	Follow system global setting.	SSLv3	SSLv3.	TLSv1	TLSv1.	TLSv1-1	TLSv1.1.	TLSv1-2	TLSv1.2.			
Option	Description															
default	Follow system global setting.															
SSLv3	SSLv3.															
TLSv1	TLSv1.															
TLSv1-1	TLSv1.1.															
TLSv1-2	TLSv1.2.															
certificate	Certificate used to communicate with Syslog server.	string	Maximum length: 35													
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>auto</td><td>Set outgoing interface automatically.</td></tr></table>	Option	Description	auto	Set outgoing interface automatically.											
Option	Description															
auto	Set outgoing interface automatically.															

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>specify</i>	Set outgoing interface manually.		
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	

config custom-field-name

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 255	0
name	Field name [A-Za-z0-9_].	string	Maximum length: 35	
custom	Field custom name [A-Za-z0-9_].	string	Maximum length: 35	

config log-templates

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	<i>traffic</i>	Traffic log.		
	<i>event</i>	Event log.		
	<i>virus</i>	Antivirus log.		
	<i>webfilter</i>	Web filter log.		
	<i>attack</i>	Attack log.		
	<i>spam</i>	Antispam log.		
	<i>anomaly</i>	Anomaly log.		
	<i>voip</i>	VoIP log.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>dlp</i>	DLP log.		
	<i>app-ctrl</i>	Application control log.		
	<i>waf</i>	Web application firewall log.		
	<i>dns</i>	DNS detail log.		
	<i>ssh</i>	SSH log.		
	<i>ssl</i>	SSL log.		
	<i>file-filter</i>	File filter log.		
	<i>icap</i>	ICAP log.		
empty-value-indicator	A character to indicate log field is empty.	string	Maximum length: 1	
template	Log template string.	string	Maximum length: 2047	

config log syslogd setting

Global settings for remote syslog server.

```

config log syslogd setting
    Description: Global settings for remote syslog server.
    set status [enable|disable]
    set server {string}
    set mode [udp|legacy-reliable|...]
    set port {integer}
    set facility [kernel|user|...]
    set source-ip {string}
    set format [default|csv|...]
    set priority [default|low]
    set max-log-rate {integer}
    set enc-algorithm [high-medium|high|...]
    set ssl-min-proto-version [default|SSLv3|...]
    set certificate {string}
    config custom-field-name
        Description: Custom field name for CEF format logging.
        edit <id>
            set name {string}
            set custom {string}
        next
    end
    set interface-select-method [auto|specify]

```

```

set interface {string}
config log-templates
  Description: Custom log templates.
  edit <id>
    set category [traffic|event|...]
    set empty-value-indicator {string}
    set template {string}
  next
end
end

```

config log syslogd setting

Parameter	Description	Type	Size	Default
status	Enable/disable remote syslog logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Log to remote syslog server.		
	<i>disable</i>	Do not log to remote syslog server.		
server	Address of remote syslog server.	string	Maximum length: 127	
mode	Remote syslog logging over UDP/Reliable TCP.	option	-	udp
	Option	Description		
	<i>udp</i>	Enable syslogging over UDP.		
	<i>legacy-reliable</i>	Enable legacy reliable syslogging by RFC3195 (Reliable Delivery for Syslog).		
	<i>reliable</i>	Enable reliable syslogging by RFC6587 (Transmission of Syslog Messages over TCP).		
port	Server listen port.	integer	Minimum value: 0 Maximum value: 65535	514
facility	Remote syslog facility.	option	-	local7
	Option	Description		
	<i>kernel</i>	Kernel messages.		
	<i>user</i>	Random user-level messages.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>mail</i>	Mail system.		
	<i>daemon</i>	System daemons.		
	<i>auth</i>	Security/authorization messages.		
	<i>syslog</i>	Messages generated internally by syslog.		
	<i>lpr</i>	Line printer subsystem.		
	<i>news</i>	Network news subsystem.		
	<i>uucp</i>	Network news subsystem.		
	<i>cron</i>	Clock daemon.		
	<i>authpriv</i>	Security/authorization messages (private).		
	<i>ftp</i>	FTP daemon.		
	<i>ntp</i>	NTP daemon.		
	<i>audit</i>	Log audit.		
	<i>alert</i>	Log alert.		
	<i>clock</i>	Clock daemon.		
	<i>local0</i>	Reserved for local use.		
	<i>local1</i>	Reserved for local use.		
	<i>local2</i>	Reserved for local use.		
	<i>local3</i>	Reserved for local use.		
	<i>local4</i>	Reserved for local use.		
	<i>local5</i>	Reserved for local use.		
<i>local6</i>	Reserved for local use.			
<i>local7</i>	Reserved for local use.			
source-ip	Source IP address of syslog.	string	Maximum length: 63	
format	Log format.	option	-	default
	Option	Description		
	<i>default</i>	Syslog format.		
	<i>csv</i>	CSV (Comma Separated Values) format.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>cef</i>	CEF (Common Event Format) format.		
	<i>rfc5424</i>	Syslog RFC5424 format.		
	<i>json</i>	JSON (JavaScript Object Notation) format.		
	<i>custom</i>	Custom format.		
priority	Set log transmission priority.	option	-	default
	Option	Description		
	<i>default</i>	Set Syslog transmission priority to default.		
	<i>low</i>	Set Syslog transmission priority to low.		
max-log-rate	Syslog maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0
enc-algorithm	Enable/disable reliable syslogging with TLS encryption.	option	-	disable
	Option	Description		
	<i>high-medium</i>	SSL communication with high and medium encryption algorithms.		
	<i>high</i>	SSL communication with high encryption algorithms.		
	<i>low</i>	SSL communication with low encryption algorithms.		
	<i>disable</i>	Disable SSL communication.		
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default
	Option	Description		
	<i>default</i>	Follow system global setting.		
	<i>SSLv3</i>	SSLv3.		
	<i>TLSv1</i>	TLSv1.		
	<i>TLSv1-1</i>	TLSv1.1.		
	<i>TLSv1-2</i>	TLSv1.2.		

Parameter	Description	Type	Size	Default						
certificate	Certificate used to communicate with Syslog server.	string	Maximum length: 35							
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Set outgoing interface automatically.</td></tr><tr><td><i>specify</i></td><td>Set outgoing interface manually.</td></tr></table>				Option	Description	<i>auto</i>	Set outgoing interface automatically.	<i>specify</i>	Set outgoing interface manually.
Option	Description									
<i>auto</i>	Set outgoing interface automatically.									
<i>specify</i>	Set outgoing interface manually.									
interface	Specify outgoing interface to reach server.	string	Maximum length: 15							

config custom-field-name

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 255	0
name	Field name [A-Za-z0-9_].	string	Maximum length: 35	
custom	Field custom name [A-Za-z0-9_].	string	Maximum length: 35	

config log-templates

Parameter	Description	Type	Size	Default								
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0								
category	Log category.	option	-	traffic								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>traffic</td><td>Traffic log.</td></tr><tr><td>event</td><td>Event log.</td></tr><tr><td>virus</td><td>Antivirus log.</td></tr></table>				Option	Description	traffic	Traffic log.	event	Event log.	virus	Antivirus log.
	Option	Description										
	traffic	Traffic log.										
	event	Event log.										
virus	Antivirus log.											

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>webfilter</i>	Web filter log.		
	<i>attack</i>	Attack log.		
	<i>spam</i>	Antispam log.		
	<i>anomaly</i>	Anomaly log.		
	<i>voip</i>	VoIP log.		
	<i>dlp</i>	DLP log.		
	<i>app-ctrl</i>	Application control log.		
	<i>waf</i>	Web application firewall log.		
	<i>dns</i>	DNS detail log.		
	<i>ssh</i>	SSH log.		
	<i>ssl</i>	SSL log.		
	<i>file-filter</i>	File filter log.		
	<i>icap</i>	ICAP log.		
empty-value-indicator	A character to indicate log field is empty.	string	Maximum length: 1	
template	Log template string.	string	Maximum length: 2047	

config log syslogd2 filter

Filters for remote system server.

```

config log syslogd2 filter
    Description: Filters for remote system server.
    set severity [emergency|alert|...]
    set forward-traffic [enable|disable]
    set local-traffic [enable|disable]
    set multicast-traffic [enable|disable]
    set sniffer-traffic [enable|disable]
    set ztna-traffic [enable|disable]
    set http-transaction [enable|disable]
    set anomaly [enable|disable]
    set voip [enable|disable]
config free-style
    Description: Free style filters.
    edit <id>

```



```

        set category [traffic|event|...]
        set filter {string}
        set filter-type [include|exclude]
    next
end
end

```

config log syslogd2 filter

Parameter	Description	Type	Size	Default
severity	Lowest severity level to log.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		
forward-traffic	Enable/disable forward traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable multicast traffic logging.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable multicast traffic logging.		
	<i>enable</i>	Enable sniffer traffic logging.		
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable sniffer traffic logging.		
	<i>disable</i>	Disable sniffer traffic logging.		
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option Description			
	traffic	Traffic log.		
	event	Event log.		
	virus	Antivirus log.		
	webfilter	Web filter log.		
	attack	Attack log.		
	spam	Antispam log.		
	anomaly	Anomaly log.		
	voip	VoIP log.		
	dlp	DLP log.		
	app-ctrl	Application control log.		
	waf	Web application firewall log.		
	dns	DNS detail log.		
	ssh	SSH log.		
	ssl	SSL log.		
	file-filter	File filter log.		
	icap	ICAP log.		
filter	Free style filter string.	string	Maximum length: 1023	
filter-type	Include/exclude logs that match the filter.	option	-	include
	Option Description			
	include	Include logs that match the filter.		
	exclude	Exclude logs that match the filter.		

config log syslogd2 override-filter

Override filters for remote system server.

```
config log syslogd2 override-filter
  Description: Override filters for remote system server.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]
  set sniffer-traffic [enable|disable]
  set ztna-traffic [enable|disable]
  set http-transaction [enable|disable]
  set anomaly [enable|disable]
  set voip [enable|disable]
  config free-style
    Description: Free style filters.
    edit <id>
      set category [traffic|event|...]
      set filter {string}
      set filter-type [include|exclude]
    next
  end
end
```

config log syslogd2 override-filter

Parameter	Description	Type	Size	Default
severity	Lowest severity level to log.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		
forward-traffic	Enable/disable forward traffic logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable multicast traffic logging.		
	<i>disable</i>	Disable multicast traffic logging.		
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable sniffer traffic logging.		
	<i>disable</i>	Disable sniffer traffic logging.		
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	<i>traffic</i>	Traffic log.		
	<i>event</i>	Event log.		
	<i>virus</i>	Antivirus log.		
	<i>webfilter</i>	Web filter log.		
	<i>attack</i>	Attack log.		
	<i>spam</i>	Antispam log.		
	<i>anomaly</i>	Anomaly log.		
	<i>voip</i>	VoIP log.		
	<i>dlp</i>	DLP log.		
	<i>app-ctrl</i>	Application control log.		
	<i>waf</i>	Web application firewall log.		
	<i>dns</i>	DNS detail log.		
	<i>ssh</i>	SSH log.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>ssl</i>	SSL log.		
	<i>file-filter</i>	File filter log.		
	<i>icap</i>	ICAP log.		
filter	Free style filter string.	string	Maximum length: 1023	
filter-type	Include/exclude logs that match the filter.	option	-	include
	Option	Description		
	<i>include</i>	Include logs that match the filter.		
	<i>exclude</i>	Exclude logs that match the filter.		

config log syslogd2 override-setting

Override settings for remote syslog server.

```

config log syslogd2 override-setting
    Description: Override settings for remote syslog server.
    set status [enable|disable]
    set server {string}
    set mode [udp|legacy-reliable|...]
    set port {integer}
    set facility [kernel|user|...]
    set source-ip {string}
    set format [default|csv|...]
    set priority [default|low]
    set max-log-rate {integer}
    set enc-algorithm [high-medium|high|...]
    set ssl-min-proto-version [default|SSLv3|...]
    set certificate {string}
    config custom-field-name
        Description: Custom field name for CEF format logging.
        edit <id>
            set name {string}
            set custom {string}
        next
    end
    set interface-select-method [auto|specify]
    set interface {string}
    config log-templates
        Description: Custom log templates.
        edit <id>
            set category [traffic|event|...]

```

```

        set empty-value-indicator {string}
        set template {string}
    next
end
end

```

config log syslogd2 override-setting

Parameter	Description	Type	Size	Default												
status	Enable/disable remote syslog logging.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Log to remote syslog server.</td></tr><tr><td><i>disable</i></td><td>Do not log to remote syslog server.</td></tr></table>	Option	Description	<i>enable</i>	Log to remote syslog server.	<i>disable</i>	Do not log to remote syslog server.									
Option	Description															
<i>enable</i>	Log to remote syslog server.															
<i>disable</i>	Do not log to remote syslog server.															
server	Address of remote syslog server.	string	Maximum length: 127													
mode	Remote syslog logging over UDP/Reliable TCP.	option	-	udp												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>udp</i></td><td>Enable syslogging over UDP.</td></tr><tr><td><i>legacy-reliable</i></td><td>Enable legacy reliable syslogging by RFC3195 (Reliable Delivery for Syslog).</td></tr><tr><td><i>reliable</i></td><td>Enable reliable syslogging by RFC6587 (Transmission of Syslog Messages over TCP).</td></tr></table>	Option	Description	<i>udp</i>	Enable syslogging over UDP.	<i>legacy-reliable</i>	Enable legacy reliable syslogging by RFC3195 (Reliable Delivery for Syslog).	<i>reliable</i>	Enable reliable syslogging by RFC6587 (Transmission of Syslog Messages over TCP).							
Option	Description															
<i>udp</i>	Enable syslogging over UDP.															
<i>legacy-reliable</i>	Enable legacy reliable syslogging by RFC3195 (Reliable Delivery for Syslog).															
<i>reliable</i>	Enable reliable syslogging by RFC6587 (Transmission of Syslog Messages over TCP).															
port	Server listen port.	integer	Minimum value: 0 Maximum value: 65535	514												
facility	Remote syslog facility.	option	-	local7												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>kernel</i></td><td>Kernel messages.</td></tr><tr><td><i>user</i></td><td>Random user-level messages.</td></tr><tr><td><i>mail</i></td><td>Mail system.</td></tr><tr><td><i>daemon</i></td><td>System daemons.</td></tr><tr><td><i>auth</i></td><td>Security/authorization messages.</td></tr></table>	Option	Description	<i>kernel</i>	Kernel messages.	<i>user</i>	Random user-level messages.	<i>mail</i>	Mail system.	<i>daemon</i>	System daemons.	<i>auth</i>	Security/authorization messages.			
Option	Description															
<i>kernel</i>	Kernel messages.															
<i>user</i>	Random user-level messages.															
<i>mail</i>	Mail system.															
<i>daemon</i>	System daemons.															
<i>auth</i>	Security/authorization messages.															

Parameter	Description	Type	Size	Default																																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>syslog</i></td><td>Messages generated internally by syslog.</td></tr><tr><td><i>lpr</i></td><td>Line printer subsystem.</td></tr><tr><td><i>news</i></td><td>Network news subsystem.</td></tr><tr><td><i>uucp</i></td><td>Network news subsystem.</td></tr><tr><td><i>cron</i></td><td>Clock daemon.</td></tr><tr><td><i>authpriv</i></td><td>Security/authorization messages (private).</td></tr><tr><td><i>ftp</i></td><td>FTP daemon.</td></tr><tr><td><i>ntp</i></td><td>NTP daemon.</td></tr><tr><td><i>audit</i></td><td>Log audit.</td></tr><tr><td><i>alert</i></td><td>Log alert.</td></tr><tr><td><i>clock</i></td><td>Clock daemon.</td></tr><tr><td><i>local0</i></td><td>Reserved for local use.</td></tr><tr><td><i>local1</i></td><td>Reserved for local use.</td></tr><tr><td><i>local2</i></td><td>Reserved for local use.</td></tr><tr><td><i>local3</i></td><td>Reserved for local use.</td></tr><tr><td><i>local4</i></td><td>Reserved for local use.</td></tr><tr><td><i>local5</i></td><td>Reserved for local use.</td></tr><tr><td><i>local6</i></td><td>Reserved for local use.</td></tr><tr><td><i>local7</i></td><td>Reserved for local use.</td></tr></table>	Option	Description	<i>syslog</i>	Messages generated internally by syslog.	<i>lpr</i>	Line printer subsystem.	<i>news</i>	Network news subsystem.	<i>uucp</i>	Network news subsystem.	<i>cron</i>	Clock daemon.	<i>authpriv</i>	Security/authorization messages (private).	<i>ftp</i>	FTP daemon.	<i>ntp</i>	NTP daemon.	<i>audit</i>	Log audit.	<i>alert</i>	Log alert.	<i>clock</i>	Clock daemon.	<i>local0</i>	Reserved for local use.	<i>local1</i>	Reserved for local use.	<i>local2</i>	Reserved for local use.	<i>local3</i>	Reserved for local use.	<i>local4</i>	Reserved for local use.	<i>local5</i>	Reserved for local use.	<i>local6</i>	Reserved for local use.	<i>local7</i>	Reserved for local use.			
	Option	Description																																										
	<i>syslog</i>	Messages generated internally by syslog.																																										
	<i>lpr</i>	Line printer subsystem.																																										
	<i>news</i>	Network news subsystem.																																										
	<i>uucp</i>	Network news subsystem.																																										
	<i>cron</i>	Clock daemon.																																										
	<i>authpriv</i>	Security/authorization messages (private).																																										
	<i>ftp</i>	FTP daemon.																																										
	<i>ntp</i>	NTP daemon.																																										
	<i>audit</i>	Log audit.																																										
	<i>alert</i>	Log alert.																																										
	<i>clock</i>	Clock daemon.																																										
	<i>local0</i>	Reserved for local use.																																										
	<i>local1</i>	Reserved for local use.																																										
	<i>local2</i>	Reserved for local use.																																										
	<i>local3</i>	Reserved for local use.																																										
	<i>local4</i>	Reserved for local use.																																										
	<i>local5</i>	Reserved for local use.																																										
	<i>local6</i>	Reserved for local use.																																										
<i>local7</i>	Reserved for local use.																																											
source-ip	Source IP address of syslog.	string	Maximum length: 63																																									
format	Log format.	option	-	default																																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Syslog format.</td></tr><tr><td><i>csv</i></td><td>CSV (Comma Separated Values) format.</td></tr><tr><td><i>cef</i></td><td>CEF (Common Event Format) format.</td></tr><tr><td><i>rfc5424</i></td><td>Syslog RFC5424 format.</td></tr><tr><td><i>json</i></td><td>JSON (JavaScript Object Notation) format.</td></tr><tr><td><i>custom</i></td><td>Custom format.</td></tr></table>	Option	Description	<i>default</i>	Syslog format.	<i>csv</i>	CSV (Comma Separated Values) format.	<i>cef</i>	CEF (Common Event Format) format.	<i>rfc5424</i>	Syslog RFC5424 format.	<i>json</i>	JSON (JavaScript Object Notation) format.	<i>custom</i>	Custom format.																													
	Option	Description																																										
	<i>default</i>	Syslog format.																																										
	<i>csv</i>	CSV (Comma Separated Values) format.																																										
	<i>cef</i>	CEF (Common Event Format) format.																																										
	<i>rfc5424</i>	Syslog RFC5424 format.																																										
	<i>json</i>	JSON (JavaScript Object Notation) format.																																										
<i>custom</i>	Custom format.																																											

Parameter	Description	Type	Size	Default												
priority	Set log transmission priority.	option	-	default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>default</td><td>Set Syslog transmission priority to default.</td></tr><tr><td>low</td><td>Set Syslog transmission priority to low.</td></tr></table>	Option	Description	default	Set Syslog transmission priority to default.	low	Set Syslog transmission priority to low.									
	Option	Description														
	default	Set Syslog transmission priority to default.														
low	Set Syslog transmission priority to low.															
max-log-rate	Syslog maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0												
enc-algorithm	Enable/disable reliable syslogging with TLS encryption.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>high-medium</td><td>SSL communication with high and medium encryption algorithms.</td></tr><tr><td>high</td><td>SSL communication with high encryption algorithms.</td></tr><tr><td>low</td><td>SSL communication with low encryption algorithms.</td></tr><tr><td>disable</td><td>Disable SSL communication.</td></tr></table>	Option	Description	high-medium	SSL communication with high and medium encryption algorithms.	high	SSL communication with high encryption algorithms.	low	SSL communication with low encryption algorithms.	disable	Disable SSL communication.					
	Option	Description														
	high-medium	SSL communication with high and medium encryption algorithms.														
	high	SSL communication with high encryption algorithms.														
	low	SSL communication with low encryption algorithms.														
disable	Disable SSL communication.															
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>default</td><td>Follow system global setting.</td></tr><tr><td>SSLv3</td><td>SSLv3.</td></tr><tr><td>TLSv1</td><td>TLSv1.</td></tr><tr><td>TLSv1-1</td><td>TLSv1.1.</td></tr><tr><td>TLSv1-2</td><td>TLSv1.2.</td></tr></table>	Option	Description	default	Follow system global setting.	SSLv3	SSLv3.	TLSv1	TLSv1.	TLSv1-1	TLSv1.1.	TLSv1-2	TLSv1.2.			
	Option	Description														
	default	Follow system global setting.														
	SSLv3	SSLv3.														
	TLSv1	TLSv1.														
	TLSv1-1	TLSv1.1.														
TLSv1-2	TLSv1.2.															
certificate	Certificate used to communicate with Syslog server.	string	Maximum length: 35													
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>auto</td><td>Set outgoing interface automatically.</td></tr></table>	Option	Description	auto	Set outgoing interface automatically.											
	Option	Description														
auto	Set outgoing interface automatically.															

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>specify</i>	Set outgoing interface manually.		
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	

config custom-field-name

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 255	0
name	Field name [A-Za-z0-9_].	string	Maximum length: 35	
custom	Field custom name [A-Za-z0-9_].	string	Maximum length: 35	

config log-templates

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	<i>traffic</i>	Traffic log.		
	<i>event</i>	Event log.		
	<i>virus</i>	Antivirus log.		
	<i>webfilter</i>	Web filter log.		
	<i>attack</i>	Attack log.		
	<i>spam</i>	Antispam log.		
	<i>anomaly</i>	Anomaly log.		
	<i>voip</i>	VoIP log.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>dlp</i>	DLP log.		
	<i>app-ctrl</i>	Application control log.		
	<i>waf</i>	Web application firewall log.		
	<i>dns</i>	DNS detail log.		
	<i>ssh</i>	SSH log.		
	<i>ssl</i>	SSL log.		
	<i>file-filter</i>	File filter log.		
	<i>icap</i>	ICAP log.		
empty-value-indicator	A character to indicate log field is empty.	string	Maximum length: 1	
template	Log template string.	string	Maximum length: 2047	

config log syslogd2 setting

Global settings for remote syslog server.

```

config log syslogd2 setting
    Description: Global settings for remote syslog server.
    set status [enable|disable]
    set server {string}
    set mode [udp|legacy-reliable|...]
    set port {integer}
    set facility [kernel|user|...]
    set source-ip {string}
    set format [default|csv|...]
    set priority [default|low]
    set max-log-rate {integer}
    set enc-algorithm [high-medium|high|...]
    set ssl-min-proto-version [default|SSLv3|...]
    set certificate {string}
    config custom-field-name
        Description: Custom field name for CEF format logging.
        edit <id>
            set name {string}
            set custom {string}
        next
    end
    set interface-select-method [auto|specify]

```

```

set interface {string}
config log-templates
    Description: Custom log templates.
    edit <id>
        set category [traffic|event|...]
        set empty-value-indicator {string}
        set template {string}
    next
end
end
end

```

config log syslogd2 setting

Parameter	Description	Type	Size	Default
status	Enable/disable remote syslog logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Log to remote syslog server.		
	<i>disable</i>	Do not log to remote syslog server.		
server	Address of remote syslog server.	string	Maximum length: 127	
mode	Remote syslog logging over UDP/Reliable TCP.	option	-	udp
	Option	Description		
	<i>udp</i>	Enable syslogging over UDP.		
	<i>legacy-reliable</i>	Enable legacy reliable syslogging by RFC3195 (Reliable Delivery for Syslog).		
	<i>reliable</i>	Enable reliable syslogging by RFC6587 (Transmission of Syslog Messages over TCP).		
port	Server listen port.	integer	Minimum value: 0 Maximum value: 65535	514
facility	Remote syslog facility.	option	-	local7
	Option	Description		
	<i>kernel</i>	Kernel messages.		
	<i>user</i>	Random user-level messages.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>mail</i>	Mail system.		
	<i>daemon</i>	System daemons.		
	<i>auth</i>	Security/authorization messages.		
	<i>syslog</i>	Messages generated internally by syslog.		
	<i>lpr</i>	Line printer subsystem.		
	<i>news</i>	Network news subsystem.		
	<i>uucp</i>	Network news subsystem.		
	<i>cron</i>	Clock daemon.		
	<i>authpriv</i>	Security/authorization messages (private).		
	<i>ftp</i>	FTP daemon.		
	<i>ntp</i>	NTP daemon.		
	<i>audit</i>	Log audit.		
	<i>alert</i>	Log alert.		
	<i>clock</i>	Clock daemon.		
	<i>local0</i>	Reserved for local use.		
	<i>local1</i>	Reserved for local use.		
	<i>local2</i>	Reserved for local use.		
	<i>local3</i>	Reserved for local use.		
	<i>local4</i>	Reserved for local use.		
	<i>local5</i>	Reserved for local use.		
	<i>local6</i>	Reserved for local use.		
	<i>local7</i>	Reserved for local use.		
source-ip	Source IP address of syslog.	string	Maximum length: 63	
format	Log format.	option	-	default
	Option	Description		
	<i>default</i>	Syslog format.		
	<i>csv</i>	CSV (Comma Separated Values) format.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>cef</i>	CEF (Common Event Format) format.		
	<i>rfc5424</i>	Syslog RFC5424 format.		
	<i>json</i>	JSON (JavaScript Object Notation) format.		
	<i>custom</i>	Custom format.		
priority	Set log transmission priority.	option	-	default
	Option	Description		
	<i>default</i>	Set Syslog transmission priority to default.		
	<i>low</i>	Set Syslog transmission priority to low.		
max-log-rate	Syslog maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0
enc-algorithm	Enable/disable reliable syslogging with TLS encryption.	option	-	disable
	Option	Description		
	<i>high-medium</i>	SSL communication with high and medium encryption algorithms.		
	<i>high</i>	SSL communication with high encryption algorithms.		
	<i>low</i>	SSL communication with low encryption algorithms.		
	<i>disable</i>	Disable SSL communication.		
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default
	Option	Description		
	<i>default</i>	Follow system global setting.		
	<i>SSLv3</i>	SSLv3.		
	<i>TLSv1</i>	TLSv1.		
	<i>TLSv1-1</i>	TLSv1.1.		
	<i>TLSv1-2</i>	TLSv1.2.		

Parameter	Description	Type	Size	Default						
certificate	Certificate used to communicate with Syslog server.	string	Maximum length: 35							
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Set outgoing interface automatically.</td></tr><tr><td><i>specify</i></td><td>Set outgoing interface manually.</td></tr></table>				Option	Description	<i>auto</i>	Set outgoing interface automatically.	<i>specify</i>	Set outgoing interface manually.
Option	Description									
<i>auto</i>	Set outgoing interface automatically.									
<i>specify</i>	Set outgoing interface manually.									
interface	Specify outgoing interface to reach server.	string	Maximum length: 15							

config custom-field-name

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 255	0
name	Field name [A-Za-z0-9_].	string	Maximum length: 35	
custom	Field custom name [A-Za-z0-9_].	string	Maximum length: 35	

config log-templates

Parameter	Description	Type	Size	Default								
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0								
category	Log category.	option	-	traffic								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>traffic</td><td>Traffic log.</td></tr><tr><td>event</td><td>Event log.</td></tr><tr><td>virus</td><td>Antivirus log.</td></tr></table>				Option	Description	traffic	Traffic log.	event	Event log.	virus	Antivirus log.
	Option	Description										
	traffic	Traffic log.										
	event	Event log.										
virus	Antivirus log.											

Parameter	Description	Type	Size	Default																												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>webfilter</i></td><td>Web filter log.</td></tr><tr><td><i>attack</i></td><td>Attack log.</td></tr><tr><td><i>spam</i></td><td>Antispam log.</td></tr><tr><td><i>anomaly</i></td><td>Anomaly log.</td></tr><tr><td><i>voip</i></td><td>VoIP log.</td></tr><tr><td><i>dlp</i></td><td>DLP log.</td></tr><tr><td><i>app-ctrl</i></td><td>Application control log.</td></tr><tr><td><i>waf</i></td><td>Web application firewall log.</td></tr><tr><td><i>dns</i></td><td>DNS detail log.</td></tr><tr><td><i>ssh</i></td><td>SSH log.</td></tr><tr><td><i>ssl</i></td><td>SSL log.</td></tr><tr><td><i>file-filter</i></td><td>File filter log.</td></tr><tr><td><i>icap</i></td><td>ICAP log.</td></tr></table>	Option	Description	<i>webfilter</i>	Web filter log.	<i>attack</i>	Attack log.	<i>spam</i>	Antispam log.	<i>anomaly</i>	Anomaly log.	<i>voip</i>	VoIP log.	<i>dlp</i>	DLP log.	<i>app-ctrl</i>	Application control log.	<i>waf</i>	Web application firewall log.	<i>dns</i>	DNS detail log.	<i>ssh</i>	SSH log.	<i>ssl</i>	SSL log.	<i>file-filter</i>	File filter log.	<i>icap</i>	ICAP log.			
	Option	Description																														
	<i>webfilter</i>	Web filter log.																														
	<i>attack</i>	Attack log.																														
	<i>spam</i>	Antispam log.																														
	<i>anomaly</i>	Anomaly log.																														
	<i>voip</i>	VoIP log.																														
	<i>dlp</i>	DLP log.																														
	<i>app-ctrl</i>	Application control log.																														
	<i>waf</i>	Web application firewall log.																														
	<i>dns</i>	DNS detail log.																														
	<i>ssh</i>	SSH log.																														
	<i>ssl</i>	SSL log.																														
	<i>file-filter</i>	File filter log.																														
<i>icap</i>	ICAP log.																															
empty-value-indicator	A character to indicate log field is empty.	string	Maximum length: 1																													
template	Log template string.	string	Maximum length: 2047																													

config log syslogd3 filter

Filters for remote system server.

```
config log syslogd3 filter
    Description: Filters for remote system server.
    set severity [emergency|alert|...]
    set forward-traffic [enable|disable]
    set local-traffic [enable|disable]
    set multicast-traffic [enable|disable]
    set sniffer-traffic [enable|disable]
    set ztna-traffic [enable|disable]
    set http-transaction [enable|disable]
    set anomaly [enable|disable]
    set voip [enable|disable]
config free-style
    Description: Free style filters.
    edit <id>
```

```

        set category [traffic|event|...]
        set filter {string}
        set filter-type [include|exclude]
    next
end
end

```

config log syslogd3 filter

Parameter	Description	Type	Size	Default
severity	Lowest severity level to log.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		
forward-traffic	Enable/disable forward traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable multicast traffic logging.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable multicast traffic logging.		
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable sniffer traffic logging.		
	<i>disable</i>	Disable sniffer traffic logging.		
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	OptionDescription			
	traffic	Traffic log.		
	event	Event log.		
	virus	Antivirus log.		
	webfilter	Web filter log.		
	attack	Attack log.		
	spam	Antispam log.		
	anomaly	Anomaly log.		
	voip	VoIP log.		
	dlp	DLP log.		
	app-ctrl	Application control log.		
	waf	Web application firewall log.		
	dns	DNS detail log.		
	ssh	SSH log.		
	ssl	SSL log.		
	file-filter	File filter log.		
	icap	ICAP log.		
filter	Free style filter string.	string	Maximum length: 1023	
filter-type	Include/exclude logs that match the filter.	option	-	include
	OptionDescription			
	include	Include logs that match the filter.		
	exclude	Exclude logs that match the filter.		

config log syslogd3 override-filter

Override filters for remote system server.

```
config log syslogd3 override-filter
  Description: Override filters for remote system server.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]
  set sniffer-traffic [enable|disable]
  set ztna-traffic [enable|disable]
  set http-transaction [enable|disable]
  set anomaly [enable|disable]
  set voip [enable|disable]
  config free-style
    Description: Free style filters.
    edit <id>
      set category [traffic|event|...]
      set filter {string}
      set filter-type [include|exclude]
    next
  end
end
```

config log syslogd3 override-filter

Parameter	Description	Type	Size	Default
severity	Lowest severity level to log.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		
forward-traffic	Enable/disable forward traffic logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable multicast traffic logging.		
	<i>disable</i>	Disable multicast traffic logging.		
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable sniffer traffic logging.		
	<i>disable</i>	Disable sniffer traffic logging.		
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	<i>traffic</i>	Traffic log.		
	<i>event</i>	Event log.		
	<i>virus</i>	Antivirus log.		
	<i>webfilter</i>	Web filter log.		
	<i>attack</i>	Attack log.		
	<i>spam</i>	Antispam log.		
	<i>anomaly</i>	Anomaly log.		
	<i>voip</i>	VoIP log.		
	<i>dlp</i>	DLP log.		
	<i>app-ctrl</i>	Application control log.		
	<i>waf</i>	Web application firewall log.		
	<i>dns</i>	DNS detail log.		
	<i>ssh</i>	SSH log.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>ssl</i>	SSL log.		
	<i>file-filter</i>	File filter log.		
	<i>icap</i>	ICAP log.		
filter	Free style filter string.	string	Maximum length: 1023	
filter-type	Include/exclude logs that match the filter.	option	-	include
	Option	Description		
	<i>include</i>	Include logs that match the filter.		
	<i>exclude</i>	Exclude logs that match the filter.		

config log syslogd3 override-setting

Override settings for remote syslog server.

```

config log syslogd3 override-setting
    Description: Override settings for remote syslog server.
    set status [enable|disable]
    set server {string}
    set mode [udp|legacy-reliable|...]
    set port {integer}
    set facility [kernel|user|...]
    set source-ip {string}
    set format [default|csv|...]
    set priority [default|low]
    set max-log-rate {integer}
    set enc-algorithm [high-medium|high|...]
    set ssl-min-proto-version [default|SSLv3|...]
    set certificate {string}
    config custom-field-name
        Description: Custom field name for CEF format logging.
        edit <id>
            set name {string}
            set custom {string}
        next
    end
    set interface-select-method [auto|specify]
    set interface {string}
    config log-templates
        Description: Custom log templates.
        edit <id>
            set category [traffic|event|...]

```



```

        set empty-value-indicator {string}
        set template {string}
    next
end
end

```

config log syslogd3 override-setting

Parameter	Description	Type	Size	Default												
status	Enable/disable remote syslog logging.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Log to remote syslog server.</td></tr><tr><td><i>disable</i></td><td>Do not log to remote syslog server.</td></tr></table>	Option	Description	<i>enable</i>	Log to remote syslog server.	<i>disable</i>	Do not log to remote syslog server.									
Option	Description															
<i>enable</i>	Log to remote syslog server.															
<i>disable</i>	Do not log to remote syslog server.															
server	Address of remote syslog server.	string	Maximum length: 127													
mode	Remote syslog logging over UDP/Reliable TCP.	option	-	udp												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>udp</i></td><td>Enable syslogging over UDP.</td></tr><tr><td><i>legacy-reliable</i></td><td>Enable legacy reliable syslogging by RFC3195 (Reliable Delivery for Syslog).</td></tr><tr><td><i>reliable</i></td><td>Enable reliable syslogging by RFC6587 (Transmission of Syslog Messages over TCP).</td></tr></table>	Option	Description	<i>udp</i>	Enable syslogging over UDP.	<i>legacy-reliable</i>	Enable legacy reliable syslogging by RFC3195 (Reliable Delivery for Syslog).	<i>reliable</i>	Enable reliable syslogging by RFC6587 (Transmission of Syslog Messages over TCP).							
Option	Description															
<i>udp</i>	Enable syslogging over UDP.															
<i>legacy-reliable</i>	Enable legacy reliable syslogging by RFC3195 (Reliable Delivery for Syslog).															
<i>reliable</i>	Enable reliable syslogging by RFC6587 (Transmission of Syslog Messages over TCP).															
port	Server listen port.	integer	Minimum value: 0 Maximum value: 65535	514												
facility	Remote syslog facility.	option	-	local7												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>kernel</i></td><td>Kernel messages.</td></tr><tr><td><i>user</i></td><td>Random user-level messages.</td></tr><tr><td><i>mail</i></td><td>Mail system.</td></tr><tr><td><i>daemon</i></td><td>System daemons.</td></tr><tr><td><i>auth</i></td><td>Security/authorization messages.</td></tr></table>	Option	Description	<i>kernel</i>	Kernel messages.	<i>user</i>	Random user-level messages.	<i>mail</i>	Mail system.	<i>daemon</i>	System daemons.	<i>auth</i>	Security/authorization messages.			
Option	Description															
<i>kernel</i>	Kernel messages.															
<i>user</i>	Random user-level messages.															
<i>mail</i>	Mail system.															
<i>daemon</i>	System daemons.															
<i>auth</i>	Security/authorization messages.															

Parameter	Description	Type	Size	Default																																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>syslog</i></td><td>Messages generated internally by syslog.</td></tr><tr><td><i>lpr</i></td><td>Line printer subsystem.</td></tr><tr><td><i>news</i></td><td>Network news subsystem.</td></tr><tr><td><i>uucp</i></td><td>Network news subsystem.</td></tr><tr><td><i>cron</i></td><td>Clock daemon.</td></tr><tr><td><i>authpriv</i></td><td>Security/authorization messages (private).</td></tr><tr><td><i>ftp</i></td><td>FTP daemon.</td></tr><tr><td><i>ntp</i></td><td>NTP daemon.</td></tr><tr><td><i>audit</i></td><td>Log audit.</td></tr><tr><td><i>alert</i></td><td>Log alert.</td></tr><tr><td><i>clock</i></td><td>Clock daemon.</td></tr><tr><td><i>local0</i></td><td>Reserved for local use.</td></tr><tr><td><i>local1</i></td><td>Reserved for local use.</td></tr><tr><td><i>local2</i></td><td>Reserved for local use.</td></tr><tr><td><i>local3</i></td><td>Reserved for local use.</td></tr><tr><td><i>local4</i></td><td>Reserved for local use.</td></tr><tr><td><i>local5</i></td><td>Reserved for local use.</td></tr><tr><td><i>local6</i></td><td>Reserved for local use.</td></tr><tr><td><i>local7</i></td><td>Reserved for local use.</td></tr></table>	Option	Description	<i>syslog</i>	Messages generated internally by syslog.	<i>lpr</i>	Line printer subsystem.	<i>news</i>	Network news subsystem.	<i>uucp</i>	Network news subsystem.	<i>cron</i>	Clock daemon.	<i>authpriv</i>	Security/authorization messages (private).	<i>ftp</i>	FTP daemon.	<i>ntp</i>	NTP daemon.	<i>audit</i>	Log audit.	<i>alert</i>	Log alert.	<i>clock</i>	Clock daemon.	<i>local0</i>	Reserved for local use.	<i>local1</i>	Reserved for local use.	<i>local2</i>	Reserved for local use.	<i>local3</i>	Reserved for local use.	<i>local4</i>	Reserved for local use.	<i>local5</i>	Reserved for local use.	<i>local6</i>	Reserved for local use.	<i>local7</i>	Reserved for local use.			
	Option	Description																																										
	<i>syslog</i>	Messages generated internally by syslog.																																										
	<i>lpr</i>	Line printer subsystem.																																										
	<i>news</i>	Network news subsystem.																																										
	<i>uucp</i>	Network news subsystem.																																										
	<i>cron</i>	Clock daemon.																																										
	<i>authpriv</i>	Security/authorization messages (private).																																										
	<i>ftp</i>	FTP daemon.																																										
	<i>ntp</i>	NTP daemon.																																										
	<i>audit</i>	Log audit.																																										
	<i>alert</i>	Log alert.																																										
	<i>clock</i>	Clock daemon.																																										
	<i>local0</i>	Reserved for local use.																																										
	<i>local1</i>	Reserved for local use.																																										
	<i>local2</i>	Reserved for local use.																																										
	<i>local3</i>	Reserved for local use.																																										
	<i>local4</i>	Reserved for local use.																																										
	<i>local5</i>	Reserved for local use.																																										
	<i>local6</i>	Reserved for local use.																																										
<i>local7</i>	Reserved for local use.																																											
source-ip	Source IP address of syslog.	string	Maximum length: 63																																									
format	Log format.	option	-	default																																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Syslog format.</td></tr><tr><td><i>csv</i></td><td>CSV (Comma Separated Values) format.</td></tr><tr><td><i>cef</i></td><td>CEF (Common Event Format) format.</td></tr><tr><td><i>rfc5424</i></td><td>Syslog RFC5424 format.</td></tr><tr><td><i>json</i></td><td>JSON (JavaScript Object Notation) format.</td></tr><tr><td><i>custom</i></td><td>Custom format.</td></tr></table>	Option	Description	<i>default</i>	Syslog format.	<i>csv</i>	CSV (Comma Separated Values) format.	<i>cef</i>	CEF (Common Event Format) format.	<i>rfc5424</i>	Syslog RFC5424 format.	<i>json</i>	JSON (JavaScript Object Notation) format.	<i>custom</i>	Custom format.																													
	Option	Description																																										
	<i>default</i>	Syslog format.																																										
	<i>csv</i>	CSV (Comma Separated Values) format.																																										
	<i>cef</i>	CEF (Common Event Format) format.																																										
	<i>rfc5424</i>	Syslog RFC5424 format.																																										
	<i>json</i>	JSON (JavaScript Object Notation) format.																																										
<i>custom</i>	Custom format.																																											

Parameter	Description	Type	Size	Default												
priority	Set log transmission priority.	option	-	default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>default</td><td>Set Syslog transmission priority to default.</td></tr><tr><td>low</td><td>Set Syslog transmission priority to low.</td></tr></table>				Option	Description	default	Set Syslog transmission priority to default.	low	Set Syslog transmission priority to low.						
	Option	Description														
	default	Set Syslog transmission priority to default.														
low	Set Syslog transmission priority to low.															
max-log-rate	Syslog maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0												
enc-algorithm	Enable/disable reliable syslogging with TLS encryption.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>high-medium</td><td>SSL communication with high and medium encryption algorithms.</td></tr><tr><td>high</td><td>SSL communication with high encryption algorithms.</td></tr><tr><td>low</td><td>SSL communication with low encryption algorithms.</td></tr><tr><td>disable</td><td>Disable SSL communication.</td></tr></table>				Option	Description	high-medium	SSL communication with high and medium encryption algorithms.	high	SSL communication with high encryption algorithms.	low	SSL communication with low encryption algorithms.	disable	Disable SSL communication.		
	Option	Description														
	high-medium	SSL communication with high and medium encryption algorithms.														
	high	SSL communication with high encryption algorithms.														
	low	SSL communication with low encryption algorithms.														
disable	Disable SSL communication.															
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>default</td><td>Follow system global setting.</td></tr><tr><td>SSLv3</td><td>SSLv3.</td></tr><tr><td>TLSv1</td><td>TLSv1.</td></tr><tr><td>TLSv1-1</td><td>TLSv1.1.</td></tr><tr><td>TLSv1-2</td><td>TLSv1.2.</td></tr></table>				Option	Description	default	Follow system global setting.	SSLv3	SSLv3.	TLSv1	TLSv1.	TLSv1-1	TLSv1.1.	TLSv1-2	TLSv1.2.
	Option	Description														
	default	Follow system global setting.														
	SSLv3	SSLv3.														
	TLSv1	TLSv1.														
	TLSv1-1	TLSv1.1.														
TLSv1-2	TLSv1.2.															
certificate	Certificate used to communicate with Syslog server.	string	Maximum length: 35													
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>auto</td><td>Set outgoing interface automatically.</td></tr></table>				Option	Description	auto	Set outgoing interface automatically.								
	Option	Description														
auto	Set outgoing interface automatically.															

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>specify</i>	Set outgoing interface manually.		
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	

config custom-field-name

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 255	0
name	Field name [A-Za-z0-9_].	string	Maximum length: 35	
custom	Field custom name [A-Za-z0-9_].	string	Maximum length: 35	

config log-templates

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	<i>traffic</i>	Traffic log.		
	<i>event</i>	Event log.		
	<i>virus</i>	Antivirus log.		
	<i>webfilter</i>	Web filter log.		
	<i>attack</i>	Attack log.		
	<i>spam</i>	Antispam log.		
	<i>anomaly</i>	Anomaly log.		
	<i>voip</i>	VoIP log.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>dlp</i>	DLP log.		
	<i>app-ctrl</i>	Application control log.		
	<i>waf</i>	Web application firewall log.		
	<i>dns</i>	DNS detail log.		
	<i>ssh</i>	SSH log.		
	<i>ssl</i>	SSL log.		
	<i>file-filter</i>	File filter log.		
	<i>icap</i>	ICAP log.		
empty-value-indicator	A character to indicate log field is empty.	string	Maximum length: 1	
template	Log template string.	string	Maximum length: 2047	

config log syslogd3 setting

Global settings for remote syslog server.

```

config log syslogd3 setting
    Description: Global settings for remote syslog server.
    set status [enable|disable]
    set server {string}
    set mode [udp|legacy-reliable|...]
    set port {integer}
    set facility [kernel|user|...]
    set source-ip {string}
    set format [default|csv|...]
    set priority [default|low]
    set max-log-rate {integer}
    set enc-algorithm [high-medium|high|...]
    set ssl-min-proto-version [default|SSLv3|...]
    set certificate {string}
    config custom-field-name
        Description: Custom field name for CEF format logging.
        edit <id>
            set name {string}
            set custom {string}
        next
    end
    set interface-select-method [auto|specify]

```

```

set interface {string}
config log-templates
  Description: Custom log templates.
  edit <id>
    set category [traffic|event|...]
    set empty-value-indicator {string}
    set template {string}
  next
end
end

```

config log syslogd3 setting

Parameter	Description	Type	Size	Default
status	Enable/disable remote syslog logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Log to remote syslog server.		
	<i>disable</i>	Do not log to remote syslog server.		
server	Address of remote syslog server.	string	Maximum length: 127	
mode	Remote syslog logging over UDP/Reliable TCP.	option	-	udp
	Option	Description		
	<i>udp</i>	Enable syslogging over UDP.		
	<i>legacy-reliable</i>	Enable legacy reliable syslogging by RFC3195 (Reliable Delivery for Syslog).		
	<i>reliable</i>	Enable reliable syslogging by RFC6587 (Transmission of Syslog Messages over TCP).		
port	Server listen port.	integer	Minimum value: 0 Maximum value: 65535	514
facility	Remote syslog facility.	option	-	local7
	Option	Description		
	<i>kernel</i>	Kernel messages.		
	<i>user</i>	Random user-level messages.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>mail</i>	Mail system.		
	<i>daemon</i>	System daemons.		
	<i>auth</i>	Security/authorization messages.		
	<i>syslog</i>	Messages generated internally by syslog.		
	<i>lpr</i>	Line printer subsystem.		
	<i>news</i>	Network news subsystem.		
	<i>uucp</i>	Network news subsystem.		
	<i>cron</i>	Clock daemon.		
	<i>authpriv</i>	Security/authorization messages (private).		
	<i>ftp</i>	FTP daemon.		
	<i>ntp</i>	NTP daemon.		
	<i>audit</i>	Log audit.		
	<i>alert</i>	Log alert.		
	<i>clock</i>	Clock daemon.		
	<i>local0</i>	Reserved for local use.		
	<i>local1</i>	Reserved for local use.		
	<i>local2</i>	Reserved for local use.		
	<i>local3</i>	Reserved for local use.		
	<i>local4</i>	Reserved for local use.		
	<i>local5</i>	Reserved for local use.		
	<i>local6</i>	Reserved for local use.		
<i>local7</i>	Reserved for local use.			
source-ip	Source IP address of syslog.	string	Maximum length: 63	
format	Log format.	option	-	default
	Option	Description		
	<i>default</i>	Syslog format.		
	<i>csv</i>	CSV (Comma Separated Values) format.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>cef</i>	CEF (Common Event Format) format.		
	<i>rfc5424</i>	Syslog RFC5424 format.		
	<i>json</i>	JSON (JavaScript Object Notation) format.		
	<i>custom</i>	Custom format.		
priority	Set log transmission priority.	option	-	default
	Option	Description		
	<i>default</i>	Set Syslog transmission priority to default.		
	<i>low</i>	Set Syslog transmission priority to low.		
max-log-rate	Syslog maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0
enc-algorithm	Enable/disable reliable syslogging with TLS encryption.	option	-	disable
	Option	Description		
	<i>high-medium</i>	SSL communication with high and medium encryption algorithms.		
	<i>high</i>	SSL communication with high encryption algorithms.		
	<i>low</i>	SSL communication with low encryption algorithms.		
	<i>disable</i>	Disable SSL communication.		
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default
	Option	Description		
	<i>default</i>	Follow system global setting.		
	<i>SSLv3</i>	SSLv3.		
	<i>TLSv1</i>	TLSv1.		
	<i>TLSv1-1</i>	TLSv1.1.		
	<i>TLSv1-2</i>	TLSv1.2.		

Parameter	Description	Type	Size	Default						
certificate	Certificate used to communicate with Syslog server.	string	Maximum length: 35							
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Set outgoing interface automatically.</td></tr><tr><td><i>specify</i></td><td>Set outgoing interface manually.</td></tr></table>				Option	Description	<i>auto</i>	Set outgoing interface automatically.	<i>specify</i>	Set outgoing interface manually.
Option	Description									
<i>auto</i>	Set outgoing interface automatically.									
<i>specify</i>	Set outgoing interface manually.									
interface	Specify outgoing interface to reach server.	string	Maximum length: 15							

config custom-field-name

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 255	0
name	Field name [A-Za-z0-9_].	string	Maximum length: 35	
custom	Field custom name [A-Za-z0-9_].	string	Maximum length: 35	

config log-templates

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	traffic	Traffic log.		
	event	Event log.		
	virus	Antivirus log.		

Parameter	Description	Type	Size	Default																												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>webfilter</i></td><td>Web filter log.</td></tr><tr><td><i>attack</i></td><td>Attack log.</td></tr><tr><td><i>spam</i></td><td>Antispam log.</td></tr><tr><td><i>anomaly</i></td><td>Anomaly log.</td></tr><tr><td><i>voip</i></td><td>VoIP log.</td></tr><tr><td><i>dlp</i></td><td>DLP log.</td></tr><tr><td><i>app-ctrl</i></td><td>Application control log.</td></tr><tr><td><i>waf</i></td><td>Web application firewall log.</td></tr><tr><td><i>dns</i></td><td>DNS detail log.</td></tr><tr><td><i>ssh</i></td><td>SSH log.</td></tr><tr><td><i>ssl</i></td><td>SSL log.</td></tr><tr><td><i>file-filter</i></td><td>File filter log.</td></tr><tr><td><i>icap</i></td><td>ICAP log.</td></tr></table>	Option	Description	<i>webfilter</i>	Web filter log.	<i>attack</i>	Attack log.	<i>spam</i>	Antispam log.	<i>anomaly</i>	Anomaly log.	<i>voip</i>	VoIP log.	<i>dlp</i>	DLP log.	<i>app-ctrl</i>	Application control log.	<i>waf</i>	Web application firewall log.	<i>dns</i>	DNS detail log.	<i>ssh</i>	SSH log.	<i>ssl</i>	SSL log.	<i>file-filter</i>	File filter log.	<i>icap</i>	ICAP log.			
	Option	Description																														
	<i>webfilter</i>	Web filter log.																														
	<i>attack</i>	Attack log.																														
	<i>spam</i>	Antispam log.																														
	<i>anomaly</i>	Anomaly log.																														
	<i>voip</i>	VoIP log.																														
	<i>dlp</i>	DLP log.																														
	<i>app-ctrl</i>	Application control log.																														
	<i>waf</i>	Web application firewall log.																														
	<i>dns</i>	DNS detail log.																														
	<i>ssh</i>	SSH log.																														
	<i>ssl</i>	SSL log.																														
	<i>file-filter</i>	File filter log.																														
<i>icap</i>	ICAP log.																															
empty-value-indicator	A character to indicate log field is empty.	string	Maximum length: 1																													
template	Log template string.	string	Maximum length: 2047																													

config log syslogd4 filter

Filters for remote system server.

```

config log syslogd4 filter
    Description: Filters for remote system server.
    set severity [emergency|alert|...]
    set forward-traffic [enable|disable]
    set local-traffic [enable|disable]
    set multicast-traffic [enable|disable]
    set sniffer-traffic [enable|disable]
    set ztna-traffic [enable|disable]
    set http-transaction [enable|disable]
    set anomaly [enable|disable]
    set voip [enable|disable]
config free-style
    Description: Free style filters.
    edit <id>

```

```

        set category [traffic|event|...]
        set filter {string}
        set filter-type [include|exclude]
    next
end
end

```

config log syslogd4 filter

Parameter	Description	Type	Size	Default
severity	Lowest severity level to log.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		
forward-traffic	Enable/disable forward traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable multicast traffic logging.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable multicast traffic logging.		
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable sniffer traffic logging.		
	<i>disable</i>	Disable sniffer traffic logging.		
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		

config free-style

Parameter	Description	Type	Size	Default																																		
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0																																		
category	Log category.	option	-	traffic																																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>traffic</td><td>Traffic log.</td></tr><tr><td>event</td><td>Event log.</td></tr><tr><td>virus</td><td>Antivirus log.</td></tr><tr><td>webfilter</td><td>Web filter log.</td></tr><tr><td>attack</td><td>Attack log.</td></tr><tr><td>spam</td><td>Antispam log.</td></tr><tr><td>anomaly</td><td>Anomaly log.</td></tr><tr><td>voip</td><td>VoIP log.</td></tr><tr><td>dlp</td><td>DLP log.</td></tr><tr><td>app-ctrl</td><td>Application control log.</td></tr><tr><td>waf</td><td>Web application firewall log.</td></tr><tr><td>dns</td><td>DNS detail log.</td></tr><tr><td>ssh</td><td>SSH log.</td></tr><tr><td>ssl</td><td>SSL log.</td></tr><tr><td>file-filter</td><td>File filter log.</td></tr><tr><td>icap</td><td>ICAP log.</td></tr></table>	Option	Description	traffic	Traffic log.	event	Event log.	virus	Antivirus log.	webfilter	Web filter log.	attack	Attack log.	spam	Antispam log.	anomaly	Anomaly log.	voip	VoIP log.	dlp	DLP log.	app-ctrl	Application control log.	waf	Web application firewall log.	dns	DNS detail log.	ssh	SSH log.	ssl	SSL log.	file-filter	File filter log.	icap	ICAP log.			
	Option	Description																																				
	traffic	Traffic log.																																				
	event	Event log.																																				
	virus	Antivirus log.																																				
	webfilter	Web filter log.																																				
	attack	Attack log.																																				
	spam	Antispam log.																																				
	anomaly	Anomaly log.																																				
	voip	VoIP log.																																				
	dlp	DLP log.																																				
	app-ctrl	Application control log.																																				
	waf	Web application firewall log.																																				
	dns	DNS detail log.																																				
	ssh	SSH log.																																				
	ssl	SSL log.																																				
	file-filter	File filter log.																																				
icap	ICAP log.																																					
filter	Free style filter string.	string	Maximum length: 1023																																			
filter-type	Include/exclude logs that match the filter.	option	-	include																																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>include</td><td>Include logs that match the filter.</td></tr><tr><td>exclude</td><td>Exclude logs that match the filter.</td></tr></table>	Option	Description	include	Include logs that match the filter.	exclude	Exclude logs that match the filter.																															
	Option	Description																																				
	include	Include logs that match the filter.																																				
exclude	Exclude logs that match the filter.																																					

config log syslogd4 override-filter

Override filters for remote system server.

```
config log syslogd4 override-filter
  Description: Override filters for remote system server.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]
  set sniffer-traffic [enable|disable]
  set ztna-traffic [enable|disable]
  set http-transaction [enable|disable]
  set anomaly [enable|disable]
  set voip [enable|disable]
  config free-style
    Description: Free style filters.
    edit <id>
      set category [traffic|event|...]
      set filter {string}
      set filter-type [include|exclude]
    next
  end
end
```

config log syslogd4 override-filter

Parameter	Description	Type	Size	Default
severity	Lowest severity level to log.	option	-	information
	Option	Description		
	<i>emergency</i>	Emergency level.		
	<i>alert</i>	Alert level.		
	<i>critical</i>	Critical level.		
	<i>error</i>	Error level.		
	<i>warning</i>	Warning level.		
	<i>notification</i>	Notification level.		
	<i>information</i>	Information level.		
	<i>debug</i>	Debug level.		
forward-traffic	Enable/disable forward traffic logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable forward traffic logging.		
	<i>disable</i>	Disable forward traffic logging.		
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local in or out traffic logging.		
	<i>disable</i>	Disable local in or out traffic logging.		
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable multicast traffic logging.		
	<i>disable</i>	Disable multicast traffic logging.		
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable sniffer traffic logging.		
	<i>disable</i>	Disable sniffer traffic logging.		
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	<i>traffic</i>	Traffic log.		
	<i>event</i>	Event log.		
	<i>virus</i>	Antivirus log.		
	<i>webfilter</i>	Web filter log.		
	<i>attack</i>	Attack log.		
	<i>spam</i>	Antispam log.		
	<i>anomaly</i>	Anomaly log.		
	<i>voip</i>	VoIP log.		
	<i>dlp</i>	DLP log.		
	<i>app-ctrl</i>	Application control log.		
	<i>waf</i>	Web application firewall log.		
	<i>dns</i>	DNS detail log.		
	<i>ssh</i>	SSH log.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>ssl</i>	SSL log.		
	<i>file-filter</i>	File filter log.		
	<i>icap</i>	ICAP log.		
filter	Free style filter string.	string	Maximum length: 1023	
filter-type	Include/exclude logs that match the filter.	option	-	include
	Option	Description		
	<i>include</i>	Include logs that match the filter.		
	<i>exclude</i>	Exclude logs that match the filter.		

config log syslogd4 override-setting

Override settings for remote syslog server.

```

config log syslogd4 override-setting
    Description: Override settings for remote syslog server.
    set status [enable|disable]
    set server {string}
    set mode [udp|legacy-reliable|...]
    set port {integer}
    set facility [kernel|user|...]
    set source-ip {string}
    set format [default|csv|...]
    set priority [default|low]
    set max-log-rate {integer}
    set enc-algorithm [high-medium|high|...]
    set ssl-min-proto-version [default|SSLv3|...]
    set certificate {string}
    config custom-field-name
        Description: Custom field name for CEF format logging.
        edit <id>
            set name {string}
            set custom {string}
        next
    end
    set interface-select-method [auto|specify]
    set interface {string}
    config log-templates
        Description: Custom log templates.
        edit <id>
            set category [traffic|event|...]

```

```

        set empty-value-indicator {string}
        set template {string}
    next
end
end

```

config log syslogd4 override-setting

Parameter	Description	Type	Size	Default												
status	Enable/disable remote syslog logging.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Log to remote syslog server.</td></tr><tr><td><i>disable</i></td><td>Do not log to remote syslog server.</td></tr></table>	Option	Description	<i>enable</i>	Log to remote syslog server.	<i>disable</i>	Do not log to remote syslog server.									
Option	Description															
<i>enable</i>	Log to remote syslog server.															
<i>disable</i>	Do not log to remote syslog server.															
server	Address of remote syslog server.	string	Maximum length: 127													
mode	Remote syslog logging over UDP/Reliable TCP.	option	-	udp												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>udp</i></td><td>Enable syslogging over UDP.</td></tr><tr><td><i>legacy-reliable</i></td><td>Enable legacy reliable syslogging by RFC3195 (Reliable Delivery for Syslog).</td></tr><tr><td><i>reliable</i></td><td>Enable reliable syslogging by RFC6587 (Transmission of Syslog Messages over TCP).</td></tr></table>	Option	Description	<i>udp</i>	Enable syslogging over UDP.	<i>legacy-reliable</i>	Enable legacy reliable syslogging by RFC3195 (Reliable Delivery for Syslog).	<i>reliable</i>	Enable reliable syslogging by RFC6587 (Transmission of Syslog Messages over TCP).							
Option	Description															
<i>udp</i>	Enable syslogging over UDP.															
<i>legacy-reliable</i>	Enable legacy reliable syslogging by RFC3195 (Reliable Delivery for Syslog).															
<i>reliable</i>	Enable reliable syslogging by RFC6587 (Transmission of Syslog Messages over TCP).															
port	Server listen port.	integer	Minimum value: 0 Maximum value: 65535	514												
facility	Remote syslog facility.	option	-	local7												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>kernel</i></td><td>Kernel messages.</td></tr><tr><td><i>user</i></td><td>Random user-level messages.</td></tr><tr><td><i>mail</i></td><td>Mail system.</td></tr><tr><td><i>daemon</i></td><td>System daemons.</td></tr><tr><td><i>auth</i></td><td>Security/authorization messages.</td></tr></table>	Option	Description	<i>kernel</i>	Kernel messages.	<i>user</i>	Random user-level messages.	<i>mail</i>	Mail system.	<i>daemon</i>	System daemons.	<i>auth</i>	Security/authorization messages.			
Option	Description															
<i>kernel</i>	Kernel messages.															
<i>user</i>	Random user-level messages.															
<i>mail</i>	Mail system.															
<i>daemon</i>	System daemons.															
<i>auth</i>	Security/authorization messages.															

Parameter	Description	Type	Size	Default																																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>syslog</i></td><td>Messages generated internally by syslog.</td></tr><tr><td><i>lpr</i></td><td>Line printer subsystem.</td></tr><tr><td><i>news</i></td><td>Network news subsystem.</td></tr><tr><td><i>uucp</i></td><td>Network news subsystem.</td></tr><tr><td><i>cron</i></td><td>Clock daemon.</td></tr><tr><td><i>authpriv</i></td><td>Security/authorization messages (private).</td></tr><tr><td><i>ftp</i></td><td>FTP daemon.</td></tr><tr><td><i>ntp</i></td><td>NTP daemon.</td></tr><tr><td><i>audit</i></td><td>Log audit.</td></tr><tr><td><i>alert</i></td><td>Log alert.</td></tr><tr><td><i>clock</i></td><td>Clock daemon.</td></tr><tr><td><i>local0</i></td><td>Reserved for local use.</td></tr><tr><td><i>local1</i></td><td>Reserved for local use.</td></tr><tr><td><i>local2</i></td><td>Reserved for local use.</td></tr><tr><td><i>local3</i></td><td>Reserved for local use.</td></tr><tr><td><i>local4</i></td><td>Reserved for local use.</td></tr><tr><td><i>local5</i></td><td>Reserved for local use.</td></tr><tr><td><i>local6</i></td><td>Reserved for local use.</td></tr><tr><td><i>local7</i></td><td>Reserved for local use.</td></tr></table>	Option	Description	<i>syslog</i>	Messages generated internally by syslog.	<i>lpr</i>	Line printer subsystem.	<i>news</i>	Network news subsystem.	<i>uucp</i>	Network news subsystem.	<i>cron</i>	Clock daemon.	<i>authpriv</i>	Security/authorization messages (private).	<i>ftp</i>	FTP daemon.	<i>ntp</i>	NTP daemon.	<i>audit</i>	Log audit.	<i>alert</i>	Log alert.	<i>clock</i>	Clock daemon.	<i>local0</i>	Reserved for local use.	<i>local1</i>	Reserved for local use.	<i>local2</i>	Reserved for local use.	<i>local3</i>	Reserved for local use.	<i>local4</i>	Reserved for local use.	<i>local5</i>	Reserved for local use.	<i>local6</i>	Reserved for local use.	<i>local7</i>	Reserved for local use.			
	Option	Description																																										
	<i>syslog</i>	Messages generated internally by syslog.																																										
	<i>lpr</i>	Line printer subsystem.																																										
	<i>news</i>	Network news subsystem.																																										
	<i>uucp</i>	Network news subsystem.																																										
	<i>cron</i>	Clock daemon.																																										
	<i>authpriv</i>	Security/authorization messages (private).																																										
	<i>ftp</i>	FTP daemon.																																										
	<i>ntp</i>	NTP daemon.																																										
	<i>audit</i>	Log audit.																																										
	<i>alert</i>	Log alert.																																										
	<i>clock</i>	Clock daemon.																																										
	<i>local0</i>	Reserved for local use.																																										
	<i>local1</i>	Reserved for local use.																																										
	<i>local2</i>	Reserved for local use.																																										
	<i>local3</i>	Reserved for local use.																																										
	<i>local4</i>	Reserved for local use.																																										
	<i>local5</i>	Reserved for local use.																																										
	<i>local6</i>	Reserved for local use.																																										
<i>local7</i>	Reserved for local use.																																											
source-ip	Source IP address of syslog.	string	Maximum length: 63																																									
format	Log format.	option	-	default																																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Syslog format.</td></tr><tr><td><i>csv</i></td><td>CSV (Comma Separated Values) format.</td></tr><tr><td><i>cef</i></td><td>CEF (Common Event Format) format.</td></tr><tr><td><i>rfc5424</i></td><td>Syslog RFC5424 format.</td></tr><tr><td><i>json</i></td><td>JSON (JavaScript Object Notation) format.</td></tr><tr><td><i>custom</i></td><td>Custom format.</td></tr></table>	Option	Description	<i>default</i>	Syslog format.	<i>csv</i>	CSV (Comma Separated Values) format.	<i>cef</i>	CEF (Common Event Format) format.	<i>rfc5424</i>	Syslog RFC5424 format.	<i>json</i>	JSON (JavaScript Object Notation) format.	<i>custom</i>	Custom format.																													
	Option	Description																																										
	<i>default</i>	Syslog format.																																										
	<i>csv</i>	CSV (Comma Separated Values) format.																																										
	<i>cef</i>	CEF (Common Event Format) format.																																										
	<i>rfc5424</i>	Syslog RFC5424 format.																																										
	<i>json</i>	JSON (JavaScript Object Notation) format.																																										
<i>custom</i>	Custom format.																																											

Parameter	Description	Type	Size	Default												
priority	Set log transmission priority.	option	-	default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>default</td><td>Set Syslog transmission priority to default.</td></tr><tr><td>low</td><td>Set Syslog transmission priority to low.</td></tr></table>	Option	Description	default	Set Syslog transmission priority to default.	low	Set Syslog transmission priority to low.									
	Option	Description														
	default	Set Syslog transmission priority to default.														
low	Set Syslog transmission priority to low.															
max-log-rate	Syslog maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0												
enc-algorithm	Enable/disable reliable syslogging with TLS encryption.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>high-medium</td><td>SSL communication with high and medium encryption algorithms.</td></tr><tr><td>high</td><td>SSL communication with high encryption algorithms.</td></tr><tr><td>low</td><td>SSL communication with low encryption algorithms.</td></tr><tr><td>disable</td><td>Disable SSL communication.</td></tr></table>	Option	Description	high-medium	SSL communication with high and medium encryption algorithms.	high	SSL communication with high encryption algorithms.	low	SSL communication with low encryption algorithms.	disable	Disable SSL communication.					
	Option	Description														
	high-medium	SSL communication with high and medium encryption algorithms.														
	high	SSL communication with high encryption algorithms.														
	low	SSL communication with low encryption algorithms.														
disable	Disable SSL communication.															
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>default</td><td>Follow system global setting.</td></tr><tr><td>SSLv3</td><td>SSLv3.</td></tr><tr><td>TLSv1</td><td>TLSv1.</td></tr><tr><td>TLSv1-1</td><td>TLSv1.1.</td></tr><tr><td>TLSv1-2</td><td>TLSv1.2.</td></tr></table>	Option	Description	default	Follow system global setting.	SSLv3	SSLv3.	TLSv1	TLSv1.	TLSv1-1	TLSv1.1.	TLSv1-2	TLSv1.2.			
	Option	Description														
	default	Follow system global setting.														
	SSLv3	SSLv3.														
	TLSv1	TLSv1.														
	TLSv1-1	TLSv1.1.														
TLSv1-2	TLSv1.2.															
certificate	Certificate used to communicate with Syslog server.	string	Maximum length: 35													
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>auto</td><td>Set outgoing interface automatically.</td></tr></table>	Option	Description	auto	Set outgoing interface automatically.											
	Option	Description														
auto	Set outgoing interface automatically.															

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>specify</i>	Set outgoing interface manually.		
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	

config custom-field-name

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 255	0
name	Field name [A-Za-z0-9_].	string	Maximum length: 35	
custom	Field custom name [A-Za-z0-9_].	string	Maximum length: 35	

config log-templates

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	<i>traffic</i>	Traffic log.		
	<i>event</i>	Event log.		
	<i>virus</i>	Antivirus log.		
	<i>webfilter</i>	Web filter log.		
	<i>attack</i>	Attack log.		
	<i>spam</i>	Antispam log.		
	<i>anomaly</i>	Anomaly log.		
	<i>voip</i>	VoIP log.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>dlp</i>	DLP log.		
	<i>app-ctrl</i>	Application control log.		
	<i>waf</i>	Web application firewall log.		
	<i>dns</i>	DNS detail log.		
	<i>ssh</i>	SSH log.		
	<i>ssl</i>	SSL log.		
	<i>file-filter</i>	File filter log.		
	<i>icap</i>	ICAP log.		
empty-value-indicator	A character to indicate log field is empty.	string	Maximum length: 1	
template	Log template string.	string	Maximum length: 2047	

config log syslogd4 setting

Global settings for remote syslog server.

```

config log syslogd4 setting
    Description: Global settings for remote syslog server.
    set status [enable|disable]
    set server {string}
    set mode [udp|legacy-reliable|...]
    set port {integer}
    set facility [kernel|user|...]
    set source-ip {string}
    set format [default|csv|...]
    set priority [default|low]
    set max-log-rate {integer}
    set enc-algorithm [high-medium|high|...]
    set ssl-min-proto-version [default|SSLv3|...]
    set certificate {string}
    config custom-field-name
        Description: Custom field name for CEF format logging.
        edit <id>
            set name {string}
            set custom {string}
        next
    end
    set interface-select-method [auto|specify]

```

```

set interface {string}
config log-templates
  Description: Custom log templates.
  edit <id>
    set category [traffic|event|...]
    set empty-value-indicator {string}
    set template {string}
  next
end
end

```

config log syslogd4 setting

Parameter	Description	Type	Size	Default
status	Enable/disable remote syslog logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Log to remote syslog server.		
	<i>disable</i>	Do not log to remote syslog server.		
server	Address of remote syslog server.	string	Maximum length: 127	
mode	Remote syslog logging over UDP/Reliable TCP.	option	-	udp
	Option	Description		
	<i>udp</i>	Enable syslogging over UDP.		
	<i>legacy-reliable</i>	Enable legacy reliable syslogging by RFC3195 (Reliable Delivery for Syslog).		
	<i>reliable</i>	Enable reliable syslogging by RFC6587 (Transmission of Syslog Messages over TCP).		
port	Server listen port.	integer	Minimum value: 0 Maximum value: 65535	514
facility	Remote syslog facility.	option	-	local7
	Option	Description		
	<i>kernel</i>	Kernel messages.		
	<i>user</i>	Random user-level messages.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>mail</i>	Mail system.		
	<i>daemon</i>	System daemons.		
	<i>auth</i>	Security/authorization messages.		
	<i>syslog</i>	Messages generated internally by syslog.		
	<i>lpr</i>	Line printer subsystem.		
	<i>news</i>	Network news subsystem.		
	<i>uucp</i>	Network news subsystem.		
	<i>cron</i>	Clock daemon.		
	<i>authpriv</i>	Security/authorization messages (private).		
	<i>ftp</i>	FTP daemon.		
	<i>ntp</i>	NTP daemon.		
	<i>audit</i>	Log audit.		
	<i>alert</i>	Log alert.		
	<i>clock</i>	Clock daemon.		
	<i>local0</i>	Reserved for local use.		
	<i>local1</i>	Reserved for local use.		
	<i>local2</i>	Reserved for local use.		
	<i>local3</i>	Reserved for local use.		
	<i>local4</i>	Reserved for local use.		
	<i>local5</i>	Reserved for local use.		
	<i>local6</i>	Reserved for local use.		
	<i>local7</i>	Reserved for local use.		
source-ip	Source IP address of syslog.	string	Maximum length: 63	
format	Log format.	option	-	default
	Option	Description		
	<i>default</i>	Syslog format.		
	<i>csv</i>	CSV (Comma Separated Values) format.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>cef</i>	CEF (Common Event Format) format.		
	<i>rfc5424</i>	Syslog RFC5424 format.		
	<i>json</i>	JSON (JavaScript Object Notation) format.		
	<i>custom</i>	Custom format.		
priority	Set log transmission priority.	option	-	default
	Option	Description		
	<i>default</i>	Set Syslog transmission priority to default.		
	<i>low</i>	Set Syslog transmission priority to low.		
max-log-rate	Syslog maximum log rate in MBps (0 = unlimited).	integer	Minimum value: 0 Maximum value: 100000	0
enc-algorithm	Enable/disable reliable syslogging with TLS encryption.	option	-	disable
	Option	Description		
	<i>high-medium</i>	SSL communication with high and medium encryption algorithms.		
	<i>high</i>	SSL communication with high encryption algorithms.		
	<i>low</i>	SSL communication with low encryption algorithms.		
	<i>disable</i>	Disable SSL communication.		
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default
	Option	Description		
	<i>default</i>	Follow system global setting.		
	<i>SSLv3</i>	SSLv3.		
	<i>TLSv1</i>	TLSv1.		
	<i>TLSv1-1</i>	TLSv1.1.		
	<i>TLSv1-2</i>	TLSv1.2.		

Parameter	Description	Type	Size	Default						
certificate	Certificate used to communicate with Syslog server.	string	Maximum length: 35							
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Set outgoing interface automatically.</td></tr><tr><td><i>specify</i></td><td>Set outgoing interface manually.</td></tr></table>				Option	Description	<i>auto</i>	Set outgoing interface automatically.	<i>specify</i>	Set outgoing interface manually.
Option	Description									
<i>auto</i>	Set outgoing interface automatically.									
<i>specify</i>	Set outgoing interface manually.									
interface	Specify outgoing interface to reach server.	string	Maximum length: 15							

config custom-field-name

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 255	0
name	Field name [A-Za-z0-9_].	string	Maximum length: 35	
custom	Field custom name [A-Za-z0-9_].	string	Maximum length: 35	

config log-templates

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic
	Option	Description		
	traffic	Traffic log.		
	event	Event log.		
	virus	Antivirus log.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>webfilter</i>	Web filter log.		
	<i>attack</i>	Attack log.		
	<i>spam</i>	Antispam log.		
	<i>anomaly</i>	Anomaly log.		
	<i>voip</i>	VoIP log.		
	<i>dlp</i>	DLP log.		
	<i>app-ctrl</i>	Application control log.		
	<i>waf</i>	Web application firewall log.		
	<i>dns</i>	DNS detail log.		
	<i>ssh</i>	SSH log.		
	<i>ssl</i>	SSL log.		
	<i>file-filter</i>	File filter log.		
	<i>icap</i>	ICAP log.		
empty-value-indicator	A character to indicate log field is empty.	string	Maximum length: 1	
template	Log template string.	string	Maximum length: 2047	

config log tacacs+accounting filter

Settings for TACACS+ accounting events filter.

```

config log tacacs+accounting filter
  Description: Settings for TACACS+ accounting events filter.
  set login-audit [enable|disable]
  set config-change-audit [enable|disable]
  set cli-cmd-audit [enable|disable]
end

```

config log tacacs+accounting filter

Parameter	Description	Type	Size	Default						
login-audit	Enable/disable TACACS+ accounting for login events audit.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable TACACS+ accounting for login events audit.</td></tr><tr><td><i>disable</i></td><td>Disable TACACS+ accounting for login events audit.</td></tr></table>	Option	Description	<i>enable</i>	Enable TACACS+ accounting for login events audit.	<i>disable</i>	Disable TACACS+ accounting for login events audit.			
Option	Description									
<i>enable</i>	Enable TACACS+ accounting for login events audit.									
<i>disable</i>	Disable TACACS+ accounting for login events audit.									
config-change-audit	Enable/disable TACACS+ accounting for configuration change events audit.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable TACACS+ accounting for configuration change events audit.</td></tr><tr><td><i>disable</i></td><td>Disable TACACS+ accounting for configuration change events audit.</td></tr></table>	Option	Description	<i>enable</i>	Enable TACACS+ accounting for configuration change events audit.	<i>disable</i>	Disable TACACS+ accounting for configuration change events audit.			
Option	Description									
<i>enable</i>	Enable TACACS+ accounting for configuration change events audit.									
<i>disable</i>	Disable TACACS+ accounting for configuration change events audit.									
cli-cmd-audit	Enable/disable TACACS+ accounting for CLI commands audit.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable TACACS+ accounting for CLI commands audit.</td></tr><tr><td><i>disable</i></td><td>Disable TACACS+ accounting for CLI commands audit.</td></tr></table>	Option	Description	<i>enable</i>	Enable TACACS+ accounting for CLI commands audit.	<i>disable</i>	Disable TACACS+ accounting for CLI commands audit.			
Option	Description									
<i>enable</i>	Enable TACACS+ accounting for CLI commands audit.									
<i>disable</i>	Disable TACACS+ accounting for CLI commands audit.									

config log tacacs+accounting setting

Settings for TACACS+ accounting.

```
config log tacacs+accounting setting
  Description: Settings for TACACS+ accounting.
  set status [enable|disable]
  set server {string}
  set server-key {password}
  set source-ip {string}
  set interface-select-method [auto|specify]
  set interface {string}
end
```

config log tacacs+accounting setting

Parameter	Description	Type	Size	Default
status	Enable/disable TACACS+ accounting.	option	-	disable
	Option Description			
	<i>enable</i>	Enable TACACS+ accounting.		
	<i>disable</i>	Disable TACACS+ accounting.		
server	Address of TACACS+ server.	string	Maximum length: 63	
server-key	Key to access the TACACS+ server.	password	Not Specified	
source-ip	Source IP address for communication to TACACS+ server.	string	Maximum length: 63	
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto
	Option Description			
	<i>auto</i>	Set outgoing interface automatically.		
	<i>specify</i>	Set outgoing interface manually.		
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	

config log tacacs+accounting2 filter

Settings for TACACS+ accounting events filter.

```
config log tacacs+accounting2 filter
  Description: Settings for TACACS+ accounting events filter.
  set login-audit [enable|disable]
  set config-change-audit [enable|disable]
  set cli-cmd-audit [enable|disable]
end
```

config log tacacs+accounting2 filter

Parameter	Description	Type	Size	Default						
login-audit	Enable/disable TACACS+ accounting for login events audit.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable TACACS+ accounting for login events audit.</td></tr><tr><td><i>disable</i></td><td>Disable TACACS+ accounting for login events audit.</td></tr></table>	Option	Description	<i>enable</i>	Enable TACACS+ accounting for login events audit.	<i>disable</i>	Disable TACACS+ accounting for login events audit.			
Option	Description									
<i>enable</i>	Enable TACACS+ accounting for login events audit.									
<i>disable</i>	Disable TACACS+ accounting for login events audit.									
config-change-audit	Enable/disable TACACS+ accounting for configuration change events audit.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable TACACS+ accounting for configuration change events audit.</td></tr><tr><td><i>disable</i></td><td>Disable TACACS+ accounting for configuration change events audit.</td></tr></table>	Option	Description	<i>enable</i>	Enable TACACS+ accounting for configuration change events audit.	<i>disable</i>	Disable TACACS+ accounting for configuration change events audit.			
Option	Description									
<i>enable</i>	Enable TACACS+ accounting for configuration change events audit.									
<i>disable</i>	Disable TACACS+ accounting for configuration change events audit.									
cli-cmd-audit	Enable/disable TACACS+ accounting for CLI commands audit.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable TACACS+ accounting for CLI commands audit.</td></tr><tr><td><i>disable</i></td><td>Disable TACACS+ accounting for CLI commands audit.</td></tr></table>	Option	Description	<i>enable</i>	Enable TACACS+ accounting for CLI commands audit.	<i>disable</i>	Disable TACACS+ accounting for CLI commands audit.			
Option	Description									
<i>enable</i>	Enable TACACS+ accounting for CLI commands audit.									
<i>disable</i>	Disable TACACS+ accounting for CLI commands audit.									

config log tacacs+accounting2 setting

Settings for TACACS+ accounting.

```
config log tacacs+accounting2 setting
  Description: Settings for TACACS+ accounting.
  set status [enable|disable]
  set server {string}
  set server-key {password}
  set source-ip {string}
  set interface-select-method [auto|specify]
  set interface {string}
end
```

config log tacacs+accounting2 setting

Parameter	Description	Type	Size	Default
status	Enable/disable TACACS+ accounting.	option	-	disable
	Option Description			
	<i>enable</i>	Enable TACACS+ accounting.		
	<i>disable</i>	Disable TACACS+ accounting.		
server	Address of TACACS+ server.	string	Maximum length: 63	
server-key	Key to access the TACACS+ server.	password	Not Specified	
source-ip	Source IP address for communication to TACACS+ server.	string	Maximum length: 63	
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto
	Option Description			
	<i>auto</i>	Set outgoing interface automatically.		
	<i>specify</i>	Set outgoing interface manually.		
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	

config log tacacs+accounting3 filter

Settings for TACACS+ accounting events filter.

```
config log tacacs+accounting3 filter
  Description: Settings for TACACS+ accounting events filter.
  set login-audit [enable|disable]
  set config-change-audit [enable|disable]
  set cli-cmd-audit [enable|disable]
end
```

config log tacacs+accounting3 filter

Parameter	Description	Type	Size	Default						
login-audit	Enable/disable TACACS+ accounting for login events audit.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable TACACS+ accounting for login events audit.</td></tr><tr><td><i>disable</i></td><td>Disable TACACS+ accounting for login events audit.</td></tr></table>	Option	Description	<i>enable</i>	Enable TACACS+ accounting for login events audit.	<i>disable</i>	Disable TACACS+ accounting for login events audit.			
Option	Description									
<i>enable</i>	Enable TACACS+ accounting for login events audit.									
<i>disable</i>	Disable TACACS+ accounting for login events audit.									
config-change-audit	Enable/disable TACACS+ accounting for configuration change events audit.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable TACACS+ accounting for configuration change events audit.</td></tr><tr><td><i>disable</i></td><td>Disable TACACS+ accounting for configuration change events audit.</td></tr></table>	Option	Description	<i>enable</i>	Enable TACACS+ accounting for configuration change events audit.	<i>disable</i>	Disable TACACS+ accounting for configuration change events audit.			
Option	Description									
<i>enable</i>	Enable TACACS+ accounting for configuration change events audit.									
<i>disable</i>	Disable TACACS+ accounting for configuration change events audit.									
cli-cmd-audit	Enable/disable TACACS+ accounting for CLI commands audit.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable TACACS+ accounting for CLI commands audit.</td></tr><tr><td><i>disable</i></td><td>Disable TACACS+ accounting for CLI commands audit.</td></tr></table>	Option	Description	<i>enable</i>	Enable TACACS+ accounting for CLI commands audit.	<i>disable</i>	Disable TACACS+ accounting for CLI commands audit.			
Option	Description									
<i>enable</i>	Enable TACACS+ accounting for CLI commands audit.									
<i>disable</i>	Disable TACACS+ accounting for CLI commands audit.									

config log tacacs+accounting3 setting

Settings for TACACS+ accounting.

```
config log tacacs+accounting3 setting
  Description: Settings for TACACS+ accounting.
  set status [enable|disable]
  set server {string}
  set server-key {password}
  set source-ip {string}
  set interface-select-method [auto|specify]
  set interface {string}
end
```


config log tacacs+accounting3 setting

Parameter	Description	Type	Size	Default
status	Enable/disable TACACS+ accounting.	option	-	disable
	Option Description			
	<i>enable</i>	Enable TACACS+ accounting.		
	<i>disable</i>	Disable TACACS+ accounting.		
server	Address of TACACS+ server.	string	Maximum length: 63	
server-key	Key to access the TACACS+ server.	password	Not Specified	
source-ip	Source IP address for communication to TACACS+ server.	string	Maximum length: 63	
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto
	Option Description			
	<i>auto</i>	Set outgoing interface automatically.		
	<i>specify</i>	Set outgoing interface manually.		
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	

config log threat-weight

Configure threat weight settings.

```
config log threat-weight
  Description: Configure threat weight settings.
  set status [enable|disable]
  config level
    Description: Score mapping for threat weight levels.
    set low {integer}
    set medium {integer}
    set high {integer}
    set critical {integer}
  end
  set blocked-connection [disable|low|...]
  set failed-connection [disable|low|...]
  set url-block-detected [disable|low|...]
  set botnet-connection-detected [disable|low|...]
```

```

config malware
    Description: Anti-virus malware threat weight settings.
    set virus-infected [disable|low|...]
    set fortindr [disable|low|...]
    set fortisandbox [disable|low|...]
    set file-blocked [disable|low|...]
    set command-blocked [disable|low|...]
    set oversized [disable|low|...]
    set virus-scan-error [disable|low|...]
    set switch-proto [disable|low|...]
    set mimefragmented [disable|low|...]
    set virus-file-type-executable [disable|low|...]
    set virus-outbreak-prevention [disable|low|...]
    set content-disarm [disable|low|...]
    set malware-list [disable|low|...]
    set ems-threat-feed [disable|low|...]
    set fsa-malicious [disable|low|...]
    set fsa-high-risk [disable|low|...]
    set fsa-medium-risk [disable|low|...]
end
config ips
    Description: IPS threat weight settings.
    set info-severity [disable|low|...]
    set low-severity [disable|low|...]
    set medium-severity [disable|low|...]
    set high-severity [disable|low|...]
    set critical-severity [disable|low|...]
end
config web
    Description: Web filtering threat weight settings.
    edit <id>
        set category {integer}
        set level [disable|low|...]
    next
end
config geolocation
    Description: Geolocation-based threat weight settings.
    edit <id>
        set country {string}
        set level [disable|low|...]
    next
end
config application
    Description: Application-control threat weight settings.
    edit <id>
        set category {integer}
        set level [disable|low|...]
    next
end
end

```

config log threat-weight

Parameter	Description	Type	Size	Default
status	Enable/disable the threat weight feature.	option	-	enable
	Option	Description		
	enable	Enable the threat weight feature.		
	disable	Disable the threat weight feature.		
blocked-connection	Threat weight score for blocked connections.	option	-	high
	Option	Description		
	disable	Disable threat weight scoring for blocked connections.		
	low	Use the low level score for blocked connections.		
	medium	Use the medium level score for blocked connections.		
	high	Use the high level score for blocked connections.		
	critical	Use the critical level score for blocked connections.		
failed-connection	Threat weight score for failed connections.	option	-	low
	Option	Description		
	disable	Disable threat weight scoring for failed connections.		
	low	Use the low level score for failed connections.		
	medium	Use the medium level score for failed connections.		
	high	Use the high level score for failed connections.		
	critical	Use the critical level score for failed connections.		
url-block-detected	Threat weight score for URL blocking.	option	-	high
	Option	Description		
	disable	Disable threat weight scoring for URL blocking.		
	low	Use the low level score for URL blocking.		
	medium	Use the medium level score for URL blocking.		
	high	Use the high level score for URL blocking.		
	critical	Use the critical level score for URL blocking.		

Parameter	Description	Type	Size	Default
botnet-connection-detected	Threat weight score for detected botnet connections.	option	-	critical
Option	Description			
<i>disable</i>	Disable threat weight scoring for detected botnet connections.			
<i>low</i>	Use the low level score for detected botnet connections.			
<i>medium</i>	Use the medium level score for detected botnet connections.			
<i>high</i>	Use the high level score for detected botnet connections.			
<i>critical</i>	Use the critical level score for detected botnet connections.			

config level

Parameter	Description	Type	Size	Default
low	Low level score value (1 - 100).	integer	Minimum value: 1 Maximum value: 100	5
medium	Medium level score value (1 - 100).	integer	Minimum value: 1 Maximum value: 100	10
high	High level score value (1 - 100).	integer	Minimum value: 1 Maximum value: 100	30
critical	Critical level score value (1 - 100).	integer	Minimum value: 1 Maximum value: 100	50

config malware

Parameter	Description	Type	Size	Default
virus-infected	Threat weight score for virus (infected) detected.	option	-	critical

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable threat weight scoring for virus (infected) detected.		
	<i>low</i>	Use the low level score for virus (infected) detected.		
	<i>medium</i>	Use the medium level score for virus (infected) detected.		
	<i>high</i>	Use the high level score for virus (infected) detected.		
	<i>critical</i>	Use the critical level score for virus (infected) detected.		
fortindr	Threat weight score for FortiNDR-detected virus.	option	-	critical
	Option	Description		
	<i>disable</i>	Disable threat weight scoring for virus detected by FortiNDR.		
	<i>low</i>	Use the low level score for virus detected by FortiNDR.		
	<i>medium</i>	Use the medium level score for virus detected by FortiNDR.		
	<i>high</i>	Use the high level score for virus detected by FortiNDR.		
	<i>critical</i>	Use the critical level score for virus detected by FortiNDR.		
fortisandbox	Threat weight score for FortiSandbox-detected virus.	option	-	critical
	Option	Description		
	<i>disable</i>	Disable threat weight scoring for virus detected by FortiSandbox.		
	<i>low</i>	Use the low level score for virus detected by FortiSandbox.		
	<i>medium</i>	Use the medium level score for virus detected by FortiSandbox.		
	<i>high</i>	Use the high level score for virus detected by FortiSandbox.		
	<i>critical</i>	Use the critical level score for virus detected by FortiSandbox.		
file-blocked	Threat weight score for blocked file detected.	option	-	low
	Option	Description		
	<i>disable</i>	Disable threat weight scoring for blocked file detected.		
	<i>low</i>	Use the low level score for blocked file detected.		

Parameter	Description	Type	Size	Default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>medium</i></td><td>Use the medium level score for blocked file detected.</td></tr><tr><td><i>high</i></td><td>Use the high level score for blocked file detected.</td></tr><tr><td><i>critical</i></td><td>Use the critical level score for blocked file detected.</td></tr></table>	Option	Description	<i>medium</i>	Use the medium level score for blocked file detected.	<i>high</i>	Use the high level score for blocked file detected.	<i>critical</i>	Use the critical level score for blocked file detected.							
	Option	Description														
	<i>medium</i>	Use the medium level score for blocked file detected.														
	<i>high</i>	Use the high level score for blocked file detected.														
<i>critical</i>	Use the critical level score for blocked file detected.															
command-blocked	Threat weight score for blocked command detected.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable threat weight scoring for blocked command detected.</td></tr><tr><td><i>low</i></td><td>Use the low level score for blocked command detected.</td></tr><tr><td><i>medium</i></td><td>Use the medium level score for blocked command detected.</td></tr><tr><td><i>high</i></td><td>Use the high level score for blocked command detected.</td></tr><tr><td><i>critical</i></td><td>Use the critical level score for blocked command detected.</td></tr></table>	Option	Description	<i>disable</i>	Disable threat weight scoring for blocked command detected.	<i>low</i>	Use the low level score for blocked command detected.	<i>medium</i>	Use the medium level score for blocked command detected.	<i>high</i>	Use the high level score for blocked command detected.	<i>critical</i>	Use the critical level score for blocked command detected.			
	Option	Description														
	<i>disable</i>	Disable threat weight scoring for blocked command detected.														
	<i>low</i>	Use the low level score for blocked command detected.														
	<i>medium</i>	Use the medium level score for blocked command detected.														
	<i>high</i>	Use the high level score for blocked command detected.														
<i>critical</i>	Use the critical level score for blocked command detected.															
oversized	Threat weight score for oversized file detected.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable threat weight scoring for oversized file detected.</td></tr><tr><td><i>low</i></td><td>Use the low level score for oversized file detected.</td></tr><tr><td><i>medium</i></td><td>Use the medium level score for oversized file detected.</td></tr><tr><td><i>high</i></td><td>Use the high level score for oversized file detected.</td></tr><tr><td><i>critical</i></td><td>Use the critical level score for oversized file detected.</td></tr></table>	Option	Description	<i>disable</i>	Disable threat weight scoring for oversized file detected.	<i>low</i>	Use the low level score for oversized file detected.	<i>medium</i>	Use the medium level score for oversized file detected.	<i>high</i>	Use the high level score for oversized file detected.	<i>critical</i>	Use the critical level score for oversized file detected.			
	Option	Description														
	<i>disable</i>	Disable threat weight scoring for oversized file detected.														
	<i>low</i>	Use the low level score for oversized file detected.														
	<i>medium</i>	Use the medium level score for oversized file detected.														
	<i>high</i>	Use the high level score for oversized file detected.														
<i>critical</i>	Use the critical level score for oversized file detected.															
virus-scan-error	Threat weight score for virus (scan error) detected.	option	-	high												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable threat weight scoring for virus (scan error) detected.</td></tr><tr><td><i>low</i></td><td>Use the low level score for virus (scan error) detected.</td></tr><tr><td><i>medium</i></td><td>Use the medium level score for virus (scan error) detected.</td></tr><tr><td><i>high</i></td><td>Use the high level score for virus (scan error) detected.</td></tr><tr><td><i>critical</i></td><td>Use the critical level score for virus (scan error) detected.</td></tr></table>	Option	Description	<i>disable</i>	Disable threat weight scoring for virus (scan error) detected.	<i>low</i>	Use the low level score for virus (scan error) detected.	<i>medium</i>	Use the medium level score for virus (scan error) detected.	<i>high</i>	Use the high level score for virus (scan error) detected.	<i>critical</i>	Use the critical level score for virus (scan error) detected.			
	Option	Description														
	<i>disable</i>	Disable threat weight scoring for virus (scan error) detected.														
	<i>low</i>	Use the low level score for virus (scan error) detected.														
	<i>medium</i>	Use the medium level score for virus (scan error) detected.														
	<i>high</i>	Use the high level score for virus (scan error) detected.														
<i>critical</i>	Use the critical level score for virus (scan error) detected.															

Parameter	Description	Type	Size	Default												
switch-proto	Threat weight score for switch proto detected.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable threat weight scoring for switch proto detected.</td></tr><tr><td><i>low</i></td><td>Use the low level score for switch proto detected.</td></tr><tr><td><i>medium</i></td><td>Use the medium level score for switch proto detected.</td></tr><tr><td><i>high</i></td><td>Use the high level score for switch proto detected.</td></tr><tr><td><i>critical</i></td><td>Use the critical level score for switch proto detected.</td></tr></table>	Option	Description	<i>disable</i>	Disable threat weight scoring for switch proto detected.	<i>low</i>	Use the low level score for switch proto detected.	<i>medium</i>	Use the medium level score for switch proto detected.	<i>high</i>	Use the high level score for switch proto detected.	<i>critical</i>	Use the critical level score for switch proto detected.			
	Option	Description														
	<i>disable</i>	Disable threat weight scoring for switch proto detected.														
	<i>low</i>	Use the low level score for switch proto detected.														
	<i>medium</i>	Use the medium level score for switch proto detected.														
	<i>high</i>	Use the high level score for switch proto detected.														
<i>critical</i>	Use the critical level score for switch proto detected.															
mimefragmented	Threat weight score for mimefragmented detected.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable threat weight scoring for mimefragmented detected.</td></tr><tr><td><i>low</i></td><td>Use the low level score for mimefragmented detected.</td></tr><tr><td><i>medium</i></td><td>Use the medium level score for mimefragmented detected.</td></tr><tr><td><i>high</i></td><td>Use the high level score for mimefragmented detected.</td></tr><tr><td><i>critical</i></td><td>Use the critical level score for mimefragmented detected.</td></tr></table>	Option	Description	<i>disable</i>	Disable threat weight scoring for mimefragmented detected.	<i>low</i>	Use the low level score for mimefragmented detected.	<i>medium</i>	Use the medium level score for mimefragmented detected.	<i>high</i>	Use the high level score for mimefragmented detected.	<i>critical</i>	Use the critical level score for mimefragmented detected.			
	Option	Description														
	<i>disable</i>	Disable threat weight scoring for mimefragmented detected.														
	<i>low</i>	Use the low level score for mimefragmented detected.														
	<i>medium</i>	Use the medium level score for mimefragmented detected.														
	<i>high</i>	Use the high level score for mimefragmented detected.														
<i>critical</i>	Use the critical level score for mimefragmented detected.															
virus-file-type-executable	Threat weight score for virus (file type executable) detected.	option	-	medium												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable threat weight scoring for virus (filetype executable) detected.</td></tr><tr><td><i>low</i></td><td>Use the low level score for virus (filetype executable) detected.</td></tr><tr><td><i>medium</i></td><td>Use the medium level score for virus (filetype executable) detected.</td></tr><tr><td><i>high</i></td><td>Use the high level score for virus (filetype executable) detected.</td></tr><tr><td><i>critical</i></td><td>Use the critical level score for virus (filetype executable) detected.</td></tr></table>	Option	Description	<i>disable</i>	Disable threat weight scoring for virus (filetype executable) detected.	<i>low</i>	Use the low level score for virus (filetype executable) detected.	<i>medium</i>	Use the medium level score for virus (filetype executable) detected.	<i>high</i>	Use the high level score for virus (filetype executable) detected.	<i>critical</i>	Use the critical level score for virus (filetype executable) detected.			
	Option	Description														
	<i>disable</i>	Disable threat weight scoring for virus (filetype executable) detected.														
	<i>low</i>	Use the low level score for virus (filetype executable) detected.														
	<i>medium</i>	Use the medium level score for virus (filetype executable) detected.														
	<i>high</i>	Use the high level score for virus (filetype executable) detected.														
<i>critical</i>	Use the critical level score for virus (filetype executable) detected.															
virus-outbreak-prevention	Threat weight score for virus (outbreak prevention) event.	option	-	critical												

Parameter	Description	Type	Size	Default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable threat weight scoring for virus (outbreak prevention) event.</td></tr><tr><td><i>low</i></td><td>Use the low level score for virus (outbreak prevention) event.</td></tr><tr><td><i>medium</i></td><td>Use the medium level score for virus (outbreak prevention) event.</td></tr><tr><td><i>high</i></td><td>Use the high level score for virus (outbreak prevention) event.</td></tr><tr><td><i>critical</i></td><td>Use the critical level score for virus (outbreak prevention) event.</td></tr></table>	Option	Description	<i>disable</i>	Disable threat weight scoring for virus (outbreak prevention) event.	<i>low</i>	Use the low level score for virus (outbreak prevention) event.	<i>medium</i>	Use the medium level score for virus (outbreak prevention) event.	<i>high</i>	Use the high level score for virus (outbreak prevention) event.	<i>critical</i>	Use the critical level score for virus (outbreak prevention) event.			
	Option	Description														
	<i>disable</i>	Disable threat weight scoring for virus (outbreak prevention) event.														
	<i>low</i>	Use the low level score for virus (outbreak prevention) event.														
	<i>medium</i>	Use the medium level score for virus (outbreak prevention) event.														
	<i>high</i>	Use the high level score for virus (outbreak prevention) event.														
<i>critical</i>	Use the critical level score for virus (outbreak prevention) event.															
content-disarm	Threat weight score for virus (content disarm) detected.	option	-	medium												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable threat weight scoring for virus (content disarm) detected.</td></tr><tr><td><i>low</i></td><td>Use the low level score for virus (content disarm) detected.</td></tr><tr><td><i>medium</i></td><td>Use the medium level score for virus (content disarm) detected.</td></tr><tr><td><i>high</i></td><td>Use the high level score for virus (content disarm) detected.</td></tr><tr><td><i>critical</i></td><td>Use the critical level score for virus (content disarm) detected.</td></tr></table>	Option	Description	<i>disable</i>	Disable threat weight scoring for virus (content disarm) detected.	<i>low</i>	Use the low level score for virus (content disarm) detected.	<i>medium</i>	Use the medium level score for virus (content disarm) detected.	<i>high</i>	Use the high level score for virus (content disarm) detected.	<i>critical</i>	Use the critical level score for virus (content disarm) detected.			
	Option	Description														
	<i>disable</i>	Disable threat weight scoring for virus (content disarm) detected.														
	<i>low</i>	Use the low level score for virus (content disarm) detected.														
	<i>medium</i>	Use the medium level score for virus (content disarm) detected.														
	<i>high</i>	Use the high level score for virus (content disarm) detected.														
<i>critical</i>	Use the critical level score for virus (content disarm) detected.															
malware-list	Threat weight score for virus (malware list) detected.	option	-	medium												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable threat weight scoring for virus (malware list) detected.</td></tr><tr><td><i>low</i></td><td>Use the low level score for virus (malware list) detected.</td></tr><tr><td><i>medium</i></td><td>Use the medium level score for virus (malware list) detected.</td></tr><tr><td><i>high</i></td><td>Use the high level score for virus (malware list) detected.</td></tr><tr><td><i>critical</i></td><td>Use the critical level score for virus (malware list) detected.</td></tr></table>	Option	Description	<i>disable</i>	Disable threat weight scoring for virus (malware list) detected.	<i>low</i>	Use the low level score for virus (malware list) detected.	<i>medium</i>	Use the medium level score for virus (malware list) detected.	<i>high</i>	Use the high level score for virus (malware list) detected.	<i>critical</i>	Use the critical level score for virus (malware list) detected.			
	Option	Description														
	<i>disable</i>	Disable threat weight scoring for virus (malware list) detected.														
	<i>low</i>	Use the low level score for virus (malware list) detected.														
	<i>medium</i>	Use the medium level score for virus (malware list) detected.														
	<i>high</i>	Use the high level score for virus (malware list) detected.														
<i>critical</i>	Use the critical level score for virus (malware list) detected.															
ems-threat-feed	Threat weight score for virus (EMS threat feed) detected.	option	-	medium												

Parameter	Description	Type	Size	Default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable threat weight scoring for virus (EMS threat feed) detected.</td></tr><tr><td><i>low</i></td><td>Use the low level score for virus (EMS threat feed) detected.</td></tr><tr><td><i>medium</i></td><td>Use the medium level score for virus (EMS threat feed) detected.</td></tr><tr><td><i>high</i></td><td>Use the high level score for virus (EMS threat feed) detected.</td></tr><tr><td><i>critical</i></td><td>Use the critical level score for virus (EMS threat feed) detected.</td></tr></table>	Option	Description	<i>disable</i>	Disable threat weight scoring for virus (EMS threat feed) detected.	<i>low</i>	Use the low level score for virus (EMS threat feed) detected.	<i>medium</i>	Use the medium level score for virus (EMS threat feed) detected.	<i>high</i>	Use the high level score for virus (EMS threat feed) detected.	<i>critical</i>	Use the critical level score for virus (EMS threat feed) detected.			
	Option	Description														
	<i>disable</i>	Disable threat weight scoring for virus (EMS threat feed) detected.														
	<i>low</i>	Use the low level score for virus (EMS threat feed) detected.														
	<i>medium</i>	Use the medium level score for virus (EMS threat feed) detected.														
	<i>high</i>	Use the high level score for virus (EMS threat feed) detected.														
<i>critical</i>	Use the critical level score for virus (EMS threat feed) detected.															
fsa-malicious	Threat weight score for FortiSandbox malicious malware detected.	option	-	critical												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable threat weight scoring for FortiSandbox malicious malware detected.</td></tr><tr><td><i>low</i></td><td>Use the low level score for FortiSandbox malicious malware detected.</td></tr><tr><td><i>medium</i></td><td>Use the medium level score for FortiSandbox malicious malware detected.</td></tr><tr><td><i>high</i></td><td>Use the high level score for FortiSandbox malicious malware detected.</td></tr><tr><td><i>critical</i></td><td>Use the critical level score for FortiSandbox malicious malware detected.</td></tr></table>	Option	Description	<i>disable</i>	Disable threat weight scoring for FortiSandbox malicious malware detected.	<i>low</i>	Use the low level score for FortiSandbox malicious malware detected.	<i>medium</i>	Use the medium level score for FortiSandbox malicious malware detected.	<i>high</i>	Use the high level score for FortiSandbox malicious malware detected.	<i>critical</i>	Use the critical level score for FortiSandbox malicious malware detected.			
	Option	Description														
	<i>disable</i>	Disable threat weight scoring for FortiSandbox malicious malware detected.														
	<i>low</i>	Use the low level score for FortiSandbox malicious malware detected.														
	<i>medium</i>	Use the medium level score for FortiSandbox malicious malware detected.														
	<i>high</i>	Use the high level score for FortiSandbox malicious malware detected.														
<i>critical</i>	Use the critical level score for FortiSandbox malicious malware detected.															
fsa-high-risk	Threat weight score for FortiSandbox high risk malware detected.	option	-	high												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable threat weight scoring for FortiSandbox high risk malware detected.</td></tr><tr><td><i>low</i></td><td>Use the low level score for FortiSandbox high risk malware detected.</td></tr><tr><td><i>medium</i></td><td>Use the medium level score for FortiSandbox high risk malware detected.</td></tr><tr><td><i>high</i></td><td>Use the high level score for FortiSandbox high risk malware detected.</td></tr></table>	Option	Description	<i>disable</i>	Disable threat weight scoring for FortiSandbox high risk malware detected.	<i>low</i>	Use the low level score for FortiSandbox high risk malware detected.	<i>medium</i>	Use the medium level score for FortiSandbox high risk malware detected.	<i>high</i>	Use the high level score for FortiSandbox high risk malware detected.					
	Option	Description														
	<i>disable</i>	Disable threat weight scoring for FortiSandbox high risk malware detected.														
	<i>low</i>	Use the low level score for FortiSandbox high risk malware detected.														
<i>medium</i>	Use the medium level score for FortiSandbox high risk malware detected.															
<i>high</i>	Use the high level score for FortiSandbox high risk malware detected.															

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>critical</i>	Use the critical level score for FortiSandbox high risk malware detected.		
fsa-medium-risk	Threat weight score for FortiSandbox medium risk malware detected.	option	-	medium
	Option	Description		
	<i>disable</i>	Disable threat weight scoring for FortiSandbox medium risk malware detected.		
	<i>low</i>	Use the low level score for FortiSandbox medium risk malware detected.		
	<i>medium</i>	Use the medium level score for FortiSandbox medium risk malware detected.		
	<i>high</i>	Use the high level score for FortiSandbox medium risk malware detected.		
	<i>critical</i>	Use the critical level score for FortiSandbox medium risk malware detected.		

config ips

Parameter	Description	Type	Size	Default
info-severity	Threat weight score for IPS info severity events.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable threat weight scoring for IPS info severity events.		
	<i>low</i>	Use the low level score for IPS info severity events.		
	<i>medium</i>	Use the medium level score for IPS info severity events.		
	<i>high</i>	Use the high level score for IPS info severity events.		
	<i>critical</i>	Use the critical level score for IPS info severity events.		
low-severity	Threat weight score for IPS low severity events.	option	-	low
	Option	Description		
	<i>disable</i>	Disable threat weight scoring for IPS low severity events.		
	<i>low</i>	Use the low level score for IPS low severity events.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>medium</i>	Use the medium level score for IPS low severity events.		
	<i>high</i>	Use the high level score for IPS low severity events.		
	<i>critical</i>	Use the critical level score for IPS low severity events.		
medium-severity	Threat weight score for IPS medium severity events.	option	-	medium
	Option	Description		
	<i>disable</i>	Disable threat weight scoring for IPS medium severity events.		
	<i>low</i>	Use the low level score for IPS medium severity events.		
	<i>medium</i>	Use the medium level score for IPS medium severity events.		
	<i>high</i>	Use the high level score for IPS medium severity events.		
	<i>critical</i>	Use the critical level score for IPS medium severity events.		
high-severity	Threat weight score for IPS high severity events.	option	-	high
	Option	Description		
	<i>disable</i>	Disable threat weight scoring for IPS high severity events.		
	<i>low</i>	Use the low level score for IPS high severity events.		
	<i>medium</i>	Use the medium level score for IPS high severity events.		
	<i>high</i>	Use the high level score for IPS high severity events.		
	<i>critical</i>	Use the critical level score for IPS high severity events.		
critical-severity	Threat weight score for IPS critical severity events.	option	-	critical
	Option	Description		
	<i>disable</i>	Disable threat weight scoring for IPS critical severity events.		
	<i>low</i>	Use the low level score for IPS critical severity events.		
	<i>medium</i>	Use the medium level score for IPS critical severity events.		
	<i>high</i>	Use the high level score for IPS critical severity events.		
	<i>critical</i>	Use the critical level score for IPS critical severity events.		

config web

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 255	0
category	Threat weight score for web category filtering matches.	integer	Minimum value: 0 Maximum value: 255	0
level	Threat weight score for web category filtering matches.	option	-	low
		Option	Description	
		<i>disable</i>	Disable threat weight scoring for web category filtering matches.	
		<i>low</i>	Use the low level score for web category filtering matches.	
		<i>medium</i>	Use the medium level score for web category filtering matches.	
		<i>high</i>	Use the high level score for web category filtering matches.	
		<i>critical</i>	Use the critical level score for web category filtering matches.	

config geolocation

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 255	0
country	Country code.	string	Maximum length: 2	
level	Threat weight score for Geolocation-based events.	option	-	low
		Option	Description	
		<i>disable</i>	Disable threat weight scoring for Geolocation-based events.	
		<i>low</i>	Use the low level score for Geolocation-based events.	
		<i>medium</i>	Use the medium level score for Geolocation-based events.	
		<i>high</i>	Use the high level score for Geolocation-based events.	
		<i>critical</i>	Use the critical level score for Geolocation-based events.	

config application

Parameter	Description	Type	Size	Default												
id	Entry ID.	integer	Minimum value: 0 Maximum value: 255	0												
category	Application category.	integer	Minimum value: 0 Maximum value: 65535	0												
level	Threat weight score for Application events.	option	-	low												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable threat weight scoring for Application events.</td></tr><tr><td><i>low</i></td><td>Use the low level score for Application events.</td></tr><tr><td><i>medium</i></td><td>Use the medium level score for Application events.</td></tr><tr><td><i>high</i></td><td>Use the high level score for Application events.</td></tr><tr><td><i>critical</i></td><td>Use the critical level score for Application events.</td></tr></table>				Option	Description	<i>disable</i>	Disable threat weight scoring for Application events.	<i>low</i>	Use the low level score for Application events.	<i>medium</i>	Use the medium level score for Application events.	<i>high</i>	Use the high level score for Application events.	<i>critical</i>	Use the critical level score for Application events.
Option	Description															
<i>disable</i>	Disable threat weight scoring for Application events.															
<i>low</i>	Use the low level score for Application events.															
<i>medium</i>	Use the medium level score for Application events.															
<i>high</i>	Use the high level score for Application events.															
<i>critical</i>	Use the critical level score for Application events.															

config log webtrends filter

Filters for WebTrends.

```
config log webtrends filter
  Description: Filters for WebTrends.
  set severity [emergency|alert|...]
  set forward-traffic [enable|disable]
  set local-traffic [enable|disable]
  set multicast-traffic [enable|disable]
  set sniffer-traffic [enable|disable]
  set ztna-traffic [enable|disable]
  set http-transaction [enable|disable]
  set anomaly [enable|disable]
  set voip [enable|disable]
  config free-style
    Description: Free style filters.
    edit <id>
      set category [traffic|event|...]
      set filter {string}
      set filter-type [include|exclude]
    next
```

```
end
end
```

config log webtrends filter

Parameter	Description	Type	Size	Default																		
severity	Lowest severity level to log to WebTrends.	option	-	information																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>emergency</i></td><td>Emergency level.</td></tr><tr><td><i>alert</i></td><td>Alert level.</td></tr><tr><td><i>critical</i></td><td>Critical level.</td></tr><tr><td><i>error</i></td><td>Error level.</td></tr><tr><td><i>warning</i></td><td>Warning level.</td></tr><tr><td><i>notification</i></td><td>Notification level.</td></tr><tr><td><i>information</i></td><td>Information level.</td></tr><tr><td><i>debug</i></td><td>Debug level.</td></tr></table>	Option	Description	<i>emergency</i>	Emergency level.	<i>alert</i>	Alert level.	<i>critical</i>	Critical level.	<i>error</i>	Error level.	<i>warning</i>	Warning level.	<i>notification</i>	Notification level.	<i>information</i>	Information level.	<i>debug</i>	Debug level.			
Option	Description																					
<i>emergency</i>	Emergency level.																					
<i>alert</i>	Alert level.																					
<i>critical</i>	Critical level.																					
<i>error</i>	Error level.																					
<i>warning</i>	Warning level.																					
<i>notification</i>	Notification level.																					
<i>information</i>	Information level.																					
<i>debug</i>	Debug level.																					
forward-traffic	Enable/disable forward traffic logging.	option	-	enable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable forward traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable forward traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable forward traffic logging.	<i>disable</i>	Disable forward traffic logging.															
Option	Description																					
<i>enable</i>	Enable forward traffic logging.																					
<i>disable</i>	Disable forward traffic logging.																					
local-traffic	Enable/disable local in or out traffic logging.	option	-	enable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable local in or out traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable local in or out traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable local in or out traffic logging.	<i>disable</i>	Disable local in or out traffic logging.															
Option	Description																					
<i>enable</i>	Enable local in or out traffic logging.																					
<i>disable</i>	Disable local in or out traffic logging.																					
multicast-traffic	Enable/disable multicast traffic logging.	option	-	enable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable multicast traffic logging.</td></tr><tr><td><i>disable</i></td><td>Disable multicast traffic logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable multicast traffic logging.	<i>disable</i>	Disable multicast traffic logging.															
Option	Description																					
<i>enable</i>	Enable multicast traffic logging.																					
<i>disable</i>	Disable multicast traffic logging.																					
sniffer-traffic	Enable/disable sniffer traffic logging.	option	-	enable																		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable sniffer traffic logging.		
	<i>disable</i>	Disable sniffer traffic logging.		
ztna-traffic	Enable/disable ztna traffic logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ztna traffic logging.		
	<i>disable</i>	Disable ztna traffic logging.		
http-transaction	Enable/disable log http-transaction messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable http transaction logging.		
	<i>disable</i>	Disable http transaction logging.		
anomaly	Enable/disable anomaly logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable anomaly logging.		
	<i>disable</i>	Disable anomaly logging.		
voip	Enable/disable VoIP logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VoIP logging.		
	<i>disable</i>	Disable VoIP logging.		

config free-style

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	Log category.	option	-	traffic

Parameter	Description	Type	Size	Default																																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>traffic</i></td><td>Traffic log.</td></tr><tr><td><i>event</i></td><td>Event log.</td></tr><tr><td><i>virus</i></td><td>Antivirus log.</td></tr><tr><td><i>webfilter</i></td><td>Web filter log.</td></tr><tr><td><i>attack</i></td><td>Attack log.</td></tr><tr><td><i>spam</i></td><td>Antispam log.</td></tr><tr><td><i>anomaly</i></td><td>Anomaly log.</td></tr><tr><td><i>voip</i></td><td>VoIP log.</td></tr><tr><td><i>dlp</i></td><td>DLP log.</td></tr><tr><td><i>app-ctrl</i></td><td>Application control log.</td></tr><tr><td><i>waf</i></td><td>Web application firewall log.</td></tr><tr><td><i>dns</i></td><td>DNS detail log.</td></tr><tr><td><i>ssh</i></td><td>SSH log.</td></tr><tr><td><i>ssl</i></td><td>SSL log.</td></tr><tr><td><i>file-filter</i></td><td>File filter log.</td></tr><tr><td><i>icap</i></td><td>ICAP log.</td></tr></table>	Option	Description	<i>traffic</i>	Traffic log.	<i>event</i>	Event log.	<i>virus</i>	Antivirus log.	<i>webfilter</i>	Web filter log.	<i>attack</i>	Attack log.	<i>spam</i>	Antispam log.	<i>anomaly</i>	Anomaly log.	<i>voip</i>	VoIP log.	<i>dlp</i>	DLP log.	<i>app-ctrl</i>	Application control log.	<i>waf</i>	Web application firewall log.	<i>dns</i>	DNS detail log.	<i>ssh</i>	SSH log.	<i>ssl</i>	SSL log.	<i>file-filter</i>	File filter log.	<i>icap</i>	ICAP log.			
	Option	Description																																				
	<i>traffic</i>	Traffic log.																																				
	<i>event</i>	Event log.																																				
	<i>virus</i>	Antivirus log.																																				
	<i>webfilter</i>	Web filter log.																																				
	<i>attack</i>	Attack log.																																				
	<i>spam</i>	Antispam log.																																				
	<i>anomaly</i>	Anomaly log.																																				
	<i>voip</i>	VoIP log.																																				
	<i>dlp</i>	DLP log.																																				
	<i>app-ctrl</i>	Application control log.																																				
	<i>waf</i>	Web application firewall log.																																				
	<i>dns</i>	DNS detail log.																																				
	<i>ssh</i>	SSH log.																																				
	<i>ssl</i>	SSL log.																																				
	<i>file-filter</i>	File filter log.																																				
<i>icap</i>	ICAP log.																																					
filter	Free style filter string.	string	Maximum length: 1023																																			
filter-type	Include/exclude logs that match the filter.	option	-	include																																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>include</i></td><td>Include logs that match the filter.</td></tr><tr><td><i>exclude</i></td><td>Exclude logs that match the filter.</td></tr></table>	Option	Description	<i>include</i>	Include logs that match the filter.	<i>exclude</i>	Exclude logs that match the filter.																															
	Option	Description																																				
	<i>include</i>	Include logs that match the filter.																																				
<i>exclude</i>	Exclude logs that match the filter.																																					

config log webtrends setting

Settings for WebTrends.

```

config log webtrends setting
    Description: Settings for WebTrends.
    set status [enable|disable]
    set server {string}
end

```


config log webtrends setting

Parameter	Description	Type	Size	Default
status	Enable/disable logging to WebTrends.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable logging to WebTrends.		
	<i>disable</i>	Disble logging to WebTrends.		
server	Address of the remote WebTrends server.	string	Maximum length: 63	

mgmt-data

This section includes syntax for the following commands:

- [config mgmt-data status on page 690](#)

config mgmt-data status

Status for mgmt-data.

```
config mgmt-data status
    Description: Status for mgmt-data.
end
```

report

This section includes syntax for the following commands:

- [config report layout on page 691](#)
- [config report setting on page 699](#)
- [config report sql status on page 700](#)

config report layout

Report layout configuration.

```
config report layout
  Description: Report layout configuration.
  edit <name>
    set title {string}
    set subtitle {string}
    set description {string}
    set style-theme {string}
    set options {option1}, {option2}, ...
    set format {option1}, {option2}, ...
    set schedule-type [demand|daily|...]
    set day [sunday|monday|...]
    set time {user}
    set cutoff-option [run-time|custom]
    set cutoff-time {user}
    set email-send [enable|disable]
    set email-recipients {string}
    set max-pdf-report {integer}
  config page
    Description: Configure report page.
    set paper [a4|letter]
    set column-break-before {option1}, {option2}, ...
    set page-break-before {option1}, {option2}, ...
    set options {option1}, {option2}, ...
  config header
    Description: Configure report page header.
    set style {string}
  config header-item
    Description: Configure report header item.
    edit <id>
      set description {string}
      set type [text|image]
      set style {string}
      set content {string}
      set img-src {string}
```

```

        next
    end
end
config footer
    Description: Configure report page footer.
    set style {string}
    config footer-item
        Description: Configure report footer item.
        edit <id>
            set description {string}
            set type [text|image]
            set style {string}
            set content {string}
            set img-src {string}
        next
    end
end
end
config body-item
    Description: Configure report body item.
    edit <id>
        set description {string}
        set type [text|image|...]
        set style {string}
        set top-n {integer}
        config parameters
            Description: Parameters.
            edit <id>
                set name {string}
                set value {string}
            next
        end
        set text-component [text|heading1|...]
        set content {string}
        set img-src {string}
        set chart {string}
        set chart-options {option1}, {option2}, ...
        set misc-component [hline|page-break|...]
        set title {string}
    next
end
next
end
end

```

config report layout

Parameter	Description	Type	Size	Default
name	Report layout name.	string	Maximum length: 35	

Parameter	Description	Type	Size	Default												
title	Report title.	string	Maximum length: 127													
subtitle	Report subtitle.	string	Maximum length: 127													
description	Description.	string	Maximum length: 127													
style-theme	Report style theme.	string	Maximum length: 35													
options	Report layout options.	option	-	include-table-of-content auto-numbering-heading view-chart-as-heading												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>include-table-of-content</i></td><td>Include table of content in the report.</td></tr><tr><td><i>auto-numbering-heading</i></td><td>Prepend heading with auto numbering.</td></tr><tr><td><i>view-chart-as-heading</i></td><td>Auto add heading for each chart.</td></tr><tr><td><i>show-html-navbar-before-heading</i></td><td>Show HTML navigation bar before each heading.</td></tr><tr><td><i>dummy-option</i></td><td>Use this option if you need none of the above options.</td></tr></table>				Option	Description	<i>include-table-of-content</i>	Include table of content in the report.	<i>auto-numbering-heading</i>	Prepend heading with auto numbering.	<i>view-chart-as-heading</i>	Auto add heading for each chart.	<i>show-html-navbar-before-heading</i>	Show HTML navigation bar before each heading.	<i>dummy-option</i>	Use this option if you need none of the above options.
Option	Description															
<i>include-table-of-content</i>	Include table of content in the report.															
<i>auto-numbering-heading</i>	Prepend heading with auto numbering.															
<i>view-chart-as-heading</i>	Auto add heading for each chart.															
<i>show-html-navbar-before-heading</i>	Show HTML navigation bar before each heading.															
<i>dummy-option</i>	Use this option if you need none of the above options.															
format	Report format.	option	-	pdf												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>pdf</i></td><td>PDF.</td></tr></table>				Option	Description	<i>pdf</i>	PDF.								
Option	Description															
<i>pdf</i>	PDF.															
schedule-type	Report schedule type.	option	-	daily												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>demand</i></td><td>Run on demand.</td></tr></table>				Option	Description	<i>demand</i>	Run on demand.								
Option	Description															
<i>demand</i>	Run on demand.															

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>daily</i>	Schedule daily.		
	<i>weekly</i>	Schedule weekly.		
day	Schedule days of week to generate report.	option	-	sunday
	Option	Description		
	<i>sunday</i>	Sunday.		
	<i>monday</i>	Monday.		
	<i>tuesday</i>	Tuesday.		
	<i>wednesday</i>	Wednesday.		
	<i>thursday</i>	Thursday.		
	<i>friday</i>	Friday.		
	<i>saturday</i>	Saturday.		
time	Schedule time to generate report (format = hh:mm).	user	Not Specified	
cutoff-option	Cutoff-option is either run-time or custom.	option	-	run-time
	Option	Description		
	<i>run-time</i>	Run time.		
	<i>custom</i>	Custom.		
cutoff-time	Custom cutoff time to generate report (format = hh:mm).	user	Not Specified	
email-send	Enable/disable sending emails after reports are generated.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable sending emails after generating reports.		
	<i>disable</i>	Disable sending emails after generating reports.		
email-recipients	Email recipients for generated reports.	string	Maximum length: 511	
max-pdf-report	Maximum number of PDF reports to keep at one time (oldest report is overwritten).	integer	Minimum value: 1 Maximum value: 365	31

config page

Parameter	Description	Type	Size	Default								
paper	Report page paper.	option	-	a4								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>a4</i></td><td>A 4 paper.</td></tr><tr><td><i>letter</i></td><td>Letter paper.</td></tr></table>	Option	Description	<i>a4</i>	A 4 paper.	<i>letter</i>	Letter paper.					
Option	Description											
<i>a4</i>	A 4 paper.											
<i>letter</i>	Letter paper.											
column-break-before	Report page auto column break before heading.	option	-									
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>heading1</i></td><td>Column break before heading 1.</td></tr><tr><td><i>heading2</i></td><td>Column break before heading 2.</td></tr><tr><td><i>heading3</i></td><td>Column break before heading 3.</td></tr></table>	Option	Description	<i>heading1</i>	Column break before heading 1.	<i>heading2</i>	Column break before heading 2.	<i>heading3</i>	Column break before heading 3.			
Option	Description											
<i>heading1</i>	Column break before heading 1.											
<i>heading2</i>	Column break before heading 2.											
<i>heading3</i>	Column break before heading 3.											
page-break-before	Report page auto page break before heading.	option	-									
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>heading1</i></td><td>Page break before heading 1.</td></tr><tr><td><i>heading2</i></td><td>Page break before heading 2.</td></tr><tr><td><i>heading3</i></td><td>Page break before heading 3.</td></tr></table>	Option	Description	<i>heading1</i>	Page break before heading 1.	<i>heading2</i>	Page break before heading 2.	<i>heading3</i>	Page break before heading 3.			
Option	Description											
<i>heading1</i>	Page break before heading 1.											
<i>heading2</i>	Page break before heading 2.											
<i>heading3</i>	Page break before heading 3.											
options	Report page options.	option	-									
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>header-on-first-page</i></td><td>Show header on first page.</td></tr><tr><td><i>footer-on-first-page</i></td><td>Show footer on first page.</td></tr></table>	Option	Description	<i>header-on-first-page</i>	Show header on first page.	<i>footer-on-first-page</i>	Show footer on first page.					
Option	Description											
<i>header-on-first-page</i>	Show header on first page.											
<i>footer-on-first-page</i>	Show footer on first page.											

config header

Parameter	Description	Type	Size	Default
style	Report header style.	string	Maximum length: 71	

config header-item

Parameter	Description	Type	Size	Default						
id	Report item ID.	integer	Minimum value: 0 Maximum value: 4294967295	0						
description	Description.	string	Maximum length: 63							
type	Report item type.	option	-	text						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>text</i></td><td>Text.</td></tr><tr><td><i>image</i></td><td>Image.</td></tr></table>				Option	Description	<i>text</i>	Text.	<i>image</i>	Image.
Option	Description									
<i>text</i>	Text.									
<i>image</i>	Image.									
style	Report item style.	string	Maximum length: 71							
content	Report item text content.	string	Maximum length: 511							
img-src	Report item image file name.	string	Maximum length: 127							

config footer

Parameter	Description	Type	Size	Default
style	Report footer style.	string	Maximum length: 71	

config footer-item

Parameter	Description	Type	Size	Default
id	Report item ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
description	Description.	string	Maximum length: 63	
type	Report item type.	option	-	text

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>text</i>	Text.		
	<i>image</i>	Image.		
style	Report item style.	string	Maximum length: 71	
content	Report item text content.	string	Maximum length: 511	
img-src	Report item image file name.	string	Maximum length: 127	

config body-item

Parameter	Description	Type	Size	Default
id	Report item ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
description	Description.	string	Maximum length: 63	
type	Report item type.	option	-	text
	Option	Description		
	<i>text</i>	Text.		
	<i>image</i>	Image.		
	<i>chart</i>	Chart.		
	<i>misc</i>	Miscellaneous.		
style	Report item style.	string	Maximum length: 71	
top-n	Value of top.	integer	Minimum value: 0 Maximum value: 4294967295	0
text-component	Report item text component.	option	-	text

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>text</i>	Normal text.		
	<i>heading1</i>	Heading 1.		
	<i>heading2</i>	Heading 2.		
	<i>heading3</i>	Heading 3.		
content	Report item text content.	string	Maximum length: 511	
img-src	Report item image file name.	string	Maximum length: 127	
chart	Report item chart name.	string	Maximum length: 71	
chart-options	Report chart options.	option	-	include-no-data hide-title show-caption
	Option	Description		
	<i>include-no-data</i>	Include chart with no data.		
	<i>hide-title</i>	Hide chart title.		
	<i>show-caption</i>	Show chart caption.		
misc-component	Report item miscellaneous component.	option	-	hline
	Option	Description		
	<i>hline</i>	Horizontal line.		
	<i>page-break</i>	Page break.		
	<i>column-break</i>	Column break.		
	<i>section-start</i>	Section start.		
title	Report section title.	string	Maximum length: 511	

config parameters

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Field name that match field of parameters defined in dataset.	string	Maximum length: 127	
value	Value to replace corresponding field of parameters defined in dataset.	string	Maximum length: 1023	

config report setting

Report setting configuration.

```
config report setting
  Description: Report setting configuration.
  set pdf-report [enable|disable]
  set fortiview [enable|disable]
  set report-source {option1}, {option2}, ...
  set web-browsing-threshold {integer}
  set top-n {integer}
end
```

config report setting

Parameter	Description	Type	Size	Default						
pdf-report	Enable/disable PDF report.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable PDF report.</td></tr><tr><td><i>disable</i></td><td>Disable PDF report.</td></tr></table>	Option	Description	<i>enable</i>	Enable PDF report.	<i>disable</i>	Disable PDF report.			
Option	Description									
<i>enable</i>	Enable PDF report.									
<i>disable</i>	Disable PDF report.									
fortiview	Enable/disable historical FortiView.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable historical FortiView.</td></tr><tr><td><i>disable</i></td><td>Disable historical FortiView.</td></tr></table>	Option	Description	<i>enable</i>	Enable historical FortiView.	<i>disable</i>	Disable historical FortiView.			
Option	Description									
<i>enable</i>	Enable historical FortiView.									
<i>disable</i>	Disable historical FortiView.									

Parameter	Description	Type	Size	Default								
report-source	Report log source.	option	-	forward-traffic								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>forward-traffic</i></td><td>Report includes forward traffic logs.</td></tr><tr><td><i>sniffer-traffic</i></td><td>Report includes sniffer traffic logs.</td></tr><tr><td><i>local-deny-traffic</i></td><td>Report includes local deny traffic logs.</td></tr></table>	Option	Description	<i>forward-traffic</i>	Report includes forward traffic logs.	<i>sniffer-traffic</i>	Report includes sniffer traffic logs.	<i>local-deny-traffic</i>	Report includes local deny traffic logs.			
Option	Description											
<i>forward-traffic</i>	Report includes forward traffic logs.											
<i>sniffer-traffic</i>	Report includes sniffer traffic logs.											
<i>local-deny-traffic</i>	Report includes local deny traffic logs.											
web-browsing-threshold	Web browsing time calculation threshold (3 - 15 min).	integer	Minimum value: 3 Maximum value: 15	3								
top-n	Number of items to populate (1000 - 20000).	integer	Minimum value: 1000 Maximum value: 20000	1000								

config report sql status

Show report database status.

```
config report sql status
    Description: Show report database status.
end
```

router

This section includes syntax for the following commands:

- [config router policy on page 701](#)
- [config router static on page 703](#)
- [config router static6 on page 705](#)

config router policy

Configure IPv4 routing policies.

```
config router policy
  Description: Configure IPv4 routing policies.
  edit <seq-num>
    set input-device <name1>, <name2>, ...
    set src <subnet1>, <subnet2>, ...
    set dst <subnet1>, <subnet2>, ...
    set action [deny|permit]
    set protocol {integer}
    set start-port {integer}
    set end-port {integer}
    set start-source-port {integer}
    set end-source-port {integer}
    set gateway {ipv4-address}
    set output-device {string}
    set status [enable|disable]
    set comments {var-string}
    set internet-service-id <id1>, <id2>, ...
    set internet-service-custom <name1>, <name2>, ...
  next
end
```

config router policy

Parameter	Description	Type	Size	Default
seq-num	Sequence number(1-65535).	integer	Minimum value: 1 Maximum value: 2048	0
input-device <name>	Incoming interface name. Interface name.	string	Maximum length: 79	

Parameter	Description	Type	Size	Default						
src <subnet>	Source IP and mask (x.x.x.x/x). IP and mask.	string	Maximum length: 79							
dst <subnet>	Destination IP and mask (x.x.x.x/x). IP and mask.	string	Maximum length: 79							
action	Action of the policy route.	option	-	permit						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>deny</td><td>Do not search policy route table.</td></tr><tr><td>permit</td><td>Use this policy route for forwarding.</td></tr></table>				Option	Description	deny	Do not search policy route table.	permit	Use this policy route for forwarding.
Option	Description									
deny	Do not search policy route table.									
permit	Use this policy route for forwarding.									
protocol	Protocol number (0 - 255).	integer	Minimum value: 0 Maximum value: 255	0						
start-port	Start destination port number (1 - 65534).	integer	Minimum value: 0 Maximum value: 65535	1						
end-port	End destination port number (1 - 65534).	integer	Minimum value: 0 Maximum value: 65535	65534						
start-source-port	Start source port number (1 - 65534).	integer	Minimum value: 0 Maximum value: 65535	1						
end-source-port	End source port number (1 - 65534).	integer	Minimum value: 0 Maximum value: 65535	65534						
gateway	IP address of the gateway.	ipv4-address	Not Specified	0.0.0.0						
output-device	Outgoing interface name.	string	Maximum length: 35							
status	Enable/disable this policy route.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable this policy route.</td></tr><tr><td>disable</td><td>Disable this policy route.</td></tr></table>				Option	Description	enable	Enable this policy route.	disable	Disable this policy route.
Option	Description									
enable	Enable this policy route.									
disable	Disable this policy route.									

Parameter	Description	Type	Size	Default
comments	Optional comments.	var-string	Maximum length: 255	
internet-service-id <id>	Destination Internet Service ID. Destination Internet Service ID.	integer	Minimum value: 0 Maximum value: 4294967295	
internet-service-custom <name>	Custom Destination Internet Service name. Custom Destination Internet Service name.	string	Maximum length: 79	

config router static

Configure IPv4 static routing tables.

```

config router static
  Description: Configure IPv4 static routing tables.
  edit <seq-num>
    set status [enable|disable]
    set dst {ipv4-classnet}
    set src {ipv4-classnet}
    set gateway {ipv4-address}
    set preferred-source {ipv4-address}
    set weight {integer}
    set priority {integer}
    set device {string}
    set comment {var-string}
    set blackhole [enable|disable]
    set sdwan-zone <name1>, <name2>, ...
    set dstaddr {string}
    set link-monitor-exempt [enable|disable]
    set tag {integer}
  next
end

```

config router static

Parameter	Description	Type	Size	Default
seq-num	Sequence number.	integer	Minimum value: 0 Maximum value: 4294967295	0
status	Enable/disable this static route.	option	-	enable
	Option		Description	
	<i>enable</i>		Enable static route.	
	<i>disable</i>		Disable static route.	
dst	Destination IP and mask for this route.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0
src	Source prefix for this route.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0
gateway	Gateway IP for this route.	ipv4-address	Not Specified	0.0.0.0
preferred-source	Preferred source IP for this route.	ipv4-address	Not Specified	0.0.0.0
weight	Administrative weight (0 - 255).	integer	Minimum value: 0 Maximum value: 255	0
priority	Administrative priority (1 - 65535).	integer	Minimum value: 1 Maximum value: 65535	1
device	Gateway out interface or tunnel.	string	Maximum length: 35	
comment	Optional comments.	var-string	Maximum length: 255	
blackhole	Enable/disable black hole.	option	-	disable
	Option		Description	
	<i>enable</i>		Enable black hole.	
	<i>disable</i>		Disable black hole.	

Parameter	Description	Type	Size	Default						
sdwan-zone <name>	Choose SD-WAN Zone. SD-WAN zone name.	string	Maximum length: 79							
dstaddr	Name of firewall address or address group.	string	Maximum length: 79							
link-monitor-exempt	Enable/disable withdrawal of this static route when link monitor or health check is down.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Keep this static route when link monitor or health check is down.</td></tr><tr><td><i>disable</i></td><td>Withdraw this static route when link monitor or health check is down. (default)</td></tr></table>				Option	Description	<i>enable</i>	Keep this static route when link monitor or health check is down.	<i>disable</i>	Withdraw this static route when link monitor or health check is down. (default)
Option	Description									
<i>enable</i>	Keep this static route when link monitor or health check is down.									
<i>disable</i>	Withdraw this static route when link monitor or health check is down. (default)									
tag	Route tag.	integer	Minimum value: 0 Maximum value: 4294967295	0						

config router static6

Configure IPv6 static routing tables.

```

config router static6
    Description: Configure IPv6 static routing tables.
    edit <seq-num>
        set status [enable|disable]
        set dst {ipv6-network}
        set gateway {ipv6-address}
        set device {string}
        set devindex {integer}
        set weight {integer}
        set priority {integer}
        set comment {var-string}
        set blackhole [enable|disable]
        set sdwan-zone <name1>, <name2>, ...
        set dstaddr {string}
        set link-monitor-exempt [enable|disable]
    next
end

```

config router static6

Parameter	Description	Type	Size	Default
seq-num	Sequence number.	integer	Minimum value: 0 Maximum value: 4294967295	0
status	Enable/disable this static route.	option	-	enable
	Option		Description	
	<i>enable</i>		Enable static route.	
	<i>disable</i>		Disable static route.	
dst	Destination IPv6 prefix.	ipv6-network	Not Specified	::/0
gateway	IPv6 address of the gateway.	ipv6-address	Not Specified	::
device	Gateway out interface or tunnel.	string	Maximum length: 35	
devindex	Device index (0 - 4294967295).	integer	Minimum value: 0 Maximum value: 4294967295	0
weight	Administrative weight (0 - 255).	integer	Minimum value: 0 Maximum value: 255	0
priority	Administrative priority (1 - 65535).	integer	Minimum value: 1 Maximum value: 65535	1024
comment	Optional comments.	var-string	Maximum length: 255	
blackhole	Enable/disable black hole.	option	-	disable
	Option		Description	
	<i>enable</i>		Enable black hole.	
	<i>disable</i>		Disable black hole.	

Parameter	Description	Type	Size	Default
sdwan-zone <name>	Choose SD-WAN Zone. SD-WAN zone name.	string	Maximum length: 79	
dstaddr	Name of firewall address or address group.	string	Maximum length: 79	
link- monitor- exempt	Enable/disable withdrawal of this static route when link monitor or health check is down.	option	-	disable
		Option	Description	
		<i>enable</i>	Keep this static route when link monitor or health check is down.	
		<i>disable</i>	Withdraw this static route when link monitor or health check is down. (default)	

rule

This section includes syntax for the following commands:

- [config rule fmwp on page 708](#)

config rule fmwp

Show FMWP rules.

```
config rule fmwp
  Description: Show FMWP rules.
  edit <name>
    set log [disable|enable]
    set log-packet [disable|enable]
    set action [pass|block]
    set group {string}
    set severity {user}
    set location {user}
    set os {user}
    set application {user}
    set service {user}
    set rule-id {integer}
    set rev {integer}
    set date {integer}
    config metadata
      Description: Meta data.
      edit <id>
        set metaid {integer}
        set valueid {integer}
      next
    end
  next
end
```

config rule fmwp

Parameter	Description	Type	Size	Default
name	Rule name.	string	Maximum length: 63	
log	Enable/disable logging.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable logging.		
	<i>enable</i>	Enable logging.		
log-packet	Enable/disable packet logging.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable packet logging.		
	<i>enable</i>	Enable packet logging.		
action	Action.	option	-	pass
	Option	Description		
	<i>pass</i>	Pass or allow matching traffic.		
	<i>block</i>	Block or drop matching traffic.		
group	Group.	string	Maximum length: 63	
severity	Severity.	user	Not Specified	
location	Vulnerable location.	user	Not Specified	
os	Vulnerable operation systems.	user	Not Specified	
application	Vulnerable applications.	user	Not Specified	
service	Vulnerable service.	user	Not Specified	
rule-id	Rule ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
rev	Revision.	integer	Minimum value: 0 Maximum value: 4294967295	0
date	Date.	integer	Minimum value: 0 Maximum value: 4294967295	0

config metadata

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
metaid	Meta ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
valueid	Value ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

ssh-filter

This section includes syntax for the following commands:

- [config ssh-filter profile on page 711](#)

config ssh-filter profile

Configure SSH filter profile.

```
config ssh-filter profile
  Description: Configure SSH filter profile.
  edit <name>
    set block {option1}, {option2}, ...
    set log {option1}, {option2}, ...
    set default-command-log [enable|disable]
    config shell-commands
      Description: SSH command filter.
      edit <id>
        set type [simple|regex]
        set pattern {string}
        set action [block|allow]
        set log [enable|disable]
        set alert [enable|disable]
        set severity [low|medium|...]
      next
    end
  next
end
```

config ssh-filter profile

Parameter	Description	Type	Size	Default
name	SSH filter profile name.	string	Maximum length: 35	
block	SSH blocking options.	option	-	
	Option	Description		
	<i>x11</i>	X server forwarding.		
	<i>shell</i>	SSH shell.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>exec</i>	SSH execution.		
	<i>port-forward</i>	Port forwarding.		
	<i>tun-forward</i>	Tunnel forwarding.		
	<i>sftp</i>	SFTP.		
	<i>scp</i>	SCP.		
	<i>unknown</i>	Unknown channel.		
log	SSH logging options.	option	-	
	Option	Description		
	<i>x11</i>	X server forwarding.		
	<i>shell</i>	SSH shell.		
	<i>exec</i>	SSH execution.		
	<i>port-forward</i>	Port forwarding.		
	<i>tun-forward</i>	Tunnel forwarding.		
	<i>sftp</i>	SFTP.		
	<i>scp</i>	SCP.		
	<i>unknown</i>	Unknown channel.		
default-command-log	Enable/disable logging unmatched shell commands.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable log unmatched shell commands.		
	<i>disable</i>	Disable log unmatched shell commands.		

config shell-commands

Parameter	Description	Type	Size	Default
id	Id.	integer	Minimum value: 0 Maximum value: 4294967295	0

Parameter	Description	Type	Size	Default
type	Matching type.	option	-	simple
	Option	Description		
	<i>simple</i>	Match single command.		
	<i>regex</i>	Match command line using regular expression.		
pattern	SSH shell command pattern.	string	Maximum length: 128	
action	Action to take for SSH shell command matches.	option	-	block
	Option	Description		
	<i>block</i>	Block the SSH shell command.		
	<i>allow</i>	Allow the SSH shell command.		
log	Enable/disable logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable logging.		
	<i>disable</i>	Disable logging.		
alert	Enable/disable alert.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable alert.		
	<i>disable</i>	Disable alert.		
severity	Log severity.	option	-	medium
	Option	Description		
	<i>low</i>	Severity low.		
	<i>medium</i>	Severity medium.		
	<i>high</i>	Severity high.		
	<i>critical</i>	Severity critical.		

system

This section includes syntax for the following commands:

- [config system accprofile on page 717](#)
- [config system acme on page 727](#)
- [config system admin on page 728](#)
- [config system affinity-interrupt on page 736](#)
- [config system affinity-packet-redistribution on page 737](#)
- [config system alarm on page 738](#)
- [config system alias on page 741](#)
- [config system api-user on page 741](#)
- [config system arp-table on page 743](#)
- [config system arp on page 743](#)
- [config system auto-install on page 759](#)
- [config system auto-script on page 760](#)
- [config system auto-update status on page 761](#)
- [config system auto-update versions on page 761](#)
- [config system automation-action on page 744](#)
- [config system automation-destination on page 750](#)
- [config system automation-stitch on page 751](#)
- [config system automation-trigger on page 752](#)
- [config system autoupdate schedule on page 757](#)
- [config system autoupdate tunneling on page 758](#)
- [config system central-management on page 761](#)
- [config system central-mgmt on page 766](#)
- [config system checksum status on page 767](#)
- [config system cmdb on page 767](#)
- [config system console on page 767](#)
- [config system csf on page 768](#)
- [config system custom-language on page 774](#)
- [config system ddns on page 775](#)
- [config system device-upgrade on page 778](#)
- [config system dhcp6 server on page 796](#)
- [config system dhcp server on page 781](#)
- [config system dns-database on page 802](#)
- [config system dns-server on page 806](#)
- [config system dns on page 799](#)
- [config system dscp-based-priority on page 807](#)
- [config system email-server on page 808](#)

-
- [config system external-resource on page 810](#)
 - [config system fabric-vpn on page 813](#)
 - [config system federated-upgrade on page 817](#)
 - [config system fips-cc on page 820](#)
 - [config system fortianalyzer-connectivity on page 821](#)
 - [config system fortiguard-log-service on page 832](#)
 - [config system fortiguard-service on page 832](#)
 - [config system fortiguard on page 821](#)
 - [config system fortindr on page 833](#)
 - [config system fortisandbox on page 833](#)
 - [config system fsso-polling on page 835](#)
 - [config system ftm-push on page 836](#)
 - [config system geoip-country on page 837](#)
 - [config system geoip-override on page 838](#)
 - [config system global on page 839](#)
 - [config system gre-tunnel on page 895](#)
 - [config system ha-lic on page 908](#)
 - [config system ha-monitor on page 909](#)
 - [config system ha-nonsync-csum on page 909](#)
 - [config system ha on page 897](#)
 - [config system info admin ssh on page 910](#)
 - [config system info admin status on page 910](#)
 - [config system interface on page 910](#)
 - [config system ip-conflict status on page 949](#)
 - [config system ipam on page 944](#)
 - [config system ips-urlfilter-dns on page 947](#)
 - [config system ips-urlfilter-dns6 on page 948](#)
 - [config system ips on page 946](#)
 - [config system ipv6-neighbor-cache on page 948](#)
 - [config system link-monitor on page 949](#)
 - [config system management-tunnel on page 954](#)
 - [config system mgmt-csum on page 956](#)
 - [config system nethsm on page 956](#)
 - [config system network-visibility on page 960](#)
 - [config system ntp on page 961](#)
 - [config system object-tagging on page 965](#)
 - [config system password-policy-guest-admin on page 968](#)
 - [config system password-policy on page 966](#)
 - [config system performance status on page 971](#)
 - [config system performance top on page 971](#)
 - [config system probe-response on page 971](#)
 - [config system proxy-arp on page 973](#)
 - [config system ptp on page 973](#)

-
- [config system replacemsg-group on page 991](#)
 - [config system replacemsg-image on page 1004](#)
 - [config system replacemsg admin on page 975](#)
 - [config system replacemsg alertmail on page 976](#)
 - [config system replacemsg auth on page 977](#)
 - [config system replacemsg automation on page 978](#)
 - [config system replacemsg custom-message on page 979](#)
 - [config system replacemsg fortiguard-wf on page 980](#)
 - [config system replacemsg ftp on page 981](#)
 - [config system replacemsg http on page 982](#)
 - [config system replacemsg icap on page 983](#)
 - [config system replacemsg mail on page 984](#)
 - [config system replacemsg nac-quar on page 985](#)
 - [config system replacemsg spam on page 986](#)
 - [config system replacemsg sslvpn on page 987](#)
 - [config system replacemsg traffic-quota on page 988](#)
 - [config system replacemsg utm on page 989](#)
 - [config system replacemsg webproxy on page 990](#)
 - [config system resource-limits on page 1005](#)
 - [config system saml on page 1007](#)
 - [config system sdn-connector on page 1011](#)
 - [config system session-ttl on page 1020](#)
 - [config system session on page 1019](#)
 - [config system session6 on page 1019](#)
 - [config system settings on page 1021](#)
 - [config system sms-server on page 1035](#)
 - [config system snmp community on page 1036](#)
 - [config system snmp mib-view on page 1042](#)
 - [config system snmp sysinfo on page 1043](#)
 - [config system snmp user on page 1045](#)
 - [config system source-ip status on page 1050](#)
 - [config system span-port on page 1050](#)
 - [config system speed-test-schedule on page 1051](#)
 - [config system speed-test-server on page 1053](#)
 - [config system speed-test-setting on page 1055](#)
 - [config system sso-admin on page 1055](#)
 - [config system sso-forticloud-admin on page 1056](#)
 - [config system sso-fortigate-cloud-admin on page 1057](#)
 - [config system startup-error-log on page 1057](#)
 - [config system status on page 1057](#)
 - [config system storage on page 1058](#)
 - [config system vdom-dns on page 1060](#)
 - [config system vdom-exception on page 1062](#)

- [config system vdom-link on page 1065](#)
- [config system vdom-property on page 1065](#)
- [config system vdom-radius-server on page 1067](#)
- [config system vdom on page 1059](#)
- [config system vne-tunnel on page 1067](#)
- [config system vxlan on page 1069](#)
- [config system wccp on page 1070](#)
- [config system zone on page 1074](#)

config system accprofile

Configure access profiles for system administrators.

```
config system accprofile
  Description: Configure access profiles for system administrators.
  edit <name>
    set scope [vdom|global]
    set comments {var-string}
    set secfabgrp [none|read|...]
    set ftviewgrp [none|read|...]
    set authgrp [none|read|...]
    set sysgrp [none|read|...]
    set netgrp [none|read|...]
    set loggrp [none|read|...]
    set fwgrp [none|read|...]
    set vpngrp [none|read|...]
    set utmgrp [none|read|...]
    set wanoptgrp [none|read|...]
    config netgrp-permission
      Description: Custom network permission.
      set cfg [none|read|...]
      set packet-capture [none|read|...]
      set route-cfg [none|read|...]
    end
    config sysgrp-permission
      Description: Custom system permission.
      set admin [none|read|...]
      set upd [none|read|...]
      set cfg [none|read|...]
      set mnt [none|read|...]
    end
    config fwgrp-permission
      Description: Custom firewall permission.
      set policy [none|read|...]
      set address [none|read|...]
      set service [none|read|...]
      set schedule [none|read|...]
      set others [none|read|...]
    end
  end
```

```

config loggrp-permission
    Description: Custom Log & Report permission.
    set config [none|read|...]
    set data-access [none|read|...]
    set report-access [none|read|...]
    set threat-weight [none|read|...]
end
config utmgrp-permission
    Description: Custom Security Profile permissions.
    set antivirus [none|read|...]
    set ips [none|read|...]
    set webfilter [none|read|...]
    set emailfilter [none|read|...]
    set data-leak-prevention [none|read|...]
    set file-filter [none|read|...]
    set application-control [none|read|...]
    set icap [none|read|...]
    set voip [none|read|...]
    set waf [none|read|...]
    set dnsfilter [none|read|...]
    set endpoint-control [none|read|...]
    set videofilter [none|read|...]
end
set admintimeout-override [enable|disable]
set admintimeout {integer}
set system-diagnostics [enable|disable]
set system-execute-ssh [enable|disable]
set system-execute-telnet [enable|disable]
next
end

```

config system accprofile

Parameter	Description	Type	Size	Default						
name	Profile name.	string	Maximum length: 35							
scope	Scope of admin access: global or specific VDOM(s).	option	-	vdom						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>vdom</i></td><td>VDOM access.</td></tr><tr><td><i>global</i></td><td>Global access.</td></tr></table>				Option	Description	<i>vdom</i>	VDOM access.	<i>global</i>	Global access.
	Option	Description								
	<i>vdom</i>	VDOM access.								
<i>global</i>	Global access.									
comments	Comment.	var-string	Maximum length: 255							
secfabgrp	Security Fabric.	option	-	none						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
ftviewgrp	FortiView.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
authgrp	Administrator access to Users and Devices.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
sysgrp	System Configuration.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
	<i>custom</i>	Customized access.		
netgrp	Network Configuration.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
	<i>custom</i>	Customized access.		
loggrp	Administrator access to Logging and Reporting including viewing log messages.	option	-	none

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
	<i>custom</i>	Customized access.		
fwgrp	Administrator access to the Firewall configuration.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
	<i>custom</i>	Customized access.		
vpngrp	Administrator access to IPsec, SSL, PPTP, and L2TP VPN.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
utmgrp	Administrator access to Security Profiles.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
	<i>custom</i>	Customized access.		
wanoptgrp	Administrator access to WAN Opt & Cache.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>read-write</i>	Read/write access.		
admintimeout-override	Enable/disable overriding the global administrator idle timeout.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable overriding the global administrator idle timeout.		
	<i>disable</i>	Disable overriding the global administrator idle timeout.		
admintimeout	Administrator timeout for this access profile (0 - 480 min, default = 10, 0 means never timeout).	integer	Minimum value: 1 Maximum value: 480	10
system-diagnostics	Enable/disable permission to run system diagnostic commands.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable permission to run system diagnostic commands.		
	<i>disable</i>	Disable permission to run system diagnostic commands.		
system-execute-ssh	Enable/disable permission to execute SSH commands.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable permission to execute SSH commands.		
	<i>disable</i>	Disable permission to execute SSH commands.		
system-execute-telnet	Enable/disable permission to execute TELNET commands.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable permission to execute TELNET commands.		
	<i>disable</i>	Disable permission to execute TELNET commands.		

config netgrp-permission

Parameter	Description	Type	Size	Default
cfg	Network Configuration.	option	-	none

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
packet-capture	Packet Capture Configuration.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
route-cfg	Router Configuration.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		

config sysgrp-permission

Parameter	Description	Type	Size	Default
admin	Administrator Users.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
upd	FortiGuard Updates.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
cfg	System Configuration.	option	-	none

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
mnt	Maintenance.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		

config fwgrp-permission

Parameter	Description	Type	Size	Default
policy	Policy Configuration.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
address	Address Configuration.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
service	Service Configuration.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
schedule	Schedule Configuration.	option	-	none

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
others	Other Firewall Configuration.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		

config loggrp-permission

Parameter	Description	Type	Size	Default
config	Log & Report configuration.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
data-access	Log & Report Data Access.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
report-access	Log & Report Report Access.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
threat-weight	Log & Report Threat Weight.	option	-	none

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		

config utmgrp-permission

Parameter	Description	Type	Size	Default
antivirus	Antivirus profiles and settings.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
ips	IPS profiles and settings.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
webfilter	Web Filter profiles and settings.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
emailfilter	Email Filter and settings.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
data-leak-prevention	DLP profiles and settings.	option	-	none

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
file-filter	File-filter profiles and settings.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
application-control	Application Control profiles and settings.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
icap	ICAP profiles and settings.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
voip	VoIP profiles and settings.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
waf	Web Application Firewall profiles and settings.	option	-	none
	Option	Description		
	<i>none</i>	No access.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
dnsfilter	DNS Filter profiles and settings.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
endpoint-control	FortiClient Profiles.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		
videofilter	Video filter profiles and settings.	option	-	none
	Option	Description		
	<i>none</i>	No access.		
	<i>read</i>	Read access.		
	<i>read-write</i>	Read/write access.		

config system acme

Configure ACME client.

```

config system acme
  Description: Configure ACME client.
  set interface <interface-name1>, <interface-name2>, ...
  set source-ip {ipv4-address}
  set source-ip6 {ipv6-address}
  config accounts
    Description: ACME accounts list.
    edit <id>
      set status {string}
      set url {string}
      set ca_url {string}

```

```

        set email {string}
        set privatekey {string}
    next
end
end

```

config system acme

Parameter	Description	Type	Size	Default
interface <interface-name>	Interface(s) on which the ACME client will listen for challenges. Interface name.	string	Maximum length: 79	
source-ip	Source IPv4 address used to connect to the ACME server.	ipv4-address	Not Specified	0.0.0.0
source-ip6	Source IPv6 address used to connect to the ACME server.	ipv6-address	Not Specified	::

config accounts

Parameter	Description	Type	Size	Default
id	Account id.	string	Maximum length: 255	
status	Account status.	string	Maximum length: 127	
url	Account url.	string	Maximum length: 511	
ca_url	Account ca_url.	string	Maximum length: 255	
email	Account email.	string	Maximum length: 255	
privatekey	Account Private Key.	string	Maximum length: 8191	

config system admin

Configure admin users.

```

config system admin
    Description: Configure admin users.

```



```

edit <name>
    set wildcard [enable|disable]
    set remote-auth [enable|disable]
    set remote-group {string}
    set password {password-2}
    set peer-auth [enable|disable]
    set peer-group {string}
    set trusthost1 {ipv4-classnet}
    set trusthost2 {ipv4-classnet}
    set trusthost3 {ipv4-classnet}
    set trusthost4 {ipv4-classnet}
    set trusthost5 {ipv4-classnet}
    set trusthost6 {ipv4-classnet}
    set trusthost7 {ipv4-classnet}
    set trusthost8 {ipv4-classnet}
    set trusthost9 {ipv4-classnet}
    set trusthost10 {ipv4-classnet}
    set ip6-trusthost1 {ipv6-prefix}
    set ip6-trusthost2 {ipv6-prefix}
    set ip6-trusthost3 {ipv6-prefix}
    set ip6-trusthost4 {ipv6-prefix}
    set ip6-trusthost5 {ipv6-prefix}
    set ip6-trusthost6 {ipv6-prefix}
    set ip6-trusthost7 {ipv6-prefix}
    set ip6-trusthost8 {ipv6-prefix}
    set ip6-trusthost9 {ipv6-prefix}
    set ip6-trusthost10 {ipv6-prefix}
    set accprofile {string}
    set allow-remove-admin-session [enable|disable]
    set comments {var-string}
    set vdom <name1>, <name2>, ...
    set ssh-public-key1 {user}
    set ssh-public-key2 {user}
    set ssh-public-key3 {user}
    set ssh-certificate {string}
    set schedule {string}
    set accprofile-override [enable|disable]
    set vdom-override [enable|disable]
    set password-expire {user}
    set force-password-change [enable|disable]
    set two-factor [disable|fortitoken|...]
    set two-factor-authentication [fortitoken|email|...]
    set two-factor-notification [email|sms]
    set fortitoken {string}
    set email-to {string}
    set sms-server [fortiguard|custom]
    set sms-custom-server {string}
    set sms-phone {string}
    set guest-auth [disable|enable]
    set guest-usergroups <name1>, <name2>, ...
    set guest-lang {string}
    config trusthosts

```

```

        Description: Table of trusthosts.
        edit <id>
            set type [ipv4|ipv6]
            set ipv4 {ipv4-classnet}
            set ipv6 {ipv6-prefix}
        next
    end
next
end
end

```

config system admin

Parameter	Description	Type	Size	Default
name	User name.	string	Maximum length: 64	
wildcard	Enable/disable wildcard RADIUS authentication.	option	-	disable
	Option		Description	
	<i>enable</i>		Enable username wildcard.	
	<i>disable</i>		Disable username wildcard.	
remote-auth	Enable/disable authentication using a remote RADIUS, LDAP, or TACACS+ server.	option	-	disable
	Option		Description	
	<i>enable</i>		Enable remote authentication.	
	<i>disable</i>		Disable remote authentication.	
remote-group	User group name used for remote auth.	string	Maximum length: 35	
password	Admin user password.	password-2	Not Specified	
peer-auth	Set to enable peer certificate authentication (for HTTPS admin access).	option	-	disable
	Option		Description	
	<i>enable</i>		Enable peer.	
	<i>disable</i>		Disable peer.	

Parameter	Description	Type	Size	Default
peer-group	Name of peer group defined under config user group which has PKI members. Used for peer certificate authentication (for HTTPS admin access).	string	Maximum length: 35	
trusthost1	Any IPv4 address or subnet address and netmask from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv4 address.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0
trusthost2	Any IPv4 address or subnet address and netmask from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv4 address.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0
trusthost3	Any IPv4 address or subnet address and netmask from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv4 address.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0
trusthost4	Any IPv4 address or subnet address and netmask from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv4 address.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0
trusthost5	Any IPv4 address or subnet address and netmask from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv4 address.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0
trusthost6	Any IPv4 address or subnet address and netmask from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv4 address.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0
trusthost7	Any IPv4 address or subnet address and netmask from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv4 address.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0

Parameter	Description	Type	Size	Default
trusthost8	Any IPv4 address or subnet address and netmask from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv4 address.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0
trusthost9	Any IPv4 address or subnet address and netmask from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv4 address.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0
trusthost10	Any IPv4 address or subnet address and netmask from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv4 address.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0
ip6-trusthost1	Any IPv6 address from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv6 address.	ipv6-prefix	Not Specified	::/0
ip6-trusthost2	Any IPv6 address from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv6 address.	ipv6-prefix	Not Specified	::/0
ip6-trusthost3	Any IPv6 address from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv6 address.	ipv6-prefix	Not Specified	::/0
ip6-trusthost4	Any IPv6 address from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv6 address.	ipv6-prefix	Not Specified	::/0
ip6-trusthost5	Any IPv6 address from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv6 address.	ipv6-prefix	Not Specified	::/0
ip6-trusthost6	Any IPv6 address from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv6 address.	ipv6-prefix	Not Specified	::/0

Parameter	Description	Type	Size	Default						
ip6-trusthost7	Any IPv6 address from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv6 address.	ipv6-prefix	Not Specified	::/0						
ip6-trusthost8	Any IPv6 address from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv6 address.	ipv6-prefix	Not Specified	::/0						
ip6-trusthost9	Any IPv6 address from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv6 address.	ipv6-prefix	Not Specified	::/0						
ip6-trusthost10	Any IPv6 address from which the administrator can connect to the FortiProxy unit. Default allows access from any IPv6 address.	ipv6-prefix	Not Specified	::/0						
accprofile	Access profile for this administrator. Access profiles control administrator access to FortiProxy features.	string	Maximum length: 35							
allow-remove-admin-session	Enable/disable allow admin session to be removed by privileged admin users.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable allow-remove option.</td></tr><tr><td><i>disable</i></td><td>Disable allow-remove option.</td></tr></table>				Option	Description	<i>enable</i>	Enable allow-remove option.	<i>disable</i>	Disable allow-remove option.
Option	Description									
<i>enable</i>	Enable allow-remove option.									
<i>disable</i>	Disable allow-remove option.									
comments	Comment.	var-string	Maximum length: 255							
vdom <name>	Virtual domain(s) that the administrator can access. Virtual domain name.	string	Maximum length: 79							
ssh-public-key1	Public key of an SSH client. The client is authenticated without being asked for credentials. Create the public-private key pair in the SSH client application.	user	Not Specified							
ssh-public-key2	Public key of an SSH client. The client is authenticated without being asked for credentials. Create the public-private key pair in the SSH client application.	user	Not Specified							

Parameter	Description	Type	Size	Default						
ssh-public-key3	Public key of an SSH client. The client is authenticated without being asked for credentials. Create the public-private key pair in the SSH client application.	user	Not Specified							
ssh-certificate	Select the certificate to be used by the FortiProxy for authentication with an SSH client.	string	Maximum length: 35							
schedule	Firewall schedule used to restrict when the administrator can log in. No schedule means no restrictions.	string	Maximum length: 35							
accprofile-override	Enable to use the name of an access profile provided by the remote authentication server to control the FortiProxy features that this administrator can access.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable access profile override.</td></tr><tr><td>disable</td><td>Disable access profile override.</td></tr></table>				Option	Description	enable	Enable access profile override.	disable	Disable access profile override.
Option	Description									
enable	Enable access profile override.									
disable	Disable access profile override.									
vdom-override	Enable to use the names of VDOMs provided by the remote authentication server to control the VDOMs that this administrator can access.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable VDOM override.</td></tr><tr><td>disable</td><td>Disable VDOM override.</td></tr></table>				Option	Description	enable	Enable VDOM override.	disable	Disable VDOM override.
Option	Description									
enable	Enable VDOM override.									
disable	Disable VDOM override.									
password-expire	Password expire time.	user	Not Specified							
force-password-change	Enable/disable force password change on next login.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable force password change on next login.</td></tr><tr><td>disable</td><td>Disable force password change on next login.</td></tr></table>				Option	Description	enable	Enable force password change on next login.	disable	Disable force password change on next login.
Option	Description									
enable	Enable force password change on next login.									
disable	Disable force password change on next login.									

Parameter	Description	Type	Size	Default												
two-factor	Enable/disable two-factor authentication.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable two-factor authentication.</td></tr><tr><td><i>fortitoken</i></td><td>Use FortiToken or FortiToken mobile two-factor authentication.</td></tr><tr><td><i>fortitoken-cloud</i></td><td>FortiToken Cloud Service.</td></tr><tr><td><i>email</i></td><td>Send a two-factor authentication code to the configured email-to email address.</td></tr><tr><td><i>sms</i></td><td>Send a two-factor authentication code to the configured sms-server and sms-phone.</td></tr></table>	Option	Description	<i>disable</i>	Disable two-factor authentication.	<i>fortitoken</i>	Use FortiToken or FortiToken mobile two-factor authentication.	<i>fortitoken-cloud</i>	FortiToken Cloud Service.	<i>email</i>	Send a two-factor authentication code to the configured email-to email address.	<i>sms</i>	Send a two-factor authentication code to the configured sms-server and sms-phone.			
Option	Description															
<i>disable</i>	Disable two-factor authentication.															
<i>fortitoken</i>	Use FortiToken or FortiToken mobile two-factor authentication.															
<i>fortitoken-cloud</i>	FortiToken Cloud Service.															
<i>email</i>	Send a two-factor authentication code to the configured email-to email address.															
<i>sms</i>	Send a two-factor authentication code to the configured sms-server and sms-phone.															
two-factor-authentication	Authentication method by FortiToken Cloud.	option	-													
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>fortitoken</i></td><td>FortiToken authentication.</td></tr><tr><td><i>email</i></td><td>Email one time password.</td></tr><tr><td><i>sms</i></td><td>SMS one time password.</td></tr></table>	Option	Description	<i>fortitoken</i>	FortiToken authentication.	<i>email</i>	Email one time password.	<i>sms</i>	SMS one time password.							
Option	Description															
<i>fortitoken</i>	FortiToken authentication.															
<i>email</i>	Email one time password.															
<i>sms</i>	SMS one time password.															
two-factor-notification	Notification method for user activation by FortiToken Cloud.	option	-													
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>email</i></td><td>Email notification for activation code.</td></tr><tr><td><i>sms</i></td><td>SMS notification for activation code.</td></tr></table>	Option	Description	<i>email</i>	Email notification for activation code.	<i>sms</i>	SMS notification for activation code.									
Option	Description															
<i>email</i>	Email notification for activation code.															
<i>sms</i>	SMS notification for activation code.															
fortitoken	This administrator's FortiToken serial number.	string	Maximum length: 16													
email-to	This administrator's email address.	string	Maximum length: 63													
sms-server	Send SMS messages using the FortiGuard SMS server or a custom server.	option	-	fortiguard												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>fortiguard</i></td><td>Send SMS by FortiGuard.</td></tr><tr><td><i>custom</i></td><td>Send SMS by custom server.</td></tr></table>	Option	Description	<i>fortiguard</i>	Send SMS by FortiGuard.	<i>custom</i>	Send SMS by custom server.									
Option	Description															
<i>fortiguard</i>	Send SMS by FortiGuard.															
<i>custom</i>	Send SMS by custom server.															

Parameter	Description	Type	Size	Default						
sms-custom-server	Custom SMS server to send SMS messages to.	string	Maximum length: 35							
sms-phone	Phone number on which the administrator receives SMS messages.	string	Maximum length: 15							
guest-auth	Enable/disable guest authentication.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable guest authentication.</td></tr><tr><td><i>enable</i></td><td>Enable guest authentication.</td></tr></table>				Option	Description	<i>disable</i>	Disable guest authentication.	<i>enable</i>	Enable guest authentication.
	Option	Description								
	<i>disable</i>	Disable guest authentication.								
<i>enable</i>	Enable guest authentication.									
guest-usergroups <name>	Select guest user groups. Select guest user groups.	string	Maximum length: 79							
guest-lang	Guest management portal language.	string	Maximum length: 35							

config trusthosts

Parameter	Description	Type	Size	Default						
type	Trusthost type.	option	-	ipv4						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>ipv4</td><td>IPv4 trusthost.</td></tr><tr><td>ipv6</td><td>IPv6 trusthost.</td></tr></table>				Option	Description	ipv4	IPv4 trusthost.	ipv6	IPv6 trusthost.
	Option	Description								
	ipv4	IPv4 trusthost.								
ipv6	IPv6 trusthost.									
ipv4	IPv4 trusthost.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0						
ipv6	IPv6 trusthost.	ipv6-prefix	Not Specified	::/0						

config system affinity-interrupt

Configure interrupt affinity.

```
config system affinity-interrupt
  Description: Configure interrupt affinity.
  edit <id>
    set interrupt {string}
    set affinity-cpumask {string}
    set default-affinity-cpumask {string}
```



```
next
end
```

config system affinity-interrupt

Parameter	Description	Type	Size	Default
id	ID of the interrupt affinity setting.	integer	Minimum value: 0 Maximum value: 4294967295	0
interrupt	Interrupt name.	string	Maximum length: 127	
affinity-cpumask	Affinity setting (64-bit hexadecimal value in the format of 0xxxxxxxxxxxxxxxxx).	string	Maximum length: 127	
default-affinity-cpumask	Default affinity setting (64-bit hexadecimal value in the format of 0xxxxxxxxxxxxxxxxx).	string	Maximum length: 127	

config system affinity-packet-redistribution

Configure packet redistribution.

```
config system affinity-packet-redistribution
  Description: Configure packet redistribution.
  edit <id>
    set interface {string}
    set rxqid {integer}
    set affinity-cpumask {string}
  next
end
```

config system affinity-packet-redistribution

Parameter	Description	Type	Size	Default
id	ID of the packet redistribution setting.	integer	Minimum value: 0 Maximum value: 4294967295	0

Parameter	Description	Type	Size	Default
interface	Physical interface name on which to perform packet redistribution.	string	Maximum length: 127	
rxqid	ID of the receive queue (when the interface has multiple queues) on which to perform packet redistribution.	integer	Minimum value: 0 Maximum value: 255	0
affinity-cpumask	Affinity setting for VM throughput (64-bit hexadecimal value in the format of 0xxxxxxxxxxxxxxxxxx).	string	Maximum length: 127	

config system alarm

Configure alarm.

```

config system alarm
  Description: Configure alarm.
  set status [enable|disable]
  set audible [enable|disable]
  config groups
    Description: Alarm groups.
    edit <id>
      set period {integer}
      set admin-auth-failure-threshold {integer}
      set admin-auth-lockout-threshold {integer}
      set user-auth-failure-threshold {integer}
      set user-auth-lockout-threshold {integer}
      set replay-attempt-threshold {integer}
      set self-test-failure-threshold {integer}
      set log-full-warning-threshold {integer}
      set encryption-failure-threshold {integer}
      set decryption-failure-threshold {integer}
      config fw-policy-violations
        Description: Firewall policy violations.
        edit <id>
          set threshold {integer}
          set src-ip {ipv4-address}
          set dst-ip {ipv4-address}
          set src-port {integer}
          set dst-port {integer}
        next
      end
      set fw-policy-id {integer}
      set fw-policy-id-threshold {integer}
    next
  end
end
end

```

config system alarm

Parameter	Description	Type	Size	Default
status	Enable/disable alarm.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable alarm.		
	<i>disable</i>	Disable alarm.		
audible	Enable/disable audible alarm.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable audible alarm.		
	<i>disable</i>	Disable audible alarm.		

config groups

Parameter	Description	Type	Size	Default
id	Group ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
period	Time period in seconds (0 = from start up).	integer	Minimum value: 0 Maximum value: 4294967295	0
admin-auth-failure-threshold	Admin authentication failure threshold.	integer	Minimum value: 0 Maximum value: 1024	0
admin-auth-lockout-threshold	Admin authentication lockout threshold.	integer	Minimum value: 0 Maximum value: 1024	0
user-auth-failure-threshold	User authentication failure threshold.	integer	Minimum value: 0 Maximum value: 1024	0

Parameter	Description	Type	Size	Default
user-auth-lockout-threshold	User authentication lockout threshold.	integer	Minimum value: 0 Maximum value: 1024	0
replay-attempt-threshold	Replay attempt threshold.	integer	Minimum value: 0 Maximum value: 1024	0
self-test-failure-threshold	Self-test failure threshold.	integer	Minimum value: 0 Maximum value: 1	0
log-full-warning-threshold	Log full warning threshold.	integer	Minimum value: 0 Maximum value: 1024	0
encryption-failure-threshold	Encryption failure threshold.	integer	Minimum value: 0 Maximum value: 1024	0
decryption-failure-threshold	Decryption failure threshold.	integer	Minimum value: 0 Maximum value: 1024	0
fw-policy-id	Firewall policy ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
fw-policy-id-threshold	Firewall policy ID threshold.	integer	Minimum value: 0 Maximum value: 1024	0

config fw-policy-violations

Parameter	Description	Type	Size	Default
id	Firewall policy violations ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

Parameter	Description	Type	Size	Default
threshold	Firewall policy violation threshold.	integer	Minimum value: 0 Maximum value: 1024	0
src-ip	Source IP (0=all).	ipv4-address	Not Specified	0.0.0.0
dst-ip	Destination IP (0=all).	ipv4-address	Not Specified	0.0.0.0
src-port	Source port (0=all).	integer	Minimum value: 0 Maximum value: 65535	0
dst-port	Destination port (0=all).	integer	Minimum value: 0 Maximum value: 65535	0

config system alias

Configure alias command.

```
config system alias
  Description: Configure alias command.
  edit <name>
    set command {var-string}
  next
end
```

config system alias

Parameter	Description	Type	Size	Default
name	Alias command name.	string	Maximum length: 35	
command	Command list to execute.	var-string	Maximum length: 255	

config system api-user

Configure API users.

```

config system api-user
    Description: Configure API users.
    edit <name>
        set comments {var-string}
        set api-key {password-2}
        set accprofile {string}
        set vdom <name1>, <name2>, ...
        set schedule {string}
        set cors-allow-origin {string}
        set peer-auth [enable|disable]
        set peer-group {string}
        config trusthost
            Description: Trusthost.
            edit <id>
                set type [ipv4-trusthost|ipv6-trusthost]
                set ipv4-trusthost {ipv4-classnet}
                set ipv6-trusthost {ipv6-prefix}
            next
        end
    next
end

```

config system api-user

Parameter	Description	Type	Size	Default
name	User name.	string	Maximum length: 35	
comments	Comment.	var-string	Maximum length: 255	
api-key	Admin user password.	password-2	Not Specified	
accprofile	Admin user access profile.	string	Maximum length: 35	
vdom <name>	Virtual domains. Virtual domain name.	string	Maximum length: 79	
schedule	Schedule name.	string	Maximum length: 35	
cors-allow-origin	Value for Access-Control-Allow-Origin on API responses. Avoid using '*' if possible.	string	Maximum length: 269	
peer-auth	Enable/disable peer authentication.	option	-	disable

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable peer.</td></tr><tr><td><i>disable</i></td><td>Disable peer.</td></tr></table>				Option	Description	<i>enable</i>	Enable peer.	<i>disable</i>	Disable peer.
	Option	Description								
	<i>enable</i>	Enable peer.								
<i>disable</i>	Disable peer.									
peer-group	Peer group name.	string	Maximum length: 35							

config trusthost

Parameter	Description	Type	Size	Default						
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0						
type	Trusthost type.	option	-	ipv4-trusthost						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>ipv4-trusthost</td><td>IPv4 trusthost.</td></tr><tr><td>ipv6-trusthost</td><td>IPv6 trusthost.</td></tr></table>				Option	Description	ipv4-trusthost	IPv4 trusthost.	ipv6-trusthost	IPv6 trusthost.
	Option	Description								
	ipv4-trusthost	IPv4 trusthost.								
ipv6-trusthost	IPv6 trusthost.									
ipv4-trusthost	IPv4 trusted host address.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0						
ipv6-trusthost	IPv6 trusted host address.	ipv6-prefix	Not Specified	::/0						

config system arp

IPv4 ARP table.

```
config system arp
  Description: IPv4 ARP table.
end
```

config system arp-table

Configure ARP table.

```

config system arp-table
  Description: Configure ARP table.
  edit <id>
    set interface {string}
    set ip {ipv4-address}
    set mac {mac-address}
  next
end

```

config system arp-table

Parameter	Description	Type	Size	Default
id	Unique integer ID of the entry.	integer	Minimum value: 0 Maximum value: 4294967295	0
interface	Interface name.	string	Maximum length: 15	
ip	IP address.	ipv4-address	Not Specified	0.0.0.0
mac	MAC address.	mac-address	Not Specified	00:00:00:00:00:00

config system automation-action

Action for automation stitches.

```

config system automation-action
  Description: Action for automation stitches.
  edit <name>
    set description {var-string}
    set action-type [email|fortiexplorer-notification|...]
    set system-action [reboot|shutdown|...]
    set tls-certificate {string}
    set email-to <name1>, <name2>, ...
    set email-from {var-string}
    set email-subject {var-string}
    set minimum-interval {integer}
    set aws-api-key {password}
    set azure-function-authorization [anonymous|function|...]
    set azure-api-key {password}
    set alicloud-function-authorization [anonymous|function]
    set alicloud-access-key-id {string}
    set alicloud-access-key-secret {password}
  end
end

```



```

set message-type [text|json]
set message {string}
set replacement-message [enable|disable]
set replacemsg-group {string}
set protocol [http|https]
set method [post|put|...]
set uri {var-string}
set http-body {var-string}
set port {integer}
config http-headers
    Description: Request headers.
    edit <id>
        set key {var-string}
        set value {var-string}
    next
end
set verify-host-cert [enable|disable]
set script {var-string}
set output-size {integer}
set timeout {integer}
set password {password}
set execute-security-fabric [enable|disable]
set accprofile {string}
set security-tag {string}
set sdn-connector <name1>, <name2>, ...
next
end

```

config system automation-action

Parameter	Description	Type	Size	Default
name	Name.	string	Maximum length: 64	
description	Description.	var-string	Maximum length: 255	
action-type	Action type.	option	-	alert
		Option	Description	
		<i>email</i>	Send notification email.	
		<i>fortiexplorer-notification</i>	Send push notification to FortiExplorer.	
		<i>alert</i>	Generate FortiProxy dashboard alert.	
		<i>disable-ssid</i>	Disable interface.	

Parameter	Description	Type	Size	Default																														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>system-actions</i></td><td>Perform immediate system operations on this FortiGate unit.</td></tr><tr><td><i>quarantine</i></td><td>Quarantine host.</td></tr><tr><td><i>quarantine-forticlient</i></td><td>Quarantine FortiClient by EMS.</td></tr><tr><td><i>quarantine-nsx</i></td><td>Quarantine NSX instance.</td></tr><tr><td><i>quarantine-fortinac</i></td><td>Quarantine host by FortiNAC.</td></tr><tr><td><i>ban-ip</i></td><td>Ban IP address.</td></tr><tr><td><i>aws-lambda</i></td><td>Send log data to integrated AWS service.</td></tr><tr><td><i>azure-function</i></td><td>Send log data to an Azure function.</td></tr><tr><td><i>google-cloud-function</i></td><td>Send log data to a Google Cloud function.</td></tr><tr><td><i>alicloud-function</i></td><td>Send log data to an AliCloud function.</td></tr><tr><td><i>webhook</i></td><td>Send an HTTP request.</td></tr><tr><td><i>cli-script</i></td><td>Run CLI script.</td></tr><tr><td><i>slack-notification</i></td><td>Send a notification message to a Slack incoming webhook.</td></tr><tr><td><i>microsoft-teams-notification</i></td><td>Send a notification message to a Microsoft Teams incoming webhook.</td></tr></table>	Option	Description	<i>system-actions</i>	Perform immediate system operations on this FortiGate unit.	<i>quarantine</i>	Quarantine host.	<i>quarantine-forticlient</i>	Quarantine FortiClient by EMS.	<i>quarantine-nsx</i>	Quarantine NSX instance.	<i>quarantine-fortinac</i>	Quarantine host by FortiNAC.	<i>ban-ip</i>	Ban IP address.	<i>aws-lambda</i>	Send log data to integrated AWS service.	<i>azure-function</i>	Send log data to an Azure function.	<i>google-cloud-function</i>	Send log data to a Google Cloud function.	<i>alicloud-function</i>	Send log data to an AliCloud function.	<i>webhook</i>	Send an HTTP request.	<i>cli-script</i>	Run CLI script.	<i>slack-notification</i>	Send a notification message to a Slack incoming webhook.	<i>microsoft-teams-notification</i>	Send a notification message to a Microsoft Teams incoming webhook.			
	Option	Description																																
	<i>system-actions</i>	Perform immediate system operations on this FortiGate unit.																																
	<i>quarantine</i>	Quarantine host.																																
	<i>quarantine-forticlient</i>	Quarantine FortiClient by EMS.																																
	<i>quarantine-nsx</i>	Quarantine NSX instance.																																
	<i>quarantine-fortinac</i>	Quarantine host by FortiNAC.																																
	<i>ban-ip</i>	Ban IP address.																																
	<i>aws-lambda</i>	Send log data to integrated AWS service.																																
	<i>azure-function</i>	Send log data to an Azure function.																																
	<i>google-cloud-function</i>	Send log data to a Google Cloud function.																																
	<i>alicloud-function</i>	Send log data to an AliCloud function.																																
	<i>webhook</i>	Send an HTTP request.																																
	<i>cli-script</i>	Run CLI script.																																
	<i>slack-notification</i>	Send a notification message to a Slack incoming webhook.																																
<i>microsoft-teams-notification</i>	Send a notification message to a Microsoft Teams incoming webhook.																																	
system-action	System action type.	option	-																															
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>reboot</i></td><td>Reboot this FortiGate unit.</td></tr><tr><td><i>shutdown</i></td><td>Shutdown this FortiGate unit.</td></tr><tr><td><i>backup-config</i></td><td>Backup current configuration to the disk revisions.</td></tr></table>	Option	Description	<i>reboot</i>	Reboot this FortiGate unit.	<i>shutdown</i>	Shutdown this FortiGate unit.	<i>backup-config</i>	Backup current configuration to the disk revisions.																									
	Option	Description																																
	<i>reboot</i>	Reboot this FortiGate unit.																																
	<i>shutdown</i>	Shutdown this FortiGate unit.																																
<i>backup-config</i>	Backup current configuration to the disk revisions.																																	
tls-certificate	Custom TLS certificate for API request.	string	Maximum length: 35																															
email-to <name>	Email addresses. Email address.	string	Maximum length: 255																															
email-from	Email sender name.	var-string	Maximum length: 127																															

Parameter	Description	Type	Size	Default								
email-subject	Email subject.	var-string	Maximum length: 511									
minimum-interval	Limit execution to no more than once in this interval (in seconds).	integer	Minimum value: 0 Maximum value: 2592000	0								
aws-api-key	AWS API Gateway API key.	password	Not Specified									
azure-function-authorization	Azure function authorization level.	option	-	anonymous								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>anonymous</i></td><td>Anonymous authorization level (No authorization required).</td></tr><tr><td><i>function</i></td><td>Function authorization level (Function or Host Key required).</td></tr><tr><td><i>admin</i></td><td>Admin authorization level (Master Host Key required).</td></tr></table>				Option	Description	<i>anonymous</i>	Anonymous authorization level (No authorization required).	<i>function</i>	Function authorization level (Function or Host Key required).	<i>admin</i>	Admin authorization level (Master Host Key required).
Option	Description											
<i>anonymous</i>	Anonymous authorization level (No authorization required).											
<i>function</i>	Function authorization level (Function or Host Key required).											
<i>admin</i>	Admin authorization level (Master Host Key required).											
azure-api-key	Azure function API key.	password	Not Specified									
alicloud-function-authorization	AliCloud function authorization type.	option	-	anonymous								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>anonymous</i></td><td>Anonymous authorization (No authorization required).</td></tr><tr><td><i>function</i></td><td>Function authorization (Authorization required).</td></tr></table>				Option	Description	<i>anonymous</i>	Anonymous authorization (No authorization required).	<i>function</i>	Function authorization (Authorization required).		
Option	Description											
<i>anonymous</i>	Anonymous authorization (No authorization required).											
<i>function</i>	Function authorization (Authorization required).											
alicloud-access-key-id	AliCloud AccessKey ID.	string	Maximum length: 35									
alicloud-access-key-secret	AliCloud AccessKey secret.	password	Not Specified									
message-type	Message type.	option	-	text								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>text</i></td><td>Plaintext.</td></tr><tr><td><i>json</i></td><td>Custom JSON.</td></tr></table>				Option	Description	<i>text</i>	Plaintext.	<i>json</i>	Custom JSON.		
Option	Description											
<i>text</i>	Plaintext.											
<i>json</i>	Custom JSON.											

Parameter	Description	Type	Size	Default
message	Message content.	string	Maximum length: 4095	%%log%%
replacement-message	Enable/disable replacement message.	option	-	disable
	Option	Description		
	enable	Enable replacement message.		
	disable	Disable replacement message.		
replacemsg-group	Replacement message group.	string	Maximum length: 35	
protocol	Request protocol.	option	-	http
	Option	Description		
	http	HTTP.		
	https	HTTPS.		
method	Request method (POST, PUT, GET, PATCH or DELETE).	option	-	post
	Option	Description		
	post	POST.		
	put	PUT.		
	get	GET.		
	patch	PATCH.		
	delete	DELETE.		
uri	Request API URI.	var-string	Maximum length: 1023	
http-body	Request body (if necessary). Should be serialized json string.	var-string	Maximum length: 4095	
port	Protocol port.	integer	Minimum value: 1 Maximum value: 65535	0

Parameter	Description	Type	Size	Default						
verify-host-cert	Enable/disable verification of the remote host certificate.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable verification of the remote host certificate.</td></tr><tr><td><i>disable</i></td><td>Disable verification of the remote host certificate.</td></tr></table>	Option	Description	<i>enable</i>	Enable verification of the remote host certificate.	<i>disable</i>	Disable verification of the remote host certificate.			
Option	Description									
<i>enable</i>	Enable verification of the remote host certificate.									
<i>disable</i>	Disable verification of the remote host certificate.									
script	CLI script.	var-string	Maximum length: 1023							
output-size	Number of megabytes to limit script output to (1 - 1024, default = 10).	integer	Minimum value: 1 Maximum value: 1024	10						
timeout	Maximum running time for this script in seconds (0 = no timeout).	integer	Minimum value: 0 Maximum value: 300	0						
password	Script password to replace %%PASSWD%% tag in the script. Use cases include replacing a password tag for sftp/ftp server password.	password	Not Specified							
execute-security-fabric	Enable/disable execution of CLI script on all or only one FortiGate unit in the Security Fabric.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>CLI script executes on all FortiGate units in the Security Fabric.</td></tr><tr><td><i>disable</i></td><td>CLI script executes only on the FortiGate unit that the stitch is triggered.</td></tr></table>	Option	Description	<i>enable</i>	CLI script executes on all FortiGate units in the Security Fabric.	<i>disable</i>	CLI script executes only on the FortiGate unit that the stitch is triggered.			
Option	Description									
<i>enable</i>	CLI script executes on all FortiGate units in the Security Fabric.									
<i>disable</i>	CLI script executes only on the FortiGate unit that the stitch is triggered.									
accprofile	Access profile for CLI script action to access FortiProxy features.	string	Maximum length: 35							
security-tag	NSX security tag.	string	Maximum length: 255							
sdn-connector <name>	NSX SDN connector names. SDN connector name.	string	Maximum length: 79							

config http-headers

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
key	Request header key.	var-string	Maximum length: 1023	
value	Request header value.	var-string	Maximum length: 4095	

config system automation-destination

Automation destinations.

```
config system automation-destination
  Description: Automation destinations.
  edit <name>
    set type [fortiproxy|ha-cluster]
    set destination <name1>, <name2>, ...
    set ha-group-id {integer}
  next
end
```

config system automation-destination

Parameter	Description	Type	Size	Default						
name	Name.	string	Maximum length: 35							
type	Destination type.	option	-	fortiproxy						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>fortiproxy</i></td><td>FortiProxy set as destination.</td></tr><tr><td><i>ha-cluster</i></td><td>HA cluster set as destination.</td></tr></table>				Option	Description	<i>fortiproxy</i>	FortiProxy set as destination.	<i>ha-cluster</i>	HA cluster set as destination.
	Option	Description								
	<i>fortiproxy</i>	FortiProxy set as destination.								
<i>ha-cluster</i>	HA cluster set as destination.									
destination <name>	Destinations. Destination.	string	Maximum length: 31							

Parameter	Description	Type	Size	Default
ha-group-id	Cluster group ID set for this destination (default = 0).	integer	Minimum value: 0 Maximum value: 255	0

config system automation-stitch

Automation stitches.

```

config system automation-stitch
  Description: Automation stitches.
  edit <name>
    set description {var-string}
    set status [enable|disable]
    set trigger {string}
    config actions
      Description: Configure stitch actions.
      edit <id>
        set action {string}
        set delay {integer}
        set required [enable|disable]
      next
    end
    set destination <name1>, <name2>, ...
  next
end

```

config system automation-stitch

Parameter	Description	Type	Size	Default						
name	Name.	string	Maximum length: 35							
description	Description.	var-string	Maximum length: 255							
status	Enable/disable this stitch.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable stitch.</td></tr><tr><td><i>disable</i></td><td>Disable stitch.</td></tr></table>				Option	Description	<i>enable</i>	Enable stitch.	<i>disable</i>	Disable stitch.
	Option	Description								
	<i>enable</i>	Enable stitch.								
<i>disable</i>	Disable stitch.									
trigger	Trigger name.	string	Maximum length: 35							

Parameter	Description	Type	Size	Default
destination <name>	Serial number/HA group-name of destination devices. Destination name.	string	Maximum length: 79	

config actions

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
action	Action name.	string	Maximum length: 64	
delay	Delay before execution (in seconds).	integer	Minimum value: 0 Maximum value: 3600	0
required	Required in action chain.	option	-	disable
	Option	Description		
	enable	Required in action chain.		
	disable	Not required in action chain.		

config system automation-trigger

Trigger for automation stitches.

```

config system automation-trigger
  Description: Trigger for automation stitches.
  edit <name>
    set description {var-string}
    set trigger-type [event-based|scheduled]
    set event-type [ioc|event-log|...]
    set vdom <name1>, <name2>, ...
    set license-type [forticare-support|fortiguard-webfilter|...]
    set report-type [posture|coverage|...]
    set logid <id1>, <id2>, ...
    set trigger-frequency [hourly|daily|...]
    set trigger-weekday [sunday|monday|...]
    set trigger-day {integer}
    set trigger-hour {integer}
  
```



```

set trigger-minute {integer}
set trigger-datetime {datetime}
config fields
    Description: Customized trigger field settings.
    edit <id>
        set name {string}
        set value {var-string}
    next
end
set faz-event-name {var-string}
set faz-event-severity {var-string}
set faz-event-tags {var-string}
set serial {var-string}
set fabric-event-name {var-string}
set fabric-event-severity {var-string}
next
end

```

config system automation-trigger

Parameter	Description	Type	Size	Default												
name	Name.	string	Maximum length: 35													
description	Description.	var-string	Maximum length: 255													
trigger-type	Trigger type.	option	-	event-based												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>event-based</i></td><td>Event based trigger.</td></tr><tr><td><i>scheduled</i></td><td>Scheduled trigger.</td></tr></table>				Option	Description	<i>event-based</i>	Event based trigger.	<i>scheduled</i>	Scheduled trigger.						
	Option	Description														
	<i>event-based</i>	Event based trigger.														
<i>scheduled</i>	Scheduled trigger.															
event-type	Event type.	option	-	ioc												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ioc</i></td><td>Indicator of compromise detected.</td></tr><tr><td><i>event-log</i></td><td>Use log ID as trigger.</td></tr><tr><td><i>reboot</i></td><td>Device reboot.</td></tr><tr><td><i>low-memory</i></td><td>Conserve mode due to low memory.</td></tr><tr><td><i>high-cpu</i></td><td>High CPU usage.</td></tr></table>				Option	Description	<i>ioc</i>	Indicator of compromise detected.	<i>event-log</i>	Use log ID as trigger.	<i>reboot</i>	Device reboot.	<i>low-memory</i>	Conserve mode due to low memory.	<i>high-cpu</i>	High CPU usage.
	Option	Description														
	<i>ioc</i>	Indicator of compromise detected.														
	<i>event-log</i>	Use log ID as trigger.														
	<i>reboot</i>	Device reboot.														
	<i>low-memory</i>	Conserve mode due to low memory.														
<i>high-cpu</i>	High CPU usage.															

Parameter	Description	Type	Size	Default																																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>license-near-expiry</i></td><td>License near expiration date.</td></tr><tr><td><i>local-cert-near-expiry</i></td><td>The local certificate near expiration date.</td></tr><tr><td><i>ha-failover</i></td><td>HA failover.</td></tr><tr><td><i>config-change</i></td><td>Configuration change.</td></tr><tr><td><i>security-rating-summary</i></td><td>Security rating summary.</td></tr><tr><td><i>virus-ips-db-updated</i></td><td>Virus and IPS database updated.</td></tr><tr><td><i>faz-event</i></td><td>FortiAnalyzer event.</td></tr><tr><td><i>incoming-webhook</i></td><td>Incoming webhook call.</td></tr><tr><td><i>fabric-event</i></td><td>Fabric connector event.</td></tr><tr><td><i>ips-logs</i></td><td>IPS logs.</td></tr><tr><td><i>anomaly-logs</i></td><td>Anomaly logs.</td></tr><tr><td><i>virus-logs</i></td><td>Virus logs.</td></tr><tr><td><i>ssh-logs</i></td><td>SSH logs.</td></tr><tr><td><i>webfilter-violation</i></td><td>Webfilter violation.</td></tr><tr><td><i>traffic-violation</i></td><td>Traffic violation.</td></tr></table>	Option	Description	<i>license-near-expiry</i>	License near expiration date.	<i>local-cert-near-expiry</i>	The local certificate near expiration date.	<i>ha-failover</i>	HA failover.	<i>config-change</i>	Configuration change.	<i>security-rating-summary</i>	Security rating summary.	<i>virus-ips-db-updated</i>	Virus and IPS database updated.	<i>faz-event</i>	FortiAnalyzer event.	<i>incoming-webhook</i>	Incoming webhook call.	<i>fabric-event</i>	Fabric connector event.	<i>ips-logs</i>	IPS logs.	<i>anomaly-logs</i>	Anomaly logs.	<i>virus-logs</i>	Virus logs.	<i>ssh-logs</i>	SSH logs.	<i>webfilter-violation</i>	Webfilter violation.	<i>traffic-violation</i>	Traffic violation.			
	Option	Description																																		
	<i>license-near-expiry</i>	License near expiration date.																																		
	<i>local-cert-near-expiry</i>	The local certificate near expiration date.																																		
	<i>ha-failover</i>	HA failover.																																		
	<i>config-change</i>	Configuration change.																																		
	<i>security-rating-summary</i>	Security rating summary.																																		
	<i>virus-ips-db-updated</i>	Virus and IPS database updated.																																		
	<i>faz-event</i>	FortiAnalyzer event.																																		
	<i>incoming-webhook</i>	Incoming webhook call.																																		
	<i>fabric-event</i>	Fabric connector event.																																		
	<i>ips-logs</i>	IPS logs.																																		
	<i>anomaly-logs</i>	Anomaly logs.																																		
	<i>virus-logs</i>	Virus logs.																																		
	<i>ssh-logs</i>	SSH logs.																																		
<i>webfilter-violation</i>	Webfilter violation.																																			
<i>traffic-violation</i>	Traffic violation.																																			
vdom <name>	Virtual domain(s) that this trigger is valid for. Virtual domain name.	string	Maximum length: 79																																	
license-type	License type.	option	-	forticare-support																																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>forticare-support</i></td><td>FortiCare support license.</td></tr></table>	Option	Description	<i>forticare-support</i>	FortiCare support license.																															
	Option	Description																																		
<i>forticare-support</i>	FortiCare support license.																																			

Parameter	Description	Type	Size	Default																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>fortiguard-webfilter</i></td><td>FortiGuard web filter license.</td></tr><tr><td><i>fortiguard-antispam</i></td><td>FortiGuard antispam license.</td></tr><tr><td><i>fortiguard-antivirus</i></td><td>FortiGuard AntiVirus license.</td></tr><tr><td><i>fortiguard-ips</i></td><td>FortiGuard IPS license.</td></tr><tr><td><i>fortiguard-management</i></td><td>FortiGuard management service license.</td></tr><tr><td><i>forticloud</i></td><td>FortiCloud license.</td></tr><tr><td><i>any</i></td><td>Any license.</td></tr></table>	Option	Description	<i>fortiguard-webfilter</i>	FortiGuard web filter license.	<i>fortiguard-antispam</i>	FortiGuard antispam license.	<i>fortiguard-antivirus</i>	FortiGuard AntiVirus license.	<i>fortiguard-ips</i>	FortiGuard IPS license.	<i>fortiguard-management</i>	FortiGuard management service license.	<i>forticloud</i>	FortiCloud license.	<i>any</i>	Any license.			
	Option	Description																		
	<i>fortiguard-webfilter</i>	FortiGuard web filter license.																		
	<i>fortiguard-antispam</i>	FortiGuard antispam license.																		
	<i>fortiguard-antivirus</i>	FortiGuard AntiVirus license.																		
	<i>fortiguard-ips</i>	FortiGuard IPS license.																		
	<i>fortiguard-management</i>	FortiGuard management service license.																		
	<i>forticloud</i>	FortiCloud license.																		
<i>any</i>	Any license.																			
report-type	Security Rating report.	option	-	posture																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>posture</i></td><td>Posture report.</td></tr><tr><td><i>coverage</i></td><td>Coverage report.</td></tr><tr><td><i>optimization</i></td><td>Optimization report</td></tr><tr><td><i>any</i></td><td>Any report.</td></tr></table>	Option	Description	<i>posture</i>	Posture report.	<i>coverage</i>	Coverage report.	<i>optimization</i>	Optimization report	<i>any</i>	Any report.									
	Option	Description																		
	<i>posture</i>	Posture report.																		
	<i>coverage</i>	Coverage report.																		
	<i>optimization</i>	Optimization report																		
<i>any</i>	Any report.																			
logid <id>	Log IDs to trigger event. Log ID.	integer	Minimum value: 1 Maximum value: 65535																	
trigger-frequency	Scheduled trigger frequency (default = daily).	option	-	daily																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>hourly</i></td><td>Run hourly.</td></tr><tr><td><i>daily</i></td><td>Run daily.</td></tr><tr><td><i>weekly</i></td><td>Run weekly.</td></tr><tr><td><i>monthly</i></td><td>Run monthly.</td></tr><tr><td><i>once</i></td><td>Run once at specified date time.</td></tr></table>	Option	Description	<i>hourly</i>	Run hourly.	<i>daily</i>	Run daily.	<i>weekly</i>	Run weekly.	<i>monthly</i>	Run monthly.	<i>once</i>	Run once at specified date time.							
	Option	Description																		
	<i>hourly</i>	Run hourly.																		
	<i>daily</i>	Run daily.																		
	<i>weekly</i>	Run weekly.																		
	<i>monthly</i>	Run monthly.																		
<i>once</i>	Run once at specified date time.																			

Parameter	Description	Type	Size	Default																
trigger-weekday	Day of week for trigger.	option	-																	
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>sunday</i></td><td>Sunday.</td></tr><tr><td><i>monday</i></td><td>Monday.</td></tr><tr><td><i>tuesday</i></td><td>Tuesday.</td></tr><tr><td><i>wednesday</i></td><td>Wednesday.</td></tr><tr><td><i>thursday</i></td><td>Thursday.</td></tr><tr><td><i>friday</i></td><td>Friday.</td></tr><tr><td><i>saturday</i></td><td>Saturday.</td></tr></table>	Option	Description	<i>sunday</i>	Sunday.	<i>monday</i>	Monday.	<i>tuesday</i>	Tuesday.	<i>wednesday</i>	Wednesday.	<i>thursday</i>	Thursday.	<i>friday</i>	Friday.	<i>saturday</i>	Saturday.			
	Option	Description																		
	<i>sunday</i>	Sunday.																		
	<i>monday</i>	Monday.																		
	<i>tuesday</i>	Tuesday.																		
	<i>wednesday</i>	Wednesday.																		
	<i>thursday</i>	Thursday.																		
	<i>friday</i>	Friday.																		
<i>saturday</i>	Saturday.																			
trigger-day	Day within a month to trigger.	integer	Minimum value: 1 Maximum value: 31	1																
trigger-hour	Hour of the day on which to trigger (0 - 23, default = 1).	integer	Minimum value: 0 Maximum value: 23	0																
trigger-minute	Minute of the hour on which to trigger (0 - 59, default = 0).	integer	Minimum value: 0 Maximum value: 59	0																
trigger-datetime	Trigger date and time (YYYY-MM-DD HH:MM:SS).	datetime	Not Specified	0000-00-00 00:00:00																
faz-event-name	FortiAnalyzer event handler name.	var-string	Maximum length: 255																	
faz-event-severity	FortiAnalyzer event severity.	var-string	Maximum length: 255																	
faz-event-tags	FortiAnalyzer event tags.	var-string	Maximum length: 255																	
serial	Fabric connector serial number.	var-string	Maximum length: 255																	
fabric-event-name	Fabric connector event handler name.	var-string	Maximum length: 255																	
fabric-event-severity	Fabric connector event severity.	var-string	Maximum length: 255																	

config fields

Parameter	Description	Type	Size	Default
id	Entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Name.	string	Maximum length: 35	
value	Value.	var-string	Maximum length: 63	

config system autoupdate schedule

Configure update schedule.

```
config system autoupdate schedule
  Description: Configure update schedule.
  set status [enable|disable]
  set frequency [every|daily|...]
  set time {user}
  set day [Sunday|Monday|...]
end
```

config system autoupdate schedule

Parameter	Description	Type	Size	Default								
status	Enable/disable scheduled updates.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.					
Option	Description											
<i>enable</i>	Enable setting.											
<i>disable</i>	Disable setting.											
frequency	Update frequency.	option	-	automatic								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>every</i></td><td>Time interval.</td></tr><tr><td><i>daily</i></td><td>Every day.</td></tr><tr><td><i>weekly</i></td><td>Every week.</td></tr></table>	Option	Description	<i>every</i>	Time interval.	<i>daily</i>	Every day.	<i>weekly</i>	Every week.			
Option	Description											
<i>every</i>	Time interval.											
<i>daily</i>	Every day.											
<i>weekly</i>	Every week.											

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>automatic</i>	Update automatically within every one hour period.		
time	Update time.	user	Not Specified	
day	Update day.	option	-	Monday
	Option	Description		
	<i>Sunday</i>	Update every Sunday.		
	<i>Monday</i>	Update every Monday.		
	<i>Tuesday</i>	Update every Tuesday.		
	<i>Wednesday</i>	Update every Wednesday.		
	<i>Thursday</i>	Update every Thursday.		
	<i>Friday</i>	Update every Friday.		
	<i>Saturday</i>	Update every Saturday.		

config system autoupdate tunneling

Configure web proxy tunneling for the FDN.

```
config system autoupdate tunneling
  Description: Configure web proxy tunneling for the FDN.
  set status [enable|disable]
  set address {string}
  set port {integer}
  set username {string}
  set password {password}
end
```

config system autoupdate tunneling

Parameter	Description	Type	Size	Default
status	Enable/disable web proxy tunneling.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

Parameter	Description	Type	Size	Default
address	Web proxy IP address or FQDN.	string	Maximum length: 63	
port	Web proxy port.	integer	Minimum value: 0 Maximum value: 65535	0
username	Web proxy username.	string	Maximum length: 49	
password	Web proxy password.	password	Not Specified	

config system auto-install

Configure USB auto installation.

```
config system auto-install
    Description: Configure USB auto installation.
    set auto-install-config [enable|disable]
    set auto-install-image [enable|disable]
    set default-config-file {string}
    set default-image-file {string}
end
```

config system auto-install

Parameter	Description	Type	Size	Default						
auto-install-config	Enable/disable auto install the config in USB disk.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable config.</td></tr><tr><td><i>disable</i></td><td>Disable config.</td></tr></table>	Option	Description	<i>enable</i>	Enable config.	<i>disable</i>	Disable config.			
Option	Description									
<i>enable</i>	Enable config.									
<i>disable</i>	Disable config.									
auto-install-image	Enable/disable auto install the image in USB disk.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable config.</td></tr><tr><td><i>disable</i></td><td>Disable config.</td></tr></table>	Option	Description	<i>enable</i>	Enable config.	<i>disable</i>	Disable config.			
Option	Description									
<i>enable</i>	Enable config.									
<i>disable</i>	Disable config.									

Parameter	Description	Type	Size	Default
default-config-file	Default config file name in USB disk.	string	Maximum length: 127	fpx_system.conf
default-image-file	Default image file name in USB disk.	string	Maximum length: 127	image.out

config system auto-script

Configure auto script.

```

config system auto-script
  Description: Configure auto script.
  edit <name>
    set interval {integer}
    set repeat {integer}
    set start [manual|auto]
    set script {var-string}
    set password {password}
    set output-size {integer}
    set timeout {integer}
  next
end

```

config system auto-script

Parameter	Description	Type	Size	Default
name	Auto script name.	string	Maximum length: 35	
interval	Repeat interval in seconds.	integer	Minimum value: 0 Maximum value: 31557600	0
repeat	Number of times to repeat this script (0 = infinite).	integer	Minimum value: 0 Maximum value: 65535	1
start	Script starting mode.	option	-	manual

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>manual</i></td><td>Starting manually.</td></tr><tr><td><i>auto</i></td><td>Starting automatically.</td></tr></table>	Option	Description	<i>manual</i>	Starting manually.	<i>auto</i>	Starting automatically.			
	Option	Description								
	<i>manual</i>	Starting manually.								
<i>auto</i>	Starting automatically.									
script	List of FortiProxy CLI commands to repeat.	var-string	Maximum length: 1023							
password	Script password to replace %%PASSWD%% tag in the script. Use cases include replacing a password tag for sftp/ftp server password.	password	Not Specified							
output-size	Number of megabytes to limit script output to (10 - 1024, default = 10).	integer	Minimum value: 10 Maximum value: 1024	10						
timeout	Maximum running time for this script in seconds (0 = no timeout).	integer	Minimum value: 0 Maximum value: 300	0						

config system auto-update status

Status of automatic updates.

```
config system auto-update status
    Description: Status of automatic updates.
end
```

config system auto-update versions

Update object versions.

```
config system auto-update versions
    Description: Update object versions.
end
```

config system central-management

Configure central management.

```

config system central-management
    Description: Configure central management.
    set mode [normal|backup]
    set type [fortimanager|fortiguard|...]
    set fortigate-cloud-sso-default-profile {string}
    set schedule-config-restore [enable|disable]
    set schedule-script-restore [enable|disable]
    set allow-push-configuration [enable|disable]
    set allow-push-firmware [enable|disable]
    set allow-remote-firmware-upgrade [enable|disable]
    set allow-monitor [enable|disable]
    set serial-number {user}
    set fmg {user}
    set fmg-source-ip {ipv4-address}
    set fmg-source-ip6 {ipv6-address}
    set local-cert {string}
    set ca-cert {user}
    set vdom {string}
    config server-list
        Description: Additional servers that the FortiProxy can use for updates (for AV, IPS,
updates) and ratings (for web filter and antispam ratings) servers.
        edit <id>
            set server-type {option1}, {option2}, ...
            set addr-type [ipv4|ipv6|...]
            set server-address {ipv4-address}
            set server-address6 {ipv6-address}
            set fqdn {string}
        next
    end
    set fmg-update-port [8890|443]
    set include-default-servers [enable|disable]
    set enc-algorithm [default|high|...]
    set interface-select-method [auto|specify]
    set interface {string}
end

```

config system central-management

Parameter	Description	Type	Size	Default
mode	Central management mode.	option	-	normal
	Option	Description		
	<i>normal</i>	Manage and configure this FortiProxy from FortiManager.		
	<i>backup</i>	Manage and configure this FortiProxy locally and back up its configuration to FortiManager.		
type	Central management type.	option	-	none

Parameter	Description	Type	Size	Default
	Option Description			
	<i>fortimanager</i>	FortiManager.		
	<i>fortiguard</i>	Central management of this FortiProxy using FortiCloud.		
	<i>none</i>	No central management.		
fortigate-cloud-sso-default-profile	Override access profile.	string	Maximum length: 35	
schedule-config-restore	Enable/disable allowing the central management server to restore the configuration of this FortiProxy.	option	-	enable
	Option Description			
	<i>enable</i>	Enable scheduled configuration restore.		
	<i>disable</i>	Disable scheduled configuration restore.		
schedule-script-restore	Enable/disable allowing the central management server to restore the scripts stored on this FortiProxy.	option	-	enable
	Option Description			
	<i>enable</i>	Enable scheduled script restore.		
	<i>disable</i>	Disable scheduled script restore.		
allow-push-configuration	Enable/disable allowing the central management server to push configuration changes to this FortiProxy.	option	-	enable
	Option Description			
	<i>enable</i>	Enable push configuration.		
	<i>disable</i>	Disable push configuration.		
allow-push-firmware	Enable/disable allowing the central management server to push firmware updates to this FortiProxy.	option	-	enable
	Option Description			
	<i>enable</i>	Enable push firmware.		
	<i>disable</i>	Disable push firmware.		

Parameter	Description	Type	Size	Default						
allow-remote-firmware-upgrade	Enable/disable remotely upgrading the firmware on this FortiProxy from the central management server.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable remote firmware upgrade.</td></tr><tr><td><i>disable</i></td><td>Disable remote firmware upgrade.</td></tr></table>	Option	Description	<i>enable</i>	Enable remote firmware upgrade.	<i>disable</i>	Disable remote firmware upgrade.			
Option	Description									
<i>enable</i>	Enable remote firmware upgrade.									
<i>disable</i>	Disable remote firmware upgrade.									
allow-monitor	Enable/disable allowing the central management server to remotely monitor this FortiProxy unit.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable remote monitoring of device.</td></tr><tr><td><i>disable</i></td><td>Disable remote monitoring of device.</td></tr></table>	Option	Description	<i>enable</i>	Enable remote monitoring of device.	<i>disable</i>	Disable remote monitoring of device.			
Option	Description									
<i>enable</i>	Enable remote monitoring of device.									
<i>disable</i>	Disable remote monitoring of device.									
serial-number	Serial number.	user	Not Specified							
fmg	IP address or FQDN of the FortiManager.	user	Not Specified							
fmg-source-ip	IPv4 source address that this FortiProxy uses when communicating with FortiManager.	ipv4-address	Not Specified	0.0.0.0						
fmg-source-ip6	IPv6 source address that this FortiProxy uses when communicating with FortiManager.	ipv6-address	Not Specified	::						
local-cert	Certificate to be used by FGFM protocol.	string	Maximum length: 35							
ca-cert	CA certificate to be used by FGFM protocol.	user	Not Specified							
vdom	Virtual domain (VDOM) name to use when communicating with FortiManager.	string	Maximum length: 31	root						
fmg-update-port	Port used to communicate with FortiManager that is acting as a FortiGuard update server.	option	-	8890						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>8890</i></td><td>Use port 8890 to communicate with FortiManager that is acting as a FortiGuard update server.</td></tr></table>	Option	Description	<i>8890</i>	Use port 8890 to communicate with FortiManager that is acting as a FortiGuard update server.					
Option	Description									
<i>8890</i>	Use port 8890 to communicate with FortiManager that is acting as a FortiGuard update server.									

Parameter	Description	Type	Size	Default								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>443</td><td>Use port 443 to communicate with FortiManager that is acting as a FortiGuard update server.</td></tr></table>	Option	Description	443	Use port 443 to communicate with FortiManager that is acting as a FortiGuard update server.							
Option	Description											
443	Use port 443 to communicate with FortiManager that is acting as a FortiGuard update server.											
include-default-servers	Enable/disable inclusion of public FortiGuard servers in the override server list.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable inclusion of public FortiGuard servers in the override server list.</td></tr><tr><td>disable</td><td>Disable inclusion of public FortiGuard servers in the override server list.</td></tr></table>	Option	Description	enable	Enable inclusion of public FortiGuard servers in the override server list.	disable	Disable inclusion of public FortiGuard servers in the override server list.					
Option	Description											
enable	Enable inclusion of public FortiGuard servers in the override server list.											
disable	Disable inclusion of public FortiGuard servers in the override server list.											
enc-algorithm	Encryption strength for communications between the FortiProxy and central management.	option	-	high								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>default</td><td>High strength algorithms and medium-strength 128-bit key length algorithms.</td></tr><tr><td>high</td><td>128-bit and larger key length algorithms.</td></tr><tr><td>low</td><td>64-bit or 56-bit key length algorithms without export restrictions.</td></tr></table>	Option	Description	default	High strength algorithms and medium-strength 128-bit key length algorithms.	high	128-bit and larger key length algorithms.	low	64-bit or 56-bit key length algorithms without export restrictions.			
Option	Description											
default	High strength algorithms and medium-strength 128-bit key length algorithms.											
high	128-bit and larger key length algorithms.											
low	64-bit or 56-bit key length algorithms without export restrictions.											
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>auto</td><td>Set outgoing interface automatically.</td></tr><tr><td>specify</td><td>Set outgoing interface manually.</td></tr></table>	Option	Description	auto	Set outgoing interface automatically.	specify	Set outgoing interface manually.					
Option	Description											
auto	Set outgoing interface automatically.											
specify	Set outgoing interface manually.											
interface	Specify outgoing interface to reach server.	string	Maximum length: 15									

config server-list

Parameter	Description	Type	Size	Default										
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0										
server-type	FortiGuard service type.	option	-											
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>update</td><td>AV, IPS, and AV-query update server.</td></tr><tr><td>rating</td><td>Web filter and anti-spam rating server.</td></tr><tr><td>iot-query</td><td>IoT query server.</td></tr><tr><td>iot-collect</td><td>IoT device collection server.</td></tr></table>				Option	Description	update	AV, IPS, and AV-query update server.	rating	Web filter and anti-spam rating server.	iot-query	IoT query server.	iot-collect	IoT device collection server.
	Option	Description												
	update	AV, IPS, and AV-query update server.												
	rating	Web filter and anti-spam rating server.												
	iot-query	IoT query server.												
iot-collect	IoT device collection server.													
addr-type	Indicate whether the FortiProxy communicates with the override server using an IPv4 address, an IPv6 address or a FQDN.	option	-	ipv4										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>ipv4</td><td>IPv4 address.</td></tr><tr><td>ipv6</td><td>IPv6 address.</td></tr><tr><td>fqdn</td><td>FQDN.</td></tr></table>				Option	Description	ipv4	IPv4 address.	ipv6	IPv6 address.	fqdn	FQDN.		
	Option	Description												
	ipv4	IPv4 address.												
	ipv6	IPv6 address.												
	fqdn	FQDN.												
server-address	IPv4 address of override server.	ipv4-address	Not Specified	0.0.0.0										
server-address6	IPv6 address of override server.	ipv6-address	Not Specified	::										
fqdn	FQDN address of override server.	string	Maximum length: 255											

config system central-mgmt

Configuration of Central Management Service.

```
config system central-mgmt
    Description: Configuration of Central Management Service.
end
```

config system checksum status

System checksum.

```
config system checksum status
    Description: System checksum.
end
```

config system cmdb

System CMDB information.

```
config system cmdb
    Description: System CMDB information.
end
```

config system console

Configure console.

```
config system console
    Description: Configure console.
    set baudrate [9600|19200|...]
    set output [standard|more]
    set login [enable|disable]
end
```

config system console

Parameter	Description	Type	Size	Default
baudrate	Console baud rate.	option	-	9600
	Option	Description		
	9600	9600		
	19200	19200		
	38400	38400		
	57600	57600		
	115200	115200		
output	Console output mode.	option	-	more

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>standard</i>	Standard output.		
	<i>more</i>	More page output.		
login	Enable/disable serial console and FortiExplorer.	option	-	enable
	Option	Description		
	<i>enable</i>	Console login enable.		
	<i>disable</i>	Console login disable.		

config system csf

Add this FortiProxy to a Security Fabric or set up a new Security Fabric on this FortiProxy.

```
config system csf
  Description: Add this FortiProxy to a Security Fabric or set up a new Security Fabric on this
  FortiProxy.
  set status [enable|disable]
  set upstream {string}
  set source-ip {ipv4-address}
  set upstream-interface-select-method [auto|specify]
  set upstream-interface {string}
  set upstream-port {integer}
  set group-name {string}
  set group-password {password}
  set accept-auth-by-cert [disable|enable]
  set log-unification [disable|enable]
  set authorization-request-type [serial|certificate]
  set certificate {string}
  set fabric-workers {integer}
  set downstream-access [enable|disable]
  set license-sharing [enable|disable]
  set preferred-seats {integer}
  set legacy-authentication [disable|enable]
  set downstream-acprofile {string}
  set configuration-sync [default|local]
  set fabric-object-unification [default|local]
  set saml-configuration-sync [default|local]
  config trusted-list
    Description: Pre-authorized and blocked security fabric nodes.
    edit <name>
      set authorization-type [serial|certificate]
      set serial {string}
      set certificate {var-string}
      set action [accept|deny]
```



```

        set ha-members {string}
        set downstream-authorization [enable|disable]
        set preferred-seats {integer}
        set index {integer}
    next
end
config fabric-connector
    Description: Fabric connector configuration.
    edit <serial>
        set accprofile {string}
        set configuration-write-access [enable|disable]
    next
end
set forticloud-account-enforcement [enable|disable]
set file-mgmt [enable|disable]
set file-quota {integer}
set file-quota-warning {integer}
end

```

config system csf

Parameter	Description	Type	Size	Default
status	Enable/disable Security Fabric.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable Security Fabric.		
	<i>disable</i>	Disable Security Fabric.		
upstream	IP/FQDN of the FortiProxy upstream from this FortiProxy in the Security Fabric.	string	Maximum length: 255	
source-ip	Source IP address for communication with the upstream FortiGate.	ipv4-address	Not Specified	0.0.0.0
upstream-interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto
	Option	Description		
	<i>auto</i>	Set outgoing interface automatically.		
	<i>specify</i>	Set outgoing interface manually.		
upstream-interface	Specify outgoing interface to reach server.	string	Maximum length: 15	

Parameter	Description	Type	Size	Default						
upstream-port	The port number to use to communicate with the FortiProxy upstream from this FortiProxy in the Security Fabric (default = 8013).	integer	Minimum value: 1 Maximum value: 65535	8013						
group-name	Security Fabric group name. All FortiProxys in a Security Fabric must have the same group name.	string	Maximum length: 35							
group-password	Security Fabric group password. All FortiProxys in a Security Fabric must have the same group password.	password	Not Specified							
accept-auth-by-cert	Accept connections with unknown certificates and ask admin for approval.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not accept SSL connections with unknown certificates.</td></tr><tr><td><i>enable</i></td><td>Accept SSL connections without automatic certificate verification.</td></tr></table>	Option	Description	<i>disable</i>	Do not accept SSL connections with unknown certificates.	<i>enable</i>	Accept SSL connections without automatic certificate verification.			
Option	Description									
<i>disable</i>	Do not accept SSL connections with unknown certificates.									
<i>enable</i>	Accept SSL connections without automatic certificate verification.									
log-unification	Enable/disable broadcast of discovery messages for log unification.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable broadcast of discovery messages for log unification.</td></tr><tr><td><i>enable</i></td><td>Enable broadcast of discovery messages for log unification.</td></tr></table>	Option	Description	<i>disable</i>	Disable broadcast of discovery messages for log unification.	<i>enable</i>	Enable broadcast of discovery messages for log unification.			
Option	Description									
<i>disable</i>	Disable broadcast of discovery messages for log unification.									
<i>enable</i>	Enable broadcast of discovery messages for log unification.									
authorization-request-type	Authorization request type.	option	-	serial						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>serial</i></td><td>Request verification by serial number.</td></tr><tr><td><i>certificate</i></td><td>Request verification by certificate.</td></tr></table>	Option	Description	<i>serial</i>	Request verification by serial number.	<i>certificate</i>	Request verification by certificate.			
Option	Description									
<i>serial</i>	Request verification by serial number.									
<i>certificate</i>	Request verification by certificate.									
certificate	Certificate.	string	Maximum length: 35							
fabric-workers	Number of worker processes for Security Fabric daemon.	integer	Minimum value: 1 Maximum value: 4	2						

Parameter	Description	Type	Size	Default						
downstream-access	Enable/disable downstream device access to this device's configuration and data.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable downstream device access to this device's configuration and data.</td></tr><tr><td><i>disable</i></td><td>Disable downstream device access to this device's configuration and data.</td></tr></table>	Option	Description	<i>enable</i>	Enable downstream device access to this device's configuration and data.	<i>disable</i>	Disable downstream device access to this device's configuration and data.			
Option	Description									
<i>enable</i>	Enable downstream device access to this device's configuration and data.									
<i>disable</i>	Disable downstream device access to this device's configuration and data.									
license-sharing	Enable/disable license sharing between FortiProxy devices.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable license sharing.</td></tr><tr><td><i>disable</i></td><td>Disable license sharing.</td></tr></table>	Option	Description	<i>enable</i>	Enable license sharing.	<i>disable</i>	Disable license sharing.			
Option	Description									
<i>enable</i>	Enable license sharing.									
<i>disable</i>	Disable license sharing.									
preferred-seats	The number of seats this FortiProxy device as CSF root should be allocated with. The number of gurrantt seats is capped by minimum of the number of local purchased seats and the number of preferred seats. And the rest of preferred seats will be allocated from shared pool at higher priority.	integer	Minimum value: 0 Maximum value: 4294967295	0						
legacy-authentication	Enable/disable legacy authentication.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not accept legacy authentication requests.</td></tr><tr><td><i>enable</i></td><td>Accept legacy authentication requests.</td></tr></table>	Option	Description	<i>disable</i>	Do not accept legacy authentication requests.	<i>enable</i>	Accept legacy authentication requests.			
Option	Description									
<i>disable</i>	Do not accept legacy authentication requests.									
<i>enable</i>	Accept legacy authentication requests.									
downstream-accprofile	Default access profile for requests from downstream devices.	string	Maximum length: 35							
configuration-sync	Configuration sync mode.	option	-	default						

Parameter	Description	Type	Size	Default
	Option Description			
	<i>default</i>	Synchronize configuration for IPAM, FortiAnalyzer, FortiSandbox, and Central Management to root node.		
	<i>local</i>	Do not synchronize configuration with root node.		
fabric-object-unification	Fabric CMDB Object Unification.	option	-	default
	Option Description			
	<i>default</i>	Global CMDB objects will be synchronized in Security Fabric.		
	<i>local</i>	Global CMDB objects will not be synchronized to and from this device.		
saml-configuration-sync	SAML setting configuration synchronization.	option	-	default
	Option Description			
	<i>default</i>	SAML setting for fabric members is created by fabric root.		
	<i>local</i>	Do not apply SAML configuration generated by root.		
forticloud-account-enforcement	Fabric FortiCloud account unification.	option	-	enable
	Option Description			
	<i>enable</i>	Enable FortiCloud account ID matching for Security Fabric.		
	<i>disable</i>	Disable FortiCloud account ID matching for Security Fabric.		
file-mgmt	Enable/disable Security Fabric daemon file management.	option	-	enable
	Option Description			
	<i>enable</i>	Enable daemon file management.		
	<i>disable</i>	Disable daemon file management.		
file-quota	Maximum amount of memory that can be used by the daemon files (in bytes).	integer	Minimum value: 0 Maximum value: 4294967295	268435456

Parameter	Description	Type	Size	Default
file-quota-warning	Warn when the set percentage of quota has been used.	integer	Minimum value: 1 Maximum value: 99	90

config trusted-list

Parameter	Description	Type	Size	Default						
name	Name.	string	Maximum length: 35							
authorization-type	Authorization type.	option	-	serial						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>serial</i></td><td>Verify downstream by serial number.</td></tr><tr><td><i>certificate</i></td><td>Verify downstream by certificate.</td></tr></table>				Option	Description	<i>serial</i>	Verify downstream by serial number.	<i>certificate</i>	Verify downstream by certificate.
Option	Description									
<i>serial</i>	Verify downstream by serial number.									
<i>certificate</i>	Verify downstream by certificate.									
serial	Serial.	string	Maximum length: 19							
certificate	Certificate.	var-string	Maximum length: 32767							
action	Security fabric authorization action.	option	-	accept						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>accept</i></td><td>Accept authorization request.</td></tr><tr><td><i>deny</i></td><td>Deny authorization request.</td></tr></table>				Option	Description	<i>accept</i>	Accept authorization request.	<i>deny</i>	Deny authorization request.
Option	Description									
<i>accept</i>	Accept authorization request.									
<i>deny</i>	Deny authorization request.									
ha-members	HA members.	string	Maximum length: 19							
downstream-authorization	Trust authorizations by this node's administrator.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable downstream authorization.</td></tr><tr><td><i>disable</i></td><td>Disable downstream authorization.</td></tr></table>				Option	Description	<i>enable</i>	Enable downstream authorization.	<i>disable</i>	Disable downstream authorization.
Option	Description									
<i>enable</i>	Enable downstream authorization.									
<i>disable</i>	Disable downstream authorization.									

Parameter	Description	Type	Size	Default
preferred-seats	The number of seats this FortiProxy device should be allocated with. The number of gurranttred seats is capped by minimum of the number of local purchased seats and the number of preferred seats. And the rest of preferred seats will be allocated from shared pool at higher priority.	integer	Minimum value: 0 Maximum value: 4294967295	0
index	Index of the downstream in tree.	integer	Minimum value: 1 Maximum value: 1024	0

config fabric-connector

Parameter	Description	Type	Size	Default						
serial	Serial.	string	Maximum length: 19							
accprofile	Override access profile.	string	Maximum length: 35							
configuration-write-access	Enable/disable downstream device write access to configuration.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable downstream device write access to configuration.</td></tr><tr><td><i>disable</i></td><td>Disable downstream device write access to configuration.</td></tr></table>				Option	Description	<i>enable</i>	Enable downstream device write access to configuration.	<i>disable</i>	Disable downstream device write access to configuration.
Option	Description									
<i>enable</i>	Enable downstream device write access to configuration.									
<i>disable</i>	Disable downstream device write access to configuration.									

config system custom-language

Configure custom languages.

```

config system custom-language
  Description: Configure custom languages.
  edit <name>
    set filename {string}
    set comments {var-string}
  next
end

```

config system custom-language

Parameter	Description	Type	Size	Default
name	Name.	string	Maximum length: 35	
filename	Custom language file path.	string	Maximum length: 63	
comments	Comment.	var-string	Maximum length: 255	

config system ddns

Configure DDNS.

```
config system ddns
  Description: Configure DDNS.
  edit <ddnsid>
    set ddns-server [dyndns.org|dyns.net|...]
    set server-type [ipv4|ipv6]
    set ddns-server-addr <addr1>, <addr2>, ...
    set ddns-zone {string}
    set ddns-ttl {integer}
    set ddns-auth [disable|tsig]
    set ddns-keyname {string}
    set ddns-key {password_aes256}
    set ddns-domain {string}
    set ddns-username {string}
    set ddns-sn {string}
    set ddns-password {password}
    set use-public-ip [disable|enable]
    set addr-type [ipv4|ipv6]
    set update-interval {integer}
    set clear-text [disable|enable]
    set ssl-certificate {string}
    set bound-ip {string}
    set monitor-interface <interface-name1>, <interface-name2>, ...
  next
end
```

config system ddns

Parameter	Description	Type	Size	Default																								
ddnsid	DDNS ID.	integer	Minimum value: 0 Maximum value: 4294967295	0																								
ddns-server	Select a DDNS service provider.	option	-																									
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>dyndns.org</i></td><td>members.dyndns.org and dnsalias.com</td></tr><tr><td><i>dyns.net</i></td><td>www.dyns.net</td></tr><tr><td><i>tzo.com</i></td><td>rh.tzo.com</td></tr><tr><td><i>vavic.com</i></td><td>Peanut Hull</td></tr><tr><td><i>dipdns.net</i></td><td>dipdnsserver.dipdns.com</td></tr><tr><td><i>now.net.cn</i></td><td>ip.todayisp.com</td></tr><tr><td><i>dhs.org</i></td><td>members.dhs.org</td></tr><tr><td><i>easydns.com</i></td><td>members.easydns.com</td></tr><tr><td><i>genericDDNS</i></td><td>Generic DDNS based on RFC2136.</td></tr><tr><td><i>FortiGuardDDNS</i></td><td>FortiGuard DDNS service.</td></tr><tr><td><i>noip.com</i></td><td>dynupdate.no-ip.com</td></tr></table>	Option	Description	<i>dyndns.org</i>	members.dyndns.org and dnsalias.com	<i>dyns.net</i>	www.dyns.net	<i>tzo.com</i>	rh.tzo.com	<i>vavic.com</i>	Peanut Hull	<i>dipdns.net</i>	dipdnsserver.dipdns.com	<i>now.net.cn</i>	ip.todayisp.com	<i>dhs.org</i>	members.dhs.org	<i>easydns.com</i>	members.easydns.com	<i>genericDDNS</i>	Generic DDNS based on RFC2136.	<i>FortiGuardDDNS</i>	FortiGuard DDNS service.	<i>noip.com</i>	dynupdate.no-ip.com			
Option	Description																											
<i>dyndns.org</i>	members.dyndns.org and dnsalias.com																											
<i>dyns.net</i>	www.dyns.net																											
<i>tzo.com</i>	rh.tzo.com																											
<i>vavic.com</i>	Peanut Hull																											
<i>dipdns.net</i>	dipdnsserver.dipdns.com																											
<i>now.net.cn</i>	ip.todayisp.com																											
<i>dhs.org</i>	members.dhs.org																											
<i>easydns.com</i>	members.easydns.com																											
<i>genericDDNS</i>	Generic DDNS based on RFC2136.																											
<i>FortiGuardDDNS</i>	FortiGuard DDNS service.																											
<i>noip.com</i>	dynupdate.no-ip.com																											
server-type	Address type of the DDNS server.	option	-	ipv4																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ipv4</i></td><td>Use IPv4 addressing.</td></tr><tr><td><i>ipv6</i></td><td>Use IPv6 addressing.</td></tr></table>	Option	Description	<i>ipv4</i>	Use IPv4 addressing.	<i>ipv6</i>	Use IPv6 addressing.																					
Option	Description																											
<i>ipv4</i>	Use IPv4 addressing.																											
<i>ipv6</i>	Use IPv6 addressing.																											
ddns-server-addr <addr>	Generic DDNS server IP/FQDN list. IP address or FQDN of the server.	string	Maximum length: 256																									
ddns-zone	Zone of your domain name (for example, DDNS.com).	string	Maximum length: 64																									
ddns-ttl	Time-to-live for DDNS packets.	integer	Minimum value: 60 Maximum value: 86400	300																								
ddns-auth	Enable/disable TSIG authentication for your DDNS server.	option	-	disable																								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable DDNS authentication.		
	<i>tsig</i>	Enable TSIG authentication based on RFC2845.		
ddns-keyname	DDNS update key name.	string	Maximum length: 64	
ddns-key	DDNS update key (base 64 encoding).	password_aes256	Not Specified	
ddns-domain	Your fully qualified domain name. For example, yourname.ddns.com.	string	Maximum length: 64	
ddns-username	DDNS user name.	string	Maximum length: 64	
ddns-sn	DDNS Serial Number.	string	Maximum length: 64	
ddns-password	DDNS password.	password	Not Specified	
use-public-ip	Enable/disable use of public IP address.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable use of public IP address.		
	<i>enable</i>	Enable use of public IP address.		
addr-type	Address type of interface address in DDNS update.	option	-	ipv4
	Option	Description		
	<i>ipv4</i>	Use IPv4 address of the interface.		
	<i>ipv6</i>	Use IPv6 address of the interface.		
update-interval	DDNS update interval (60 - 2592000 sec, 0 means default).	integer	Minimum value: 60 Maximum value: 2592000	0
clear-text	Enable/disable use of clear text connections.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable use of clear text connections.		
	<i>enable</i>	Enable use of clear text connections.		
ssl-certificate	Name of local certificate for SSL connections.	string	Maximum length: 35	Fortinet_Factory
bound-ip	Bound IP address.	string	Maximum length: 46	
monitor-interface <interface-name>	Monitored interface. Interface name.	string	Maximum length: 79	

config system device-upgrade

Independent upgrades for managed devices.

```

config system device-upgrade
  Description: Independent upgrades for managed devices.
  edit <serial>
    set timing [immediate|scheduled]
    set maximum-minutes {integer}
    set time {user}
    set setup-time {user}
    set upgrade-path {user}
    set device-type [fortiswitch|fortiap|...]
    set status [disabled|initialized|...]
    set failure-reason [none|internal|...]
  next
end

```

config system device-upgrade

Parameter	Description	Type	Size	Default
serial	Serial number of the node to include.	string	Maximum length: 79	
timing	Run immediately or at a scheduled time.	option	-	immediate

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>immediate</i>	Begin the upgrade immediately.		
	<i>scheduled</i>	Begin the upgrade at a configured time.		
maximum-minutes	Maximum number of minutes to allow for immediate upgrade preparation.	integer	Minimum value: 5 Maximum value: 10080	15
time	Scheduled upgrade execution time in UTC (hh:mm yyyy/mm/dd UTC).	user	Not Specified	
setup-time	Upgrade preparation start time in UTC (hh:mm yyyy/mm/dd UTC).	user	Not Specified	
upgrade-path	Fortinet OS image versions to upgrade through in major-minor-patch format, such as 7-0-4.	user	Not Specified	
device-type	Fortinet device type.	option	-	fortiswitch
	Option	Description		
	<i>fortiswitch</i>	This device is a FortiSwitch.		
	<i>fortiap</i>	This device is a FortiAP.		
	<i>fortiextender</i>	This device is a FortiExtender.		
status	Current status of the upgrade.	option	-	disabled
	Option	Description		
	<i>disabled</i>	No federated upgrade has been configured.		
	<i>initialized</i>	The upgrade has been configured.		
	<i>downloading</i>	The image is downloading in preparation for the upgrade.		
	<i>device-disconnected</i>	The image downloads are complete, but one or more devices have disconnected.		
	<i>ready</i>	The image download finished and the upgrade is pending.		
	<i>coordinating</i>	The upgrade is coordinating with other running upgrades.		
	<i>staging</i>	The upgrade is confirmed and images are being staged.		
	<i>final-check</i>	The upgrade is ready and final checks are in progress.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>upgrade-devices</i>	The upgrade is ready and devices are being rebooted.		
	<i>cancelled</i>	The upgrade was cancelled due to the tree not being ready.		
	<i>confirmed</i>	The upgrade was confirmed and reboots are running.		
	<i>done</i>	The upgrade completed successfully.		
	<i>failed</i>	The upgrade failed due to a local issue.		
failure-reason	Upgrade failure reason.	option	-	none
	Option	Description		
	<i>none</i>	No failure.		
	<i>internal</i>	An internal error occurred.		
	<i>timeout</i>	The upgrade timed out.		
	<i>device-type-unsupported</i>	The device type was not supported by the FortiGate.		
	<i>download-failed</i>	The image could not be downloaded.		
	<i>device-missing</i>	The device was disconnected from the FortiGate.		
	<i>version-unavailable</i>	An image matching the device and version could not be found.		
	<i>staging-failed</i>	The image could not be pushed to the device.		
	<i>reboot-failed</i>	The device could not be rebooted.		
	<i>device-not-reconnected</i>	The device did not reconnect after rebooting.		
	<i>node-not-ready</i>	A device in the Security Fabric tree was not ready.		
	<i>no-final-confirmation</i>	The coordinating FortiGate did not confirm the upgrade.		
	<i>no-confirmation-query</i>	A downstream FortiGate did not initiate final confirmation.		
	<i>config-error-log-nonempty</i>	Configuration errors encountered during the upgrade.		
<i>node-failed</i>	A device in the Security Fabric tree failed.			

config system dhcp server

Configure DHCP servers.

```
config system dhcp server
  Description: Configure DHCP servers.
  edit <id>
    set status [disable|enable]
    set lease-time {integer}
    set mac-acl-default-action [assign|block]
    set forticlient-on-net-status [disable|enable]
    set dns-service [local|default|...]
    set dns-server1 {ipv4-address}
    set dns-server2 {ipv4-address}
    set dns-server3 {ipv4-address}
    set dns-server4 {ipv4-address}
    set wifi-ac-service [specify|local]
    set wifi-ac1 {ipv4-address}
    set wifi-ac2 {ipv4-address}
    set wifi-ac3 {ipv4-address}
    set ntp-service [local|default|...]
    set ntp-server1 {ipv4-address}
    set ntp-server2 {ipv4-address}
    set ntp-server3 {ipv4-address}
    set domain {string}
    set wins-server1 {ipv4-address}
    set wins-server2 {ipv4-address}
    set default-gateway {ipv4-address}
    set next-server {ipv4-address}
    set netmask {ipv4-netmask}
    set interface {string}
  config ip-range
    Description: DHCP IP range configuration.
    edit <id>
      set start-ip {ipv4-address}
      set end-ip {ipv4-address}
      set vci-match [disable|enable]
      set vci-string <vci-string1>, <vci-string2>, ...
      set uci-match [disable|enable]
      set uci-string <uci-string1>, <uci-string2>, ...
      set lease-time {integer}
    next
  end
  set timezone-option [disable|default|...]
  set timezone [01|02|...]
  set tftp-server <tftp-server1>, <tftp-server2>, ...
  set filename {string}
  config options
    Description: DHCP options.
    edit <id>
      set code {integer}
```

```

        set type [hex|string|...]
        set value {string}
        set ip {user}
        set vci-match [disable|enable]
        set vci-string <vci-string1>, <vci-string2>, ...
        set uci-match [disable|enable]
        set uci-string <uci-string1>, <uci-string2>, ...
    next
end
set server-type [regular|ipsec]
set ip-mode [range|usrgrp]
set conflicted-ip-timeout {integer}
set ipsec-lease-hold {integer}
set auto-configuration [disable|enable]
set dhcp-settings-from-fortipam [disable|enable]
set auto-managed-status [disable|enable]
set ddns-update [disable|enable]
set ddns-update-override [disable|enable]
set ddns-server-ip {ipv4-address}
set ddns-zone {string}
set ddns-auth [disable|tsig]
set ddns-keyname {string}
set ddns-key {password_aes256}
set ddns-ttl {integer}
set vci-match [disable|enable]
set vci-string <vci-string1>, <vci-string2>, ...
config exclude-range
    Description: Exclude one or more ranges of IP addresses from being assigned to
clients.
    edit <id>
        set start-ip {ipv4-address}
        set end-ip {ipv4-address}
        set vci-match [disable|enable]
        set vci-string <vci-string1>, <vci-string2>, ...
        set uci-match [disable|enable]
        set uci-string <uci-string1>, <uci-string2>, ...
        set lease-time {integer}
    next
end
config reserved-address
    Description: Options for the DHCP server to assign IP settings to specific MAC
addresses.
    edit <id>
        set type [mac|option82]
        set ip {ipv4-address}
        set mac {mac-address}
        set action [assign|block|...]
        set circuit-id-type [hex|string]
        set circuit-id {string}
        set remote-id-type [hex|string]
        set remote-id {string}
        set description {var-string}

```

```

        next
    end
next
end

```

config system dhcp server

Parameter	Description	Type	Size	Default						
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0						
status	Enable/disable this DHCP configuration.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not use this DHCP server configuration.</td></tr><tr><td><i>enable</i></td><td>Use this DHCP server configuration.</td></tr></table>				Option	Description	<i>disable</i>	Do not use this DHCP server configuration.	<i>enable</i>	Use this DHCP server configuration.
	Option	Description								
	<i>disable</i>	Do not use this DHCP server configuration.								
<i>enable</i>	Use this DHCP server configuration.									
lease-time	Lease time in seconds, 0 means unlimited.	integer	Minimum value: 300 Maximum value: 8640000	604800						
mac-acl-default-action	MAC access control default action (allow or block assigning IP settings).	option	-	assign						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>assign</i></td><td>Allow the DHCP server to assign IP settings to clients on the MAC access control list.</td></tr><tr><td><i>block</i></td><td>Block the DHCP server from assigning IP settings to clients on the MAC access control list.</td></tr></table>				Option	Description	<i>assign</i>	Allow the DHCP server to assign IP settings to clients on the MAC access control list.	<i>block</i>	Block the DHCP server from assigning IP settings to clients on the MAC access control list.
	Option	Description								
	<i>assign</i>	Allow the DHCP server to assign IP settings to clients on the MAC access control list.								
<i>block</i>	Block the DHCP server from assigning IP settings to clients on the MAC access control list.									
forticlient-on-net-status	Enable/disable FortiClient-On-Net service for this DHCP server.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable FortiClient On-Net Status.</td></tr><tr><td><i>enable</i></td><td>Enable FortiClient On-Net Status.</td></tr></table>				Option	Description	<i>disable</i>	Disable FortiClient On-Net Status.	<i>enable</i>	Enable FortiClient On-Net Status.
	Option	Description								
	<i>disable</i>	Disable FortiClient On-Net Status.								
<i>enable</i>	Enable FortiClient On-Net Status.									
dns-service	Options for assigning DNS servers to DHCP clients.	option	-	specify						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>local</i>	IP address of the interface the DHCP server is added to becomes the client's DNS server IP address.		
	<i>default</i>	Clients are assigned the FortiProxy's configured DNS servers.		
	<i>specify</i>	Specify up to 3 DNS servers in the DHCP server configuration.		
dns-server1	DNS server 1.	ipv4-address	Not Specified	0.0.0.0
dns-server2	DNS server 2.	ipv4-address	Not Specified	0.0.0.0
dns-server3	DNS server 3.	ipv4-address	Not Specified	0.0.0.0
dns-server4	DNS server 4.	ipv4-address	Not Specified	0.0.0.0
wifi-ac-service	Options for assigning WiFi access controllers to DHCP clients.	option	-	specify
	Option	Description		
	<i>specify</i>	Specify up to 3 WiFi Access Controllers in the DHCP server configuration.		
	<i>local</i>	IP address of the interface the DHCP server is added to becomes the client's WiFi Access Controller IP address.		
wifi-ac1	WiFi Access Controller 1 IP address (DHCP option 138, RFC 5417).	ipv4-address	Not Specified	0.0.0.0
wifi-ac2	WiFi Access Controller 2 IP address (DHCP option 138, RFC 5417).	ipv4-address	Not Specified	0.0.0.0
wifi-ac3	WiFi Access Controller 3 IP address (DHCP option 138, RFC 5417).	ipv4-address	Not Specified	0.0.0.0
ntp-service	Options for assigning Network Time Protocol (NTP) servers to DHCP clients.	option	-	specify
	Option	Description		
	<i>local</i>	IP address of the interface the DHCP server is added to becomes the client's NTP server IP address.		
	<i>default</i>	Clients are assigned the FortiProxy's configured NTP servers.		
	<i>specify</i>	Specify up to 3 NTP servers in the DHCP server configuration.		

Parameter	Description	Type	Size	Default								
ntp-server1	NTP server 1.	ipv4-address	Not Specified	0.0.0.0								
ntp-server2	NTP server 2.	ipv4-address	Not Specified	0.0.0.0								
ntp-server3	NTP server 3.	ipv4-address	Not Specified	0.0.0.0								
domain	Domain name suffix for the IP addresses that the DHCP server assigns to clients.	string	Maximum length: 35									
wins-server1	WINS server 1.	ipv4-address	Not Specified	0.0.0.0								
wins-server2	WINS server 2.	ipv4-address	Not Specified	0.0.0.0								
default-gateway	Default gateway IP address assigned by the DHCP server.	ipv4-address	Not Specified	0.0.0.0								
next-server	IP address of a server (for example, a TFTP sever) that DHCP clients can download a boot file from.	ipv4-address	Not Specified	0.0.0.0								
netmask	Netmask assigned by the DHCP server.	ipv4-netmask	Not Specified	0.0.0.0								
interface	DHCP server can assign IP configurations to clients connected to this interface.	string	Maximum length: 15									
timezone-option	Options for the DHCP server to set the client's time zone.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Do not set the client's time zone.</td></tr><tr><td>default</td><td>Clients are assigned the FortiProxy's configured time zone.</td></tr><tr><td>specify</td><td>Specify the time zone to be assigned to DHCP clients.</td></tr></table>				Option	Description	disable	Do not set the client's time zone.	default	Clients are assigned the FortiProxy's configured time zone.	specify	Specify the time zone to be assigned to DHCP clients.
Option	Description											
disable	Do not set the client's time zone.											
default	Clients are assigned the FortiProxy's configured time zone.											
specify	Specify the time zone to be assigned to DHCP clients.											
timezone	Select the time zone to be assigned to DHCP clients.	option	-	00								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>01</td><td>(GMT-11:00) Midway Island, Samoa</td></tr><tr><td>02</td><td>(GMT-10:00) Hawaii</td></tr></table>				Option	Description	01	(GMT-11:00) Midway Island, Samoa	02	(GMT-10:00) Hawaii		
Option	Description											
01	(GMT-11:00) Midway Island, Samoa											
02	(GMT-10:00) Hawaii											

Parameter	Description	Type	Size	Default
	Option	Description		
	03	(GMT-9:00) Alaska		
	04	(GMT-8:00) Pacific Time (US & Canada)		
	05	(GMT-7:00) Arizona		
	81	(GMT-7:00) Baja California Sur, Chihuahua		
	06	(GMT-7:00) Mountain Time (US & Canada)		
	07	(GMT-6:00) Central America		
	08	(GMT-6:00) Central Time (US & Canada)		
	09	(GMT-6:00) Mexico City		
	10	(GMT-6:00) Saskatchewan		
	11	(GMT-5:00) Bogota, Lima, Quito		
	12	(GMT-5:00) Eastern Time (US & Canada)		
	13	(GMT-5:00) Indiana (East)		
	74	(GMT-4:00) Caracas		
	14	(GMT-4:00) Atlantic Time (Canada)		
	77	(GMT-4:00) Georgetown		
	15	(GMT-4:00) La Paz		
	87	(GMT-4:00) Paraguay		
	16	(GMT-3:00) Santiago		
	17	(GMT-3:30) Newfoundland		
	18	(GMT-3:00) Brasilia		
	19	(GMT-3:00) Buenos Aires		
	20	(GMT-3:00) Nuuk (Greenland)		
	75	(GMT-3:00) Uruguay		
	21	(GMT-2:00) Mid-Atlantic		
	22	(GMT-1:00) Azores		
	23	(GMT-1:00) Cape Verde Is.		
	24	(GMT) Monrovia		
	80	(GMT) Greenwich Mean Time		
	79	(GMT) Casablanca		

Parameter	Description	Type	Size	Default
	Option	Description		
	25	(GMT) Dublin, Edinburgh, Lisbon, London, Canary Is.		
	26	(GMT+1:00) Amsterdam, Berlin, Bern, Rome, Stockholm, Vienna		
	27	(GMT+1:00) Belgrade, Bratislava, Budapest, Ljubljana, Prague		
	28	(GMT+1:00) Brussels, Copenhagen, Madrid, Paris		
	78	(GMT+1:00) Namibia		
	29	(GMT+1:00) Sarajevo, Skopje, Warsaw, Zagreb		
	30	(GMT+1:00) West Central Africa		
	31	(GMT+2:00) Kyiv, Athens, Sofia, Vilnius		
	32	(GMT+2:00) Bucharest		
	33	(GMT+2:00) Cairo		
	34	(GMT+2:00) Harare, Pretoria		
	35	(GMT+2:00) Helsinki, Riga, Tallinn		
	36	(GMT+2:00) Jerusalem		
	37	(GMT+3:00) Baghdad		
	38	(GMT+3:00) Kuwait, Riyadh		
	83	(GMT+3:00) Moscow		
	84	(GMT+3:00) Minsk		
	40	(GMT+3:00) Nairobi		
	85	(GMT+3:00) Istanbul		
	39	(GMT+3:00) St. Petersburg, Volgograd		
	41	(GMT+3:30) Tehran		
	42	(GMT+4:00) Abu Dhabi, Muscat		
	43	(GMT+4:00) Baku		
	44	(GMT+4:30) Kabul		
	45	(GMT+5:00) Ekaterinburg		
	46	(GMT+5:00) Islamabad, Karachi, Tashkent		
	47	(GMT+5:30) Kolkata, Chennai, Mumbai, New Delhi		
	51	(GMT+5:30) Sri Jayawardenepara		
	48	(GMT+5:45) Kathmandu		

Parameter	Description	Type	Size	Default
	Option	Description		
	49	(GMT+5:00) Almaty, Astana		
	50	(GMT+6:00) Dhaka		
	52	(GMT+6:30) Rangoon		
	53	(GMT+7:00) Bangkok, Hanoi, Jakarta, Novosibirsk		
	54	(GMT+7:00) Krasnoyarsk		
	55	(GMT+8:00) Beijing, ChongQing, HongKong, Urumgi, Irkutsk		
	56	(GMT+8:00) Ulaan Bataar		
	57	(GMT+8:00) Kuala Lumpur, Singapore		
	58	(GMT+8:00) Perth		
	59	(GMT+8:00) Taipei		
	60	(GMT+9:00) Osaka, Sapporo, Tokyo, Seoul		
	61	(GMT+9:00) Yakutsk		
	62	(GMT+9:30) Adelaide		
	63	(GMT+9:30) Darwin		
	64	(GMT+10:00) Brisbane		
	65	(GMT+10:00) Canberra, Melbourne, Sydney		
	66	(GMT+10:00) Guam, Port Moresby		
	67	(GMT+10:00) Hobart		
	68	(GMT+10:00) Vladivostok		
	69	(GMT+10:00) Magadan		
	70	(GMT+11:00) Solomon Is., New Caledonia		
	71	(GMT+12:00) Auckland, Wellington		
	72	(GMT+12:00) Fiji, Kamchatka, Marshall Is.		
	00	(GMT+12:00) Eniwetok, Kwajalein		
	82	(GMT+12:45) Chatham Islands		
	73	(GMT+13:00) Nuku'alofa		
	86	(GMT+13:00) Samoa		
	76	(GMT+14:00) Kiritimati		

Parameter	Description	Type	Size	Default						
tftp-server <tftp-server>	One or more hostnames or IP addresses of the TFTP servers in quotes separated by spaces. TFTP server.	string	Maximum length: 63							
filename	Name of the boot file on the TFTP server.	string	Maximum length: 127							
server-type	DHCP server can be a normal DHCP server or an IPsec DHCP server.	option	-	regular						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>regular</i></td><td>Regular DHCP service.</td></tr><tr><td><i>ipsec</i></td><td>DHCP over IPsec service.</td></tr></table>	Option	Description	<i>regular</i>	Regular DHCP service.	<i>ipsec</i>	DHCP over IPsec service.			
Option	Description									
<i>regular</i>	Regular DHCP service.									
<i>ipsec</i>	DHCP over IPsec service.									
ip-mode	Method used to assign client IP.	option	-	range						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>range</i></td><td>Use range defined by start-ip/end-ip to assign client IP.</td></tr><tr><td><i>usrgrp</i></td><td>Use user-group defined method to assign client IP.</td></tr></table>	Option	Description	<i>range</i>	Use range defined by start-ip/end-ip to assign client IP.	<i>usrgrp</i>	Use user-group defined method to assign client IP.			
Option	Description									
<i>range</i>	Use range defined by start-ip/end-ip to assign client IP.									
<i>usrgrp</i>	Use user-group defined method to assign client IP.									
conflicted-ip-timeout	Time in seconds to wait after a conflicted IP address is removed from the DHCP range before it can be reused.	integer	Minimum value: 60 Maximum value: 8640000	1800						
ipsec-lease-hold	DHCP over IPsec leases expire this many seconds after tunnel down (0 to disable forced-expiry).	integer	Minimum value: 0 Maximum value: 8640000	60						
auto-configuration	Enable/disable auto configuration.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable auto configuration.</td></tr><tr><td><i>enable</i></td><td>Enable auto configuration.</td></tr></table>	Option	Description	<i>disable</i>	Disable auto configuration.	<i>enable</i>	Enable auto configuration.			
Option	Description									
<i>disable</i>	Disable auto configuration.									
<i>enable</i>	Enable auto configuration.									
dhcp-settings-from-fortiipam	Enable/disable populating of DHCP server settings from FortiIPAM.	option	-	disable						

Parameter	Description	Type	Size	Default
	Option Description			
	<i>disable</i>	Disable populating of DHCP server settings from FortiIPAM.		
	<i>enable</i>	Enable populating of DHCP server settings from FortiIPAM.		
auto-managed-status	Enable/disable use of this DHCP server once this interface has been assigned an IP address from FortiIPAM.	option	-	enable
	Option Description			
	<i>disable</i>	Disable use of this DHCP server once this interface has been assigned an IP address from FortiIPAM.		
	<i>enable</i>	Enable use of this DHCP server once this interface has been assigned an IP address from FortiIPAM.		
ddns-update	Enable/disable DDNS update for DHCP.	option	-	disable
	Option Description			
	<i>disable</i>	Disable DDNS update for DHCP.		
	<i>enable</i>	Enable DDNS update for DHCP.		
ddns-update-override	Enable/disable DDNS update override for DHCP.	option	-	disable
	Option Description			
	<i>disable</i>	Disable DDNS update override for DHCP.		
	<i>enable</i>	Enable DDNS update override for DHCP.		
ddns-server-ip	DDNS server IP.	ipv4-address	Not Specified	0.0.0.0
ddns-zone	Zone of your domain name (ex. DDNS.com).	string	Maximum length: 64	
ddns-auth	DDNS authentication mode.	option	-	disable
	Option Description			
	<i>disable</i>	Disable DDNS authentication.		
	<i>tsig</i>	TSIG based on RFC2845.		
ddns-keyname	DDNS update key name.	string	Maximum length: 64	

Parameter	Description	Type	Size	Default
ddns-key	DDNS update key (base 64 encoding).	password_aes256	Not Specified	
ddns-ttl	TTL.	integer	Minimum value: 60 Maximum value: 86400	300
vci-match	Enable/disable vendor class identifier (VCI) matching. When enabled only DHCP requests with a matching VCI are served.	option	-	disable
	Option		Description	
	<i>disable</i>		Disable VCI matching.	
	<i>enable</i>		Enable VCI matching.	
vci-string <vci-string>	One or more VCI strings in quotes separated by spaces. VCI strings.	string	Maximum length: 255	

config ip-range

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
start-ip	Start of IP range.	ipv4-address	Not Specified	0.0.0.0
end-ip	End of IP range.	ipv4-address	Not Specified	0.0.0.0
vci-match	Enable/disable vendor class identifier (VCI) matching. When enabled only DHCP requests with a matching VCI are served with this range.	option	-	disable
	Option		Description	
	<i>disable</i>		Disable VCI matching.	
	<i>enable</i>		Enable VCI matching.	

Parameter	Description	Type	Size	Default						
vci-string <vci-string>	One or more VCI strings in quotes separated by spaces. VCI strings.	string	Maximum length: 255							
uci-match	Enable/disable user class identifier (UCI) matching. When enabled only DHCP requests with a matching UCI are served with this range.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable UCI matching.</td></tr><tr><td>enable</td><td>Enable UCI matching.</td></tr></table>				Option	Description	disable	Disable UCI matching.	enable	Enable UCI matching.
Option	Description									
disable	Disable UCI matching.									
enable	Enable UCI matching.									
uci-string <uci-string>	One or more UCI strings in quotes separated by spaces. UCI strings.	string	Maximum length: 255							
lease-time	Lease time in seconds, 0 means default lease time.	integer	Minimum value: 300 Maximum value: 8640000	0						

config options

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
code	DHCP option code.	integer	Minimum value: 0 Maximum value: 255	0
type	DHCP option type.	option	-	hex
	Option	Description		
	<i>hex</i>	DHCP option in hex.		
	<i>string</i>	DHCP option in string.		
	<i>ip</i>	DHCP option in IP.		
	<i>fqdn</i>	DHCP option in domain search option format.		

Parameter	Description	Type	Size	Default						
value	DHCP option value.	string	Maximum length: 312							
ip	DHCP option IPs.	user	Not Specified							
vci-match	Enable/disable vendor class identifier (VCI) matching. When enabled only DHCP requests with a matching VCI are served with this option.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable VCI matching.</td></tr><tr><td>enable</td><td>Enable VCI matching.</td></tr></table>				Option	Description	disable	Disable VCI matching.	enable	Enable VCI matching.
Option	Description									
disable	Disable VCI matching.									
enable	Enable VCI matching.									
vci-string <vci-string>	One or more VCI strings in quotes separated by spaces. VCI strings.	string	Maximum length: 255							
uci-match	Enable/disable user class identifier (UCI) matching. When enabled only DHCP requests with a matching UCI are served with this option.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable UCI matching.</td></tr><tr><td>enable</td><td>Enable UCI matching.</td></tr></table>				Option	Description	disable	Disable UCI matching.	enable	Enable UCI matching.
Option	Description									
disable	Disable UCI matching.									
enable	Enable UCI matching.									
uci-string <uci-string>	One or more UCI strings in quotes separated by spaces. UCI strings.	string	Maximum length: 255							

config exclude-range

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
start-ip	Start of IP range.	ipv4-address	Not Specified	0.0.0.0
end-ip	End of IP range.	ipv4-address	Not Specified	0.0.0.0

Parameter	Description	Type	Size	Default						
vci-match	Enable/disable vendor class identifier (VCI) matching. When enabled only DHCP requests with a matching VCI are served with this range.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable VCI matching.</td></tr><tr><td>enable</td><td>Enable VCI matching.</td></tr></table>	Option	Description	disable	Disable VCI matching.	enable	Enable VCI matching.			
Option	Description									
disable	Disable VCI matching.									
enable	Enable VCI matching.									
vci-string <vci-string>	One or more VCI strings in quotes separated by spaces. VCI strings.	string	Maximum length: 255							
uci-match	Enable/disable user class identifier (UCI) matching. When enabled only DHCP requests with a matching UCI are served with this range.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable UCI matching.</td></tr><tr><td>enable</td><td>Enable UCI matching.</td></tr></table>	Option	Description	disable	Disable UCI matching.	enable	Enable UCI matching.			
Option	Description									
disable	Disable UCI matching.									
enable	Enable UCI matching.									
uci-string <uci-string>	One or more UCI strings in quotes separated by spaces. UCI strings.	string	Maximum length: 255							
lease-time	Lease time in seconds, 0 means default lease time.	integer	Minimum value: 300 Maximum value: 8640000	0						

config reserved-address

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
type	DHCP reserved-address type.	option	-	mac

Parameter	Description	Type	Size	Default
	Option Description			
	<i>mac</i>	Match with MAC address.		
	<i>option82</i>	Match with DHCP option 82.		
ip	IP address to be reserved for the MAC address.	ipv4-address	Not Specified	0.0.0.0
mac	MAC address of the client that will get the reserved IP address.	mac-address	Not Specified	00:00:00:00:00:00
action	Options for the DHCP server to configure the client with the reserved MAC address.	option	-	reserved
	Option Description			
	<i>assign</i>	Configure the client with this MAC address like any other client.		
	<i>block</i>	Block the DHCP server from assigning IP settings to the client with this MAC address.		
	<i>reserved</i>	Assign the reserved IP address to the client with this MAC address.		
circuit-id-type	DHCP option type.	option	-	string
	Option Description			
	<i>hex</i>	DHCP option in hex.		
	<i>string</i>	DHCP option in string.		
circuit-id	Option 82 circuit-ID of the client that will get the reserved IP address.	string	Maximum length: 312	
remote-id-type	DHCP option type.	option	-	string
	Option Description			
	<i>hex</i>	DHCP option in hex.		
	<i>string</i>	DHCP option in string.		
remote-id	Option 82 remote-ID of the client that will get the reserved IP address.	string	Maximum length: 312	

Parameter	Description	Type	Size	Default
description	Description.	var-string	Maximum length: 255	

config system dhcp6 server

Configure DHCPv6 servers.

```

config system dhcp6 server
    Description: Configure DHCPv6 servers.
    edit <id>
        set status [disable|enable]
        set rapid-commit [disable|enable]
        set lease-time {integer}
        set dns-service [delegated|default|...]
        set dns-search-list [delegated|specify]
        set dns-server1 {ipv6-address}
        set dns-server2 {ipv6-address}
        set dns-server3 {ipv6-address}
        set dns-server4 {ipv6-address}
        set domain {string}
        set subnet {ipv6-prefix}
        set interface {string}
        set option1 {user}
        set option2 {user}
        set option3 {user}
        set upstream-interface {string}
        set delegated-prefix-iaid {integer}
        set ip-mode [range|delegated]
        set prefix-mode [dhcp6|ra]
        config prefix-range
            Description: DHCP prefix configuration.
            edit <id>
                set start-prefix {ipv6-address}
                set end-prefix {ipv6-address}
                set prefix-length {integer}
            next
        end
        config ip-range
            Description: DHCP IP range configuration.
            edit <id>
                set start-ip {ipv6-address}
                set end-ip {ipv6-address}
            next
        end
    next
end

```

config system dhcp6 server

Parameter	Description	Type	Size	Default								
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0								
status	Enable/disable this DHCPv6 configuration.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Enable this DHCPv6 server configuration.</td></tr><tr><td><i>enable</i></td><td>Disable this DHCPv6 server configuration.</td></tr></table>	Option	Description	<i>disable</i>	Enable this DHCPv6 server configuration.	<i>enable</i>	Disable this DHCPv6 server configuration.					
Option	Description											
<i>disable</i>	Enable this DHCPv6 server configuration.											
<i>enable</i>	Disable this DHCPv6 server configuration.											
rapid-commit	Enable/disable allow/disallow rapid commit.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not allow rapid commit.</td></tr><tr><td><i>enable</i></td><td>Allow rapid commit.</td></tr></table>	Option	Description	<i>disable</i>	Do not allow rapid commit.	<i>enable</i>	Allow rapid commit.					
Option	Description											
<i>disable</i>	Do not allow rapid commit.											
<i>enable</i>	Allow rapid commit.											
lease-time	Lease time in seconds, 0 means unlimited.	integer	Minimum value: 300 Maximum value: 8640000	604800								
dns-service	Options for assigning DNS servers to DHCPv6 clients.	option	-	specify								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>delegated</i></td><td>Delegated DNS settings.</td></tr><tr><td><i>default</i></td><td>Clients are assigned the FortiProxy's configured DNS servers.</td></tr><tr><td><i>specify</i></td><td>Specify up to 3 DNS servers in the DHCPv6 server configuration.</td></tr></table>	Option	Description	<i>delegated</i>	Delegated DNS settings.	<i>default</i>	Clients are assigned the FortiProxy's configured DNS servers.	<i>specify</i>	Specify up to 3 DNS servers in the DHCPv6 server configuration.			
Option	Description											
<i>delegated</i>	Delegated DNS settings.											
<i>default</i>	Clients are assigned the FortiProxy's configured DNS servers.											
<i>specify</i>	Specify up to 3 DNS servers in the DHCPv6 server configuration.											
dns-search-list	DNS search list options.	option	-	specify								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>delegated</i></td><td>Delegated the DNS search list.</td></tr><tr><td><i>specify</i></td><td>Specify the DNS search list.</td></tr></table>	Option	Description	<i>delegated</i>	Delegated the DNS search list.	<i>specify</i>	Specify the DNS search list.					
Option	Description											
<i>delegated</i>	Delegated the DNS search list.											
<i>specify</i>	Specify the DNS search list.											

Parameter	Description	Type	Size	Default						
dns-server1	DNS server 1.	ipv6-address	Not Specified	::						
dns-server2	DNS server 2.	ipv6-address	Not Specified	::						
dns-server3	DNS server 3.	ipv6-address	Not Specified	::						
dns-server4	DNS server 4.	ipv6-address	Not Specified	::						
domain	Domain name suffix for the IP addresses that the DHCP server assigns to clients.	string	Maximum length: 35							
subnet	Subnet or subnet-id if the IP mode is delegated.	ipv6-prefix	Not Specified	::/0						
interface	DHCP server can assign IP configurations to clients connected to this interface.	string	Maximum length: 15							
option1	Option 1.	user	Not Specified							
option2	Option 2.	user	Not Specified							
option3	Option 3.	user	Not Specified							
upstream-interface	Interface name from where delegated information is provided.	string	Maximum length: 15							
delegated-prefix-iaid	IAID of obtained delegated-prefix from the upstream interface.	integer	Minimum value: 0 Maximum value: 4294967295	0						
ip-mode	Method used to assign client IP.	option	-	range						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>range</td><td>Use range defined by start IP/end IP to assign client IP.</td></tr><tr><td>delegated</td><td>Use delegated prefix method to assign client IP.</td></tr></table>				Option	Description	range	Use range defined by start IP/end IP to assign client IP.	delegated	Use delegated prefix method to assign client IP.
Option	Description									
range	Use range defined by start IP/end IP to assign client IP.									
delegated	Use delegated prefix method to assign client IP.									
prefix-mode	Assigning a prefix from a DHCPv6 client or RA.	option	-	dhcp6						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>dhcp6</td><td>Use delegated prefix from a DHCPv6 client.</td></tr><tr><td>ra</td><td>Use prefix from RA.</td></tr></table>				Option	Description	dhcp6	Use delegated prefix from a DHCPv6 client.	ra	Use prefix from RA.
Option	Description									
dhcp6	Use delegated prefix from a DHCPv6 client.									
ra	Use prefix from RA.									

config prefix-range

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
start-prefix	Start of prefix range.	ipv6-address	Not Specified	::
end-prefix	End of prefix range.	ipv6-address	Not Specified	::
prefix-length	Prefix length.	integer	Minimum value: 1 Maximum value: 128	0

config ip-range

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
start-ip	Start of IP range.	ipv6-address	Not Specified	::
end-ip	End of IP range.	ipv6-address	Not Specified	::

config system dns

Configure DNS.

```
config system dns
  Description: Configure DNS.
  set primary {ipv4-address}
  set secondary {ipv4-address}
  set protocol {option1}, {option2}, ...
  set ssl-certificate {string}
  set server-hostname <hostname1>, <hostname2>, ...
  set domain <domain1>, <domain2>, ...
  set ip6-primary {ipv6-address}
```

```

set ip6-secondary {ipv6-address}
set timeout {integer}
set retry {integer}
set dns-cache-limit {integer}
set dns-cache-ttl {integer}
set cache-notfound-responses [disable|enable]
set source-ip {ipv4-address}
set interface-select-method [auto|specify]
set interface {string}
set server-select-method [least-rtt|failover]
set alt-primary {ipv4-address}
set alt-secondary {ipv4-address}
set log [disable|error|...]
set fqdn-cache-ttl {integer}
set fqdn-min-refresh {integer}
end

```

config system dns

Parameter	Description	Type	Size	Default								
primary	Primary DNS server IP address.	ipv4-address	Not Specified	0.0.0.0								
secondary	Secondary DNS server IP address.	ipv4-address	Not Specified	0.0.0.0								
protocol	DNS transport protocols.	option	-	cleartext								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>cleartext</td><td>DNS over UDP/53, DNS over TCP/53.</td></tr><tr><td>dot</td><td>DNS over TLS/853.</td></tr><tr><td>doh</td><td>DNS over HTTPS/443.</td></tr></table>				Option	Description	cleartext	DNS over UDP/53, DNS over TCP/53.	dot	DNS over TLS/853.	doh	DNS over HTTPS/443.
Option	Description											
cleartext	DNS over UDP/53, DNS over TCP/53.											
dot	DNS over TLS/853.											
doh	DNS over HTTPS/443.											
ssl-certificate	Name of local certificate for SSL connections.	string	Maximum length: 35	Fortinet_Factory								
server-hostname <hostname>	DNS server host name list. DNS server host name list separated by space (maximum 4 domains).	string	Maximum length: 127									
domain <domain>	Search suffix list for hostname lookup. DNS search domain list separated by space (maximum 8 domains).	string	Maximum length: 127									
ip6-primary	Primary DNS server IPv6 address.	ipv6-address	Not Specified	::								

Parameter	Description	Type	Size	Default						
ip6-secondary	Secondary DNS server IPv6 address.	ipv6-address	Not Specified	::						
timeout	DNS query timeout interval in seconds (1 - 10).	integer	Minimum value: 1 Maximum value: 10	5						
retry	Number of times to retry (0 - 5).	integer	Minimum value: 0 Maximum value: 5	2						
dns-cache-limit	Maximum number of records in the DNS cache.	integer	Minimum value: 0 Maximum value: 4294967295	5000						
dns-cache-ttl	Duration in seconds that the DNS cache retains information.	integer	Minimum value: 60 Maximum value: 86400	1800						
cache-notfound-responses	Enable/disable response from the DNS server when a record is not in cache.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable cache NOTFOUND responses from DNS server.</td></tr><tr><td><i>enable</i></td><td>Enable cache NOTFOUND responses from DNS server.</td></tr></table>				Option	Description	<i>disable</i>	Disable cache NOTFOUND responses from DNS server.	<i>enable</i>	Enable cache NOTFOUND responses from DNS server.
Option	Description									
<i>disable</i>	Disable cache NOTFOUND responses from DNS server.									
<i>enable</i>	Enable cache NOTFOUND responses from DNS server.									
source-ip	IP address used by the DNS server as its source IP.	ipv4-address	Not Specified	0.0.0.0						
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Set outgoing interface automatically.</td></tr><tr><td><i>specify</i></td><td>Set outgoing interface manually.</td></tr></table>				Option	Description	<i>auto</i>	Set outgoing interface automatically.	<i>specify</i>	Set outgoing interface manually.
Option	Description									
<i>auto</i>	Set outgoing interface automatically.									
<i>specify</i>	Set outgoing interface manually.									
interface	Specify outgoing interface to reach server.	string	Maximum length: 15							

Parameter	Description	Type	Size	Default
server-select-method	Specify how configured servers are prioritized.	option	-	least-rtt
	Option	Description		
	<i>least-rtt</i>	Select servers based on least round trip time.		
	<i>failover</i>	Select servers based on the order they are configured.		
alt-primary	Alternate primary DNS server. This is not used as a failover DNS server.	ipv4-address	Not Specified	0.0.0.0
alt-secondary	Alternate secondary DNS server. This is not used as a failover DNS server.	ipv4-address	Not Specified	0.0.0.0
log	Local DNS log setting.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable.		
	<i>error</i>	Enable local DNS error log.		
	<i>all</i>	Enable local DNS log.		
fqdn-cache-ttl	FQDN cache time to live in seconds (0 - 86400, default = 0).	integer	Minimum value: 0 Maximum value: 86400	0
fqdn-min-refresh	FQDN cache minimum refresh time in seconds (10 - 3600, default = 60).	integer	Minimum value: 10 Maximum value: 3600	60

config system dns-database

Configure DNS databases.

```

config system dns-database
  Description: Configure DNS databases.
  edit <name>
    set status [enable|disable]
    set domain {string}
    set allow-transfer {user}
    set type [primary|secondary]
    set view [shadow|public|...]
    set ip-primary {ipv4-address-any}
    set primary-name {string}
    set contact {string}

```

```

set ttl {integer}
set authoritative [enable|disable]
set forwarder {user}
set source-ip {ipv4-address}
set rr-max {integer}
config dns-entry
    Description: DNS entry.
    edit <id>
        set status [enable|disable]
        set type [A|NS|...]
        set ttl {integer}
        set preference {integer}
        set ip {ipv4-address-any}
        set ipv6 {ipv6-address}
        set hostname {string}
        set canonical-name {string}
    next
end
next
end

```

config system dns-database

Parameter	Description	Type	Size	Default						
name	Zone name.	string	Maximum length: 35							
status	Enable/disable this DNS zone.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
domain	Domain name.	string	Maximum length: 255							
allow-transfer	DNS zone transfer IP address list.	user	Not Specified							
type	Zone type (primary to manage entries directly, secondary to import entries from other zones).	option	-	primary						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>primary</i></td><td>Primary DNS zone, to manage entries directly.</td></tr><tr><td><i>secondary</i></td><td>Secondary DNS zone, to import entries from other DNS zones.</td></tr></table>	Option	Description	<i>primary</i>	Primary DNS zone, to manage entries directly.	<i>secondary</i>	Secondary DNS zone, to import entries from other DNS zones.			
Option	Description									
<i>primary</i>	Primary DNS zone, to manage entries directly.									
<i>secondary</i>	Secondary DNS zone, to import entries from other DNS zones.									

Parameter	Description	Type	Size	Default
view	Zone view (public to serve public clients, shadow to serve internal clients).	option	-	shadow
	Option	Description		
	<i>shadow</i>	Shadow DNS zone to serve internal clients.		
	<i>public</i>	Public DNS zone to serve public clients.		
	<i>shadow-ztna</i>	implicit DNS zone for ztna dox tunnel.		
ip-primary	IP address of primary DNS server. Entries in this primary DNS server and imported into the DNS zone.	ipv4-address-any	Not Specified	0.0.0.0
primary-name	Domain name of the default DNS server for this zone.	string	Maximum length: 255	dns
contact	Email address of the administrator for this zone. You can specify only the username, such as admin or the full email address, such as admin@test.com When using only a username, the domain of the email will be this zone.	string	Maximum length: 255	host
ttd	Default time-to-live value for the entries of this DNS zone (0 - 2147483647 sec, default = 86400).	integer	Minimum value: 0 Maximum value: 2147483647	86400
authoritative	Enable/disable authoritative zone.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable authoritative zone.		
	<i>disable</i>	Disable authoritative zone.		
forwarder	DNS zone forwarder IP address list.	user	Not Specified	
source-ip	Source IP for forwarding to DNS server.	ipv4-address	Not Specified	0.0.0.0
rr-max	Maximum number of resource records (10 - 65536, 0 means infinite).	integer	Minimum value: 10 Maximum value: 65536	16384

config dns-entry

Parameter	Description	Type	Size	Default																
id	DNS entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0																
status	Enable/disable resource record status.	option	-	enable																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable resource record status.</td></tr><tr><td><i>disable</i></td><td>Disable resource record status.</td></tr></table>				Option	Description	<i>enable</i>	Enable resource record status.	<i>disable</i>	Disable resource record status.										
	Option	Description																		
	<i>enable</i>	Enable resource record status.																		
<i>disable</i>	Disable resource record status.																			
type	Resource record type.	option	-	A																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>A</i></td><td>Host type.</td></tr><tr><td><i>NS</i></td><td>Name server type.</td></tr><tr><td><i>CNAME</i></td><td>Canonical name type.</td></tr><tr><td><i>MX</i></td><td>Mail exchange type.</td></tr><tr><td><i>AAAA</i></td><td>IPv6 host type.</td></tr><tr><td><i>PTR</i></td><td>Pointer type.</td></tr><tr><td><i>PTR_V6</i></td><td>IPv6 pointer type.</td></tr></table>				Option	Description	<i>A</i>	Host type.	<i>NS</i>	Name server type.	<i>CNAME</i>	Canonical name type.	<i>MX</i>	Mail exchange type.	<i>AAAA</i>	IPv6 host type.	<i>PTR</i>	Pointer type.	<i>PTR_V6</i>	IPv6 pointer type.
	Option	Description																		
	<i>A</i>	Host type.																		
	<i>NS</i>	Name server type.																		
	<i>CNAME</i>	Canonical name type.																		
	<i>MX</i>	Mail exchange type.																		
	<i>AAAA</i>	IPv6 host type.																		
	<i>PTR</i>	Pointer type.																		
<i>PTR_V6</i>	IPv6 pointer type.																			
ttl	Time-to-live for this entry (0 to 2147483647 sec, default = 0).	integer	Minimum value: 0 Maximum value: 2147483647	0																
preference	DNS entry preference (0 - 65535, highest preference = 0, default = 10).	integer	Minimum value: 0 Maximum value: 65535	10																
ip	IPv4 address of the host.	ipv4-address-any	Not Specified	0.0.0.0																
ipv6	IPv6 address of the host.	ipv6-address	Not Specified	::																
hostname	Name of the host.	string	Maximum length: 255																	

Parameter	Description	Type	Size	Default
canonical-name	Canonical name of the host.	string	Maximum length: 255	

config system dns-server

Configure DNS servers.

```

config system dns-server
    Description: Configure DNS servers.
    edit <name>
        set mode [recursive|non-recursive|...]
        set dnsfilter-profile {string}
        set doh [enable|disable]
        set doh3 [enable|disable]
        set doq [enable|disable]
    next
end

```

config system dns-server

Parameter	Description	Type	Size	Default								
name	DNS server name.	string	Maximum length: 15									
mode	DNS server mode.	option	-	recursive								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>recursive</i></td><td>Shadow DNS database and forward.</td></tr><tr><td><i>non-recursive</i></td><td>Public DNS database only.</td></tr><tr><td><i>forward-only</i></td><td>Forward only.</td></tr></table>				Option	Description	<i>recursive</i>	Shadow DNS database and forward.	<i>non-recursive</i>	Public DNS database only.	<i>forward-only</i>	Forward only.
	Option	Description										
	<i>recursive</i>	Shadow DNS database and forward.										
	<i>non-recursive</i>	Public DNS database only.										
<i>forward-only</i>	Forward only.											
dnsfilter-profile	DNS filter profile.	string	Maximum length: 35									
doh	Enable/disable DNS over HTTPS/443 (default = disable).	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable DNS over HTTPS.</td></tr><tr><td><i>disable</i></td><td>Disable DNS over HTTPS.</td></tr></table>				Option	Description	<i>enable</i>	Enable DNS over HTTPS.	<i>disable</i>	Disable DNS over HTTPS.		
	Option	Description										
	<i>enable</i>	Enable DNS over HTTPS.										
<i>disable</i>	Disable DNS over HTTPS.											

Parameter	Description	Type	Size	Default						
doh3	Enable/disable DNS over QUIC/HTTP3/443 (default = disable).	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable DNS over HTTP3/QUIC.</td></tr><tr><td><i>disable</i></td><td>Disable DNS over HTTP3/QUIC.</td></tr></table>	Option	Description	<i>enable</i>	Enable DNS over HTTP3/QUIC.	<i>disable</i>	Disable DNS over HTTP3/QUIC.			
Option	Description									
<i>enable</i>	Enable DNS over HTTP3/QUIC.									
<i>disable</i>	Disable DNS over HTTP3/QUIC.									
doq	Enable/disable DNS over QUIC/853 (default = disable).	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable DNS over QUIC.</td></tr><tr><td><i>disable</i></td><td>Disable DNS over QUIC.</td></tr></table>	Option	Description	<i>enable</i>	Enable DNS over QUIC.	<i>disable</i>	Disable DNS over QUIC.			
Option	Description									
<i>enable</i>	Enable DNS over QUIC.									
<i>disable</i>	Disable DNS over QUIC.									

config system dscp-based-priority

Configure DSCP based priority table.

```

config system dscp-based-priority
    Description: Configure DSCP based priority table.
    edit <id>
        set ds {integer}
        set priority [low|medium|...]
    next
end

```

config system dscp-based-priority

Parameter	Description	Type	Size	Default
id	Item ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
ds	DSCP(DiffServ) DS value (0 - 63).	integer	Minimum value: 0 Maximum value: 63	0
priority	DSCP based priority level.	option	-	high

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>low</i>	Low priority.		
	<i>medium</i>	Medium priority.		
	<i>high</i>	High priority.		

config system email-server

Configure the email server used by the FortiProxy various things. For example, for sending email messages to users to support user authentication features.

```
config system email-server
    Description: Configure the email server used by the FortiProxy various things. For example,
    for sending email messages to users to support user authentication features.
    set type {option}
    set reply-to {string}
    set server {string}
    set port {integer}
    set source-ip {ipv4-address}
    set source-ip6 {ipv6-address}
    set authenticate [enable|disable]
    set validate-server [enable|disable]
    set username {string}
    set password {password}
    set security [none|starttls|...]
    set ssl-min-proto-version [default|SSLv3|...]
    set interface-select-method [auto|specify]
    set interface {string}
end
```

config system email-server

Parameter	Description	Type	Size	Default
type	Use FortiGuard Message service or custom email server.	option	-	custom
	Option	Description		
	<i>custom</i>	Use custom email server.		
reply-to	Reply-To email address.	string	Maximum length: 63	

Parameter	Description	Type	Size	Default								
server	SMTP server IP address or hostname.	string	Maximum length: 63									
port	SMTP server port.	integer	Minimum value: 1 Maximum value: 65535	25								
source-ip	SMTP server IPv4 source IP.	ipv4-address	Not Specified	0.0.0.0								
source-ip6	SMTP server IPv6 source IP.	ipv6-address	Not Specified	::								
authenticate	Enable/disable authentication.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable authentication.</td></tr><tr><td><i>disable</i></td><td>Disable authentication.</td></tr></table>				Option	Description	<i>enable</i>	Enable authentication.	<i>disable</i>	Disable authentication.		
Option	Description											
<i>enable</i>	Enable authentication.											
<i>disable</i>	Disable authentication.											
validate-server	Enable/disable validation of server certificate.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable validation of server certificate.</td></tr><tr><td><i>disable</i></td><td>Disable validation of server certificate.</td></tr></table>				Option	Description	<i>enable</i>	Enable validation of server certificate.	<i>disable</i>	Disable validation of server certificate.		
Option	Description											
<i>enable</i>	Enable validation of server certificate.											
<i>disable</i>	Disable validation of server certificate.											
username	SMTP server user name for authentication.	string	Maximum length: 63									
password	SMTP server user password for authentication.	password	Not Specified									
security	Connection security used by the email server.	option	-	none								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>none</i></td><td>None.</td></tr><tr><td><i>starttls</i></td><td>STARTTLS.</td></tr><tr><td><i>smtps</i></td><td>SSL/TLS.</td></tr></table>				Option	Description	<i>none</i>	None.	<i>starttls</i>	STARTTLS.	<i>smtps</i>	SSL/TLS.
Option	Description											
<i>none</i>	None.											
<i>starttls</i>	STARTTLS.											
<i>smtps</i>	SSL/TLS.											
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default								

Parameter	Description	Type	Size	Default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Follow system global setting.</td></tr><tr><td><i>SSLv3</i></td><td>SSLv3.</td></tr><tr><td><i>TLSv1</i></td><td>TLSv1.</td></tr><tr><td><i>TLSv1-1</i></td><td>TLSv1.1.</td></tr><tr><td><i>TLSv1-2</i></td><td>TLSv1.2.</td></tr></table>	Option	Description	<i>default</i>	Follow system global setting.	<i>SSLv3</i>	SSLv3.	<i>TLSv1</i>	TLSv1.	<i>TLSv1-1</i>	TLSv1.1.	<i>TLSv1-2</i>	TLSv1.2.			
	Option	Description														
	<i>default</i>	Follow system global setting.														
	<i>SSLv3</i>	SSLv3.														
	<i>TLSv1</i>	TLSv1.														
	<i>TLSv1-1</i>	TLSv1.1.														
<i>TLSv1-2</i>	TLSv1.2.															
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Set outgoing interface automatically.</td></tr><tr><td><i>specify</i></td><td>Set outgoing interface manually.</td></tr></table>	Option	Description	<i>auto</i>	Set outgoing interface automatically.	<i>specify</i>	Set outgoing interface manually.									
	Option	Description														
	<i>auto</i>	Set outgoing interface automatically.														
<i>specify</i>	Set outgoing interface manually.															
interface	Specify outgoing interface to reach server.	string	Maximum length: 15													

config system external-resource

Configure external resource.

```

config system external-resource
  Description: Configure external resource.
  edit <name>
    set uuid {uuid}
    set status [enable|disable]
    set type [category|address|...]
    set update-method [feed|push]
    set category {integer}
    set username {string}
    set password {password}
    set comments {var-string}
    set resource {string}
    set user-agent {var-string}
    set server-identity-check [none|basic|...]
    set proxy {string}
    set proxy-port {integer}
    set proxy-username {string}
    set proxy-password {password}
    set refresh-rate {integer}
    set source-ip {ipv4-address}
    set interface-select-method [auto|specify]
    set interface {string}

```

```
next
end
```

config system external-resource

Parameter	Description	Type	Size	Default														
name	External resource name.	string	Maximum length: 35															
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000														
status	Enable/disable user resource.	option	-	enable														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable user resource.</td></tr><tr><td><i>disable</i></td><td>Disable user resource.</td></tr></table>	Option	Description	<i>enable</i>	Enable user resource.	<i>disable</i>	Disable user resource.											
Option	Description																	
<i>enable</i>	Enable user resource.																	
<i>disable</i>	Disable user resource.																	
type	User resource type.	option	-	category														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>category</i></td><td>FortiGuard category.</td></tr><tr><td><i>address</i></td><td>Firewall IP address.</td></tr><tr><td><i>domain</i></td><td>Domain Name.</td></tr><tr><td><i>malware</i></td><td>Malware hash.</td></tr><tr><td><i>url</i></td><td>URL List.</td></tr><tr><td><i>data</i></td><td>Data file.</td></tr></table>	Option	Description	<i>category</i>	FortiGuard category.	<i>address</i>	Firewall IP address.	<i>domain</i>	Domain Name.	<i>malware</i>	Malware hash.	<i>url</i>	URL List.	<i>data</i>	Data file.			
Option	Description																	
<i>category</i>	FortiGuard category.																	
<i>address</i>	Firewall IP address.																	
<i>domain</i>	Domain Name.																	
<i>malware</i>	Malware hash.																	
<i>url</i>	URL List.																	
<i>data</i>	Data file.																	
update-method	External resource update method.	option	-	feed														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>feed</i></td><td>FortiGate unit will pull update from the external resource.</td></tr><tr><td><i>push</i></td><td>External Resource update is pushed to the FortiGate unit through the FortiGate unit's RESTAPI/CLI.</td></tr></table>	Option	Description	<i>feed</i>	FortiGate unit will pull update from the external resource.	<i>push</i>	External Resource update is pushed to the FortiGate unit through the FortiGate unit's RESTAPI/CLI.											
Option	Description																	
<i>feed</i>	FortiGate unit will pull update from the external resource.																	
<i>push</i>	External Resource update is pushed to the FortiGate unit through the FortiGate unit's RESTAPI/CLI.																	
category	User resource category.	integer	Minimum value: 192 Maximum value: 221	0														

Parameter	Description	Type	Size	Default								
username	HTTP basic authentication user name.	string	Maximum length: 64									
password	HTTP basic authentication password.	password	Not Specified									
comments	Comment.	var-string	Maximum length: 255									
resource	URI of external resource.	string	Maximum length: 511									
user-agent	HTTP User-Agent header (default = 'curl/7.58.0').	var-string	Maximum length: 255									
server-identity-check	Certificate verification option.	option	-	none								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>none</i></td><td>No certificate verification.</td></tr><tr><td><i>basic</i></td><td>Check server certificate only.</td></tr><tr><td><i>full</i></td><td>Check server certificate and verify the domain matches in the server certificate.</td></tr></table>				Option	Description	<i>none</i>	No certificate verification.	<i>basic</i>	Check server certificate only.	<i>full</i>	Check server certificate and verify the domain matches in the server certificate.
Option	Description											
<i>none</i>	No certificate verification.											
<i>basic</i>	Check server certificate only.											
<i>full</i>	Check server certificate and verify the domain matches in the server certificate.											
proxy	Proxy server host(ip or domain name).	string	Maximum length: 255									
proxy-port	Port number that the proxy server expects to receive HTTP sessions on (1 - 65535, default = 8080).	integer	Minimum value: 1 Maximum value: 65535	8080								
proxy-username	HTTP proxy basic authentication user name.	string	Maximum length: 64									
proxy-password	HTTP proxy basic authentication password.	password	Not Specified									
refresh-rate	Time interval to refresh external resource (1 - 43200 min, default = 5 min).	integer	Minimum value: 1 Maximum value: 43200	5								
source-ip	Source IPv4 address used to communicate with server.	ipv4-address	Not Specified	0.0.0.0								

Parameter	Description	Type	Size	Default
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto
		Option	Description	
		<i>auto</i>	Set outgoing interface automatically.	
		<i>specify</i>	Set outgoing interface manually.	
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	

config system fabric-vpn

Setup for self orchestrated fabric auto discovery VPN.

```

config system fabric-vpn
  Description: Setup for self orchestrated fabric auto discovery VPN.
  set status [enable|disable]
  set sync-mode [enable|disable]
  set branch-name {string}
  set policy-rule [health-check|manual|...]
  set vpn-role [hub|spoke]
  config overlays
    Description: Local overlay interfaces table.
    edit <name>
      set overlay-tunnel-block {ipv4-classnet-host}
      set remote-gw {ipv4-address-any}
      set interface {string}
      set bgp-neighbor {string}
      set overlay-policy {integer}
      set bgp-network {integer}
      set route-policy {integer}
      set bgp-neighbor-group {string}
      set bgp-neighbor-range {integer}
      set ipsec-phase1 {string}
      set sdwan-member {integer}
    next
  end
  config advertised-subnets
    Description: Local advertised subnets.
    edit <id>
      set prefix {ipv4-classnet}
      set access [inbound|bidirectional]
      set bgp-network {integer}
      set firewall-address {string}
      set policies {integer}
    next

```

```

end
set loopback-address-block {ipv4-classnet-host}
set loopback-interface {string}
set loopback-advertised-subnet {integer}
set psksecret {password-3}
set bgp-as {integer}
set sdwan-zone {string}
set health-checks {string}
end

```

config system fabric-vpn

Parameter	Description	Type	Size	Default
status	Enable/disable Fabric VPN.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable Fabric VPN.		
	<i>disable</i>	Disable Fabric VPN.		
sync-mode	Setting synchronised by fabric or manual.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable fabric led configuration synchronisation.		
	<i>disable</i>	Disable fabric led configuration synchronisation.		
branch-name	Branch name.	string	Maximum length: 35	
policy-rule	Policy creation rule.	option	-	health-check
	Option	Description		
	<i>health-check</i>	Create health check policy automatically.		
	<i>manual</i>	All policies will be created manually.		
	<i>auto</i>	Automatically create allow policies.		
vpn-role	Fabric VPN role.	option	-	hub
	Option	Description		
	<i>hub</i>	VPN hub.		
	<i>spoke</i>	VPN spoke.		

Parameter	Description	Type	Size	Default
loopback-address-block	IPv4 address and subnet mask for hub's loopback address, syntax: X.X.X.X/24.	ipv4-classnet-host	Not Specified	0.0.0.0 0.0.0.0
loopback-interface	Loopback interface.	string	Maximum length: 15	
loopback-advertised-subnet	Loopback advertised subnet reference.	integer	Minimum value: 0 Maximum value: 4294967295	0
psksecret	Pre-shared secret for ADVPN.	password-3	Not Specified	
bgp-as	BGP Router AS number, valid from 1 to 4294967295.	integer	Minimum value: 0 Maximum value: 4294967295	0
sdwan-zone	Reference to created SD-WAN zone.	string	Maximum length: 35	
health-checks	Underlying health checks.	string	Maximum length: 35	

config overlays

Parameter	Description	Type	Size	Default
name	Overlay name.	string	Maximum length: 79	
overlay-tunnel-block	IPv4 address and subnet mask for the overlay tunnel , syntax: X.X.X.X/24.	ipv4-classnet-host	Not Specified	0.0.0.0 0.0.0.0
remote-gw	IP address of the hub gateway (Set by hub).	ipv4-address-any	Not Specified	0.0.0.0
interface	Underlying interface name.	string	Maximum length: 15	
bgp-neighbor	Underlying BGP neighbor entry.	string	Maximum length: 45	

Parameter	Description	Type	Size	Default
overlay-policy	The overlay policy to allow ADVPN thru traffic.	integer	Minimum value: 0 Maximum value: 4294967295	0
bgp-network	Underlying BGP network.	integer	Minimum value: 0 Maximum value: 4294967295	0
route-policy	Underlying router policy.	integer	Minimum value: 0 Maximum value: 4294967295	0
bgp-neighbor-group	Underlying BGP neighbor group entry.	string	Maximum length: 45	
bgp-neighbor-range	Underlying BGP neighbor range entry.	integer	Minimum value: 0 Maximum value: 4294967295	0
ipsec-phase1	IPsec interface.	string	Maximum length: 35	
sdwan-member	Reference to SD-WAN member entry.	integer	Minimum value: 0 Maximum value: 4294967295	0

config advertised-subnets

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967294	0
prefix	Network prefix.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0

Parameter	Description	Type	Size	Default
access	Access policy direction.	option	-	inbound
	Option	Description		
	<i>inbound</i>	Allow inbound traffic to subnet.		
	<i>bidirectional</i>	Allow inbound and outbound traffic to subnet.		
bgp-network	Underlying BGP network.	integer	Minimum value: 0 Maximum value: 4294967295	0
firewall-address	Underlying firewall address.	string	Maximum length: 79	
policies	Underlying policies.	integer	Minimum value: 0 Maximum value: 4294967295	

config system federated-upgrade

Coordinate federated upgrades within the Security Fabric.

```

config system federated-upgrade
    Description: Coordinate federated upgrades within the Security Fabric.
    set status [disabled|initialized|...]
    set source [user|auto-firmware-upgrade]
    set failure-reason [none|internal|...]
    set failure-device {string}
    set upgrade-id {integer}
    set next-path-index {integer}
    set ha-reboot-controller {string}
    config node-list
        Description: Nodes which will be included in the upgrade.
        edit <serial>
            set timing [immediate|scheduled]
            set maximum-minutes {integer}
            set time {user}
            set setup-time {user}
            set upgrade-path {user}
            set device-type [fortiproxy|fortiswitch|...]
            set coordinating-fortiproxy {string}
        next
    end
end
end

```

config system federated-upgrade

Parameter	Description	Type	Size	Default
status	Current status of the upgrade.	option	-	disabled
	Option	Description		
	<i>disabled</i>	No federated upgrade has been configured.		
	<i>initialized</i>	The upgrade has been configured.		
	<i>downloading</i>	The image is downloading in preparation for the upgrade.		
	<i>device-disconnected</i>	The image downloads are complete, but one or more devices have disconnected.		
	<i>ready</i>	The image download finished and the upgrade is pending.		
	<i>coordinating</i>	The upgrade is coordinating with other running upgrades.		
	<i>staging</i>	The upgrade is confirmed and images are being staged.		
	<i>final-check</i>	The upgrade is ready and final checks are in progress.		
	<i>upgrade-devices</i>	The upgrade is ready and devices are being rebooted.		
	<i>cancelled</i>	The upgrade was cancelled due to the tree not being ready.		
	<i>confirmed</i>	The upgrade was confirmed and reboots are running.		
	<i>done</i>	The upgrade completed successfully.		
	<i>failed</i>	The upgrade failed due to a local issue.		
	source	Source that set up the federated upgrade config.	option	-
	Option	Description		
	<i>user</i>	Upgrade configured based on user input.		
	<i>auto-firmware-upgrade</i>	Upgrade configured by the FortiGuard auto-firmware-upgrade feature.		
failure-reason	Reason for upgrade failure.	option	-	none
	Option	Description		
	<i>none</i>	No failure.		
	<i>internal</i>	An internal error occurred.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>timeout</i>	The upgrade timed out.		
	<i>device-type-unsupported</i>	The device type was not supported by the FortiGate.		
	<i>download-failed</i>	The image could not be downloaded.		
	<i>device-missing</i>	The device was disconnected from the FortiGate.		
	<i>version-unavailable</i>	An image matching the device and version could not be found.		
	<i>staging-failed</i>	The image could not be pushed to the device.		
	<i>reboot-failed</i>	The device could not be rebooted.		
	<i>device-not-reconnected</i>	The device did not reconnect after rebooting.		
	<i>node-not-ready</i>	A device in the Security Fabric tree was not ready.		
	<i>no-final-confirmation</i>	The coordinating FortiGate did not confirm the upgrade.		
	<i>no-confirmation-query</i>	A downstream FortiGate did not initiate final confirmation.		
	<i>config-error-log-nonempty</i>	Configuration errors encountered during the upgrade.		
	<i>node-failed</i>	A device in the Security Fabric tree failed.		
failure-device	Serial number of the node to include.	string	Maximum length: 79	
upgrade-id	Unique identifier for this upgrade.	integer	Minimum value: 0 Maximum value: 4294967295	0
next-path-index	The index of the next image to upgrade to.	integer	Minimum value: 0 Maximum value: 10	0
ha-reboot-controller	Serial number of the FortiGate unit that will control the reboot process for the federated upgrade of the HA cluster.	string	Maximum length: 79	

config node-list

Parameter	Description	Type	Size	Default
serial	Serial number of the node to include.	string	Maximum length: 79	
timing	Run immediately or at a scheduled time.	option	-	immediate
	Option	Description		
	<i>immediate</i>	Begin the upgrade immediately.		
	<i>scheduled</i>	Begin the upgrade at a configured time.		
maximum-minutes	Maximum number of minutes to allow for immediate upgrade preparation.	integer	Minimum value: 5 Maximum value: 10080	15
time	Scheduled upgrade execution time in UTC (hh:mm yyyy/mm/dd UTC).	user	Not Specified	
setup-time	Upgrade preparation start time in UTC (hh:mm yyyy/mm/dd UTC).	user	Not Specified	
upgrade-path	Fortinet OS image versions to upgrade through in major-minor-patch format, such as 7-0-4.	user	Not Specified	
device-type	Fortinet device type.	option	-	fortiproxy
	Option	Description		
	<i>fortiproxy</i>	This device is a FortiProxy.		
	<i>fortiswitch</i>	This device is a FortiSwitch.		
	<i>fortiap</i>	This device is a FortiAP.		
	<i>fortiextender</i>	This device is a FortiExtender.		
coordinating-fortiproxy	Serial number of the FortiProxy unit that controls this device.	string	Maximum length: 79	

config system fips-cc

Configure FIPS-CC mode.

```
config system fips-cc
  Description: Configure FIPS-CC mode.
  set status [enable|disable]
  set self-test-period {integer}
```

```
set key-generation-self-test [enable|disable]
end
```

config system fips-cc

Parameter	Description	Type	Size	Default
status	Enable/disable ciphers for FIPS mode of operation.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable FIPS-CC mode.		
	<i>disable</i>	Disable FIPS-CC mode.		
self-test-period	Self test period.	integer	Minimum value: 1 Maximum value: 1440	1440
key-generation-self-test	Enable/disable self tests after key generation.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable self tests after key generation.		
	<i>disable</i>	Disable self tests after key generation.		

config system fortianalyzer-connectivity

FortiAnalyzer Connectivity.

```
config system fortianalyzer-connectivity
  Description: FortiAnalyzer Connectivity.
end
```

config system fortiguard

Configure FortiGuard services.

```
config system fortiguard
  Description: Configure FortiGuard services.
  set fortiguard-anycast [enable|disable]
  set fortiguard-anycast-source [fortinet|aws|...]
```

```

set protocol [udp|http|...]
set port [8888|53|...]
set load-balance-servers {integer}
set auto-join-forticloud [enable|disable]
set update-server-location [automatic|usa|...]
set sandbox-region {string}
set sandbox-inline-scan [enable|disable]
set update-ffdb [enable|disable]
set update-uwdb [enable|disable]
set update-dldb [enable|disable]
set update-extdb [enable|disable]
set update-build-proxy [enable|disable]
set persistent-connection [enable|disable]
set vdom {string}
set auto-firmware-upgrade [enable|disable]
set auto-firmware-upgrade-day {option1}, {option2}, ...
set auto-firmware-upgrade-delay {integer}
set auto-firmware-upgrade-start-hour {integer}
set auto-firmware-upgrade-end-hour {integer}
set gui-prompt-auto-upgrade [enable|disable]
set antispam-force-off [enable|disable]
set antispam-cache [enable|disable]
set antispam-cache-ttl {integer}
set antispam-cache-mpersent {integer}
set antispam-license {integer}
set antispam-expiration {integer}
set antispam-timeout {integer}
set outbreak-prevention-force-off [enable|disable]
set outbreak-prevention-cache [enable|disable]
set outbreak-prevention-cache-ttl {integer}
set outbreak-prevention-cache-mpersent {integer}
set outbreak-prevention-license {integer}
set outbreak-prevention-expiration {integer}
set outbreak-prevention-timeout {integer}
set ia-license {integer}
set ia-expiration {integer}
set fnbi-license {integer}
set fnbi-expiration {integer}
set webfilter-force-off [enable|disable]
set webfilter-cache [enable|disable]
set webfilter-cache-ttl {integer}
set webfilter-license {integer}
set webfilter-expiration {integer}
set webfilter-timeout {integer}
set sdns-server-ip {user}
set sdns-server-port {integer}
set anycast-sdns-server-ip {ipv4-address}
set anycast-sdns-server-port {integer}
set sdns-options {option1}, {option2}, ...
set source-ip {ipv4-address}
set source-ip6 {ipv6-address}
set proxy-server-ip {string}

```

```

set proxy-server-port {integer}
set proxy-username {string}
set proxy-password {password}
set videofilter-license {integer}
set videofilter-expiration {integer}
set ddns-server-ip {ipv4-address}
set ddns-server-ip6 {ipv6-address}
set ddns-server-port {integer}
set interface-select-method [auto|specify]
set interface {string}
end

```

config system fortiguard

Parameter	Description	Type	Size	Default
fortiguard-anycast	Enable/disable use of FortiGuard's Anycast network.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable use of FortiGuard's Anycast network.		
	<i>disable</i>	Disable use of FortiGuard's Anycast network.		
fortiguard-anycast-source	Configure which of Fortinet's servers to provide FortiGuard services in FortiGuard's anycast network. Default is Fortinet.	option	-	fortinet
	Option	Description		
	<i>fortinet</i>	Use Fortinet's servers to provide FortiGuard services in FortiGuard's anycast network.		
	<i>aws</i>	Use Fortinet's AWS servers to provide FortiGuard services in FortiGuard's anycast network.		
	<i>debug</i>	Use Fortinet's internal test servers to provide FortiGuard services in FortiGuard's anycast network.		
protocol	Protocol used to communicate with the FortiGuard servers.	option	-	https
	Option	Description		
	<i>udp</i>	UDP for server communication (for use by FortiGuard or FortiManager).		
	<i>http</i>	HTTP for server communication (for use only by FortiManager).		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>https</i>	HTTPS for server communication (for use by FortiGuard or FortiManager).		
port	Port used to communicate with the FortiGuard servers.	option	-	443
	Option	Description		
	<i>8888</i>	port 8888 for server communication.		
	<i>53</i>	port 53 for server communication.		
	<i>80</i>	port 80 for server communication.		
	<i>443</i>	port 443 for server communication.		
load-balance-servers	Number of servers to alternate between as first FortiGuard option.	integer	Minimum value: 1 Maximum value: 266	1
auto-join-forticloud	Automatically connect to and login to FortiCloud.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable automatic connection and login to FortiCloud.		
	<i>disable</i>	Disable automatic connection and login to FortiCloud.		
update-server-location	Location from which to receive FortiGuard updates.	option	-	automatic
	Option	Description		
	<i>automatic</i>	FortiGuard servers chosen based on closest proximity to FortiProxy unit.		
	<i>usa</i>	FortiGuard servers in United States.		
	<i>eu</i>	FortiGuard servers in the European Union.		
sandbox-region	FortiCloud Sandbox region.	string	Maximum length: 63	
sandbox-inline-scan	Enable/disable FortiCloud Sandbox inline-scan.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable FortiCloud Sandbox inline scan.		
	<i>disable</i>	Disable FortiCloud Sandbox inline scan.		
update-ffdb	Enable/disable Internet Service Database update.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable Internet Service Database update.		
	<i>disable</i>	Disable Internet Service Database update.		
update-uwdb	Enable/disable allowlist update.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable allowlist update.		
	<i>disable</i>	Disable allowlist update.		
update-dldb	Enable/disable DLP signature update.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable DLP signature update.		
	<i>disable</i>	Disable DLP signature update.		
update-extdb	Enable/disable external resource update.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable external resource update.		
	<i>disable</i>	Disable external resource update.		
update-build-proxy	Enable/disable proxy dictionary rebuild.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable proxy dictionary rebuild.		
	<i>disable</i>	Disable proxy dictionary rebuild.		
persistent-connection	Enable/disable use of persistent connection to receive update notification from FortiGuard.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable persistent connection to receive update notification from FortiGuard.		
	<i>disable</i>	Disable persistent connection to receive update notification from FortiGuard.		
vdom	FortiGuard Service virtual domain name.	string	Maximum length: 31	
auto-firmware-upgrade	Enable/disable automatic patch-level firmware upgrade from FortiGuard. The FortiGate unit searches for new patches only in the same major and minor version.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable automatic patch-level firmware upgrade to latest version from FortiGuard.		
	<i>disable</i>	Disable automatic patch-level firmware upgrade to latest version from FortiGuard.		
auto-firmware-upgrade-day	Allowed day(s) of the week to install an automatic patch-level firmware upgrade from FortiGuard (default is none). Disallow any day of the week to use auto-firmware-upgrade-delay instead, which waits for designated days before installing an automatic patch-level firmware upgrade.	option	-	
	Option	Description		
	<i>sunday</i>	Sunday.		
	<i>monday</i>	Monday.		
	<i>tuesday</i>	Tuesday.		
	<i>wednesday</i>	Wednesday.		
	<i>thursday</i>	Thursday.		
	<i>friday</i>	Friday.		
	<i>saturday</i>	Saturday.		

Parameter	Description	Type	Size	Default						
auto-firmware-upgrade-delay	Delay of day(s) before installing an automatic patch-level firmware upgrade from FortiGuard (default = 3). Set it 0 to use auto-firmware-upgrade-day instead, which selects allowed day(s) of the week for installing an automatic patch-level firmware upgrade.	integer	Minimum value: 0 Maximum value: 14	3						
auto-firmware-upgrade-start-hour	Start time in the designated time window for automatic patch-level firmware upgrade from FortiGuard in 24 hour time (0 ~ 23, default = 2). The actual upgrade time is selected randomly within the time window.	integer	Minimum value: 0 Maximum value: 23	1						
auto-firmware-upgrade-end-hour	End time in the designated time window for automatic patch-level firmware upgrade from FortiGuard in 24 hour time (0 ~ 23, default = 4). When the end time is smaller than the start time, the end time is interpreted as the next day. The actual upgrade time is selected randomly within the time window.	integer	Minimum value: 0 Maximum value: 23	4						
gui-prompt-auto-upgrade	Enable/disable prompting of automatic patch-level firmware upgrade recommendation.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable prompting of automatic patch-level firmware upgrade recommendation.</td></tr><tr><td><i>disable</i></td><td>Disable prompting of automatic patch-level firmware upgrade recommendation.</td></tr></table>	Option	Description	<i>enable</i>	Enable prompting of automatic patch-level firmware upgrade recommendation.	<i>disable</i>	Disable prompting of automatic patch-level firmware upgrade recommendation.			
Option	Description									
<i>enable</i>	Enable prompting of automatic patch-level firmware upgrade recommendation.									
<i>disable</i>	Disable prompting of automatic patch-level firmware upgrade recommendation.									
antispam-force-off	Enable/disable turning off the FortiGuard antispam service.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Turn off the FortiGuard antispam service.</td></tr><tr><td><i>disable</i></td><td>Allow the FortiGuard antispam service.</td></tr></table>	Option	Description	<i>enable</i>	Turn off the FortiGuard antispam service.	<i>disable</i>	Allow the FortiGuard antispam service.			
Option	Description									
<i>enable</i>	Turn off the FortiGuard antispam service.									
<i>disable</i>	Allow the FortiGuard antispam service.									

Parameter	Description	Type	Size	Default						
antispam-cache	Enable/disable FortiGuard antispam request caching. Uses a small amount of memory but improves performance.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable FortiGuard antispam request caching.</td></tr><tr><td>disable</td><td>Disable FortiGuard antispam request caching.</td></tr></table>	Option	Description	enable	Enable FortiGuard antispam request caching.	disable	Disable FortiGuard antispam request caching.			
Option	Description									
enable	Enable FortiGuard antispam request caching.									
disable	Disable FortiGuard antispam request caching.									
antispam-cache-ttl	Time-to-live for antispam cache entries in seconds (300 - 86400). Lower times reduce the cache size. Higher times may improve performance since the cache will have more entries.	integer	Minimum value: 300 Maximum value: 86400	1800						
antispam-cache-mpercent	Maximum percent of FortiProxy memory the antispam cache is allowed to use (1 - 15%).	integer	Minimum value: 1 Maximum value: 15	2						
antispam-license	Interval of time between license checks for the FortiGuard antispam contract.	integer	Minimum value: 0 Maximum value: 4294967295	4294967295						
antispam-expiration	Expiration date of the FortiGuard antispam contract.	integer	Minimum value: 0 Maximum value: 4294967295	0						
antispam-timeout	Antispam query time out (1 - 30 sec, default = 7).	integer	Minimum value: 1 Maximum value: 30	7						
outbreak-prevention-force-off	Turn off FortiGuard Virus Outbreak Prevention service.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Turn off FortiGuard antivirus service.</td></tr><tr><td>disable</td><td>Allow the FortiGuard antivirus service.</td></tr></table>	Option	Description	enable	Turn off FortiGuard antivirus service.	disable	Allow the FortiGuard antivirus service.			
Option	Description									
enable	Turn off FortiGuard antivirus service.									
disable	Allow the FortiGuard antivirus service.									

Parameter	Description	Type	Size	Default
outbreak-prevention-cache	Enable/disable FortiGuard Virus Outbreak Prevention cache.	option	-	enable
	Option	Description		
	enable	Enable FortiGuard antivirus caching.		
	disable	Disable FortiGuard antivirus caching.		
outbreak-prevention-cache-ttl	Time-to-live for FortiGuard Virus Outbreak Prevention cache entries (300 - 86400 sec, default = 300).	integer	Minimum value: 300 Maximum value: 86400	300
outbreak-prevention-cache-mpercent	Maximum percent of memory FortiGuard Virus Outbreak Prevention cache can use (1 - 15%, default = 2).	integer	Minimum value: 1 Maximum value: 15	2
outbreak-prevention-license	Interval of time between license checks for FortiGuard Virus Outbreak Prevention contract.	integer	Minimum value: 0 Maximum value: 4294967295	4294967295
outbreak-prevention-expiration	Expiration date of FortiGuard Virus Outbreak Prevention contract.	integer	Minimum value: 0 Maximum value: 4294967295	0
outbreak-prevention-timeout	FortiGuard Virus Outbreak Prevention time out (1 - 30 sec, default = 7).	integer	Minimum value: 1 Maximum value: 30	7
ia-license	License type.	integer	Minimum value: 0 Maximum value: 4294967295	0
ia-expiration	License expiration.	integer	Minimum value: 0 Maximum value: 4294967295	0

Parameter	Description	Type	Size	Default						
fnbi-license	License type.	integer	Minimum value: 0 Maximum value: 4294967295	0						
fnbi-expiration	License expiration.	integer	Minimum value: 0 Maximum value: 4294967295	0						
webfilter-force-off	Enable/disable turning off the FortiGuard web filtering service.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Turn off the FortiGuard web filtering service.</td></tr><tr><td><i>disable</i></td><td>Allow the FortiGuard web filtering service to operate.</td></tr></table>				Option	Description	<i>enable</i>	Turn off the FortiGuard web filtering service.	<i>disable</i>	Allow the FortiGuard web filtering service to operate.
Option	Description									
<i>enable</i>	Turn off the FortiGuard web filtering service.									
<i>disable</i>	Allow the FortiGuard web filtering service to operate.									
webfilter-cache	Enable/disable FortiGuard web filter caching.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable FortiGuard web filter caching.</td></tr><tr><td><i>disable</i></td><td>Disable FortiGuard web filter caching.</td></tr></table>				Option	Description	<i>enable</i>	Enable FortiGuard web filter caching.	<i>disable</i>	Disable FortiGuard web filter caching.
Option	Description									
<i>enable</i>	Enable FortiGuard web filter caching.									
<i>disable</i>	Disable FortiGuard web filter caching.									
webfilter-cache-ttl	Time-to-live for web filter cache entries in seconds (300 - 86400).	integer	Minimum value: 300 Maximum value: 86400	3600						
webfilter-license	Interval of time between license checks for the FortiGuard web filter contract.	integer	Minimum value: 0 Maximum value: 4294967295	4294967295						
webfilter-expiration	Expiration date of the FortiGuard web filter contract.	integer	Minimum value: 0 Maximum value: 4294967295	0						
webfilter-timeout	Web filter query time out (1 - 30 sec, default = 7).	integer	Minimum value: 1 Maximum value: 30	15						

Parameter	Description	Type	Size	Default				
sdns-server-ip	IP address of the FortiGuard DNS rating server.	user	Not Specified					
sdns-server-port	Port to connect to on the FortiGuard DNS rating server.	integer	Minimum value: 1 Maximum value: 65535	53				
anycast-sdns-server-ip	IP address of the FortiGuard anycast DNS rating server.	ipv4-address	Not Specified	0.0.0.0				
anycast-sdns-server-port	Port to connect to on the FortiGuard anycast DNS rating server.	integer	Minimum value: 1 Maximum value: 65535	853				
sdns-options	Customization options for the FortiGuard DNS service.	option	-					
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>include-question-section</i></td><td>Include DNS question section in the FortiGuard DNS setup message.</td></tr></table>				Option	Description	<i>include-question-section</i>	Include DNS question section in the FortiGuard DNS setup message.
Option	Description							
<i>include-question-section</i>	Include DNS question section in the FortiGuard DNS setup message.							
source-ip	Source IPv4 address used to communicate with FortiGuard.	ipv4-address	Not Specified	0.0.0.0				
source-ip6	Source IPv6 address used to communicate with FortiGuard.	ipv6-address	Not Specified	::				
proxy-server-ip	Hostname or IP address of the proxy server.	string	Maximum length: 63					
proxy-server-port	Port used to communicate with the proxy server.	integer	Minimum value: 0 Maximum value: 65535	0				
proxy-username	Proxy user name.	string	Maximum length: 64					
proxy-password	Proxy user password.	password	Not Specified					
videofilter-license	Interval of time between license checks for the FortiGuard video filter contract.	integer	Minimum value: 0 Maximum value: 4294967295	4294967295				

Parameter	Description	Type	Size	Default						
videofilter-expiration	Expiration date of the FortiGuard video filter contract.	integer	Minimum value: 0 Maximum value: 4294967295	0						
ddns-server-ip	IP address of the FortiDDNS server.	ipv4-address	Not Specified	0.0.0.0						
ddns-server-ip6	IPv6 address of the FortiDDNS server.	ipv6-address	Not Specified	::						
ddns-server-port	Port used to communicate with FortiDDNS servers.	integer	Minimum value: 1 Maximum value: 65535	443						
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>auto</td><td>Set outgoing interface automatically.</td></tr><tr><td>specify</td><td>Set outgoing interface manually.</td></tr></table>				Option	Description	auto	Set outgoing interface automatically.	specify	Set outgoing interface manually.
Option	Description									
auto	Set outgoing interface automatically.									
specify	Set outgoing interface manually.									
interface	Specify outgoing interface to reach server.	string	Maximum length: 15							

config system fortiguard-log-service

Configuration of FortiCloud log service.

```
config system fortiguard-log-service
    Description: Configuration of FortiCloud log service.
end
```

config system fortiguard-service

Configuration of FortiGuard services.

```
config system fortiguard-service
    Description: Configuration of FortiGuard services.
end
```


config system fortindr

Configure FortiNDR.

```
config system fortindr
  Description: Configure FortiNDR.
  set status [disable|enable]
  set source-ip {string}
  set interface-select-method [auto|specify]
  set interface {string}
end
```

config system fortindr

Parameter	Description	Type	Size	Default
status	Enable/disable FortiNDR.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable FortiNDR.		
	<i>enable</i>	Enable FortiNDR.		
source-ip	Source IP address for communications to FortiNDR.	string	Maximum length: 63	
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto
	Option	Description		
	<i>auto</i>	Set outgoing interface automatically.		
	<i>specify</i>	Set outgoing interface manually.		
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	

config system fortisandbox

Configure FortiSandbox.

```
config system fortisandbox
  Description: Configure FortiSandbox.
  set status [enable|disable]
  set forticloud [enable|disable]
  set inline-scan [enable|disable]
```

```

set server {string}
set alt-server {string}
set health-check-interval {integer}
set source-ip {string}
set interface-select-method [auto|specify]
set interface {string}
set enc-algorithm [default|high|...]
set ssl-min-proto-version [default|SSLv3|...]
set email {string}
end

```

config system fortisandbox

Parameter	Description	Type	Size	Default						
status	Enable/disable FortiSandbox.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable FortiSandbox.</td></tr><tr><td><i>disable</i></td><td>Disable FortiSandbox.</td></tr></table>	Option	Description	<i>enable</i>	Enable FortiSandbox.	<i>disable</i>	Disable FortiSandbox.			
Option	Description									
<i>enable</i>	Enable FortiSandbox.									
<i>disable</i>	Disable FortiSandbox.									
forticloud	Enable/disable FortiSandbox Cloud.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable FortiSandbox Cloud.</td></tr><tr><td><i>disable</i></td><td>Disable FortiSandbox Cloud.</td></tr></table>	Option	Description	<i>enable</i>	Enable FortiSandbox Cloud.	<i>disable</i>	Disable FortiSandbox Cloud.			
Option	Description									
<i>enable</i>	Enable FortiSandbox Cloud.									
<i>disable</i>	Disable FortiSandbox Cloud.									
inline-scan	Enable/disable FortiSandbox inline scan.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable FortiSandbox inline scan.</td></tr><tr><td><i>disable</i></td><td>Disable FortiSandbox inline scan.</td></tr></table>	Option	Description	<i>enable</i>	Enable FortiSandbox inline scan.	<i>disable</i>	Disable FortiSandbox inline scan.			
Option	Description									
<i>enable</i>	Enable FortiSandbox inline scan.									
<i>disable</i>	Disable FortiSandbox inline scan.									
server	Server address of the remote FortiSandbox.	string	Maximum length: 63							
alt-server	Server address of the alternative remote FortiSandbox.	string	Maximum length: 63							
health-check-interval	FortiSandbox failover health check interval in seconds.	integer	Minimum value: 1 Maximum value: 120	5						
source-ip	Source IP address for communications to FortiSandbox.	string	Maximum length: 63							


```

    set auth-password {password}
end

```

config system fsso-polling

Parameter	Description	Type	Size	Default
status	Enable/disable FSSO Polling Mode.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable FSSO Polling Mode.		
	<i>disable</i>	Disable FSSO Polling Mode.		
listening-port	Listening port to accept clients (1 - 65535).	integer	Minimum value: 1 Maximum value: 65535	8000
authentication	Enable/disable FSSO Agent Authentication.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable FSSO Agent Authentication.		
	<i>disable</i>	Disable FSSO Agent Authentication.		
auth-password	Password to connect to FSSO Agent.	password	Not Specified	

config system ftm-push

Configure FortiToken Mobile push services.

```

config system ftm-push
    Description: Configure FortiToken Mobile push services.
    set server-port {integer}
    set server-cert {string}
    set server-ip {ipv4-address}
    set server {string}
    set status [enable|disable]
end

```

config system ftm-push

Parameter	Description	Type	Size	Default
server-port	Port to communicate with FortiToken Mobile push services server (1 - 65535, default = 4433).	integer	Minimum value: 1 Maximum value: 65535	4433
server-cert	Name of the server certificate to be used for SSL (default = Fortinet_Factory).	string	Maximum length: 35	Fortinet_Factory
server-ip	IPv4 address of FortiToken Mobile push services server (format: xxx.xxx.xxx.xxx).	ipv4-address	Not Specified	0.0.0.0
server	IPv4 address or domain name of FortiToken Mobile push services server.	string	Maximum length: 127	
status	Enable/disable the use of FortiToken Mobile push services.	option	-	disable
		Option	Description	
		<i>enable</i>	Enable FortiToken Mobile push services.	
		<i>disable</i>	Disable FortiToken Mobile push services.	

config system geoip-country

Define geoip country name-ID table.

```
config system geoip-country
  Description: Define geoip country name-ID table.
  edit <id>
    set name {string}
  next
end
```

config system geoip-country

Parameter	Description	Type	Size	Default
id	Country ID.	string	Maximum length: 2	
name	Country name.	string	Maximum length: 63	

config system geoip-override

Configure geographical location mapping for IP address(es) to override mappings from FortiGuard.

```
config system geoip-override
  Description: Configure geographical location mapping for IP address(es) to override mappings
  from FortiGuard.
  edit <name>
    set description {string}
    set country-id {string}
    config ip-range
      Description: Table of IP ranges assigned to country.
      edit <id>
        set start-ip {ipv4-address}
        set end-ip {ipv4-address}
      next
    end
    config ip6-range
      Description: Table of IPv6 ranges assigned to country.
      edit <id>
        set start-ip {ipv6-address}
        set end-ip {ipv6-address}
      next
    end
  next
end
```

config system geoip-override

Parameter	Description	Type	Size	Default
name	Location name.	string	Maximum length: 63	
description	Description.	string	Maximum length: 127	
country-id	Two character Country ID code.	string	Maximum length: 2	

config ip-range

Parameter	Description	Type	Size	Default
id	ID of individual entry in the IP range table.	integer	Minimum value: 0 Maximum value: 65535	0
start-ip	Starting IP address, inclusive, of the address range (format: xxx.xxx.xxx.xxx).	ipv4-address	Not Specified	0.0.0.0
end-ip	Ending IP address, inclusive, of the address range (format: xxx.xxx.xxx.xxx).	ipv4-address	Not Specified	0.0.0.0

config ip6-range

Parameter	Description	Type	Size	Default
id	ID of individual entry in the IPv6 range table.	integer	Minimum value: 0 Maximum value: 65535	0
start-ip	Starting IP address, inclusive, of the address range (format: xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx).	ipv6-address	Not Specified	::
end-ip	Ending IP address, inclusive, of the address range (format: xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx).	ipv6-address	Not Specified	::

config system global

Configure global attributes.

```
config system global
  Description: Configure global attributes.
  set language [english|french|...]
  set gui-ipv6 [enable|disable]
  set gui-replacement-message-groups [enable|disable]
  set gui-local-out [enable|disable]
  set gui-certificates [enable|disable]
  set gui-custom-language [enable|disable]
  set gui-app-detection-sdwan [enable|disable]
  set gui-display-hostname [enable|disable]
  set gui-fortigate-cloud-sandbox [enable|disable]
  set gui-firmware-upgrade-warning [enable|disable]
```

```

set gui-forticare-registration-setup-warning [enable|disable]
set gui-auto-upgrade-setup-warning [enable|disable]
set gui-workflow-management [enable|disable]
set gui-cdn-usage [enable|disable]
set admin-https-ssl-versions {option1}, {option2}, ...
set admin-https-ssl-ciphersuites {option1}, {option2}, ...
set admin-https-ssl-banned-ciphers {option1}, {option2}, ...
set admin-timeout {integer}
set admin-console-timeout {integer}
set ssd-trim-freq [never|hourly|...]
set ssd-trim-hour {integer}
set ssd-trim-min {integer}
set ssd-trim-weekday [sunday|monday|...]
set ssd-trim-date {integer}
set admin-concurrent [enable|disable]
set admin-lockout-threshold {integer}
set admin-lockout-duration {integer}
set refresh {integer}
set interval {integer}
set failtime {integer}
set daily-restart [enable|disable]
set restart-time {user}
set wad-restart-mode [none|time|...]
set wad-restart-start-time {user}
set wad-restart-end-time {user}
set radius-port {integer}
set admin-login-max {integer}
set remoteauthtimeout {integer}
set ldapconntimeout {integer}
set batch-cmdb [enable|disable]
set multi-factor-authentication [optional|mandatory]
set ssl-min-proto-version [SSLv3|TLSv1|...]
set autorun-log-fsck [enable|disable]
set timezone [01|02|...]
set traffic-priority [tos|dscp]
set traffic-priority-level [low|medium|...]
set quic-congestion-control-algo [cubic|bbr|...]
set quic-max-datagram-size {integer}
set quic-udp-payload-size-shaping-per-cid [enable|disable]
set quic-ack-thresold {integer}
set quic-pmtud [enable|disable]
set quic-tls-handshake-timeout {integer}
set anti-replay [disable|loose|...]
set pmtu-discovery [enable|disable]
set revision-image-auto-backup [enable|disable]
set revision-backup-on-logout [enable|disable]
set hostname {string}
set alias {string}
set strong-crypto [enable|disable]
set ssl-static-key-ciphers [enable|disable]
set ssh-kex-algo {option1}, {option2}, ...
set ssh-enc-algo {option1}, {option2}, ...

```



```
set ssh-mac-algo {option1}, {option2}, ...
set snat-route-change [enable|disable]
set speedtest-server [enable|disable]
set cli-audit-log [enable|disable]
set dh-params [1024|1536|...]
set fds-statistics [enable|disable]
set fds-statistics-period {integer}
set tcp-option [enable|disable]
set lldp-transmission [enable|disable]
set lldp-reception [enable|disable]
set proxy-auth-timeout {integer}
set resigned-pkey-period {integer}
set proxy-keep-alive-mode [session|traffic|...]
set proxy-re-authentication-time {integer}
set proxy-auth-lifetime [enable|disable]
set proxy-auth-lifetime-timeout {integer}
set proxy-auth-machine-timeout {integer}
set proxy-resource-mode [enable|disable]
set proxy-cert-use-mgmt-vdom [enable|disable]
set update-tls-finger-print [enable|disable]
set sys-perf-log-interval {integer}
set check-protocol-header [loose|strict]
set vip-arp-range [unlimited|restricted]
set tcp-halfclose-timer {integer}
set tcp-halfopen-timer {integer}
set tcp-timewait-timer {integer}
set tcp-rst-timer {integer}
set udp-idle-timer {integer}
set block-session-timer {integer}
set ip-src-port-range {user}
set pre-login-banner [enable|disable]
set post-login-banner [disable|enable]
set tftp [enable|disable]
set av-failopen [pass|off|...]
set av-failopen-session [enable|disable]
set kernel-panic-timeout {integer}
set kernel-panic-debug [enable|disable]
set kernel-panic-on-warn [enable|disable]
set memory-use-threshold-extreme {integer}
set memory-use-threshold-red {integer}
set memory-use-threshold-green {integer}
set ip-fragment-mem-thresholds {integer}
set cpu-use-threshold {integer}
set log-single-cpu-high [enable|disable]
set check-reset-range [strict|disable]
set admin-port {integer}
set admin-sport {integer}
set admin-host {string}
set admin-https-redirect [enable|disable]
set admin-hsts-max-age {integer}
set admin-ssh-password [enable|disable]
set admin-restrict-local [enable|disable]
```

```

set admin-ssh-port {integer}
set admin-ssh-grace-time {integer}
set admin-ssh-v1 [enable|disable]
set admin-telnet [enable|disable]
set admin-telnet-port {integer}
set admin-forticloud-sso-login [enable|disable]
set admin-forticloud-sso-default-profile {string}
set default-service-source-port {user}
set admin-server-cert {string}
set admin-https-pki-required [enable|disable]
set auth-http-port {integer}
set auth-https-port {integer}
set auth-ike-saml-port {integer}
set auth-keepalive [enable|disable]
set policy-auth-concurrent {integer}
set auth-session-limit [block-new|logout-inactive]
set auth-cert {string}
set clt-cert-req [enable|disable]
set fortiservice-port {integer}
set cfg-save [automatic|manual|...]
set cfg-revert-timeout {integer}
set reboot-upon-config-restore [enable|disable]
set admin-scp [enable|disable]
set security-rating-result-submission [enable|disable]
set security-rating-run-on-schedule [enable|disable]
set fortiextender-data-port {integer}
set fortiextender [disable|enable]
set extender-controller-reserved-network {ipv4-classnet-host}
set fortiextender-discovery-lockdown [disable|enable]
set fortiextender-provision-on-authorization [enable|disable]
set dnsproxy-worker-count {integer}
set url-filter-count {integer}
set proxy-worker-count {integer}
set scanunit-count {integer}
set fgd-alert-subscription {option1}, {option2}, ...
set ipv6-accept-dad {integer}
set ipv6-allow-multicast-probe [enable|disable]
set ipv6-allow-local-in-silent-drop [enable|disable]
set csr-ca-attribute [enable|disable]
set wimax-4g-usb [enable|disable]
set cert-chain-max {integer}
set two-factor-ftk-expiry {integer}
set two-factor-email-expiry {integer}
set two-factor-sms-expiry {integer}
set two-factor-fac-expiry {integer}
set two-factor-ftm-expiry {integer}
set max-img-cache-size {integer}
set img-cache-mode [stop|rolling]
set per-user-bal [enable|disable]
set wad-worker-count {integer}
set wad-csvc-cs-count {integer}
set wad-csvc-db-count {integer}

```

```

set http-view [enable|disable]
set wad-source-affinity [disable|enable]
set wad-memory-change-granularity {integer}
set login-timestamp [enable|disable]
set miglogd-children {integer}
set special-file-23-support [disable|enable]
set log-uuid-address [enable|disable]
set log-ssl-connection [enable|disable]
set gui-rest-api-cache [enable|disable]
set gui-fortiguard-resource-fetch [enable|disable]
set arp-max-entry {integer}
set ha-affinity {string}
set cmdbsvr-affinity {string}
set av-affinity {string}
set wad-affinity {string}
set ips-affinity {string}
set miglog-affinity {string}
set syslog-affinity {string}
set url-filter-affinity {string}
set ndp-max-entry {integer}
set br-fdb-max-entry {integer}
set max-route-cache-size {integer}
set ipsec-round-robin [enable|disable]
set ipsec-soft-dec-async [enable|disable]
set device-idle-timeout {integer}
set user-device-store-max-devices {integer}
set user-device-store-max-users {integer}
set user-device-store-max-unified-mem {integer}
set gui-device-latitude {string}
set gui-device-longitude {string}
set v-tpm [disable|enable]
set private-data-encryption [disable|enable]
set auto-auth-extension-device [enable|disable]
set gui-theme [jade|neutrino|...]
set gui-date-format [yyyy/MM/dd|dd/MM/yyyy|...]
set gui-date-time-source [system|browser]
set igmp-state-limit {integer}
set cloud-communication [enable|disable]
set ipsec-ha-seqjump-rate {integer}
set fortitoken-cloud [enable|disable]
set faz-disk-buffer-size {integer}
set irq-time-accounting [auto|force]
set management-ip {string}
set management-port {integer}
set management-port-use-admin-sport [enable|disable]
set internet-service-database [mini|standard|...]
set early-tcp-npu-session [enable|disable]
set interface-subnet-usage [disable|enable]
set sflowd-max-children-num {integer}
set license-overlimit [bypass|block]
set max-session-per-user {integer}
set conntrack {integer}

```

```

set established-timeout {integer}
set time-wait-timeout {integer}
set fin-wait-timeout {integer}
set close-wait-timeout {integer}
set syn-sent-timeout {integer}
set syn-recv-timeout {integer}
set last-ack-timeout {integer}
set udp-timeout {integer}
set udp-stream-timeout {integer}
set username-case-sensitivity [enable|disable]
set tcp-random-source-port [enable|disable]
end

```

config system global

Parameter	Description	Type	Size	Default
language	GUI display language.	option	-	english
	Option	Description		
	<i>english</i>	English.		
	<i>french</i>	French.		
	<i>spanish</i>	Spanish.		
	<i>portuguese</i>	Portuguese.		
	<i>japanese</i>	Japanese.		
	<i>trach</i>	Traditional Chinese.		
	<i>simch</i>	Simplified Chinese.		
	<i>korean</i>	Korean.		
gui-ipv6	Enable/disable IPv6 settings on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Display the feature in GUI.		
	<i>disable</i>	Do not display the feature in GUI.		
gui-replacement-message-groups	Enable/disable replacement message groups on the GUI.	option	-	disable

Parameter	Description	Type	Size	Default
	Option Description			
	<i>enable</i>	Display the feature in GUI.		
	<i>disable</i>	Do not display the feature in GUI.		
gui-local-out	Enable/disable Local-out traffic on the GUI.	option	-	disable
	Option Description			
	<i>enable</i>	Display the feature in GUI.		
	<i>disable</i>	Do not display the feature in GUI.		
gui-certificates	Enable/disable the System > Certificate GUI page, allowing you to add and configure certificates from the GUI.	option	-	enable
	Option Description			
	<i>enable</i>	Display the feature in GUI.		
	<i>disable</i>	Do not display the feature in GUI.		
gui-custom-language	Enable/disable custom languages in GUI.	option	-	disable
	Option Description			
	<i>enable</i>	Display the feature in GUI.		
	<i>disable</i>	Do not display the feature in GUI.		
gui-app-detection-sdwan	Enable/disable Allow app-detection based SD-WAN.	option	-	disable
	Option Description			
	<i>enable</i>	Display the feature in GUI.		
	<i>disable</i>	Do not display the feature in GUI.		

Parameter	Description	Type	Size	Default
gui-display-hostname	Enable/disable displaying the FortiProxy's hostname on the GUI login page.	option	-	disable
	Option	Description		
	<i>enable</i>	Display the feature in GUI.		
	<i>disable</i>	Do not display the feature in GUI.		
gui-fortigate-cloud-sandbox	Enable/disable displaying FortiProxy Cloud Sandbox on the GUI.	option	-	disable
	Option	Description		
	<i>enable</i>	Display the feature in GUI.		
	<i>disable</i>	Do not display the feature in GUI.		
gui-firmware-upgrade-warning	Enable/disable the firmware upgrade warning on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Display the feature in GUI.		
	<i>disable</i>	Do not display the feature in GUI.		
gui-forticare-registration-setup-warning	Enable/disable the FortiCare registration setup warning on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Display the feature in GUI.		
	<i>disable</i>	Do not display the feature in GUI.		
gui-auto-upgrade-setup-warning	Enable/disable the automatic patch upgrade setup prompt on the GUI.	option	-	enable

Parameter	Description	Type	Size	Default
	Option Description			
	<i>enable</i>	Display the feature in GUI.		
	<i>disable</i>	Do not display the feature in GUI.		
gui-workflow-management	Enable/disable Workflow management features on the GUI.	option	-	disable
	Option Description			
	<i>enable</i>	Display the feature in GUI.		
	<i>disable</i>	Do not display the feature in GUI.		
gui-cdn-usage	Enable/disable Load GUI static files from a CDN.	option	-	enable
	Option Description			
	<i>enable</i>	Display the feature in GUI.		
	<i>disable</i>	Do not display the feature in GUI.		
admin-https-ssl-versions	Allowed TLS versions for web administration.	option	-	tlsv1-2 tlsv1-3
	Option Description			
	<i>tlsv1-1</i>	TLS 1.1.		
	<i>tlsv1-2</i>	TLS 1.2.		
	<i>tlsv1-3</i>	TLS 1.3.		
admin-https-ssl-ciphersuites	Select one or more TLS 1.3 ciphersuites to enable. Does not affect ciphers in TLS 1.2 and below. At least one must be enabled. To disable all, remove TLS1.3 from admin-https-ssl-versions.	option	-	TLS-AES-128-GCM-SHA256 TLS-AES-256-GCM-SHA384 TLS-CHACHA20-POLY1305-SHA256

Parameter	Description	Type	Size	Default																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>TLS-AES-128-GCM-SHA256</i></td><td>Enable TLS-AES-128-GCM-SHA256 in TLS 1.3.</td></tr><tr><td><i>TLS-AES-256-GCM-SHA384</i></td><td>Enable TLS-AES-256-GCM-SHA384 in TLS 1.3.</td></tr><tr><td><i>TLS-CHACHA20-POLY1305-SHA256</i></td><td>Enable TLS-CHACHA20-POLY1305-SHA256 in TLS 1.3.</td></tr><tr><td><i>TLS-AES-128-CCM-SHA256</i></td><td>Enable TLS-AES-128-CCM-SHA256 in TLS 1.3.</td></tr><tr><td><i>TLS-AES-128-CCM-8-SHA256</i></td><td>Enable TLS-AES-128-CCM-8-SHA256 in TLS 1.3.</td></tr></table>	Option	Description	<i>TLS-AES-128-GCM-SHA256</i>	Enable TLS-AES-128-GCM-SHA256 in TLS 1.3.	<i>TLS-AES-256-GCM-SHA384</i>	Enable TLS-AES-256-GCM-SHA384 in TLS 1.3.	<i>TLS-CHACHA20-POLY1305-SHA256</i>	Enable TLS-CHACHA20-POLY1305-SHA256 in TLS 1.3.	<i>TLS-AES-128-CCM-SHA256</i>	Enable TLS-AES-128-CCM-SHA256 in TLS 1.3.	<i>TLS-AES-128-CCM-8-SHA256</i>	Enable TLS-AES-128-CCM-8-SHA256 in TLS 1.3.											
	Option	Description																						
	<i>TLS-AES-128-GCM-SHA256</i>	Enable TLS-AES-128-GCM-SHA256 in TLS 1.3.																						
	<i>TLS-AES-256-GCM-SHA384</i>	Enable TLS-AES-256-GCM-SHA384 in TLS 1.3.																						
	<i>TLS-CHACHA20-POLY1305-SHA256</i>	Enable TLS-CHACHA20-POLY1305-SHA256 in TLS 1.3.																						
	<i>TLS-AES-128-CCM-SHA256</i>	Enable TLS-AES-128-CCM-SHA256 in TLS 1.3.																						
<i>TLS-AES-128-CCM-8-SHA256</i>	Enable TLS-AES-128-CCM-8-SHA256 in TLS 1.3.																							
admin-https-ssl-banned-ciphers	Select one or more cipher technologies that cannot be used in GUI HTTPS negotiations. Only applies to TLS 1.2 and below.	option	-																					
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>RSA</i></td><td>Ban the use of cipher suites using RSA key.</td></tr><tr><td><i>DHE</i></td><td>Ban the use of cipher suites using authenticated ephemeral DH key agreement.</td></tr><tr><td><i>ECDHE</i></td><td>Ban the use of cipher suites using authenticated ephemeral ECDH key agreement.</td></tr><tr><td><i>DSS</i></td><td>Ban the use of cipher suites using DSS authentication.</td></tr><tr><td><i>ECDSA</i></td><td>Ban the use of cipher suites using ECDSA authentication.</td></tr><tr><td><i>AES</i></td><td>Ban the use of cipher suites using either 128 or 256 bit AES.</td></tr><tr><td><i>AESGCM</i></td><td>Ban the use of cipher suites using AES in Galois Counter Mode (GCM).</td></tr><tr><td><i>CAMELLIA</i></td><td>Ban the use of cipher suites using either 128 or 256 bit CAMELLIA.</td></tr><tr><td><i>3DES</i></td><td>Ban the use of cipher suites using triple DES.</td></tr></table>	Option	Description	<i>RSA</i>	Ban the use of cipher suites using RSA key.	<i>DHE</i>	Ban the use of cipher suites using authenticated ephemeral DH key agreement.	<i>ECDHE</i>	Ban the use of cipher suites using authenticated ephemeral ECDH key agreement.	<i>DSS</i>	Ban the use of cipher suites using DSS authentication.	<i>ECDSA</i>	Ban the use of cipher suites using ECDSA authentication.	<i>AES</i>	Ban the use of cipher suites using either 128 or 256 bit AES.	<i>AESGCM</i>	Ban the use of cipher suites using AES in Galois Counter Mode (GCM).	<i>CAMELLIA</i>	Ban the use of cipher suites using either 128 or 256 bit CAMELLIA.	<i>3DES</i>	Ban the use of cipher suites using triple DES.			
	Option	Description																						
	<i>RSA</i>	Ban the use of cipher suites using RSA key.																						
	<i>DHE</i>	Ban the use of cipher suites using authenticated ephemeral DH key agreement.																						
	<i>ECDHE</i>	Ban the use of cipher suites using authenticated ephemeral ECDH key agreement.																						
	<i>DSS</i>	Ban the use of cipher suites using DSS authentication.																						
	<i>ECDSA</i>	Ban the use of cipher suites using ECDSA authentication.																						
	<i>AES</i>	Ban the use of cipher suites using either 128 or 256 bit AES.																						
	<i>AESGCM</i>	Ban the use of cipher suites using AES in Galois Counter Mode (GCM).																						
<i>CAMELLIA</i>	Ban the use of cipher suites using either 128 or 256 bit CAMELLIA.																							
<i>3DES</i>	Ban the use of cipher suites using triple DES.																							

Parameter	Description	Type	Size	Default																	
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>SHA1</td><td>Ban the use of cipher suites using HMAC-SHA1.</td></tr><tr><td>SHA256</td><td>Ban the use of cipher suites using HMAC-SHA256.</td></tr><tr><td>SHA384</td><td>Ban the use of cipher suites using HMAC-SHA384.</td></tr><tr><td>STATIC</td><td>Ban the use of cipher suites using static keys.</td></tr><tr><td>CHACHA20</td><td>Ban the use of cipher suites using ChaCha20.</td></tr><tr><td>ARIA</td><td>Ban the use of cipher suites using ARIA.</td></tr><tr><td>AESCCM</td><td>Ban the use of cipher suites using AESCCM.</td></tr></table>		Option	Description	SHA1	Ban the use of cipher suites using HMAC-SHA1.	SHA256	Ban the use of cipher suites using HMAC-SHA256.	SHA384	Ban the use of cipher suites using HMAC-SHA384.	STATIC	Ban the use of cipher suites using static keys.	CHACHA20	Ban the use of cipher suites using ChaCha20.	ARIA	Ban the use of cipher suites using ARIA.	AESCCM	Ban the use of cipher suites using AESCCM.			
	Option	Description																			
	SHA1	Ban the use of cipher suites using HMAC-SHA1.																			
	SHA256	Ban the use of cipher suites using HMAC-SHA256.																			
	SHA384	Ban the use of cipher suites using HMAC-SHA384.																			
	STATIC	Ban the use of cipher suites using static keys.																			
	CHACHA20	Ban the use of cipher suites using ChaCha20.																			
ARIA	Ban the use of cipher suites using ARIA.																				
AESCCM	Ban the use of cipher suites using AESCCM.																				
admin-timeout	Number of minutes before an idle administrator session times out (1 - 480 minutes (8 hours), default = 5). A shorter idle timeout is more secure.	integer	Minimum value: 1 Maximum value: 480	5																	
admin-console-timeout	Console login timeout that overrides the admin timeout value (15 - 300 seconds, default = 0, which disables the timeout).	integer	Minimum value: 15 Maximum value: 300	0																	
ssd-trim-freq	How often to run SSD Trim (default = weekly). SSD Trim prevents SSD drive data loss by finding and isolating errors.	option	-	weekly																	
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>never</td><td>Never Run SSD Trim.</td></tr><tr><td>hourly</td><td>Run SSD Trim Hourly.</td></tr><tr><td>daily</td><td>Run SSD Trim Daily.</td></tr><tr><td>weekly</td><td>Run SSD Trim Weekly.</td></tr><tr><td>monthly</td><td>Run SSD Trim Monthly.</td></tr></table>		Option	Description	never	Never Run SSD Trim.	hourly	Run SSD Trim Hourly.	daily	Run SSD Trim Daily.	weekly	Run SSD Trim Weekly.	monthly	Run SSD Trim Monthly.							
	Option	Description																			
	never	Never Run SSD Trim.																			
	hourly	Run SSD Trim Hourly.																			
	daily	Run SSD Trim Daily.																			
weekly	Run SSD Trim Weekly.																				
monthly	Run SSD Trim Monthly.																				

Parameter	Description	Type	Size	Default
ssd-trim-hour	Hour of the day on which to run SSD Trim (0 - 23, default = 1).	integer	Minimum value: 0 Maximum value: 23	1
ssd-trim-min	Minute of the hour on which to run SSD Trim (0 - 59, 60 for random).	integer	Minimum value: 0 Maximum value: 60	60
ssd-trim-weekday	Day of week to run SSD Trim.	option	-	sunday
	Option	Description		
	<i>sunday</i>	Sunday		
	<i>monday</i>	Monday		
	<i>tuesday</i>	Tuesday		
	<i>wednesday</i>	Wednesday		
	<i>thursday</i>	Thursday		
	<i>friday</i>	Friday		
	<i>saturday</i>	Saturday		
ssd-trim-date	Date within a month to run ssd trim.	integer	Minimum value: 1 Maximum value: 31	1
admin-concurrent	Enable/disable concurrent administrator logins. Use policy-auth-concurrent for firewall authenticated users.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable admin concurrent login.		
	<i>disable</i>	Disable admin concurrent login.		

Parameter	Description	Type	Size	Default
admin-lockout-threshold	Number of failed login attempts before an administrator account is locked out for the admin-lockout-duration.	integer	Minimum value: 1 Maximum value: 10	3
admin-lockout-duration	Amount of time in seconds that an administrator account is locked out after reaching the admin-lockout-threshold for repeated failed login attempts.	integer	Minimum value: 1 Maximum value: 2147483647	60
refresh	Statistics refresh interval second(s) in GUI.	integer	Minimum value: 0 Maximum value: 4294967295	0
interval	Dead gateway detection interval.	integer	Minimum value: 0 Maximum value: 4294967295	5
failtime	Fail-time for server lost.	integer	Minimum value: 0 Maximum value: 4294967295	5
daily-restart	Enable/disable daily restart of FortiProxy unit. Use the restart-time option to set the time of day for the restart.	option	-	disable
		Option	Description	
		<i>enable</i>	Enable daily reboot of the FortiProxy.	
		<i>disable</i>	Disable daily reboot of the FortiProxy.	

Parameter	Description	Type	Size	Default
restart-time	Daily restart time (hh:mm).	user	Not Specified	
wad-restart-mode	WAD worker restart mode (default = none).	option	-	none
	Option	Description		
	<i>none</i>	Disable restart of WAD workers.		
	<i>time</i>	Enable daily restart of WAD workers.		
	<i>memory</i>	Enable restart of WAD workers based on memory usage.		
wad-restart-start-time	WAD workers daily restart time (hh:mm).	user	Not Specified	
wad-restart-end-time	WAD workers daily restart end time (hh:mm).	user	Not Specified	
radius-port	RADIUS service port number.	integer	Minimum value: 1 Maximum value: 65535	1812
admin-login-max	Maximum number of administrators who can be logged in at the same time (1 - 100, default = 100).	integer	Minimum value: 1 Maximum value: 100	100
remoteauthtimeout	Number of seconds that the FortiProxy waits for responses from remote RADIUS, LDAP, or TACACS+ authentication servers. (1-300 sec, default = 5).	integer	Minimum value: 1 Maximum value: 300	5
ldapconntimeout	Global timeout for connections with remote LDAP servers in milliseconds (1 - 300000, default 500).	integer	Minimum value: 1 Maximum value: 300000	500

Parameter	Description	Type	Size	Default												
batch-cmdb	Enable/disable batch mode, allowing you to enter a series of CLI commands that will execute as a group once they are loaded.	option	-	enable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable batch mode to execute in CMDB server.</td></tr><tr><td><i>disable</i></td><td>Disable batch mode to execute in CMDB server.</td></tr></table>	Option	Description	<i>enable</i>	Enable batch mode to execute in CMDB server.	<i>disable</i>	Disable batch mode to execute in CMDB server.									
Option	Description															
<i>enable</i>	Enable batch mode to execute in CMDB server.															
<i>disable</i>	Disable batch mode to execute in CMDB server.															
multi-factor-authentication	Enforce all login methods to require an additional authentication factor (default = optional).	option	-	optional												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>optional</i></td><td>Do not enforce all login methods to require an additional authentication factor (controlled by user settings).</td></tr><tr><td><i>mandatory</i></td><td>Enforce all login methods to require an additional authentication factor.</td></tr></table>	Option	Description	<i>optional</i>	Do not enforce all login methods to require an additional authentication factor (controlled by user settings).	<i>mandatory</i>	Enforce all login methods to require an additional authentication factor.									
Option	Description															
<i>optional</i>	Do not enforce all login methods to require an additional authentication factor (controlled by user settings).															
<i>mandatory</i>	Enforce all login methods to require an additional authentication factor.															
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default = TLSv1.2).	option	-	TLSv1-2												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>SSLv3</i></td><td>SSLv3.</td></tr><tr><td><i>TLSv1</i></td><td>TLSv1.</td></tr><tr><td><i>TLSv1-1</i></td><td>TLSv1.1.</td></tr><tr><td><i>TLSv1-2</i></td><td>TLSv1.2.</td></tr><tr><td><i>TLSv1-3</i></td><td>TLSv1.3.</td></tr></table>	Option	Description	<i>SSLv3</i>	SSLv3.	<i>TLSv1</i>	TLSv1.	<i>TLSv1-1</i>	TLSv1.1.	<i>TLSv1-2</i>	TLSv1.2.	<i>TLSv1-3</i>	TLSv1.3.			
Option	Description															
<i>SSLv3</i>	SSLv3.															
<i>TLSv1</i>	TLSv1.															
<i>TLSv1-1</i>	TLSv1.1.															
<i>TLSv1-2</i>	TLSv1.2.															
<i>TLSv1-3</i>	TLSv1.3.															
autorun-log-fsck	Enable/disable automatic log partition check after ungraceful shutdown.	option	-	disable												

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable automatic log partition check after ungraceful shutdown.		
	<i>disable</i>	Disable automatic log partition check after ungraceful shutdown.		
timezone	Number corresponding to your time zone from 00 to 86. Enter set timezone ? to view the list of time zones and the numbers that represent them.	option	-	00
	Option	Description		
	01	(GMT-11:00) Midway Island, Samoa		
	02	(GMT-10:00) Hawaii		
	03	(GMT-9:00) Alaska		
	04	(GMT-8:00) Pacific Time (US & Canada)		
	05	(GMT-7:00) Arizona		
	81	(GMT-7:00) Baja California Sur, Chihuahua		
	06	(GMT-7:00) Mountain Time (US & Canada)		
	07	(GMT-6:00) Central America		
	08	(GMT-6:00) Central Time (US & Canada)		
	09	(GMT-6:00) Mexico City		
	10	(GMT-6:00) Saskatchewan		
	11	(GMT-5:00) Bogota, Lima,Quito		
	12	(GMT-5:00) Eastern Time (US & Canada)		
	13	(GMT-5:00) Indiana (East)		
	74	(GMT-4:00) Caracas		
	14	(GMT-4:00) Atlantic Time (Canada)		
	77	(GMT-4:00) Georgetown		
15	(GMT-4:00) La Paz			

Parameter	Description	Type	Size	Default
	Option	Description		
	87	(GMT-4:00) Paraguay		
	16	(GMT-3:00) Santiago		
	17	(GMT-3:30) Newfoundland		
	18	(GMT-3:00) Brasilia		
	19	(GMT-3:00) Buenos Aires		
	20	(GMT-3:00) Nuuk (Greenland)		
	75	(GMT-3:00) Uruguay		
	21	(GMT-2:00) Mid-Atlantic		
	22	(GMT-1:00) Azores		
	23	(GMT-1:00) Cape Verde Is.		
	24	(GMT) Monrovia		
	80	(GMT) Greenwich Mean Time		
	79	(GMT) Casablanca		
	25	(GMT) Dublin, Edinburgh, Lisbon, London, Canary Is.		
	26	(GMT+1:00) Amsterdam, Berlin, Bern, Rome, Stockholm, Vienna		
	27	(GMT+1:00) Belgrade, Bratislava, Budapest, Ljubljana, Prague		
	28	(GMT+1:00) Brussels, Copenhagen, Madrid, Paris		
	78	(GMT+1:00) Namibia		
	29	(GMT+1:00) Sarajevo, Skopje, Warsaw, Zagreb		
	30	(GMT+1:00) West Central Africa		
	31	(GMT+2:00) Kyiv, Athens, Sofia, Vilnius		
	32	(GMT+2:00) Bucharest		
	33	(GMT+2:00) Cairo		
	34	(GMT+2:00) Harare, Pretoria		
	35	(GMT+2:00) Helsinki, Riga, Tallinn		
	36	(GMT+2:00) Jerusalem		
	37	(GMT+3:00) Baghdad		

Parameter	Description	Type	Size	Default
	Option	Description		
	38	(GMT+3:00) Kuwait, Riyadh		
	83	(GMT+3:00) Moscow		
	84	(GMT+3:00) Minsk		
	40	(GMT+3:00) Nairobi		
	85	(GMT+3:00) Istanbul		
	39	(GMT+3:00) St. Petersburg, Volgograd		
	41	(GMT+3:30) Tehran		
	42	(GMT+4:00) Abu Dhabi, Muscat		
	43	(GMT+4:00) Baku		
	44	(GMT+4:30) Kabul		
	45	(GMT+5:00) Ekaterinburg		
	46	(GMT+5:00) Islamabad, Karachi, Tashkent		
	47	(GMT+5:30) Kolkata, Chennai, Mumbai, New Delhi		
	51	(GMT+5:30) Sri Jayawardenepara		
	48	(GMT+5:45) Kathmandu		
	49	(GMT+5:00) Almaty, Astana		
	50	(GMT+6:00) Dhaka		
	52	(GMT+6:30) Rangoon		
	53	(GMT+7:00) Bangkok, Hanoi, Jakarta, Novosibirsk		
	54	(GMT+7:00) Krasnoyarsk		
	55	(GMT+8:00) Beijing, ChongQing, HongKong, Urumgi, Irkutsk		
	56	(GMT+8:00) Ulaan Bataar		
	57	(GMT+8:00) Kuala Lumpur, Singapore		
	58	(GMT+8:00) Perth		
	59	(GMT+8:00) Taipei		
	60	(GMT+9:00) Osaka, Sapporo, Tokyo, Seoul		
	61	(GMT+9:00) Yakutsk		
	62	(GMT+9:30) Adelaide		

Parameter	Description	Type	Size	Default																																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>63</td><td>(GMT+9:30) Darwin</td></tr><tr><td>64</td><td>(GMT+10:00) Brisbane</td></tr><tr><td>65</td><td>(GMT+10:00) Canberra, Melbourne, Sydney</td></tr><tr><td>66</td><td>(GMT+10:00) Guam, Port Moresby</td></tr><tr><td>67</td><td>(GMT+10:00) Hobart</td></tr><tr><td>68</td><td>(GMT+10:00) Vladivostok</td></tr><tr><td>69</td><td>(GMT+10:00) Magadan</td></tr><tr><td>70</td><td>(GMT+11:00) Solomon Is., New Caledonia</td></tr><tr><td>71</td><td>(GMT+12:00) Auckland, Wellington</td></tr><tr><td>72</td><td>(GMT+12:00) Fiji, Kamchatka, Marshall Is.</td></tr><tr><td>00</td><td>(GMT+12:00) Eniwetok, Kwajalein</td></tr><tr><td>82</td><td>(GMT+12:45) Chatham Islands</td></tr><tr><td>73</td><td>(GMT+13:00) Nuku'alofa</td></tr><tr><td>86</td><td>(GMT+13:00) Samoa</td></tr><tr><td>76</td><td>(GMT+14:00) Kiritimati</td></tr></table>	Option	Description	63	(GMT+9:30) Darwin	64	(GMT+10:00) Brisbane	65	(GMT+10:00) Canberra, Melbourne, Sydney	66	(GMT+10:00) Guam, Port Moresby	67	(GMT+10:00) Hobart	68	(GMT+10:00) Vladivostok	69	(GMT+10:00) Magadan	70	(GMT+11:00) Solomon Is., New Caledonia	71	(GMT+12:00) Auckland, Wellington	72	(GMT+12:00) Fiji, Kamchatka, Marshall Is.	00	(GMT+12:00) Eniwetok, Kwajalein	82	(GMT+12:45) Chatham Islands	73	(GMT+13:00) Nuku'alofa	86	(GMT+13:00) Samoa	76	(GMT+14:00) Kiritimati			
	Option	Description																																		
	63	(GMT+9:30) Darwin																																		
	64	(GMT+10:00) Brisbane																																		
	65	(GMT+10:00) Canberra, Melbourne, Sydney																																		
	66	(GMT+10:00) Guam, Port Moresby																																		
	67	(GMT+10:00) Hobart																																		
	68	(GMT+10:00) Vladivostok																																		
	69	(GMT+10:00) Magadan																																		
	70	(GMT+11:00) Solomon Is., New Caledonia																																		
	71	(GMT+12:00) Auckland, Wellington																																		
	72	(GMT+12:00) Fiji, Kamchatka, Marshall Is.																																		
	00	(GMT+12:00) Eniwetok, Kwajalein																																		
	82	(GMT+12:45) Chatham Islands																																		
	73	(GMT+13:00) Nuku'alofa																																		
	86	(GMT+13:00) Samoa																																		
	76	(GMT+14:00) Kiritimati																																		
traffic-priority	Choose Type of Service (ToS) or Differentiated Services Code Point (DSCP) for traffic prioritization in traffic shaping.	option	-	tos																																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>tos</td><td>IP TOS.</td></tr><tr><td>dscp</td><td>DSCP (DiffServ) DS.</td></tr></table>	Option	Description	tos	IP TOS.	dscp	DSCP (DiffServ) DS.																													
	Option	Description																																		
	tos	IP TOS.																																		
dscp	DSCP (DiffServ) DS.																																			
traffic-priority-level	Default system-wide level of priority for traffic prioritization.	option	-	medium																																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>low</td><td>Low priority.</td></tr></table>	Option	Description	low	Low priority.																															
	Option	Description																																		
low	Low priority.																																			

Parameter	Description	Type	Size	Default
	Option Description			
	<i>medium</i>	Medium priority.		
	<i>high</i>	High priority.		
quic-congestion-control-algo	QUIC congestion control algorithm (default = cubic).	option	-	cubic
	Option Description			
	<i>cubic</i>	Cubic.		
	<i>bbr</i>	BBR.		
	<i>bbr2</i>	BBR2.		
	<i>reno</i>	Reno.		
quic-max-datagram-size	Maximum transmit datagram size (1200 - 1500, default = 1500).	integer	Minimum value: 1200 Maximum value: 1500	1500
quic-udp-payload-size-shaping-per-cid	Enable/disable UDP payload size shaping per connection ID (default = enable).	option	-	enable
	Option Description			
	<i>enable</i>	Enable UDP payload size shaping per connection ID.		
	<i>disable</i>	Disable UDP payload size shaping per connection ID.		
quic-ack-threshold	Maximum number of unacknowledged packets before sending ACK (2 - 5, default = 3).	integer	Minimum value: 2 Maximum value: 5	3
quic-pmtud	Enable/disable path MTU discovery (default = enable).	option	-	enable
	Option Description			
	<i>enable</i>	Enable path MTU discovery.		
	<i>disable</i>	Disable path MTU discovery.		

Parameter	Description	Type	Size	Default								
quic-tls-handshake-timeout	Time-to-live (TTL) for TLS handshake in seconds (1 - 60, default = 5).	integer	Minimum value: 1 Maximum value: 60	5								
anti-replay	Level of checking for packet replay and TCP sequence checking.	option	-	strict								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable anti-replay check.</td></tr><tr><td><i>loose</i></td><td>Loose anti-replay check.</td></tr><tr><td><i>strict</i></td><td>Strict anti-replay check.</td></tr></table>	Option	Description	<i>disable</i>	Disable anti-replay check.	<i>loose</i>	Loose anti-replay check.	<i>strict</i>	Strict anti-replay check.			
Option	Description											
<i>disable</i>	Disable anti-replay check.											
<i>loose</i>	Loose anti-replay check.											
<i>strict</i>	Strict anti-replay check.											
pmtu-discovery	Enable/disable path MTU discovery.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable path MTU discovery.</td></tr><tr><td><i>disable</i></td><td>Disable path MTU discovery.</td></tr></table>	Option	Description	<i>enable</i>	Enable path MTU discovery.	<i>disable</i>	Disable path MTU discovery.					
Option	Description											
<i>enable</i>	Enable path MTU discovery.											
<i>disable</i>	Disable path MTU discovery.											
revision-image-auto-backup	Enable/disable back-up of the latest image revision after the firmware is upgraded.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable revision image backup automatically when upgrading image.</td></tr><tr><td><i>disable</i></td><td>Disable revision image backup automatically when upgrading image.</td></tr></table>	Option	Description	<i>enable</i>	Enable revision image backup automatically when upgrading image.	<i>disable</i>	Disable revision image backup automatically when upgrading image.					
Option	Description											
<i>enable</i>	Enable revision image backup automatically when upgrading image.											
<i>disable</i>	Disable revision image backup automatically when upgrading image.											
revision-backup-on-logout	Enable/disable back-up of the latest configuration revision when an administrator logs out of the CLI or GUI.	option	-	disable								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable revision config backup automatically when logout.		
	<i>disable</i>	Disable revision config backup automatically when logout.		
hostname	FortiProxy unit's hostname. Most models will truncate names longer than 24 characters. Some models support hostnames up to 35 characters.	string	Maximum length: 35	
alias	Alias for your FortiProxy unit.	string	Maximum length: 35	
strong-crypto	Enable to use strong encryption and only allow strong ciphers and digest for HTTPS/SSH/TLS/SSL functions.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable strong crypto for HTTPS/SSH/TLS/SSL.		
	<i>disable</i>	Disable strong crypto for HTTPS/SSH/TLS/SSL.		
ssl-static-key-ciphers	Enable/disable static key ciphers in SSL/TLS connections (e.g. AES128-SHA, AES256-SHA, AES128-SHA256, AES256-SHA256).	option	-	enable
	Option	Description		
	<i>enable</i>	Enable static key ciphers in SSL/TLS connections.		
	<i>disable</i>	Disable static key ciphers in SSL/TLS connections.		

Parameter	Description	Type	Size	Default																								
ssh-kex-algo	Select one or more SSH kex algorithms.	option	-	diffie-hellman-group14-sha256 diffie-hellman-group16-sha512 diffie-hellman-group18-sha512 diffie-hellman-group-exchange-sha256 curve25519-sha256@libssh.org ecdh-sha2-nistp256 ecdh-sha2-nistp384 ecdh-sha2-nistp521																								
<table><tr><th>Option</th><th>Description</th></tr><tr><td>diffie-hellman-group1-sha1</td><td>diffie-hellman-group1-sha1</td></tr><tr><td>diffie-hellman-group14-sha1</td><td>diffie-hellman-group14-sha1</td></tr><tr><td>diffie-hellman-group14-sha256</td><td>diffie-hellman-group14-sha256</td></tr><tr><td>diffie-hellman-group16-sha512</td><td>diffie-hellman-group16-sha512</td></tr><tr><td>diffie-hellman-group18-sha512</td><td>diffie-hellman-group18-sha512</td></tr><tr><td>diffie-hellman-group-exchange-sha1</td><td>diffie-hellman-group-exchange-sha1</td></tr><tr><td>diffie-hellman-group-exchange-sha256</td><td>diffie-hellman-group-exchange-sha256</td></tr><tr><td>curve25519-sha256@libssh.org</td><td>curve25519-sha256@libssh.org</td></tr><tr><td>ecdh-sha2-nistp256</td><td>ecdh-sha2-nistp256</td></tr><tr><td>ecdh-sha2-nistp384</td><td>ecdh-sha2-nistp384</td></tr><tr><td>ecdh-sha2-nistp521</td><td>ecdh-sha2-nistp521</td></tr></table>					Option	Description	diffie-hellman-group1-sha1	diffie-hellman-group1-sha1	diffie-hellman-group14-sha1	diffie-hellman-group14-sha1	diffie-hellman-group14-sha256	diffie-hellman-group14-sha256	diffie-hellman-group16-sha512	diffie-hellman-group16-sha512	diffie-hellman-group18-sha512	diffie-hellman-group18-sha512	diffie-hellman-group-exchange-sha1	diffie-hellman-group-exchange-sha1	diffie-hellman-group-exchange-sha256	diffie-hellman-group-exchange-sha256	curve25519-sha256@libssh.org	curve25519-sha256@libssh.org	ecdh-sha2-nistp256	ecdh-sha2-nistp256	ecdh-sha2-nistp384	ecdh-sha2-nistp384	ecdh-sha2-nistp521	ecdh-sha2-nistp521
Option	Description																											
diffie-hellman-group1-sha1	diffie-hellman-group1-sha1																											
diffie-hellman-group14-sha1	diffie-hellman-group14-sha1																											
diffie-hellman-group14-sha256	diffie-hellman-group14-sha256																											
diffie-hellman-group16-sha512	diffie-hellman-group16-sha512																											
diffie-hellman-group18-sha512	diffie-hellman-group18-sha512																											
diffie-hellman-group-exchange-sha1	diffie-hellman-group-exchange-sha1																											
diffie-hellman-group-exchange-sha256	diffie-hellman-group-exchange-sha256																											
curve25519-sha256@libssh.org	curve25519-sha256@libssh.org																											
ecdh-sha2-nistp256	ecdh-sha2-nistp256																											
ecdh-sha2-nistp384	ecdh-sha2-nistp384																											
ecdh-sha2-nistp521	ecdh-sha2-nistp521																											
ssh-enc-algo	Select one or more SSH ciphers.	option	-	aes256-ctr aes256-gcm@openssh.com																								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>chacha20-poly1305@openssh.com</i>	chacha20-poly1305@openssh.com		
	<i>aes128-ctr</i>	aes128-ctr		
	<i>aes192-ctr</i>	aes192-ctr		
	<i>aes256-ctr</i>	aes256-ctr		
	<i>arcfour256</i>	arcfour256		
	<i>arcfour128</i>	arcfour128		
	<i>aes128-cbc</i>	aes128-cbc		
	<i>3des-cbc</i>	3des-cbc		
	<i>blowfish-cbc</i>	blowfish-cbc		
	<i>cast128-cbc</i>	cast128-cbc		
	<i>aes192-cbc</i>	aes192-cbc		
	<i>aes256-cbc</i>	aes256-cbc		
	<i>arcfour</i>	arcfour		
	<i>rijndael-cbc@lysator.liu.se</i>	rijndael-cbc@lysator.liu.se		
	<i>aes128-gcm@openssh.com</i>	aes128-gcm@openssh.com		
	<i>aes256-gcm@openssh.com</i>	aes256-gcm@openssh.com		
ssh-mac-algo	Select one or more SSH MAC algorithms.	option	-	hmac-sha2-256 hmac-sha2-256-etm@openssh.com hmac-sha2-512 hmac-sha2-512-etm@openssh.com
	Option	Description		
	<i>hmac-md5</i>	hmac-md5		
	<i>hmac-md5-etm@openssh.com</i>	hmac-md5-etm@openssh.com		
	<i>hmac-md5-96</i>	hmac-md5-96		

Parameter	Description	Type	Size	Default																															
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>hmac-md5-96-etm@openssh.com</i></td><td>hmac-md5-96-etm@openssh.com</td></tr><tr><td><i>hmac-sha1</i></td><td>hmac-sha1</td></tr><tr><td><i>hmac-sha1-etm@openssh.com</i></td><td>hmac-sha1-etm@openssh.com</td></tr><tr><td><i>hmac-sha2-256</i></td><td>hmac-sha2-256</td></tr><tr><td><i>hmac-sha2-256-etm@openssh.com</i></td><td>hmac-sha2-256-etm@openssh.com</td></tr><tr><td><i>hmac-sha2-512</i></td><td>hmac-sha2-512</td></tr><tr><td><i>hmac-sha2-512-etm@openssh.com</i></td><td>hmac-sha2-512-etm@openssh.com</td></tr><tr><td><i>hmac-ripemd160</i></td><td>hmac-ripemd160</td></tr><tr><td><i>hmac-ripemd160@openssh.com</i></td><td>hmac-ripemd160@openssh.com</td></tr><tr><td><i>hmac-ripemd160-etm@openssh.com</i></td><td>hmac-ripemd160-etm@openssh.com</td></tr><tr><td><i>umac-64@openssh.com</i></td><td>umac-64@openssh.com</td></tr><tr><td><i>umac-128@openssh.com</i></td><td>umac-128@openssh.com</td></tr><tr><td><i>umac-64-etm@openssh.com</i></td><td>umac-64-etm@openssh.com</td></tr><tr><td><i>umac-128-etm@openssh.com</i></td><td>umac-128-etm@openssh.com</td></tr></table>	Option	Description	<i>hmac-md5-96-etm@openssh.com</i>	hmac-md5-96-etm@openssh.com	<i>hmac-sha1</i>	hmac-sha1	<i>hmac-sha1-etm@openssh.com</i>	hmac-sha1-etm@openssh.com	<i>hmac-sha2-256</i>	hmac-sha2-256	<i>hmac-sha2-256-etm@openssh.com</i>	hmac-sha2-256-etm@openssh.com	<i>hmac-sha2-512</i>	hmac-sha2-512	<i>hmac-sha2-512-etm@openssh.com</i>	hmac-sha2-512-etm@openssh.com	<i>hmac-ripemd160</i>	hmac-ripemd160	<i>hmac-ripemd160@openssh.com</i>	hmac-ripemd160@openssh.com	<i>hmac-ripemd160-etm@openssh.com</i>	hmac-ripemd160-etm@openssh.com	<i>umac-64@openssh.com</i>	umac-64@openssh.com	<i>umac-128@openssh.com</i>	umac-128@openssh.com	<i>umac-64-etm@openssh.com</i>	umac-64-etm@openssh.com	<i>umac-128-etm@openssh.com</i>	umac-128-etm@openssh.com				
	Option	Description																																	
	<i>hmac-md5-96-etm@openssh.com</i>	hmac-md5-96-etm@openssh.com																																	
	<i>hmac-sha1</i>	hmac-sha1																																	
	<i>hmac-sha1-etm@openssh.com</i>	hmac-sha1-etm@openssh.com																																	
	<i>hmac-sha2-256</i>	hmac-sha2-256																																	
	<i>hmac-sha2-256-etm@openssh.com</i>	hmac-sha2-256-etm@openssh.com																																	
	<i>hmac-sha2-512</i>	hmac-sha2-512																																	
	<i>hmac-sha2-512-etm@openssh.com</i>	hmac-sha2-512-etm@openssh.com																																	
	<i>hmac-ripemd160</i>	hmac-ripemd160																																	
	<i>hmac-ripemd160@openssh.com</i>	hmac-ripemd160@openssh.com																																	
	<i>hmac-ripemd160-etm@openssh.com</i>	hmac-ripemd160-etm@openssh.com																																	
	<i>umac-64@openssh.com</i>	umac-64@openssh.com																																	
	<i>umac-128@openssh.com</i>	umac-128@openssh.com																																	
<i>umac-64-etm@openssh.com</i>	umac-64-etm@openssh.com																																		
<i>umac-128-etm@openssh.com</i>	umac-128-etm@openssh.com																																		
snat-route-change	Enable/disable the ability to change the source NAT route.	option	-	disable																															
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable SNAT route change.</td></tr><tr><td><i>disable</i></td><td>Disable SNAT route change.</td></tr></table>	Option	Description	<i>enable</i>	Enable SNAT route change.	<i>disable</i>	Disable SNAT route change.																												
	Option	Description																																	
	<i>enable</i>	Enable SNAT route change.																																	
<i>disable</i>	Disable SNAT route change.																																		
speedtest-server	Enable/disable speed test server.	option	-	disable																															

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable speed test server service.		
	<i>disable</i>	Disable speed test server service.		
cli-audit-log	Enable/disable CLI audit log.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable CLI audit log.		
	<i>disable</i>	Disable CLI audit log.		
dh-params	Number of bits to use in the Diffie-Hellman exchange for HTTPS/SSH protocols.	option	-	2048
	Option	Description		
	<i>1024</i>	1024 bits.		
	<i>1536</i>	1536 bits.		
	<i>2048</i>	2048 bits.		
	<i>3072</i>	3072 bits.		
	<i>4096</i>	4096 bits.		
	<i>6144</i>	6144 bits.		
	<i>8192</i>	8192 bits.		
fds-statistics	Enable/disable sending IPS, Application Control, and AntiVirus data to FortiGuard. This data is used to improve FortiGuard services and is not shared with external parties and is protected by Fortinet's privacy policy.	option	-	enable

Parameter	Description	Type	Size	Default
	Option Description			
	<i>enable</i>	Enable FortiGuard statistics.		
	<i>disable</i>	Disable FortiGuard statistics.		
fds-statistics-period	FortiGuard statistics collection period in minutes. (1 - 1440 min (1 min to 24 hours), default = 60).	integer	Minimum value: 1 Maximum value: 1440	60
tcp-option	Enable SACK, timestamp and MSS TCP options.	option	-	enable
	Option Description			
	<i>enable</i>	Enable TCP option.		
	<i>disable</i>	Disable TCP option.		
lldp-transmission	Enable/disable Link Layer Discovery Protocol (LLDP) transmission.	option	-	disable
	Option Description			
	<i>enable</i>	Enable transmission of Link Layer Discovery Protocol (LLDP).		
	<i>disable</i>	Disable transmission of Link Layer Discovery Protocol (LLDP).		
lldp-reception	Enable/disable Link Layer Discovery Protocol (LLDP) reception.	option	-	disable
	Option Description			
	<i>enable</i>	Enable reception of Link Layer Discovery Protocol (LLDP).		
	<i>disable</i>	Disable reception of Link Layer Discovery Protocol (LLDP).		

Parameter	Description	Type	Size	Default
proxy-auth-timeout	Authentication timeout in minutes for authenticated users (1 - 10000 min, default = 10).	integer	Minimum value: 1 Maximum value: 10000	10
resigned-pkey-period	Resigned cert private key regeration period in hours(0 - 600 hours, 0 means static config).	integer	Minimum value: 0 Maximum value: 600	0
proxy-keep-alive-mode	Control if users must re-authenticate after a session is closed, traffic has been idle, or from the point at which the user was authenticated.	option	-	session
	Option	Description		
	session	Proxy keep-alive timeout begins at the closure of the session.		
	traffic	Proxy keep-alive timeout begins after traffic has not been received.		
	re-authentication	Proxy keep-alive timeout begins when the user was authenticated.		
proxy-re-authentication-time	The time limit that users must re-authenticate if proxy-keep-alive-mode is set to re-authenticate (1 - 86400 sec, default=30s.	integer	Minimum value: 1 Maximum value: 86400	30
proxy-auth-lifetime	Enable/disable authenticated users lifetime control. This is a cap on the total time a proxy user can be authenticated for after which re-authentication will take place.	option	-	disable

Parameter	Description	Type	Size	Default
	Option Description			
	<i>enable</i>	Enable authenticated users lifetime control.		
	<i>disable</i>	Disable authenticated users lifetime control.		
proxy-auth-lifetime-timeout	Lifetime timeout in minutes for authenticated users (5 - 65535 min, default=480 (8 hours)).	integer	Minimum value: 5 Maximum value: 65535	480
proxy-auth-machine-timeout	Machine account timeout in seconds for authenticated machines (5 - 30 seconds, default=15s).	integer	Minimum value: 5 Maximum value: 30	15
proxy-resource-mode	Enable/disable use of the maximum memory usage on the FortiProxy unit's proxy processing of resources, such as block lists, allow lists, and external resources.	option	-	disable
	Option Description			
	<i>enable</i>	Enable use of the maximum memory usage.		
	<i>disable</i>	Disable use of the maximum memory usage.		
proxy-cert-use-mgmt-vdom	Enable/disable using management VDOM to send requests.	option	-	disable
	Option Description			
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

Parameter	Description	Type	Size	Default						
update-tls-finger-print	Enable/disable update TLS fingerprint when deep-inspection is enabled.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
sys-perf-log-interval	Time in minutes between updates of performance statistics logging. (1 - 15 min, default = 5, 0 = disabled).	integer	Minimum value: 0 Maximum value: 15	5						
check-protocol-header	Level of checking performed on protocol headers. Strict checking is more thorough but may affect performance. Loose checking is OK in most cases.	option	-	loose						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>loose</i></td><td>Check protocol header loosely.</td></tr><tr><td><i>strict</i></td><td>Check protocol header strictly.</td></tr></table>	Option	Description	<i>loose</i>	Check protocol header loosely.	<i>strict</i>	Check protocol header strictly.			
Option	Description									
<i>loose</i>	Check protocol header loosely.									
<i>strict</i>	Check protocol header strictly.									
vip-arp-range	Controls the number of ARPs that the FortiProxy sends for a Virtual IP (VIP) address range.	option	-	restricted						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>unlimited</i></td><td>Send ARPs for all addresses in VIP range.</td></tr><tr><td><i>restricted</i></td><td>Send ARPs for the first 8192 addresses in VIP range.</td></tr></table>	Option	Description	<i>unlimited</i>	Send ARPs for all addresses in VIP range.	<i>restricted</i>	Send ARPs for the first 8192 addresses in VIP range.			
Option	Description									
<i>unlimited</i>	Send ARPs for all addresses in VIP range.									
<i>restricted</i>	Send ARPs for the first 8192 addresses in VIP range.									

Parameter	Description	Type	Size	Default
tcp-halfclose-timer	Number of seconds the FortiProxy unit should wait to close a session after one peer has sent a FIN packet but the other has not responded (1 - 86400 sec (1 day), default = 120).	integer	Minimum value: 1 Maximum value: 86400	120
tcp-halfopen-timer	Number of seconds the FortiProxy unit should wait to close a session after one peer has sent an open session packet but the other has not responded (1 - 86400 sec (1 day), default = 10).	integer	Minimum value: 1 Maximum value: 86400	10
tcp-timewait-timer	Length of the TCP TIME-WAIT state in seconds (1 - 300 sec, default = 1).	integer	Minimum value: 0 Maximum value: 300	1
tcp-rst-timer	Length of the TCP CLOSE state in seconds (5 - 300 sec, default = 5).	integer	Minimum value: 5 Maximum value: 300	5
udp-idle-timer	UDP connection session timeout. This command can be useful in managing CPU and memory resources (1 - 86400 seconds (1 day), default = 60).	integer	Minimum value: 1 Maximum value: 86400	180
block-session-timer	Duration in seconds for blocked sessions (1 - 300 sec (5 minutes), default = 30).	integer	Minimum value: 1 Maximum value: 300	30

Parameter	Description	Type	Size	Default						
ip-src-port-range	IP source port range used for traffic originating from the FortiProxy unit.	user	Not Specified	1024-65001						
pre-login-banner	Enable/disable displaying the administrator access disclaimer message on the login page before an administrator logs in.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable pre-login banner.</td></tr><tr><td><i>disable</i></td><td>Disable pre-login banner.</td></tr></table>	Option	Description	<i>enable</i>	Enable pre-login banner.	<i>disable</i>	Disable pre-login banner.			
Option	Description									
<i>enable</i>	Enable pre-login banner.									
<i>disable</i>	Disable pre-login banner.									
post-login-banner	Enable/disable displaying the administrator access disclaimer message after an administrator successfully logs in.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable post-login banner.</td></tr><tr><td><i>enable</i></td><td>Enable post-login banner.</td></tr></table>	Option	Description	<i>disable</i>	Disable post-login banner.	<i>enable</i>	Enable post-login banner.			
Option	Description									
<i>disable</i>	Disable post-login banner.									
<i>enable</i>	Enable post-login banner.									
tftp	Enable/disable TFTP.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable TFTP.</td></tr><tr><td><i>disable</i></td><td>Disable TFTP.</td></tr></table>	Option	Description	<i>enable</i>	Enable TFTP.	<i>disable</i>	Disable TFTP.			
Option	Description									
<i>enable</i>	Enable TFTP.									
<i>disable</i>	Disable TFTP.									
av-failopen	Set the action to take if the FortiProxy is running low on memory or the proxy connection limit has been reached.	option	-	pass						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>pass</i>	Bypass the antivirus system when memory is low. Antivirus scanning resumes when the low memory condition is resolved.		
	<i>off</i>	Stop accepting new AV sessions when entering conserve mode, but continue to process current active sessions.		
	<i>one-shot</i>	Bypass the antivirus system when memory is low.		
av-failopen-session	When enabled and a proxy for a protocol runs out of room in its session table, that protocol goes into failopen mode and enacts the action specified by av-failopen.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable AV fail open session option.		
	<i>disable</i>	Disable AV fail open session option.		
kernel-panic-timeout	Reboot timeout after kernel panic in seconds. Value of 0 means do not reboot.	integer	Minimum value: 0 Maximum value: 3600	5
kernel-panic-debug	Enable/disable kernel panic debug messages.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable kernel panic debug messages.		
	<i>disable</i>	Disable kernel panic debug messages.		
kernel-panic-on-warn	Enable/disable kernel panic and reboot on kernel warning.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable panic and reboot on kernel warning.		
	<i>disable</i>	Disable panic and reboot on kernel warning.		

Parameter	Description	Type	Size	Default
memory-use-threshold-extreme	Threshold at which memory usage is considered extreme (new sessions are dropped) (% of total RAM, default = 95).	integer	Minimum value: 70 Maximum value: 97	95
memory-use-threshold-red	Threshold at which memory usage forces the FortiProxy to enter conserve mode (% of total RAM, default = 88).	integer	Minimum value: 70 Maximum value: 97	88
memory-use-threshold-green	Threshold at which memory usage forces the FortiProxy to exit conserve mode (% of total RAM, default = 82).	integer	Minimum value: 70 Maximum value: 97	82
ip-fragment-mem-thresholds	Maximum memory (MB) used to reassemble IPv4/IPv6 fragments.	integer	Minimum value: 32 Maximum value: 2047	32
cpu-use-threshold	Threshold at which CPU usage is reported (% of total CPU, default = 90).	integer	Minimum value: 50 Maximum value: 99	90
log-single-cpu-high	Enable/disable logging the event of a single CPU core reaching CPU usage threshold.	option	-	disable
		Option	Description	
		<i>enable</i>	Enable logging the event of a single CPU core reaching CPU usage threshold.	
		<i>disable</i>	Disable logging the event of a single CPU core reaching CPU usage threshold.	

Parameter	Description	Type	Size	Default						
check-reset-range	Configure ICMP error message verification. You can either apply strict RST range checking or disable it.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>strict</i></td><td>Check RST range strictly.</td></tr><tr><td><i>disable</i></td><td>Disable RST range check.</td></tr></table>	Option	Description	<i>strict</i>	Check RST range strictly.	<i>disable</i>	Disable RST range check.			
Option	Description									
<i>strict</i>	Check RST range strictly.									
<i>disable</i>	Disable RST range check.									
admin-port	Administrative access port for HTTP. (1 - 65535, default = 80).	integer	Minimum value: 1 Maximum value: 65535	80						
admin-sport	Administrative access port for HTTPS. (1 - 65535, default = 443).	integer	Minimum value: 1 Maximum value: 65535	443						
admin-host	Administrative host for HTTP and HTTPS. When set, will be used in lieu of the client's Host header for any redirection.	string	Maximum length: 255							
admin-https-redirect	Enable/disable redirection of HTTP administration access to HTTPS.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable redirecting HTTP administration access to HTTPS.</td></tr><tr><td><i>disable</i></td><td>Disable redirecting HTTP administration access to HTTPS.</td></tr></table>	Option	Description	<i>enable</i>	Enable redirecting HTTP administration access to HTTPS.	<i>disable</i>	Disable redirecting HTTP administration access to HTTPS.			
Option	Description									
<i>enable</i>	Enable redirecting HTTP administration access to HTTPS.									
<i>disable</i>	Disable redirecting HTTP administration access to HTTPS.									

Parameter	Description	Type	Size	Default						
admin-hsts-max-age	HTTPS Strict-Transport-Security header max-age in seconds. A value of 0 will reset any HSTS records in the browser.When admin-https-redirect is disabled the header max-age will be 0.	integer	Minimum value: 0 Maximum value: 2147483647	15552000						
admin-ssh-password	Enable/disable password authentication for SSH admin access.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable password authentication for SSH admin access.</td></tr><tr><td><i>disable</i></td><td>Disable password authentication for SSH admin access.</td></tr></table>	Option	Description	<i>enable</i>	Enable password authentication for SSH admin access.	<i>disable</i>	Disable password authentication for SSH admin access.			
Option	Description									
<i>enable</i>	Enable password authentication for SSH admin access.									
<i>disable</i>	Disable password authentication for SSH admin access.									
admin-restrict-local	Enable/disable local admin authentication restriction when remote authenticator is up and running (default = disable).	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable local admin authentication restriction.</td></tr><tr><td><i>disable</i></td><td>Disable local admin authentication restriction.</td></tr></table>	Option	Description	<i>enable</i>	Enable local admin authentication restriction.	<i>disable</i>	Disable local admin authentication restriction.			
Option	Description									
<i>enable</i>	Enable local admin authentication restriction.									
<i>disable</i>	Disable local admin authentication restriction.									
admin-ssh-port	Administrative access port for SSH. (1 - 65535, default = 22).	integer	Minimum value: 1 Maximum value: 65535	22						
admin-ssh-grace-time	Maximum time in seconds permitted between making an SSH connection to the FortiProxy unit and authenticating (10 - 3600 sec (1 hour), default 120).	integer	Minimum value: 10 Maximum value: 3600	120						

Parameter	Description	Type	Size	Default
admin-ssh-v1	Enable/disable SSH v1 compatibility.	option	-	disable
	Option Description			
	<i>enable</i>	Enable SSH v1 compatibility.		
	<i>disable</i>	Disable SSH v1 compatibility.		
admin-telnet	Enable/disable TELNET service.	option	-	enable
	Option Description			
	<i>enable</i>	Enable TELNET service.		
	<i>disable</i>	Disable TELNET service.		
admin-telnet-port	Administrative access port for TELNET. (1 - 65535, default = 23).	integer	Minimum value: 1 Maximum value: 65535	23
admin-forticloud-sso-login	Enable/disable FortiCloud admin login via SSO.	option	-	disable
	Option Description			
	<i>enable</i>	Enable FortiCloud admin login via SSO.		
	<i>disable</i>	Disable FortiCloud admin login via SSO.		
admin-forticloud-sso-default-profile	Override access profile.	string	Maximum length: 35	
default-service-source-port	Default service source port range (default = 1 - 65535).	user	Not Specified	
admin-server-cert	Server certificate that the FortiProxy uses for HTTPS administrative connections.	string	Maximum length: 35	Fortinet_GUI_Server

Parameter	Description	Type	Size	Default						
admin-https-pki-required	Enable/disable admin login method. Enable to force administrators to provide a valid certificate to log in if PKI is enabled. Disable to allow administrators to log in with a certificate or password.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Admin users must provide a valid certificate when PKI is enabled for HTTPS admin access.</td></tr><tr><td><i>disable</i></td><td>Admin users can login by providing a valid certificate or password.</td></tr></table>	Option	Description	<i>enable</i>	Admin users must provide a valid certificate when PKI is enabled for HTTPS admin access.	<i>disable</i>	Admin users can login by providing a valid certificate or password.			
Option	Description									
<i>enable</i>	Admin users must provide a valid certificate when PKI is enabled for HTTPS admin access.									
<i>disable</i>	Admin users can login by providing a valid certificate or password.									
auth-http-port	User authentication HTTP port. (1 - 65535, default = 1000).	integer	Minimum value: 1 Maximum value: 65535	1000						
auth-https-port	User authentication HTTPS port. (1 - 65535, default = 1003).	integer	Minimum value: 1 Maximum value: 65535	1003						
auth-ike-saml-port	User IKE SAML authentication port (0 - 65535, default = 1001).	integer	Minimum value: 0 Maximum value: 65535	1001						
auth-keepalive	Enable to prevent user authentication sessions from timing out when idle.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable use of keep alive to extend authentication.</td></tr><tr><td><i>disable</i></td><td>Disable use of keep alive to extend authentication.</td></tr></table>	Option	Description	<i>enable</i>	Enable use of keep alive to extend authentication.	<i>disable</i>	Disable use of keep alive to extend authentication.			
Option	Description									
<i>enable</i>	Enable use of keep alive to extend authentication.									
<i>disable</i>	Disable use of keep alive to extend authentication.									

Parameter	Description	Type	Size	Default						
policy-auth-concurrent	Number of concurrent firewall use logins from the same user (1 - 100, default = 0 means no limit).	integer	Minimum value: 0 Maximum value: 100	0						
auth-session-limit	Action to take when the number of allowed user authenticated sessions is reached.	option	-	block-new						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>block-new</i></td><td>Block new user authentication attempts.</td></tr><tr><td><i>logout-inactive</i></td><td>Logout the most inactive user authenticated sessions.</td></tr></table>				Option	Description	<i>block-new</i>	Block new user authentication attempts.	<i>logout-inactive</i>	Logout the most inactive user authenticated sessions.
Option	Description									
<i>block-new</i>	Block new user authentication attempts.									
<i>logout-inactive</i>	Logout the most inactive user authenticated sessions.									
auth-cert	Server certificate that the FortiProxy uses for HTTPS firewall authentication connections.	string	Maximum length: 35	Fortinet_Factory						
clt-cert-req	Enable/disable requiring administrators to have a client certificate to log into the GUI using HTTPS.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable require client certificate for GUI login.</td></tr><tr><td><i>disable</i></td><td>Disable require client certificate for GUI login.</td></tr></table>				Option	Description	<i>enable</i>	Enable require client certificate for GUI login.	<i>disable</i>	Disable require client certificate for GUI login.
Option	Description									
<i>enable</i>	Enable require client certificate for GUI login.									
<i>disable</i>	Disable require client certificate for GUI login.									
fortiservice-port	FortiService port (1 - 65535, default = 8013). Used by FortiClient endpoint compliance. Older versions of FortiClient used a different port.	integer	Minimum value: 1 Maximum value: 65535	8013						

Parameter	Description	Type	Size	Default
cfg-save	Configuration file save mode for CLI changes.	option	-	automatic
	Option	Description		
	<i>automatic</i>	Automatically save config.		
	<i>manual</i>	Manually save config.		
	<i>revert</i>	Manually save config and revert the config when timeout.		
cfg-revert-timeout	Time-out for reverting to the last saved configuration. (10 - 4294967295 seconds, default = 600).	integer	Minimum value: 10 Maximum value: 4294967295	600
reboot-upon-config-restore	Enable/disable reboot of system upon restoring configuration.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable reboot of system upon restoring configuration.		
	<i>disable</i>	Disable reboot of system upon restoring configuration.		
admin-scp	Enable/disable using SCP to download the system configuration. You can use SCP as an alternative method for backing up the configuration.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable allow system configuration download by SCP.		
	<i>disable</i>	Disable allow system configuration download by SCP.		
security-rating-result-submission	Enable/disable the submission of Security Rating results to FortiGuard.	option	-	enable

Parameter	Description	Type	Size	Default
	Option Description			
	<i>enable</i>	Enable submission of Security Rating results to FortiGuard.		
	<i>disable</i>	Disable submission of Security Rating results to FortiGuard.		
security-rating-run-on-schedule	Enable/disable scheduled runs of Security Rating.	option	-	enable
	Option Description			
	<i>enable</i>	Enable scheduled runs of Security Rating.		
	<i>disable</i>	Disable scheduled runs of Security Rating.		
fortiextender-data-port	FortiExtender data port (1024 - 49150, default = 25246).	integer	Minimum value: 1024 Maximum value: 49150	25246
fortiextender	Enable/disable FortiExtender.	option	-	disable
	Option Description			
	<i>disable</i>	Disable FortiExtender controller.		
	<i>enable</i>	Enable FortiExtender controller.		
extender-controller-reserved-network	Configure reserved network subnet for managed LAN extension FortiExtender units. This is available when the FortiExtender daemon is running.	ipv4-classnet-host	Not Specified	10.252.0.1 255.255.0.0
fortiextender-discovery-lockdown	Enable/disable FortiExtender CAPWAP lockdown.	option	-	disable
	Option Description			
	<i>disable</i>	Unlock down new FortiExtender device discovery.		
	<i>enable</i>	Lock down new FortiExtender device discovery.		

Parameter	Description	Type	Size	Default
fortiextender-provision-on-authorization	Enable/disable automatic provisioning of latest FortiExtender firmware on authorization.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable FortiExtender firmware provision on authorization.		
	<i>disable</i>	Disable FortiExtender firmware provision on authorization.		
dnsproxy-worker-count	DNS proxy worker count. For a FortiGate with multiple logical CPUs, you can set the DNS process number from 1 to the number of logical CPUs.	integer	Minimum value: 1 Maximum value: 255	1
url-filter-count	URL filter daemon count.	integer	Minimum value: 1 Maximum value: 10	1
proxy-worker-count	Proxy worker count.	integer	Minimum value: 1 Maximum value: 255	0
scanunit-count	Number of scanunits. The range and the default depend on the number of CPUs. Only available on FortiProxy units with multiple CPUs.	integer	Minimum value: 2 Maximum value: 255	0
fgd-alert-subscription	Type of alert to retrieve from FortiGuard.	option	-	
	Option	Description		
	<i>advisory</i>	Retrieve FortiGuard advisories, report and news alerts.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>latest-threat</i>	Retrieve latest FortiGuard threats alerts.		
	<i>latest-virus</i>	Retrieve latest FortiGuard virus alerts.		
	<i>latest-attack</i>	Retrieve latest FortiGuard attack alerts.		
	<i>new-antivirus-db</i>	Retrieve FortiGuard AV database release alerts.		
	<i>new-attack-db</i>	Retrieve FortiGuard IPS database release alerts.		
ipv6-accept-dad	Enable/disable acceptance of IPv6 Duplicate Address Detection (DAD).	integer	Minimum value: 0 Maximum value: 2	1
ipv6-allow-multicast-probe	Enable/disable IPv6 address probe through Multicast.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable probing of IPv6 address space through Multicast.		
	<i>disable</i>	Disable probing of IPv6 address space through Multicast.		
ipv6-allow-local-in-silent-drop	Enable/disable silent drop of IPv6 local-in traffic.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable silent drop of IPv6 local-in traffic.		
	<i>disable</i>	Disable silent drop of IPv6 local-in traffic.		
csr-ca-attribute	Enable/disable the CA attribute in certificates. Some CA servers reject CSRs that have the CA attribute.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable CA attribute in CSR.		
	<i>disable</i>	Disable CA attribute in CSR.		

Parameter	Description	Type	Size	Default						
wimax-4g-usb	Enable/disable comparability with WiMAX 4G USB devices.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable WiMax 4G.</td></tr><tr><td><i>disable</i></td><td>Disable WiMax 4G.</td></tr></table>	Option	Description	<i>enable</i>	Enable WiMax 4G.	<i>disable</i>	Disable WiMax 4G.			
Option	Description									
<i>enable</i>	Enable WiMax 4G.									
<i>disable</i>	Disable WiMax 4G.									
cert-chain-max	Maximum number of certificates that can be traversed in a certificate chain.	integer	Minimum value: 1 Maximum value: 2147483647	8						
two-factor-ftk-expiry	FortiToken authentication session timeout (60 - 600 sec (10 minutes), default = 60).	integer	Minimum value: 60 Maximum value: 600	60						
two-factor-email-expiry	Email-based two-factor authentication session timeout (30 - 300 seconds (5 minutes), default = 60).	integer	Minimum value: 30 Maximum value: 300	60						
two-factor-sms-expiry	SMS-based two-factor authentication session timeout (30 - 300 sec, default = 60).	integer	Minimum value: 30 Maximum value: 300	60						
two-factor-fac-expiry	FortiAuthenticator token authentication session timeout (10 - 3600 seconds (1 hour), default = 60).	integer	Minimum value: 10 Maximum value: 3600	60						
two-factor-ftm-expiry	FortiToken Mobile session timeout (1 - 168 hours (7 days), default = 72).	integer	Minimum value: 1 Maximum value: 168	72						

Parameter	Description	Type	Size	Default						
max-img-cache-size	Maximum space (MB) can be used by image-analyzer to store blocked images into ram disk.	integer	Minimum value: 30 Maximum value: 300	60						
img-cache-mode	Select image cache mode for image-analyzer (default = rolling)	option	-	rolling						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>stop</td><td>Stop caching blocked images into ram disk when limit reaches.</td></tr><tr><td>rolling</td><td>Evict old cached images when limit reaches.</td></tr></table>	Option	Description	stop	Stop caching blocked images into ram disk when limit reaches.	rolling	Evict old cached images when limit reaches.			
Option	Description									
stop	Stop caching blocked images into ram disk when limit reaches.									
rolling	Evict old cached images when limit reaches.									
per-user-bal	Enable/disable per-user block/allow list filter.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable per-user block/allow list filter.</td></tr><tr><td>disable</td><td>Disable per-user block/allow list filter.</td></tr></table>	Option	Description	enable	Enable per-user block/allow list filter.	disable	Disable per-user block/allow list filter.			
Option	Description									
enable	Enable per-user block/allow list filter.									
disable	Disable per-user block/allow list filter.									
wad-worker-count	Number of explicit proxy WAN optimization daemon (WAD) processes. By default WAN optimization, explicit proxy, and web caching is handled by all of the CPU cores in a FortiProxy unit.	integer	Minimum value: 0 Maximum value: 255	0						
wad-csvc-cs-count	Number of concurrent WAD-cache-service object-cache processes.	integer	Minimum value: 1 Maximum value: 1	1						
wad-csvc-db-count	Number of concurrent WAD-cache-service byte-cache processes.	integer	Minimum value: 0 Maximum value: 255	0						

Parameter	Description	Type	Size	Default						
http-view	Enable/disable logging and viewing of HTTP/S cache traffic.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable logging and viewing of HTTP/S cache traffic.</td></tr><tr><td><i>disable</i></td><td>Disable logging and viewing of HTTP/S cache traffic.</td></tr></table>	Option	Description	<i>enable</i>	Enable logging and viewing of HTTP/S cache traffic.	<i>disable</i>	Disable logging and viewing of HTTP/S cache traffic.			
Option	Description									
<i>enable</i>	Enable logging and viewing of HTTP/S cache traffic.									
<i>disable</i>	Disable logging and viewing of HTTP/S cache traffic.									
wad-source-affinity	Enable/disable dispatching traffic to WAD workers based on source affinity.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable dispatching traffic to WAD workers based on source affinity.</td></tr><tr><td><i>enable</i></td><td>Enable dispatching traffic to WAD workers based on source affinity.</td></tr></table>	Option	Description	<i>disable</i>	Disable dispatching traffic to WAD workers based on source affinity.	<i>enable</i>	Enable dispatching traffic to WAD workers based on source affinity.			
Option	Description									
<i>disable</i>	Disable dispatching traffic to WAD workers based on source affinity.									
<i>enable</i>	Enable dispatching traffic to WAD workers based on source affinity.									
wad-memory-change-granularity	Minimum percentage change in system memory usage detected by the wad daemon prior to adjusting TCP window size for any active connection.	integer	Minimum value: 5 Maximum value: 25	10						
login-timestamp	Enable/disable login time recording.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable login time recording.</td></tr><tr><td><i>disable</i></td><td>Disable login time recording.</td></tr></table>	Option	Description	<i>enable</i>	Enable login time recording.	<i>disable</i>	Disable login time recording.			
Option	Description									
<i>enable</i>	Enable login time recording.									
<i>disable</i>	Disable login time recording.									

Parameter	Description	Type	Size	Default						
miglogd-children	Number of logging (miglogd) processes to be allowed to run. Higher number can reduce performance; lower number can slow log processing time. No logs will be dropped or lost if the number is changed.	integer	Minimum value: 0 Maximum value: 15	0						
special-file-23-support	Enable/disable detection of those special format files when using Data Leak Prevention.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable detection of those special format files when using Data Leak Prevention.</td></tr><tr><td>enable</td><td>Enable detection of those special format files when using Data Leak Prevention.</td></tr></table>	Option	Description	disable	Disable detection of those special format files when using Data Leak Prevention.	enable	Enable detection of those special format files when using Data Leak Prevention.			
Option	Description									
disable	Disable detection of those special format files when using Data Leak Prevention.									
enable	Enable detection of those special format files when using Data Leak Prevention.									
log-uuid-address	Enable/disable insertion of address UUIDs to traffic logs.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable insertion of address UUID to traffic logs.</td></tr><tr><td>disable</td><td>Disable insertion of address UUID to traffic logs.</td></tr></table>	Option	Description	enable	Enable insertion of address UUID to traffic logs.	disable	Disable insertion of address UUID to traffic logs.			
Option	Description									
enable	Enable insertion of address UUID to traffic logs.									
disable	Disable insertion of address UUID to traffic logs.									
log-ssl-connection	Enable/disable logging of SSL connection events.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable logging of SSL connection events.</td></tr><tr><td>disable</td><td>Disable logging of SSL connection events.</td></tr></table>	Option	Description	enable	Enable logging of SSL connection events.	disable	Disable logging of SSL connection events.			
Option	Description									
enable	Enable logging of SSL connection events.									
disable	Disable logging of SSL connection events.									
gui-rest-api-cache	Enable/disable REST API result caching on FortiProxy.	option	-	enable						

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable REST API result caching on FortiProxy.</td></tr><tr><td><i>disable</i></td><td>Disable REST API result caching on FortiProxy.</td></tr></table>	Option	Description	<i>enable</i>	Enable REST API result caching on FortiProxy.	<i>disable</i>	Disable REST API result caching on FortiProxy.			
	Option	Description								
	<i>enable</i>	Enable REST API result caching on FortiProxy.								
<i>disable</i>	Disable REST API result caching on FortiProxy.									
gui-fortiguard-resource-fetch	Enable/disable retrieving static GUI resources from FortiGuard. Disabling it will improve GUI load time for air-gapped environments.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable retrieving static GUI resources from FortiGuard.</td></tr><tr><td><i>disable</i></td><td>Disable retrieving static GUI resources from FortiGuard.</td></tr></table>	Option	Description	<i>enable</i>	Enable retrieving static GUI resources from FortiGuard.	<i>disable</i>	Disable retrieving static GUI resources from FortiGuard.			
	Option	Description								
	<i>enable</i>	Enable retrieving static GUI resources from FortiGuard.								
<i>disable</i>	Disable retrieving static GUI resources from FortiGuard.									
arp-max-entry	Maximum number of dynamically learned MAC addresses that can be added to the ARP table (131072 - 2147483647, default = 131072).	integer	Minimum value: 131072 Maximum value: 2147483647	131072						
ha-affinity	Affinity setting for HA daemons (hexadecimal value up to 256 bits in the format of xxxxxxxxxxxxxxxxx).	string	Maximum length: 79	1						
cmdbsvr-affinity	Affinity setting for cmdbsvr (hexadecimal value up to 256 bits in the format of xxxxxxxxxxxxxxxxx).	string	Maximum length: 79	1						
av-affinity	Affinity setting for AV scanning (hexadecimal value up to 256 bits in the format of xxxxxxxxxxxxxxxxx).	string	Maximum length: 79	0						

Parameter	Description	Type	Size	Default
wad-affinity	Affinity setting for wad (hexadecimal value up to 256 bits in the format of xxxxxxxxxxxxxxxxx).	string	Maximum length: 79	0
ips-affinity	Affinity setting for IPS (hexadecimal value up to 256 bits in the format of xxxxxxxxxxxxxxxxx; allowed CPUs must be less than total number of IPS engine daemons).	string	Maximum length: 79	0
miglog-affinity	Affinity setting for logging (hexadecimal value up to 256 bits in the format of xxxxxxxxxxxxxxxxx).	string	Maximum length: 79	0
syslog-affinity	Affinity setting for syslog (hexadecimal value up to 256 bits in the format of xxxxxxxxxxxxxxxxx).	string	Maximum length: 79	0
url-filter-affinity	URL filter CPU affinity.	string	Maximum length: 79	0
ndp-max-entry	Maximum number of NDP table entries (set to 65,536 or higher; if set to 0, kernel holds 65,536 entries).	integer	Minimum value: 65536 Maximum value: 2147483647	0
br-fdb-max-entry	Maximum number of bridge forwarding database (FDB) entries.	integer	Minimum value: 8192 Maximum value: 2147483647	8192
max-route-cache-size	Maximum number of IP route cache entries (0 - 2147483647).	integer	Minimum value: 0 Maximum value: 2147483647	0

Parameter	Description	Type	Size	Default						
ipsec-round-robin	Enable/disable round-robin redistribution to multiple CPUs for IPsec VPN traffic.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable round-robin redistribution for IPsec VPN.</td></tr><tr><td><i>disable</i></td><td>Disable round-robin redistribution for IPsec VPN.</td></tr></table>	Option	Description	<i>enable</i>	Enable round-robin redistribution for IPsec VPN.	<i>disable</i>	Disable round-robin redistribution for IPsec VPN.			
Option	Description									
<i>enable</i>	Enable round-robin redistribution for IPsec VPN.									
<i>disable</i>	Disable round-robin redistribution for IPsec VPN.									
ipsec-soft-dec-async	Enable/disable software decryption asynchronization (using multiple CPUs to do decryption) for IPsec VPN traffic.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable software decryption asynchronization for IPsec VPN.</td></tr><tr><td><i>disable</i></td><td>Disable software decryption asynchronization for IPsec VPN.</td></tr></table>	Option	Description	<i>enable</i>	Enable software decryption asynchronization for IPsec VPN.	<i>disable</i>	Disable software decryption asynchronization for IPsec VPN.			
Option	Description									
<i>enable</i>	Enable software decryption asynchronization for IPsec VPN.									
<i>disable</i>	Disable software decryption asynchronization for IPsec VPN.									
device-idle-timeout	Time in seconds that a device must be idle to automatically log the device user out. (30 - 31536000 sec (30 sec to 1 year), default = 300).	integer	Minimum value: 30 Maximum value: 31536000	300						
user-device-store-max-devices	Maximum number of devices allowed in user device store.	integer	Minimum value: 20654 Maximum value: 59012	41308						
user-device-store-max-users	Maximum number of users allowed in user device store.	integer	Minimum value: 20654 Maximum value: 59012	41308						
user-device-store-max-unified-mem	Maximum unified memory allowed in user device store.	integer	Minimum value: 41308815 Maximum value: 413088153	206544076						

Parameter	Description	Type	Size	Default						
gui-device-latitude	Add the latitude of the location of this FortiProxy to position it on the Threat Map.	string	Maximum length: 19							
gui-device-longitude	Add the longitude of the location of this FortiProxy to position it on the Threat Map.	string	Maximum length: 19							
v-tpm	Enable/disable vTPM on VM.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable vTPM.</td></tr><tr><td><i>enable</i></td><td>Enable vTPM</td></tr></table>		Option	Description	<i>disable</i>	Disable vTPM.	<i>enable</i>	Enable vTPM		
Option	Description									
<i>disable</i>	Disable vTPM.									
<i>enable</i>	Enable vTPM									
private-data-encryption	Enable/disable private data encryption using an AES 128-bit key or passphrase.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable private data encryption using an AES 128-bit key.</td></tr><tr><td><i>enable</i></td><td>Enable private data encryption using an AES 128-bit key.</td></tr></table>		Option	Description	<i>disable</i>	Disable private data encryption using an AES 128-bit key.	<i>enable</i>	Enable private data encryption using an AES 128-bit key.		
Option	Description									
<i>disable</i>	Disable private data encryption using an AES 128-bit key.									
<i>enable</i>	Enable private data encryption using an AES 128-bit key.									
auto-auth-extension-device	Enable/disable automatic authorization of dedicated Fortinet extension devices.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable automatic authorization of dedicated Fortinet extension device globally.</td></tr><tr><td><i>disable</i></td><td>Disable automatic authorization of dedicated Fortinet extension device globally.</td></tr></table>		Option	Description	<i>enable</i>	Enable automatic authorization of dedicated Fortinet extension device globally.	<i>disable</i>	Disable automatic authorization of dedicated Fortinet extension device globally.		
Option	Description									
<i>enable</i>	Enable automatic authorization of dedicated Fortinet extension device globally.									
<i>disable</i>	Disable automatic authorization of dedicated Fortinet extension device globally.									
gui-theme	Color scheme for the administration GUI.	option	-	jade						

Parameter	Description	Type	Size	Default																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>jade</i></td><td>Jade theme.</td></tr><tr><td><i>neutrino</i></td><td>Neutrino theme.</td></tr><tr><td><i>mariner</i></td><td>Mariner theme.</td></tr><tr><td><i>graphite</i></td><td>Graphite theme.</td></tr><tr><td><i>melongene</i></td><td>Melongene theme.</td></tr><tr><td><i>retro</i></td><td>FortiProxy v3 Retro theme.</td></tr><tr><td><i>dark-matter</i></td><td>Dark Matter theme.</td></tr><tr><td><i>onyx</i></td><td>Onyx theme.</td></tr><tr><td><i>eclipse</i></td><td>Eclipse theme.</td></tr></table>	Option	Description	<i>jade</i>	Jade theme.	<i>neutrino</i>	Neutrino theme.	<i>mariner</i>	Mariner theme.	<i>graphite</i>	Graphite theme.	<i>melongene</i>	Melongene theme.	<i>retro</i>	FortiProxy v3 Retro theme.	<i>dark-matter</i>	Dark Matter theme.	<i>onyx</i>	Onyx theme.	<i>eclipse</i>	Eclipse theme.			
	Option	Description																						
	<i>jade</i>	Jade theme.																						
	<i>neutrino</i>	Neutrino theme.																						
	<i>mariner</i>	Mariner theme.																						
	<i>graphite</i>	Graphite theme.																						
	<i>melongene</i>	Melongene theme.																						
	<i>retro</i>	FortiProxy v3 Retro theme.																						
	<i>dark-matter</i>	Dark Matter theme.																						
	<i>onyx</i>	Onyx theme.																						
<i>eclipse</i>	Eclipse theme.																							
gui-date-format	Default date format used throughout GUI.	option	-	yyyy/MM/dd																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>yyyy/MM/dd</i></td><td>Year/Month/Day.</td></tr><tr><td><i>dd/MM/yyyy</i></td><td>Day/Month/Year.</td></tr><tr><td><i>MM/dd/yyyy</i></td><td>Month/Day/Year.</td></tr><tr><td><i>yyyy-MM-dd</i></td><td>Year-Month-Day.</td></tr><tr><td><i>dd-MM-yyyy</i></td><td>Day-Month-Year.</td></tr><tr><td><i>MM-dd-yyyy</i></td><td>Month-Day-Year.</td></tr></table>	Option	Description	<i>yyyy/MM/dd</i>	Year/Month/Day.	<i>dd/MM/yyyy</i>	Day/Month/Year.	<i>MM/dd/yyyy</i>	Month/Day/Year.	<i>yyyy-MM-dd</i>	Year-Month-Day.	<i>dd-MM-yyyy</i>	Day-Month-Year.	<i>MM-dd-yyyy</i>	Month-Day-Year.									
	Option	Description																						
	<i>yyyy/MM/dd</i>	Year/Month/Day.																						
	<i>dd/MM/yyyy</i>	Day/Month/Year.																						
	<i>MM/dd/yyyy</i>	Month/Day/Year.																						
	<i>yyyy-MM-dd</i>	Year-Month-Day.																						
	<i>dd-MM-yyyy</i>	Day-Month-Year.																						
	<i>MM-dd-yyyy</i>	Month-Day-Year.																						
gui-date-time-source	Source from which the FortiProxy GUI uses to display date and time entries.	option	-	system																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>system</i></td><td>Use this FortiProxy unit's configured timezone.</td></tr><tr><td><i>browser</i></td><td>Use the web browser's timezone.</td></tr></table>	Option	Description	<i>system</i>	Use this FortiProxy unit's configured timezone.	<i>browser</i>	Use the web browser's timezone.																	
	Option	Description																						
	<i>system</i>	Use this FortiProxy unit's configured timezone.																						
<i>browser</i>	Use the web browser's timezone.																							
igmp-state-limit	Maximum number of IGMP memberships (96 - 64000, default = 3200).	integer	Minimum value: 96 Maximum value: 128000	3200																				

Parameter	Description	Type	Size	Default
cloud-communication	Enable/disable all cloud communication.	option	-	enable
	Option	Description		
	<i>enable</i>	Allow cloud communication.		
	<i>disable</i>	Disable all cloud-related settings.		
ipsec-ha-seqjump-rate	ESP jump ahead rate (1G - 10G pps equivalent).	integer	Minimum value: 1 Maximum value: 10	10
fortitoken-cloud	Enable/disable FortiToken Cloud service.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable FortiToken Cloud service.		
	<i>disable</i>	Disable FortiToken Cloud service.		
faz-disk-buffer-size	Maximum disk buffer size to temporarily store logs destined for FortiAnalyzer. To be used in the event that FortiAnalyzer is unavailable.	integer	Not Specified	0
irq-time-accounting	Configure CPU IRQ time accounting mode.	option	-	auto
	Option	Description		
	<i>auto</i>	Automatically switch CPU accounting mode.		
	<i>force</i>	Force the use of CPU IRQ time accounting mode.		
management-ip	Management IP address of this FortiProxy. Used to log into this FortiProxy from another FortiProxy in the Security Fabric.	string	Maximum length: 255	

Parameter	Description	Type	Size	Default
management-port	Overriding port for management connection (Overrides admin port).	integer	Minimum value: 1 Maximum value: 65535	443
management-port-use-admin-sport	Enable/disable use of the admin-sport setting for the management port. If disabled, FortiGate will allow user to specify management-port.	option	-	enable
	Option		Description	
	<i>enable</i>		Enable use of the admin-sport setting for the management port.	
	<i>disable</i>		Disable use of the admin-sport setting for the management port.	
internet-service-database	Configure which Internet Service database size to download from FortiGuard and use.	option	-	full
	Option		Description	
	<i>mini</i>		Small sized Internet Service database with very limited IP addresses.	
	<i>standard</i>		Medium sized Internet Service database with most IP addresses.	
	<i>full</i>		Full sized Internet Service database with all IP addresses.	
	<i>on-demand</i>		Internet Service database with customer selected IP addresses.	
early-tcp-npu-session	Enable/disable early TCP NPU session.	option	-	disable
	Option		Description	
	<i>enable</i>		Enable early TCP NPU session in order to guarantee packet order of 3-way handshake.	

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable early TCP NPU session in order to guarantee packet order of 3-way handshake.		
interface-subnet-usage	Enable/disable allowing use of interface-subnet setting in firewall addresses (default = enable).	option	-	enable
	Option	Description		
	<i>disable</i>	Disallow use of the interface-subnet setting in firewall addresses. Use in conjunction with the FortiGate REST API and when a large number of firewall addresses exist in the configuration.		
	<i>enable</i>	Allow use of the interface-subnet setting in firewall addresses.		
sflowd-max-children-num	Maximum number of sflowd child processes allowed to run.	integer	Minimum value: 0 Maximum value: 6	6
license-overlimit	System behaviour when max licensed proxy user is reached.	option	-	bypass
	Option	Description		
	<i>bypass</i>	Bypass further traffic when licensed user is reached.		
	<i>block</i>	Block further traffic when licensed user is reached.		
max-session-per-user	Max UTM sessions per user.	integer	Minimum value: 0 Maximum value: 4294967295	0
conntrack	Max numbers of conntrack.	integer	Minimum value: 60000 Maximum value: 10000000	700000

Parameter	Description	Type	Size	Default
established-timeout	Default established session timeout (seconds).	integer	Minimum value: 10 Maximum value: 432000	1800
time-wait-timeout	Default time-wait timeout (seconds).	integer	Minimum value: 10 Maximum value: 432000	60
fin-wait-timeout	Default fin-wait timeout (seconds).	integer	Minimum value: 10 Maximum value: 432000	60
close-wait-timeout	Default close-wait timeout (seconds).	integer	Minimum value: 10 Maximum value: 432000	30
syn-sent-timeout	Default syn-sent timeout (seconds).	integer	Minimum value: 10 Maximum value: 432000	60
syn-recv-timeout	Default syn-recv timeout (seconds).	integer	Minimum value: 10 Maximum value: 432000	30
last-ack-timeout	Default last-ack timeout (seconds).	integer	Minimum value: 10 Maximum value: 432000	15
udp-timeout	Default last-ack timeout (seconds).	integer	Minimum value: 10 Maximum value: 432000	30
udp-stream-timeout	Default last-ack timeout (seconds).	integer	Minimum value: 10 Maximum value: 432000	180
username-case-sensitivity	Case sensitivity when performing username matching	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Check case when performing username matching		
	<i>disable</i>	Ignore case when performing username matching		
tcp-random-source-port	Disable/Enable TCP IPv4 random source port.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable source port randomness.		
	<i>disable</i>	Disable source port randomness.		

config system gre-tunnel

Configure GRE tunnel.

```

config system gre-tunnel
  Description: Configure GRE tunnel.
  edit <name>
    set interface {string}
    set remote-gw {ipv4-address}
    set local-gw {ipv4-address-any}
    set sequence-number-transmission [disable|enable]
    set sequence-number-reception [disable|enable]
    set checksum-transmission [disable|enable]
    set checksum-reception [disable|enable]
    set key-outbound {integer}
    set key-inbound {integer}
    set keepalive-interval {integer}
    set keepalive-failtimes {integer}
  next
end

```

config system gre-tunnel

Parameter	Description	Type	Size	Default
name	Tunnel name.	string	Maximum length: 15	
interface	Interface name.	string	Maximum length: 15	

Parameter	Description	Type	Size	Default						
remote-gw	IP address of the remote gateway.	ipv4-address	Not Specified	0.0.0.0						
local-gw	IP address of the local gateway.	ipv4-address-any	Not Specified	0.0.0.0						
sequence-number-transmission	Enable/disable including of sequence numbers in transmitted GRE packets.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Include sequence numbers in transmitted GRE packets.</td></tr><tr><td>enable</td><td>Do not include sequence numbers in transmitted GRE packets.</td></tr></table>	Option	Description	disable	Include sequence numbers in transmitted GRE packets.	enable	Do not include sequence numbers in transmitted GRE packets.			
Option	Description									
disable	Include sequence numbers in transmitted GRE packets.									
enable	Do not include sequence numbers in transmitted GRE packets.									
sequence-number-reception	Enable/disable validating sequence numbers in received GRE packets.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Do not validate sequence number in received GRE packets.</td></tr><tr><td>enable</td><td>Validate sequence numbers in received GRE packets.</td></tr></table>	Option	Description	disable	Do not validate sequence number in received GRE packets.	enable	Validate sequence numbers in received GRE packets.			
Option	Description									
disable	Do not validate sequence number in received GRE packets.									
enable	Validate sequence numbers in received GRE packets.									
checksum-transmission	Enable/disable including checksums in transmitted GRE packets.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Do not include checksums in transmitted GRE packets.</td></tr><tr><td>enable</td><td>Include checksums in transmitted GRE packets.</td></tr></table>	Option	Description	disable	Do not include checksums in transmitted GRE packets.	enable	Include checksums in transmitted GRE packets.			
Option	Description									
disable	Do not include checksums in transmitted GRE packets.									
enable	Include checksums in transmitted GRE packets.									
checksum-reception	Enable/disable validating checksums in received GRE packets.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Do not validate checksums in received GRE packets.</td></tr><tr><td>enable</td><td>Validate checksums in received GRE packets.</td></tr></table>	Option	Description	disable	Do not validate checksums in received GRE packets.	enable	Validate checksums in received GRE packets.			
Option	Description									
disable	Do not validate checksums in received GRE packets.									
enable	Validate checksums in received GRE packets.									
key-outbound	Include this key in transmitted GRE packets (0 - 4294967295).	integer	Minimum value: 0 Maximum value: 4294967295	0						

Parameter	Description	Type	Size	Default
key-inbound	Require received GRE packets contain this key (0 - 4294967295).	integer	Minimum value: 0 Maximum value: 4294967295	0
keepalive-interval	Keepalive message interval (0 - 32767, 0 = disabled).	integer	Minimum value: 0 Maximum value: 32767	0
keepalive-faultimes	Number of consecutive unreturned keepalive messages before a GRE connection is considered down (1 - 255).	integer	Minimum value: 1 Maximum value: 255	10

config system ha

Configure HA.

```

config system ha
    Description: Configure HA.
    set group-id {integer}
    set group-name {string}
    set mode [standalone|config-sync-only|...]
    set sync-packet-balance [enable|disable]
    set password {password}
    set key {password}
    set hbdev {user}
    set unicast-hb [enable|disable]
    set unicast-hb-peerip {ipv4-address}
    set unicast-hb-netmask {ipv4-netmask}
    set route-ttl {integer}
    set route-wait {integer}
    set route-hold {integer}
    set multicast-ttl {integer}
    set encryption [enable|disable]
    set authentication [enable|disable]
    set hb-interval {integer}
    set hb-interval-in-milliseconds [100ms|10ms]
    set hb-lost-threshold {integer}
    set hello-holddown {integer}
    set gratuitous-arps [enable|disable]
    set arps {integer}
    set arps-interval {integer}
    set link-failed-signal [enable|disable]
    set uninterruptible-upgrade [enable|disable]
    set sequential-upgrade [enable|disable]

```

```

set uninterruptible-primary-wait {integer}
set primary-hold-before-reboot {integer}
set ha-mgmt-status [enable|disable]
config ha-mgmt-interfaces
    Description: Reserve interfaces to manage individual cluster units.
    edit <id>
        set interface {string}
        set dst {ipv4-classnet}
        set gateway {ipv4-address}
        set gateway6 {ipv6-address}
    next
end
set ha-uptime-diff-margin {integer}
set unicast-status [enable|disable]
set unicast-gateway {ipv4-address}
config unicast-peers
    Description: Number of unicast peers.
    edit <id>
        set peer-ip {ipv4-address}
    next
end
set weight {user}
set cpu-threshold {user}
set memory-threshold {user}
set http-proxy-threshold {user}
set ftp-proxy-threshold {user}
set imap-proxy-threshold {user}
set nntp-proxy-threshold {user}
set pop3-proxy-threshold {user}
set smtp-proxy-threshold {user}
set override [enable|disable]
set priority {integer}
set override-wait-time {integer}
set monitor {user}
set pingserver-monitor-interface {user}
set pingserver-failover-threshold {integer}
set pingserver-secondary-force-reset [enable|disable]
set pingserver-flip-timeout {integer}
set vcluster-status [enable|disable]
config vcluster
    Description: Virtual cluster table.
    edit <vcluster-id>
        set override [enable|disable]
        set priority {integer}
        set override-wait-time {integer}
        set monitor {user}
        set pingserver-monitor-interface {user}
        set pingserver-failover-threshold {integer}
        set pingserver-secondary-force-reset [enable|disable]
        set vdom <name1>, <name2>, ...
    next
end

```

```

set ha-direct [enable|disable]
set ssd-failover [enable|disable]
set memory-compatible-mode [enable|disable]
set memory-based-failover [enable|disable]
set memory-failover-threshold {integer}
set memory-failover-monitor-period {integer}
set memory-failover-sample-rate {integer}
set memory-failover-flip-timeout {integer}
set failover-hold-time {integer}
end

```

config system ha

Parameter	Description	Type	Size	Default								
group-id	HA group ID (0 - 1023; or 0 - 7 when there are more than 2 vclusters). Must be the same for all members.	integer	Minimum value: 0 Maximum value: 1023	0								
group-name	Cluster group name. Must be the same for all members.	string	Maximum length: 32									
mode	HA mode. Must be the same for all members. FGSP requires standalone.	option	-	standalone								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>standalone</i></td><td>Disable HA feature.</td></tr><tr><td><i>config-sync-only</i></td><td>Enable Config sync only</td></tr><tr><td><i>active-passive</i></td><td>Enable Active-passive mode.</td></tr></table>	Option	Description	<i>standalone</i>	Disable HA feature.	<i>config-sync-only</i>	Enable Config sync only	<i>active-passive</i>	Enable Active-passive mode.			
Option	Description											
<i>standalone</i>	Disable HA feature.											
<i>config-sync-only</i>	Enable Config sync only											
<i>active-passive</i>	Enable Active-passive mode.											
sync-packet-balance	Enable/disable HA packet distribution to multiple CPUs.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable HA packet distribution to multiple CPUs.</td></tr><tr><td><i>disable</i></td><td>Disable HA packet distribution to multiple CPUs.</td></tr></table>	Option	Description	<i>enable</i>	Enable HA packet distribution to multiple CPUs.	<i>disable</i>	Disable HA packet distribution to multiple CPUs.					
Option	Description											
<i>enable</i>	Enable HA packet distribution to multiple CPUs.											
<i>disable</i>	Disable HA packet distribution to multiple CPUs.											
password	Cluster password. Must be the same for all members.	password	Not Specified									
key	Key.	password	Not Specified									
hbdev	Heartbeat interfaces. Must be the same for all members.	user	Not Specified									

Parameter	Description	Type	Size	Default						
unicast-hb	Enable/disable unicast heartbeat.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>				Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.
	Option	Description								
	<i>enable</i>	Enable setting.								
<i>disable</i>	Disable setting.									
unicast-hb-peerip	Unicast heartbeat peer IP.	ipv4-address	Not Specified	0.0.0.0						
unicast-hb-netmask	Unicast heartbeat netmask.	ipv4-netmask	Not Specified	0.0.0.0						
route-ttl	TTL for primary unit routes (5 - 3600 sec). Increase to maintain active routes during failover.	integer	Minimum value: 5 Maximum value: 3600	10						
route-wait	Time to wait before sending new routes to the cluster (0 - 3600 sec).	integer	Minimum value: 0 Maximum value: 3600	0						
route-hold	Time to wait between routing table updates to the cluster (0 - 3600 sec).	integer	Minimum value: 0 Maximum value: 3600	10						
multicast-ttl	HA multicast TTL on primary (5 - 3600 sec).	integer	Minimum value: 5 Maximum value: 3600	600						
encryption	Enable/disable heartbeat message encryption.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable heartbeat message encryption.</td></tr><tr><td><i>disable</i></td><td>Disable heartbeat message encryption.</td></tr></table>				Option	Description	<i>enable</i>	Enable heartbeat message encryption.	<i>disable</i>	Disable heartbeat message encryption.
	Option	Description								
	<i>enable</i>	Enable heartbeat message encryption.								
<i>disable</i>	Disable heartbeat message encryption.									
authentication	Enable/disable heartbeat message authentication.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable heartbeat message authentication.</td></tr><tr><td><i>disable</i></td><td>Disable heartbeat message authentication.</td></tr></table>				Option	Description	<i>enable</i>	Enable heartbeat message authentication.	<i>disable</i>	Disable heartbeat message authentication.
	Option	Description								
	<i>enable</i>	Enable heartbeat message authentication.								
<i>disable</i>	Disable heartbeat message authentication.									

Parameter	Description	Type	Size	Default
hb-interval	Time between sending heartbeat packets (1 - 20). Increase to reduce false positives.	integer	Minimum value: 1 Maximum value: 20	2
hb-interval-in-milliseconds	Number of milliseconds for each heartbeat interval: 100ms or 10ms.	option	-	100ms
	Option	Description		
	100ms	Each heartbeat interval is 100ms.		
	10ms	Each heartbeat interval is 10ms.		
hb-lost-threshold	Number of lost heartbeats to signal a failure (1 - 60). Increase to reduce false positives.	integer	Minimum value: 1 Maximum value: 60	20
hello-holddown	Time to wait before changing from hello to work state (5 - 300 sec).	integer	Minimum value: 5 Maximum value: 300	20
gratuitous-arps	Enable/disable gratuitous ARPs. Disable if link-failed-signal enabled.	option	-	enable
	Option	Description		
	enable	Enable gratuitous ARPs.		
	disable	Disable gratuitous ARPs.		
arps	Number of gratuitous ARPs (1 - 60). Lower to reduce traffic. Higher to reduce failover time.	integer	Minimum value: 1 Maximum value: 60	5
arps-interval	Time between gratuitous ARPs (1 - 20 sec). Lower to reduce failover time. Higher to reduce traffic.	integer	Minimum value: 1 Maximum value: 20	8
link-failed-signal	Enable to shut down all interfaces for 1 sec after a failover. Use if gratuitous ARPs do not update network.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
uninterruptible-upgrade	Enable to upgrade a cluster without blocking network traffic.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
sequential-upgrade	Enable to upgrade secondaries one by one.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
uninterruptible-primary-wait	Number of minutes the primary HA unit waits before the secondary HA unit is considered upgraded and the system is started before starting its own upgrade (15 - 300, default = 30).	integer	Minimum value: 15 Maximum value: 300	30
primary-hold-before-reboot	Number of seconds the primary HA unit waits after the secondary HA unit upgraded and joined back HA then starts its own upgrade (0 - 600, default = 0).	integer	Minimum value: 0 Maximum value: 600	0
ha-mgmt-status	Enable to reserve interfaces to manage individual cluster units.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
ha-uptime-diff-margin	Normally you would only reduce this value for failover testing.	integer	Minimum value: 1 Maximum value: 65535	300

Parameter	Description	Type	Size	Default
unicast-status	Enable/disable unicast connection.	option	-	disable
	Option	Description		
	enable	Enable setting.		
	disable	Disable setting.		
unicast-gateway	Default route gateway for unicast interface.	ipv4-address	Not Specified	0.0.0.0
weight	Weight-round-robin weight for each cluster unit. Syntax <priority> <weight>.	user	Not Specified	0 40
cpu-threshold	Dynamic weighted load balancing CPU usage weight and high and low thresholds.	user	Not Specified	
memory-threshold	Dynamic weighted load balancing memory usage weight and high and low thresholds.	user	Not Specified	
http-proxy-threshold	Dynamic weighted load balancing weight and high and low number of HTTP proxy sessions.	user	Not Specified	
ftp-proxy-threshold	Dynamic weighted load balancing weight and high and low number of FTP proxy sessions.	user	Not Specified	
imap-proxy-threshold	Dynamic weighted load balancing weight and high and low number of IMAP proxy sessions.	user	Not Specified	
nntp-proxy-threshold	Dynamic weighted load balancing weight and high and low number of NNTP proxy sessions.	user	Not Specified	
pop3-proxy-threshold	Dynamic weighted load balancing weight and high and low number of POP3 proxy sessions.	user	Not Specified	
smtp-proxy-threshold	Dynamic weighted load balancing weight and high and low number of SMTP proxy sessions.	user	Not Specified	
override	Enable and increase the priority of the unit that should always be primary (master).	option	-	disable

Parameter	Description	Type	Size	Default
	Option Description			
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
priority	Increase the priority to select the primary unit (0 - 255).	integer	Minimum value: 0 Maximum value: 255	128
override-wait-time	Delay negotiating if override is enabled (0 - 3600 sec). Reduces how often the cluster negotiates.	integer	Minimum value: 0 Maximum value: 3600	0
monitor	Interfaces to check for port monitoring (or link failure).	user	Not Specified	
pingserver-monitor-interface	Interfaces to check for remote IP monitoring.	user	Not Specified	
pingserver-failover-threshold	Remote IP monitoring failover threshold (0 - 50).	integer	Minimum value: 0 Maximum value: 50	0
pingserver-secondary-force-reset	Enable to force the cluster to negotiate after a remote IP monitoring failover.	option	-	enable
	Option Description			
	<i>enable</i>	Enable force reset of secondary member after PING server failure.		
	<i>disable</i>	Disable force reset of secondary member after PING server failure.		
pingserver-flip-timeout	Time to wait in minutes before renegotiating after a remote IP monitoring failover.	integer	Minimum value: 6 Maximum value: 2147483647	60
vcluster-status	Enable/disable virtual cluster for virtual clustering.	option	-	disable
	Option Description			
	<i>enable</i>	Enable setting.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable setting.		
ha-direct	Enable/disable using ha-mgmt interface for syslog, remote authentication (RADIUS), FortiAnalyzer, FortiSandbox.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable using ha-mgmt interface for syslog, SNMP, remote authentication (RADIUS), FortiAnalyzer, FortiSandbox.		
	<i>disable</i>	Disable using ha-mgmt interface for syslog, SNMP, remote authentication (RADIUS), FortiAnalyzer, FortiSandbox.		
ssd-failover	Enable/disable automatic HA failover on SSD disk failure.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
memory-compatible-mode	Enable/disable memory compatible mode.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
memory-based-failover	Enable/disable memory based failover.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
memory-failover-threshold	Memory usage threshold to trigger memory based failover (0 means using conserve mode threshold in system.global).	integer	Minimum value: 0 Maximum value: 95	0

Parameter	Description	Type	Size	Default
memory-failover-monitor-period	Duration of high memory usage before memory based failover is triggered in seconds (1 - 300, default = 60).	integer	Minimum value: 1 Maximum value: 300	60
memory-failover-sample-rate	Rate at which memory usage is sampled in order to measure memory usage in seconds (1 - 60, default = 1).	integer	Minimum value: 1 Maximum value: 60	1
memory-failover-flip-timeout	Time to wait between subsequent memory based failovers in minutes (6 - 2147483647, default = 6).	integer	Minimum value: 6 Maximum value: 2147483647	6
failover-hold-time	Time to wait before failover (0 - 300 sec, default = 0), to avoid flip.	integer	Minimum value: 0 Maximum value: 300	0

config ha-mgmt-interfaces

Parameter	Description	Type	Size	Default
id	Table ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
interface	Interface to reserve for HA management.	string	Maximum length: 15	
dst	Default route destination for reserved HA management interface.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0
gateway	Default route gateway for reserved HA management interface.	ipv4-address	Not Specified	0.0.0.0
gateway6	Default IPv6 gateway for reserved HA management interface.	ipv6-address	Not Specified	::

config unicast-peers

Parameter	Description	Type	Size	Default
id	Table ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
peer-ip	Unicast peer IP.	ipv4-address	Not Specified	0.0.0.0

config vcluster

Parameter	Description	Type	Size	Default
vcluster-id	ID.	integer	Minimum value: 1 Maximum value: 30	1
override	Enable and increase the priority of the unit that should always be primary (master).	option	-	disable
	Option	Description		
	enable	Enable setting.		
	disable	Disable setting.		
priority	Increase the priority to select the primary unit (0 - 255).	integer	Minimum value: 0 Maximum value: 255	128
override-wait-time	Delay negotiating if override is enabled (0 - 3600 sec). Reduces how often the cluster negotiates.	integer	Minimum value: 0 Maximum value: 3600	0
monitor	Interfaces to check for port monitoring (or link failure).	user	Not Specified	
pingserver-monitor-interface	Interfaces to check for remote IP monitoring.	user	Not Specified	

Parameter	Description	Type	Size	Default
pingserver-failover-threshold	Remote IP monitoring failover threshold (0 - 50).	integer	Minimum value: 0 Maximum value: 50	0
pingserver-secondary-force-reset	Enable to force the cluster to negotiate after a remote IP monitoring failover.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable force reset of secondary member after PING server failure.		
	<i>disable</i>	Disable force reset of secondary member after PING server failure.		
vdom <name>	Virtual domain(s) in the virtual cluster. Virtual domain name.	string	Maximum length: 79	

config system ha-lic

ha-lic

```
config system ha-lic
  Description: ha-lic
  edit <serial-num>
    set last-sync-time {password}
    set last-sync-seat {password}
    set last-sync-seat-fnbi {password}
    set last-sync-seat-fcas {password}
  next
end
```

config system ha-lic

Parameter	Description	Type	Size	Default
serial-num	The Serial Number that joined an HA cluster.	string	Maximum length: 16	
last-sync-time	Last time_t when SN updated the user seats.	password	Not Specified	
last-sync-seat	Last seats when SN updated the user seats.	password	Not Specified	

Parameter	Description	Type	Size	Default
last-sync-seat-fnbi	Last seats when SN updated the isolator seats.	password	Not Specified	
last-sync-seat-fcas	Last seats when SN updated the image AI seats.	password	Not Specified	

config system ha-monitor

Configure HA monitor.

```
config system ha-monitor
  Description: Configure HA monitor.
  set monitor-vlan [enable|disable]
  set vlan-hb-interval {integer}
  set vlan-hb-lost-threshold {integer}
end
```

config system ha-monitor

Parameter	Description	Type	Size	Default
monitor-vlan	Enable/disable monitor VLAN interfaces.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable monitor VLAN interfaces.		
	<i>disable</i>	Disable monitor VLAN interfaces.		
vlan-hb-interval	Configure heartbeat interval (seconds).	integer	Minimum value: 1 Maximum value: 30	5
vlan-hb-lost-threshold	VLAN lost heartbeat threshold (1 - 60).	integer	Minimum value: 1 Maximum value: 60	3

config system ha-nonsync-csum

System checksum for FortiManager use only.

```
config system ha-nonsync-csum
    Description: System checksum for FortiManager use only.
end
```

config system info admin ssh

Show SSH status.

```
config system info admin ssh
    Description: Show SSH status.
end
```

config system info admin status

Show logged in administrators.

```
config system info admin status
    Description: Show logged in administrators.
end
```

config system interface

Configure interfaces.

```
config system interface
    Description: Configure interfaces.
    edit <name>
        set vdom {string}
        set cli-conn-status {integer}
        set mode [static|dhcp|...]
        config client-options
            Description: DHCP client options.
            edit <id>
                set code {integer}
                set type [hex|string|...]
                set value {string}
                set ip {user}
            next
        end
        set distance {integer}
        set priority {integer}
        set dhcp-relay-interface-select-method [auto|specify]
        set dhcp-relay-interface {string}
        set dhcp-relay-service [disable|enable]
        set dhcp-relay-ip {user}
    end
```

```

set dhcp-relay-link-selection {ipv4-address}
set dhcp-relay-request-all-server [disable|enable]
set dhcp-relay-type [regular|ipsec]
set dhcp-relay-agent-option [enable|disable]
set dhcp-classless-route-addition [enable|disable]
set ip {ipv4-classnet-host}
set allowaccess {option1}, {option2}, ...
set gwdetect [enable|disable]
set ping-serv-status {integer}
set detectserver {user}
set detectprotocol {option1}, {option2}, ...
set ha-priority {integer}
set fail-detect [enable|disable]
set fail-detect-option {option1}, {option2}, ...
set fail-alert-method [link-failed-signal|link-down]
set fail-action-on-extender [soft-restart|hard-restart|...]
set fail-alert-interfaces <name1>, <name2>, ...
set dhcp-client-identifier {string}
set dhcp-renew-time {integer}
set ipunnumbered {ipv4-address}
set username {string}
set pppoe-unnumbered-negotiate [enable|disable]
set password {password}
set idle-timeout {integer}
set detected-peer-mtu {integer}
set disc-retry-timeout {integer}
set padt-retry-timeout {integer}
set service-name {string}
set ac-name {string}
set lcp-echo-interval {integer}
set lcp-max-echo-fails {integer}
set defaultgw [enable|disable]
set dns-server-override [enable|disable]
set dns-server-protocol {option1}, {option2}, ...
set auth-type [auto|pap|...]
set pptp-client [enable|disable]
set pptp-user {string}
set pptp-password {password}
set pptp-server-ip {ipv4-address}
set pptp-auth-type [auto|pap|...]
set pptp-timeout {integer}
set arpforward [enable|disable]
set broadcast-forward [enable|disable]
set bfd [global|enable|...]
set bfd-desired-min-tx {integer}
set bfd-detect-mult {integer}
set bfd-required-min-rx {integer}
set l2forward [enable|disable]
set icmp-send-redirect [enable|disable]
set icmp-accept-redirect [enable|disable]
set stpforward [enable|disable]
set stpforward-mode [rpl-all-ext-id|rpl-bridge-ext-id|...]

```

```

set macaddr {mac-address}
set substitute-dst-mac {mac-address}
set large-receive-offload [enable|disable]
set generic-receive-offload [enable|disable]
set speed [auto|10full|...]
set status [up|down]
set netbios-forward [disable|enable]
set wins-ip {ipv4-address}
set type [physical|vlan|...]
set dedicated-to [none|management]
set trust-ip-1 {ipv4-classnet-any}
set trust-ip-2 {ipv4-classnet-any}
set trust-ip-3 {ipv4-classnet-any}
set trust-ip6-1 {ipv6-prefix}
set trust-ip6-2 {ipv6-prefix}
set trust-ip6-3 {ipv6-prefix}
set ring-rx {integer}
set ring-tx {integer}
set wccp [enable|disable]
set drop-overlapped-fragment [enable|disable]
set drop-fragment [enable|disable]
set src-check [enable|disable]
set explicit-web-proxy [enable|disable]
set explicit-ftp-proxy [enable|disable]
set proxy-captive-portal [enable|disable]
set tcp-mss {integer}
set inbandwidth {integer}
set outbandwidth {integer}
set egress-shaping-profile {string}
set ingress-shaping-profile {string}
set disconnect-threshold {integer}
set spillover-threshold {integer}
set ingress-spillover-threshold {integer}
set weight {integer}
set interface {string}
set external [enable|disable]
set mtu-override [enable|disable]
set mtu {integer}
set vlan-protocol [8021q|8021ad]
set vlanid {integer}
set forward-domain {integer}
set remote-ip {ipv4-classnet-host}
set member <interface-name1>, <interface-name2>, ...
set lacp-mode {option}
set lacp-ha-secondary [enable|disable]
set system-id-type [auto|user]
set system-id {mac-address}
set lacp-speed [slow|fast]
set min-links {integer}
set min-links-down [operational|administrative]
set algorithm [L2|L3|...]
set link-up-delay {integer}

```



```

set aggregate-type [physical|vxlan]
set priority-override [enable|disable]
set aggregate {string}
set redundant-interface {string}
set devindex {integer}
set switch {string}
set description {var-string}
set alias {string}
set security-mode [none|captive-portal|...]
set security-mac-auth-bypass [mac-auth-only|enable|...]
set security-external-web {var-string}
set security-external-logout {string}
set replacemsg-override-group {string}
set security-redirect-url {var-string}
set auth-cert {string}
set auth-portal-addr {string}
set security-exempt-list {string}
set security-groups <name1>, <name2>, ...
set ike-saml-server {string}
set role [lan|wan|...]
set snmp-index {integer}
set secondary-IP [enable|disable]
config secondaryip
    Description: Second IP address of interface.
    edit <id>
        set ip {ipv4-classnet-host}
        set allowaccess {option1}, {option2}, ...
        set gwdetect [enable|disable]
        set ping-serv-status {integer}
        set detectserver {user}
        set detectprotocol {option1}, {option2}, ...
        set ha-priority {integer}
    next
end
set color {integer}
config tagging
    Description: Config object tagging.
    edit <name>
        set category {string}
        set tags <name1>, <name2>, ...
    next
end
set eap-supPLICant [enable|disable]
set eap-method [tls|peap]
set eap-identity {string}
set eap-password {password}
set eap-ca-cert {string}
set eap-user-cert {string}
config ipv6
    Description: IPv6 of interface.
    set ip6-mode [static|dhcp|...]
    set nd-mode [basic|SEND-compatible]

```

```

set nd-cert {string}
set nd-security-level {integer}
set nd-timestamp-delta {integer}
set nd-timestamp-fuzz {integer}
set nd-cga-modifier {user}
set ip6-dns-server-override [enable|disable]
set ip6-address {ipv6-prefix}
config ip6-extra-addr
    Description: Extra IPv6 address prefixes of interface.
    edit <prefix>
        next
    end
set ip6-allowaccess {option1}, {option2}, ...
set ip6-send-adv [enable|disable]
set icmp6-send-redirect [enable|disable]
set ip6-manage-flag [enable|disable]
set ip6-other-flag [enable|disable]
set ip6-max-interval {integer}
set ip6-min-interval {integer}
set ip6-link-mtu {integer}
set ra-send-mtu [enable|disable]
set ip6-reachable-time {integer}
set ip6-retrans-time {integer}
set ip6-default-life {integer}
set ip6-hop-limit {integer}
set autoconf [enable|disable]
set unique-autoconf-addr [enable|disable]
set interface-identifier {ipv6-address}
set ip6-prefix-mode [dhcp6|ra]
set ip6-delegated-prefix-iaid {integer}
set ip6-upstream-interface {string}
set ip6-subnet {ipv6-prefix}
config ip6-prefix-list
    Description: Advertised prefix list.
    edit <prefix>
        set autonomous-flag [enable|disable]
        set onlink-flag [enable|disable]
        set valid-life-time {integer}
        set preferred-life-time {integer}
        set rdns {user}
        set dnssl <domain1>, <domain2>, ...
    next
end
config ip6-delegated-prefix-list
    Description: Advertised IPv6 delegated prefix list.
    edit <prefix-id>
        set upstream-interface {string}
        set delegated-prefix-iaid {integer}
        set autonomous-flag [enable|disable]
        set onlink-flag [enable|disable]
        set subnet {ipv6-network}
        set rdns-service [delegated|default|...]

```

```

        set rdns {user}
    next
end
set dhcp6-relay-service [disable|enable]
set dhcp6-relay-type {option}
set dhcp6-relay-source-interface [disable|enable]
set dhcp6-relay-ip {user}
set dhcp6-client-options {option1}, {option2}, ...
set dhcp6-prefix-delegation [enable|disable]
set dhcp6-information-request [enable|disable]
config dhcp6-iapd-list
    Description: DHCPv6 IA-PD list.
    edit <iaid>
        set prefix-hint {ipv6-network}
        set prefix-hint-plt {integer}
        set prefix-hint-vlt {integer}
    next
end
set cli-conn6-status {integer}
end
next
end

```

config system interface

Parameter	Description	Type	Size	Default								
name	Name.	string	Maximum length: 15									
vdom	Interface is in this virtual domain (VDOM).	string	Maximum length: 31									
cli-conn-status	CLI connection status.	integer	Minimum value: 0 Maximum value: 4294967295	0								
mode	Addressing mode (static, DHCP, PPPoE).	option	-	static								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>static</i></td><td>Static setting.</td></tr><tr><td><i>dhcp</i></td><td>External DHCP client mode.</td></tr><tr><td><i>pppoe</i></td><td>External PPPoE mode.</td></tr></table>				Option	Description	<i>static</i>	Static setting.	<i>dhcp</i>	External DHCP client mode.	<i>pppoe</i>	External PPPoE mode.
Option	Description											
<i>static</i>	Static setting.											
<i>dhcp</i>	External DHCP client mode.											
<i>pppoe</i>	External PPPoE mode.											

Parameter	Description	Type	Size	Default
distance	Distance for routes learned through PPPoE or DHCP, lower distance indicates preferred route.	integer	Minimum value: 1 Maximum value: 255	5
priority	Priority of learned routes.	integer	Minimum value: 1 Maximum value: 65535	0
dhcp-relay-interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto
	Option		Description	
	<i>auto</i>		Set outgoing interface automatically.	
	<i>specify</i>		Set outgoing interface manually.	
dhcp-relay-interface	Specify outgoing interface to reach server.	string	Maximum length: 15	
dhcp-relay-service	Enable/disable allowing this interface to act as a DHCP relay.	option	-	disable
	Option		Description	
	<i>disable</i>		None.	
	<i>enable</i>		DHCP relay agent.	
dhcp-relay-ip	DHCP relay IP address.	user	Not Specified	
dhcp-relay-link-selection	DHCP relay link selection.	ipv4-address	Not Specified	0.0.0.0
dhcp-relay-request-all-server	Enable/disable sending of DHCP requests to all servers.	option	-	disable
	Option		Description	
	<i>disable</i>		Send DHCP requests only to a matching server.	
	<i>enable</i>		Send DHCP requests to all servers.	
dhcp-relay-type	DHCP relay type (regular or IPsec).	option	-	regular

Parameter	Description	Type	Size	Default																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>regular</i></td><td>Regular DHCP relay.</td></tr><tr><td><i>ipsec</i></td><td>DHCP relay for IPsec.</td></tr></table>	Option	Description	<i>regular</i>	Regular DHCP relay.	<i>ipsec</i>	DHCP relay for IPsec.															
	Option	Description																				
	<i>regular</i>	Regular DHCP relay.																				
<i>ipsec</i>	DHCP relay for IPsec.																					
dhcp-relay-agent-option	Enable/disable DHCP relay agent option.	option	-	enable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable DHCP relay agent option.</td></tr><tr><td><i>disable</i></td><td>Disable DHCP relay agent option.</td></tr></table>	Option	Description	<i>enable</i>	Enable DHCP relay agent option.	<i>disable</i>	Disable DHCP relay agent option.															
	Option	Description																				
	<i>enable</i>	Enable DHCP relay agent option.																				
<i>disable</i>	Disable DHCP relay agent option.																					
dhcp-classless-route-addition	Enable/disable addition of classless static routes retrieved from DHCP server.	option	-	disable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable addition of classless static routes retrieved from DHCP server.</td></tr><tr><td><i>disable</i></td><td>Disable addition of classless static routes retrieved from DHCP server.</td></tr></table>	Option	Description	<i>enable</i>	Enable addition of classless static routes retrieved from DHCP server.	<i>disable</i>	Disable addition of classless static routes retrieved from DHCP server.															
	Option	Description																				
	<i>enable</i>	Enable addition of classless static routes retrieved from DHCP server.																				
<i>disable</i>	Disable addition of classless static routes retrieved from DHCP server.																					
ip	Interface IPv4 address and subnet mask, syntax: X.X.X.X/24.	ipv4-classnet-host	Not Specified	0.0.0.0 0.0.0.0																		
allowaccess	Permitted types of management access to this interface.	option	-																			
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ping</i></td><td>PING access.</td></tr><tr><td><i>https</i></td><td>HTTPS access.</td></tr><tr><td><i>ssh</i></td><td>SSH access.</td></tr><tr><td><i>snmp</i></td><td>SNMP access.</td></tr><tr><td><i>http</i></td><td>HTTP access.</td></tr><tr><td><i>telnet</i></td><td>TELNET access.</td></tr><tr><td><i>fgfm</i></td><td>FortiManager access.</td></tr><tr><td><i>radius-acct</i></td><td>RADIUS accounting access.</td></tr></table>	Option	Description	<i>ping</i>	PING access.	<i>https</i>	HTTPS access.	<i>ssh</i>	SSH access.	<i>snmp</i>	SNMP access.	<i>http</i>	HTTP access.	<i>telnet</i>	TELNET access.	<i>fgfm</i>	FortiManager access.	<i>radius-acct</i>	RADIUS accounting access.			
	Option	Description																				
	<i>ping</i>	PING access.																				
	<i>https</i>	HTTPS access.																				
	<i>ssh</i>	SSH access.																				
	<i>snmp</i>	SNMP access.																				
	<i>http</i>	HTTP access.																				
	<i>telnet</i>	TELNET access.																				
<i>fgfm</i>	FortiManager access.																					
<i>radius-acct</i>	RADIUS accounting access.																					

Parameter	Description	Type	Size	Default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>probe-response</i></td><td>Probe access.</td></tr><tr><td><i>fabric</i></td><td>Security Fabric access.</td></tr><tr><td><i>ftm</i></td><td>FTM access.</td></tr><tr><td><i>speed-test</i></td><td>Speed test access.</td></tr></table>	Option	Description	<i>probe-response</i>	Probe access.	<i>fabric</i>	Security Fabric access.	<i>ftm</i>	FTM access.	<i>speed-test</i>	Speed test access.			
	Option	Description												
	<i>probe-response</i>	Probe access.												
	<i>fabric</i>	Security Fabric access.												
	<i>ftm</i>	FTM access.												
<i>speed-test</i>	Speed test access.													
gwdetect	Enable/disable detect gateway alive for first.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable detect gateway alive for first.</td></tr><tr><td><i>disable</i></td><td>Disable detect gateway alive for first.</td></tr></table>	Option	Description	<i>enable</i>	Enable detect gateway alive for first.	<i>disable</i>	Disable detect gateway alive for first.							
	Option	Description												
	<i>enable</i>	Enable detect gateway alive for first.												
<i>disable</i>	Disable detect gateway alive for first.													
ping-serv-status	PING server status.	integer	Minimum value: 0 Maximum value: 255	0										
detectserver	Gateway's ping server for this IP.	user	Not Specified											
detectprotocol	Protocols used to detect the server.	option	-	ping										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ping</i></td><td>PING.</td></tr><tr><td><i>tcp-echo</i></td><td>TCP echo.</td></tr><tr><td><i>udp-echo</i></td><td>UDP echo.</td></tr></table>	Option	Description	<i>ping</i>	PING.	<i>tcp-echo</i>	TCP echo.	<i>udp-echo</i>	UDP echo.					
	Option	Description												
	<i>ping</i>	PING.												
	<i>tcp-echo</i>	TCP echo.												
<i>udp-echo</i>	UDP echo.													
ha-priority	HA election priority for the PING server.	integer	Minimum value: 1 Maximum value: 50	1										
fail-detect	Enable/disable fail detection features for this interface.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable interface failed option status.</td></tr><tr><td><i>disable</i></td><td>Disable interface failed option status.</td></tr></table>	Option	Description	<i>enable</i>	Enable interface failed option status.	<i>disable</i>	Disable interface failed option status.							
	Option	Description												
	<i>enable</i>	Enable interface failed option status.												
<i>disable</i>	Disable interface failed option status.													

Parameter	Description	Type	Size	Default								
fail-detect-option	Options for detecting that this interface has failed.	option	-	link-down								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>detectserver</i></td><td>Use a ping server to determine if the interface has failed.</td></tr><tr><td><i>link-down</i></td><td>Use port detection to determine if the interface has failed.</td></tr></table>	Option	Description	<i>detectserver</i>	Use a ping server to determine if the interface has failed.	<i>link-down</i>	Use port detection to determine if the interface has failed.					
Option	Description											
<i>detectserver</i>	Use a ping server to determine if the interface has failed.											
<i>link-down</i>	Use port detection to determine if the interface has failed.											
fail-alert-method	Select link-failed-signal or link-down method to alert about a failed link.	option	-	link-down								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>link-failed-signal</i></td><td>Link-failed-signal.</td></tr><tr><td><i>link-down</i></td><td>Link-down.</td></tr></table>	Option	Description	<i>link-failed-signal</i>	Link-failed-signal.	<i>link-down</i>	Link-down.					
Option	Description											
<i>link-failed-signal</i>	Link-failed-signal.											
<i>link-down</i>	Link-down.											
fail-action-on-extender	Action on FortiExtender when interface fail.	option	-	soft-restart								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>soft-restart</i></td><td>Soft-restart-on-extender.</td></tr><tr><td><i>hard-restart</i></td><td>Hard-restart-on-extender.</td></tr><tr><td><i>reboot</i></td><td>Reboot-on-extender.</td></tr></table>	Option	Description	<i>soft-restart</i>	Soft-restart-on-extender.	<i>hard-restart</i>	Hard-restart-on-extender.	<i>reboot</i>	Reboot-on-extender.			
Option	Description											
<i>soft-restart</i>	Soft-restart-on-extender.											
<i>hard-restart</i>	Hard-restart-on-extender.											
<i>reboot</i>	Reboot-on-extender.											
fail-alert-interfaces <name>	Names of the FortiProxy interfaces to which the link failure alert is sent. Names of the non-virtual interface.	string	Maximum length: 15									
dhcp-client-identifier	DHCP client identifier.	string	Maximum length: 48									
dhcp-renew-time	DHCP renew time in seconds (300-604800), 0 means use the renew time provided by the server.	integer	Minimum value: 300 Maximum value: 604800	0								
ipunnumbered	Unnumbered IP used for PPPoE interfaces for which no unique local address is provided.	ipv4-address	Not Specified	0.0.0.0								

Parameter	Description	Type	Size	Default						
username	Username of the PPPoE account, provided by your ISP.	string	Maximum length: 64							
pppoe-unnumbered-negotiate	Enable/disable PPPoE unnumbered negotiation.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable IP address negotiating for unnumbered.</td></tr><tr><td><i>disable</i></td><td>Disable IP address negotiating for unnumbered.</td></tr></table>				Option	Description	<i>enable</i>	Enable IP address negotiating for unnumbered.	<i>disable</i>	Disable IP address negotiating for unnumbered.
	Option	Description								
	<i>enable</i>	Enable IP address negotiating for unnumbered.								
<i>disable</i>	Disable IP address negotiating for unnumbered.									
password	PPPoE account's password.	password	Not Specified							
idle-timeout	PPPoE auto disconnect after idle timeout seconds, 0 means no timeout.	integer	Minimum value: 0 Maximum value: 32767	0						
detected-peer-mtu	MTU of detected peer (0 - 4294967295).	integer	Minimum value: 0 Maximum value: 4294967295	0						
disc-retry-timeout	Time in seconds to wait before retrying to start a PPPoE discovery, 0 means no timeout.	integer	Minimum value: 0 Maximum value: 4294967295	1						
padt-retry-timeout	PPPoE Active Discovery Terminate (PADT) used to terminate sessions after an idle time.	integer	Minimum value: 0 Maximum value: 4294967295	1						
service-name	PPPoE service name.	string	Maximum length: 63							
ac-name	PPPoE server name.	string	Maximum length: 63							
lcp-echo-interval	Time in seconds between PPPoE Link Control Protocol (LCP) echo requests.	integer	Minimum value: 0 Maximum value: 32767	5						

Parameter	Description	Type	Size	Default												
lcp-max-echo-fails	Maximum missed LCP echo messages before disconnect.	integer	Minimum value: 0 Maximum value: 32767	3												
defaultgw	Enable to get the gateway IP from the DHCP or PPPoE server.	option	-	enable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable default gateway.</td></tr><tr><td><i>disable</i></td><td>Disable default gateway.</td></tr></table>	Option	Description	<i>enable</i>	Enable default gateway.	<i>disable</i>	Disable default gateway.									
Option	Description															
<i>enable</i>	Enable default gateway.															
<i>disable</i>	Disable default gateway.															
dns-server-override	Enable/disable use DNS acquired by DHCP or PPPoE.	option	-	enable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Use DNS acquired by DHCP or PPPoE.</td></tr><tr><td><i>disable</i></td><td>No not use DNS acquired by DHCP or PPPoE.</td></tr></table>	Option	Description	<i>enable</i>	Use DNS acquired by DHCP or PPPoE.	<i>disable</i>	No not use DNS acquired by DHCP or PPPoE.									
Option	Description															
<i>enable</i>	Use DNS acquired by DHCP or PPPoE.															
<i>disable</i>	No not use DNS acquired by DHCP or PPPoE.															
dns-server-protocol	DNS transport protocols.	option	-	cleartext												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>cleartext</i></td><td>DNS over UDP/53, DNS over TCP/53.</td></tr><tr><td><i>dot</i></td><td>DNS over TLS/853.</td></tr><tr><td><i>doh</i></td><td>DNS over HTTPS/443.</td></tr></table>	Option	Description	<i>cleartext</i>	DNS over UDP/53, DNS over TCP/53.	<i>dot</i>	DNS over TLS/853.	<i>doh</i>	DNS over HTTPS/443.							
Option	Description															
<i>cleartext</i>	DNS over UDP/53, DNS over TCP/53.															
<i>dot</i>	DNS over TLS/853.															
<i>doh</i>	DNS over HTTPS/443.															
auth-type	PPP authentication type to use.	option	-	auto												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Automatically choose authentication.</td></tr><tr><td><i>pap</i></td><td>PAP authentication.</td></tr><tr><td><i>chap</i></td><td>CHAP authentication.</td></tr><tr><td><i>mschapv1</i></td><td>MS-CHAPv1 authentication.</td></tr><tr><td><i>mschapv2</i></td><td>MS-CHAPv2 authentication.</td></tr></table>	Option	Description	<i>auto</i>	Automatically choose authentication.	<i>pap</i>	PAP authentication.	<i>chap</i>	CHAP authentication.	<i>mschapv1</i>	MS-CHAPv1 authentication.	<i>mschapv2</i>	MS-CHAPv2 authentication.			
Option	Description															
<i>auto</i>	Automatically choose authentication.															
<i>pap</i>	PAP authentication.															
<i>chap</i>	CHAP authentication.															
<i>mschapv1</i>	MS-CHAPv1 authentication.															
<i>mschapv2</i>	MS-CHAPv2 authentication.															
pptp-client	Enable/disable PPTP client.	option	-	disable												

Parameter	Description	Type	Size	Default
	Option Description			
	<i>enable</i>	Enable PPTP client.		
	<i>disable</i>	Disable PPTP client.		
pptp-user	PPTP user name.	string	Maximum length: 64	
pptp-password	PPTP password.	password	Not Specified	
pptp-server-ip	PPTP server IP address.	ipv4-address	Not Specified	0.0.0.0
pptp-auth-type	PPTP authentication type.	option	-	auto
	Option Description			
	<i>auto</i>	Automatically choose authentication.		
	<i>pap</i>	PAP authentication.		
	<i>chap</i>	CHAP authentication.		
	<i>mschapv1</i>	MS-CHAPv1 authentication.		
	<i>mschapv2</i>	MS-CHAPv2 authentication.		
pptp-timeout	Idle timer in minutes (0 for disabled).	integer	Minimum value: 0 Maximum value: 65535	0
arpforward	Enable/disable ARP forwarding.	option	-	enable
	Option Description			
	<i>enable</i>	Enable ARP forwarding.		
	<i>disable</i>	Disable ARP forwarding.		
broadcast-forward	Enable/disable broadcast forwarding.	option	-	disable
	Option Description			
	<i>enable</i>	Enable broadcast forwarding.		
	<i>disable</i>	Disable broadcast forwarding.		
bfd	Bidirectional Forwarding Detection (BFD) settings.	option	-	global

Parameter	Description	Type	Size	Default
	Option	Description		
	global	BFD behavior of this interface will be based on global configuration.		
	enable	Enable BFD on this interface and ignore global configuration.		
	disable	Disable BFD on this interface and ignore global configuration.		
bfd-desired-min-tx	BFD desired minimal transmit interval.	integer	Minimum value: 1 Maximum value: 100000	250
bfd-detect-mult	BFD detection multiplier.	integer	Minimum value: 1 Maximum value: 50	3
bfd-required-min-rx	BFD required minimal receive interval.	integer	Minimum value: 1 Maximum value: 100000	250
l2forward	Enable/disable l2 forwarding.	option	-	disable
	Option	Description		
	enable	Enable L2 forwarding.		
	disable	Disable L2 forwarding.		
icmp-send-redirect	Enable/disable sending of ICMP redirects.	option	-	enable
	Option	Description		
	enable	Enable sending of ICMP redirects.		
	disable	Disable sending of ICMP redirects.		
icmp-accept-redirect	Enable/disable ICMP accept redirect.	option	-	enable
	Option	Description		
	enable	Enable ICMP accept redirect.		
	disable	Disable ICMP accept redirect.		

Parameter	Description	Type	Size	Default								
stpforward	Enable/disable STP forwarding.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable STP forwarding.</td></tr><tr><td><i>disable</i></td><td>Disable STP forwarding.</td></tr></table>	Option	Description	<i>enable</i>	Enable STP forwarding.	<i>disable</i>	Disable STP forwarding.					
Option	Description											
<i>enable</i>	Enable STP forwarding.											
<i>disable</i>	Disable STP forwarding.											
stpforward-mode	Configure STP forwarding mode.	option	-	rpl-all-ext-id								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>rpl-all-ext-id</i></td><td>Replace all extension IDs (root, bridge).</td></tr><tr><td><i>rpl-bridge-ext-id</i></td><td>Replace the bridge extension ID only.</td></tr><tr><td><i>rpl-nothing</i></td><td>Replace nothing.</td></tr></table>	Option	Description	<i>rpl-all-ext-id</i>	Replace all extension IDs (root, bridge).	<i>rpl-bridge-ext-id</i>	Replace the bridge extension ID only.	<i>rpl-nothing</i>	Replace nothing.			
Option	Description											
<i>rpl-all-ext-id</i>	Replace all extension IDs (root, bridge).											
<i>rpl-bridge-ext-id</i>	Replace the bridge extension ID only.											
<i>rpl-nothing</i>	Replace nothing.											
macaddr	Change the interface's MAC address.	mac-address	Not Specified	00:00:00:00:00:00								
substitute-dst-mac	Destination MAC address that all packets are sent to from this interface.	mac-address	Not Specified	00:00:00:00:00:00								
large-receive-offload	Enable/disable large-receive-offload.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable large-receive-offload.</td></tr><tr><td><i>disable</i></td><td>Disable large-receive-offload.</td></tr></table>	Option	Description	<i>enable</i>	Enable large-receive-offload.	<i>disable</i>	Disable large-receive-offload.					
Option	Description											
<i>enable</i>	Enable large-receive-offload.											
<i>disable</i>	Disable large-receive-offload.											
generic-receive-offload	Enable/disable generic-receive-offload.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable generic-receive-offload.</td></tr><tr><td><i>disable</i></td><td>Disable generic-receive-offload.</td></tr></table>	Option	Description	<i>enable</i>	Enable generic-receive-offload.	<i>disable</i>	Disable generic-receive-offload.					
Option	Description											
<i>enable</i>	Enable generic-receive-offload.											
<i>disable</i>	Disable generic-receive-offload.											
speed	Interface speed. The default setting and the options available depend on the interface hardware.	option	-	auto								

Parameter	Description	Type	Size	Default																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Automatically adjust speed.</td></tr><tr><td><i>10full</i></td><td>10M full-duplex.</td></tr><tr><td><i>10half</i></td><td>10M half-duplex.</td></tr><tr><td><i>100full</i></td><td>100M full-duplex.</td></tr><tr><td><i>100half</i></td><td>100M half-duplex.</td></tr><tr><td><i>1000full</i></td><td>1000M full-duplex.</td></tr><tr><td><i>1000auto</i></td><td>1000M auto adjust.</td></tr></table>	Option	Description	<i>auto</i>	Automatically adjust speed.	<i>10full</i>	10M full-duplex.	<i>10half</i>	10M half-duplex.	<i>100full</i>	100M full-duplex.	<i>100half</i>	100M half-duplex.	<i>1000full</i>	1000M full-duplex.	<i>1000auto</i>	1000M auto adjust.					
	Option	Description																				
	<i>auto</i>	Automatically adjust speed.																				
	<i>10full</i>	10M full-duplex.																				
	<i>10half</i>	10M half-duplex.																				
	<i>100full</i>	100M full-duplex.																				
	<i>100half</i>	100M half-duplex.																				
	<i>1000full</i>	1000M full-duplex.																				
<i>1000auto</i>	1000M auto adjust.																					
status	Bring the interface up or shut the interface down.	option	-	up																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>up</i></td><td>Bring the interface up.</td></tr><tr><td><i>down</i></td><td>Shut the interface down.</td></tr></table>	Option	Description	<i>up</i>	Bring the interface up.	<i>down</i>	Shut the interface down.															
	Option	Description																				
	<i>up</i>	Bring the interface up.																				
<i>down</i>	Shut the interface down.																					
netbios-forward	Enable/disable NETBIOS forwarding.	option	-	disable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable NETBIOS forwarding.</td></tr><tr><td><i>enable</i></td><td>Enable NETBIOS forwarding.</td></tr></table>	Option	Description	<i>disable</i>	Disable NETBIOS forwarding.	<i>enable</i>	Enable NETBIOS forwarding.															
	Option	Description																				
	<i>disable</i>	Disable NETBIOS forwarding.																				
<i>enable</i>	Enable NETBIOS forwarding.																					
wins-ip	WINS server IP.	ipv4-address	Not Specified	0.0.0.0																		
type	Interface type.	option	-	vlan																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>physical</i></td><td>Physical interface.</td></tr><tr><td><i>vlan</i></td><td>VLAN interface.</td></tr><tr><td><i>aggregate</i></td><td>Aggregate interface.</td></tr><tr><td><i>redundant</i></td><td>Redundant interface.</td></tr><tr><td><i>tunnel</i></td><td>Tunnel interface.</td></tr><tr><td><i>loopback</i></td><td>Loopback interface.</td></tr><tr><td><i>vdom-link</i></td><td>VDOM link interface.</td></tr><tr><td><i>vxlan</i></td><td>VXLAN interface.</td></tr></table>	Option	Description	<i>physical</i>	Physical interface.	<i>vlan</i>	VLAN interface.	<i>aggregate</i>	Aggregate interface.	<i>redundant</i>	Redundant interface.	<i>tunnel</i>	Tunnel interface.	<i>loopback</i>	Loopback interface.	<i>vdom-link</i>	VDOM link interface.	<i>vxlan</i>	VXLAN interface.			
	Option	Description																				
	<i>physical</i>	Physical interface.																				
	<i>vlan</i>	VLAN interface.																				
	<i>aggregate</i>	Aggregate interface.																				
	<i>redundant</i>	Redundant interface.																				
	<i>tunnel</i>	Tunnel interface.																				
	<i>loopback</i>	Loopback interface.																				
<i>vdom-link</i>	VDOM link interface.																					
<i>vxlan</i>	VXLAN interface.																					

Parameter	Description	Type	Size	Default						
dedicated-to	Configure interface for single purpose.	option	-	none						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>none</i></td><td>Interface not dedicated for any purpose.</td></tr><tr><td><i>management</i></td><td>Dedicate this interface for management purposes only.</td></tr></table>	Option	Description	<i>none</i>	Interface not dedicated for any purpose.	<i>management</i>	Dedicate this interface for management purposes only.			
Option	Description									
<i>none</i>	Interface not dedicated for any purpose.									
<i>management</i>	Dedicate this interface for management purposes only.									
trust-ip-1	Trusted host for dedicated management traffic (0.0.0.0/24 for all hosts).	ipv4-classnet-any	Not Specified	0.0.0.0 0.0.0.0						
trust-ip-2	Trusted host for dedicated management traffic (0.0.0.0/24 for all hosts).	ipv4-classnet-any	Not Specified	0.0.0.0 0.0.0.0						
trust-ip-3	Trusted host for dedicated management traffic (0.0.0.0/24 for all hosts).	ipv4-classnet-any	Not Specified	0.0.0.0 0.0.0.0						
trust-ip6-1	Trusted IPv6 host for dedicated management traffic (::/0 for all hosts).	ipv6-prefix	Not Specified	::/0						
trust-ip6-2	Trusted IPv6 host for dedicated management traffic (::/0 for all hosts).	ipv6-prefix	Not Specified	::/0						
trust-ip6-3	Trusted IPv6 host for dedicated management traffic (::/0 for all hosts).	ipv6-prefix	Not Specified	::/0						
ring-rx	RX ring size.	integer	Minimum value: 0 Maximum value: 4294967295	0						
ring-tx	TX ring size.	integer	Minimum value: 0 Maximum value: 4294967295	0						
wccp	Enable/disable WCCP on this interface. Used for encapsulated WCCP communication between WCCP clients and servers.	option	-	disable						

Parameter	Description	Type	Size	Default
	Option Description			
	<i>enable</i>	Enable WCCP protocol on this interface.		
	<i>disable</i>	Disable WCCP protocol on this interface.		
drop-overlapped-fragment	Enable/disable drop overlapped fragment packets.	option	-	disable
	Option Description			
	<i>enable</i>	Enable drop of overlapped fragment packets.		
	<i>disable</i>	Disable drop of overlapped fragment packets.		
drop-fragment	Enable/disable drop fragment packets.	option	-	disable
	Option Description			
	<i>enable</i>	Enable/disable drop fragment packets.		
	<i>disable</i>	Do not drop fragment packets.		
src-check	Enable/disable source IP check.	option	-	enable
	Option Description			
	<i>enable</i>	Enable source IP check.		
	<i>disable</i>	Disable source IP check.		
explicit-web-proxy	Enable/disable the explicit web proxy on this interface.	option	-	disable
	Option Description			
	<i>enable</i>	Enable explicit Web proxy on this interface.		
	<i>disable</i>	Disable explicit Web proxy on this interface.		
explicit-ftp-proxy	Enable/disable the explicit FTP proxy on this interface.	option	-	disable
	Option Description			
	<i>enable</i>	Enable explicit FTP proxy on this interface.		
	<i>disable</i>	Disable explicit FTP proxy on this interface.		

Parameter	Description	Type	Size	Default
proxy-captive-portal	Enable/disable proxy captive portal on this interface.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable proxy captive portal on this interface.		
	<i>disable</i>	Disable proxy captive portal on this interface.		
tcp-mss	TCP maximum segment size. 0 means do not change segment size.	integer	Minimum value: 48 Maximum value: 65535	0
inbandwidth	Bandwidth limit for incoming traffic (0 - 80000000 kbps), 0 means unlimited.	integer	Minimum value: 0 Maximum value: 80000000	0
outbandwidth	Bandwidth limit for outgoing traffic (0 - 80000000 kbps).	integer	Minimum value: 0 Maximum value: 80000000	0
egress-shaping-profile	Outgoing traffic shaping profile.	string	Maximum length: 35	
ingress-shaping-profile	Incoming traffic shaping profile.	string	Maximum length: 35	
disconnect-threshold	Time in milliseconds to wait before sending a notification that this interface is down or disconnected.	integer	Minimum value: 0 Maximum value: 10000	0
spillover-threshold	Egress Spillover threshold (0 - 16776000 kbps), 0 means unlimited.	integer	Minimum value: 0 Maximum value: 16776000	0
ingress-spillover-threshold	Ingress Spillover threshold (0 - 16776000 kbps), 0 means unlimited.	integer	Minimum value: 0 Maximum value: 16776000	0

Parameter	Description	Type	Size	Default
weight	Default weight for static routes (if route has no weight configured).	integer	Minimum value: 0 Maximum value: 255	0
interface	Interface name.	string	Maximum length: 15	
external	Enable/disable identifying the interface as an external interface (which usually means it's connected to the Internet).	option	-	disable
	Option		Description	
	<i>enable</i>		Enable identifying the interface as an external interface.	
	<i>disable</i>		Disable identifying the interface as an external interface.	
mtu-override	Enable to set a custom MTU for this interface.	option	-	disable
	Option		Description	
	<i>enable</i>		Override default MTU.	
	<i>disable</i>		Use default MTU.	
mtu	MTU value for this interface.	integer	Minimum value: 0 Maximum value: 4294967295	1500
vlan-protocol	Ethernet protocol of VLAN.	option	-	8021q
	Option		Description	
	<i>8021q</i>		IEEE 802.1Q.	
	<i>8021ad</i>		IEEE 802.1AD.	
vlanid	VLAN ID (1 - 4094).	integer	Minimum value: 1 Maximum value: 4094	0
forward-domain	Transparent mode forward domain.	integer	Minimum value: 1 Maximum value: 4094	1

Parameter	Description	Type	Size	Default						
remote-ip	Remote IP address of tunnel.	ipv4-classnet-host	Not Specified	0.0.0.0 0.0.0.0						
member <interface-name>	Physical interfaces that belong to the aggregate or redundant interface. Physical interface name.	string	Maximum length: 79							
lACP-mode	LACP mode.	option	-							
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>static</i></td><td>Use static aggregation, do not send and ignore any LACP messages.</td></tr></table>				Option	Description	<i>static</i>	Use static aggregation, do not send and ignore any LACP messages.		
Option	Description									
<i>static</i>	Use static aggregation, do not send and ignore any LACP messages.									
lACP-ha-secondary	LACP HA secondary member.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Allow HA secondary member to send/receive LACP messages.</td></tr><tr><td><i>disable</i></td><td>Block HA secondary member from sending/receiving LACP messages.</td></tr></table>				Option	Description	<i>enable</i>	Allow HA secondary member to send/receive LACP messages.	<i>disable</i>	Block HA secondary member from sending/receiving LACP messages.
Option	Description									
<i>enable</i>	Allow HA secondary member to send/receive LACP messages.									
<i>disable</i>	Block HA secondary member from sending/receiving LACP messages.									
system-id-type	Method in which system ID is generated.	option	-	auto						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Use the MAC address of the first member.</td></tr><tr><td><i>user</i></td><td>User-defined system ID.</td></tr></table>				Option	Description	<i>auto</i>	Use the MAC address of the first member.	<i>user</i>	User-defined system ID.
Option	Description									
<i>auto</i>	Use the MAC address of the first member.									
<i>user</i>	User-defined system ID.									
system-id	Define a system ID for the aggregate interface.	mac-address	Not Specified	00:00:00:00:00:00						
lACP-speed	How often the interface sends LACP messages.	option	-	slow						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>slow</i></td><td>Send LACP message every 30 seconds.</td></tr><tr><td><i>fast</i></td><td>Send LACP message every second.</td></tr></table>				Option	Description	<i>slow</i>	Send LACP message every 30 seconds.	<i>fast</i>	Send LACP message every second.
Option	Description									
<i>slow</i>	Send LACP message every 30 seconds.									
<i>fast</i>	Send LACP message every second.									
min-links	Minimum number of aggregated ports that must be up.	integer	Minimum value: 1 Maximum value: 32	1						

Parameter	Description	Type	Size	Default										
min-links-down	Action to take when less than the configured minimum number of links are active.	option	-	operational										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>operational</i></td><td>Set the aggregate operationally down.</td></tr><tr><td><i>administrative</i></td><td>Set the aggregate administratively down.</td></tr></table>	Option	Description	<i>operational</i>	Set the aggregate operationally down.	<i>administrative</i>	Set the aggregate administratively down.							
Option	Description													
<i>operational</i>	Set the aggregate operationally down.													
<i>administrative</i>	Set the aggregate administratively down.													
algorithm	Frame distribution algorithm.	option	-	L4										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>L2</i></td><td>Use layer 2 address for distribution.</td></tr><tr><td><i>L3</i></td><td>Use layer 3 address for distribution.</td></tr><tr><td><i>L4</i></td><td>Use layer 4 information for distribution.</td></tr><tr><td><i>Source-MAC</i></td><td>Use source MAC address for distribution.</td></tr></table>	Option	Description	<i>L2</i>	Use layer 2 address for distribution.	<i>L3</i>	Use layer 3 address for distribution.	<i>L4</i>	Use layer 4 information for distribution.	<i>Source-MAC</i>	Use source MAC address for distribution.			
Option	Description													
<i>L2</i>	Use layer 2 address for distribution.													
<i>L3</i>	Use layer 3 address for distribution.													
<i>L4</i>	Use layer 4 information for distribution.													
<i>Source-MAC</i>	Use source MAC address for distribution.													
link-up-delay	Number of milliseconds to wait before considering a link is up.	integer	Minimum value: 50 Maximum value: 3600000	50										
aggregate-type	Type of aggregation.	option	-	physical										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>physical</i></td><td>Physical interface aggregation.</td></tr><tr><td><i>vxlان</i></td><td>VXLAN interface aggregation.</td></tr></table>	Option	Description	<i>physical</i>	Physical interface aggregation.	<i>vxlان</i>	VXLAN interface aggregation.							
Option	Description													
<i>physical</i>	Physical interface aggregation.													
<i>vxlان</i>	VXLAN interface aggregation.													
priority-override	Enable/disable fail back to higher priority port once recovered.	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable fail back to higher priority port once recovered.</td></tr><tr><td><i>disable</i></td><td>Disable fail back to higher priority port once recovered.</td></tr></table>	Option	Description	<i>enable</i>	Enable fail back to higher priority port once recovered.	<i>disable</i>	Disable fail back to higher priority port once recovered.							
Option	Description													
<i>enable</i>	Enable fail back to higher priority port once recovered.													
<i>disable</i>	Disable fail back to higher priority port once recovered.													
aggregate	Aggregate interface.	string	Maximum length: 15											
redundant-interface	Redundant interface.	string	Maximum length: 15											

Parameter	Description	Type	Size	Default								
devindex	Device Index.	integer	Minimum value: 0 Maximum value: 4294967295	0								
switch	Contained in switch.	string	Maximum length: 15									
description	Description.	var-string	Maximum length: 255									
alias	Alias will be displayed with the interface name to make it easier to distinguish.	string	Maximum length: 25									
security-mode	Turn on captive portal authentication for this interface.	option	-	none								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>none</i></td><td>No security option.</td></tr><tr><td><i>captive-portal</i></td><td>Captive portal authentication.</td></tr><tr><td><i>802.1X</i></td><td>802.1X port-based authentication.</td></tr></table>				Option	Description	<i>none</i>	No security option.	<i>captive-portal</i>	Captive portal authentication.	<i>802.1X</i>	802.1X port-based authentication.
Option	Description											
<i>none</i>	No security option.											
<i>captive-portal</i>	Captive portal authentication.											
<i>802.1X</i>	802.1X port-based authentication.											
security-mac-auth-bypass	Enable/disable MAC authentication bypass.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>mac-auth-only</i></td><td>Enable MAC authentication bypass without EAP.</td></tr><tr><td><i>enable</i></td><td>Enable MAC authentication bypass.</td></tr><tr><td><i>disable</i></td><td>Disable MAC authentication bypass.</td></tr></table>				Option	Description	<i>mac-auth-only</i>	Enable MAC authentication bypass without EAP.	<i>enable</i>	Enable MAC authentication bypass.	<i>disable</i>	Disable MAC authentication bypass.
Option	Description											
<i>mac-auth-only</i>	Enable MAC authentication bypass without EAP.											
<i>enable</i>	Enable MAC authentication bypass.											
<i>disable</i>	Disable MAC authentication bypass.											
security-external-web	URL of external authentication web server.	var-string	Maximum length: 1023									
security-external-logout	URL of external authentication logout server.	string	Maximum length: 127									
replacemsg-override-group	Replacement message override group.	string	Maximum length: 35									
security-redirect-url	URL redirection after disclaimer/authentication.	var-string	Maximum length: 1023									

Parameter	Description	Type	Size	Default										
auth-cert	HTTPS server certificate.	string	Maximum length: 35											
auth-portal-addr	Address of captive portal.	string	Maximum length: 63											
security-exempt-list	Name of security-exempt-list.	string	Maximum length: 35											
security-groups <name>	User groups that can authenticate with the captive portal. Names of user groups that can authenticate with the captive portal.	string	Maximum length: 79											
ike-saml-server	Configure IKE authentication SAML server.	string	Maximum length: 35											
role	Interface role.	option	-	undefined										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>lan</td><td>Connected to local network of endpoints.</td></tr><tr><td>wan</td><td>Connected to Internet.</td></tr><tr><td>dmz</td><td>Connected to server zone.</td></tr><tr><td>undefined</td><td>Interface has no specific role.</td></tr></table>				Option	Description	lan	Connected to local network of endpoints.	wan	Connected to Internet.	dmz	Connected to server zone.	undefined	Interface has no specific role.
Option	Description													
lan	Connected to local network of endpoints.													
wan	Connected to Internet.													
dmz	Connected to server zone.													
undefined	Interface has no specific role.													
snmp-index	Permanent SNMP Index of the interface.	integer	Minimum value: 1 Maximum value: 2147483647	0										
secondary-IP	Enable/disable adding a secondary IP to this interface.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable secondary IP.</td></tr><tr><td>disable</td><td>Disable secondary IP.</td></tr></table>				Option	Description	enable	Enable secondary IP.	disable	Disable secondary IP.				
Option	Description													
enable	Enable secondary IP.													
disable	Disable secondary IP.													
color	Color of icon on the GUI.	integer	Minimum value: 0 Maximum value: 32	0										

Parameter	Description	Type	Size	Default
eap-supPLICant	Enable/disable EAP-SupPLICant.	option	-	disable
	Option Description			
	<i>enable</i>	Enable EAP SupPLICant.		
	<i>disable</i>	Disable EAP SupPLICant.		
eap-method	EAP method.	option	-	
	Option Description			
	<i>tls</i>	TLS.		
	<i>peap</i>	PEAP.		
eap-identity	EAP identity.	string	Maximum length: 35	
eap-password	EAP password.	password	Not Specified	
eap-ca-cert	EAP CA certificate name.	string	Maximum length: 79	
eap-user-cert	EAP user certificate name.	string	Maximum length: 35	

config client-options

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
code	DHCP client option code.	integer	Minimum value: 0 Maximum value: 255	0
type	DHCP client option type.	option	-	hex
	Option Description			
	<i>hex</i>	DHCP option in hex.		
	<i>string</i>	DHCP option in string.		
	<i>ip</i>	DHCP option in IP.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>fqdn</i>	DHCP option in domain search option format.		
value	DHCP client option value.	string	Maximum length: 312	
ip	DHCP option IPs.	user	Not Specified	

config secondaryip

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
ip	Secondary IP address of the interface.	ipv4-classnet-host	Not Specified	0.0.0.0 0.0.0.0
allowaccess	Management access settings for the secondary IP address.	option	-	
	Option	Description		
	<i>ping</i>	PING access.		
	<i>https</i>	HTTPS access.		
	<i>ssh</i>	SSH access.		
	<i>snmp</i>	SNMP access.		
	<i>http</i>	HTTP access.		
	<i>telnet</i>	TELNET access.		
	<i>fgfm</i>	FortiManager access.		
	<i>radius-acct</i>	RADIUS accounting access.		
	<i>probe-response</i>	Probe access.		
	<i>fabric</i>	Security Fabric access.		
	<i>ftm</i>	FTM access.		
	<i>speed-test</i>	Speed test access.		

Parameter	Description	Type	Size	Default								
gwdetect	Enable/disable detect gateway alive for first.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable detect gateway alive for first.</td></tr><tr><td><i>disable</i></td><td>Disable detect gateway alive for first.</td></tr></table>	Option	Description	<i>enable</i>	Enable detect gateway alive for first.	<i>disable</i>	Disable detect gateway alive for first.					
Option	Description											
<i>enable</i>	Enable detect gateway alive for first.											
<i>disable</i>	Disable detect gateway alive for first.											
ping-serv-status	PING server status.	integer	Minimum value: 0 Maximum value: 255	0								
detectserver	Gateway's ping server for this IP.	user	Not Specified									
detectprotocol	Protocols used to detect the server.	option	-	ping								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ping</i></td><td>PING.</td></tr><tr><td><i>tcp-echo</i></td><td>TCP echo.</td></tr><tr><td><i>udp-echo</i></td><td>UDP echo.</td></tr></table>	Option	Description	<i>ping</i>	PING.	<i>tcp-echo</i>	TCP echo.	<i>udp-echo</i>	UDP echo.			
Option	Description											
<i>ping</i>	PING.											
<i>tcp-echo</i>	TCP echo.											
<i>udp-echo</i>	UDP echo.											
ha-priority	HA election priority for the PING server.	integer	Minimum value: 1 Maximum value: 50	1								

config tagging

Parameter	Description	Type	Size	Default
name	Tagging entry name.	string	Maximum length: 63	
category	Tag category.	string	Maximum length: 63	
tags <name>	Tags. Tag name.	string	Maximum length: 79	

config ipv6

Parameter	Description	Type	Size	Default
ip6-mode	Addressing mode (static, DHCP, delegated).	option	-	static

Parameter	Description	Type	Size	Default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>static</i></td><td>Static setting.</td></tr><tr><td><i>dhcp</i></td><td>DHCPv6 client mode.</td></tr><tr><td><i>pppoe</i></td><td>IPv6 over PPPoE mode.</td></tr><tr><td><i>delegated</i></td><td>IPv6 address with delegated prefix.</td></tr></table>	Option	Description	<i>static</i>	Static setting.	<i>dhcp</i>	DHCPv6 client mode.	<i>pppoe</i>	IPv6 over PPPoE mode.	<i>delegated</i>	IPv6 address with delegated prefix.			
	Option	Description												
	<i>static</i>	Static setting.												
	<i>dhcp</i>	DHCPv6 client mode.												
	<i>pppoe</i>	IPv6 over PPPoE mode.												
<i>delegated</i>	IPv6 address with delegated prefix.													
nd-mode	Neighbor discovery mode.	option	-	basic										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>basic</i></td><td>Do not support SEND.</td></tr><tr><td><i>SEND-compatible</i></td><td>Support SEND.</td></tr></table>	Option	Description	<i>basic</i>	Do not support SEND.	<i>SEND-compatible</i>	Support SEND.							
	Option	Description												
	<i>basic</i>	Do not support SEND.												
<i>SEND-compatible</i>	Support SEND.													
nd-cert	Neighbor discovery certificate.	string	Maximum length: 35											
nd-security-level	Neighbor discovery security level (0 - 7; 0 = least secure, default = 0).	integer	Minimum value: 0 Maximum value: 7	0										
nd-timestamp-delta	Neighbor discovery timestamp delta value (1 - 3600 sec; default = 300).	integer	Minimum value: 1 Maximum value: 3600	300										
nd-timestamp-fuzz	Neighbor discovery timestamp fuzz factor (1 - 60 sec; default = 1).	integer	Minimum value: 1 Maximum value: 60	1										
nd-cga-modifier	Neighbor discovery CGA modifier.	user	Not Specified											
ip6-dns-server-override	Enable/disable using the DNS server acquired by DHCP.	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable using the DNS server acquired by DHCP.</td></tr><tr><td><i>disable</i></td><td>Disable using the DNS server acquired by DHCP.</td></tr></table>	Option	Description	<i>enable</i>	Enable using the DNS server acquired by DHCP.	<i>disable</i>	Disable using the DNS server acquired by DHCP.							
	Option	Description												
	<i>enable</i>	Enable using the DNS server acquired by DHCP.												
<i>disable</i>	Disable using the DNS server acquired by DHCP.													
ip6-address	Primary IPv6 address prefix. Syntax: xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx/xx x.	ipv6-prefix	Not Specified	::/0										

Parameter	Description	Type	Size	Default																		
ip6-allowaccess	Allow management access to the interface.	option	-																			
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ping</i></td><td>PING access.</td></tr><tr><td><i>https</i></td><td>HTTPS access.</td></tr><tr><td><i>ssh</i></td><td>SSH access.</td></tr><tr><td><i>snmp</i></td><td>SNMP access.</td></tr><tr><td><i>http</i></td><td>HTTP access.</td></tr><tr><td><i>telnet</i></td><td>TELNET access.</td></tr><tr><td><i>fgfm</i></td><td>FortiManager access.</td></tr><tr><td><i>fabric</i></td><td>Fabric access.</td></tr></table>	Option	Description	<i>ping</i>	PING access.	<i>https</i>	HTTPS access.	<i>ssh</i>	SSH access.	<i>snmp</i>	SNMP access.	<i>http</i>	HTTP access.	<i>telnet</i>	TELNET access.	<i>fgfm</i>	FortiManager access.	<i>fabric</i>	Fabric access.			
Option	Description																					
<i>ping</i>	PING access.																					
<i>https</i>	HTTPS access.																					
<i>ssh</i>	SSH access.																					
<i>snmp</i>	SNMP access.																					
<i>http</i>	HTTP access.																					
<i>telnet</i>	TELNET access.																					
<i>fgfm</i>	FortiManager access.																					
<i>fabric</i>	Fabric access.																					
ip6-send-adv	Enable/disable sending advertisements about the interface.	option	-	disable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable sending advertisements about this interface.</td></tr><tr><td><i>disable</i></td><td>Disable sending advertisements about this interface.</td></tr></table>	Option	Description	<i>enable</i>	Enable sending advertisements about this interface.	<i>disable</i>	Disable sending advertisements about this interface.															
Option	Description																					
<i>enable</i>	Enable sending advertisements about this interface.																					
<i>disable</i>	Disable sending advertisements about this interface.																					
icmp6-send-redirect	Enable/disable sending of ICMPv6 redirects.	option	-	enable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable sending of ICMPv6 redirects.</td></tr><tr><td><i>disable</i></td><td>Disable sending of ICMPv6 redirects.</td></tr></table>	Option	Description	<i>enable</i>	Enable sending of ICMPv6 redirects.	<i>disable</i>	Disable sending of ICMPv6 redirects.															
Option	Description																					
<i>enable</i>	Enable sending of ICMPv6 redirects.																					
<i>disable</i>	Disable sending of ICMPv6 redirects.																					
ip6-manage-flag	Enable/disable the managed flag.	option	-	disable																		
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable the managed IPv6 flag.</td></tr><tr><td><i>disable</i></td><td>Disable the managed IPv6 flag.</td></tr></table>	Option	Description	<i>enable</i>	Enable the managed IPv6 flag.	<i>disable</i>	Disable the managed IPv6 flag.															
Option	Description																					
<i>enable</i>	Enable the managed IPv6 flag.																					
<i>disable</i>	Disable the managed IPv6 flag.																					
ip6-other-flag	Enable/disable the other IPv6 flag.	option	-	disable																		

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable the other IPv6 flag.</td></tr><tr><td><i>disable</i></td><td>Disable the other IPv6 flag.</td></tr></table>	Option	Description	<i>enable</i>	Enable the other IPv6 flag.	<i>disable</i>	Disable the other IPv6 flag.			
	Option	Description								
	<i>enable</i>	Enable the other IPv6 flag.								
<i>disable</i>	Disable the other IPv6 flag.									
ip6-max-interval	IPv6 maximum interval (4 to 1800 sec).	integer	Minimum value: 4 Maximum value: 1800	600						
ip6-min-interval	IPv6 minimum interval (3 to 1350 sec).	integer	Minimum value: 3 Maximum value: 1350	198						
ip6-link-mtu	IPv6 link MTU.	integer	Minimum value: 1280 Maximum value: 16000	0						
ra-send-mtu	Enable/disable sending link MTU in RA packet.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable sending link MTU in RA packet.</td></tr><tr><td><i>disable</i></td><td>Disable sending link MTU in RA packet.</td></tr></table>	Option	Description	<i>enable</i>	Enable sending link MTU in RA packet.	<i>disable</i>	Disable sending link MTU in RA packet.			
	Option	Description								
	<i>enable</i>	Enable sending link MTU in RA packet.								
<i>disable</i>	Disable sending link MTU in RA packet.									
ip6-reachable-time	IPv6 reachable time (milliseconds; 0 means unspecified).	integer	Minimum value: 0 Maximum value: 3600000	0						
ip6-retrans-time	IPv6 retransmit time (milliseconds; 0 means unspecified).	integer	Minimum value: 0 Maximum value: 4294967295	0						
ip6-default-life	Default life (sec).	integer	Minimum value: 0 Maximum value: 9000	1800						
ip6-hop-limit	Hop limit (0 means unspecified).	integer	Minimum value: 0 Maximum value: 255	0						

Parameter	Description	Type	Size	Default						
autoconf	Enable/disable address auto config.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable auto-configuration.</td></tr><tr><td><i>disable</i></td><td>Disable auto-configuration.</td></tr></table>	Option	Description	<i>enable</i>	Enable auto-configuration.	<i>disable</i>	Disable auto-configuration.			
Option	Description									
<i>enable</i>	Enable auto-configuration.									
<i>disable</i>	Disable auto-configuration.									
unique-autoconf-addr	Enable/disable unique auto config address.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable unique auto-configuration address.</td></tr><tr><td><i>disable</i></td><td>Disable unique auto-configuration address.</td></tr></table>	Option	Description	<i>enable</i>	Enable unique auto-configuration address.	<i>disable</i>	Disable unique auto-configuration address.			
Option	Description									
<i>enable</i>	Enable unique auto-configuration address.									
<i>disable</i>	Disable unique auto-configuration address.									
interface-identifier	IPv6 interface identifier.	ipv6-address	Not Specified	::						
ip6-prefix-mode	Assigning a prefix from DHCP or RA.	option	-	dhcp6						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>dhcp6</i></td><td>Use delegated prefix from a DHCPv6 client to form a delegated IPv6 address.</td></tr><tr><td><i>ra</i></td><td>Use prefix from RA to form a delegated IPv6 address.</td></tr></table>	Option	Description	<i>dhcp6</i>	Use delegated prefix from a DHCPv6 client to form a delegated IPv6 address.	<i>ra</i>	Use prefix from RA to form a delegated IPv6 address.			
Option	Description									
<i>dhcp6</i>	Use delegated prefix from a DHCPv6 client to form a delegated IPv6 address.									
<i>ra</i>	Use prefix from RA to form a delegated IPv6 address.									
ip6-delegated-prefix-iaid	IAID of obtained delegated-prefix from the upstream interface.	integer	Minimum value: 0 Maximum value: 4294967295	0						
ip6-upstream-interface	Interface name providing delegated information.	string	Maximum length: 15							
ip6-subnet	Subnet to routing prefix. Syntax: xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx/xx x.	ipv6-prefix	Not Specified	::/0						
dhcp6-relay-service	Enable/disable DHCPv6 relay.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable DHCPv6 relay</td></tr><tr><td><i>enable</i></td><td>Enable DHCPv6 relay.</td></tr></table>	Option	Description	<i>disable</i>	Disable DHCPv6 relay	<i>enable</i>	Enable DHCPv6 relay.			
Option	Description									
<i>disable</i>	Disable DHCPv6 relay									
<i>enable</i>	Enable DHCPv6 relay.									

Parameter	Description	Type	Size	Default								
dhcp6-relay-type	DHCPv6 relay type.	option	-	regular								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>regular</i></td><td>Regular DHCP relay.</td></tr></table>	Option	Description	<i>regular</i>	Regular DHCP relay.							
Option	Description											
<i>regular</i>	Regular DHCP relay.											
dhcp6-relay-source-interface	Enable/disable use of address on this interface as the source address of the relay message.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Use address of the egress interface as source address of the relay message.</td></tr><tr><td><i>enable</i></td><td>Use address of this interface as source address of the relay message.</td></tr></table>	Option	Description	<i>disable</i>	Use address of the egress interface as source address of the relay message.	<i>enable</i>	Use address of this interface as source address of the relay message.					
Option	Description											
<i>disable</i>	Use address of the egress interface as source address of the relay message.											
<i>enable</i>	Use address of this interface as source address of the relay message.											
dhcp6-relay-ip	DHCPv6 relay IP address.	user	Not Specified									
dhcp6-client-options	DHCPv6 client options.	option	-									
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>rapid</i></td><td>Send rapid commit option.</td></tr><tr><td><i>iapd</i></td><td>Send including IA-PD option.</td></tr><tr><td><i>iana</i></td><td>Send including IA-NA option.</td></tr></table>	Option	Description	<i>rapid</i>	Send rapid commit option.	<i>iapd</i>	Send including IA-PD option.	<i>iana</i>	Send including IA-NA option.			
Option	Description											
<i>rapid</i>	Send rapid commit option.											
<i>iapd</i>	Send including IA-PD option.											
<i>iana</i>	Send including IA-NA option.											
dhcp6-prefix-delegation	Enable/disable DHCPv6 prefix delegation.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable DHCPv6 prefix delegation.</td></tr><tr><td><i>disable</i></td><td>Disable DHCPv6 prefix delegation.</td></tr></table>	Option	Description	<i>enable</i>	Enable DHCPv6 prefix delegation.	<i>disable</i>	Disable DHCPv6 prefix delegation.					
Option	Description											
<i>enable</i>	Enable DHCPv6 prefix delegation.											
<i>disable</i>	Disable DHCPv6 prefix delegation.											
dhcp6-information-request	Enable/disable DHCPv6 information request.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable DHCPv6 information request.</td></tr><tr><td><i>disable</i></td><td>Disable DHCPv6 information request.</td></tr></table>	Option	Description	<i>enable</i>	Enable DHCPv6 information request.	<i>disable</i>	Disable DHCPv6 information request.					
Option	Description											
<i>enable</i>	Enable DHCPv6 information request.											
<i>disable</i>	Disable DHCPv6 information request.											

Parameter	Description	Type	Size	Default
cli-conn6-status	CLI IPv6 connection status.	integer	Minimum value: 0 Maximum value: 4294967295	0

config ip6-extra-addr

Parameter	Description	Type	Size	Default
prefix	IPv6 address prefix.	ipv6-prefix	Not Specified	::/0

config ip6-prefix-list

Parameter	Description	Type	Size	Default
prefix	IPv6 prefix.	ipv6-network	Not Specified	::/0
autonomous-flag	Enable/disable the autonomous flag.	option	-	enable
	Option		Description	
	<i>enable</i>		Enable the autonomous flag.	
	<i>disable</i>		Disable the autonomous flag.	
onlink-flag	Enable/disable the onlink flag.	option	-	enable
	Option		Description	
	<i>enable</i>		Enable the onlink flag.	
	<i>disable</i>		Disable the onlink flag.	
valid-life-time	Valid life time (sec).	integer	Minimum value: 0 Maximum value: 4294967295	2592000
preferred-life-time	Preferred life time (sec).	integer	Minimum value: 0 Maximum value: 4294967295	604800
rdnss	Recursive DNS server option.	user	Not Specified	

Parameter	Description	Type	Size	Default
dnssl <domain>	DNS search list option. Domain name.	string	Maximum length: 79	

config ip6-delegated-prefix-list

Parameter	Description	Type	Size	Default								
prefix-id	Prefix ID.	integer	Minimum value: 0 Maximum value: 4294967295	0								
upstream-interface	Name of the interface that provides delegated information.	string	Maximum length: 15									
delegated-prefix-iaid	IAID of obtained delegated-prefix from the upstream interface.	integer	Minimum value: 0 Maximum value: 4294967295	0								
autonomous-flag	Enable/disable the autonomous flag.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable the autonomous flag.</td></tr><tr><td><i>disable</i></td><td>Disable the autonomous flag.</td></tr></table>	Option	Description	<i>enable</i>	Enable the autonomous flag.	<i>disable</i>	Disable the autonomous flag.					
Option	Description											
<i>enable</i>	Enable the autonomous flag.											
<i>disable</i>	Disable the autonomous flag.											
onlink-flag	Enable/disable the onlink flag.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable the onlink flag.</td></tr><tr><td><i>disable</i></td><td>Disable the onlink flag.</td></tr></table>	Option	Description	<i>enable</i>	Enable the onlink flag.	<i>disable</i>	Disable the onlink flag.					
Option	Description											
<i>enable</i>	Enable the onlink flag.											
<i>disable</i>	Disable the onlink flag.											
subnet	Add subnet ID to routing prefix.	ipv6-network	Not Specified	::/0								
rdnss-service	Recursive DNS service option.	option	-	specify								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>delegated</i></td><td>Delegated RDNSS settings.</td></tr><tr><td><i>default</i></td><td>System RDNSS settings.</td></tr><tr><td><i>specify</i></td><td>Specify recursive DNS servers.</td></tr></table>	Option	Description	<i>delegated</i>	Delegated RDNSS settings.	<i>default</i>	System RDNSS settings.	<i>specify</i>	Specify recursive DNS servers.			
Option	Description											
<i>delegated</i>	Delegated RDNSS settings.											
<i>default</i>	System RDNSS settings.											
<i>specify</i>	Specify recursive DNS servers.											
rdnss	Recursive DNS server option.	user	Not Specified									

config dhcp6-iapd-list

Parameter	Description	Type	Size	Default
iaid	Identity association identifier.	integer	Minimum value: 0 Maximum value: 4294967295	0
prefix-hint	DHCPv6 prefix that will be used as a hint to the upstream DHCPv6 server.	ipv6-network	Not Specified	::/0
prefix-hint-plt	DHCPv6 prefix hint preferred life time (sec), 0 means unlimited lease time.	integer	Minimum value: 0 Maximum value: 4294967295	604800
prefix-hint-vlt	DHCPv6 prefix hint valid life time (sec).	integer	Minimum value: 0 Maximum value: 4294967295	2592000

config system ipam

Configure IP address management services.

```
config system ipam
  Description: Configure IP address management services.
  set status [enable|disable]
  set server-type {option}
  config pools
    Description: Configure IPAM pools.
    edit <name>
      set description {string}
      set subnet {ipv4-classnet}
    next
  end
  config rules
    Description: Configure IPAM allocation rules.
    edit <name>
      set description {string}
      set device <name1>, <name2>, ...
      set interface <name1>, <name2>, ...
      set role [any|lan|...]
      set pool <name1>, <name2>, ...
      set dhcp [enable|disable]
    next
```



```
end
end
```

config system ipam

Parameter	Description	Type	Size	Default
status	Enable/disable IP address management services.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable integration with IP address management services.		
	<i>disable</i>	Disable integration with IP address management services.		
server-type	Configure the type of IPAM server to use.	option	-	fabric-root
	Option	Description		
	<i>fabric-root</i>	Use the IPAM server running on the Security Fabric root.		

config pools

Parameter	Description	Type	Size	Default
name	IPAM pool name.	string	Maximum length: 79	
description	Description.	string	Maximum length: 127	
subnet	Configure IPAM pool subnet, Class A - Class B subnet.	ipv4-classnet	Not Specified	0.0.0.0 0.0.0.0

config rules

Parameter	Description	Type	Size	Default
name	IPAM rule name.	string	Maximum length: 79	
description	Description.	string	Maximum length: 127	
device <name>	Configure serial number or wildcard of FortiGate to match. FortiGate serial number or wildcard.	string	Maximum length: 79	

Parameter	Description	Type	Size	Default												
interface <name>	Configure name or wildcard of interface to match. Interface name or wildcard.	string	Maximum length: 79													
role	Configure role of interface to match.	option	-	any												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>any</td><td>Match any interface role.</td></tr><tr><td>lan</td><td>Match interface role lan.</td></tr><tr><td>wan</td><td>Match interface role wan.</td></tr><tr><td>dmz</td><td>Match interface role dmz.</td></tr><tr><td>undefined</td><td>Match interface role undefined.</td></tr></table>	Option	Description	any	Match any interface role.	lan	Match interface role lan.	wan	Match interface role wan.	dmz	Match interface role dmz.	undefined	Match interface role undefined.			
Option	Description															
any	Match any interface role.															
lan	Match interface role lan.															
wan	Match interface role wan.															
dmz	Match interface role dmz.															
undefined	Match interface role undefined.															
pool <name>	Configure name of IPAM pool to use. Ipam pool name.	string	Maximum length: 79													
dhcp	Enable/disable DHCP server for matching IPAM interfaces.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable DHCP server on matched IPAM interface.</td></tr><tr><td>disable</td><td>Disable DHCP server on matched IPAM interface.</td></tr></table>	Option	Description	enable	Enable DHCP server on matched IPAM interface.	disable	Disable DHCP server on matched IPAM interface.									
Option	Description															
enable	Enable DHCP server on matched IPAM interface.															
disable	Disable DHCP server on matched IPAM interface.															

config system ips

Configure IPS system settings.

```
config system ips
  Description: Configure IPS system settings.
  set signature-hold-time {user}
  set override-signature-hold-by-id [enable|disable]
end
```

config system ips

Parameter	Description	Type	Size	Default
signature-hold-time	Time to hold and monitor IPS signatures. Format <#d##h> (day range: 0 - 7, hour range: 0 - 23, max hold time: 7d0h, default hold time: 0d0h).	user	Not Specified	0h

Parameter	Description	Type	Size	Default
override-signature-hold-by-id	Enable/disable override of hold of triggering signatures that are specified by IDs regardless of hold.	option	-	enable
	Option	Description		
	<i>enable</i>	Allow the signatures specified by IDs to be triggered even if they are on hold.		
	<i>disable</i>	Do not trigger the signatures that are on hold.		

config system ips-urlfilter-dns

Configure IPS URL filter DNS servers.

```
config system ips-urlfilter-dns
  Description: Configure IPS URL filter DNS servers.
  edit <address>
    set status [enable|disable]
    set ipv6-capability [enable|disable]
  next
end
```

config system ips-urlfilter-dns

Parameter	Description	Type	Size	Default
address	DNS server IP address.	ipv4-address	Not Specified	0.0.0.0
status	Enable/disable using this DNS server for IPS URL filter DNS queries.	option	-	enable
	Option	Description		
	enable	Enable this DNS server for IPS URL filter DNS queries.		
	disable	Disable this DNS server for IPS URL filter DNS queries.		
ipv6-capability	Enable/disable this server for IPv6 queries.	option	-	disable
	Option	Description		
	enable	Enable setting.		
	disable	Disable setting.		

config system ips-urlfilter-dns6

Configure IPS URL filter IPv6 DNS servers.

```
config system ips-urlfilter-dns6
  Description: Configure IPS URL filter IPv6 DNS servers.
  edit <address6>
    set status [enable|disable]
  next
end
```

config system ips-urlfilter-dns6

Parameter	Description	Type	Size	Default
address6	IPv6 address of DNS server.	ipv6-address	Not Specified	::
status	Enable/disable this server for IPv6 DNS queries.	option	-	enable
		Option	Description	
		<i>enable</i>	Enable setting.	
		<i>disable</i>	Disable setting.	

config system ipv6-neighbor-cache

Configure IPv6 neighbor cache table.

```
config system ipv6-neighbor-cache
  Description: Configure IPv6 neighbor cache table.
  edit <id>
    set interface {string}
    set ipv6 {ipv6-address}
    set mac {mac-address}
  next
end
```

config system ipv6-neighbor-cache

Parameter	Description	Type	Size	Default
id	Unique integer ID of the entry.	integer	Minimum value: 0 Maximum value: 4294967295	0
interface	Select the associated interface name from available options.	string	Maximum length: 15	
ipv6	IPv6 address (format: xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xx xx).	ipv6-address	Not Specified	::
mac	MAC address (format: xx:xx:xx:xx:xx:xx).	mac-address	Not Specified	00:00:00:00:00:00

config system ip-conflict status

List interface names and IP addresses in conflict.

```
config system ip-conflict status
    Description: List interface names and IP addresses in conflict.
end
```

config system link-monitor

Configure Link Health Monitor.

```
config system link-monitor
    Description: Configure Link Health Monitor.
    edit <name>
        set addr-mode [ipv4|ipv6]
        set srcintf {string}
        set server-config [default|individual]
        set server <address1>, <address2>, ...
        set protocol {option1}, {option2}, ...
        set port {integer}
        set gateway-ip {ipv4-address-any}
        set gateway-ip6 {ipv6-address}
        set route <subnet1>, <subnet2>, ...
        set source-ip {ipv4-address-any}
        set source-ip6 {ipv6-address}
        set http-get {string}
        set http-agent {string}
    end
```

```

set http-match {string}
set interval {integer}
set probe-timeout {integer}
set failtime {integer}
set recoverytime {integer}
set probe-count {integer}
set security-mode [none|authentication]
set password {password}
set packet-size {integer}
set ha-priority {integer}
set fail-weight {integer}
set update-cascade-interface [enable|disable]
set update-static-route [enable|disable]
set update-policy-route [enable|disable]
set status [enable|disable]
set diffservcode {user}
set class-id {integer}
set service-detection [enable|disable]
config server-list
    Description: Servers for link-monitor to monitor.
    edit <id>
        set dst {string}
        set protocol {option1}, {option2}, ...
        set port {integer}
        set weight {integer}
    next
end
next
end

```

config system link-monitor

Parameter	Description	Type	Size	Default						
name	Link monitor name.	string	Maximum length: 35							
addr-mode	Address mode (IPv4 or IPv6).	option	-	ipv4						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>ipv4</td><td>IPv4 mode.</td></tr><tr><td>ipv6</td><td>IPv6 mode.</td></tr></table>				Option	Description	ipv4	IPv4 mode.	ipv6	IPv6 mode.
	Option	Description								
	ipv4	IPv4 mode.								
ipv6	IPv6 mode.									
srcintf	Interface that receives the traffic to be monitored.	string	Maximum length: 15							
server-config	Mode of server configuration.	option	-	default						

Parameter	Description	Type	Size	Default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>All servers share the same attributes.</td></tr><tr><td><i>individual</i></td><td>Some attributes can be specified for individual servers.</td></tr></table>	Option	Description	<i>default</i>	All servers share the same attributes.	<i>individual</i>	Some attributes can be specified for individual servers.									
	Option	Description														
	<i>default</i>	All servers share the same attributes.														
<i>individual</i>	Some attributes can be specified for individual servers.															
server <address>	IP address of the server(s) to be monitored. Server address.	string	Maximum length: 79													
protocol	Protocols used to monitor the server.	option	-	ping												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ping</i></td><td>PING link monitor.</td></tr><tr><td><i>tcp-echo</i></td><td>TCP echo link monitor.</td></tr><tr><td><i>udp-echo</i></td><td>UDP echo link monitor.</td></tr><tr><td><i>http</i></td><td>HTTP-GET link monitor.</td></tr><tr><td><i>twamp</i></td><td>TWAMP link monitor.</td></tr></table>	Option	Description	<i>ping</i>	PING link monitor.	<i>tcp-echo</i>	TCP echo link monitor.	<i>udp-echo</i>	UDP echo link monitor.	<i>http</i>	HTTP-GET link monitor.	<i>twamp</i>	TWAMP link monitor.			
	Option	Description														
	<i>ping</i>	PING link monitor.														
	<i>tcp-echo</i>	TCP echo link monitor.														
	<i>udp-echo</i>	UDP echo link monitor.														
	<i>http</i>	HTTP-GET link monitor.														
<i>twamp</i>	TWAMP link monitor.															
port	Port number of the traffic to be used to monitor the server.	integer	Minimum value: 1 Maximum value: 65535	0												
gateway-ip	Gateway IP address used to probe the server.	ipv4-address-any	Not Specified	0.0.0.0												
gateway-ip6	Gateway IPv6 address used to probe the server.	ipv6-address	Not Specified	::												
route <subnet>	Subnet to monitor. IP and netmask (x.x.x.x/y).	string	Maximum length: 79													
source-ip	Source IP address used in packet to the server.	ipv4-address-any	Not Specified	0.0.0.0												
source-ip6	Source IPv6 address used in packet to the server.	ipv6-address	Not Specified	::												
http-get	If you are monitoring an HTML server you can send an HTTP-GET request with a custom string. Use this option to define the string.	string	Maximum length: 1024	/												
http-agent	String in the http-agent field in the HTTP header.	string	Maximum length: 1024	Chrome/ Safari/												

Parameter	Description	Type	Size	Default						
http-match	String that you expect to see in the HTTP-GET requests of the traffic to be monitored.	string	Maximum length: 1024							
interval	Detection interval in milliseconds (20 - 3600 * 1000 msec, default = 500).	integer	Minimum value: 20 Maximum value: 3600000	500						
probe-timeout	Time to wait before a probe packet is considered lost (20 - 5000 msec, default = 500).	integer	Minimum value: 20 Maximum value: 5000	500						
failtime	Number of retry attempts before the server is considered down (1 - 3600, default = 5).	integer	Minimum value: 1 Maximum value: 3600	5						
recoverytime	Number of successful responses received before server is considered recovered (1 - 3600, default = 5).	integer	Minimum value: 1 Maximum value: 3600	5						
probe-count	Number of most recent probes that should be used to calculate latency and jitter (5 - 30, default = 30).	integer	Minimum value: 5 Maximum value: 30	30						
security-mode	Twamp controller security mode.	option	-	none						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>none</i></td><td>Unauthenticated mode.</td></tr><tr><td><i>authentication</i></td><td>Authenticated mode.</td></tr></table>				Option	Description	<i>none</i>	Unauthenticated mode.	<i>authentication</i>	Authenticated mode.
Option	Description									
<i>none</i>	Unauthenticated mode.									
<i>authentication</i>	Authenticated mode.									
password	TWAMP controller password in authentication mode.	password	Not Specified							
packet-size	Packet size of a TWAMP test session.	integer	Minimum value: 64 Maximum value: 1024	64						
ha-priority	HA election priority (1 - 50).	integer	Minimum value: 1 Maximum value: 50	1						

Parameter	Description	Type	Size	Default						
fail-weight	Threshold weight to trigger link failure alert.	integer	Minimum value: 0 Maximum value: 255	0						
update-cascade-interface	Enable/disable update cascade interface.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable update cascade interface.</td></tr><tr><td><i>disable</i></td><td>Disable update cascade interface.</td></tr></table>	Option	Description	<i>enable</i>	Enable update cascade interface.	<i>disable</i>	Disable update cascade interface.			
Option	Description									
<i>enable</i>	Enable update cascade interface.									
<i>disable</i>	Disable update cascade interface.									
update-static-route	Enable/disable updating the static route.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable updating the static route.</td></tr><tr><td><i>disable</i></td><td>Disable updating the static route.</td></tr></table>	Option	Description	<i>enable</i>	Enable updating the static route.	<i>disable</i>	Disable updating the static route.			
Option	Description									
<i>enable</i>	Enable updating the static route.									
<i>disable</i>	Disable updating the static route.									
update-policy-route	Enable/disable updating the policy route.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable updating the policy route.</td></tr><tr><td><i>disable</i></td><td>Disable updating the policy route.</td></tr></table>	Option	Description	<i>enable</i>	Enable updating the policy route.	<i>disable</i>	Disable updating the policy route.			
Option	Description									
<i>enable</i>	Enable updating the policy route.									
<i>disable</i>	Disable updating the policy route.									
status	Enable/disable this link monitor.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable this link monitor.</td></tr><tr><td><i>disable</i></td><td>Disable this link monitor.</td></tr></table>	Option	Description	<i>enable</i>	Enable this link monitor.	<i>disable</i>	Disable this link monitor.			
Option	Description									
<i>enable</i>	Enable this link monitor.									
<i>disable</i>	Disable this link monitor.									
diffservcode	Differentiated services code point (DSCP) in the IP header of the probe packet.	user	Not Specified							
class-id	Traffic class ID.	integer	Minimum value: 0 Maximum value: 4294967295	0						

Parameter	Description	Type	Size	Default						
service-detection	Only use monitor to read quality values. If enabled, static routes and cascade interfaces will not be updated.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Only use monitor for service-detection.</td></tr><tr><td><i>disable</i></td><td>Monitor will update routes/interfaces on link failure.</td></tr></table>				Option	Description	<i>enable</i>	Only use monitor for service-detection.	<i>disable</i>	Monitor will update routes/interfaces on link failure.
Option	Description									
<i>enable</i>	Only use monitor for service-detection.									
<i>disable</i>	Monitor will update routes/interfaces on link failure.									

config server-list

Parameter	Description	Type	Size	Default												
id	Server ID.	integer	Minimum value: 1 Maximum value: 32	0												
dst	IP address of the server to be monitored.	string	Maximum length: 64													
protocol	Protocols used to monitor the server.	option	-	ping												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ping</i></td><td>PING link monitor.</td></tr><tr><td><i>tcp-echo</i></td><td>TCP echo link monitor.</td></tr><tr><td><i>udp-echo</i></td><td>UDP echo link monitor.</td></tr><tr><td><i>http</i></td><td>HTTP-GET link monitor.</td></tr><tr><td><i>twamp</i></td><td>TWAMP link monitor.</td></tr></table>				Option	Description	<i>ping</i>	PING link monitor.	<i>tcp-echo</i>	TCP echo link monitor.	<i>udp-echo</i>	UDP echo link monitor.	<i>http</i>	HTTP-GET link monitor.	<i>twamp</i>	TWAMP link monitor.
	Option	Description														
	<i>ping</i>	PING link monitor.														
	<i>tcp-echo</i>	TCP echo link monitor.														
	<i>udp-echo</i>	UDP echo link monitor.														
	<i>http</i>	HTTP-GET link monitor.														
<i>twamp</i>	TWAMP link monitor.															
port	Port number of the traffic to be used to monitor the server.	integer	Minimum value: 1 Maximum value: 65535	0												
weight	Weight of the monitor to this dst (0 - 255).	integer	Minimum value: 0 Maximum value: 255	0												

config system management-tunnel

Management tunnel configuration.

```

config system management-tunnel
    Description: Management tunnel configuration.
    set status [enable|disable]
    set allow-config-restore [enable|disable]
    set allow-push-configuration [enable|disable]
    set allow-push-firmware [enable|disable]
    set allow-collect-statistics [enable|disable]
    set authorized-manager-only [enable|disable]
    set serial-number {user}
end

```

config system management-tunnel

Parameter	Description	Type	Size	Default
status	Enable/disable FGFM tunnel.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable management tunnel.		
	<i>disable</i>	Disable management tunnel.		
allow-config-restore	Enable/disable allow config restore.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable allow config restore.		
	<i>disable</i>	Disable allow config restore.		
allow-push-configuration	Enable/disable push configuration.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable push configuration.		
	<i>disable</i>	Disable push configuration.		
allow-push-firmware	Enable/disable push firmware.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable push firmware.		
	<i>disable</i>	Disable push firmware.		
allow-collect-statistics	Enable/disable collection of run time statistics.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable collection of run time statistics.		
	<i>disable</i>	Disable collection of run time statistics.		
authorized-manager-only	Enable/disable restriction of authorized manager only.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable restriction of authorized manager only.		
	<i>disable</i>	Disable restriction of authorized manager only.		
serial-number	Serial number.	user	Not Specified	

config system mgmt-csum

System checksum for FortiManager use only.

```
config system mgmt-csum
    Description: System checksum for FortiManager use only.
end
```

config system nethsm

Configure system nethsm.

```
config system nethsm
    Description: Configure system nethsm.
    set status [enable|disable]
    set vendor [safenet|primus]
    set interface {string}
    set receivetimeout {integer}
    config servers
        Description: NetHSM server list.
        edit <name>
            set server {string}
            set port {integer}
            set server-cert {user}
            set htl [enable|disable]
        next
    end
    config slots
        Description: NetHSM slot list.
```

```

    edit <name>
        set id {integer}
        set password {password}
        set for-ha [yes|no]
    next
end
set ha [enable|disable]
set ha-status-pulling-interval {integer}
config hgroups
    Description: NetHSM HA group list.
    edit <name>
        set member <name1>, <name2>, ...
    next
end
set rsa-mech-remap [enable|disable]
set primus-cfg {user}
set secret-content {varlen_password}
config partitions
    Description: Set Hardware Security Module partition information.
    edit <name>
        set slot-id {integer}
        set pkcs11-pin {password}
    next
end
end
end

```

config system nethsm

Parameter	Description	Type	Size	Default
status	Status.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable system network HSM.		
	<i>disable</i>	Disable system network HSM.		
vendor	Vendor.	option	-	safenet
	Option	Description		
	<i>safenet</i>	SafeNet HSM.		
	<i>primus</i>	Securosys Primus HSM.		
interface	Outgoing interface	string	Maximum length: 15	

Parameter	Description	Type	Size	Default
receivetimeout	Receive timeout, specified in ms (default=20000).	integer	Minimum value: 0 Maximum value: 4294967295	20000
ha	HA option (default=disable).	option	-	disable
	Option Description			
	<i>enable</i>	Enable HA.		
	<i>disable</i>	Disable HA.		
ha-status-pulling-interval	Interval to pull HA status in minutes (default=1).	integer	Minimum value: 0 Maximum value: 60	1
rsa-mech-remap	RSA Mechanism Remap option (default=disable). Enable it if Luna server is running in FIPS mode and firmware version is 6.22.* or greater.	option	-	disable
	Option Description			
	<i>enable</i>	Enable RSA Mechanism Remap.		
	<i>disable</i>	Disable RSA Mechanism Remap.		
primus-cfg	Set primus.cfg file content	user	Not Specified	
secret-content	Set secret content	varlen_password	Not Specified	

config servers

Parameter	Description	Type	Size	Default
name	NetHSM server name.	string	Maximum length: 35	
server	{<name_str ip_str>} NetHSM server domain name or IP.	string	Maximum length: 63	
port	NetHSM server port (default=1792).	integer	Minimum value: 1 Maximum value: 65535	1792

Parameter	Description	Type	Size	Default						
server-cert	NetHSM server certificate.	user	Not Specified							
htl	HTL option (default=disable).	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable HTL.</td></tr><tr><td><i>disable</i></td><td>Disable HTL.</td></tr></table>	Option	Description	<i>enable</i>	Enable HTL.	<i>disable</i>	Disable HTL.			
Option	Description									
<i>enable</i>	Enable HTL.									
<i>disable</i>	Disable HTL.									

config slots

Parameter	Description	Type	Size	Default
name	NetHSM slot name.	string	Maximum length: 35	
id	NetHSM slot ID (0 - 4294967295).	integer	Minimum value: 0 Maximum value: 4294967295	0
password	NetHSM slot access password.	password	Not Specified	
for-ha	HA option.	option	-	no
	Option	Description		
	yes	HA slot.		
	no	Regular slot.		

config hagroups

Parameter	Description	Type	Size	Default
name	NetHSM HA group name.	string	Maximum length: 35	
member <name>	HA group members. NetHSM HA group member (slot names).	string	Maximum length: 79	

config partitions

Parameter	Description	Type	Size	Default
name	Name of the Hardware Security Module partition.	string	Maximum length: 35	
slot-id	Slot ID number of the Hardware Security Module partition.	integer	Minimum value: 0 Maximum value: 4294967295	0
pkcs11-pin	PKCS#11 PIN for the Hardware Security Module partition.	password	Not Specified	

config system network-visibility

Configure network visibility settings.

```
config system network-visibility
  Description: Configure network visibility settings.
  set destination-visibility [disable|enable]
  set source-location [disable|enable]
  set destination-hostname-visibility [disable|enable]
  set hostname-ttl {integer}
  set hostname-limit {integer}
  set destination-location [disable|enable]
end
```

config system network-visibility

Parameter	Description	Type	Size	Default						
destination-visibility	Enable/disable logging of destination visibility.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable logging of destination visibility.</td></tr><tr><td><i>enable</i></td><td>Enable logging of destination visibility.</td></tr></table>	Option	Description	<i>disable</i>	Disable logging of destination visibility.	<i>enable</i>	Enable logging of destination visibility.			
	Option	Description								
	<i>disable</i>	Disable logging of destination visibility.								
<i>enable</i>	Enable logging of destination visibility.									
source-location	Enable/disable logging of source geographical location visibility.	option	-	enable						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable logging of source geographical location visibility.		
	<i>enable</i>	Enable logging of source geographical location visibility.		
destination-hostname-visibility	Enable/disable logging of destination hostname visibility.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable logging of destination hostname visibility.		
	<i>enable</i>	Enable logging of destination hostname visibility.		
hostname-ttl	TTL of hostname table entries (60 - 86400).	integer	Minimum value: 60 Maximum value: 86400	86400
hostname-limit	Limit of the number of hostname table entries (0 - 50000).	integer	Minimum value: 0 Maximum value: 50000	5000
destination-location	Enable/disable logging of destination geographical location visibility.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable logging of destination geographical location visibility.		
	<i>enable</i>	Enable logging of destination geographical location visibility.		

config system ntp

Configure system NTP information.

```
config system ntp
  Description: Configure system NTP information.
  set ntpsync [enable|disable]
  set type [fortiguard|custom]
  set syncinterval {integer}
  config ntpserver
    Description: Configure the FortiProxy to connect to any available third-party NTP server.
    edit <id>
      set server {string}
```

```

        set ntpv3 [enable|disable]
        set authentication [enable|disable]
        set key {password}
        set key-id {integer}
        set interface-select-method [auto|specify]
        set interface {string}
    next
end
set source-ip {ipv4-address}
set source-ip6 {ipv6-address}
set server-mode [enable|disable]
set authentication [enable|disable]
set key-type [MD5|SHA1]
set key {password}
set key-id {integer}
set interface <interface-name1>, <interface-name2>, ...
end

```

config system ntp

Parameter	Description	Type	Size	Default						
ntpsync	Enable/disable setting the FortiProxy system time by synchronizing with an NTP Server.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable synchronization with NTP Server.</td></tr><tr><td><i>disable</i></td><td>Disable synchronization with NTP Server.</td></tr></table>	Option	Description	<i>enable</i>	Enable synchronization with NTP Server.	<i>disable</i>	Disable synchronization with NTP Server.			
Option	Description									
<i>enable</i>	Enable synchronization with NTP Server.									
<i>disable</i>	Disable synchronization with NTP Server.									
type	Use the FortiGuard NTP server or any other available NTP Server.	option	-	fortiguard						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>fortiguard</i></td><td>Use the FortiGuard NTP server.</td></tr><tr><td><i>custom</i></td><td>Use any other available NTP server.</td></tr></table>	Option	Description	<i>fortiguard</i>	Use the FortiGuard NTP server.	<i>custom</i>	Use any other available NTP server.			
Option	Description									
<i>fortiguard</i>	Use the FortiGuard NTP server.									
<i>custom</i>	Use any other available NTP server.									
syncinterval	NTP synchronization interval (1 - 1440 min).	integer	Minimum value: 1 Maximum value: 1440	60						
source-ip	Source IP address for communication to the NTP server.	ipv4-address	Not Specified	0.0.0.0						
source-ip6	Source IPv6 address for communication to the NTP server.	ipv6-address	Not Specified	::						

Parameter	Description	Type	Size	Default						
server-mode	Enable/disable FortiProxy NTP Server Mode. Your FortiProxy becomes an NTP server for other devices on your network. The FortiProxy relays NTP requests to its configured NTP server.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable FortiProxy NTP Server Mode.</td></tr><tr><td><i>disable</i></td><td>Disable FortiProxy NTP Server Mode.</td></tr></table>	Option	Description	<i>enable</i>	Enable FortiProxy NTP Server Mode.	<i>disable</i>	Disable FortiProxy NTP Server Mode.			
Option	Description									
<i>enable</i>	Enable FortiProxy NTP Server Mode.									
<i>disable</i>	Disable FortiProxy NTP Server Mode.									
authentication	Enable/disable authentication.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable authentication.</td></tr><tr><td><i>disable</i></td><td>Disable authentication.</td></tr></table>	Option	Description	<i>enable</i>	Enable authentication.	<i>disable</i>	Disable authentication.			
Option	Description									
<i>enable</i>	Enable authentication.									
<i>disable</i>	Disable authentication.									
key-type	Key type for authentication (MD5, SHA1).	option	-	MD5						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>MD5</i></td><td>Use MD5 to authenticate the message.</td></tr><tr><td><i>SHA1</i></td><td>Use SHA1 to authenticate the message.</td></tr></table>	Option	Description	<i>MD5</i>	Use MD5 to authenticate the message.	<i>SHA1</i>	Use SHA1 to authenticate the message.			
Option	Description									
<i>MD5</i>	Use MD5 to authenticate the message.									
<i>SHA1</i>	Use SHA1 to authenticate the message.									
key	Key for authentication.	password	Not Specified							
key-id	Key ID for authentication.	integer	Minimum value: 0 Maximum value: 4294967295	0						
interface <interface-name>	FortiProxy interface(s) with NTP server mode enabled. Devices on your network can contact these interfaces for NTP services. Interface name.	string	Maximum length: 79							

config ntpserver

Parameter	Description	Type	Size	Default						
id	NTP server ID.	integer	Minimum value: 0 Maximum value: 4294967295	0						
server	IP address or hostname of the NTP Server.	string	Maximum length: 63							
ntp3	Enable to use NTPv3 instead of NTPv4.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable NTPv3.</td></tr><tr><td>disable</td><td>Disable NTPv3 (use NTPv4).</td></tr></table>	Option	Description	enable	Enable NTPv3.	disable	Disable NTPv3 (use NTPv4).			
Option	Description									
enable	Enable NTPv3.									
disable	Disable NTPv3 (use NTPv4).									
authentication	Enable/disable MD5(NTPv3)/SHA1 (NTPv4) authentication.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable MD5(NTPv3)/SHA1(NTPv4) authentication.</td></tr><tr><td>disable</td><td>Disable MD5(NTPv3)/SHA1(NTPv4) authentication.</td></tr></table>	Option	Description	enable	Enable MD5(NTPv3)/SHA1(NTPv4) authentication.	disable	Disable MD5(NTPv3)/SHA1(NTPv4) authentication.			
Option	Description									
enable	Enable MD5(NTPv3)/SHA1(NTPv4) authentication.									
disable	Disable MD5(NTPv3)/SHA1(NTPv4) authentication.									
key	Key for MD5(NTPv3)/SHA1(NTPv4) authentication.	password	Not Specified							
key-id	Key ID for authentication.	integer	Minimum value: 0 Maximum value: 4294967295	0						
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>auto</td><td>Set outgoing interface automatically.</td></tr><tr><td>specify</td><td>Set outgoing interface manually.</td></tr></table>	Option	Description	auto	Set outgoing interface automatically.	specify	Set outgoing interface manually.			
Option	Description									
auto	Set outgoing interface automatically.									
specify	Set outgoing interface manually.									
interface	Specify outgoing interface to reach server.	string	Maximum length: 15							

config system object-tagging

Configure object tagging.

```
config system object-tagging
  Description: Configure object tagging.
  edit <category>
    set address [disable|mandatory|...]
    set device [disable|mandatory|...]
    set interface [disable|mandatory|...]
    set multiple [enable|disable]
    set color {integer}
    set tags <name1>, <name2>, ...
  next
end
```

config system object-tagging

Parameter	Description	Type	Size	Default
category	Tag Category.	string	Maximum length: 63	
address	Address.	option	-	optional
	Option	Description		
	<i>disable</i>	Disable.		
	<i>mandatory</i>	Mandatory.		
	<i>optional</i>	Optional.		
device	Device.	option	-	optional
	Option	Description		
	<i>disable</i>	Disable.		
	<i>mandatory</i>	Mandatory.		
	<i>optional</i>	Optional.		
interface	Interface.	option	-	optional
	Option	Description		
	<i>disable</i>	Disable.		
	<i>mandatory</i>	Mandatory.		
	<i>optional</i>	Optional.		

Parameter	Description	Type	Size	Default
multiple	Allow multiple tag selection.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable multi-tagging.		
	<i>disable</i>	Disable multi-tagging.		
color	Color of icon on the GUI.	integer	Minimum value: 0 Maximum value: 32	0
tags <name>	Tags. Tag name.	string	Maximum length: 79	

config system password-policy

Configure password policy for locally defined administrator passwords and IPsec VPN pre-shared keys.

```

config system password-policy
    Description: Configure password policy for locally defined administrator passwords and IPsec
VPN pre-shared keys.
    set status [enable|disable]
    set apply-to {option1}, {option2}, ...
    set minimum-length {integer}
    set min-lower-case-letter {integer}
    set min-upper-case-letter {integer}
    set min-non-alphanumeric {integer}
    set min-number {integer}
    set min-change-characters {integer}
    set expire-status [enable|disable]
    set expire-day {integer}
    set reuse-password [enable|disable]
    set login-lockout-upon-downgrade [enable|disable]
    set password-history {integer}
end

```

config system password-policy

Parameter	Description	Type	Size	Default						
status	Enable/disable setting a password policy for locally defined administrator passwords and IPsec VPN pre-shared keys.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable password policy.</td></tr><tr><td><i>disable</i></td><td>Disable password policy.</td></tr></table>	Option	Description	<i>enable</i>	Enable password policy.	<i>disable</i>	Disable password policy.			
Option	Description									
<i>enable</i>	Enable password policy.									
<i>disable</i>	Disable password policy.									
apply-to	Apply password policy to administrator passwords or IPsec pre-shared keys or both. Separate entries with a space.	option	-	admin-password						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>admin-password</i></td><td>Apply to administrator passwords.</td></tr><tr><td><i>ipsec-preshared-key</i></td><td>Apply to IPsec pre-shared keys.</td></tr></table>	Option	Description	<i>admin-password</i>	Apply to administrator passwords.	<i>ipsec-preshared-key</i>	Apply to IPsec pre-shared keys.			
Option	Description									
<i>admin-password</i>	Apply to administrator passwords.									
<i>ipsec-preshared-key</i>	Apply to IPsec pre-shared keys.									
minimum-length	Minimum password length (8 - 128, default = 8).	integer	Minimum value: 8 Maximum value: 128	8						
min-lower-case-letter	Minimum number of lowercase characters in password (0 - 128, default = 0).	integer	Minimum value: 0 Maximum value: 128	0						
min-upper-case-letter	Minimum number of uppercase characters in password (0 - 128, default = 0).	integer	Minimum value: 0 Maximum value: 128	0						
min-non-alphanumeric	Minimum number of non-alphanumeric characters in password (0 - 128, default = 0).	integer	Minimum value: 0 Maximum value: 128	0						
min-number	Minimum number of numeric characters in password (0 - 128, default = 0).	integer	Minimum value: 0 Maximum value: 128	0						

Parameter	Description	Type	Size	Default						
min-change-characters	Minimum number of unique characters in new password which do not exist in old password (0 - 128, default = 0. This attribute overrides reuse-password if both are enabled).	integer	Minimum value: 0 Maximum value: 128	0						
expire-status	Enable/disable password expiration.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Passwords expire after expire-day days.</td></tr><tr><td>disable</td><td>Passwords do not expire.</td></tr></table>	Option	Description	enable	Passwords expire after expire-day days.	disable	Passwords do not expire.			
Option	Description									
enable	Passwords expire after expire-day days.									
disable	Passwords do not expire.									
expire-day	Number of days after which passwords expire (1 - 999 days, default = 90).	integer	Minimum value: 1 Maximum value: 999	90						
reuse-password	Enable/disable reuse of password. If both reuse-password and min-change-characters are enabled, min-change-characters overrides.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Administrators are allowed to reuse the same password.</td></tr><tr><td>disable</td><td>Administrators must create a new password.</td></tr></table>	Option	Description	enable	Administrators are allowed to reuse the same password.	disable	Administrators must create a new password.			
Option	Description									
enable	Administrators are allowed to reuse the same password.									
disable	Administrators must create a new password.									
login-lockout-upon-downgrade	Enable/disable administrative user login lockout upon downgrade (default = disable). If enabled, downgrading the FortiOS firmware to a lower version where safer passwords are unsupported will lock out administrative users.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable administrative user login lockout upon downgrade.</td></tr><tr><td>disable</td><td>Disable administrative user login lockout upon downgrade.</td></tr></table>	Option	Description	enable	Enable administrative user login lockout upon downgrade.	disable	Disable administrative user login lockout upon downgrade.			
Option	Description									
enable	Enable administrative user login lockout upon downgrade.									
disable	Disable administrative user login lockout upon downgrade.									
password-history	Number of previous passwords that cannot be reused.	integer	Minimum value: 2 Maximum value: 20	2						

config system password-policy-guest-admin

Configure the password policy for guest administrators.


```

config system password-policy-guest-admin
    Description: Configure the password policy for guest administrators.
    set status [enable|disable]
    set apply-to {option1}, {option2}, ...
    set minimum-length {integer}
    set min-lower-case-letter {integer}
    set min-upper-case-letter {integer}
    set min-non-alphanumeric {integer}
    set min-number {integer}
    set min-change-characters {integer}
    set expire-status [enable|disable]
    set expire-day {integer}
    set reuse-password [enable|disable]
    set password-history {integer}
end

```

config system password-policy-guest-admin

Parameter	Description	Type	Size	Default						
status	Enable/disable setting a password policy for locally defined administrator passwords and IPsec VPN pre-shared keys.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable password policy.</td></tr><tr><td><i>disable</i></td><td>Disable password policy.</td></tr></table>	Option	Description	<i>enable</i>	Enable password policy.	<i>disable</i>	Disable password policy.			
Option	Description									
<i>enable</i>	Enable password policy.									
<i>disable</i>	Disable password policy.									
apply-to	Guest administrator to which this password policy applies.	option	-	guest-admin-password						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>guest-admin-password</i></td><td>Apply to guest administrator password.</td></tr></table>	Option	Description	<i>guest-admin-password</i>	Apply to guest administrator password.					
Option	Description									
<i>guest-admin-password</i>	Apply to guest administrator password.									
minimum-length	Minimum password length (8 - 128, default = 8).	integer	Minimum value: 8 Maximum value: 128	8						
min-lower-case-letter	Minimum number of lowercase characters in password (0 - 128, default = 0).	integer	Minimum value: 0 Maximum value: 128	0						

Parameter	Description	Type	Size	Default
min-upper-case-letter	Minimum number of uppercase characters in password (0 - 128, default = 0).	integer	Minimum value: 0 Maximum value: 128	0
min-non-alphanumeric	Minimum number of non-alphanumeric characters in password (0 - 128, default = 0).	integer	Minimum value: 0 Maximum value: 128	0
min-number	Minimum number of numeric characters in password (0 - 128, default = 0).	integer	Minimum value: 0 Maximum value: 128	0
min-change-characters	Minimum number of unique characters in new password which do not exist in old password (0 - 128, default = 0. This attribute overrides reuse-password if both are enabled).	integer	Minimum value: 0 Maximum value: 128	0
expire-status	Enable/disable password expiration.	option	-	disable
	Option	Description		
	enable	Passwords expire after expire-day days.		
	disable	Passwords do not expire.		
expire-day	Number of days after which passwords expire (1 - 999 days, default = 90).	integer	Minimum value: 1 Maximum value: 999	90
reuse-password	Enable/disable reuse of password. If both reuse-password and min-change-characters are enabled, min-change-characters overrides.	option	-	enable
	Option	Description		
	enable	Administrators are allowed to reuse the same password.		
	disable	Administrators must create a new password.		
password-history	Number of previous passwords that cannot be reused.	integer	Minimum value: 2 Maximum value: 20	2

config system performance status

System performance status.

```
config system performance status
    Description: System performance status.
end
```

config system performance top

Display information about the top CPU processes.

```
config system performance top
    Description: Display information about the top CPU processes.
    set <delay> {string}
end
```

config system performance top

Parameter	Description	Type	Size	Default
<delay>	Delay in seconds (default 5).	string	Maximum length: -	

config system probe-response

Configure system probe response.

```
config system probe-response
    Description: Configure system probe response.
    set port {integer}
    set http-probe-value {string}
    set ttl-mode [reinit|decrease|...]
    set mode [none|http-probe|...]
    set security-mode [none|authentication]
    set password {password}
    set timeout {integer}
end
```

config system probe-response

Parameter	Description	Type	Size	Default
port	Port number to response.	integer	Minimum value: 1 Maximum value: 65535	8008
http-probe-value	Value to respond to the monitoring server.	string	Maximum length: 1024	OK
ttl-mode	Mode for TWAMP packet TTL modification.	option	-	retain
	Option	Description		
	<i>reinit</i>	Reinitialize TTL.		
	<i>decrease</i>	Decrease TTL.		
	<i>retain</i>	Retain TTL.		
mode	SLA response mode.	option	-	none
	Option	Description		
	<i>none</i>	Disable probe.		
	<i>http-probe</i>	HTTP probe.		
	<i>twamp</i>	Two way active measurement protocol.		
security-mode	TWAMP responder security mode.	option	-	none
	Option	Description		
	<i>none</i>	Unauthenticated mode.		
	<i>authentication</i>	Authenticated mode.		
password	TWAMP responder password in authentication mode.	password	Not Specified	
timeout	An inactivity timer for a twamp test session.	integer	Minimum value: 10 Maximum value: 3600	300

config system proxy-arp

Configure proxy-ARP.

```
config system proxy-arp
  Description: Configure proxy-ARP.
  edit <id>
    set interface {string}
    set ip {ipv4-address}
    set end-ip {ipv4-address}
  next
end
```

config system proxy-arp

Parameter	Description	Type	Size	Default
id	Unique integer ID of the entry.	integer	Minimum value: 0 Maximum value: 4294967295	0
interface	Interface acting proxy-ARP.	string	Maximum length: 15	
ip	IP address or start IP to be proxied.	ipv4-address	Not Specified	0.0.0.0
end-ip	End IP of IP range to be proxied.	ipv4-address	Not Specified	0.0.0.0

config system ptp

Configure system PTP information.

```
config system ptp
  Description: Configure system PTP information.
  set status [enable|disable]
  set mode [multicast|hybrid]
  set delay-mechanism [E2E|P2P]
  set request-interval {integer}
  set interface {string}
  set server-mode [enable|disable]
  config server-interface
    Description: FortiGate interface(s) with PTP server mode enabled. Devices on your network
    can contact these interfaces for PTP services.
    edit <id>
```

```

        set server-interface-name {string}
        set delay-mechanism [E2E|P2P]
    next
end
end

```

config system ptp

Parameter	Description	Type	Size	Default						
status	Enable/disable setting the FortiProxy system time by synchronizing with an PTP Server.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable synchronization with PTP Server.</td></tr><tr><td><i>disable</i></td><td>Disable synchronization with PTP Server.</td></tr></table>	Option	Description	<i>enable</i>	Enable synchronization with PTP Server.	<i>disable</i>	Disable synchronization with PTP Server.			
Option	Description									
<i>enable</i>	Enable synchronization with PTP Server.									
<i>disable</i>	Disable synchronization with PTP Server.									
mode	Multicast transmission or hybrid transmission.	option	-	multicast						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>multicast</i></td><td>Send PTP packets with multicast.</td></tr><tr><td><i>hybrid</i></td><td>Send PTP packets with unicast and multicast.</td></tr></table>	Option	Description	<i>multicast</i>	Send PTP packets with multicast.	<i>hybrid</i>	Send PTP packets with unicast and multicast.			
Option	Description									
<i>multicast</i>	Send PTP packets with multicast.									
<i>hybrid</i>	Send PTP packets with unicast and multicast.									
delay-mechanism	End to end delay detection or peer to peer delay detection.	option	-	E2E						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>E2E</i></td><td>End to end delay detection.</td></tr><tr><td><i>P2P</i></td><td>Peer to peer delay detection.</td></tr></table>	Option	Description	<i>E2E</i>	End to end delay detection.	<i>P2P</i>	Peer to peer delay detection.			
Option	Description									
<i>E2E</i>	End to end delay detection.									
<i>P2P</i>	Peer to peer delay detection.									
request-interval	The delay request value is the logarithmic mean interval in seconds between the delay request messages sent by the slave to the master.	integer	Minimum value: 1 Maximum value: 6	1						
interface	PTP client will reply through this interface.	string	Maximum length: 15							
server-mode	Enable/disable FortiGate PTP server mode. Your FortiGate becomes an PTP server for other devices on your network.	option	-	disable						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable FortiGate PTP server mode.		
	<i>disable</i>	Disable FortiGate PTP server mode.		

config server-interface

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
server-interface-name	Interface name.	string	Maximum length: 15	
delay-mechanism	End to end delay detection or peer to peer delay detection.	option	-	E2E
	Option	Description		
	<i>E2E</i>	End to end delay detection.		
	<i>P2P</i>	Peer to peer delay detection.		

config system replacemsg admin

Replacement messages.

```

config system replacemsg admin
  Description: Replacement messages.
  edit <msg-type>
    set buffer {var-string}
    set header [none|http|...]
    set format [none|text|...]
  next
end

```

config system replacemsg admin

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config system replacemsg alertmail

Replacement messages.

```
config system replacemsg alertmail
  Description: Replacement messages.
  edit <msg-type>
    set buffer {var-string}
    set header [none|http|...]
    set format [none|text|...]
  next
end
```


config system replacemsg alertmail

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config system replacemsg auth

Replacement messages.

```
config system replacemsg auth
  Description: Replacement messages.
  edit <msg-type>
    set buffer {var-string}
    set header [none|http|...]
    set format [none|text|...]
  next
end
```

config system replacemsg auth

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option Description			
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option Description			
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config system replacemsg automation

Replacement messages.

```
config system replacemsg automation
  Description: Replacement messages.
  edit <msg-type>
    set buffer {var-string}
    set header [none|http|...]
    set format [none|text|...]
  next
end
```

config system replacemsg automation

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option	Description		
	none	No header type.		
	http	HTTP		
	8bit	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	none	No format type.		
	text	Text format.		
	html	HTML format.		

config system replacemsg custom-message

Replacement messages.

```
config system replacemsg custom-message
  Description: Replacement messages.
  edit <msg-type>
    set buffer {var-string}
    set header [none|http|...]
    set format [none|text|...]
  next
end
```

config system replacemsg custom-message

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option Description			
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option Description			
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config system replacemsg fortiguard-wf

Replacement messages.

```
config system replacemsg fortiguard-wf
  Description: Replacement messages.
  edit <msg-type>
    set buffer {var-string}
    set header [none|http|...]
    set format [none|text|...]
  next
end
```

config system replacemsg fortiguard-wf

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config system replacemsg ftp

Replacement messages.

```
config system replacemsg ftp
  Description: Replacement messages.
  edit <msg-type>
    set buffer {var-string}
    set header [none|http|...]
    set format [none|text|...]
  next
end
```

config system replacemsg ftp

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	OptionDescription			
	none	No header type.		
	http	HTTP		
	8bit	8 bit.		
format	Format flag.	option	-	none
	OptionDescription			
	none	No format type.		
	text	Text format.		
	html	HTML format.		

config system replacemsg http

Replacement messages.

```
config system replacemsg http
  Description: Replacement messages.
  edit <msg-type>
    set buffer {var-string}
    set header [none|http|...]
    set format [none|text|...]
  next
end
```

config system replacemsg http

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config system replacemsg icap

Replacement messages.

```
config system replacemsg icap
  Description: Replacement messages.
  edit <msg-type>
    set buffer {var-string}
    set header [none|http|...]
    set format [none|text|...]
  next
end
```

config system replacemsg icap

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	OptionDescription			
	none	No header type.		
	http	HTTP		
	8bit	8 bit.		
format	Format flag.	option	-	none
	OptionDescription			
	none	No format type.		
	text	Text format.		
	html	HTML format.		

config system replacemsg mail

Replacement messages.

```
config system replacemsg mail
  Description: Replacement messages.
  edit <msg-type>
    set buffer {var-string}
    set header [none|http|...]
    set format [none|text|...]
  next
end
```


config system replacemsg mail

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option	Description		
	none	No header type.		
	http	HTTP		
	8bit	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	none	No format type.		
	text	Text format.		
	html	HTML format.		

config system replacemsg nac-quar

Replacement messages.

```
config system replacemsg nac-quar
  Description: Replacement messages.
  edit <msg-type>
    set buffer {var-string}
    set header [none|http|...]
    set format [none|text|...]
  next
end
```

config system replacemsg nac-quar

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option	Description		
	none	No header type.		
	http	HTTP		
	8bit	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	none	No format type.		
	text	Text format.		
	html	HTML format.		

config system replacemsg spam

Replacement messages.

```
config system replacemsg spam
  Description: Replacement messages.
  edit <msg-type>
    set buffer {var-string}
    set header [none|http|...]
    set format [none|text|...]
  next
end
```

config system replacemsg spam

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config system replacemsg sslvpn

Replacement messages.

```
config system replacemsg sslvpn
  Description: Replacement messages.
  edit <msg-type>
    set buffer {var-string}
    set header [none|http|...]
    set format [none|text|...]
  next
end
```

config system replacemsg sslvpn

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	OptionDescription			
	none	No header type.		
	http	HTTP		
	8bit	8 bit.		
format	Format flag.	option	-	none
	OptionDescription			
	none	No format type.		
	text	Text format.		
	html	HTML format.		

config system replacemsg traffic-quota

Replacement messages.

```
config system replacemsg traffic-quota
  Description: Replacement messages.
  edit <msg-type>
    set buffer {var-string}
    set header [none|http|...]
    set format [none|text|...]
  next
end
```

config system replacemsg traffic-quota

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config system replacemsg utm

Replacement messages.

```
config system replacemsg utm
  Description: Replacement messages.
  edit <msg-type>
    set buffer {var-string}
    set header [none|http|...]
    set format [none|text|...]
  next
end
```

config system replacemsg utm

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option Description			
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option Description			
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config system replacemsg webproxy

Replacement messages.

```
config system replacemsg webproxy
  Description: Replacement messages.
  edit <msg-type>
    set buffer {var-string}
    set header [none|http|...]
    set format [none|text|...]
  next
end
```

config system replacemsg webproxy

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	OptionDescription			
	none	No header type.		
	http	HTTP		
	8bit	8 bit.		
format	Format flag.	option	-	none
	OptionDescription			
	none	No format type.		
	text	Text format.		
	html	HTML format.		

config system replacemsg-group

Configure replacement message groups.

```
config system replacemsg-group
  Description: Configure replacement message groups.
  edit <name>
    set comment {var-string}
    set group-type [default|utm|...]
    config mail
      Description: Replacement message table entries.
      edit <msg-type>
        set buffer {var-string}
        set header [none|http|...]
        set format [none|text|...]
      next
    end
  config http
    Description: Replacement message table entries.
    edit <msg-type>
      set buffer {var-string}
```

```

        set header [none|http|...]
        set format [none|text|...]
    next
end
config webproxy
    Description: Replacement message table entries.
    edit <msg-type>
        set buffer {var-string}
        set header [none|http|...]
        set format [none|text|...]
    next
end
config ftp
    Description: Replacement message table entries.
    edit <msg-type>
        set buffer {var-string}
        set header [none|http|...]
        set format [none|text|...]
    next
end
config fortiguard-wf
    Description: Replacement message table entries.
    edit <msg-type>
        set buffer {var-string}
        set header [none|http|...]
        set format [none|text|...]
    next
end
config spam
    Description: Replacement message table entries.
    edit <msg-type>
        set buffer {var-string}
        set header [none|http|...]
        set format [none|text|...]
    next
end
config alertmail
    Description: Replacement message table entries.
    edit <msg-type>
        set buffer {var-string}
        set header [none|http|...]
        set format [none|text|...]
    next
end
config admin
    Description: Replacement message table entries.
    edit <msg-type>
        set buffer {var-string}
        set header [none|http|...]
        set format [none|text|...]
    next
end

```



```

config auth
    Description: Replacement message table entries.
    edit <msg-type>
        set buffer {var-string}
        set header [none|http|...]
        set format [none|text|...]
    next
end
config sslvpn
    Description: Replacement message table entries.
    edit <msg-type>
        set buffer {var-string}
        set header [none|http|...]
        set format [none|text|...]
    next
end
config nac-quar
    Description: Replacement message table entries.
    edit <msg-type>
        set buffer {var-string}
        set header [none|http|...]
        set format [none|text|...]
    next
end
config traffic-quota
    Description: Replacement message table entries.
    edit <msg-type>
        set buffer {var-string}
        set header [none|http|...]
        set format [none|text|...]
    next
end
config utm
    Description: Replacement message table entries.
    edit <msg-type>
        set buffer {var-string}
        set header [none|http|...]
        set format [none|text|...]
    next
end
config custom-message
    Description: Replacement message table entries.
    edit <msg-type>
        set buffer {var-string}
        set header [none|http|...]
        set format [none|text|...]
    next
end
config icap
    Description: Replacement message table entries.
    edit <msg-type>
        set buffer {var-string}

```

```

        set header [none|http|...]
        set format [none|text|...]
    next
end
config automation
    Description: Replacement message table entries.
    edit <msg-type>
        set buffer {var-string}
        set header [none|http|...]
        set format [none|text|...]
    next
end
next
end

```

config system replacemsg-group

Parameter	Description	Type	Size	Default								
name	Group name.	string	Maximum length: 35									
comment	Comment.	var-string	Maximum length: 255									
group-type	Group type.	option	-	default								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Per-vdom replacement messages.</td></tr><tr><td><i>utm</i></td><td>For use with UTM settings in firewall policies.</td></tr><tr><td><i>auth</i></td><td>For use with authentication pages in firewall policies.</td></tr></table>				Option	Description	<i>default</i>	Per-vdom replacement messages.	<i>utm</i>	For use with UTM settings in firewall policies.	<i>auth</i>	For use with authentication pages in firewall policies.
Option	Description											
<i>default</i>	Per-vdom replacement messages.											
<i>utm</i>	For use with UTM settings in firewall policies.											
<i>auth</i>	For use with authentication pages in firewall policies.											

config mail

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config http

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config webproxy

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option Description			
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option Description			
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config ftp

Parameter	Description	Type	Size	Default								
msg-type	Message type.	string	Maximum length: 28									
buffer	Message string.	var-string	Maximum length: 32768									
header	Header flag.	option	-	none								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>none</i></td><td>No header type.</td></tr><tr><td><i>http</i></td><td>HTTP</td></tr><tr><td><i>8bit</i></td><td>8 bit.</td></tr></table>				Option	Description	<i>none</i>	No header type.	<i>http</i>	HTTP	<i>8bit</i>	8 bit.
	Option	Description										
	<i>none</i>	No header type.										
	<i>http</i>	HTTP										
<i>8bit</i>	8 bit.											
format	Format flag.	option	-	none								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config fortiguard-wf

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config spam

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config alertmail

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config admin

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option Description			
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option Description			
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config auth

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config sslvpn

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config nac-quar

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config traffic-quota

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config utm

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option Description			
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option Description			
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config custom-message

Parameter	Description	Type	Size	Default								
msg-type	Message type.	string	Maximum length: 28									
buffer	Message string.	var-string	Maximum length: 32768									
header	Header flag.	option	-	none								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>none</i></td><td>No header type.</td></tr><tr><td><i>http</i></td><td>HTTP</td></tr><tr><td><i>8bit</i></td><td>8 bit.</td></tr></table>				Option	Description	<i>none</i>	No header type.	<i>http</i>	HTTP	<i>8bit</i>	8 bit.
	Option	Description										
	<i>none</i>	No header type.										
	<i>http</i>	HTTP										
<i>8bit</i>	8 bit.											
format	Format flag.	option	-	none								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config icap

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config automation

Parameter	Description	Type	Size	Default
msg-type	Message type.	string	Maximum length: 28	
buffer	Message string.	var-string	Maximum length: 32768	
header	Header flag.	option	-	none

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>none</i>	No header type.		
	<i>http</i>	HTTP		
	<i>8bit</i>	8 bit.		
format	Format flag.	option	-	none
	Option	Description		
	<i>none</i>	No format type.		
	<i>text</i>	Text format.		
	<i>html</i>	HTML format.		

config system replacemsg-image

Configure replacement message images.

```
config system replacemsg-image
  Description: Configure replacement message images.
  edit <name>
    set image-type [gif|jpg|...]
    set image-base64 {var-string}
  next
end
```

config system replacemsg-image

Parameter	Description	Type	Size	Default
name	Image name.	string	Maximum length: 23	
image-type	Image type.	option	-	png
	Option	Description		
	<i>gif</i>	GIF image.		
	<i>jpg</i>	JPEG image.		
	<i>tiff</i>	TIFF image.		
	<i>png</i>	PNG image.		

Parameter	Description	Type	Size	Default
image-base64	Image data.	var-string	Maximum length: 32768	

config system resource-limits

Configure resource limits.

```

config system resource-limits
    Description: Configure resource limits.
    set ipsec-phase1-interface {integer}
    set ipsec-phase2-interface {integer}
    set firewall-policy {integer}
    set firewall-address {integer}
    set firewall-addrgrp {integer}
    set custom-service {integer}
    set service-group {integer}
    set onetime-schedule {integer}
    set recurring-schedule {integer}
    set user {integer}
    set user-group {integer}
    set proxy {integer}
    set log-disk-quota {integer}
end

```

config system resource-limits

Parameter	Description	Type	Size	Default
ipsec-phase1-interface	Maximum number of VPN IPsec phase1 interface tunnels.	integer	Minimum value: 0 Maximum value: 4294967295	
ipsec-phase2-interface	Maximum number of VPN IPsec phase2 interface tunnels.	integer	Minimum value: 0 Maximum value: 4294967295	
firewall-policy	Maximum number of firewall policies (policy, DoS-policy4, DoS-policy6, multicast).	integer	Minimum value: 0 Maximum value: 4294967295	

Parameter	Description	Type	Size	Default
firewall-address	Maximum number of firewall addresses (IPv4, IPv6, multicast).	integer	Minimum value: 0 Maximum value: 4294967295	
firewall-addrgrp	Maximum number of firewall address groups (IPv4, IPv6).	integer	Minimum value: 0 Maximum value: 4294967295	
custom-service	Maximum number of firewall custom services.	integer	Minimum value: 0 Maximum value: 4294967295	
service-group	Maximum number of firewall service groups.	integer	Minimum value: 0 Maximum value: 4294967295	
onetime-schedule	Maximum number of firewall one-time schedules.	integer	Minimum value: 0 Maximum value: 4294967295	
recurring-schedule	Maximum number of firewall recurring schedules.	integer	Minimum value: 0 Maximum value: 4294967295	
user	Maximum number of local users.	integer	Minimum value: 0 Maximum value: 4294967295	
user-group	Maximum number of user groups.	integer	Minimum value: 0 Maximum value: 4294967295	

Parameter	Description	Type	Size	Default
proxy	Maximum number of concurrent proxy users.	integer	Minimum value: 0 Maximum value: 4294967295	
log-disk-quota	Log disk quota in megabytes (MB).	integer	Minimum value: 0 Maximum value: 4294967295	0

config system saml

Global settings for SAML authentication.

```

config system saml
  Description: Global settings for SAML authentication.
  set status [enable|disable]
  set role [identity-provider|service-provider]
  set default-login-page [normal|sso]
  set default-profile {string}
  set cert {string}
  set binding-protocol [post|redirect]
  set portal-url {string}
  set entity-id {string}
  set single-sign-on-url {string}
  set single-logout-url {string}
  set idp-entity-id {string}
  set idp-single-sign-on-url {string}
  set idp-single-logout-url {string}
  set idp-cert {string}
  set server-address {string}
  set tolerance {integer}
  set life {integer}
  config service-providers
    Description: Authorized service providers.
    edit <name>
      set prefix {string}
      set sp-binding-protocol [post|redirect]
      set sp-cert {string}
      set sp-entity-id {string}
      set sp-single-sign-on-url {string}
      set sp-single-logout-url {string}
      set sp-portal-url {string}
      set idp-entity-id {string}
      set idp-single-sign-on-url {string}
      set idp-single-logout-url {string}

```

```

        config assertion-attributes
            Description: Customized SAML attributes to send along with assertion.
            edit <name>
                set type [username|email|...]
            next
        end
    next
end
end
end

```

config system saml

Parameter	Description	Type	Size	Default
status	Enable/disable SAML authentication (default = disable).	option	-	disable
	Option	Description		
	<i>enable</i>	Enable SAML authentication.		
	<i>disable</i>	Disable SAML authentication.		
role	SAML role.	option	-	service-provider
	Option	Description		
	<i>identity-provider</i>	Identity Provider.		
	<i>service-provider</i>	Service Provider.		
default-login-page	Choose default login page.	option	-	normal
	Option	Description		
	<i>normal</i>	Use local login page as default.		
	<i>sso</i>	Use IdP's Single Sign-On page as default.		
default-profile	Default profile for new SSO admin.	string	Maximum length: 35	
cert	Certificate to sign SAML messages.	string	Maximum length: 35	
binding-protocol	IdP Binding protocol.	option	-	redirect

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>post</i>	HTTP POST binding.		
	<i>redirect</i>	HTTP Redirect binding.		
portal-url	SP portal URL.	string	Maximum length: 255	
entity-id	SP entity ID.	string	Maximum length: 255	
single-sign-on-url	SP single sign-on URL.	string	Maximum length: 255	
single-logout-url	SP single logout URL.	string	Maximum length: 255	
idp-entity-id	IDP entity ID.	string	Maximum length: 255	
idp-single-sign-on-url	IDP single sign-on URL.	string	Maximum length: 255	
idp-single-logout-url	IDP single logout URL.	string	Maximum length: 255	
idp-cert	IDP certificate name.	string	Maximum length: 35	
server-address	Server address.	string	Maximum length: 63	
tolerance	Tolerance to the range of time when the assertion is valid (in minutes).	integer	Minimum value: 0 Maximum value: 4294967295	5
life	Length of the range of time when the assertion is valid (in minutes).	integer	Minimum value: 0 Maximum value: 4294967295	30

config service-providers

Parameter	Description	Type	Size	Default
name	Name.	string	Maximum length: 35	

Parameter	Description	Type	Size	Default						
prefix	Prefix.	string	Maximum length: 35							
sp-binding-protocol	SP binding protocol.	option	-	post						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>post</i></td><td>HTTP POST binding.</td></tr><tr><td><i>redirect</i></td><td>HTTP Redirect binding.</td></tr></table>				Option	Description	<i>post</i>	HTTP POST binding.	<i>redirect</i>	HTTP Redirect binding.
	Option	Description								
	<i>post</i>	HTTP POST binding.								
	<i>redirect</i>	HTTP Redirect binding.								
sp-cert	SP certificate name.	string	Maximum length: 35							
sp-entity-id	SP entity ID.	string	Maximum length: 255							
sp-single-sign-on-url	SP single sign-on URL.	string	Maximum length: 255							
sp-single-logout-url	SP single logout URL.	string	Maximum length: 255							
sp-portal-url	SP portal URL.	string	Maximum length: 255							
idp-entity-id	IDP entity ID.	string	Maximum length: 255							
idp-single-sign-on-url	IDP single sign-on URL.	string	Maximum length: 255							
idp-single-logout-url	IDP single logout URL.	string	Maximum length: 255							

config assertion-attributes

Parameter	Description	Type	Size	Default								
name	Name.	string	Maximum length: 35									
type	Type.	option	-	username								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>username</i></td><td>User Name.</td></tr><tr><td><i>email</i></td><td>Email Address.</td></tr><tr><td><i>profile-name</i></td><td>Profile Name.</td></tr></table>				Option	Description	<i>username</i>	User Name.	<i>email</i>	Email Address.	<i>profile-name</i>	Profile Name.
	Option	Description										
	<i>username</i>	User Name.										
	<i>email</i>	Email Address.										
<i>profile-name</i>	Profile Name.											

config system sdn-connector

Configure connection to SDN Connector.

```
config system sdn-connector
  Description: Configure connection to SDN Connector.
  edit <name>
    set status [disable|enable]
    set type [aci|alicloud|...]
    set use-metadata-iam [disable|enable]
    set ha-status [disable|enable]
    set verify-certificate [disable|enable]
    set server {string}
    set server-list <ip1>, <ip2>, ...
    set server-port {integer}
    set username {string}
    set password {password_aes256}
    set vcenter-server {string}
    set vcenter-username {string}
    set vcenter-password {password_aes256}
    set access-key {string}
    set secret-key {password}
    set region {string}
    set vpc-id {string}
    set alt-resource-ip [disable|enable]
  config external-account-list
    Description: Configure AWS external account list.
    edit <role-arn>
      set external-id {string}
      set region-list <region1>, <region2>, ...
    next
  end
  set tenant-id {string}
  set client-id {string}
  set client-secret {password}
  set subscription-id {string}
  set resource-group {string}
  set login-endpoint {string}
  set resource-url {string}
  set azure-region [global|china|...]
  config nic
    Description: Configure Azure network interface.
    edit <name>
      config ip
        Description: Configure IP configuration.
        edit <name>
          set public-ip {string}
          set resource-group {string}
        next
      end
    next
  next
```

```

end
config route-table
    Description: Configure Azure route table.
    edit <name>
        set subscription-id {string}
        set resource-group {string}
        config route
            Description: Configure Azure route.
            edit <name>
                set next-hop {string}
            next
        end
    next
end
set user-id {string}
set compartment-id {string}
set oci-region {string}
set oci-region-type [commercial|government]
set oci-cert {string}
set oci-fingerprint {string}
config external-ip
    Description: Configure GCP external IP.
    edit <name>
    next
end
config route
    Description: Configure GCP route.
    edit <name>
    next
end
config gcp-project-list
    Description: Configure GCP project list.
    edit <id>
        set gcp-zone-list <name1>, <name2>, ...
    next
end
config forwarding-rule
    Description: Configure GCP forwarding rule.
    edit <rule-name>
        set target {string}
    next
end
set service-account {string}
set private-key {user}
set secret-token {user}
set domain {string}
set group-name {string}
set server-cert {string}
set server-ca-cert {string}
set api-key {password}
set compute-generation {integer}
set ibm-region [dallas|washington-dc|...]

```

```

        set update-interval {integer}
    next
end

```

config system sdn-connector

Parameter	Description	Type	Size	Default
name	SDN connector name.	string	Maximum length: 35	
status	Enable/disable connection to the remote SDN connector.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable connection to this SDN Connector.		
	<i>enable</i>	Enable connection to this SDN Connector.		
type	Type of SDN connector.	option	-	aws
	Option	Description		
	<i>aci</i>	Application Centric Infrastructure (ACI).		
	<i>alicloud</i>	AliCloud Service (ACS).		
	<i>aws</i>	Amazon Web Services (AWS).		
	<i>azure</i>	Microsoft Azure.		
	<i>gcp</i>	Google Cloud Platform (GCP).		
	<i>nsx</i>	VMware NSX.		
	<i>nuage</i>	Nuage VSP.		
	<i>oci</i>	Oracle Cloud Infrastructure.		
	<i>openstack</i>	OpenStack.		
	<i>kubernetes</i>	Kubernetes.		
	<i>vmware</i>	VMware vSphere (vCenter & ESXi).		
	<i>sepm</i>	Symantec Endpoint Protection Manager.		
	<i>aci-direct</i>	Application Centric Infrastructure (ACI Direct Connection).		
	<i>ibm</i>	IBM Cloud Infrastructure.		
	<i>nutanix</i>	Nutanix Prism Central.		
	<i>sap</i>	SAP Control.		

Parameter	Description	Type	Size	Default						
use-metadata-iam	Enable/disable use of IAM role from metadata to call API.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable using IAM role to call API.</td></tr><tr><td><i>enable</i></td><td>Enable using IAM role to call API.</td></tr></table>	Option	Description	<i>disable</i>	Disable using IAM role to call API.	<i>enable</i>	Enable using IAM role to call API.			
	Option	Description								
	<i>disable</i>	Disable using IAM role to call API.								
<i>enable</i>	Enable using IAM role to call API.									
ha-status	Enable/disable use for FortiProxy HA service.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable use for FortiProxy HA service.</td></tr><tr><td><i>enable</i></td><td>Enable use for FortiProxy HA service.</td></tr></table>	Option	Description	<i>disable</i>	Disable use for FortiProxy HA service.	<i>enable</i>	Enable use for FortiProxy HA service.			
	Option	Description								
	<i>disable</i>	Disable use for FortiProxy HA service.								
<i>enable</i>	Enable use for FortiProxy HA service.									
verify-certificate	Enable/disable server certificate verification.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable server certificate verification.</td></tr><tr><td><i>enable</i></td><td>Enable server certificate verification.</td></tr></table>	Option	Description	<i>disable</i>	Disable server certificate verification.	<i>enable</i>	Enable server certificate verification.			
	Option	Description								
	<i>disable</i>	Disable server certificate verification.								
<i>enable</i>	Enable server certificate verification.									
server	Server address of the remote SDN connector.	string	Maximum length: 127							
server-list <ip>	Server address list of the remote SDN connector. IPv4 address.	string	Maximum length: 15							
server-port	Port number of the remote SDN connector.	integer	Minimum value: 0 Maximum value: 65535	0						
username	Username of the remote SDN connector as login credentials.	string	Maximum length: 64							
password	Password of the remote SDN connector as login credentials.	password_aes256	Not Specified							
vcenter-server	vCenter server address for NSX quarantine.	string	Maximum length: 127							
vcenter-username	vCenter server username for NSX quarantine.	string	Maximum length: 64							

Parameter	Description	Type	Size	Default								
vcenter-password	vCenter server password for NSX quarantine.	password_aes256	Not Specified									
access-key	AWS / ACS access key ID.	string	Maximum length: 31									
secret-key	AWS / ACS secret access key.	password	Not Specified									
region	AWS / ACS region name.	string	Maximum length: 31									
vpc-id	AWS VPC ID.	string	Maximum length: 31									
alt-resource-ip	Enable/disable AWS alternative resource IP.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>disable</td><td>Disable AWS alternative resource IP.</td></tr><tr><td>enable</td><td>Enable AWS alternative resource IP.</td></tr></table>				Option	Description	disable	Disable AWS alternative resource IP.	enable	Enable AWS alternative resource IP.		
	Option	Description										
	disable	Disable AWS alternative resource IP.										
enable	Enable AWS alternative resource IP.											
tenant-id	Tenant ID (directory ID).	string	Maximum length: 127									
client-id	Azure client ID (application ID).	string	Maximum length: 63									
client-secret	Azure client secret (application key).	password	Not Specified									
subscription-id	Azure subscription ID.	string	Maximum length: 63									
resource-group	Azure resource group.	string	Maximum length: 63									
login-endpoint	Azure Stack login endpoint.	string	Maximum length: 127									
resource-url	Azure Stack resource URL.	string	Maximum length: 127									
azure-region	Azure server region.	option	-	global								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>global</td><td>Global Azure Server.</td></tr><tr><td>china</td><td>China Azure Server.</td></tr><tr><td>germany</td><td>Germany Azure Server.</td></tr></table>				Option	Description	global	Global Azure Server.	china	China Azure Server.	germany	Germany Azure Server.
	Option	Description										
	global	Global Azure Server.										
	china	China Azure Server.										
germany	Germany Azure Server.											

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>usgov</i>	US Government Azure Server.		
	<i>local</i>	Azure Stack Local Server.		
user-id	User ID.	string	Maximum length: 127	
compartment-id	Compartment ID.	string	Maximum length: 127	
oci-region	OCI server region.	string	Maximum length: 31	
oci-region-type	OCI region type.	option	-	commercial
	Option	Description		
	<i>commercial</i>	Commercial region.		
	<i>government</i>	Government region.		
oci-cert	OCI certificate.	string	Maximum length: 63	
oci-fingerprint	OCI pubkey fingerprint.	string	Maximum length: 63	
service-account	GCP service account email.	string	Maximum length: 127	
private-key	Private key of GCP service account.	user	Not Specified	
secret-token	Secret token of Kubernetes service account.	user	Not Specified	
domain	Domain name.	string	Maximum length: 127	
group-name	Full path group name of computers.	string	Maximum length: 127	
server-cert	Trust servers that contain this certificate only.	string	Maximum length: 127	
server-ca-cert	Trust only those servers whose certificate is directly/indirectly signed by this certificate.	string	Maximum length: 127	
api-key	IBM cloud API key or service ID API key.	password	Not Specified	

Parameter	Description	Type	Size	Default																				
compute-generation	Compute generation for IBM cloud infrastructure.	integer	Minimum value: 1 Maximum value: 2	2																				
ibm-region	IBM cloud region name.	option	-	dallas																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>dallas</td><td>US South (Dallas) Public Endpoint.</td></tr><tr><td>washington-dc</td><td>US East (Washington DC) Public Endpoint.</td></tr><tr><td>london</td><td>United Kingdom (London) Public Endpoint.</td></tr><tr><td>frankfurt</td><td>Germany (Frankfurt) Public Endpoint.</td></tr><tr><td>sydney</td><td>Australia (Sydney) Public Endpoint.</td></tr><tr><td>tokyo</td><td>Japan (Tokyo) Public Endpoint.</td></tr><tr><td>osaka</td><td>Japan (Osaka) Public Endpoint.</td></tr><tr><td>toronto</td><td>Canada (Toronto) Public Endpoint.</td></tr><tr><td>sao-paulo</td><td>Brazil (Sao Paulo) Public Endpoint.</td></tr></table>	Option	Description	dallas	US South (Dallas) Public Endpoint.	washington-dc	US East (Washington DC) Public Endpoint.	london	United Kingdom (London) Public Endpoint.	frankfurt	Germany (Frankfurt) Public Endpoint.	sydney	Australia (Sydney) Public Endpoint.	tokyo	Japan (Tokyo) Public Endpoint.	osaka	Japan (Osaka) Public Endpoint.	toronto	Canada (Toronto) Public Endpoint.	sao-paulo	Brazil (Sao Paulo) Public Endpoint.			
	Option	Description																						
	dallas	US South (Dallas) Public Endpoint.																						
	washington-dc	US East (Washington DC) Public Endpoint.																						
	london	United Kingdom (London) Public Endpoint.																						
	frankfurt	Germany (Frankfurt) Public Endpoint.																						
	sydney	Australia (Sydney) Public Endpoint.																						
	tokyo	Japan (Tokyo) Public Endpoint.																						
	osaka	Japan (Osaka) Public Endpoint.																						
	toronto	Canada (Toronto) Public Endpoint.																						
sao-paulo	Brazil (Sao Paulo) Public Endpoint.																							
update-interval	Dynamic object update interval (30 - 3600 sec, default = 60, 0 = disabled).	integer	Minimum value: 0 Maximum value: 3600	60																				

config external-account-list

Parameter	Description	Type	Size	Default
role-arn	AWS role ARN to assume.	string	Maximum length: 2047	
external-id	AWS external ID.	string	Maximum length: 1399	
region-list <region>	AWS region name list. AWS region name.	string	Maximum length: 31	

config nic

Parameter	Description	Type	Size	Default
name	Network interface name.	string	Maximum length: 63	

config ip

Parameter	Description	Type	Size	Default
name	IP configuration name.	string	Maximum length: 63	
public-ip	Public IP name.	string	Maximum length: 63	
resource-group	Resource group of Azure public IP.	string	Maximum length: 63	

config route-table

Parameter	Description	Type	Size	Default
name	Route table name.	string	Maximum length: 63	
subscription-id	Subscription ID of Azure route table.	string	Maximum length: 63	
resource-group	Resource group of Azure route table.	string	Maximum length: 63	

config route

Parameter	Description	Type	Size	Default
name	Route name.	string	Maximum length: 63	
next-hop	Next hop address.	string	Maximum length: 127	

config external-ip

Parameter	Description	Type	Size	Default
name	External IP name.	string	Maximum length: 63	

config route

Parameter	Description	Type	Size	Default
name	Route name.	string	Maximum length: 63	

config gcp-project-list

Parameter	Description	Type	Size	Default
id	GCP project ID.	string	Maximum length: 127	
gcp-zone-list <name>	Configure GCP zone list. GCP zone name.	string	Maximum length: 127	

config forwarding-rule

Parameter	Description	Type	Size	Default
rule-name	Forwarding rule name.	string	Maximum length: 63	
target	Target instance name.	string	Maximum length: 63	

config system session

System IPv4 session.

```
config system session
  Description: System IPv4 session.
end
```

config system session6

System IPv6 session.

```
config system session6
  Description: System IPv6 session.
end
```

config system session-ttl

Configure global session TTL timers for this FortiProxy.

```
config system session-ttl
  Description: Configure global session TTL timers for this FortiProxy.
  set default {user}
  config port
    Description: Session TTL port.
    edit <id>
      set protocol {integer}
      set start-port {integer}
      set end-port {integer}
      set timeout {user}
    next
  end
end
```

config system session-ttl

Parameter	Description	Type	Size	Default
default	Default timeout.	user	Not Specified	

config port

Parameter	Description	Type	Size	Default
id	Table entry ID.	integer	Minimum value: 0 Maximum value: 65535	0
protocol	Protocol (0 - 255).	integer	Minimum value: 0 Maximum value: 255	0
start-port	Start port number.	integer	Minimum value: 0 Maximum value: 65535	0

Parameter	Description	Type	Size	Default
end-port	End port number.	integer	Minimum value: 0 Maximum value: 65535	0
timeout	Session timeout (TTL).	user	Not Specified	

config system settings

Configure VDOM settings.

```

config system settings
  Description: Configure VDOM settings.
  set comments {var-string}
  set opmode [nat|transparent]
  set forward-domain [enable|disable]
  set http-external-dest [fortiweb|forticache]
  set firewall-session-dirty [check-all|check-new|...]
  set manageip {user}
  set gateway {ipv4-address}
  set ip {ipv4-classnet-host}
  set manageip6 {ipv6-prefix}
  set gateway6 {ipv6-address}
  set ip6 {ipv6-prefix}
  set device {string}
  set utf8-spam-tagging [enable|disable]
  set wccp-cache-engine [enable|disable]
  set wccp-local-route [enable|disable]
  set vpn-stats-log {option1}, {option2}, ...
  set vpn-stats-period {integer}
  set mac-ttl {integer}
  set fw-session-hairpin [enable|disable]
  set prp-trailer-action [enable|disable]
  set snat-hairpin-traffic [enable|disable]
  set dhcp-proxy [enable|disable]
  set dhcp-proxy-interface-select-method [auto|specify]
  set dhcp-proxy-interface {string}
  set dhcp-server-ip {user}
  set dhcp6-server-ip {user}
  set gui-default-policy-columns <name1>, <name2>, ...
  set link-down-access [enable|disable]
  set asymroute [enable|disable]
  set asymroute-icmp [enable|disable]
  set tcp-session-without-syn [enable|disable]
  set ses-denied-traffic [enable|disable]
  set strict-src-check [enable|disable]

```

```
set allow-linkdown-path [enable|disable]
set asymroute6 [enable|disable]
set asymroute6-icmp [enable|disable]
set sctp-session-without-init [enable|disable]
set status [enable|disable]
set allow-subnet-overlap [enable|disable]
set deny-tcp-with-icmp [enable|disable]
set discovered-device-timeout {integer}
set email-portal-check-dns [disable|enable]
set gui-icap [enable|disable]
set gui-implicit-policy [enable|disable]
set gui-dns-database [enable|disable]
set gui-proxy-inspection [enable|disable]
set gui-multicast-policy [enable|disable]
set gui-dos-policy [enable|disable]
set gui-object-colors [enable|disable]
set gui-voip-profile [enable|disable]
set gui-security-profile-group [enable|disable]
set gui-wanopt-cache [enable|disable]
set gui-explicit-proxy [enable|disable]
set gui-policy-based-ipsec [enable|disable]
set gui-threat-weight [enable|disable]
set gui-spamfilter [enable|disable]
set gui-file-filter [enable|disable]
set gui-application-control [enable|disable]
set gui-ips [enable|disable]
set gui-dhcp-advanced [enable|disable]
set gui-vpn [enable|disable]
set gui-webfilter-advanced [enable|disable]
set gui-traffic-shaping [enable|disable]
set gui-antivirus [enable|disable]
set gui-webfilter [enable|disable]
set gui-videofilter [enable|disable]
set gui-dnsfilter [enable|disable]
set gui-advanced-policy [enable|disable]
set gui-allow-unnamed-policy [enable|disable]
set gui-email-collection [enable|disable]
set gui-multiple-interface-policy [enable|disable]
set gui-policy-disclaimer [enable|disable]
set gui-ztna [enable|disable]
set gui-ot [enable|disable]
set block-land-attack [disable|enable]
set default-app-port-as-service [enable|disable]
set application-bandwidth-tracking [disable|enable]
set default-policy-expiry-days {integer}
set gui-enforce-change-summary [disable|require|...]
set internet-service-database-cache [disable|enable]

end
```

config system settings

Parameter	Description	Type	Size	Default								
comments	VDOM comments.	var-string	Maximum length: 255									
opmode	Firewall operation mode (NAT or Transparent).	option	-	nat								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>nat</i></td><td>Change to NAT mode.</td></tr><tr><td><i>transparent</i></td><td>Change to transparent mode.</td></tr></table>	Option	Description	<i>nat</i>	Change to NAT mode.	<i>transparent</i>	Change to transparent mode.					
Option	Description											
<i>nat</i>	Change to NAT mode.											
<i>transparent</i>	Change to transparent mode.											
forward-domain	Enable/disable forward domain.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable forward domain.</td></tr><tr><td><i>disable</i></td><td>Disable forward domain.</td></tr></table>	Option	Description	<i>enable</i>	Enable forward domain.	<i>disable</i>	Disable forward domain.					
Option	Description											
<i>enable</i>	Enable forward domain.											
<i>disable</i>	Disable forward domain.											
http-external-dest	Offload HTTP traffic to FortiWeb or FortiCache.	option	-	fortiweb								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>fortiweb</i></td><td>Offload HTTP traffic to FortiWeb for Web Application Firewall inspection.</td></tr><tr><td><i>forticache</i></td><td>Offload HTTP traffic to FortiCache for external web caching and WAN optimization.</td></tr></table>	Option	Description	<i>fortiweb</i>	Offload HTTP traffic to FortiWeb for Web Application Firewall inspection.	<i>forticache</i>	Offload HTTP traffic to FortiCache for external web caching and WAN optimization.					
Option	Description											
<i>fortiweb</i>	Offload HTTP traffic to FortiWeb for Web Application Firewall inspection.											
<i>forticache</i>	Offload HTTP traffic to FortiCache for external web caching and WAN optimization.											
firewall-session-dirty	Select how to manage sessions affected by firewall policy configuration changes.	option	-	check-all								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>check-all</i></td><td>All sessions affected by a firewall policy change are flushed from the session table. When new packets are recieved they are re-evaluated by stateful inspection and re-added to the session table.</td></tr><tr><td><i>check-new</i></td><td>Established sessions for changed firewall policies continue without being affected by the policy configuration change. New sessions are evaluated according to the new firewall policy configuration.</td></tr><tr><td><i>check-policy-option</i></td><td>Sessions are managed individually depending on the firewall policy. Some sessions may restart. Some may continue.</td></tr></table>	Option	Description	<i>check-all</i>	All sessions affected by a firewall policy change are flushed from the session table. When new packets are recieved they are re-evaluated by stateful inspection and re-added to the session table.	<i>check-new</i>	Established sessions for changed firewall policies continue without being affected by the policy configuration change. New sessions are evaluated according to the new firewall policy configuration.	<i>check-policy-option</i>	Sessions are managed individually depending on the firewall policy. Some sessions may restart. Some may continue.			
Option	Description											
<i>check-all</i>	All sessions affected by a firewall policy change are flushed from the session table. When new packets are recieved they are re-evaluated by stateful inspection and re-added to the session table.											
<i>check-new</i>	Established sessions for changed firewall policies continue without being affected by the policy configuration change. New sessions are evaluated according to the new firewall policy configuration.											
<i>check-policy-option</i>	Sessions are managed individually depending on the firewall policy. Some sessions may restart. Some may continue.											

Parameter	Description	Type	Size	Default						
manageip	Transparent mode IPv4 management IP address and netmask.	user	Not Specified							
gateway	Transparent mode IPv4 default gateway IP address.	ipv4-address	Not Specified	0.0.0.0						
ip	IP address and netmask.	ipv4-classnet-host	Not Specified	0.0.0.0 0.0.0.0						
manageip6	Transparent mode IPv6 management IP address and netmask.	ipv6-prefix	Not Specified	::/0						
gateway6	Transparent mode IPv4 default gateway IP address.	ipv6-address	Not Specified	::						
ip6	IPv6 address prefix for NAT mode.	ipv6-prefix	Not Specified	::/0						
device	Interface to use for management access for NAT mode.	string	Maximum length: 35							
utf8-spam-tagging	Enable/disable converting antispam tags to UTF-8 for better non-ASCII character support.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Convert antispam tags to UTF-8.</td></tr><tr><td>disable</td><td>Do not convert antispam tags.</td></tr></table>				Option	Description	enable	Convert antispam tags to UTF-8.	disable	Do not convert antispam tags.
Option	Description									
enable	Convert antispam tags to UTF-8.									
disable	Do not convert antispam tags.									
wccp-cache-engine	Enable/disable WCCP cache engine.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable WCCP cache engine.</td></tr><tr><td>disable</td><td>Disable WCCP cache engine.</td></tr></table>				Option	Description	enable	Enable WCCP cache engine.	disable	Disable WCCP cache engine.
Option	Description									
enable	Enable WCCP cache engine.									
disable	Disable WCCP cache engine.									
wccp-local-route	Enable/disable WCCP to use local route.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable WCCP to use local route.</td></tr><tr><td>disable</td><td>Disable WCCP to use local route.</td></tr></table>				Option	Description	enable	Enable WCCP to use local route.	disable	Disable WCCP to use local route.
Option	Description									
enable	Enable WCCP to use local route.									
disable	Disable WCCP to use local route.									
vpn-stats-log	Enable/disable periodic VPN log statistics for one or more types of VPN. Separate names with a space.	option	-	ipsec pptp l2tp						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>ipsec</i>	IPsec.		
	<i>pptp</i>	PPTP.		
	<i>l2tp</i>	L2TP.		
vpn-stats-period	Period to send VPN log statistics (0 or 60 - 86400 sec).	integer	Minimum value: 0 Maximum value: 4294967295	600
mac-ttl	Duration of MAC addresses in Transparent mode (300 - 8640000 sec, default = 300).	integer	Minimum value: 300 Maximum value: 8640000	300
fw-session-hairpin	Enable/disable checking for a matching policy each time hairpin traffic goes through the FortiProxy.	option	-	disable
	Option	Description		
	<i>enable</i>	Perform a policy check every time.		
	<i>disable</i>	Perform a policy check only the first time the session is received.		
prp-trailer-action	Enable/disable action to take on PRP trailer.	option	-	disable
	Option	Description		
	<i>enable</i>	Try to keep PRP trailer.		
	<i>disable</i>	Trim PRP trailer.		
snat-hairpin-traffic	Enable/disable source NAT (SNAT) for hairpin traffic.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable SNAT for hairpin traffic.		
	<i>disable</i>	Disable SNAT for hairpin traffic.		
dhcp-proxy	Enable/disable the DHCP Proxy.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable the DHCP proxy.		
	<i>disable</i>	Disable the DHCP proxy.		
dhcp-proxy-interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto
	Option	Description		
	<i>auto</i>	Set outgoing interface automatically.		
	<i>specify</i>	Set outgoing interface manually.		
dhcp-proxy-interface	Specify outgoing interface to reach server.	string	Maximum length: 15	
dhcp-server-ip	DHCP Server IPv4 address.	user	Not Specified	
dhcp6-server-ip	DHCPv6 server IPv6 address.	user	Not Specified	
gui-default-policy-columns <name>	Default columns to display for policy lists on GUI. Select column name.	string	Maximum length: 79	
link-down-access	Enable/disable link down access traffic.	option	-	enable
	Option	Description		
	<i>enable</i>	Allow link down access traffic.		
	<i>disable</i>	Block link down access traffic.		
asymroute	Enable/disable IPv4 asymmetric routing.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable IPv4 asymmetric routing.		
	<i>disable</i>	Disable IPv4 asymmetric routing.		
asymroute-icmp	Enable/disable ICMP asymmetric routing.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable ICMP asymmetric routing.		
	<i>disable</i>	Disable ICMP asymmetric routing.		
tcp-session-without-syn	Enable/disable allowing TCP session without SYN flags.	option	-	disable
	Option	Description		
	<i>enable</i>	Allow TCP session without SYN flags.		
	<i>disable</i>	Do not allow TCP session without SYN flags.		
ses-denied-traffic	Enable/disable including denied session in the session table.	option	-	disable
	Option	Description		
	<i>enable</i>	Include denied sessions in the session table.		
	<i>disable</i>	Do not add denied sessions to the session table.		
strict-src-check	Enable/disable strict source verification.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable strict source verification.		
	<i>disable</i>	Disable strict source verification.		
allow-linkdown-path	Enable/disable link down path.	option	-	disable
	Option	Description		
	<i>enable</i>	Allow link down path.		
	<i>disable</i>	Do not allow link down path.		
asymroute6	Enable/disable asymmetric IPv6 routing.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable asymmetric IPv6 routing.		
	<i>disable</i>	Disable asymmetric IPv6 routing.		
asymroute6-icmp	Enable/disable asymmetric ICMPv6 routing.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable asymmetric ICMPv6 routing.		
	<i>disable</i>	Disable asymmetric ICMPv6 routing.		
sctp-session-without-init	Enable/disable SCTP session creation without SCTP INIT.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable SCTP session creation without SCTP INIT.		
	<i>disable</i>	Disable SCTP session creation without SCTP INIT.		
status	Enable/disable this VDOM.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable this VDOM.		
	<i>disable</i>	Disable this VDOM.		
allow-subnet-overlap	Enable/disable allowing interface subnets to use overlapping IP addresses.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable overlapping subnets.		
	<i>disable</i>	Disable overlapping subnets.		
deny-tcp-with-icmp	Enable/disable denying TCP by sending an ICMP communication prohibited packet.	option	-	disable
	Option	Description		
	<i>enable</i>	Deny TCP with ICMP.		
	<i>disable</i>	Disable denying TCP with ICMP.		
discovered-device-timeout	Timeout for discovered devices (1 - 365 days, default = 28).	integer	Minimum value: 1 Maximum value: 365	28
email-portal-check-dns	Enable/disable using DNS to validate email addresses collected by a captive portal.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable email address checking with DNS.		
	<i>enable</i>	Enable email address checking with DNS.		
gui-icap	Enable/disable ICAP on the GUI.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable ICAP on the GUI.		
	<i>disable</i>	Disable ICAP on the GUI.		
gui-implicit-policy	Enable/disable implicit firewall policies on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable implicit firewall policies on the GUI.		
	<i>disable</i>	Disable implicit firewall policies on the GUI.		
gui-dns-database	Enable/disable DNS database settings on the GUI.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable DNS database settings on the GUI.		
	<i>disable</i>	Disable DNS database settings on the GUI.		
gui-proxy-inspection	Enable/disable the proxy features on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable the proxy features on the GUI.		
	<i>disable</i>	Disable the proxy features on the GUI.		
gui-multicast-policy	Enable/disable multicast firewall policies on the GUI.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable multicast firewall policies on the GUI.		
	<i>disable</i>	Disable multicast firewall policies on the GUI.		
gui-dos-policy	Enable/disable DoS policies on the GUI.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable DoS policies on the GUI.		
	<i>disable</i>	Disable DoS policies on the GUI.		
gui-object-colors	Enable/disable object colors on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable object colors on the GUI.		
	<i>disable</i>	Disable object colors on the GUI.		
gui-voip-profile	Enable/disable VoIP profiles on the GUI.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable VoIP profiles on the GUI.		
	<i>disable</i>	Disable VoIP profiles on the GUI.		
gui-security-profile-group	Enable/disable Security Profile Groups on the GUI.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable Security Profile Groups on the GUI.		
	<i>disable</i>	Disable Security Profile Groups on the GUI.		
gui-wanopt-cache	Enable/disable WAN Optimization and Web Caching on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable WAN Optimization and Web Caching on the GUI.		
	<i>disable</i>	Disable WAN Optimization and Web Caching on the GUI.		
gui-explicit-proxy	Enable/disable the explicit proxy on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable the explicit proxy on the GUI.		
	<i>disable</i>	Disable the explicit proxy on the GUI.		
gui-policy-based-ipsec	Enable/disable policy-based IPsec VPN on the GUI.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable policy-based IPsec VPN on the GUI.		
	<i>disable</i>	Disable policy-based IPsec VPN on the GUI.		
gui-threat-weight	Enable/disable threat weight on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable threat weight on the GUI.		
	<i>disable</i>	Disable threat weight on the GUI.		
gui-spamfilter	Enable/disable Antispam on the GUI.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable Antispam on the GUI.		
	<i>disable</i>	Disable Antispam on the GUI.		
gui-file-filter	Enable/disable File-filter on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable File-filter on the GUI.		
	<i>disable</i>	Disable File-filter on the GUI.		
gui-application-control	Enable/disable application control on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable application control on the GUI.		
	<i>disable</i>	Disable application control on the GUI.		
gui-ips	Enable/disable IPS on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable IPS on the GUI.		
	<i>disable</i>	Disable IPS on the GUI.		
gui-dhcp-advanced	Enable/disable advanced DHCP options on the GUI.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable advanced DHCP options on the GUI.		
	<i>disable</i>	Disable advanced DHCP options on the GUI.		
gui-vpn	Enable/disable VPN tunnels on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable VPN tunnels on the GUI.		
	<i>disable</i>	Disable VPN tunnels on the GUI.		
gui-webfilter-advanced	Enable/disable advanced web filtering on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable advanced web filtering on the GUI.		
	<i>disable</i>	Disable advanced web filtering on the GUI.		
gui-traffic-shaping	Enable/disable traffic shaping on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable traffic shaping on the GUI.		
	<i>disable</i>	Disable traffic shaping on the GUI.		
gui-antivirus	Enable/disable AntiVirus on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable AntiVirus on the GUI.		
	<i>disable</i>	Disable AntiVirus on the GUI.		
gui-webfilter	Enable/disable Web filtering on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable Web filtering on the GUI.		
	<i>disable</i>	Disable Web filtering on the GUI.		
gui-videofilter	Enable/disable Video filtering on the GUI.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable Video filtering on the GUI.		
	<i>disable</i>	Disable Video filtering on the GUI.		
gui-dnsfilter	Enable/disable DNS Filtering on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable DNS Filtering on the GUI.		
	<i>disable</i>	Disable DNS Filtering on the GUI.		
gui-advanced-policy	Enable/disable advanced policy configuration on the GUI.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable advanced policy configuration on the GUI.		
	<i>disable</i>	Disable advanced policy configuration on the GUI.		
gui-allow-unnamed-policy	Enable/disable the requirement for policy naming on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable the requirement for policy naming on the GUI.		
	<i>disable</i>	Disable the requirement for policy naming on the GUI.		
gui-email-collection	Enable/disable email collection on the GUI.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable email collection on the GUI.		
	<i>disable</i>	Disable email collection on the GUI.		
gui-multiple-interface-policy	Enable/disable adding multiple interfaces to a policy on the GUI.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable adding multiple interfaces to a policy on the GUI.		
	<i>disable</i>	Disable adding multiple interfaces to a policy on the GUI.		

Parameter	Description	Type	Size	Default						
gui-policy-disclaimer	Enable/disable policy disclaimer on the GUI.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable policy disclaimer on the GUI.</td></tr><tr><td><i>disable</i></td><td>Disable policy disclaimer on the GUI.</td></tr></table>	Option	Description	<i>enable</i>	Enable policy disclaimer on the GUI.	<i>disable</i>	Disable policy disclaimer on the GUI.			
Option	Description									
<i>enable</i>	Enable policy disclaimer on the GUI.									
<i>disable</i>	Disable policy disclaimer on the GUI.									
gui-ztna	Enable/disable Zero Trust Network Access features on the GUI.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable Zero Trust Network Access features on the GUI.</td></tr><tr><td><i>disable</i></td><td>Disable Zero Trust Network Access features on the GUI.</td></tr></table>	Option	Description	<i>enable</i>	Enable Zero Trust Network Access features on the GUI.	<i>disable</i>	Disable Zero Trust Network Access features on the GUI.			
Option	Description									
<i>enable</i>	Enable Zero Trust Network Access features on the GUI.									
<i>disable</i>	Disable Zero Trust Network Access features on the GUI.									
gui-ot	Enable/disable Operational technology features on the GUI.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable Operational technology features on the GUI.</td></tr><tr><td><i>disable</i></td><td>Disable Operational technology features on the GUI.</td></tr></table>	Option	Description	<i>enable</i>	Enable Operational technology features on the GUI.	<i>disable</i>	Disable Operational technology features on the GUI.			
Option	Description									
<i>enable</i>	Enable Operational technology features on the GUI.									
<i>disable</i>	Disable Operational technology features on the GUI.									
block-land-attack	Enable/disable blocking of land attacks.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not block land attack.</td></tr><tr><td><i>enable</i></td><td>Block land attack.</td></tr></table>	Option	Description	<i>disable</i>	Do not block land attack.	<i>enable</i>	Block land attack.			
Option	Description									
<i>disable</i>	Do not block land attack.									
<i>enable</i>	Block land attack.									
default-app-port-as-service	Enable/disable policy service enforcement based on application default ports.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
application-bandwidth-tracking	Enable/disable application bandwidth tracking.	option	-	disable						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Disable application bandwidth tracking.		
	<i>enable</i>	Enable application bandwidth tracking.		
default-policy-expiry-days	Default policy expiry in days (0 - 365 days, default = 30).	integer	Minimum value: 0 Maximum value: 365	30
gui-enforce-change-summary	Enforce change summaries for select tables in the GUI.	option	-	require
	Option	Description		
	<i>disable</i>	No change summary requirement.		
	<i>require</i>	Change summary required.		
	<i>optional</i>	Change summary optional.		
internet-service-database-cache	Enable/disable Internet Service database caching.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable Internet Service database caching.		
	<i>enable</i>	Enable Internet Service database caching.		

config system sms-server

Configure SMS server for sending SMS messages to support user authentication.

```

config system sms-server
    Description: Configure SMS server for sending SMS messages to support user authentication.
    edit <name>
        set mail-server {string}
    next
end

```

config system sms-server

Parameter	Description	Type	Size	Default
name	Name of SMS server.	string	Maximum length: 35	
mail-server	Email-to-SMS server domain name.	string	Maximum length: 63	

config system snmp community

SNMP community configuration.

```
config system snmp community
  Description: SNMP community configuration.
  edit <id>
    set name {string}
    set status [enable|disable]
    config hosts
      Description: Configure IPv4 SNMP managers (hosts).
      edit <id>
        set source-ip {ipv4-address}
        set ip {user}
        set ha-direct [enable|disable]
        set host-type [any|query|...]
      next
    end
  config hosts6
    Description: Configure IPv6 SNMP managers.
    edit <id>
      set source-ipv6 {ipv6-address}
      set ipv6 {ipv6-prefix}
      set ha-direct [enable|disable]
      set host-type [any|query|...]
    next
  end
  set query-v1-status [enable|disable]
  set query-v1-port {integer}
  set query-v2c-status [enable|disable]
  set query-v2c-port {integer}
  set trap-v1-status [enable|disable]
  set trap-v1-lport {integer}
  set trap-v1-rport {integer}
  set trap-v2c-status [enable|disable]
  set trap-v2c-lport {integer}
  set trap-v2c-rport {integer}
  set events {option1}, {option2}, ...
  set mib-view {string}
  set vdoms <name1>, <name2>, ...
```

```
next
end
```

config system snmp community

Parameter	Description	Type	Size	Default						
id	Community ID.	integer	Minimum value: 0 Maximum value: 4294967295	0						
name	Community name.	string	Maximum length: 35							
status	Enable/disable this SNMP community.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
query-v1-status	Enable/disable SNMP v1 queries.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
query-v1-port	SNMP v1 query port (default = 161).	integer	Minimum value: 1 Maximum value: 65535	161						
query-v2c-status	Enable/disable SNMP v2c queries.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
query-v2c-port	SNMP v2c query port (default = 161).	integer	Minimum value: 0 Maximum value: 65535	161						

Parameter	Description	Type	Size	Default
trap-v1-status	Enable/disable SNMP v1 traps.	option	-	enable
	Option Description			
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
trap-v1-lport	SNMP v1 trap local port (default = 162).	integer	Minimum value: 1 Maximum value: 65535	162
trap-v1-rport	SNMP v1 trap remote port (default = 162).	integer	Minimum value: 1 Maximum value: 65535	162
trap-v2c-status	Enable/disable SNMP v2c traps.	option	-	enable
	Option Description			
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
trap-v2c-lport	SNMP v2c trap local port (default = 162).	integer	Minimum value: 1 Maximum value: 65535	162
trap-v2c-rport	SNMP v2c trap remote port (default = 162).	integer	Minimum value: 1 Maximum value: 65535	162

Parameter	Description	Type	Size	Default
events	SNMP trap events.	option	-	cpu-high mem-low log-full intf-ip vpn-tun-up vpn-tun-down ha-switch ha-hb-failure ips-signature ips-anomaly av-virus av-oversize av-pattern av-fragmented fm-if-change ha-member-up ha-member-down ent-conf-change av-conserve av-bypass av-oversize-passed av-oversize-blocked ips-pkg-update ips-fail-open faz-disconnect load-balance-real-server-down per-cpu-high dhcp-pool-usage cert-expiry

Option	Description
<i>cpu-high</i>	Send a trap when CPU usage is high.
<i>mem-low</i>	Send a trap when available memory is low.
<i>log-full</i>	Send a trap when log disk space becomes low.
<i>intf-ip</i>	Send a trap when an interface IP address is changed.

Parameter	Description	Type	Size	Default

Option	Description
<i>vpn-tun-up</i>	Send a trap when a VPN tunnel comes up.
<i>vpn-tun-down</i>	Send a trap when a VPN tunnel goes down.
<i>ha-switch</i>	Send a trap after an HA failover when the backup unit has taken over.
<i>ha-hb-failure</i>	Send a trap when HA heartbeats are not received.
<i>ips-signature</i>	Send a trap when IPS detects an attack.
<i>ips-anomaly</i>	Send a trap when IPS finds an anomaly.
<i>av-virus</i>	Send a trap when AntiVirus finds a virus.
<i>av-oversize</i>	Send a trap when AntiVirus finds an oversized file.
<i>av-pattern</i>	Send a trap when AntiVirus finds file matching pattern.
<i>av-fragmented</i>	Send a trap when AntiVirus finds a fragmented file.
<i>fm-if-change</i>	Send a trap when FortiManager interface changes. Send a FortiManager trap.
<i>fm-conf-change</i>	Send a trap when a configuration change is made by a FortiProxy administrator and the FortiProxy is managed by FortiManager.
<i>ha-member-up</i>	Send a trap when an HA cluster member goes up.
<i>ha-member-down</i>	Send a trap when an HA cluster member goes down.
<i>ent-conf-change</i>	Send a trap when an entity MIB change occurs (RFC4133).
<i>av-conserve</i>	Send a trap when the FortiProxy enters conserve mode.
<i>av-bypass</i>	Send a trap when the FortiProxy enters bypass mode.
<i>av-oversize-passed</i>	Send a trap when AntiVirus passes an oversized file.
<i>av-oversize-blocked</i>	Send a trap when AntiVirus blocks an oversized file.
<i>ips-pkg-update</i>	Send a trap when the IPS signature database or engine is updated.
<i>ips-fail-open</i>	Send a trap when the IPS network buffer is full.
<i>faz-disconnect</i>	Send a trap when a FortiAnalyzer disconnects from the FortiProxy.

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>load-balance-real-server-down</i>	Send a trap when a server load balance real server goes down.		
	<i>device-new</i>	Send a trap when a new device is found.		
	<i>per-cpu-high</i>	Send a trap when per-CPU usage is high.		
	<i>dhcp</i>	Send a trap when the DHCP server exhausts the IP pool, an IP address already is in use, or a DHCP client interface received a DHCP-NAK.		
	<i>pool-usage</i>	Send a trap about ippool usage.		
	<i>cert-expiry</i>	Send a trap when a local certificate is near expiry.		
mib-view	SNMP access control MIB view.	string	Maximum length: 32	
vdoms <name>	SNMP access control VDOMs. VDOM name.	string	Maximum length: 79	

config hosts

Parameter	Description	Type	Size	Default						
id	Host entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0						
source-ip	Source IPv4 address for SNMP traps.	ipv4-address	Not Specified	0.0.0.0						
ip	IPv4 address of the SNMP manager (host).	user	Not Specified							
ha-direct	Enable/disable direct management of HA cluster members.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>				Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.
	Option	Description								
	<i>enable</i>	Enable setting.								
<i>disable</i>	Disable setting.									
host-type	Control whether the SNMP manager sends SNMP queries, receives SNMP traps, or both. No traps will be sent when IP type is subnet.	option	-	any						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>any</i>	Accept queries from and send traps to this SNMP manager.		
	<i>query</i>	Accept queries from this SNMP manager but do not send traps.		
	<i>trap</i>	Send traps to this SNMP manager but do not accept SNMP queries from this SNMP manager.		

config hosts6

Parameter	Description	Type	Size	Default
id	Host6 entry ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
source-ipv6	Source IPv6 address for SNMP traps.	ipv6-address	Not Specified	::
ipv6	SNMP manager IPv6 address prefix.	ipv6-prefix	Not Specified	::/0
ha-direct	Enable/disable direct management of HA cluster members.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
host-type	Control whether the SNMP manager sends SNMP queries, receives SNMP traps, or both.	option	-	any
	Option	Description		
	<i>any</i>	Accept queries from and send traps to this SNMP manager.		
	<i>query</i>	Accept queries from this SNMP manager but do not send traps.		
	<i>trap</i>	Send traps to this SNMP manager but do not accept SNMP queries from this SNMP manager.		

config system snmp mib-view

SNMP Access Control MIB View configuration.

```
config system snmp mib-view
  Description: SNMP Access Control MIB View configuration.
  edit <name>
    set include {string}
    set exclude {string}
  next
end
```

config system snmp mib-view

Parameter	Description	Type	Size	Default
name	MIB view name.	string	Maximum length: 32	
include	OID subtrees to be included in the view. Maximum 16 allowed.	string	Maximum length: 79	
exclude	OID subtrees to be excluded in the view. Maximum 64 allowed.	string	Maximum length: 79	

config system snmp sysinfo

SNMP system info configuration.

```
config system snmp sysinfo
  Description: SNMP system info configuration.
  set status [enable|disable]
  set engine-id-type [text|hex|...]
  set engine-id {string}
  set description {var-string}
  set contact-info {var-string}
  set location {var-string}
  set trap-high-cpu-threshold {integer}
  set trap-low-memory-threshold {integer}
  set trap-log-full-threshold {integer}
  set append-index [enable|disable]
end
```

config system snmp sysinfo

Parameter	Description	Type	Size	Default
status	Enable/disable SNMP.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
engine-id-type	Local SNMP engineID type (text/hex/mac).	option	-	text
	Option	Description		
	<i>text</i>	Text format.		
	<i>hex</i>	Octets format.		
	<i>mac</i>	MAC address format.		
engine-id	Local SNMP engineID string (maximum 27 characters).	string	Maximum length: 54	
description	System description.	var-string	Maximum length: 255	
contact-info	Contact information.	var-string	Maximum length: 255	
location	System location.	var-string	Maximum length: 255	
trap-high-cpu-threshold	CPU usage when trap is sent.	integer	Minimum value: 1 Maximum value: 100	80
trap-low-memory-threshold	Memory usage when trap is sent.	integer	Minimum value: 1 Maximum value: 100	80
trap-log-full-threshold	Log disk usage when trap is sent.	integer	Minimum value: 1 Maximum value: 100	90
append-index	Enable/disable allowance of appending VDOM or interface index in some RFC tables.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

config system snmp user

SNMP user configuration.

```
config system snmp user
  Description: SNMP user configuration.
  edit <name>
    set status [enable|disable]
    set trap-status [enable|disable]
    set trap-lport {integer}
    set trap-rport {integer}
    set queries [enable|disable]
    set query-port {integer}
    set notify-hosts {ipv4-address}
    set notify-hosts6 {ipv6-address}
    set source-ip {ipv4-address}
    set source-ipv6 {ipv6-address}
    set ha-direct [enable|disable]
    set events {option1}, {option2}, ...
    set mib-view {string}
    set vdoms <name1>, <name2>, ...
    set security-level [no-auth-no-priv|auth-no-priv|...]
    set auth-proto [md5|sha|...]
    set auth-pwd {password}
    set priv-proto [aes|des|...]
    set priv-pwd {password}
  next
end
```

config system snmp user

Parameter	Description	Type	Size	Default
name	SNMP user name.	string	Maximum length: 32	
status	Enable/disable this SNMP user.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
trap-status	Enable/disable traps for this SNMP user.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

Parameter	Description	Type	Size	Default						
trap-lport	SNMPv3 local trap port (default = 162).	integer	Minimum value: 1 Maximum value: 65535	162						
trap-rport	SNMPv3 trap remote port (default = 162).	integer	Minimum value: 1 Maximum value: 65535	162						
queries	Enable/disable SNMP queries for this user.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>				Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.
	Option	Description								
	<i>enable</i>	Enable setting.								
<i>disable</i>	Disable setting.									
query-port	SNMPv3 query port (default = 161).	integer	Minimum value: 1 Maximum value: 65535	161						
notify-hosts	SNMP managers to send notifications (traps) to.	ipv4-address	Not Specified							
notify-hosts6	IPv6 SNMP managers to send notifications (traps) to.	ipv6-address	Not Specified							
source-ip	Source IP for SNMP trap.	ipv4-address	Not Specified	0.0.0.0						
source-ipv6	Source IPv6 for SNMP trap.	ipv6-address	Not Specified	::						
ha-direct	Enable/disable direct management of HA cluster members.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>				Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.
	Option	Description								
	<i>enable</i>	Enable setting.								
<i>disable</i>	Disable setting.									

Parameter	Description	Type	Size	Default
events	SNMP notifications (traps) to send.	option	-	cpu-high mem-low log-full intf-ip vpn-tun-up vpn-tun-down ha-switch ha-hb-failure ips-signature ips-anomaly av-virus av-oversize av-pattern av-fragmented fm-if-change ha-member-up ha-member-down ent-conf-change av-conserve av-bypass av-oversize-passed av-oversize-blocked ips-pkg-update ips-fail-open faz-disconnect load-balance-real-server-down per-cpu-high dhcp-pool-usage cert-expiry
Option		Description		
<i>cpu-high</i>		Send a trap when CPU usage is high.		
<i>mem-low</i>		Send a trap when available memory is low.		
<i>log-full</i>		Send a trap when log disk space becomes low.		
<i>intf-ip</i>		Send a trap when an interface IP address is changed.		

Parameter	Description	Type	Size	Default

Option	Description
<i>vpn-tun-up</i>	Send a trap when a VPN tunnel comes up.
<i>vpn-tun-down</i>	Send a trap when a VPN tunnel goes down.
<i>ha-switch</i>	Send a trap after an HA failover when the backup unit has taken over.
<i>ha-hb-failure</i>	Send a trap when HA heartbeats are not received.
<i>ips-signature</i>	Send a trap when IPS detects an attack.
<i>ips-anomaly</i>	Send a trap when IPS finds an anomaly.
<i>av-virus</i>	Send a trap when AntiVirus finds a virus.
<i>av-oversize</i>	Send a trap when AntiVirus finds an oversized file.
<i>av-pattern</i>	Send a trap when AntiVirus finds file matching pattern.
<i>av-fragmented</i>	Send a trap when AntiVirus finds a fragmented file.
<i>fm-if-change</i>	Send a trap when FortiManager interface changes. Send a FortiManager trap.
<i>fm-conf-change</i>	Send a trap when a configuration change is made by a FortiProxy administrator and the FortiProxy is managed by FortiManager.
<i>ha-member-up</i>	Send a trap when an HA cluster member goes up.
<i>ha-member-down</i>	Send a trap when an HA cluster member goes down.
<i>ent-conf-change</i>	Send a trap when an entity MIB change occurs (RFC4133).
<i>av-conserve</i>	Send a trap when the FortiProxy enters conserve mode.
<i>av-bypass</i>	Send a trap when the FortiProxy enters bypass mode.
<i>av-oversize-passed</i>	Send a trap when AntiVirus passes an oversized file.
<i>av-oversize-blocked</i>	Send a trap when AntiVirus blocks an oversized file.
<i>ips-pkg-update</i>	Send a trap when the IPS signature database or engine is updated.
<i>ips-fail-open</i>	Send a trap when the IPS network buffer is full.
<i>faz-disconnect</i>	Send a trap when a FortiAnalyzer disconnects from the FortiProxy.

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>load-balance-real-server-down</i>	Send a trap when a server load balance real server goes down.		
	<i>device-new</i>	Send a trap when a new device is found.		
	<i>per-cpu-high</i>	Send a trap when per-CPU usage is high.		
	<i>dhcp</i>	Send a trap when the DHCP server exhausts the IP pool, an IP address already is in use, or a DHCP client interface received a DHCP-NAK.		
	<i>pool-usage</i>	Send a trap about ippool usage.		
	<i>cert-expiry</i>	Send a trap when a local certificate is near expiry.		
mib-view	SNMP access control MIB view.	string	Maximum length: 32	
vdoms <name>	SNMP access control VDOMs. VDOM name.	string	Maximum length: 79	
security-level	Security level for message authentication and encryption.	option	-	no-auth-no-priv
	Option	Description		
	<i>no-auth-no-priv</i>	Message with no authentication and no privacy (encryption).		
	<i>auth-no-priv</i>	Message with authentication but no privacy (encryption).		
	<i>auth-priv</i>	Message with authentication and privacy (encryption).		
auth-proto	Authentication protocol.	option	-	sha
	Option	Description		
	<i>md5</i>	HMAC-MD5-96 authentication protocol.		
	<i>sha</i>	HMAC-SHA-96 authentication protocol.		
	<i>sha224</i>	HMAC-SHA224 authentication protocol.		
	<i>sha256</i>	HMAC-SHA256 authentication protocol.		
	<i>sha384</i>	HMAC-SHA384 authentication protocol.		
	<i>sha512</i>	HMAC-SHA512 authentication protocol.		
auth-pwd	Password for authentication protocol.	password	Not Specified	

Parameter	Description	Type	Size	Default										
priv-proto	Privacy (encryption) protocol.	option	-	aes										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>aes</td><td>CFB128-AES-128 symmetric encryption protocol.</td></tr><tr><td>des</td><td>CBC-DES symmetric encryption protocol.</td></tr><tr><td>aes256</td><td>CFB128-AES-256 symmetric encryption protocol.</td></tr><tr><td>aes256cisco</td><td>CFB128-AES-256 symmetric encryption protocol compatible with CISCO.</td></tr></table>				Option	Description	aes	CFB128-AES-128 symmetric encryption protocol.	des	CBC-DES symmetric encryption protocol.	aes256	CFB128-AES-256 symmetric encryption protocol.	aes256cisco	CFB128-AES-256 symmetric encryption protocol compatible with CISCO.
	Option	Description												
	aes	CFB128-AES-128 symmetric encryption protocol.												
	des	CBC-DES symmetric encryption protocol.												
	aes256	CFB128-AES-256 symmetric encryption protocol.												
aes256cisco	CFB128-AES-256 symmetric encryption protocol compatible with CISCO.													
priv-pwd	Password for privacy (encryption) protocol.	password	Not Specified											

config system source-ip status

Show configured service source-IP.

```
config system source-ip status
    Description: Show configured service source-IP.
end
```

config system span-port

Configure SPAN port.

```
config system span-port
    Description: Configure SPAN port.
    edit <id>
        set status [disable|enable]
        set span-source-port {string}
        set span-dest-port {string}
        set span-direction [rx|tx|...]
    next
end
```

config system span-port

Parameter	Description	Type	Size	Default
id	SPAN port id.	integer	Minimum value: 0 Maximum value: 4294967295	0
status	Enable/disable SPAN.	option	-	disable
	Option	Description		
	disable	Disable SPAN.		
	enable	Enable SPAN.		
span-source-port	SPAN source ports.	string	Maximum length: 15	
span-dest-port	SPAN destination port.	string	Maximum length: 15	
span-direction	SPAN direction.	option	-	both
	Option	Description		
	rx	Span receive direction only.		
	tx	Span transmit direction only.		
	both	Span both directions.		

config system speed-test-schedule

Speed test schedule for each interface.

```
config system speed-test-schedule
  Description: Speed test schedule for each interface.
  edit <interface>
    set status [disable|enable]
    set diffserv {user}
    set server-name {string}
    set mode [UDP|TCP|...]
    set schedules <name1>, <name2>, ...
    set dynamic-server [disable|enable]
    set update-inbandwidth [disable|enable]
    set update-outbandwidth [disable|enable]
    set update-inbandwidth-maximum {integer}
    set update-inbandwidth-minimum {integer}
```

```

        set update-outbandwidth-maximum {integer}
        set update-outbandwidth-minimum {integer}
    next
end

```

config system speed-test-schedule

Parameter	Description	Type	Size	Default
interface	Interface name.	string	Maximum length: 35	
status	Enable/disable scheduled speed test.	option	-	enable
	Option Description			
	<i>disable</i>	Disable scheduled speed test.		
	<i>enable</i>	Enable scheduled speed test.		
diffserv	DSCP used for speed test.	user	Not Specified	
server-name	Speed test server name.	string	Maximum length: 35	
mode	Protocol Auto(default), TCP or UDP used for speed test.	option	-	Auto
	Option Description			
	<i>UDP</i>	Protocol UDP for speed test.		
	<i>TCP</i>	Protocol TCP for speed test.		
	<i>Auto</i>	Dynamically selects TCP or UDP based on the speed test setting		
schedules <name>	Schedules for the interface. Name of a firewall recurring schedule.	string	Maximum length: 31	
dynamic-server	Enable/disable dynamic server option.	option	-	disable
	Option Description			
	<i>disable</i>	Disable dynamic server.		
	<i>enable</i>	Enable dynamic server.The speed test server will be found automatically.		
update-inbandwidth	Enable/disable bypassing interface's inbound bandwidth setting.	option	-	disable

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Honor interface's inbandwidth shaping.</td></tr><tr><td><i>enable</i></td><td>Ignore interface's inbandwidth shaping.</td></tr></table>	Option	Description	<i>disable</i>	Honor interface's inbandwidth shaping.	<i>enable</i>	Ignore interface's inbandwidth shaping.			
	Option	Description								
	<i>disable</i>	Honor interface's inbandwidth shaping.								
<i>enable</i>	Ignore interface's inbandwidth shaping.									
update-outbandwidth	Enable/disable bypassing interface's outbound bandwidth setting.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Honor interface's outbandwidth shaping.</td></tr><tr><td><i>enable</i></td><td>Ignore updating interface's outbandwidth shaping.</td></tr></table>	Option	Description	<i>disable</i>	Honor interface's outbandwidth shaping.	<i>enable</i>	Ignore updating interface's outbandwidth shaping.			
	Option	Description								
	<i>disable</i>	Honor interface's outbandwidth shaping.								
<i>enable</i>	Ignore updating interface's outbandwidth shaping.									
update-inbandwidth-maximum	Maximum downloading bandwidth (kbps) to be used in a speed test.	integer	Minimum value: 0 Maximum value: 16776000	0						
update-inbandwidth-minimum	Minimum downloading bandwidth (kbps) to be considered effective.	integer	Minimum value: 0 Maximum value: 16776000	0						
update-outbandwidth-maximum	Maximum uploading bandwidth (kbps) to be used in a speed test.	integer	Minimum value: 0 Maximum value: 16776000	0						
update-outbandwidth-minimum	Minimum uploading bandwidth (kbps) to be considered effective.	integer	Minimum value: 0 Maximum value: 16776000	0						

config system speed-test-server

Configure speed test server list.

```

config system speed-test-server
    Description: Configure speed test server list.
    edit <name>
        set timestamp {integer}
        config host
            Description: Hosts of the server.

```

```

        edit <id>
            set ip {ipv4-address}
            set port {integer}
            set user {string}
            set password {password}
            set longitude {string}
            set latitude {string}
            set distance {integer}
        next
    end
next
end

```

config system speed-test-server

Parameter	Description	Type	Size	Default
name	Speed test server name.	string	Maximum length: 35	
timestamp	Speed test server timestamp.	integer	Minimum value: 0 Maximum value: 4294967295	0

config host

Parameter	Description	Type	Size	Default
id	Server host ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
ip	Server host IPv4 address.	ipv4-address	Not Specified	0.0.0.0
port	Server host port number to communicate with client.	integer	Minimum value: 1 Maximum value: 65535	5204
user	Speed test host user name.	string	Maximum length: 64	
password	Speed test host password.	password	Not Specified	

Parameter	Description	Type	Size	Default
longitude	Speed test host longitude.	string	Maximum length: 7	
latitude	Speed test host latitude.	string	Maximum length: 7	
distance	Speed test host distance.	integer	Minimum value: 0 Maximum value: 4294967295	0

config system speed-test-setting

Configure speed test setting.

```
config system speed-test-setting
    Description: Configure speed test setting.
    set latency-threshold {integer}
    set multiple-tcp-stream {integer}
end
```

config system speed-test-setting

Parameter	Description	Type	Size	Default
latency-threshold	Speed test latency threshold in milliseconds (0 - 2000, default = 60) for the Auto mode. If the latency exceeds this threshold, the speed test will use the UDP protocol; otherwise, it will use the TCP protocol.	integer	Minimum value: 0 Maximum value: 2000	60
multiple-tcp-stream	Number of parallel client streams (1 - 64, default = 4) for the TCP protocol to run during the speed test.	integer	Minimum value: 1 Maximum value: 64	4

config system sso-admin

Configure SSO admin users.

```
config system sso-admin
    Description: Configure SSO admin users.
    edit <name>
```

```

        set accprofile {string}
        set vdom <name1>, <name2>, ...
    next
end

```

config system sso-admin

Parameter	Description	Type	Size	Default
name	SSO admin name.	string	Maximum length: 64	
accprofile	SSO admin user access profile.	string	Maximum length: 35	
vdom <name>	Virtual domain(s) that the administrator can access. Virtual domain name.	string	Maximum length: 79	

config system sso-forticloud-admin

Configure FortiCloud SSO admin users.

```

config system sso-forticloud-admin
    Description: Configure FortiCloud SSO admin users.
    edit <name>
        set accprofile {string}
        set vdom <name1>, <name2>, ...
    next
end

```

config system sso-forticloud-admin

Parameter	Description	Type	Size	Default
name	FortiCloud SSO admin name.	string	Maximum length: 64	
accprofile	FortiCloud SSO admin user access profile.	string	Maximum length: 35	
vdom <name>	Virtual domain(s) that the administrator can access. Virtual domain name.	string	Maximum length: 79	

config system sso-fortigate-cloud-admin

Configure FortiCloud SSO admin users.

```
config system sso-fortigate-cloud-admin
  Description: Configure FortiCloud SSO admin users.
  edit <name>
    set accprofile {string}
    set vdom <name1>, <name2>, ...
  next
end
```

config system sso-fortigate-cloud-admin

Parameter	Description	Type	Size	Default
name	FortiCloud SSO admin name.	string	Maximum length: 64	
accprofile	FortiCloud SSO admin user access profile.	string	Maximum length: 35	
vdom <name>	Virtual domain(s) that the administrator can access. Virtual domain name.	string	Maximum length: 79	

config system startup-error-log

Display startup config error on console.

```
config system startup-error-log
  Description: Display startup config error on console.
end
```

config system status

System status.

```
config system status
  Description: System status.
end
```

config system storage

Configure logical storage.

```
config system storage
  Description: Configure logical storage.
  edit <name>
    set status [enable|disable]
    set media-status [enable|disable|...]
    set order {integer}
    set partition {string}
    set device {string}
    set size {integer}
    set usage [log|wanopt]
    set wanopt-mode [mix|wanopt|...]
  next
end
```

config system storage

Parameter	Description	Type	Size	Default
name	Storage name.	string	Maximum length: 35	default_n
status	Enable/disable storage.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
media-status	The physical status of current media.	option	-	disable
	Option	Description		
	<i>enable</i>	Storage is enabled.		
	<i>disable</i>	Storage is disabled.		
	<i>fail</i>	Storage have some fail sector.		
order	Set storage order.	integer	Minimum value: 0 Maximum value: 255	0
partition	Label of underlying partition.	string	Maximum length: 16	<unknown>

Parameter	Description	Type	Size	Default								
device	Partition device.	string	Maximum length: 19	?								
size	Partition size.	integer	Minimum value: 0 Maximum value: 4294967295	0								
usage	Use hard disk for logging or WAN Optimization (default = log).	option	-	log								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>log</td><td>Use hard disk for logging.</td></tr><tr><td>wanopt</td><td>Use hard disk for WAN Optimization.</td></tr></table>				Option	Description	log	Use hard disk for logging.	wanopt	Use hard disk for WAN Optimization.		
Option	Description											
log	Use hard disk for logging.											
wanopt	Use hard disk for WAN Optimization.											
wanopt-mode	WAN Optimization mode (default=webcache)	option	-	webcache								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>mix</td><td>Use hard disk for WAN Optimization mix mode.</td></tr><tr><td>wanopt</td><td>Use hard disk for WAN Optimization wanopt mode.</td></tr><tr><td>webcache</td><td>Use hard disk for WAN Optimization webcache mode.</td></tr></table>				Option	Description	mix	Use hard disk for WAN Optimization mix mode.	wanopt	Use hard disk for WAN Optimization wanopt mode.	webcache	Use hard disk for WAN Optimization webcache mode.
Option	Description											
mix	Use hard disk for WAN Optimization mix mode.											
wanopt	Use hard disk for WAN Optimization wanopt mode.											
webcache	Use hard disk for WAN Optimization webcache mode.											

config system vdom

Configure virtual domain.

```

config system vdom
  Description: Configure virtual domain.
  edit <name>
    set short-name {string}
    set vcluster-id {integer}
    set flag {integer}
  next
end

```

config system vdom

Parameter	Description	Type	Size	Default
name	VDOM name.	string	Maximum length: 31	
short-name	VDOM short name.	string	Maximum length: 11	
vcluster-id	Virtual cluster ID (0 - 4294967295).	integer	Minimum value: 0 Maximum value: 4294967295	0
flag	Flag.	integer	Minimum value: 0 Maximum value: 4294967295	0

config system vdom-dns

Configure DNS servers for a non-management VDOM.

```
config system vdom-dns
  Description: Configure DNS servers for a non-management VDOM.
  set vdom-dns [enable|disable]
  set primary {ipv4-address}
  set secondary {ipv4-address}
  set protocol {option1}, {option2}, ...
  set ssl-certificate {string}
  set server-hostname <hostname1>, <hostname2>, ...
  set ip6-primary {ipv6-address}
  set ip6-secondary {ipv6-address}
  set source-ip {ipv4-address}
  set interface-select-method [auto|specify]
  set interface {string}
  set server-select-method [least-rtt|failover]
  set alt-primary {ipv4-address}
  set alt-secondary {ipv4-address}
end
```

config system vdom-dns

Parameter	Description	Type	Size	Default								
vdom-dns	Enable/disable configuring DNS servers for the current VDOM.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable configuring DNS servers for the current VDOM.</td></tr><tr><td><i>disable</i></td><td>Disable configuring DNS servers for the current VDOM.</td></tr></table>	Option	Description	<i>enable</i>	Enable configuring DNS servers for the current VDOM.	<i>disable</i>	Disable configuring DNS servers for the current VDOM.					
Option	Description											
<i>enable</i>	Enable configuring DNS servers for the current VDOM.											
<i>disable</i>	Disable configuring DNS servers for the current VDOM.											
primary	Primary DNS server IP address for the VDOM.	ipv4-address	Not Specified	0.0.0.0								
secondary	Secondary DNS server IP address for the VDOM.	ipv4-address	Not Specified	0.0.0.0								
protocol	DNS transport protocols.	option	-	cleartext								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>cleartext</i></td><td>DNS over UDP/53, DNS over TCP/53.</td></tr><tr><td><i>dot</i></td><td>DNS over TLS/853.</td></tr><tr><td><i>doh</i></td><td>DNS over HTTPS/443.</td></tr></table>	Option	Description	<i>cleartext</i>	DNS over UDP/53, DNS over TCP/53.	<i>dot</i>	DNS over TLS/853.	<i>doh</i>	DNS over HTTPS/443.			
Option	Description											
<i>cleartext</i>	DNS over UDP/53, DNS over TCP/53.											
<i>dot</i>	DNS over TLS/853.											
<i>doh</i>	DNS over HTTPS/443.											
ssl-certificate	Name of local certificate for SSL connections.	string	Maximum length: 35	Fortinet_Factory								
server-hostname <hostname>	DNS server host name list. DNS server host name list separated by space (maximum 4 domains).	string	Maximum length: 127									
ip6-primary	Primary IPv6 DNS server IP address for the VDOM.	ipv6-address	Not Specified	::								
ip6-secondary	Secondary IPv6 DNS server IP address for the VDOM.	ipv6-address	Not Specified	::								
source-ip	Source IP for communications with the DNS server.	ipv4-address	Not Specified	0.0.0.0								
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Set outgoing interface automatically.</td></tr><tr><td><i>specify</i></td><td>Set outgoing interface manually.</td></tr></table>	Option	Description	<i>auto</i>	Set outgoing interface automatically.	<i>specify</i>	Set outgoing interface manually.					
Option	Description											
<i>auto</i>	Set outgoing interface automatically.											
<i>specify</i>	Set outgoing interface manually.											

Parameter	Description	Type	Size	Default
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	
server-select-method	Specify how configured servers are prioritized.	option	-	least-rtt
	Option	Description		
	<i>least-rtt</i>	Select servers based on least round trip time.		
	<i>failover</i>	Select servers based on the order they are configured.		
alt-primary	Alternate primary DNS server. This is not used as a failover DNS server.	ipv4-address	Not Specified	0.0.0.0
alt-secondary	Alternate secondary DNS server. This is not used as a failover DNS server.	ipv4-address	Not Specified	0.0.0.0

config system vdom-exception

Global configuration objects that can be configured independently across different ha peers for all VDOMs or for the defined VDOM scope.

```

config system vdom-exception
    Description: Global configuration objects that can be configured independently across
different ha peers for all VDOMs or for the defined VDOM scope.
    edit <id>
        set object [log.fortianalyzer.setting|log.fortianalyzer.override-setting|...]
        set scope [all|inclusive|...]
        set vdom <name1>, <name2>, ...
    next
end

```

config system vdom-exception

Parameter	Description	Type	Size	Default
id	Index (1 - 4096).	integer	Minimum value: 0 1 Maximum value: 4096	0
object	Name of the configuration object that can be configured independently for all VDOMs.	option	-	

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>log.fortianalyzer.setting</i>	log.fortianalyzer.setting		
	<i>log.fortianalyzer.override-setting</i>	log.fortianalyzer.override-setting		
	<i>log.fortianalyzer2.setting</i>	log.fortianalyzer2.setting		
	<i>log.fortianalyzer2.override-setting</i>	log.fortianalyzer2.override-setting		
	<i>log.fortianalyzer3.setting</i>	log.fortianalyzer3.setting		
	<i>log.fortianalyzer3.override-setting</i>	log.fortianalyzer3.override-setting		
	<i>log.fortianalyzer-cloud.setting</i>	log.fortianalyzer-cloud.setting		
	<i>log.fortianalyzer-cloud.override-setting</i>	log.fortianalyzer-cloud.override-setting		
	<i>log.syslogd.setting</i>	log.syslogd.setting		
	<i>log.syslogd.override-setting</i>	log.syslogd.override-setting		
	<i>log.syslogd2.setting</i>	log.syslogd2.setting		
	<i>log.syslogd2.override-setting</i>	log.syslogd2.override-setting		
	<i>log.syslogd3.setting</i>	log.syslogd3.setting		
	<i>log.syslogd3.override-setting</i>	log.syslogd3.override-setting		
	<i>log.syslogd4.setting</i>	log.syslogd4.setting		
	<i>log.syslogd4.override-setting</i>	log.syslogd4.override-setting		
	<i>system.gre-tunnel</i>	system.gre-tunnel		
	<i>system.central-management</i>	system.central-management		
	<i>system.csf</i>	system.csf		
	<i>user.radius</i>	user.radius		
	<i>system.snmp.sysinfo</i>	system.snmp.sysinfo		
	<i>system.snmp.community</i>	system.snmp.community		
	<i>system.snmp.user</i>	system.snmp.user		
	<i>system.interface</i>	system.interface		
<i>vpn.ipsec.phase1-interface</i>	vpn.ipsec.phase1-interface			

Parameter	Description	Type	Size	Default																																			
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>vpn.ipsec.phase2-interface</i></td><td>vpn.ipsec.phase2-interface</td></tr><tr><td><i>router.bgp</i></td><td>router.bgp</td></tr><tr><td><i>router.route-map</i></td><td>router.route-map</td></tr><tr><td><i>router.prefix-list</i></td><td>router.prefix-list</td></tr><tr><td><i>firewall.ippool</i></td><td>firewall.ippool</td></tr><tr><td><i>firewall.ippool6</i></td><td>firewall.ippool6</td></tr><tr><td><i>router.static</i></td><td>router.static</td></tr><tr><td><i>router.static6</i></td><td>router.static6</td></tr><tr><td><i>firewall.vip</i></td><td>firewall.vip</td></tr><tr><td><i>firewall.vip6</i></td><td>firewall.vip6</td></tr><tr><td><i>system.sdwan</i></td><td>system.sdwan</td></tr><tr><td><i>system.saml</i></td><td>system.saml</td></tr><tr><td><i>router.policy</i></td><td>router.policy</td></tr><tr><td><i>router.policy6</i></td><td>router.policy6</td></tr><tr><td><i>log.syslogd.setting</i></td><td>log.syslogd.setting</td></tr><tr><td><i>log.syslogd.override-setting</i></td><td>log.syslogd.override-setting</td></tr></table>		Option	Description	<i>vpn.ipsec.phase2-interface</i>	vpn.ipsec.phase2-interface	<i>router.bgp</i>	router.bgp	<i>router.route-map</i>	router.route-map	<i>router.prefix-list</i>	router.prefix-list	<i>firewall.ippool</i>	firewall.ippool	<i>firewall.ippool6</i>	firewall.ippool6	<i>router.static</i>	router.static	<i>router.static6</i>	router.static6	<i>firewall.vip</i>	firewall.vip	<i>firewall.vip6</i>	firewall.vip6	<i>system.sdwan</i>	system.sdwan	<i>system.saml</i>	system.saml	<i>router.policy</i>	router.policy	<i>router.policy6</i>	router.policy6	<i>log.syslogd.setting</i>	log.syslogd.setting	<i>log.syslogd.override-setting</i>	log.syslogd.override-setting			
	Option	Description																																					
	<i>vpn.ipsec.phase2-interface</i>	vpn.ipsec.phase2-interface																																					
	<i>router.bgp</i>	router.bgp																																					
	<i>router.route-map</i>	router.route-map																																					
	<i>router.prefix-list</i>	router.prefix-list																																					
	<i>firewall.ippool</i>	firewall.ippool																																					
	<i>firewall.ippool6</i>	firewall.ippool6																																					
	<i>router.static</i>	router.static																																					
	<i>router.static6</i>	router.static6																																					
	<i>firewall.vip</i>	firewall.vip																																					
	<i>firewall.vip6</i>	firewall.vip6																																					
	<i>system.sdwan</i>	system.sdwan																																					
	<i>system.saml</i>	system.saml																																					
	<i>router.policy</i>	router.policy																																					
	<i>router.policy6</i>	router.policy6																																					
	<i>log.syslogd.setting</i>	log.syslogd.setting																																					
	<i>log.syslogd.override-setting</i>	log.syslogd.override-setting																																					
scope	Determine whether the configuration object can be configured separately for all VDOMs or if some VDOMs share the same configuration.	option	-	all																																			
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>all</i></td><td>Object configuration independent for all VDOMs.</td></tr><tr><td><i>inclusive</i></td><td>Object configuration independent for the listed VDOMs. Other VDOMs use the global configuration.</td></tr><tr><td><i>exclusive</i></td><td>Use the global object configuration for the listed VDOMs. Other VDOMs can be configured independently.</td></tr></table>		Option	Description	<i>all</i>	Object configuration independent for all VDOMs.	<i>inclusive</i>	Object configuration independent for the listed VDOMs. Other VDOMs use the global configuration.	<i>exclusive</i>	Use the global object configuration for the listed VDOMs. Other VDOMs can be configured independently.																													
	Option	Description																																					
	<i>all</i>	Object configuration independent for all VDOMs.																																					
	<i>inclusive</i>	Object configuration independent for the listed VDOMs. Other VDOMs use the global configuration.																																					
<i>exclusive</i>	Use the global object configuration for the listed VDOMs. Other VDOMs can be configured independently.																																						
vdom <name>	Names of the VDOMs. VDOM name.	string	Maximum length: 79																																				

config system vdom-link

Configure VDOM links.

```
config system vdom-link
  Description: Configure VDOM links.
  edit <name>
    next
  end
```

config system vdom-link

Parameter	Description	Type	Size	Default
name	VDOM link name (maximum = 11 characters).	string	Maximum length: 11	

config system vdom-property

Configure VDOM property.

```
config system vdom-property
  Description: Configure VDOM property.
  edit <name>
    set description {string}
    set snmp-index {integer}
    set ipsec-phase1-interface {user}
    set ipsec-phase2-interface {user}
    set firewall-policy {user}
    set firewall-address {user}
    set firewall-addrgroup {user}
    set custom-service {user}
    set service-group {user}
    set onetime-schedule {user}
    set recurring-schedule {user}
    set user {user}
    set user-group {user}
    set proxy {user}
    set log-disk-quota {user}
  next
end
```

config system vdom-property

Parameter	Description	Type	Size	Default
name	VDOM name.	string	Maximum length: 31	
description	Description.	string	Maximum length: 127	
snmp-index	Permanent SNMP Index of the virtual domain (1 - 2147483647).	integer	Minimum value: 1 Maximum value: 2147483647	0
ipsec-phase1-interface	Maximum guaranteed number of VPN IPsec phase1 interface tunnels.	user	Not Specified	
ipsec-phase2-interface	Maximum guaranteed number of VPN IPsec phase2 interface tunnels.	user	Not Specified	
firewall-policy	Maximum guaranteed number of firewall policies (policy, DoS-policy4, DoS-policy6, multicast).	user	Not Specified	
firewall-address	Maximum guaranteed number of firewall addresses (IPv4, IPv6, multicast).	user	Not Specified	
firewall-addrgroup	Maximum guaranteed number of firewall address groups (IPv4, IPv6).	user	Not Specified	
custom-service	Maximum guaranteed number of firewall custom services.	user	Not Specified	
service-group	Maximum guaranteed number of firewall service groups.	user	Not Specified	
onetime-schedule	Maximum guaranteed number of firewall one-time schedules.	user	Not Specified	
recurring-schedule	Maximum guaranteed number of firewall recurring schedules.	user	Not Specified	
user	Maximum guaranteed number of local users.	user	Not Specified	
user-group	Maximum guaranteed number of user groups.	user	Not Specified	
proxy	Maximum guaranteed number of concurrent proxy users.	user	Not Specified	

Parameter	Description	Type	Size	Default
log-disk-quota	Log disk quota in megabytes (MB). Range depends on how much disk space is available.	user	Not Specified	

config system vdom-radius-server

Configure a RADIUS server to use as a RADIUS Single Sign On (RSSO) server for this VDOM.

```
config system vdom-radius-server
    Description: Configure a RADIUS server to use as a RADIUS Single Sign On (RSSO) server for
    this VDOM.
    edit <name>
        set status [enable|disable]
        set radius-server-vdom {string}
    next
end
```

config system vdom-radius-server

Parameter	Description	Type	Size	Default						
name	Name of the VDOM that you are adding the RADIUS server to.	string	Maximum length: 31							
status	Enable/disable the RSSO RADIUS server for this VDOM.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable the RSSO RADIUS server for this VDOM.</td></tr><tr><td><i>disable</i></td><td>Disable the RSSO RADIUS server for this VDOM.</td></tr></table>				Option	Description	<i>enable</i>	Enable the RSSO RADIUS server for this VDOM.	<i>disable</i>	Disable the RSSO RADIUS server for this VDOM.
	Option	Description								
	<i>enable</i>	Enable the RSSO RADIUS server for this VDOM.								
<i>disable</i>	Disable the RSSO RADIUS server for this VDOM.									
radius-server-vdom	Use this option to select another VDOM containing a VDOM RSSO RADIUS server to use for the current VDOM.	string	Maximum length: 31							

config system vne-tunnel

Configure virtual network enabler tunnel.

```
config system vne-tunnel
    Description: Configure virtual network enabler tunnel.
    set status [enable|disable]
    set interface {string}
```

```

set ssl-certificate {string}
set bmr-hostname {password}
set ipv4-address {ipv4-classnet-host}
set br {string}
set update-url {string}
set mode [map-e|fixed-ip|...]
set http-username {string}
set http-password {password}
end

```

config system vne-tunnel

Parameter	Description	Type	Size	Default
status	Enable/disable VNE tunnel.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable VNE tunnel.		
	<i>disable</i>	Disable VNE tunnel.		
interface	Interface name.	string	Maximum length: 15	
ssl-certificate	Name of local certificate for SSL connections.	string	Maximum length: 35	Fortinet_Factory
bmr-hostname	BMR hostname.	password	Not Specified	
ipv4-address	Tunnel IPv4 address and netmask.	ipv4-classnet-host	Not Specified	0.0.0.0 0.0.0.0
br	IPv6 address or FQDN of the border relay.	string	Maximum length: 255	
update-url	URL of provisioning server.	string	Maximum length: 511	
mode	VNE tunnel mode.	option	-	map-e
	Option	Description		
	<i>map-e</i>	Map-e mode.		
	<i>fixed-ip</i>	Fixed-ip mode.		
	<i>ds-lite</i>	DS-Lite mode.		
http-username	HTTP authentication user name.	string	Maximum length: 64	

Parameter	Description	Type	Size	Default
http-password	HTTP authentication password.	password	Not Specified	

config system vxlan

Configure VXLAN devices.

```

config system vxlan
    Description: Configure VXLAN devices.
    edit <name>
        set interface {string}
        set vni {integer}
        set ip-version [ipv4-unicast|ipv6-unicast]
        set remote-ip <ip1>, <ip2>, ...
        set remote-ip6 <ip61>, <ip62>, ...
        set dstport {integer}
        set multicast-ttl {integer}
    next
end

```

config system vxlan

Parameter	Description	Type	Size	Default						
name	VXLAN device or interface name. Must be a unique interface name.	string	Maximum length: 15							
interface	Outgoing interface for VXLAN encapsulated traffic.	string	Maximum length: 15							
vni	VXLAN network ID.	integer	Minimum value: 1 Maximum value: 16777215	0						
ip-version	IP version to use for the VXLAN interface and so for communication over the VXLAN. IPv4 or IPv6 unicast.	option	-	ipv4-unicast						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>ipv4-unicast</td><td>Use IPv4 unicast addressing over the VXLAN.</td></tr><tr><td>ipv6-unicast</td><td>Use IPv6 unicast addressing over the VXLAN.</td></tr></table>				Option	Description	ipv4-unicast	Use IPv4 unicast addressing over the VXLAN.	ipv6-unicast	Use IPv6 unicast addressing over the VXLAN.
Option	Description									
ipv4-unicast	Use IPv4 unicast addressing over the VXLAN.									
ipv6-unicast	Use IPv6 unicast addressing over the VXLAN.									
remote-ip <ip>	IPv4 address of the VXLAN interface on the device at the remote end of the VXLAN.	string	Maximum length: 15							

Parameter	Description	Type	Size	Default
	IPv4 address.			
remote-ip6 <ip6>	IPv6 IP address of the VXLAN interface on the device at the remote end of the VXLAN. IPv6 address.	string	Maximum length: 45	
dstport	VXLAN destination port (1 - 65535, default = 4789).	integer	Minimum value: 1 Maximum value: 65535	4789
multicast-ttl	VXLAN multicast TTL (1-255, default = 0).	integer	Minimum value: 1 Maximum value: 255	0

config system wccp

Configure WCCP.

```

config system wccp
  Description: Configure WCCP.
  edit <service-id>
    set router-id {ipv4-address}
    set cache-id {ipv4-address}
    set group-address {ipv4-address-multicast}
    set server-list {user}
    set router-list {user}
    set ports-defined [source|destination]
    set server-type [forward|proxy]
    set ports {user}
    set authentication [enable|disable]
    set password {password}
    set forward-method [GRE|L2|...]
    set cache-engine-method [GRE|L2]
    set service-type [auto|standard|...]
    set primary-hash {option1}, {option2}, ...
    set priority {integer}
    set protocol {integer}
    set assignment-weight {integer}
    set assignment-bucket-format [wccp-v2|cisco-implementation]
    set return-method [GRE|L2|...]
    set assignment-method [HASH|MASK|...]
    set assignment-srcaddr-mask {ipv4-netmask-any}
    set assignment-dstaddr-mask {ipv4-netmask-any}
  next
end

```

config system wccp

Parameter	Description	Type	Size	Default						
service-id	Service ID.	string	Maximum length: 3							
router-id	IP address known to all cache engines. If all cache engines connect to the same FortiProxy interface, use the default 0.0.0.0.	ipv4-address	Not Specified	0.0.0.0						
cache-id	IP address known to all routers. If the addresses are the same, use the default 0.0.0.0.	ipv4-address	Not Specified	0.0.0.0						
group-address	IP multicast address used by the cache routers. For the FortiProxy to ignore multicast WCCP traffic, use the default 0.0.0.0.	ipv4-address-multicast	Not Specified	0.0.0.0						
server-list	IP addresses and netmasks for up to four cache servers.	user	Not Specified							
router-list	IP addresses of one or more WCCP routers.	user	Not Specified							
ports-defined	Match method.	option	-							
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>source</td><td>Source port match.</td></tr><tr><td>destination</td><td>Destination port match.</td></tr></table>				Option	Description	source	Source port match.	destination	Destination port match.
Option	Description									
source	Source port match.									
destination	Destination port match.									
server-type	Cache server type.	option	-	forward						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>forward</td><td>Forward server.</td></tr><tr><td>proxy</td><td>Proxy server.</td></tr></table>				Option	Description	forward	Forward server.	proxy	Proxy server.
Option	Description									
forward	Forward server.									
proxy	Proxy server.									
ports	Service ports.	user	Not Specified							
authentication	Enable/disable MD5 authentication.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable MD5 authentication.</td></tr><tr><td>disable</td><td>Disable MD5 authentication.</td></tr></table>				Option	Description	enable	Enable MD5 authentication.	disable	Disable MD5 authentication.
Option	Description									
enable	Enable MD5 authentication.									
disable	Disable MD5 authentication.									

Parameter	Description	Type	Size	Default										
password	Password for MD5 authentication.	password	Not Specified											
forward-method	Method used to forward traffic to the cache servers.	option	-	GRE										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>GRE</i></td><td>GRE encapsulation.</td></tr><tr><td><i>L2</i></td><td>L2 rewrite.</td></tr><tr><td><i>any</i></td><td>GRE or L2.</td></tr></table>	Option	Description	<i>GRE</i>	GRE encapsulation.	<i>L2</i>	L2 rewrite.	<i>any</i>	GRE or L2.					
Option	Description													
<i>GRE</i>	GRE encapsulation.													
<i>L2</i>	L2 rewrite.													
<i>any</i>	GRE or L2.													
cache-engine-method	Method used to forward traffic to the routers or to return to the cache engine.	option	-	GRE										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>GRE</i></td><td>GRE encapsulation.</td></tr><tr><td><i>L2</i></td><td>L2 rewrite.</td></tr></table>	Option	Description	<i>GRE</i>	GRE encapsulation.	<i>L2</i>	L2 rewrite.							
Option	Description													
<i>GRE</i>	GRE encapsulation.													
<i>L2</i>	L2 rewrite.													
service-type	WCCP service type used by the cache server for logical interception and redirection of traffic.	option	-	auto										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>auto</td></tr><tr><td><i>standard</i></td><td>Standard service.</td></tr><tr><td><i>dynamic</i></td><td>Dynamic service.</td></tr></table>	Option	Description	<i>auto</i>	auto	<i>standard</i>	Standard service.	<i>dynamic</i>	Dynamic service.					
Option	Description													
<i>auto</i>	auto													
<i>standard</i>	Standard service.													
<i>dynamic</i>	Dynamic service.													
primary-hash	Hash method.	option	-	dst-ip										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>src-ip</i></td><td>Source IP hash.</td></tr><tr><td><i>dst-ip</i></td><td>Destination IP hash.</td></tr><tr><td><i>src-port</i></td><td>Source port hash.</td></tr><tr><td><i>dst-port</i></td><td>Destination port hash.</td></tr></table>	Option	Description	<i>src-ip</i>	Source IP hash.	<i>dst-ip</i>	Destination IP hash.	<i>src-port</i>	Source port hash.	<i>dst-port</i>	Destination port hash.			
Option	Description													
<i>src-ip</i>	Source IP hash.													
<i>dst-ip</i>	Destination IP hash.													
<i>src-port</i>	Source port hash.													
<i>dst-port</i>	Destination port hash.													
priority	Service priority.	integer	Minimum value: 0 Maximum value: 255	0										

Parameter	Description	Type	Size	Default								
protocol	Service protocol.	integer	Minimum value: 0 Maximum value: 255	0								
assignment-weight	Assignment of hash weight/ratio for the WCCP cache engine.	integer	Minimum value: 0 Maximum value: 255	0								
assignment-bucket-format	Assignment bucket format for the WCCP cache engine.	option	-	cisco-implementation								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>wccp-v2</td><td>WCCP-v2 bucket format.</td></tr><tr><td>cisco-implementation</td><td>Cisco bucket format.</td></tr></table>				Option	Description	wccp-v2	WCCP-v2 bucket format.	cisco-implementation	Cisco bucket format.		
Option	Description											
wccp-v2	WCCP-v2 bucket format.											
cisco-implementation	Cisco bucket format.											
return-method	Method used to decline a redirected packet and return it to the FortiProxy unit.	option	-	GRE								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>GRE</td><td>GRE encapsulation.</td></tr><tr><td>L2</td><td>L2 rewrite.</td></tr><tr><td>any</td><td>GRE or L2.</td></tr></table>				Option	Description	GRE	GRE encapsulation.	L2	L2 rewrite.	any	GRE or L2.
Option	Description											
GRE	GRE encapsulation.											
L2	L2 rewrite.											
any	GRE or L2.											
assignment-method	Hash key assignment preference.	option	-	HASH								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>HASH</td><td>HASH assignment method.</td></tr><tr><td>MASK</td><td>MASK assignment method.</td></tr><tr><td>any</td><td>HASH or MASK.</td></tr></table>				Option	Description	HASH	HASH assignment method.	MASK	MASK assignment method.	any	HASH or MASK.
Option	Description											
HASH	HASH assignment method.											
MASK	MASK assignment method.											
any	HASH or MASK.											
assignment-srcaddr-mask	Assignment source address mask.	ipv4-netmask-any	Not Specified	0.0.23.65								
assignment-dstaddr-mask	Assignment destination address mask.	ipv4-netmask-any	Not Specified	0.0.0.0								

config system zone

Configure zones to group two or more interfaces. When a zone is created you can configure policies for the zone instead of individual interfaces in the zone.

```
config system zone
    Description: Configure zones to group two or more interfaces. When a zone is created you can
    configure policies for the zone instead of individual interfaces in the zone.
    edit <name>
        config tagging
            Description: Config object tagging.
            edit <name>
                set category {string}
                set tags <name1>, <name2>, ...
            next
        end
        set description {string}
        set interface <interface-name1>, <interface-name2>, ...
    next
end
```

config system zone

Parameter	Description	Type	Size	Default
name	Zone name.	string	Maximum length: 35	
description	Description.	string	Maximum length: 127	
interface <interface-name>	Add interfaces to this zone. Interfaces must not be assigned to another zone or have firewall policies defined. Select interfaces to add to the zone.	string	Maximum length: 79	

config tagging

Parameter	Description	Type	Size	Default
name	Tagging entry name.	string	Maximum length: 63	
category	Tag category.	string	Maximum length: 63	
tags <name>	Tags. Tag name.	string	Maximum length: 79	

test

This section includes syntax for the following commands:

- [config test acd on page 1076](#)
- [config test acsd on page 1077](#)
- [config test autod on page 1077](#)
- [config test awsd on page 1078](#)
- [config test azd on page 1078](#)
- [config test bfd on page 1078](#)
- [config test csfd on page 1079](#)
- [config test ddnsd on page 1079](#)
- [config test dhcp6c on page 1079](#)
- [config test dhcp6r on page 1080](#)
- [config test dhcprelay on page 1080](#)
- [config test dlpfingerprint on page 1081](#)
- [config test dlpfpcache on page 1081](#)
- [config test dnsproxy on page 1081](#)
- [config test dsd on page 1082](#)
- [config test eap_supp on page 1082](#)
- [config test fas on page 1082](#)
- [config test fcnacd on page 1083](#)
- [config test fds_notify on page 1083](#)
- [config test fgtlogd on page 1084](#)
- [config test fnbamd on page 1084](#)
- [config test forticldd on page 1084](#)
- [config test forticron on page 1085](#)
- [config test fsd on page 1085](#)
- [config test fsvrd on page 1085](#)
- [config test gcpcd on page 1086](#)
- [config test harelay on page 1086](#)
- [config test hasync on page 1087](#)
- [config test hataik on page 1087](#)
- [config test ibmd on page 1087](#)
- [config test imap on page 1088](#)
- [config test init on page 1088](#)
- [config test iotd on page 1088](#)
- [config test ipamd on page 1089](#)
- [config test ipamsd on page 1089](#)
- [config test ipldbd on page 1090](#)

-
- [config test ipsengine on page 1090](#)
 - [config test ipsmonitor on page 1090](#)
 - [config test ipsufd on page 1091](#)
 - [config test kubed on page 1091](#)
 - [config test l2tpcd on page 1091](#)
 - [config test lnmtd on page 1092](#)
 - [config test locallogd on page 1092](#)
 - [config test miglogd on page 1093](#)
 - [config test mrd on page 1093](#)
 - [config test netxd on page 1093](#)
 - [config test nntp on page 1094](#)
 - [config test ocid on page 1094](#)
 - [config test openstackd on page 1094](#)
 - [config test ovrd on page 1095](#)
 - [config test pop3 on page 1095](#)
 - [config test pptpcd on page 1096](#)
 - [config test quarantined on page 1096](#)
 - [config test radius-das on page 1097](#)
 - [config test radiusd on page 1096](#)
 - [config test radvd on page 1097](#)
 - [config test reportd on page 1097](#)
 - [config test rt_router on page 1098](#)
 - [config test sdncd on page 1098](#)
 - [config test sdnd on page 1099](#)
 - [config test sepmd on page 1099](#)
 - [config test sessionsync on page 1099](#)
 - [config test sfupgraded on page 1100](#)
 - [config test smtp on page 1100](#)
 - [config test snmpd on page 1100](#)
 - [config test syslogd on page 1101](#)
 - [config test updated on page 1101](#)
 - [config test uploadd on page 1102](#)
 - [config test urlfilter on page 1102](#)
 - [config test vned on page 1102](#)
 - [config test wad on page 1103](#)
 - [config test wccpd on page 1103](#)
 - [config test wf_monitor on page 1103](#)
 - [config test wiredapd on page 1104](#)

config test acd

Aggregate Controller.

```
config test acd
  Description: Aggregate Controller.
  set <Integer> {string}
end
```

config test acd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test acsd

Ali Cloud Service daemon.

```
config test acsd
  Description: Ali Cloud Service daemon.
  set <Integer> {string}
end
```

config test acsd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test autod

Automation daemon.

```
config test autod
  Description: Automation daemon.
  set <Integer> {string}
end
```

config test autod

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test awsd

Amazon Web Services (AWS) daemon.

```
config test awsd
  Description: Amazon Web Services (AWS) daemon.
  set <Integer> {string}
end
```

config test awsd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test azd

Microsoft Azure daemon.

```
config test azd
  Description: Microsoft Azure daemon.
  set <Integer> {string}
end
```

config test azd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test bfd

BFD daemon.

```
config test bfd
  Description: BFD daemon.
  set <Integer> {string}
end
```

config test bfd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test csfd

Security Fabric daemon.

```
config test csfd
  Description: Security Fabric daemon.
  set <Integer> {string}
end
```

config test csfd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test ddnsd

DDNS client daemon.

```
config test ddnsd
  Description: DDNS client daemon.
  set <Integer> {string}
end
```

config test ddnsd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test dhcp6c

DHCP6 client daemon.

```
config test dhcp6c
  Description: DHCP6 client daemon.
  set <Integer> {string}
end
```

config test dhcp6c

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test dhcp6r

DHCP6 relay daemon.

```
config test dhcp6r
  Description: DHCP6 relay daemon.
  set <Integer> {string}
end
```

config test dhcp6r

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test dhcprelay

DHCP relay daemon.

```
config test dhcprelay
  Description: DHCP relay daemon.
  set <Integer> {string}
end
```

config test dhcprelay

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test dlpfingerprint

DLP fingerprint daemon.

```
config test dlpfingerprint
  Description: DLP fingerprint daemon.
  set <Integer> {string}
end
```

config test dlpfingerprint

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test dlpfpcache

DLP fingerprint cache daemon.

```
config test dlpfpcache
  Description: DLP fingerprint cache daemon.
  set <Integer> {string}
end
```

config test dlpfpcache

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test dnsproxy

DNS proxy.

```
config test dnsproxy
  Description: DNS proxy.
  set <Integer> {string}
end
```

config test dnsproxy

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test dsd

DLP Statistics daemon.

```
config test dsd
  Description: DLP Statistics daemon.
  set <Integer> {string}
end
```

config test dsd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test eap_supp

EAP Supplicant daemon.

```
config test eap_supp
  Description: EAP Supplicant daemon.
  set <Integer> {string}
end
```

config test eap_supp

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test fas

FortiToken Cloud daemon.

```
config test fas
  Description: FortiToken Cloud daemon.
  set <Integer> {string}
end
```

config test fas

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test fcnacd

FortiClient NAC daemon.

```
config test fcnacd
  Description: FortiClient NAC daemon.
  set <Integer> {string}
end
```

config test fcnacd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test fds_notify

Update Notification daemon.

```
config test fds_notify
  Description: Update Notification daemon.
  set <Integer> {string}
end
```

config test fds_notify

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test fgtlogd

Fgtlog daemon.

```
config test fgtlogd
  Description: Fgtlog daemon.
  set <Integer> {string}
end
```

config test fgtlogd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test fnbamd

Fortiproxy non-blocking auth daemon.

```
config test fnbamd
  Description: Fortiproxy non-blocking auth daemon.
  set <Integer> {string}
end
```

config test fnbamd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test forticldd

FortiCloud daemon.

```
config test forticldd
  Description: FortiCloud daemon.
  set <Integer> {string}
end
```

config test forticldd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test forticron

Forticron daemon.

```
config test forticron
  Description: Forticron daemon.
  set <Integer> {string}
end
```

config test forticron

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test fsd

FortiExplorer daemon.

```
config test fsd
  Description: FortiExplorer daemon.
  set <Integer> {string}
end
```

config test fsd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test fsvrd

FortiService daemon.

```
config test fsvr
  Description: FortiService daemon.
  set <Integer> {string}
end
```

config test fsvr

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test gcpd

Google Cloud Platform (GCP) daemon.

```
config test gcpd
  Description: Google Cloud Platform (GCP) daemon.
  set <Integer> {string}
end
```

config test gcpd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test harelay

HA relay daemon.

```
config test harelay
  Description: HA relay daemon.
  set <Integer> {string}
end
```

config test harelay

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test hasync

HA sync daemon.

```
config test hasync
  Description: HA sync daemon.
  set <Integer> {string}
end
```

config test hasync

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test hatalk

HA talk daemon.

```
config test hatalk
  Description: HA talk daemon.
  set <Integer> {string}
end
```

config test hatalk

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test ibmd

IBM Cloud Infrastructure daemon.

```
config test ibmd
  Description: IBM Cloud Infrastructure daemon.
  set <Integer> {string}
end
```

config test ibmd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test imap

IMAP proxy.

```
config test imap
  Description: IMAP proxy.
  set <Integer> {string}
end
```

config test imap

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test init

init process.

```
config test init
  Description: init process.
  set <Integer> {string}
end
```

config test init

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test iotd

IoT device info daemon.


```
config test iotd
    Description: IoT device info daemon.
    set <Integer> {string}
end
```

config test iotd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test ipamd

IP Address Management daemon.

```
config test ipamd
    Description: IP Address Management daemon.
    set <Integer> {string}
end
```

config test ipamd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test ipamsd

IPAM server daemon.

```
config test ipamsd
    Description: IPAM server daemon.
    set <Integer> {string}
end
```

config test ipamsd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test ipldbd

IP load balancing daemon.

```
config test ipldbd
    Description: IP load balancing daemon.
    set <Integer> {string}
end
```

config test ipldbd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test ipsengine

IPS sensor.

```
config test ipsengine
    Description: IPS sensor.
    set <Integer> {string}
end
```

config test ipsengine

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test ipsmonitor

IPS monitor.

```
config test ipsmonitor
    Description: IPS monitor.
    set <Integer> {string}
end
```

config test ipsmonitor

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test ipsufd

IPS urlfilter daemon.

```
config test ipsufd
  Description: IPS urlfilter daemon.
  set <Integer> {string}
end
```

config test ipsufd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test kubed

Kubernetes daemon.

```
config test kubed
  Description: Kubernetes daemon.
  set <Integer> {string}
end
```

config test kubed

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test l2tpcd

L2TP client daemon.

```
config test l2tpcd
  Description: L2TP client daemon.
  set <Integer> {string}
end
```

config test l2tpcd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test lnkmttd

Link monitor daemon.

```
config test lnkmttd
  Description: Link monitor daemon.
  set <Integer> {string}
end
```

config test lnkmttd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test locallogd

Locallogd daemon.

```
config test locallogd
  Description: Locallogd daemon.
  set <Integer> {string}
end
```

config test locallogd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test miglogd

Miglog logging daemon.

```
config test miglogd
  Description: Miglog logging daemon.
  set <Integer> {string}
end
```

config test miglogd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test mrd

Mobile router daemon.

```
config test mrd
  Description: Mobile router daemon.
  set <Integer> {string}
end
```

config test mrd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test netxd

VMWare NetX service manager daemon.

```
config test netxd
  Description: VMWare NetX service manager daemon.
  set <Integer> {string}
end
```

config test netxd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test nntp

NNTP proxy.

```
config test nntp
  Description: NNTP proxy.
  set <Integer> {string}
end
```

config test nntp

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test ocid

Oracle Cloud Infrastructure.

```
config test ocid
  Description: Oracle Cloud Infrastructure.
  set <Integer> {string}
end
```

config test ocid

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test openstackd

OpenStack SDN connector daemon.

```
config test openstackd
  Description: OpenStack SDN connector daemon.
  set <Integer> {string}
end
```

config test openstackd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test ovrd

Override daemon.

```
config test ovrd
  Description: Override daemon.
  set <Integer> {string}
end
```

config test ovrd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test pop3

POP3 proxy.

```
config test pop3
  Description: POP3 proxy.
  set <Integer> {string}
end
```

config test pop3

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test pptpcd

PPTP client.

```
config test pptpcd
  Description: PPTP client.
  set <Integer> {string}
end
```

config test pptpcd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test quarantined

Quarantine daemon.

```
config test quarantined
  Description: Quarantine daemon.
  set <Integer> {string}
end
```

config test quarantined

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test radiusd

RADIUS daemon.

```
config test radiusd
  Description: RADIUS daemon.
  set <Integer> {string}
end
```

config test radiusd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test radius-das

Radius-das daemon.

```
config test radius-das
  Description: Radius-das daemon.
  set <Integer> {string}
end
```

config test radius-das

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test radvd

radvd daemon.

```
config test radvd
  Description: radvd daemon.
  set <Integer> {string}
end
```

config test radvd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test reportd

Report daemon.

```
config test reportd
  Description: Report daemon.
  set <Integer> {string}
end
```

config test reportd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test rt_router

Router daemon

```
config test rt_router
  Description: Router daemon
  set <Integer> {string}
end
```

config test rt_router

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test sdncd

SDN Connector daemon.

```
config test sdncd
  Description: SDN Connector daemon.
  set <Integer> {string}
end
```

config test sdncd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test sdnd

SDN connector daemon.

```
config test sdnd
  Description: SDN connector daemon.
  set <Integer> {string}
end
```

config test sdnd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test sepmd

Symantec Endpoint Protection Manager daemon.

```
config test sepmd
  Description: Symantec Endpoint Protection Manager daemon.
  set <Integer> {string}
end
```

config test sepmd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test sessionsync

Session sync daemon.

```
config test sessionsync
  Description: Session sync daemon.
  set <Integer> {string}
end
```

config test sessionsync

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test sfupgraded

Security Fabric Upgrade daemon.

```
config test sfupgraded
  Description: Security Fabric Upgrade daemon.
  set <Integer> {string}
end
```

config test sfupgraded

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test smtp

SMTP proxy.

```
config test smtp
  Description: SMTP proxy.
  set <Integer> {string}
end
```

config test smtp

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test snmpd

SNMP daemon.

```
config test snmpd
  Description: SNMP daemon.
  set <Integer> {string}
end
```

config test snmpd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test syslogd

Syslog daemon.

```
config test syslogd
  Description: Syslog daemon.
  set <Integer> {string}
end
```

config test syslogd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test updated

Update daemon.

```
config test updated
  Description: Update daemon.
  set <Integer> {string}
end
```

config test updated

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test uploadd

Upload daemon.

```
config test uploadd
  Description: Upload daemon.
  set <Integer> {string}
end
```

config test uploadd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test urlfilter

URL filter daemon.

```
config test urlfilter
  Description: URL filter daemon.
  set <Integer> {string}
end
```

config test urlfilter

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test vned

Virtual network enabler daemon.

```
config test vned
  Description: Virtual network enabler daemon.
  set <Integer> {string}
end
```

config test vned

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test wad

WAD related processes.

```
config test wad
  Description: WAD related processes.
  set <Integer> {string}
end
```

config test wad

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test wccpd

WCCP daemon.

```
config test wccpd
  Description: WCCP daemon.
  set <Integer> {string}
end
```

config test wccpd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test wf_monitor

WF monitor.

```
config test wf_monitor
  Description: WF monitor.
  set <Integer> {string}
end
```

config test wf_monitor

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

config test wiredapd

Wiredapd daemon.

```
config test wiredapd
  Description: Wiredapd daemon.
  set <Integer> {string}
end
```

config test wiredapd

Parameter	Description	Type	Size	Default
<Integer>	Test level.	string	Maximum length: -	

user

This section includes syntax for the following commands:

- [config user adgrp on page 1105](#)
- [config user certificate on page 1106](#)
- [config user domain-controller on page 1107](#)
- [config user exchange on page 1111](#)
- [config user external-identity-provider on page 1113](#)
- [config user fortitoken on page 1115](#)
- [config user fsso-polling on page 1120](#)
- [config user fsso on page 1116](#)
- [config user group on page 1122](#)
- [config user krb-keytab on page 1128](#)
- [config user ldap on page 1129](#)
- [config user local on page 1138](#)
- [config user password-policy on page 1141](#)
- [config user peer on page 1142](#)
- [config user peergrp on page 1144](#)
- [config user pop3 on page 1145](#)
- [config user radius on page 1146](#)
- [config user saml on page 1159](#)
- [config user security-exempt-list on page 1163](#)
- [config user setting on page 1164](#)
- [config user tacacs+ on page 1169](#)

config user adgrp

Configure FSSO groups.

```
config user adgrp
  Description: Configure FSSO groups.
  edit <name>
    set server-name {string}
    set connector-source {string}
    set id {integer}
  next
end
```

config user adgrp

Parameter	Description	Type	Size	Default
name	Name.	string	Maximum length: 511	
server-name	FSSO agent name.	string	Maximum length: 35	
connector-source	FSSO connector source.	string	Maximum length: 35	
id	Group ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

config user certificate

Configure certificate users.

```
config user certificate
  Description: Configure certificate users.
  edit <name>
    set id {integer}
    set status [enable|disable]
    set type [single-certificate|trusted-issuer]
    set common-name {string}
    set issuer {string}
  next
end
```

config user certificate

Parameter	Description	Type	Size	Default
name	User name.	string	Maximum length: 64	
id	User ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

Parameter	Description	Type	Size	Default						
status	Enable/disable allowing the certificate user to authenticate with the FortiGate unit.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable user.</td></tr><tr><td><i>disable</i></td><td>Disable user.</td></tr></table>	Option	Description	<i>enable</i>	Enable user.	<i>disable</i>	Disable user.			
Option	Description									
<i>enable</i>	Enable user.									
<i>disable</i>	Disable user.									
type	Type of certificate authentication method.	option	-	single-certificate						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>single-certificate</i></td><td>Single certificate.</td></tr><tr><td><i>trusted-issuer</i></td><td>Trusted CA issuer.</td></tr></table>	Option	Description	<i>single-certificate</i>	Single certificate.	<i>trusted-issuer</i>	Trusted CA issuer.			
Option	Description									
<i>single-certificate</i>	Single certificate.									
<i>trusted-issuer</i>	Trusted CA issuer.									
common-name	Certificate common name.	string	Maximum length: 64							
issuer	CA certificate used for client certificate verification.	string	Maximum length: 79							

config user domain-controller

Configure domain controller entries.

```

config user domain-controller
    Description: Configure domain controller entries.
    edit <name>
        set ad-mode [none|ds|...]
        set hostname {string}
        set username {string}
        set password {password}
        set ip-address {ipv4-address}
        set ip6 {ipv6-address}
        set port {integer}
        set source-ip-address {ipv4-address}
        set source-ip6 {ipv6-address}
        set source-port {integer}
        set interface-select-method [auto|specify]
        set interface {string}
        config extra-server
            Description: Extra servers.
            edit <id>
                set ip-address {ipv4-address}
                set port {integer}

```

```

        set source-ip-address {ipv4-address}
        set source-port {integer}
    next
end
set domain-name {string}
set domain-name-src [server|client]
set replication-port {integer}
set ldap-server <name1>, <name2>, ...
set change-detection [enable|disable]
set change-detection-period {integer}
set dns-srv-lookup [enable|disable]
set adlds-dn {string}
set adlds-ip-address {ipv4-address}
set adlds-ip6 {ipv6-address}
set adlds-port {integer}
next
end

```

config user domain-controller

Parameter	Description	Type	Size	Default
name	Domain controller entry name.	string	Maximum length: 35	
ad-mode	Set Active Directory mode.	option	-	none
	Option	Description		
	none	The server is not configured as an Active Directory Domain Server (AD DS).		
	ds	The server is configured as an Active Directory Domain Server (AD DS).		
	lds	The server is an Active Directory Lightweight Domain Server (AD LDS).		
hostname	Hostname of the server to connect to.	string	Maximum length: 255	
username	User name to sign in with. Must have proper permissions for service.	string	Maximum length: 64	
password	Password for specified username.	password	Not Specified	
ip-address	Domain controller IPv4 address.	ipv4-address	Not Specified	0.0.0.0
ip6	Domain controller IPv6 address.	ipv6-address	Not Specified	::

Parameter	Description	Type	Size	Default						
port	Port to be used for communication with the domain controller (default = 445).	integer	Minimum value: 0 Maximum value: 65535	445						
source-ip-address	FortiProxy IPv4 address to be used for communication with the domain controller.	ipv4-address	Not Specified	0.0.0.0						
source-ip6	FortiProxy IPv6 address to be used for communication with the domain controller.	ipv6-address	Not Specified	::						
source-port	Source port to be used for communication with the domain controller.	integer	Minimum value: 0 Maximum value: 65535	0						
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Set outgoing interface automatically.</td></tr><tr><td><i>specify</i></td><td>Set outgoing interface manually.</td></tr></table>				Option	Description	<i>auto</i>	Set outgoing interface automatically.	<i>specify</i>	Set outgoing interface manually.
Option	Description									
<i>auto</i>	Set outgoing interface automatically.									
<i>specify</i>	Set outgoing interface manually.									
interface	Specify outgoing interface to reach server.	string	Maximum length: 15							
domain-name	Domain DNS name.	string	Maximum length: 255							
domain-name-src	Select where to extract domain name (default = server).	option	-	client						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>server</i></td><td>Extract domain name from server's (Domain Controller) data.</td></tr><tr><td><i>client</i></td><td>Extract domain name from client's data.</td></tr></table>				Option	Description	<i>server</i>	Extract domain name from server's (Domain Controller) data.	<i>client</i>	Extract domain name from client's data.
Option	Description									
<i>server</i>	Extract domain name from server's (Domain Controller) data.									
<i>client</i>	Extract domain name from client's data.									
replication-port	Port to be used for communication with the domain controller for replication service. Port number 0 indicates automatic discovery.	integer	Minimum value: 0 Maximum value: 65535	0						
ldap-server <name>	LDAP server name(s). LDAP server name.	string	Maximum length: 79							

Parameter	Description	Type	Size	Default						
change-detection	Enable/disable detection of a configuration change in the Active Directory server.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable detection of a configuration change in the Active Directory server.</td></tr><tr><td><i>disable</i></td><td>Disable detection of a configuration change in the Active Directory server.</td></tr></table>	Option	Description	<i>enable</i>	Enable detection of a configuration change in the Active Directory server.	<i>disable</i>	Disable detection of a configuration change in the Active Directory server.			
Option	Description									
<i>enable</i>	Enable detection of a configuration change in the Active Directory server.									
<i>disable</i>	Disable detection of a configuration change in the Active Directory server.									
change-detection-period	Minutes to detect a configuration change in the Active Directory server (5 - 10080 minutes (7 days), default = 60).	integer	Minimum value: 5 Maximum value: 10080	60						
dns-srv-lookup	Enable/disable DNS service lookup.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable DNS service lookup.</td></tr><tr><td><i>disable</i></td><td>Disable DNS service lookup.</td></tr></table>	Option	Description	<i>enable</i>	Enable DNS service lookup.	<i>disable</i>	Disable DNS service lookup.			
Option	Description									
<i>enable</i>	Enable DNS service lookup.									
<i>disable</i>	Disable DNS service lookup.									
adlds-dn	AD LDS distinguished name.	string	Maximum length: 255							
adlds-ip-address	AD LDS IPv4 address.	ipv4-address	Not Specified	0.0.0.0						
adlds-ip6	AD LDS IPv6 address.	ipv6-address	Not Specified	::						
adlds-port	Port number of AD LDS service (default = 389).	integer	Minimum value: 0 Maximum value: 65535	389						

config extra-server

Parameter	Description	Type	Size	Default
id	Server ID.	integer	Minimum value: 1 Maximum value: 100	0

Parameter	Description	Type	Size	Default
ip-address	Domain controller IP address.	ipv4-address	Not Specified	0.0.0.0
port	Port to be used for communication with the domain controller (default = 445).	integer	Minimum value: 0 Maximum value: 65535	445
source-ip-address	FortiProxy IPv4 address to be used for communication with the domain controller.	ipv4-address	Not Specified	0.0.0.0
source-port	Source port to be used for communication with the domain controller.	integer	Minimum value: 0 Maximum value: 65535	0

config user exchange

Configure MS Exchange server entries.

```

config user exchange
    Description: Configure MS Exchange server entries.
    edit <name>
        set server-name {string}
        set domain-name {string}
        set username {string}
        set password {password}
        set ip {ipv4-address-any}
        set connect-protocol [rpc-over-tcp|rpc-over-http|...]
        set auth-type [spnego|ntlm|...]
        set auth-level [connect|call|...]
        set http-auth-type [basic|ntlm]
        set ssl-min-proto-version [default|SSLv3|...]
        set auto-discover-kdc [enable|disable]
        set kdc-ip <ipv41>, <ipv42>, ...
    next
end

```

config user exchange

Parameter	Description	Type	Size	Default
name	MS Exchange server entry name.	string	Maximum length: 35	

Parameter	Description	Type	Size	Default												
server-name	MS Exchange server hostname.	string	Maximum length: 63													
domain-name	MS Exchange server fully qualified domain name.	string	Maximum length: 79													
username	User name used to sign in to the server. Must have proper permissions for service.	string	Maximum length: 64													
password	Password for the specified username.	password	Not Specified													
ip	Server IPv4 address.	ipv4-address-any	Not Specified	0.0.0.0												
connect-protocol	Connection protocol used to connect to MS Exchange service.	option	-	rpc-over-https												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>rpc-over-tcp</td><td>Connect using RPC-over-TCP. Use for MS Exchange 2010 and earlier versions. Supported in MS Exchange 2013.</td></tr><tr><td>rpc-over-http</td><td>Connect using RPC-over-HTTP. Use for MS Exchange 2016 and later versions. Supported in MS Exchange 2013.</td></tr><tr><td>rpc-over-https</td><td>Connect using RPC-over-HTTPS. Use for MS Exchange 2016 and later versions. Supported in MS Exchange 2013.</td></tr></table>				Option	Description	rpc-over-tcp	Connect using RPC-over-TCP. Use for MS Exchange 2010 and earlier versions. Supported in MS Exchange 2013.	rpc-over-http	Connect using RPC-over-HTTP. Use for MS Exchange 2016 and later versions. Supported in MS Exchange 2013.	rpc-over-https	Connect using RPC-over-HTTPS. Use for MS Exchange 2016 and later versions. Supported in MS Exchange 2013.				
Option	Description															
rpc-over-tcp	Connect using RPC-over-TCP. Use for MS Exchange 2010 and earlier versions. Supported in MS Exchange 2013.															
rpc-over-http	Connect using RPC-over-HTTP. Use for MS Exchange 2016 and later versions. Supported in MS Exchange 2013.															
rpc-over-https	Connect using RPC-over-HTTPS. Use for MS Exchange 2016 and later versions. Supported in MS Exchange 2013.															
auth-type	Authentication security type used for the RPC protocol layer.	option	-	kerberos												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>spnego</td><td>Negotiate authentication.</td></tr><tr><td>ntlm</td><td>NTLM authentication.</td></tr><tr><td>kerberos</td><td>Kerberos authentication.</td></tr></table>				Option	Description	spnego	Negotiate authentication.	ntlm	NTLM authentication.	kerberos	Kerberos authentication.				
Option	Description															
spnego	Negotiate authentication.															
ntlm	NTLM authentication.															
kerberos	Kerberos authentication.															
auth-level	Authentication security level used for the RPC protocol layer.	option	-	privacy												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>connect</td><td>RPC authentication level 'connect'.</td></tr><tr><td>call</td><td>RPC authentication level 'call'.</td></tr><tr><td>packet</td><td>RPC authentication level 'packet'.</td></tr><tr><td>integrity</td><td>RPC authentication level 'integrity'.</td></tr><tr><td>privacy</td><td>RPC authentication level 'privacy'.</td></tr></table>				Option	Description	connect	RPC authentication level 'connect'.	call	RPC authentication level 'call'.	packet	RPC authentication level 'packet'.	integrity	RPC authentication level 'integrity'.	privacy	RPC authentication level 'privacy'.
Option	Description															
connect	RPC authentication level 'connect'.															
call	RPC authentication level 'call'.															
packet	RPC authentication level 'packet'.															
integrity	RPC authentication level 'integrity'.															
privacy	RPC authentication level 'privacy'.															

Parameter	Description	Type	Size	Default												
http-auth-type	Authentication security type used for the HTTP transport.	option	-	ntlm												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>basic</i></td><td>Basic HTTP authentication.</td></tr><tr><td><i>ntlm</i></td><td>NTLM HTTP authentication.</td></tr></table>	Option	Description	<i>basic</i>	Basic HTTP authentication.	<i>ntlm</i>	NTLM HTTP authentication.									
Option	Description															
<i>basic</i>	Basic HTTP authentication.															
<i>ntlm</i>	NTLM HTTP authentication.															
ssl-min-proto-version	Minimum SSL/TLS protocol version for HTTPS transport (default is to follow system global setting).	option	-	default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Follow system global setting.</td></tr><tr><td><i>SSLv3</i></td><td>SSLv3.</td></tr><tr><td><i>TLSv1</i></td><td>TLSv1.</td></tr><tr><td><i>TLSv1-1</i></td><td>TLSv1.1.</td></tr><tr><td><i>TLSv1-2</i></td><td>TLSv1.2.</td></tr></table>	Option	Description	<i>default</i>	Follow system global setting.	<i>SSLv3</i>	SSLv3.	<i>TLSv1</i>	TLSv1.	<i>TLSv1-1</i>	TLSv1.1.	<i>TLSv1-2</i>	TLSv1.2.			
Option	Description															
<i>default</i>	Follow system global setting.															
<i>SSLv3</i>	SSLv3.															
<i>TLSv1</i>	TLSv1.															
<i>TLSv1-1</i>	TLSv1.1.															
<i>TLSv1-2</i>	TLSv1.2.															
auto-discover-kdc	Enable/disable automatic discovery of KDC IP addresses.	option	-	enable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable automatic discovery of KDC IP addresses.</td></tr><tr><td><i>disable</i></td><td>Disable automatic discovery of KDC IP addresses.</td></tr></table>	Option	Description	<i>enable</i>	Enable automatic discovery of KDC IP addresses.	<i>disable</i>	Disable automatic discovery of KDC IP addresses.									
Option	Description															
<i>enable</i>	Enable automatic discovery of KDC IP addresses.															
<i>disable</i>	Disable automatic discovery of KDC IP addresses.															
kdc-ip <ipv4>	KDC IPv4 addresses for Kerberos authentication. KDC IPv4 addresses for Kerberos authentication.	string	Maximum length: 79													

config user external-identity-provider

Configure external identity provider.

```

config user external-identity-provider
  Description: Configure external identity provider.
  edit <name>
    set type {option}
    set version [v1.0|beta]
    set url {string}
    set user-attr-name {string}
  
```

```

set group-attr-name {string}
set port {integer}
set source-ip {string}
set interface-select-method [auto|specify]
set interface {string}
set server-identity-check [disable|enable]
set timeout {integer}
next
end

```

config user external-identity-provider

Parameter	Description	Type	Size	Default
name	External identity provider name.	string	Maximum length: 35	
type	External identity provider type.	option	-	
	Option	Description		
	<i>ms-graph</i>	Microsoft Graph server.		
version	External identity API version.	option	-	
	Option	Description		
	<i>v1.0</i>	MS Graph REST API v1.0.		
	<i>beta</i>	MS Graph REST API beta (debug build only).		
url	External identity provider URL (e.g. "https://example.com:8080/api/v1").	string	Maximum length: 127	
user-attr-name	User attribute name in authentication query.	string	Maximum length: 63	userPrincipalName
group-attr-name	Group attribute name in authentication query.	string	Maximum length: 63	id
port	External identity provider service port number (0 to use default).	integer	Minimum value: 0 Maximum value: 65535	0
source-ip	Use this IPv4/v6 address to connect to the external identity provider.	string	Maximum length: 63	
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>auto</i>	Set outgoing interface automatically.		
	<i>specify</i>	Set outgoing interface manually.		
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	
server-identity-check	Enable/disable server's identity check against its certificate and subject alternative name(s).	option	-	enable
	Option	Description		
	<i>disable</i>	Do not check server's identity against its certificate and subject alternative name(s).		
	<i>enable</i>	Check server's identity against its certificate and subject alternative name(s).		
timeout	Connection timeout value in seconds (default=5).	integer	Minimum value: 1 Maximum value: 60	5

config user fortitoken

Configure FortiToken.

```

config user fortitoken
  Description: Configure FortiToken.
  edit <serial-number>
    set status [active|lock]
    set comments {var-string}
    set license {string}
    set activation-code {string}
    set activation-expire {integer}
    set reg-id {string}
    set os-ver {string}
  next
end

```

config user fortitoken

Parameter	Description	Type	Size	Default
serial-number	Serial number.	string	Maximum length: 16	
status	Status.	option	-	active
	Option	Description		
	<i>active</i>	Activate FortiToken.		
	<i>lock</i>	Lock FortiToken.		
comments	Comment.	var-string	Maximum length: 255	
license	Mobile token license.	string	Maximum length: 31	
activation-code	Mobile token user activation-code.	string	Maximum length: 32	
activation-expire	Mobile token user activation-code expire time.	integer	Minimum value: 0 Maximum value: 4294967295	0
reg-id	Device Reg ID.	string	Maximum length: 256	
os-ver	Device Mobile Version.	string	Maximum length: 15	

config user fsso

Configure Fortinet Single Sign On (FSSO) agents.

```
config user fsso
  Description: Configure Fortinet Single Sign On (FSSO) agents.
  edit <name>
    set type [default|fortinac]
    set server {string}
    set port {integer}
    set password {password}
    set server2 {string}
    set port2 {integer}
    set password2 {password}
    set server3 {string}
    set port3 {integer}
```

```

set password3 {password}
set server4 {string}
set port4 {integer}
set password4 {password}
set server5 {string}
set port5 {integer}
set password5 {password}
set logon-timeout {integer}
set ldap-server {string}
set group-poll-interval {integer}
set ldap-poll [enable|disable]
set ldap-poll-interval {integer}
set ldap-poll-filter {string}
set user-info-server {string}
set ssl [enable|disable]
set sni {string}
set ssl-server-host-ip-check [enable|disable]
set ssl-trusted-cert {string}
set source-ip {ipv4-address}
set source-ip6 {ipv6-address}
set interface-select-method [auto|specify]
set interface {string}
next
end

```

config user fsso

Parameter	Description	Type	Size	Default
name	Name.	string	Maximum length: 35	
type	Server type.	option	-	default
	Option	Description		
	<i>default</i>	All other unspecified types of servers.		
	<i>fortinac</i>	FortiNAC server.		
server	Domain name or IP address of the first FSSO collector agent.	string	Maximum length: 63	
port	Port of the first FSSO collector agent.	integer	Minimum value: 1 Maximum value: 65535	8000

Parameter	Description	Type	Size	Default
password	Password of the first FSSO collector agent.	password	Not Specified	
server2	Domain name or IP address of the second FSSO collector agent.	string	Maximum length: 63	
port2	Port of the second FSSO collector agent.	integer	Minimum value: 1 Maximum value: 65535	8000
password2	Password of the second FSSO collector agent.	password	Not Specified	
server3	Domain name or IP address of the third FSSO collector agent.	string	Maximum length: 63	
port3	Port of the third FSSO collector agent.	integer	Minimum value: 1 Maximum value: 65535	8000
password3	Password of the third FSSO collector agent.	password	Not Specified	
server4	Domain name or IP address of the fourth FSSO collector agent.	string	Maximum length: 63	
port4	Port of the fourth FSSO collector agent.	integer	Minimum value: 1 Maximum value: 65535	8000
password4	Password of the fourth FSSO collector agent.	password	Not Specified	
server5	Domain name or IP address of the fifth FSSO collector agent.	string	Maximum length: 63	
port5	Port of the fifth FSSO collector agent.	integer	Minimum value: 1 Maximum value: 65535	8000

Parameter	Description	Type	Size	Default						
password5	Password of the fifth FSSO collector agent.	password	Not Specified							
logon-timeout	Interval in minutes to keep logons after FSSO server down.	integer	Minimum value: 1 Maximum value: 2880	5						
ldap-server	LDAP server to get group information.	string	Maximum length: 35							
group-poll-interval	Interval in minutes within to fetch groups from FSSO server, or unset to disable.	integer	Minimum value: 1 Maximum value: 2880	0						
ldap-poll	Enable/disable automatic fetching of groups from LDAP server.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable automatic fetching of groups from LDAP server.</td></tr><tr><td><i>disable</i></td><td>Disable automatic fetching of groups from LDAP server.</td></tr></table>				Option	Description	<i>enable</i>	Enable automatic fetching of groups from LDAP server.	<i>disable</i>	Disable automatic fetching of groups from LDAP server.
Option	Description									
<i>enable</i>	Enable automatic fetching of groups from LDAP server.									
<i>disable</i>	Disable automatic fetching of groups from LDAP server.									
ldap-poll-interval	Interval in minutes within to fetch groups from LDAP server.	integer	Minimum value: 1 Maximum value: 2880	180						
ldap-poll-filter	Filter used to fetch groups.	string	Maximum length: 2047	(objectCategory=group)						
user-info-server	LDAP server to get user information.	string	Maximum length: 35							
ssl	Enable/disable use of SSL.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable use of SSL.</td></tr><tr><td><i>disable</i></td><td>Disable use of SSL.</td></tr></table>				Option	Description	<i>enable</i>	Enable use of SSL.	<i>disable</i>	Disable use of SSL.
Option	Description									
<i>enable</i>	Enable use of SSL.									
<i>disable</i>	Disable use of SSL.									
sni	Server Name Indication.	string	Maximum length: 255							

Parameter	Description	Type	Size	Default
ssl-server-host-ip-check	Enable/disable server host/IP verification.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable server host/IP verification.		
	<i>disable</i>	Disable server host/IP verification.		
ssl-trusted-cert	Trusted server certificate or CA certificate.	string	Maximum length: 79	
source-ip	Source IP for communications to FSSO agent.	ipv4-address	Not Specified	0.0.0.0
source-ip6	IPv6 source for communications to FSSO agent.	ipv6-address	Not Specified	::
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto
	Option	Description		
	<i>auto</i>	Set outgoing interface automatically.		
	<i>specify</i>	Set outgoing interface manually.		
interface	Specify outgoing interface to reach server.	string	Maximum length: 15	

config user fsso-polling

Configure FSSO active directory servers for polling mode.

```

config user fsso-polling
  Description: Configure FSSO active directory servers for polling mode.
  edit <id>
    set status [enable|disable]
    set server {string}
    set default-domain {string}
    set port {integer}
    set user {string}
    set password {password}
    set ldap-server {string}
    set logon-history {integer}
    set polling-frequency {integer}

```



```

config adgrp
    Description: LDAP Group Info.
    edit <name>
        next
    end
    set smbv1 [enable|disable]
    set smb-ntlmv1-auth [enable|disable]
next
end

```

config user fsso-polling

Parameter	Description	Type	Size	Default						
id	Active Directory server ID.	integer	Minimum value: 0 Maximum value: 4294967295	0						
status	Enable/disable polling for the status of this Active Directory server.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable setting.</td></tr><tr><td>disable</td><td>Disable setting.</td></tr></table>				Option	Description	enable	Enable setting.	disable	Disable setting.
	Option	Description								
	enable	Enable setting.								
disable	Disable setting.									
server	Host name or IP address of the Active Directory server.	string	Maximum length: 63							
default-domain	Default domain managed by this Active Directory server.	string	Maximum length: 35							
port	Port to communicate with this Active Directory server.	integer	Minimum value: 0 Maximum value: 65535	0						
user	User name required to log into this Active Directory server.	string	Maximum length: 35							
password	Password required to log into this Active Directory server.	password	Not Specified							
ldap-server	LDAP server name used in LDAP connection strings.	string	Maximum length: 35							

Parameter	Description	Type	Size	Default
logon-history	Number of hours of logon history to keep, 0 means keep all history.	integer	Minimum value: 0 Maximum value: 48	8
polling-frequency	Polling frequency (every 1 to 30 seconds).	integer	Minimum value: 1 Maximum value: 30	10
smbv1	Enable/disable support of SMBv1 for Samba.	option	-	disable
	Option		Description	
	<i>enable</i>		Enable support of SMBv1 for Samba.	
	<i>disable</i>		Disable support of SMBv1 for Samba.	
smb-ntlmv1-auth	Enable/disable support of NTLMv1 for Samba authentication.	option	-	disable
	Option		Description	
	<i>enable</i>		Enable support of NTLMv1 for Samba authentication.	
	<i>disable</i>		Disable support of NTLMv1 for Samba authentication.	

config adgrp

Parameter	Description	Type	Size	Default
name	Name.	string	Maximum length: 511	

config user group

Configure user groups.

```

config user group
  Description: Configure user groups.
  edit <name>
    set id {integer}
    set group-type [firewall|fsso-service|...]
    set authtimeout {integer}
    set auth-concurrent-override [enable|disable]
    set auth-concurrent-value {integer}
    set http-digest-realm {string}
    set sso-attribute-value {string}
  
```

```

set logic-type [or|and]
set negate [enable|disable]
set member <name1>, <name2>, ...
config match
    Description: Group matches.
    edit <id>
        set server-name {string}
        set group-name {string}
    next
end
set user-id [email|auto-generate|...]
set password [auto-generate|specify|...]
set user-name [disable|enable]
set sponsor [optional|mandatory|...]
set company [optional|mandatory|...]
set email [disable|enable]
set mobile-phone [disable|enable]
set sms-server [fortiguard|custom]
set sms-custom-server {string}
set expire-type [immediately|first-successful-login]
set expire {integer}
set max-accounts {integer}
set multiple-guest-add [disable|enable]
config guest
    Description: Guest User.
    edit <id>
        set user-id {string}
        set name {string}
        set password {password}
        set mobile-phone {string}
        set sponsor {string}
        set company {string}
        set email {string}
        set expiration {user}
        set comment {var-string}
    next
end
next
end

```

config user group

Parameter	Description	Type	Size	Default
name	Group name.	string	Maximum length: 35	

Parameter	Description	Type	Size	Default										
id	Group ID.	integer	Minimum value: 0 Maximum value: 4294967295	0										
group-type	Set the group to be for firewall authentication, FSSO, RSSO, or guest users.	option	-	firewall										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>firewall</td><td>Firewall.</td></tr><tr><td>fsso-service</td><td>Fortinet Single Sign-On Service.</td></tr><tr><td>rsso</td><td>RADIUS based Single Sign-On Service.</td></tr><tr><td>guest</td><td>Guest.</td></tr></table>				Option	Description	firewall	Firewall.	fsso-service	Fortinet Single Sign-On Service.	rsso	RADIUS based Single Sign-On Service.	guest	Guest.
Option	Description													
firewall	Firewall.													
fsso-service	Fortinet Single Sign-On Service.													
rsso	RADIUS based Single Sign-On Service.													
guest	Guest.													
authtimeout	Authentication timeout in minutes for this user group. 0 to use the global user setting auth-timeout.	integer	Minimum value: 0 Maximum value: 43200	0										
auth-concurrent-override	Enable/disable overriding the global number of concurrent authentication sessions for this user group.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable auth-concurrent-override.</td></tr><tr><td>disable</td><td>Disable auth-concurrent-override.</td></tr></table>				Option	Description	enable	Enable auth-concurrent-override.	disable	Disable auth-concurrent-override.				
Option	Description													
enable	Enable auth-concurrent-override.													
disable	Disable auth-concurrent-override.													
auth-concurrent-value	Maximum number of concurrent authenticated connections per user (0 - 100).	integer	Minimum value: 0 Maximum value: 100	0										
http-digest-realm	Realm attribute for MD5-digest authentication.	string	Maximum length: 35											
sso-attribute-value	Name of the RADIUS user group that this local user group represents.	string	Maximum length: 511											
logic-type	Set the logic between members or matching entries.	option	-	or										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>or</td><td>Logic OR between members or match entries.</td></tr></table>				Option	Description	or	Logic OR between members or match entries.						
Option	Description													
or	Logic OR between members or match entries.													

Parameter	Description	Type	Size	Default								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>and</i></td><td>Logic AND between members or match entries.</td></tr></table>	Option	Description	<i>and</i>	Logic AND between members or match entries.							
Option	Description											
<i>and</i>	Logic AND between members or match entries.											
negate	When enabled, user group match against any user EXCEPT the specified user group.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable user group negate.</td></tr><tr><td><i>disable</i></td><td>Disable user group negate.</td></tr></table>	Option	Description	<i>enable</i>	Enable user group negate.	<i>disable</i>	Disable user group negate.					
Option	Description											
<i>enable</i>	Enable user group negate.											
<i>disable</i>	Disable user group negate.											
member <name>	Names of users, peers, LDAP severs, RADIUS servers or external idp servers to add to the user group. Group member name.	string	Maximum length: 511									
user-id	Guest user ID type.	option	-	email								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>email</i></td><td>Email address.</td></tr><tr><td><i>auto-generate</i></td><td>Automatically generate.</td></tr><tr><td><i>specify</i></td><td>Specify.</td></tr></table>	Option	Description	<i>email</i>	Email address.	<i>auto-generate</i>	Automatically generate.	<i>specify</i>	Specify.			
Option	Description											
<i>email</i>	Email address.											
<i>auto-generate</i>	Automatically generate.											
<i>specify</i>	Specify.											
password	Guest user password type.	option	-	auto-generate								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto-generate</i></td><td>Automatically generate.</td></tr><tr><td><i>specify</i></td><td>Specify.</td></tr><tr><td><i>disable</i></td><td>Disable.</td></tr></table>	Option	Description	<i>auto-generate</i>	Automatically generate.	<i>specify</i>	Specify.	<i>disable</i>	Disable.			
Option	Description											
<i>auto-generate</i>	Automatically generate.											
<i>specify</i>	Specify.											
<i>disable</i>	Disable.											
user-name	Enable/disable the guest user name entry.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr></table>	Option	Description	<i>disable</i>	Disable setting.	<i>enable</i>	Enable setting.					
Option	Description											
<i>disable</i>	Disable setting.											
<i>enable</i>	Enable setting.											
sponsor	Set the action for the sponsor guest user field.	option	-	optional								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>optional</i>	Optional.		
	<i>mandatory</i>	Mandatory.		
	<i>disabled</i>	Disabled.		
company	Set the action for the company guest user field.	option	-	optional
	Option	Description		
	<i>optional</i>	Optional.		
	<i>mandatory</i>	Mandatory.		
	<i>disabled</i>	Disabled.		
email	Enable/disable the guest user email address field.	option	-	enable
	Option	Description		
	<i>disable</i>	Disable setting.		
	<i>enable</i>	Enable setting.		
mobile-phone	Enable/disable the guest user mobile phone number field.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable setting.		
	<i>enable</i>	Enable setting.		
sms-server	Send SMS through FortiGuard or other external server.	option	-	fortiguard
	Option	Description		
	<i>fortiguard</i>	Send SMS by FortiGuard.		
	<i>custom</i>	Send SMS by custom server.		
sms-custom-server	SMS server.	string	Maximum length: 35	
expire-type	Determine when the expiration countdown begins.	option	-	immediately

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>immediately</i>	Immediately.		
	<i>first-successful-login</i>	First successful login.		
expire	Time in seconds before guest user accounts expire (1 - 31536000).	integer	Minimum value: 1 Maximum value: 31536000	14400
max-accounts	Maximum number of guest accounts that can be created for this group (0 means unlimited).	integer	Minimum value: 0 Maximum value: 1024	0
multiple-guest-add	Enable/disable addition of multiple guests.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable setting.		
	<i>enable</i>	Enable setting.		

config match

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
server-name	Name of remote auth server.	string	Maximum length: 35	
group-name	Name of matching user or group on remote authentication server.	string	Maximum length: 511	

config guest

Parameter	Description	Type	Size	Default
id	Guest ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
user-id	Guest ID.	string	Maximum length: 64	
name	Guest name.	string	Maximum length: 64	
password	Guest password.	password	Not Specified	
mobile-phone	Mobile phone.	string	Maximum length: 35	
sponsor	Set the action for the sponsor guest user field.	string	Maximum length: 35	
company	Set the action for the company guest user field.	string	Maximum length: 35	
email	Email.	string	Maximum length: 64	
expiration	Expire time.	user	Not Specified	
comment	Comment.	var-string	Maximum length: 255	

config user krb-keytab

Configure Kerberos keytab entries.

```
config user krb-keytab
  Description: Configure Kerberos keytab entries.
  edit <name>
    set pac-data [enable|disable]
    set principal {string}
    set ldap-server <name1>, <name2>, ...
    set keytab {string}
  next
end
```


config user krb-keytab

Parameter	Description	Type	Size	Default
name	Kerberos keytab entry name.	string	Maximum length: 35	
pac-data	Enable/disable parsing PAC data in the ticket.	option	-	enable
	Option	Description		
	enable	Enable parsing PAC data in the ticket.		
	disable	Disable parsing PAC data in the ticket.		
principal	Kerberos service principal. For example, HTTP/myfgt.example.com@example.com.	string	Maximum length: 511	
ldap-server <name>	LDAP server name(s). LDAP server name.	string	Maximum length: 79	
keytab	Base64 coded keytab file containing a pre-shared key.	string	Maximum length: 8191	

config user ldap

Configure LDAP server entries.

```
config user ldap
  Description: Configure LDAP server entries.
  edit <name>
    set server {string}
    set secondary-server {string}
    set tertiary-server {string}
    set server-identity-check [enable|disable]
    set source-ip {string}
    set source-port {integer}
    set cnid {string}
    set dn {string}
    set type [simple|anonymous|...]
    set two-factor [disable|fortitoken-cloud]
    set two-factor-authentication [fortitoken|email|...]
    set two-factor-notification [email|sms]
    set two-factor-filter {string}
    set username {string}
    set password {password}
    set group-member-check [user-attr|group-object|...]
    set group-search-base {string}
    set group-object-filter {string}
    set group-filter {string}
```

```

set secure [disable|starttls|...]
set ssl-max-proto-version [SSLv3|TLSv1|...]
set ssl-min-proto-version [default|SSLv3|...]
set ca-cert {string}
set port {integer}
set password-expiry-warning [enable|disable]
set password-renewal [enable|disable]
set member-attr {string}
set account-key-processing [same|strip]
set account-key-upn-san [othername|rfc822name|...]
set account-key-filter {string}
set search-type {option1}, {option2}, ...
set max-connections {integer}
set client-cert-auth [enable|disable]
set client-cert {string}
set obtain-user-info [enable|disable]
set user-info-exchange-server {string}
set interface-select-method [auto|specify]
set interface {string}
set antiphish [enable|disable]
set password-attr {string}
next
end

```

config user ldap

Parameter	Description	Type	Size	Default
name	LDAP server entry name.	string	Maximum length: 35	
server	LDAP server CN domain name or IP.	string	Maximum length: 63	
secondary-server	Secondary LDAP server CN domain name or IP.	string	Maximum length: 63	
tertiary-server	Tertiary LDAP server CN domain name or IP.	string	Maximum length: 63	

Parameter	Description	Type	Size	Default						
server-identity-check	Enable/disable LDAP server identity check (verify server domain name/IP address against the server certificate).	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable server identity check.</td></tr><tr><td><i>disable</i></td><td>Disable server identity check.</td></tr></table>	Option	Description	<i>enable</i>	Enable server identity check.	<i>disable</i>	Disable server identity check.			
Option	Description									
<i>enable</i>	Enable server identity check.									
<i>disable</i>	Disable server identity check.									
source-ip	FortiProxy IP address to be used for communication with the LDAP server.	string	Maximum length: 63							
source-port	Source port to be used for communication with the LDAP server.	integer	Minimum value: 0 Maximum value: 65535	0						
cnid	Common name identifier for the LDAP server. The common name identifier for most LDAP servers is "cn".	string	Maximum length: 20	cn						
dn	Distinguished name used to look up entries on the LDAP server.	string	Maximum length: 511							

Parameter	Description	Type	Size	Default								
type	Authentication type for LDAP searches.	option	-	simple								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>simple</i></td><td>Simple password authentication without search.</td></tr><tr><td><i>anonymous</i></td><td>Bind using anonymous user search.</td></tr><tr><td><i>regular</i></td><td>Bind using username/password and then search.</td></tr></table>	Option	Description	<i>simple</i>	Simple password authentication without search.	<i>anonymous</i>	Bind using anonymous user search.	<i>regular</i>	Bind using username/password and then search.			
Option	Description											
<i>simple</i>	Simple password authentication without search.											
<i>anonymous</i>	Bind using anonymous user search.											
<i>regular</i>	Bind using username/password and then search.											
two-factor	Enable/disable two-factor authentication.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>disable two-factor authentication.</td></tr><tr><td><i>fortitoken-cloud</i></td><td>FortiToken Cloud Service.</td></tr></table>	Option	Description	<i>disable</i>	disable two-factor authentication.	<i>fortitoken-cloud</i>	FortiToken Cloud Service.					
Option	Description											
<i>disable</i>	disable two-factor authentication.											
<i>fortitoken-cloud</i>	FortiToken Cloud Service.											
two-factor-authentication	Authentication method by FortiToken Cloud.	option	-									
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>fortitoken</i></td><td>FortiToken authentication.</td></tr><tr><td><i>email</i></td><td>Email one time password.</td></tr><tr><td><i>sms</i></td><td>SMS one time password.</td></tr></table>	Option	Description	<i>fortitoken</i>	FortiToken authentication.	<i>email</i>	Email one time password.	<i>sms</i>	SMS one time password.			
Option	Description											
<i>fortitoken</i>	FortiToken authentication.											
<i>email</i>	Email one time password.											
<i>sms</i>	SMS one time password.											
two-factor-notification	Notification method for user activation by FortiToken Cloud.	option	-									
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>email</i></td><td>Email notification for activation code.</td></tr><tr><td><i>sms</i></td><td>SMS notification for activation code.</td></tr></table>	Option	Description	<i>email</i>	Email notification for activation code.	<i>sms</i>	SMS notification for activation code.					
Option	Description											
<i>email</i>	Email notification for activation code.											
<i>sms</i>	SMS notification for activation code.											

Parameter	Description	Type	Size	Default								
two-factor-filter	Filter used to synchronize users to FortiToken Cloud.	string	Maximum length: 2047									
username	Username (full DN) for initial binding.	string	Maximum length: 511									
password	Password for initial binding.	password	Not Specified									
group-member-check	Group member checking methods.	option	-	user-attr								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>user-attr</i></td><td>User attribute checking.</td></tr><tr><td><i>group-object</i></td><td>Group object checking.</td></tr><tr><td><i>posix-group-object</i></td><td>POSIX group object checking.</td></tr></table>				Option	Description	<i>user-attr</i>	User attribute checking.	<i>group-object</i>	Group object checking.	<i>posix-group-object</i>	POSIX group object checking.
Option	Description											
<i>user-attr</i>	User attribute checking.											
<i>group-object</i>	Group object checking.											
<i>posix-group-object</i>	POSIX group object checking.											
group-search-base	Search base used for group searching.	string	Maximum length: 511									
group-object-filter	Filter used for group searching.	string	Maximum length: 2047	(&(objectcategory=group)(member=*))								
group-filter	Filter used for group matching.	string	Maximum length: 2047									
secure	Port to be used for authentication.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>No SSL.</td></tr><tr><td><i>starttls</i></td><td>Use StartTLS.</td></tr><tr><td><i>ldaps</i></td><td>Use LDAPS.</td></tr></table>				Option	Description	<i>disable</i>	No SSL.	<i>starttls</i>	Use StartTLS.	<i>ldaps</i>	Use LDAPS.
Option	Description											
<i>disable</i>	No SSL.											
<i>starttls</i>	Use StartTLS.											
<i>ldaps</i>	Use LDAPS.											

Parameter	Description	Type	Size	Default														
ssl-max- proto- version	Maximum supported protocol version for SSL/TLS connections.	option	-	TLSv1-3														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>SSLv3</td><td>SSLv3.</td></tr><tr><td>TLSv1</td><td>TLSv1.</td></tr><tr><td>TLSv1-1</td><td>TLSv1.1.</td></tr><tr><td>TLSv1-2</td><td>TLSv1.2.</td></tr><tr><td>TLSv1-3</td><td>TLSv1.3.</td></tr></table>	Option	Description	SSLv3	SSLv3.	TLSv1	TLSv1.	TLSv1-1	TLSv1.1.	TLSv1-2	TLSv1.2.	TLSv1-3	TLSv1.3.					
Option	Description																	
SSLv3	SSLv3.																	
TLSv1	TLSv1.																	
TLSv1-1	TLSv1.1.																	
TLSv1-2	TLSv1.2.																	
TLSv1-3	TLSv1.3.																	
ssl-min- proto- version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>default</td><td>Follow system global setting.</td></tr><tr><td>SSLv3</td><td>SSLv3.</td></tr><tr><td>TLSv1</td><td>TLSv1.</td></tr><tr><td>TLSv1-1</td><td>TLSv1.1.</td></tr><tr><td>TLSv1-2</td><td>TLSv1.2.</td></tr><tr><td>TLSv1-3</td><td>TLSv1.3.</td></tr></table>	Option	Description	default	Follow system global setting.	SSLv3	SSLv3.	TLSv1	TLSv1.	TLSv1-1	TLSv1.1.	TLSv1-2	TLSv1.2.	TLSv1-3	TLSv1.3.			
Option	Description																	
default	Follow system global setting.																	
SSLv3	SSLv3.																	
TLSv1	TLSv1.																	
TLSv1-1	TLSv1.1.																	
TLSv1-2	TLSv1.2.																	
TLSv1-3	TLSv1.3.																	
ca-cert	CA certificate name.	string	Maximum length: 79															

Parameter	Description	Type	Size	Default						
port	Port to be used for communication with the LDAP server (default = 389).	integer	Minimum value: 1 Maximum value: 65535	389						
password-expiry-warning	Enable/disable password expiry warnings.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable password expiry warnings.</td></tr><tr><td><i>disable</i></td><td>Disable password expiry warnings.</td></tr></table>	Option	Description	<i>enable</i>	Enable password expiry warnings.	<i>disable</i>	Disable password expiry warnings.			
Option	Description									
<i>enable</i>	Enable password expiry warnings.									
<i>disable</i>	Disable password expiry warnings.									
password-renewal	Enable/disable online password renewal.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable online password renewal.</td></tr><tr><td><i>disable</i></td><td>Disable online password renewal.</td></tr></table>	Option	Description	<i>enable</i>	Enable online password renewal.	<i>disable</i>	Disable online password renewal.			
Option	Description									
<i>enable</i>	Enable online password renewal.									
<i>disable</i>	Disable online password renewal.									
member-attr	Name of attribute from which to get group membership.	string	Maximum length: 63	memberOf						
account-key-processing	Account key processing operation, either keep or strip domain string of UPN in the token.	option	-	same						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>same</i></td><td>Same as UPN.</td></tr><tr><td><i>strip</i></td><td>Strip domain string from UPN.</td></tr></table>	Option	Description	<i>same</i>	Same as UPN.	<i>strip</i>	Strip domain string from UPN.			
Option	Description									
<i>same</i>	Same as UPN.									
<i>strip</i>	Strip domain string from UPN.									

Parameter	Description	Type	Size	Default
account-key-upn-san	Define SAN in certificate for user principle name matching.	option	-	othername
	Option	Description		
	<i>othername</i>	Other name in SAN.		
	<i>rfc822name</i>	RFC822 Email address in SAN.		
	<i>dnsname</i>	DNS name in SAN.		
account-key-filter	Account key filter, using the UPN as the search filter.	string	Maximum length: 2047	(&(userPrincipalName=%s)(!(UserAccountControl:1.2.840.113556.1.4.803:=2)))
search-type	Search type.	option	-	recursive
	Option	Description		
	<i>recursive</i>	Recursively retrieve the user-group chain information of a user in a particular Microsoft AD domain.		
max-connections	Maximum LDAP server connections (16-5000, default 64).	integer	Minimum value: 16 Maximum value: 5000	64
client-cert-auth	Enable/disable using client certificate for TLS authentication.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable using client certificate for TLS authentication.		
	<i>disable</i>	Disable using client certificate for TLS authentication.		
client-cert	Client certificate name.	string	Maximum length: 79	

Parameter	Description	Type	Size	Default						
obtain-user-info	Enable/disable obtaining of user information.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable obtaining of user information.</td></tr><tr><td>disable</td><td>Disable obtaining of user information.</td></tr></table>	Option	Description	enable	Enable obtaining of user information.	disable	Disable obtaining of user information.			
Option	Description									
enable	Enable obtaining of user information.									
disable	Disable obtaining of user information.									
user-info-exchange-server	MS Exchange server from which to fetch user information.	string	Maximum length: 35							
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>auto</td><td>Set outgoing interface automatically.</td></tr><tr><td>specify</td><td>Set outgoing interface manually.</td></tr></table>	Option	Description	auto	Set outgoing interface automatically.	specify	Set outgoing interface manually.			
Option	Description									
auto	Set outgoing interface automatically.									
specify	Set outgoing interface manually.									
interface	Specify outgoing interface to reach server.	string	Maximum length: 15							
antiphish	Enable/disable AntiPhishing credential backend.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable AntiPhishing credential backend.</td></tr><tr><td>disable</td><td>Disable AntiPhishing credential backend.</td></tr></table>	Option	Description	enable	Enable AntiPhishing credential backend.	disable	Disable AntiPhishing credential backend.			
Option	Description									
enable	Enable AntiPhishing credential backend.									
disable	Disable AntiPhishing credential backend.									
password-attr	Name of attribute to get password hash.	string	Maximum length: 35	userPassword						

config user local

Configure local users.

```
config user local
  Description: Configure local users.
  edit <name>
    set id {integer}
    set status [enable|disable]
    set type [password|radius|...]
    set passwd {password}
    set ldap-server {string}
    set radius-server {string}
    set tacacs+-server {string}
    set two-factor [disable|fortitoken|...]
    set two-factor-authentication [fortitoken|email|...]
    set two-factor-notification [email|sms]
    set fortitoken {string}
    set email-to {string}
    set sms-server [fortiguard|custom]
    set sms-custom-server {string}
    set sms-phone {string}
    set passwd-policy {string}
    set passwd-time {user}
    set authtimeout {integer}
    set workstation {string}
    set auth-concurrent-override [enable|disable]
    set auth-concurrent-value {integer}
    set ppk-secret {password-3}
    set ppk-identity {string}
    set username-sensitivity [disable|enable]
  next
end
```

config user local

Parameter	Description	Type	Size	Default
name	Local user name.	string	Maximum length: 64	
id	User ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

Parameter	Description	Type	Size	Default
status	Enable/disable allowing the local user to authenticate with the FortiProxy unit.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable user.		
	<i>disable</i>	Disable user.		
type	Authentication method.	option	-	password
	Option	Description		
	<i>password</i>	Password authentication.		
	<i>radius</i>	RADIUS server authentication.		
	<i>tacacs+</i>	TACACS+ server authentication.		
	<i>ldap</i>	LDAP server authentication.		
passwd	User's password.	password	Not Specified	
ldap-server	Name of LDAP server with which the user must authenticate.	string	Maximum length: 35	
radius-server	Name of RADIUS server with which the user must authenticate.	string	Maximum length: 35	
tacacs+-server	Name of TACACS+ server with which the user must authenticate.	string	Maximum length: 35	
two-factor	Enable/disable two-factor authentication.	option	-	disable
	Option	Description		
	<i>disable</i>	disable		
	<i>fortitoken</i>	FortiToken		
	<i>fortitoken-cloud</i>	FortiToken Cloud Service.		
	<i>email</i>	Email authentication code.		
	<i>sms</i>	SMS authentication code.		
two-factor-authentication	Authentication method by FortiToken Cloud.	option	-	

Parameter	Description	Type	Size	Default								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>fortitoken</i></td><td>FortiToken authentication.</td></tr><tr><td><i>email</i></td><td>Email one time password.</td></tr><tr><td><i>sms</i></td><td>SMS one time password.</td></tr></table>	Option	Description	<i>fortitoken</i>	FortiToken authentication.	<i>email</i>	Email one time password.	<i>sms</i>	SMS one time password.			
	Option	Description										
	<i>fortitoken</i>	FortiToken authentication.										
	<i>email</i>	Email one time password.										
<i>sms</i>	SMS one time password.											
two-factor-notification	Notification method for user activation by FortiToken Cloud.	option	-									
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>email</i></td><td>Email notification for activation code.</td></tr><tr><td><i>sms</i></td><td>SMS notification for activation code.</td></tr></table>	Option	Description	<i>email</i>	Email notification for activation code.	<i>sms</i>	SMS notification for activation code.					
	Option	Description										
	<i>email</i>	Email notification for activation code.										
<i>sms</i>	SMS notification for activation code.											
fortitoken	Two-factor recipient's FortiToken serial number.	string	Maximum length: 16									
email-to	Two-factor recipient's email address.	string	Maximum length: 63									
sms-server	Send SMS through FortiGuard or other external server.	option	-	fortiguard								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>fortiguard</i></td><td>Send SMS by FortiGuard.</td></tr><tr><td><i>custom</i></td><td>Send SMS by custom server.</td></tr></table>	Option	Description	<i>fortiguard</i>	Send SMS by FortiGuard.	<i>custom</i>	Send SMS by custom server.					
	Option	Description										
	<i>fortiguard</i>	Send SMS by FortiGuard.										
<i>custom</i>	Send SMS by custom server.											
sms-custom-server	Two-factor recipient's SMS server.	string	Maximum length: 35									
sms-phone	Two-factor recipient's mobile phone number.	string	Maximum length: 15									
passwd-policy	Password policy to apply to this user, as defined in config user password-policy.	string	Maximum length: 35									
passwd-time	Time of the last password update.	user	Not Specified									
authtimeout	Time in minutes before the authentication timeout for a user is reached.	integer	Minimum value: 0 Maximum value: 1440	0								
workstation	Name of the remote user workstation, if you want to limit the user to authenticate only from a particular workstation.	string	Maximum length: 35									

Parameter	Description	Type	Size	Default
auth-concurrent-override	Enable/disable overriding the policy-auth-concurrent under config system global.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable auth-concurrent-override.		
	<i>disable</i>	Disable auth-concurrent-override.		
auth-concurrent-value	Maximum number of concurrent logins permitted from the same user.	integer	Minimum value: 0 Maximum value: 100	0
ppk-secret	IKEv2 Postquantum Preshared Key (ASCII string or hexadecimal encoded with a leading 0x).	password-3	Not Specified	
ppk-identity	IKEv2 Postquantum Preshared Key Identity.	string	Maximum length: 35	
username-sensitivity	Enable/disable case and accent sensitivity when performing username matching (accents are stripped and case is ignored when disabled).	option	-	enable
	Option	Description		
	<i>disable</i>	Ignore case and accents. Username at prompt not required to match case or accents.		
	<i>enable</i>	Do not ignore case and accents. Username at prompt must be an exact match.		

config user password-policy

Configure user password policy.

```

config user password-policy
  Description: Configure user password policy.
  edit <name>
    set expire-days {integer}
    set warn-days {integer}
    set expired-password-renewal [enable|disable]
  next
end

```

config user password-policy

Parameter	Description	Type	Size	Default
name	Password policy name.	string	Maximum length: 35	
expire-days	Time in days before the user's password expires.	integer	Minimum value: 0 Maximum value: 999	180
warn-days	Time in days before a password expiration warning message is displayed to the user upon login.	integer	Minimum value: 0 Maximum value: 30	15
expired-password-renewal	Enable/disable renewal of a password that already is expired.	option	-	disable
		Option	Description	
		<i>enable</i>	Enable renewal of a password that already is expired.	
		<i>disable</i>	Disable renewal of a password that already is expired.	

config user peer

Configure peer users.

```
config user peer
  Description: Configure peer users.
  edit <name>
    set mandatory-ca-verify [enable|disable]
    set ca {string}
    set subject {string}
    set cn {string}
    set cn-type [string|email|...]
    set ldap-server {string}
    set ldap-username {string}
    set ldap-password {password}
    set ldap-mode [password|principal-name]
    set ocsf-override-server {string}
    set two-factor [enable|disable]
    set passwd {password}
  next
end
```

config user peer

Parameter	Description	Type	Size	Default												
name	Peer name.	string	Maximum length: 35													
mandatory-ca-verify	Determine what happens to the peer if the CA certificate is not installed. Disable to automatically consider the peer certificate as valid.	option	-	enable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>				Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.						
Option	Description															
<i>enable</i>	Enable setting.															
<i>disable</i>	Disable setting.															
ca	Name of the CA certificate.	string	Maximum length: 127													
subject	Peer certificate name constraints.	string	Maximum length: 255													
cn	Peer certificate common name.	string	Maximum length: 255													
cn-type	Peer certificate common name type.	option	-	string												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>string</i></td><td>Normal string.</td></tr><tr><td><i>email</i></td><td>Email address.</td></tr><tr><td><i>FQDN</i></td><td>Fully Qualified Domain Name.</td></tr><tr><td><i>ipv4</i></td><td>IPv4 address.</td></tr><tr><td><i>ipv6</i></td><td>IPv6 address.</td></tr></table>				Option	Description	<i>string</i>	Normal string.	<i>email</i>	Email address.	<i>FQDN</i>	Fully Qualified Domain Name.	<i>ipv4</i>	IPv4 address.	<i>ipv6</i>	IPv6 address.
Option	Description															
<i>string</i>	Normal string.															
<i>email</i>	Email address.															
<i>FQDN</i>	Fully Qualified Domain Name.															
<i>ipv4</i>	IPv4 address.															
<i>ipv6</i>	IPv6 address.															
ldap-server	Name of an LDAP server defined under the user ldap command. Performs client access rights check.	string	Maximum length: 35													
ldap-username	Username for LDAP server bind.	string	Maximum length: 35													
ldap-password	Password for LDAP server bind.	password	Not Specified													
ldap-mode	Mode for LDAP peer authentication.	option	-	password												

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>password</i>	Username/password.		
	<i>principal-name</i>	Principal name.		
ocsp-override-server	Online Certificate Status Protocol (OCSP) server for certificate retrieval.	string	Maximum length: 35	
two-factor	Enable/disable two-factor authentication, applying certificate and password-based authentication.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable 2-factor authentication.		
	<i>disable</i>	Disable 2-factor authentication.		
passwd	Peer's password used for two-factor authentication.	password	Not Specified	

config user peergrp

Configure peer groups.

```
config user peergrp
  Description: Configure peer groups.
  edit <name>
    set member <name1>, <name2>, ...
  next
end
```

config user peergrp

Parameter	Description	Type	Size	Default
name	Peer group name.	string	Maximum length: 35	
member <name>	Peer group members. Peer group member name.	string	Maximum length: 35	

config user pop3

POP3 server entry configuration.

```
config user pop3
  Description: POP3 server entry configuration.
  edit <name>
    set server {string}
    set port {integer}
    set secure [none|starttls|...]
    set ssl-min-proto-version [default|SSLv3|...]
  next
end
```

config user pop3

Parameter	Description	Type	Size	Default
name	POP3 server entry name.	string	Maximum length: 35	
server	Server domain name or IP address.	string	Maximum length: 63	
port	POP3 service port number.	integer	Minimum value: 0 Maximum value: 65535	0
secure	SSL connection.	option	-	starttls
	Option Description			
	<i>none</i>	None.		
	<i>starttls</i>	Use StartTLS.		
	<i>pop3s</i>	Use POP3 over SSL.		
ssl-min-proto-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default
	Option Description			
	<i>default</i>	Follow system global setting.		
	<i>SSLv3</i>	SSLv3.		
	<i>TLSv1</i>	TLSv1.		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>TLSv1-1</i>	TLSv1.1.		
	<i>TLSv1-2</i>	TLSv1.2.		

config user radius

Configure RADIUS server entries.

```

config user radius
    Description: Configure RADIUS server entries.
    edit <name>
        set server {string}
        set secret {password}
        set secondary-server {string}
        set secondary-secret {password}
        set tertiary-server {string}
        set tertiary-secret {password}
        set timeout {integer}
        set all-usergroup [disable|enable]
        set use-management-vdom [enable|disable]
        set nas-ip {ipv4-address}
        set nas-id-type [legacy|custom|...]
        set nas-id {string}
        set acct-interim-interval {integer}
        set radius-coa [enable|disable]
        set radius-port {integer}
        set h3c-compatibility [enable|disable]
        set auth-type [auto|ms_chap_v2|...]
        set source-ip {string}
        set username-case-sensitive [enable|disable]
        set group-override-attr-type [filter-Id|class]
        set class <name1>, <name2>, ...
        set password-renewal [enable|disable]
        set require-message-authenticator [enable|disable]
        set password-encoding [auto|ISO-8859-1]
        set mac-username-delimiter [hyphen|single-hyphen|...]
        set mac-password-delimiter [hyphen|single-hyphen|...]
        set mac-case [uppercase|lowercase]
        set acct-all-servers [enable|disable]
        set switch-controller-acct-fast-framedip-detect {integer}
        set interface-select-method [auto|specify]
        set interface {string}
        set switch-controller-service-type {option1}, {option2}, ...
        set rso [enable|disable]
        set rso-radius-server-port {integer}
        set rso-radius-response [enable|disable]

```

```

set rso-validate-request-secret [enable|disable]
set rso-secret {password}
set rso-endpoint-attribute [User-Name|NAS-IP-Address|...]
set rso-endpoint-block-attribute [User-Name|NAS-IP-Address|...]
set sso-attribute [User-Name|NAS-IP-Address|...]
set sso-attribute-key {string}
set sso-attribute-value-override [enable|disable]
set rso-context-timeout {integer}
set rso-log-period {integer}
set rso-log-flags {option1}, {option2}, ...
set rso-flush-ip-session [enable|disable]
set rso-ep-one-ip-only [enable|disable]
set delimiter [plus|comma]
config accounting-server
    Description: Additional accounting servers.
    edit <id>
        set status [enable|disable]
        set server {string}
        set secret {password}
        set port {integer}
        set source-ip {string}
        set interface-select-method [auto|specify]
        set interface {string}
    next
end
next
end

```

config user radius

Parameter	Description	Type	Size	Default
name	RADIUS server entry name.	string	Maximum length: 35	
server	Primary RADIUS server CN domain name or IP address.	string	Maximum length: 63	
secret	Pre-shared secret key used to access the primary RADIUS server.	password	Not Specified	
secondary-server	Secondary RADIUS CN domain name or IP address.	string	Maximum length: 63	
secondary-secret	Secret key to access the secondary server.	password	Not Specified	
tertiary-server	Tertiary RADIUS CN domain name or IP address.	string	Maximum length: 63	

Parameter	Description	Type	Size	Default								
tertiary-secret	Secret key to access the tertiary server.	password	Not Specified									
timeout	Time in seconds between re-sending authentication requests.	integer	Minimum value: 1 Maximum value: 300	5								
all-usergroup	Enable/disable automatically including this RADIUS server in all user groups.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not automatically include this server in a user group.</td></tr><tr><td><i>enable</i></td><td>Include this RADIUS server in every user group.</td></tr></table>				Option	Description	<i>disable</i>	Do not automatically include this server in a user group.	<i>enable</i>	Include this RADIUS server in every user group.		
Option	Description											
<i>disable</i>	Do not automatically include this server in a user group.											
<i>enable</i>	Include this RADIUS server in every user group.											
use-management-vdom	Enable/disable using management VDOM to send requests.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Send requests using the management VDOM.</td></tr><tr><td><i>disable</i></td><td>Send requests using the current VDOM.</td></tr></table>				Option	Description	<i>enable</i>	Send requests using the management VDOM.	<i>disable</i>	Send requests using the current VDOM.		
Option	Description											
<i>enable</i>	Send requests using the management VDOM.											
<i>disable</i>	Send requests using the current VDOM.											
nas-ip	IP address used to communicate with the RADIUS server and used as NAS-IP-Address and Called-Station-ID attributes.	ipv4-address	Not Specified	0.0.0.0								
nas-id-type	NAS identifier type configuration (default = legacy).	option	-	legacy								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>legacy</i></td><td>NAS-ID value is the value previously used by each daemon.</td></tr><tr><td><i>custom</i></td><td>NAS-ID value is customized.</td></tr><tr><td><i>hostname</i></td><td>NAS-ID value is hostname or HA group name if applicable.</td></tr></table>				Option	Description	<i>legacy</i>	NAS-ID value is the value previously used by each daemon.	<i>custom</i>	NAS-ID value is customized.	<i>hostname</i>	NAS-ID value is hostname or HA group name if applicable.
Option	Description											
<i>legacy</i>	NAS-ID value is the value previously used by each daemon.											
<i>custom</i>	NAS-ID value is customized.											
<i>hostname</i>	NAS-ID value is hostname or HA group name if applicable.											
nas-id	Custom NAS identifier.	string	Maximum length: 255									
acct-interim-interval	Time in seconds between each accounting interim update message.	integer	Minimum value: 60 Maximum value: 86400	0								

Parameter	Description	Type	Size	Default												
radius-coa	Enable to allow a mechanism to change the attributes of an authentication, authorization, and accounting session after it is authenticated.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable RADIUS CoA.</td></tr><tr><td><i>disable</i></td><td>Disable RADIUS CoA.</td></tr></table>	Option	Description	<i>enable</i>	Enable RADIUS CoA.	<i>disable</i>	Disable RADIUS CoA.									
Option	Description															
<i>enable</i>	Enable RADIUS CoA.															
<i>disable</i>	Disable RADIUS CoA.															
radius-port	RADIUS service port number.	integer	Minimum value: 0 Maximum value: 65535	0												
h3c-compatibility	Enable/disable compatibility with the H3C, a mechanism that performs security checking for authentication.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable H3C compatibility.</td></tr><tr><td><i>disable</i></td><td>Disable H3C compatibility.</td></tr></table>	Option	Description	<i>enable</i>	Enable H3C compatibility.	<i>disable</i>	Disable H3C compatibility.									
Option	Description															
<i>enable</i>	Enable H3C compatibility.															
<i>disable</i>	Disable H3C compatibility.															
auth-type	Authentication methods/protocols permitted for this RADIUS server.	option	-	auto												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Use PAP, MSCHAP_v2, and CHAP (in that order).</td></tr><tr><td><i>ms_chap_v2</i></td><td>Microsoft Challenge Handshake Authentication Protocol version 2.</td></tr><tr><td><i>ms_chap</i></td><td>Microsoft Challenge Handshake Authentication Protocol.</td></tr><tr><td><i>chap</i></td><td>Challenge Handshake Authentication Protocol.</td></tr><tr><td><i>pap</i></td><td>Password Authentication Protocol.</td></tr></table>	Option	Description	<i>auto</i>	Use PAP, MSCHAP_v2, and CHAP (in that order).	<i>ms_chap_v2</i>	Microsoft Challenge Handshake Authentication Protocol version 2.	<i>ms_chap</i>	Microsoft Challenge Handshake Authentication Protocol.	<i>chap</i>	Challenge Handshake Authentication Protocol.	<i>pap</i>	Password Authentication Protocol.			
Option	Description															
<i>auto</i>	Use PAP, MSCHAP_v2, and CHAP (in that order).															
<i>ms_chap_v2</i>	Microsoft Challenge Handshake Authentication Protocol version 2.															
<i>ms_chap</i>	Microsoft Challenge Handshake Authentication Protocol.															
<i>chap</i>	Challenge Handshake Authentication Protocol.															
<i>pap</i>	Password Authentication Protocol.															
source-ip	Source IP address for communications to the RADIUS server.	string	Maximum length: 63													
username-case-sensitive	Enable/disable case sensitive user names.	option	-	disable												

Parameter	Description	Type	Size	Default
	Option Description			
	<i>enable</i>	Enable username case-sensitive.		
	<i>disable</i>	Disable username case-sensitive.		
group-override-attr-type	RADIUS attribute type to override user group information.	option	-	
	Option Description			
	<i>filter-Id</i>	Filter-Id		
	<i>class</i>	Class		
class <name>	Class attribute name(s). Class name.	string	Maximum length: 79	
password-renewal	Enable/disable password renewal.	option	-	enable
	Option Description			
	<i>enable</i>	Enable password renewal.		
	<i>disable</i>	Disable password renewal.		
require-message-authenticator	Require message authenticator in authentication response.	option	-	enable
	Option Description			
	<i>enable</i>	Make the validation of message authenticator mandatory in authentication response.		
	<i>disable</i>	Make the validation of message authenticator optional in authentication response.		
password-encoding	Password encoding.	option	-	auto
	Option Description			
	<i>auto</i>	Use original password encoding.		
	<i>ISO-8859-1</i>	Use ISO-8859-1 password encoding.		
mac-username-delimiter	MAC authentication username delimiter (default = hyphen).	option	-	hyphen

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>hyphen</i>	Use hyphen as delimiter for MAC authentication username.		
	<i>single-hyphen</i>	Use single hyphen as delimiter for MAC authentication username.		
	<i>colon</i>	Use colon as delimiter for MAC authentication username.		
	<i>none</i>	No delimiter for MAC authentication username.		
mac-password-delimiter	MAC authentication password delimiter (default = hyphen).	option	-	hyphen
	Option	Description		
	<i>hyphen</i>	Use hyphen as delimiter for MAC authentication password.		
	<i>single-hyphen</i>	Use single hyphen as delimiter for MAC authentication password.		
	<i>colon</i>	Use colon as delimiter for MAC authentication password.		
	<i>none</i>	No delimiter for MAC authentication password.		
mac-case	MAC authentication case (default = lowercase).	option	-	lowercase
	Option	Description		
	<i>uppercase</i>	Use uppercase MAC.		
	<i>lowercase</i>	Use lowercase MAC.		
acct-all-servers	Enable/disable sending of accounting messages to all configured servers (default = disable).	option	-	disable
	Option	Description		
	<i>enable</i>	Send accounting messages to all configured servers.		
	<i>disable</i>	Send accounting message only to servers that are confirmed to be reachable.		
switch-controller-acct-fast-framedip-detect	Switch controller accounting message Framed-IP detection from DHCP snooping (seconds, default=2).	integer	Minimum value: 2 Maximum value: 600	2
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto

Parameter	Description	Type	Size	Default																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Set outgoing interface automatically.</td></tr><tr><td><i>specify</i></td><td>Set outgoing interface manually.</td></tr></table>				Option	Description	<i>auto</i>	Set outgoing interface automatically.	<i>specify</i>	Set outgoing interface manually.																		
	Option	Description																										
	<i>auto</i>	Set outgoing interface automatically.																										
<i>specify</i>	Set outgoing interface manually.																											
interface	Specify outgoing interface to reach server.	string	Maximum length: 15																									
switch-controller-service-type	RADIUS service type.	option	-																									
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>login</i></td><td>User should be connected to a host.</td></tr><tr><td><i>framed</i></td><td>User use Framed Protocol.</td></tr><tr><td><i>callback-login</i></td><td>User disconnected and called back.</td></tr><tr><td><i>callback-framed</i></td><td>User disconnected and called back, then a Framed Protocol.</td></tr><tr><td><i>outbound</i></td><td>User granted access to outgoing devices.</td></tr><tr><td><i>administrative</i></td><td>User granted access to the administrative unsigned interface.</td></tr><tr><td><i>nas-prompt</i></td><td>User provided a command prompt on the NAS.</td></tr><tr><td><i>authenticate-only</i></td><td>Authentication requested, and no auth info needs to be returned.</td></tr><tr><td><i>callback-nas-prompt</i></td><td>User disconnected and called back, then provided a command prompt.</td></tr><tr><td><i>call-check</i></td><td>Used by the NAS in an Access-Request packet, Access-Accept to answer the call.</td></tr><tr><td><i>callback-administrative</i></td><td>User disconnected and called back, granted access to the admin unsigned interface.</td></tr></table>				Option	Description	<i>login</i>	User should be connected to a host.	<i>framed</i>	User use Framed Protocol.	<i>callback-login</i>	User disconnected and called back.	<i>callback-framed</i>	User disconnected and called back, then a Framed Protocol.	<i>outbound</i>	User granted access to outgoing devices.	<i>administrative</i>	User granted access to the administrative unsigned interface.	<i>nas-prompt</i>	User provided a command prompt on the NAS.	<i>authenticate-only</i>	Authentication requested, and no auth info needs to be returned.	<i>callback-nas-prompt</i>	User disconnected and called back, then provided a command prompt.	<i>call-check</i>	Used by the NAS in an Access-Request packet, Access-Accept to answer the call.	<i>callback-administrative</i>	User disconnected and called back, granted access to the admin unsigned interface.
	Option	Description																										
	<i>login</i>	User should be connected to a host.																										
	<i>framed</i>	User use Framed Protocol.																										
	<i>callback-login</i>	User disconnected and called back.																										
	<i>callback-framed</i>	User disconnected and called back, then a Framed Protocol.																										
	<i>outbound</i>	User granted access to outgoing devices.																										
	<i>administrative</i>	User granted access to the administrative unsigned interface.																										
	<i>nas-prompt</i>	User provided a command prompt on the NAS.																										
	<i>authenticate-only</i>	Authentication requested, and no auth info needs to be returned.																										
	<i>callback-nas-prompt</i>	User disconnected and called back, then provided a command prompt.																										
	<i>call-check</i>	Used by the NAS in an Access-Request packet, Access-Accept to answer the call.																										
<i>callback-administrative</i>	User disconnected and called back, granted access to the admin unsigned interface.																											
rsso	Enable/disable RADIUS based single sign on feature.	option	-	disable																								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable RADIUS based single sign on feature.</td></tr><tr><td><i>disable</i></td><td>Disable RADIUS based single sign on feature.</td></tr></table>				Option	Description	<i>enable</i>	Enable RADIUS based single sign on feature.	<i>disable</i>	Disable RADIUS based single sign on feature.																		
	Option	Description																										
	<i>enable</i>	Enable RADIUS based single sign on feature.																										
<i>disable</i>	Disable RADIUS based single sign on feature.																											
rsso-radius-server-port	UDP port to listen on for RADIUS Start and Stop records.	integer	Minimum value: 0 Maximum value: 65535	1813																								

Parameter	Description	Type	Size	Default																						
rsso-radius-response	Enable/disable sending RADIUS response packets after receiving Start and Stop records.	option	-	disable																						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable sending RADIUS response packets.</td></tr><tr><td><i>disable</i></td><td>Disable sending RADIUS response packets.</td></tr></table>	Option	Description	<i>enable</i>	Enable sending RADIUS response packets.	<i>disable</i>	Disable sending RADIUS response packets.																			
Option	Description																									
<i>enable</i>	Enable sending RADIUS response packets.																									
<i>disable</i>	Disable sending RADIUS response packets.																									
rsso-validate-request-secret	Enable/disable validating the RADIUS request shared secret in the Start or End record.	option	-	disable																						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable validating RADIUS request shared secret.</td></tr><tr><td><i>disable</i></td><td>Disable validating RADIUS request shared secret.</td></tr></table>	Option	Description	<i>enable</i>	Enable validating RADIUS request shared secret.	<i>disable</i>	Disable validating RADIUS request shared secret.																			
Option	Description																									
<i>enable</i>	Enable validating RADIUS request shared secret.																									
<i>disable</i>	Disable validating RADIUS request shared secret.																									
rsso-secret	RADIUS secret used by the RADIUS accounting server.	password	Not Specified																							
rsso-endpoint-attribute	RADIUS attributes used to extract the user end point identifier from the RADIUS Start record.	option	-	Calling-Station-Id																						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>User-Name</i></td><td>Use this attribute.</td></tr><tr><td><i>NAS-IP-Address</i></td><td>Use this attribute.</td></tr><tr><td><i>Framed-IP-Address</i></td><td>Use this attribute.</td></tr><tr><td><i>Framed-IP-Netmask</i></td><td>Use this attribute.</td></tr><tr><td><i>Filter-Id</i></td><td>Use this attribute.</td></tr><tr><td><i>Login-IP-Host</i></td><td>Use this attribute.</td></tr><tr><td><i>Reply-Message</i></td><td>Use this attribute.</td></tr><tr><td><i>Callback-Number</i></td><td>Use this attribute.</td></tr><tr><td><i>Callback-Id</i></td><td>Use this attribute.</td></tr><tr><td><i>Framed-Route</i></td><td>Use this attribute.</td></tr></table>	Option	Description	<i>User-Name</i>	Use this attribute.	<i>NAS-IP-Address</i>	Use this attribute.	<i>Framed-IP-Address</i>	Use this attribute.	<i>Framed-IP-Netmask</i>	Use this attribute.	<i>Filter-Id</i>	Use this attribute.	<i>Login-IP-Host</i>	Use this attribute.	<i>Reply-Message</i>	Use this attribute.	<i>Callback-Number</i>	Use this attribute.	<i>Callback-Id</i>	Use this attribute.	<i>Framed-Route</i>	Use this attribute.			
Option	Description																									
<i>User-Name</i>	Use this attribute.																									
<i>NAS-IP-Address</i>	Use this attribute.																									
<i>Framed-IP-Address</i>	Use this attribute.																									
<i>Framed-IP-Netmask</i>	Use this attribute.																									
<i>Filter-Id</i>	Use this attribute.																									
<i>Login-IP-Host</i>	Use this attribute.																									
<i>Reply-Message</i>	Use this attribute.																									
<i>Callback-Number</i>	Use this attribute.																									
<i>Callback-Id</i>	Use this attribute.																									
<i>Framed-Route</i>	Use this attribute.																									

Parameter	Description	Type	Size	Default																										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>Framed-IPX-Network</i></td><td>Use this attribute.</td></tr><tr><td><i>Class</i></td><td>Use this attribute.</td></tr><tr><td><i>Called-Station-Id</i></td><td>Use this attribute.</td></tr><tr><td><i>Calling-Station-Id</i></td><td>Use this attribute.</td></tr><tr><td><i>NAS-Identifier</i></td><td>Use this attribute.</td></tr><tr><td><i>Proxy-State</i></td><td>Use this attribute.</td></tr><tr><td><i>Login-LA T-Service</i></td><td>Use this attribute.</td></tr><tr><td><i>Login-LA T-Node</i></td><td>Use this attribute.</td></tr><tr><td><i>Login-LA T-Group</i></td><td>Use this attribute.</td></tr><tr><td><i>Framed-AppleTalk-Zone</i></td><td>Use this attribute.</td></tr><tr><td><i>Acct-Session-Id</i></td><td>Use this attribute.</td></tr><tr><td><i>Acct-Multi-Session-Id</i></td><td>Use this attribute.</td></tr></table>	Option	Description	<i>Framed-IPX-Network</i>	Use this attribute.	<i>Class</i>	Use this attribute.	<i>Called-Station-Id</i>	Use this attribute.	<i>Calling-Station-Id</i>	Use this attribute.	<i>NAS-Identifier</i>	Use this attribute.	<i>Proxy-State</i>	Use this attribute.	<i>Login-LA T-Service</i>	Use this attribute.	<i>Login-LA T-Node</i>	Use this attribute.	<i>Login-LA T-Group</i>	Use this attribute.	<i>Framed-AppleTalk-Zone</i>	Use this attribute.	<i>Acct-Session-Id</i>	Use this attribute.	<i>Acct-Multi-Session-Id</i>	Use this attribute.			
	Option	Description																												
	<i>Framed-IPX-Network</i>	Use this attribute.																												
	<i>Class</i>	Use this attribute.																												
	<i>Called-Station-Id</i>	Use this attribute.																												
	<i>Calling-Station-Id</i>	Use this attribute.																												
	<i>NAS-Identifier</i>	Use this attribute.																												
	<i>Proxy-State</i>	Use this attribute.																												
	<i>Login-LA T-Service</i>	Use this attribute.																												
	<i>Login-LA T-Node</i>	Use this attribute.																												
	<i>Login-LA T-Group</i>	Use this attribute.																												
	<i>Framed-AppleTalk-Zone</i>	Use this attribute.																												
	<i>Acct-Session-Id</i>	Use this attribute.																												
<i>Acct-Multi-Session-Id</i>	Use this attribute.																													
rsso-endpoint-block-attribute	RADIUS attributes used to block a user.	option	-																											
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>User-Name</i></td><td>Use this attribute.</td></tr><tr><td><i>NAS-IP-Address</i></td><td>Use this attribute.</td></tr><tr><td><i>Framed-IP-Address</i></td><td>Use this attribute.</td></tr><tr><td><i>Framed-IP-Netmask</i></td><td>Use this attribute.</td></tr><tr><td><i>Filter-Id</i></td><td>Use this attribute.</td></tr></table>	Option	Description	<i>User-Name</i>	Use this attribute.	<i>NAS-IP-Address</i>	Use this attribute.	<i>Framed-IP-Address</i>	Use this attribute.	<i>Framed-IP-Netmask</i>	Use this attribute.	<i>Filter-Id</i>	Use this attribute.																	
	Option	Description																												
	<i>User-Name</i>	Use this attribute.																												
	<i>NAS-IP-Address</i>	Use this attribute.																												
	<i>Framed-IP-Address</i>	Use this attribute.																												
	<i>Framed-IP-Netmask</i>	Use this attribute.																												
<i>Filter-Id</i>	Use this attribute.																													

Parameter	Description	Type	Size	Default																																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>Login-IP-Host</i></td><td>Use this attribute.</td></tr><tr><td><i>Reply-Message</i></td><td>Use this attribute.</td></tr><tr><td><i>Callback-Number</i></td><td>Use this attribute.</td></tr><tr><td><i>Callback-Id</i></td><td>Use this attribute.</td></tr><tr><td><i>Framed-Route</i></td><td>Use this attribute.</td></tr><tr><td><i>Framed-IPX-Network</i></td><td>Use this attribute.</td></tr><tr><td><i>Class</i></td><td>Use this attribute.</td></tr><tr><td><i>Called-Station-Id</i></td><td>Use this attribute.</td></tr><tr><td><i>Calling-Station-Id</i></td><td>Use this attribute.</td></tr><tr><td><i>NAS-Identifier</i></td><td>Use this attribute.</td></tr><tr><td><i>Proxy-State</i></td><td>Use this attribute.</td></tr><tr><td><i>Login-LAT-Service</i></td><td>Use this attribute.</td></tr><tr><td><i>Login-LAT-Node</i></td><td>Use this attribute.</td></tr><tr><td><i>Login-LAT-Group</i></td><td>Use this attribute.</td></tr><tr><td><i>Framed-AppleTalk-Zone</i></td><td>Use this attribute.</td></tr><tr><td><i>Acct-Session-Id</i></td><td>Use this attribute.</td></tr><tr><td><i>Acct-Multi-Session-Id</i></td><td>Use this attribute.</td></tr></table>	Option	Description	<i>Login-IP-Host</i>	Use this attribute.	<i>Reply-Message</i>	Use this attribute.	<i>Callback-Number</i>	Use this attribute.	<i>Callback-Id</i>	Use this attribute.	<i>Framed-Route</i>	Use this attribute.	<i>Framed-IPX-Network</i>	Use this attribute.	<i>Class</i>	Use this attribute.	<i>Called-Station-Id</i>	Use this attribute.	<i>Calling-Station-Id</i>	Use this attribute.	<i>NAS-Identifier</i>	Use this attribute.	<i>Proxy-State</i>	Use this attribute.	<i>Login-LAT-Service</i>	Use this attribute.	<i>Login-LAT-Node</i>	Use this attribute.	<i>Login-LAT-Group</i>	Use this attribute.	<i>Framed-AppleTalk-Zone</i>	Use this attribute.	<i>Acct-Session-Id</i>	Use this attribute.	<i>Acct-Multi-Session-Id</i>	Use this attribute.			
	Option	Description																																						
	<i>Login-IP-Host</i>	Use this attribute.																																						
	<i>Reply-Message</i>	Use this attribute.																																						
	<i>Callback-Number</i>	Use this attribute.																																						
	<i>Callback-Id</i>	Use this attribute.																																						
	<i>Framed-Route</i>	Use this attribute.																																						
	<i>Framed-IPX-Network</i>	Use this attribute.																																						
	<i>Class</i>	Use this attribute.																																						
	<i>Called-Station-Id</i>	Use this attribute.																																						
	<i>Calling-Station-Id</i>	Use this attribute.																																						
	<i>NAS-Identifier</i>	Use this attribute.																																						
	<i>Proxy-State</i>	Use this attribute.																																						
	<i>Login-LAT-Service</i>	Use this attribute.																																						
	<i>Login-LAT-Node</i>	Use this attribute.																																						
	<i>Login-LAT-Group</i>	Use this attribute.																																						
	<i>Framed-AppleTalk-Zone</i>	Use this attribute.																																						
	<i>Acct-Session-Id</i>	Use this attribute.																																						
<i>Acct-Multi-Session-Id</i>	Use this attribute.																																							
sso-attribute	RADIUS attribute that contains the profile group name to be extracted from the RADIUS Start record.	option	-	Class																																				

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>User-Name</i>	Use this attribute.		
	<i>NAS-IP-Address</i>	Use this attribute.		
	<i>Framed-IP-Address</i>	Use this attribute.		
	<i>Framed-IP-Netmask</i>	Use this attribute.		
	<i>Filter-Id</i>	Use this attribute.		
	<i>Login-IP-Host</i>	Use this attribute.		
	<i>Reply-Message</i>	Use this attribute.		
	<i>Callback-Number</i>	Use this attribute.		
	<i>Callback-Id</i>	Use this attribute.		
	<i>Framed-Route</i>	Use this attribute.		
	<i>Framed-IPX-Network</i>	Use this attribute.		
	<i>Class</i>	Use this attribute.		
	<i>Called-Station-Id</i>	Use this attribute.		
	<i>Calling-Station-Id</i>	Use this attribute.		
	<i>NAS-Identifier</i>	Use this attribute.		
	<i>Proxy-State</i>	Use this attribute.		
	<i>Login-LAT-Service</i>	Use this attribute.		
	<i>Login-LAT-Node</i>	Use this attribute.		
	<i>Login-LAT-Group</i>	Use this attribute.		
	<i>Framed-AppleTalk-Zone</i>	Use this attribute.		

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>Acct-Session-Id</i></td><td>Use this attribute.</td></tr><tr><td><i>Acct-Multi-Session-Id</i></td><td>Use this attribute.</td></tr></table>	Option	Description	<i>Acct-Session-Id</i>	Use this attribute.	<i>Acct-Multi-Session-Id</i>	Use this attribute.			
	Option	Description								
	<i>Acct-Session-Id</i>	Use this attribute.								
<i>Acct-Multi-Session-Id</i>	Use this attribute.									
sso-attribute-key	Key prefix for SSO group value in the SSO attribute.	string	Maximum length: 35							
sso-attribute-value-override	Enable/disable override old attribute value with new value for the same endpoint.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable override old attribute value with new value for the same endpoint.</td></tr><tr><td><i>disable</i></td><td>Disable override old attribute value with new value for the same endpoint.</td></tr></table>	Option	Description	<i>enable</i>	Enable override old attribute value with new value for the same endpoint.	<i>disable</i>	Disable override old attribute value with new value for the same endpoint.			
	Option	Description								
	<i>enable</i>	Enable override old attribute value with new value for the same endpoint.								
<i>disable</i>	Disable override old attribute value with new value for the same endpoint.									
rsso-context-timeout	Time in seconds before the logged out user is removed from the "user context list" of logged on users.	integer	Minimum value: 0 Maximum value: 4294967295	28800						
rsso-log-period	Time interval in seconds that group event log messages will be generated for dynamic profile events.	integer	Minimum value: 0 Maximum value: 4294967295	0						
rsso-log-flags	Events to log.	option	-	protocol-error profile-missing accounting-stop-missed accounting-event endpoint-block radiusd-other						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>protocol-error</i></td><td>Enable this log type.</td></tr></table>	Option	Description	<i>protocol-error</i>	Enable this log type.					
	Option	Description								
<i>protocol-error</i>	Enable this log type.									

Parameter	Description	Type	Size	Default														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>profile-missing</i></td><td>Enable this log type.</td></tr><tr><td><i>accounting-stop-missed</i></td><td>Enable this log type.</td></tr><tr><td><i>accounting-event</i></td><td>Enable this log type.</td></tr><tr><td><i>endpoint-block</i></td><td>Enable this log type.</td></tr><tr><td><i>radiusd-other</i></td><td>Enable this log type.</td></tr><tr><td><i>none</i></td><td>Disable all logging.</td></tr></table>	Option	Description	<i>profile-missing</i>	Enable this log type.	<i>accounting-stop-missed</i>	Enable this log type.	<i>accounting-event</i>	Enable this log type.	<i>endpoint-block</i>	Enable this log type.	<i>radiusd-other</i>	Enable this log type.	<i>none</i>	Disable all logging.			
	Option	Description																
	<i>profile-missing</i>	Enable this log type.																
	<i>accounting-stop-missed</i>	Enable this log type.																
	<i>accounting-event</i>	Enable this log type.																
	<i>endpoint-block</i>	Enable this log type.																
	<i>radiusd-other</i>	Enable this log type.																
<i>none</i>	Disable all logging.																	
rsso-flush-ip-session	Enable/disable flushing user IP sessions on RADIUS accounting Stop messages.	option	-	disable														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable flush user IP sessions on RADIUS accounting stop.</td></tr><tr><td><i>disable</i></td><td>Disable flush user IP sessions on RADIUS accounting stop.</td></tr></table>	Option	Description	<i>enable</i>	Enable flush user IP sessions on RADIUS accounting stop.	<i>disable</i>	Disable flush user IP sessions on RADIUS accounting stop.											
	Option	Description																
	<i>enable</i>	Enable flush user IP sessions on RADIUS accounting stop.																
<i>disable</i>	Disable flush user IP sessions on RADIUS accounting stop.																	
rsso-ep-one-ip-only	Enable/disable the replacement of old IP addresses with new ones for the same endpoint on RADIUS accounting Start messages.	option	-	disable														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable replacement of old IP address with new IP address for the same endpoint on RADIUS accounting start.</td></tr><tr><td><i>disable</i></td><td>Disable replacement of old IP address with new IP address for the same endpoint on RADIUS accounting start.</td></tr></table>	Option	Description	<i>enable</i>	Enable replacement of old IP address with new IP address for the same endpoint on RADIUS accounting start.	<i>disable</i>	Disable replacement of old IP address with new IP address for the same endpoint on RADIUS accounting start.											
	Option	Description																
	<i>enable</i>	Enable replacement of old IP address with new IP address for the same endpoint on RADIUS accounting start.																
<i>disable</i>	Disable replacement of old IP address with new IP address for the same endpoint on RADIUS accounting start.																	
delimiter	Configure delimiter to be used for separating profile group names in the SSO attribute (default = plus character "+").	option	-	plus														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>plus</i></td><td>Plus character "+".</td></tr><tr><td><i>comma</i></td><td>Comma character ",".</td></tr></table>	Option	Description	<i>plus</i>	Plus character "+".	<i>comma</i>	Comma character ",".											
	Option	Description																
	<i>plus</i>	Plus character "+".																
<i>comma</i>	Comma character ",".																	

config accounting-server

Parameter	Description	Type	Size	Default						
id	ID (0 - 4294967295).	integer	Minimum value: 0 Maximum value: 4294967295	0						
status	Status.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Log to remote syslog server.</td></tr><tr><td><i>disable</i></td><td>Do not log to remote syslog server.</td></tr></table>				Option	Description	<i>enable</i>	Log to remote syslog server.	<i>disable</i>	Do not log to remote syslog server.
	Option	Description								
	<i>enable</i>	Log to remote syslog server.								
<i>disable</i>	Do not log to remote syslog server.									
server	Server CN domain name or IP address.	string	Maximum length: 63							
secret	Secret key.	password	Not Specified							
port	RADIUS accounting port number.	integer	Minimum value: 0 Maximum value: 65535	0						
source-ip	Source IP address for communications to the RADIUS server.	string	Maximum length: 63							
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Set outgoing interface automatically.</td></tr><tr><td><i>specify</i></td><td>Set outgoing interface manually.</td></tr></table>				Option	Description	<i>auto</i>	Set outgoing interface automatically.	<i>specify</i>	Set outgoing interface manually.
	Option	Description								
	<i>auto</i>	Set outgoing interface automatically.								
<i>specify</i>	Set outgoing interface manually.									
interface	Specify outgoing interface to reach server.	string	Maximum length: 15							

config user saml

SAML server entry configuration.

```
config user saml
  Description: SAML server entry configuration.
  edit <name>
    set cert {string}
    set entity-id {string}
```

```

set single-sign-on-url {string}
set single-logout-url {string}
set idp-entity-id {string}
set idp-single-sign-on-url {string}
set idp-single-logout-url {string}
set idp-cert {string}
set user-name {string}
set group-name {string}
set digest-method [sha1|sha256]
set limit-relaystate [enable|disable]
set clock-tolerance {integer}
set adfs-claim [enable|disable]
set user-claim-type [email|given-name|...]
set group-claim-type [email|given-name|...]
next
end

```

config user saml

Parameter	Description	Type	Size	Default
name	SAML server entry name.	string	Maximum length: 35	
cert	Certificate to sign SAML messages.	string	Maximum length: 35	
entity-id	SP entity ID.	string	Maximum length: 255	
single-sign-on-url	SP single sign-on URL.	string	Maximum length: 255	
single-logout-url	SP single logout URL.	string	Maximum length: 255	
idp-entity-id	IDP entity ID.	string	Maximum length: 255	
idp-single-sign-on-url	IDP single sign-on URL.	string	Maximum length: 255	
idp-single-logout-url	IDP single logout url.	string	Maximum length: 255	
idp-cert	IDP Certificate name.	string	Maximum length: 35	
user-name	User name in assertion statement.	string	Maximum length: 255	
group-name	Group name in assertion statement.	string	Maximum length: 255	

Parameter	Description	Type	Size	Default												
digest-method	Digest method algorithm (default = sha1).	option	-	sha1												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>sha1</td><td>Digest Method Algorithm is SHA1.</td></tr><tr><td>sha256</td><td>Digest Method Algorithm is SHA256.</td></tr></table>	Option	Description	sha1	Digest Method Algorithm is SHA1.	sha256	Digest Method Algorithm is SHA256.									
Option	Description															
sha1	Digest Method Algorithm is SHA1.															
sha256	Digest Method Algorithm is SHA256.															
limit-relaystate	Enable/disable limiting of relay-state parameter when it exceeds SAML 2.0 specification limits (80 bytes).	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable limiting of relay-state parameter when it exceeds SAML 2.0 specification limits (80 bytes).</td></tr><tr><td>disable</td><td>Disable limiting of relay-state parameter when it exceeds SAML 2.0 specification limits (80 bytes).</td></tr></table>	Option	Description	enable	Enable limiting of relay-state parameter when it exceeds SAML 2.0 specification limits (80 bytes).	disable	Disable limiting of relay-state parameter when it exceeds SAML 2.0 specification limits (80 bytes).									
Option	Description															
enable	Enable limiting of relay-state parameter when it exceeds SAML 2.0 specification limits (80 bytes).															
disable	Disable limiting of relay-state parameter when it exceeds SAML 2.0 specification limits (80 bytes).															
clock-tolerance	Clock skew tolerance in seconds (0 - 300, default = 15, 0 = no tolerance).	integer	Minimum value: 0 Maximum value: 300	15												
adfs-claim	Enable/disable ADFS Claim for user/group attribute in assertion statement (default = disable).	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable ADFS Claim for user/group attribute in assertion statement.</td></tr><tr><td>disable</td><td>Disable ADFS Claim for user/group attribute in assertion statement.</td></tr></table>	Option	Description	enable	Enable ADFS Claim for user/group attribute in assertion statement.	disable	Disable ADFS Claim for user/group attribute in assertion statement.									
Option	Description															
enable	Enable ADFS Claim for user/group attribute in assertion statement.															
disable	Disable ADFS Claim for user/group attribute in assertion statement.															
user-claim-type	User name claim in assertion statement.	option	-	upn												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>email</td><td>E-mail address of the user.</td></tr><tr><td>given-name</td><td>Given name of the user.</td></tr><tr><td>name</td><td>Unique name of the user.</td></tr><tr><td>upn</td><td>User principal name (UPN) of the user.</td></tr><tr><td>common-name</td><td>Common name of the user.</td></tr></table>	Option	Description	email	E-mail address of the user.	given-name	Given name of the user.	name	Unique name of the user.	upn	User principal name (UPN) of the user.	common-name	Common name of the user.			
Option	Description															
email	E-mail address of the user.															
given-name	Given name of the user.															
name	Unique name of the user.															
upn	User principal name (UPN) of the user.															
common-name	Common name of the user.															

Parameter	Description	Type	Size	Default																																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>email-adfs-1x</i></td><td>E-mail address of the user when interoperating with AD FS 1.1 or ADFS 1.0.</td></tr><tr><td><i>group</i></td><td>Group that the user is a member of.</td></tr><tr><td><i>upn-adfs-1x</i></td><td>User principal name (UPN) of the user.</td></tr><tr><td><i>role</i></td><td>Role that the user has.</td></tr><tr><td><i>sur-name</i></td><td>Surname of the user</td></tr><tr><td><i>ppid</i></td><td>Private identifier of the user.</td></tr><tr><td><i>name-identifier</i></td><td>SAML name identifier of the user.</td></tr><tr><td><i>authentication-method</i></td><td>Method used to authenticate the user.</td></tr><tr><td><i>deny-only-group-sid</i></td><td>Deny-only group SID of the user.</td></tr><tr><td><i>deny-only-primary-sid</i></td><td>Deny-only primary SID of the user.</td></tr><tr><td><i>deny-only-primary-group-sid</i></td><td>Deny-only primary group SID of the user.</td></tr><tr><td><i>group-sid</i></td><td>Group SID of the user.</td></tr><tr><td><i>primary-group-sid</i></td><td>Primary group SID of the user.</td></tr><tr><td><i>primary-sid</i></td><td>Primary SID of the user.</td></tr><tr><td><i>windows-account-name</i></td><td>Domain account name of the user in the form of <domain>\<user>.</td></tr></table>	Option	Description	<i>email-adfs-1x</i>	E-mail address of the user when interoperating with AD FS 1.1 or ADFS 1.0.	<i>group</i>	Group that the user is a member of.	<i>upn-adfs-1x</i>	User principal name (UPN) of the user.	<i>role</i>	Role that the user has.	<i>sur-name</i>	Surname of the user	<i>ppid</i>	Private identifier of the user.	<i>name-identifier</i>	SAML name identifier of the user.	<i>authentication-method</i>	Method used to authenticate the user.	<i>deny-only-group-sid</i>	Deny-only group SID of the user.	<i>deny-only-primary-sid</i>	Deny-only primary SID of the user.	<i>deny-only-primary-group-sid</i>	Deny-only primary group SID of the user.	<i>group-sid</i>	Group SID of the user.	<i>primary-group-sid</i>	Primary group SID of the user.	<i>primary-sid</i>	Primary SID of the user.	<i>windows-account-name</i>	Domain account name of the user in the form of <domain>\<user>.			
	Option	Description																																		
	<i>email-adfs-1x</i>	E-mail address of the user when interoperating with AD FS 1.1 or ADFS 1.0.																																		
	<i>group</i>	Group that the user is a member of.																																		
	<i>upn-adfs-1x</i>	User principal name (UPN) of the user.																																		
	<i>role</i>	Role that the user has.																																		
	<i>sur-name</i>	Surname of the user																																		
	<i>ppid</i>	Private identifier of the user.																																		
	<i>name-identifier</i>	SAML name identifier of the user.																																		
	<i>authentication-method</i>	Method used to authenticate the user.																																		
	<i>deny-only-group-sid</i>	Deny-only group SID of the user.																																		
	<i>deny-only-primary-sid</i>	Deny-only primary SID of the user.																																		
	<i>deny-only-primary-group-sid</i>	Deny-only primary group SID of the user.																																		
	<i>group-sid</i>	Group SID of the user.																																		
	<i>primary-group-sid</i>	Primary group SID of the user.																																		
<i>primary-sid</i>	Primary SID of the user.																																			
<i>windows-account-name</i>	Domain account name of the user in the form of <domain>\<user>.																																			
group-claim-type	Group claim in assertion statement.	option	-	group																																
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>email</i></td><td>E-mail address of the user.</td></tr><tr><td><i>given-name</i></td><td>Given name of the user.</td></tr><tr><td><i>name</i></td><td>Unique name of the user.</td></tr><tr><td><i>upn</i></td><td>User principal name (UPN) of the user.</td></tr><tr><td><i>common-name</i></td><td>Common name of the user.</td></tr></table>	Option	Description	<i>email</i>	E-mail address of the user.	<i>given-name</i>	Given name of the user.	<i>name</i>	Unique name of the user.	<i>upn</i>	User principal name (UPN) of the user.	<i>common-name</i>	Common name of the user.																							
	Option	Description																																		
	<i>email</i>	E-mail address of the user.																																		
	<i>given-name</i>	Given name of the user.																																		
	<i>name</i>	Unique name of the user.																																		
	<i>upn</i>	User principal name (UPN) of the user.																																		
<i>common-name</i>	Common name of the user.																																			

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>email-adfs-1x</i>	E-mail address of the user when interoperating with AD FS 1.1 or ADFS 1.0.		
	<i>group</i>	Group that the user is a member of.		
	<i>upn-adfs-1x</i>	User principal name (UPN) of the user.		
	<i>role</i>	Role that the user has.		
	<i>sur-name</i>	Surname of the user		
	<i>ppid</i>	Private identifier of the user.		
	<i>name-identifier</i>	SAML name identifier of the user.		
	<i>authentication-method</i>	Method used to authenticate the user.		
	<i>deny-only-group-sid</i>	Deny-only group SID of the user.		
	<i>deny-only-primary-sid</i>	Deny-only primary SID of the user.		
	<i>deny-only-primary-group-sid</i>	Deny-only primary group SID of the user.		
	<i>group-sid</i>	Group SID of the user.		
	<i>primary-group-sid</i>	Primary group SID of the user.		
	<i>primary-sid</i>	Primary SID of the user.		
	<i>windows-account-name</i>	Domain account name of the user in the form of <domain>\<user>.		

config user security-exempt-list

Configure security exemption list.

```

config user security-exempt-list
  Description: Configure security exemption list.
  edit <name>
    set description {string}
    config rule
      Description: Configure rules for exempting users from captive portal authentication.
      edit <id>
        set srcaddr <name1>, <name2>, ...
        set dstaddr <name1>, <name2>, ...

```

```

        set service <name1>, <name2>, ...
    next
end
next
end

```

config user security-exempt-list

Parameter	Description	Type	Size	Default
name	Name of the exempt list.	string	Maximum length: 35	
description	Description.	string	Maximum length: 127	

config rule

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
srcaddr <name>	Source addresses or address groups. Address or group name.	string	Maximum length: 79	
dstaddr <name>	Destination addresses or address groups. Address or group name.	string	Maximum length: 79	
service <name>	Destination services. Service name.	string	Maximum length: 79	

config user setting

Configure user authentication setting.

```

config user setting
    Description: Configure user authentication setting.
    set auth-type {option1}, {option2}, ...
    set auth-cert {string}
    set auth-ca-cert {string}
    set auth-secure-http [enable|disable]
    set auth-http-basic [enable|disable]
    set auth-ssl-allow-renegotiation [enable|disable]
    set auth-src-mac [enable|disable]

```

```

set auth-on-demand [always|implicitly]
set auth-portal-timeout {integer}
set radius-ses-timeout-act [hard-timeout|ignore-timeout]
set auth-blackout-time {integer}
set auth-invalid-max {integer}
set auth-lockout-threshold {integer}
set auth-lockout-duration {integer}
set per-policy-disclaimer [enable|disable]
config auth-ports
    Description: Set up non-standard ports for authentication with HTTP, HTTPS, FTP, and
TELNET.
    edit <id>
        set type [http|https|...]
        set port {integer}
    next
end
set auth-ssl-min-proto-version [default|SSLv3|...]
set auth-ssl-max-proto-version [sslv3|tlsv1|...]
set auth-ssl-sigalgs [no-rsa-pss|all]
end

```

config user setting

Parameter	Description	Type	Size	Default										
auth-type	Supported firewall policy authentication protocols/methods.	option	-	http https ftp telnet										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>http</td><td>Allow HTTP authentication.</td></tr><tr><td>https</td><td>Allow HTTPS authentication.</td></tr><tr><td>ftp</td><td>Allow FTP authentication.</td></tr><tr><td>telnet</td><td>Allow TELNET authentication.</td></tr></table>	Option	Description	http	Allow HTTP authentication.	https	Allow HTTPS authentication.	ftp	Allow FTP authentication.	telnet	Allow TELNET authentication.			
Option	Description													
http	Allow HTTP authentication.													
https	Allow HTTPS authentication.													
ftp	Allow FTP authentication.													
telnet	Allow TELNET authentication.													
auth-cert	HTTPS server certificate for policy authentication.	string	Maximum length: 35											
auth-ca-cert	HTTPS CA certificate for policy authentication.	string	Maximum length: 35											
auth-secure-http	Enable/disable redirecting HTTP user authentication to more secure HTTPS.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable setting.</td></tr><tr><td>disable</td><td>Disable setting.</td></tr></table>	Option	Description	enable	Enable setting.	disable	Disable setting.							
Option	Description													
enable	Enable setting.													
disable	Disable setting.													

Parameter	Description	Type	Size	Default						
auth-http-basic	Enable/disable use of HTTP basic authentication for identity-based firewall policies.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
auth-ssl-allow-renegotiation	Allow/forbid SSL re-negotiation for HTTPS authentication.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Allow SSL re-negotiation.</td></tr><tr><td><i>disable</i></td><td>Forbid SSL re-negotiation.</td></tr></table>	Option	Description	<i>enable</i>	Allow SSL re-negotiation.	<i>disable</i>	Forbid SSL re-negotiation.			
Option	Description									
<i>enable</i>	Allow SSL re-negotiation.									
<i>disable</i>	Forbid SSL re-negotiation.									
auth-src-mac	Enable/disable source MAC for user identity.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable source MAC for user identity.</td></tr><tr><td><i>disable</i></td><td>Disable source MAC for user identity.</td></tr></table>	Option	Description	<i>enable</i>	Enable source MAC for user identity.	<i>disable</i>	Disable source MAC for user identity.			
Option	Description									
<i>enable</i>	Enable source MAC for user identity.									
<i>disable</i>	Disable source MAC for user identity.									
auth-on-demand	Always/implicitly trigger firewall authentication on demand.	option	-	implicitly						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>always</i></td><td>Always trigger firewall authentication on demand.</td></tr><tr><td><i>implicitly</i></td><td>Implicitly trigger firewall authentication on demand.</td></tr></table>	Option	Description	<i>always</i>	Always trigger firewall authentication on demand.	<i>implicitly</i>	Implicitly trigger firewall authentication on demand.			
Option	Description									
<i>always</i>	Always trigger firewall authentication on demand.									
<i>implicitly</i>	Implicitly trigger firewall authentication on demand.									
auth-portal-timeout	Time in minutes before captive portal user have to re-authenticate (1 - 30 min, default 3 min).	integer	Minimum value: 1 Maximum value: 30	3						
radius-ses-timeout-act	Set the RADIUS session timeout to a hard timeout or to ignore RADIUS server session timeouts.	option	-	hard-timeout						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>hard-timeout</i></td><td>Use session timeout from RADIUS as hard-timeout.</td></tr><tr><td><i>ignore-timeout</i></td><td>Ignore session timeout from RADIUS.</td></tr></table>	Option	Description	<i>hard-timeout</i>	Use session timeout from RADIUS as hard-timeout.	<i>ignore-timeout</i>	Ignore session timeout from RADIUS.			
Option	Description									
<i>hard-timeout</i>	Use session timeout from RADIUS as hard-timeout.									
<i>ignore-timeout</i>	Ignore session timeout from RADIUS.									

Parameter	Description	Type	Size	Default												
auth-blackout-time	Time in seconds an IP address is denied access after failing to authenticate five times within one minute.	integer	Minimum value: 0 Maximum value: 3600	0												
auth-invalid-max	Maximum number of failed authentication attempts before the user is blocked.	integer	Minimum value: 1 Maximum value: 100	5												
auth-lockout-threshold	Maximum number of failed login attempts before login lockout is triggered.	integer	Minimum value: 1 Maximum value: 10	3												
auth-lockout-duration	Lockout period in seconds after too many login failures.	integer	Minimum value: 0 Maximum value: 4294967295	0												
per-policy-disclaimer	Enable/disable per policy disclaimer.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable per policy disclaimer.</td></tr><tr><td><i>disable</i></td><td>Disable per policy disclaimer.</td></tr></table>				Option	Description	<i>enable</i>	Enable per policy disclaimer.	<i>disable</i>	Disable per policy disclaimer.						
Option	Description															
<i>enable</i>	Enable per policy disclaimer.															
<i>disable</i>	Disable per policy disclaimer.															
auth-ssl-min-proto-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>default</i></td><td>Follow system global setting.</td></tr><tr><td><i>SSLv3</i></td><td>SSLv3.</td></tr><tr><td><i>TLSv1</i></td><td>TLSv1.</td></tr><tr><td><i>TLSv1-1</i></td><td>TLSv1.1.</td></tr><tr><td><i>TLSv1-2</i></td><td>TLSv1.2.</td></tr></table>				Option	Description	<i>default</i>	Follow system global setting.	<i>SSLv3</i>	SSLv3.	<i>TLSv1</i>	TLSv1.	<i>TLSv1-1</i>	TLSv1.1.	<i>TLSv1-2</i>	TLSv1.2.
Option	Description															
<i>default</i>	Follow system global setting.															
<i>SSLv3</i>	SSLv3.															
<i>TLSv1</i>	TLSv1.															
<i>TLSv1-1</i>	TLSv1.1.															
<i>TLSv1-2</i>	TLSv1.2.															
auth-ssl-max-proto-version	Maximum supported protocol version for SSL/TLS connections (default is no limit).	option	-													

Parameter	Description	Type	Size	Default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ssl/v3</i></td><td>SSLv3.</td></tr><tr><td><i>tlsv1</i></td><td>TLSv1.</td></tr><tr><td><i>tlsv1-1</i></td><td>TLSv1.1.</td></tr><tr><td><i>tlsv1-2</i></td><td>TLSv1.2.</td></tr><tr><td><i>tlsv1-3</i></td><td>TLSv1.3.</td></tr></table>	Option	Description	<i>ssl/v3</i>	SSLv3.	<i>tlsv1</i>	TLSv1.	<i>tlsv1-1</i>	TLSv1.1.	<i>tlsv1-2</i>	TLSv1.2.	<i>tlsv1-3</i>	TLSv1.3.			
	Option	Description														
	<i>ssl/v3</i>	SSLv3.														
	<i>tlsv1</i>	TLSv1.														
	<i>tlsv1-1</i>	TLSv1.1.														
	<i>tlsv1-2</i>	TLSv1.2.														
<i>tlsv1-3</i>	TLSv1.3.															
auth-ssl-sigalgs	Set signature algorithms related to HTTPS authentication (affects TLS version <= 1.2 only, default is to enable all).	option	-	all												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>no-rsa-pss</i></td><td>Disable RSA-PSS signature algorithms for HTTPS authentication.</td></tr><tr><td><i>all</i></td><td>Enable all supported signature algorithms for HTTPS authentication.</td></tr></table>	Option	Description	<i>no-rsa-pss</i>	Disable RSA-PSS signature algorithms for HTTPS authentication.	<i>all</i>	Enable all supported signature algorithms for HTTPS authentication.									
	Option	Description														
	<i>no-rsa-pss</i>	Disable RSA-PSS signature algorithms for HTTPS authentication.														
<i>all</i>	Enable all supported signature algorithms for HTTPS authentication.															

config auth-ports

Parameter	Description	Type	Size	Default										
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0										
type	Service type.	option	-	http										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>http</td><td>HTTP service.</td></tr><tr><td>https</td><td>HTTPS service.</td></tr><tr><td>ftp</td><td>FTP service.</td></tr><tr><td>telnet</td><td>TELNET service.</td></tr></table>				Option	Description	http	HTTP service.	https	HTTPS service.	ftp	FTP service.	telnet	TELNET service.
	Option	Description												
	http	HTTP service.												
	https	HTTPS service.												
	ftp	FTP service.												
telnet	TELNET service.													
port	Non-standard port for firewall user authentication.	integer	Minimum value: 1 Maximum value: 65535	1024										

config user tacacs+

Configure TACACS+ server entries.

```
config user tacacs+
  Description: Configure TACACS+ server entries.
  edit <name>
    set server {string}
    set secondary-server {string}
    set tertiary-server {string}
    set port {integer}
    set key {password}
    set secondary-key {password}
    set tertiary-key {password}
    set authen-type [mschap|chap|...]
    set authorization [enable|disable]
    set source-ip {string}
    set interface-select-method [auto|specify]
    set interface {string}
  next
end
```

config user tacacs+

Parameter	Description	Type	Size	Default
name	TACACS+ server entry name.	string	Maximum length: 35	
server	Primary TACACS+ server CN domain name or IP address.	string	Maximum length: 63	
secondary-server	Secondary TACACS+ server CN domain name or IP address.	string	Maximum length: 63	
tertiary-server	Tertiary TACACS+ server CN domain name or IP address.	string	Maximum length: 63	
port	Port number of the TACACS+ server.	integer	Minimum value: 1 Maximum value: 65535	49
key	Key to access the primary server.	password	Not Specified	
secondary-key	Key to access the secondary server.	password	Not Specified	
tertiary-key	Key to access the tertiary server.	password	Not Specified	

Parameter	Description	Type	Size	Default												
authen-type	Allowed authentication protocols/methods.	option	-	auto												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>mschap</i></td><td>MSCHAP.</td></tr><tr><td><i>chap</i></td><td>CHAP.</td></tr><tr><td><i>pap</i></td><td>PAP.</td></tr><tr><td><i>ascii</i></td><td>ASCII.</td></tr><tr><td><i>auto</i></td><td>Use PAP, MSCHAP, and CHAP (in that order).</td></tr></table>	Option	Description	<i>mschap</i>	MSCHAP.	<i>chap</i>	CHAP.	<i>pap</i>	PAP.	<i>ascii</i>	ASCII.	<i>auto</i>	Use PAP, MSCHAP, and CHAP (in that order).			
Option	Description															
<i>mschap</i>	MSCHAP.															
<i>chap</i>	CHAP.															
<i>pap</i>	PAP.															
<i>ascii</i>	ASCII.															
<i>auto</i>	Use PAP, MSCHAP, and CHAP (in that order).															
authorization	Enable/disable TACACS+ authorization.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable TACACS+ authorization.</td></tr><tr><td><i>disable</i></td><td>Disable TACACS+ authorization.</td></tr></table>	Option	Description	<i>enable</i>	Enable TACACS+ authorization.	<i>disable</i>	Disable TACACS+ authorization.									
Option	Description															
<i>enable</i>	Enable TACACS+ authorization.															
<i>disable</i>	Disable TACACS+ authorization.															
source-ip	Source IP address for communications to TACACS+ server.	string	Maximum length: 63													
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Set outgoing interface automatically.</td></tr><tr><td><i>specify</i></td><td>Set outgoing interface manually.</td></tr></table>	Option	Description	<i>auto</i>	Set outgoing interface automatically.	<i>specify</i>	Set outgoing interface manually.									
Option	Description															
<i>auto</i>	Set outgoing interface automatically.															
<i>specify</i>	Set outgoing interface manually.															
interface	Specify outgoing interface to reach server.	string	Maximum length: 15													

videofilter

This section includes syntax for the following commands:

- [config videofilter profile on page 1171](#)
- [config videofilter youtube-channel-filter on page 1173](#)
- [config videofilter youtube-key on page 1175](#)

config videofilter profile

Configure VideoFilter profile.

```
config videofilter profile
  Description: Configure VideoFilter profile.
  edit <name>
    set comment {var-string}
    set default-action [allow|monitor|...]
    set log [enable|disable]
    set youtube-channel-filter {integer}
    config fortiguard-category
      Description: Configure FortiGuard categories.
      config filters
        Description: Configure VideoFilter FortiGuard category.
        edit <id>
          set action [allow|monitor|...]
          set category-id {integer}
          set log [enable|disable]
        next
      end
    end
    set youtube [enable|disable]
    set vimeo [enable|disable]
    set dailymotion [enable|disable]
    set replacemsg-group {string}
  next
end
```

config videofilter profile

Parameter	Description	Type	Size	Default
name	Name.	string	Maximum length: 35	

Parameter	Description	Type	Size	Default								
comment	Comment.	var-string	Maximum length: 255									
default-action	Video filter default action.	option	-	monitor								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow videos to be accessed.</td></tr><tr><td><i>monitor</i></td><td>Monitor videos.</td></tr><tr><td><i>block</i></td><td>Block videos.</td></tr></table>	Option	Description	<i>allow</i>	Allow videos to be accessed.	<i>monitor</i>	Monitor videos.	<i>block</i>	Block videos.			
Option	Description											
<i>allow</i>	Allow videos to be accessed.											
<i>monitor</i>	Monitor videos.											
<i>block</i>	Block videos.											
log	Enable/disable logging.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable logging.</td></tr><tr><td><i>disable</i></td><td>Disable logging.</td></tr></table>	Option	Description	<i>enable</i>	Enable logging.	<i>disable</i>	Disable logging.					
Option	Description											
<i>enable</i>	Enable logging.											
<i>disable</i>	Disable logging.											
youtube-channel-filter	Set YouTube channel filter.	integer	Minimum value: 0 Maximum value: 4294967295	0								
youtube	Enable/disable YouTube video source.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable YouTube source.</td></tr><tr><td><i>disable</i></td><td>Disable YouTube source.</td></tr></table>	Option	Description	<i>enable</i>	Enable YouTube source.	<i>disable</i>	Disable YouTube source.					
Option	Description											
<i>enable</i>	Enable YouTube source.											
<i>disable</i>	Disable YouTube source.											
vimeo	Enable/disable Vimeo video source.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable Vimeo source.</td></tr><tr><td><i>disable</i></td><td>Disable Vimeo source.</td></tr></table>	Option	Description	<i>enable</i>	Enable Vimeo source.	<i>disable</i>	Disable Vimeo source.					
Option	Description											
<i>enable</i>	Enable Vimeo source.											
<i>disable</i>	Disable Vimeo source.											
dailymotion	Enable/disable Dailymotion video source.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable Dailymotion source.</td></tr><tr><td><i>disable</i></td><td>Disable Dailymotion source.</td></tr></table>	Option	Description	<i>enable</i>	Enable Dailymotion source.	<i>disable</i>	Disable Dailymotion source.					
Option	Description											
<i>enable</i>	Enable Dailymotion source.											
<i>disable</i>	Disable Dailymotion source.											
replacemsg-group	Replacement message group.	string	Maximum length: 35									

config filters

Parameter	Description	Type	Size	Default								
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0								
action	VideoFilter action.	option	-	monitor								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow videos to be accessed.</td></tr><tr><td><i>monitor</i></td><td>Monitor videos.</td></tr><tr><td><i>block</i></td><td>Block videos.</td></tr></table>				Option	Description	<i>allow</i>	Allow videos to be accessed.	<i>monitor</i>	Monitor videos.	<i>block</i>	Block videos.
	Option	Description										
	<i>allow</i>	Allow videos to be accessed.										
	<i>monitor</i>	Monitor videos.										
<i>block</i>	Block videos.											
category-id	Category ID.	integer	Minimum value: 0 Maximum value: 4294967295	0								
log	Enable/disable logging.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable logging.</td></tr><tr><td><i>disable</i></td><td>Disable logging.</td></tr></table>				Option	Description	<i>enable</i>	Enable logging.	<i>disable</i>	Disable logging.		
	Option	Description										
	<i>enable</i>	Enable logging.										
<i>disable</i>	Disable logging.											

config videofilter youtube-channel-filter

Configure YouTube channel filter.

```
config videofilter youtube-channel-filter
  Description: Configure YouTube channel filter.
  edit <id>
    set name {string}
    set comment {var-string}
    config entries
      Description: YouTube filter entries.
      edit <id>
        set comment {var-string}
        set action [allow|monitor|...]
        set channel-id {string}
      next
    end
  set log [enable|disable]
```

```
next
end
```

config videofilter youtube-channel-filter

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Name.	string	Maximum length: 35	
comment	Comment.	var-string	Maximum length: 255	
log	Enable/disable logging.	option	-	enable
	Option	Description		
	enable	Enable logging.		
	disable	Disable logging.		

config entries

Parameter	Description	Type	Size	Default								
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0								
comment	Comment.	var-string	Maximum length: 255									
action	YouTube channel filter action.	option	-	monitor								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow videos to be accessed.</td></tr><tr><td><i>monitor</i></td><td>Monitor videos.</td></tr><tr><td><i>block</i></td><td>Block videos.</td></tr></table>				Option	Description	<i>allow</i>	Allow videos to be accessed.	<i>monitor</i>	Monitor videos.	<i>block</i>	Block videos.
	Option	Description										
	<i>allow</i>	Allow videos to be accessed.										
	<i>monitor</i>	Monitor videos.										
<i>block</i>	Block videos.											
channel-id	Channel ID.	string	Maximum length: 255									

config videofilter youtube-key

Configure YouTube API keys.

```
config videofilter youtube-key
  Description: Configure YouTube API keys.
  edit <id>
    set key {string}
  next
end
```

config videofilter youtube-key

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
key	Key.	string	Maximum length: 47	

vpn

This section includes syntax for the following commands:

- [config vpn certificate ca on page 1176](#)
- [config vpn certificate crl on page 1178](#)
- [config vpn certificate local on page 1179](#)
- [config vpn certificate ocsf-server on page 1184](#)
- [config vpn certificate remote on page 1185](#)
- [config vpn certificate setting on page 1186](#)
- [config vpn ipsec phase1-interface on page 1192](#)
- [config vpn ipsec phase2-interface on page 1208](#)

config vpn certificate ca

CA certificate.

```
config vpn certificate ca
  Description: CA certificate.
  edit <name>
    set ca {user}
    set range [global|vdom]
    set source [factory|user|...]
    set ssl-inspection-trusted [enable|disable]
    set scep-url {string}
    set auto-update-days {integer}
    set auto-update-days-warning {integer}
    set source-ip {ipv4-address}
    set ca-identifier {string}
    set obsolete [disable|enable]
  next
end
```

config vpn certificate ca

Parameter	Description	Type	Size	Default
name	Name.	string	Maximum length: 79	
ca	CA certificate as a PEM file.	user	Not Specified	

Parameter	Description	Type	Size	Default								
range	Either global or VDOM IP address range for the CA certificate.	option	-	vdom								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>global</i></td><td>Global range.</td></tr><tr><td><i>vdom</i></td><td>VDOM IP address range.</td></tr></table>	Option	Description	<i>global</i>	Global range.	<i>vdom</i>	VDOM IP address range.					
Option	Description											
<i>global</i>	Global range.											
<i>vdom</i>	VDOM IP address range.											
source	CA certificate source type.	option	-	user								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>factory</i></td><td>Factory installed certificate.</td></tr><tr><td><i>user</i></td><td>User generated certificate.</td></tr><tr><td><i>bundle</i></td><td>Bundle file certificate.</td></tr></table>	Option	Description	<i>factory</i>	Factory installed certificate.	<i>user</i>	User generated certificate.	<i>bundle</i>	Bundle file certificate.			
Option	Description											
<i>factory</i>	Factory installed certificate.											
<i>user</i>	User generated certificate.											
<i>bundle</i>	Bundle file certificate.											
ssl-inspection-trusted	Enable/disable this CA as a trusted CA for SSL inspection.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Trusted CA for SSL inspection.</td></tr><tr><td><i>disable</i></td><td>Untrusted CA for SSL inspection.</td></tr></table>	Option	Description	<i>enable</i>	Trusted CA for SSL inspection.	<i>disable</i>	Untrusted CA for SSL inspection.					
Option	Description											
<i>enable</i>	Trusted CA for SSL inspection.											
<i>disable</i>	Untrusted CA for SSL inspection.											
scep-url	URL of the SCEP server.	string	Maximum length: 255									
auto-update-days	Number of days to wait before requesting an updated CA certificate (0 - 4294967295, 0 = disabled).	integer	Minimum value: 0 Maximum value: 4294967295	0								
auto-update-days-warning	Number of days before an expiry-warning message is generated (0 - 4294967295, 0 = disabled).	integer	Minimum value: 0 Maximum value: 4294967295	0								
source-ip	Source IP address for communications to the SCEP server.	ipv4-address	Not Specified	0.0.0.0								
ca-identifier	CA identifier of the SCEP server.	string	Maximum length: 255									
obsolete	Enable/disable this CA as obsoleted.	option	-	disable								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>disable</i>	Alive.		
	<i>enable</i>	Obsolete.		

config vpn certificate crl

Certificate Revocation List as a PEM file.

```

config vpn certificate crl
    Description: Certificate Revocation List as a PEM file.
    edit <name>
        set crl {user}
        set range [global|vdom]
        set source [factory|user|...]
        set update-vdom {string}
        set ldap-server {string}
        set ldap-username {string}
        set ldap-password {password}
        set http-url {string}
        set scep-url {string}
        set scep-cert {string}
        set update-interval {integer}
        set source-ip {ipv4-address}
    next
end

```

config vpn certificate crl

Parameter	Description	Type	Size	Default
name	Name.	string	Maximum length: 35	
crl	Certificate Revocation List as a PEM file.	user	Not Specified	
range	Either global or VDOM IP address range for the certificate.	option	-	vdom
	Option	Description		
	<i>global</i>	Global range.		
	<i>vdom</i>	VDOM IP address range.		
source	Certificate source type.	option	-	user

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>factory</i>	Factory installed certificate.		
	<i>user</i>	User generated certificate.		
	<i>bundle</i>	Bundle file certificate.		
update-vdom	VDOM for CRL update.	string	Maximum length: 31	root
ldap-server	LDAP server name for CRL auto-update.	string	Maximum length: 35	
ldap-username	LDAP server user name.	string	Maximum length: 63	
ldap-password	LDAP server user password.	password	Not Specified	
http-url	HTTP server URL for CRL auto-update.	string	Maximum length: 255	
scep-url	SCEP server URL for CRL auto-update.	string	Maximum length: 255	
scep-cert	Local certificate for SCEP communication for CRL auto-update.	string	Maximum length: 35	Fortinet_CA_SSL
update-interval	Time in seconds before the FortiProxy checks for an updated CRL. Set to 0 to update only when it expires.	integer	Minimum value: 0 Maximum value: 4294967295	0
source-ip	Source IP address for communications to a HTTP or SCEP CA server.	ipv4-address	Not Specified	0.0.0.0

config vpn certificate local

Local keys and certificates.

```

config vpn certificate local
  Description: Local keys and certificates.
  edit <name>
    set type [normal|hsm]
    set password {password}
    set hsm-vendor [safenet|primus]
    set hsm-slot {string}
    set hsm-keytype [rsa|ec]
    set comments {string}
  
```

```

set private-key {user}
set certificate {user}
set csr {user}
set state {user}
set scep-url {string}
set range [global|vdom]
set source [factory|user|...]
set auto-regenerate-days {integer}
set auto-regenerate-days-warning {integer}
set scep-password {password}
set ca-identifier {string}
set name-encoding [printable|utf8]
set source-ip {ipv4-address}
set ike-localid {string}
set ike-localid-type [asn1dn|fqdn]
set enroll-protocol [none|scep|...]
set private-key-retain [enable|disable]
set cmp-server {string}
set cmp-path {string}
set cmp-server-cert {string}
set cmp-regeneration-method [keyupdate|renewal]
set acme-ca-url {string}
set acme-domain {string}
set acme-email {string}
set acme-rsa-key-size {integer}
set acme-renew-window {integer}
next
end

```

config vpn certificate local

Parameter	Description	Type	Size	Default
name	Name.	string	Maximum length: 35	
type	Type.	option	-	normal
	Option Description			
	<i>normal</i>	Normal		
	<i>hsm</i>	HSM		
password	Password as a PEM file.	password	Not Specified	
hsm-vendor	HSM vendor.	option	-	safenet

Parameter	Description	Type	Size	Default
	Option Description			
	<i>safenet</i>	Safenet HSM.		
	<i>primus</i>	Securosys Primus HSM.		
hsm-slot	HSM slot to use with this certificate.	string	Maximum length: 35	
hsm-keytype	HSM certificate key type.	option	-	rsa
	Option Description			
	<i>rsa</i>	RSA key type.		
	<i>ec</i>	EC key type.		
comments	Comment.	string	Maximum length: 511	
private-key	PEM format key encrypted with a password.	user	Not Specified	
certificate	PEM format certificate.	user	Not Specified	
csr	Certificate Signing Request.	user	Not Specified	
state	Certificate Signing Request State.	user	Not Specified	
scep-url	SCEP server URL.	string	Maximum length: 255	
range	Either a global or VDOM IP address range for the certificate.	option	-	vdom
	Option Description			
	<i>global</i>	Global range.		
	<i>vdom</i>	VDOM IP address range.		
source	Certificate source type.	option	-	user

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>factory</i>	Factory installed certificate.		
	<i>user</i>	User generated certificate.		
	<i>bundle</i>	Bundle file certificate.		
auto-regenerate-days	Number of days to wait before expiry of an updated local certificate is requested (0 = disabled).	integer	Minimum value: 0 Maximum value: 4294967295	0
auto-regenerate-days-warning	Number of days to wait before an expiry warning message is generated (0 = disabled).	integer	Minimum value: 0 Maximum value: 4294967295	0
scep-password	SCEP server challenge password for auto-regeneration.	password	Not Specified	
ca-identifier	CA identifier of the CA server for signing via SCEP.	string	Maximum length: 255	
name-encoding	Name encoding method for auto-regeneration.	option	-	printable
	Option	Description		
	<i>printable</i>	Printable encoding (default).		
	<i>utf8</i>	UTF-8 encoding.		
source-ip	Source IP address for communications to the SCEP server.	ipv4-address	Not Specified	0.0.0.0

Parameter	Description	Type	Size	Default										
ike-localid	Local ID the FortiProxy uses for authentication as a VPN client.	string	Maximum length: 63											
ike-localid-type	IKE local ID type.	option	-	asn1dn										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>asn1dn</td><td>ASN.1 distinguished name.</td></tr><tr><td>fqdn</td><td>Fully qualified domain name.</td></tr></table>	Option	Description	asn1dn	ASN.1 distinguished name.	fqdn	Fully qualified domain name.							
Option	Description													
asn1dn	ASN.1 distinguished name.													
fqdn	Fully qualified domain name.													
enroll-protocol	Certificate enrollment protocol.	option	-	none										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>none</td><td>None (default).</td></tr><tr><td>scep</td><td>Simple Certificate Enrollment Protocol.</td></tr><tr><td>cmpv2</td><td>Certificate Management Protocol Version 2.</td></tr><tr><td>acme2</td><td>Automated Certificate Management Environment Version 2.</td></tr></table>	Option	Description	none	None (default).	scep	Simple Certificate Enrollment Protocol.	cmpv2	Certificate Management Protocol Version 2.	acme2	Automated Certificate Management Environment Version 2.			
Option	Description													
none	None (default).													
scep	Simple Certificate Enrollment Protocol.													
cmpv2	Certificate Management Protocol Version 2.													
acme2	Automated Certificate Management Environment Version 2.													
private-key-retain	Enable/disable retention of private key during SCEP renewal (default = disable).	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Keep the existing private key during SCEP renewal.</td></tr><tr><td>disable</td><td>Generate a new private key during SCEP renewal.</td></tr></table>	Option	Description	enable	Keep the existing private key during SCEP renewal.	disable	Generate a new private key during SCEP renewal.							
Option	Description													
enable	Keep the existing private key during SCEP renewal.													
disable	Generate a new private key during SCEP renewal.													
cmp-server	Address and port for CMP server (format = address:port).	string	Maximum length: 63											
cmp-path	Path location inside CMP server.	string	Maximum length: 255											

Parameter	Description	Type	Size	Default
cmp-server-cert	CMP server certificate.	string	Maximum length: 79	
cmp-regeneration-method	CMP auto-regeneration method.	option	-	keyupate
	Option	Description		
	keyupate	Key Update.		
	renewal	Renewal.		
acme-ca-url	The URL for the ACME CA server (Let's Encrypt is the default provider).	string	Maximum length: 255	https://acme-v02.api.letsencrypt.org/directory
acme-domain	A valid domain that resolves to this FortiProxy unit.	string	Maximum length: 255	
acme-email	Contact email address that is required by some CAs like LetsEncrypt.	string	Maximum length: 255	
acme-rsa-key-size	Length of the RSA private key of the generated cert (Minimum 2048 bits).	integer	Minimum value: 2048 Maximum value: 4096	2048
acme-renew-window	Beginning of the renewal window (in days before certificate expiration, 30 by default).	integer	Minimum value: 1 Maximum value: 60	30

config vpn certificate ocsf-server

OCSP server configuration.

```
config vpn certificate ocsf-server
  Description: OCSP server configuration.
```



```

edit <name>
    set url {string}
    set cert {string}
    set secondary-url {string}
    set secondary-cert {string}
    set unavail-action [revoke|ignore]
    set source-ip {string}
next
end

```

config vpn certificate ocsf-server

Parameter	Description	Type	Size	Default						
name	OCSP server entry name.	string	Maximum length: 35							
url	OCSP server URL.	string	Maximum length: 127							
cert	OCSP server certificate.	string	Maximum length: 127							
secondary-url	Secondary OCSP server URL.	string	Maximum length: 127							
secondary-cert	Secondary OCSP server certificate.	string	Maximum length: 127							
unavail-action	Action when server is unavailable (revoke the certificate or ignore the result of the check).	option	-	revoke						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>revoke</td><td>Revoke certificate if server is unavailable.</td></tr><tr><td>ignore</td><td>Ignore OCSP check if server is unavailable.</td></tr></table>				Option	Description	revoke	Revoke certificate if server is unavailable.	ignore	Ignore OCSP check if server is unavailable.
Option	Description									
revoke	Revoke certificate if server is unavailable.									
ignore	Ignore OCSP check if server is unavailable.									
source-ip	Source IP address for dynamic AIA and OCSP queries.	string	Maximum length: 63							

config vpn certificate remote

Remote certificate as a PEM file.

```

config vpn certificate remote
    Description: Remote certificate as a PEM file.
    edit <name>
        set remote {user}
    end
end

```

```

        set range [global|vdom]
        set source [factory|user|...]
    next
end

```

config vpn certificate remote

Parameter	Description	Type	Size	Default								
name	Name.	string	Maximum length: 35									
remote	Remote certificate.	user	Not Specified									
range	Either the global or VDOM IP address range for the remote certificate.	option	-	vdom								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>global</i></td><td>Global range.</td></tr><tr><td><i>vdom</i></td><td>VDOM IP address range.</td></tr></table>				Option	Description	<i>global</i>	Global range.	<i>vdom</i>	VDOM IP address range.		
Option	Description											
<i>global</i>	Global range.											
<i>vdom</i>	VDOM IP address range.											
source	Remote certificate source type.	option	-	user								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>factory</i></td><td>Factory installed certificate.</td></tr><tr><td><i>user</i></td><td>User generated certificate.</td></tr><tr><td><i>bundle</i></td><td>Bundle file certificate.</td></tr></table>				Option	Description	<i>factory</i>	Factory installed certificate.	<i>user</i>	User generated certificate.	<i>bundle</i>	Bundle file certificate.
Option	Description											
<i>factory</i>	Factory installed certificate.											
<i>user</i>	User generated certificate.											
<i>bundle</i>	Bundle file certificate.											

config vpn certificate setting

VPN certificate setting.

```

config vpn certificate setting
    Description: VPN certificate setting.
    set oosp-status [enable|disable]
    set oosp-option [certificate|server]
    set proxy {string}
    set proxy-port {integer}
    set proxy-username {string}
    set proxy-password {password}
    set source-ip {string}
    set oosp-default-server {string}
    set interface-select-method [auto|specify]
    set interface {string}

```

```

set check-ca-cert [enable|disable]
set check-ca-chain [enable|disable]
set subject-match [substring|value]
set subject-set [subset|superset]
set cn-match [substring|value]
set cn-allow-multi [disable|enable]
config crl-verification
    Description: CRL verification options.
    set expiry [ignore|revoke]
    set leaf-crl-absence [ignore|revoke]
    set chain-crl-absence [ignore|revoke]
end
set strict-ocsp-check [enable|disable]
set ssl-min-proto-version [default|SSLv3|...]
set cmp-save-extra-certs [enable|disable]
set cmp-key-usage-checking [enable|disable]
set cert-expire-warning {integer}
set certname-rsa1024 {string}
set certname-rsa2048 {string}
set certname-rsa4096 {string}
set certname-dsa1024 {string}
set certname-dsa2048 {string}
set certname-ecdsa256 {string}
set certname-ecdsa384 {string}
set certname-ecdsa521 {string}
set certname-ed25519 {string}
set certname-ed448 {string}
end

```

config vpn certificate setting

Parameter	Description	Type	Size	Default						
ocsp-status	Enable/disable receiving certificates using the OCSP.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
ocsp-option	Specify whether the OCSP URL is from certificate or configured OCSP server.	option	-	server						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>certificate</i></td><td>Use URL from certificate.</td></tr><tr><td><i>server</i></td><td>Use URL from configured OCSP server.</td></tr></table>	Option	Description	<i>certificate</i>	Use URL from certificate.	<i>server</i>	Use URL from configured OCSP server.			
Option	Description									
<i>certificate</i>	Use URL from certificate.									
<i>server</i>	Use URL from configured OCSP server.									

Parameter	Description	Type	Size	Default						
proxy	Proxy server FQDN or IP for OCSP/CA queries during certificate verification.	string	Maximum length: 127							
proxy-port	Proxy server port (1 - 65535, default = 8080).	integer	Minimum value: 1 Maximum value: 65535	8080						
proxy-username	Proxy server user name.	string	Maximum length: 63							
proxy-password	Proxy server password.	password	Not Specified							
source-ip	Source IP address for dynamic AIA and OCSP queries.	string	Maximum length: 63							
ocsp-default-server	Default OCSP server.	string	Maximum length: 35							
interface-select-method	Specify how to select outgoing interface to reach server.	option	-	auto						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>auto</i></td><td>Set outgoing interface automatically.</td></tr><tr><td><i>specify</i></td><td>Set outgoing interface manually.</td></tr></table>				Option	Description	<i>auto</i>	Set outgoing interface automatically.	<i>specify</i>	Set outgoing interface manually.
Option	Description									
<i>auto</i>	Set outgoing interface automatically.									
<i>specify</i>	Set outgoing interface manually.									
interface	Specify outgoing interface to reach server.	string	Maximum length: 15							
check-ca-cert	Enable/disable verification of the user certificate and pass authentication if any CA in the chain is trusted (default = enable).	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable verification of the user certificate.</td></tr><tr><td><i>disable</i></td><td>Disable verification of the user certificate.</td></tr></table>				Option	Description	<i>enable</i>	Enable verification of the user certificate.	<i>disable</i>	Disable verification of the user certificate.
Option	Description									
<i>enable</i>	Enable verification of the user certificate.									
<i>disable</i>	Disable verification of the user certificate.									
check-ca-chain	Enable/disable verification of the entire certificate chain and pass authentication only if the chain is complete and all of the CAs in the chain are trusted (default = disable).	option	-	disable						

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable verification of the entire certificate chain.</td></tr><tr><td><i>disable</i></td><td>Disable verification of the entire certificate chain.</td></tr></table>	Option	Description	<i>enable</i>	Enable verification of the entire certificate chain.	<i>disable</i>	Disable verification of the entire certificate chain.			
	Option	Description								
	<i>enable</i>	Enable verification of the entire certificate chain.								
<i>disable</i>	Disable verification of the entire certificate chain.									
subject-match	When searching for a matching certificate, control how to do RDN value matching with certificate subject name (default = substring).	option	-	substring						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>substring</i></td><td>Find a match if the name being searched for is a part or the same as a certificate subject RDN.</td></tr><tr><td><i>value</i></td><td>Find a match if the name being searched for is same as a certificate subject RDN.</td></tr></table>	Option	Description	<i>substring</i>	Find a match if the name being searched for is a part or the same as a certificate subject RDN.	<i>value</i>	Find a match if the name being searched for is same as a certificate subject RDN.			
	Option	Description								
	<i>substring</i>	Find a match if the name being searched for is a part or the same as a certificate subject RDN.								
<i>value</i>	Find a match if the name being searched for is same as a certificate subject RDN.									
subject-set	When searching for a matching certificate, control how to do RDN set matching with certificate subject name (default = subset).	option	-	subset						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>subset</i></td><td>Find a match if the name being searched for is a subset of a certificate subject.</td></tr><tr><td><i>superset</i></td><td>Find a match if the name being searched for is a superset of a certificate subject.</td></tr></table>	Option	Description	<i>subset</i>	Find a match if the name being searched for is a subset of a certificate subject.	<i>superset</i>	Find a match if the name being searched for is a superset of a certificate subject.			
	Option	Description								
	<i>subset</i>	Find a match if the name being searched for is a subset of a certificate subject.								
<i>superset</i>	Find a match if the name being searched for is a superset of a certificate subject.									
cn-match	When searching for a matching certificate, control how to do CN value matching with certificate subject name (default = substring).	option	-	substring						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>substring</i></td><td>Find a match if the name being searched for is a part or the same as a certificate CN.</td></tr><tr><td><i>value</i></td><td>Find a match if the name being searched for is same as a certificate CN.</td></tr></table>	Option	Description	<i>substring</i>	Find a match if the name being searched for is a part or the same as a certificate CN.	<i>value</i>	Find a match if the name being searched for is same as a certificate CN.			
	Option	Description								
	<i>substring</i>	Find a match if the name being searched for is a part or the same as a certificate CN.								
<i>value</i>	Find a match if the name being searched for is same as a certificate CN.									
cn-allow-multi	When searching for a matching certificate, allow multiple CN fields in certificate subject name (default = enable).	option	-	enable						

Parameter	Description	Type	Size	Default
	Option Description			
	<i>disable</i>	Does not allow multiple CN entries in certificate matching.		
	<i>enable</i>	Allow multiple CN entries in certificate matching.		
strict-ocsp-check	Enable/disable strict mode OCSP checking.	option	-	disable
	Option Description			
	<i>enable</i>	Enable strict mode OCSP checking.		
	<i>disable</i>	Disable strict mode OCSP checking.		
ssl-min-protocol-version	Minimum supported protocol version for SSL/TLS connections (default is to follow system global setting).	option	-	default
	Option Description			
	<i>default</i>	Follow system global setting.		
	<i>SSLv3</i>	SSLv3.		
	<i>TLSv1</i>	TLSv1.		
	<i>TLSv1-1</i>	TLSv1.1.		
	<i>TLSv1-2</i>	TLSv1.2.		
cmp-save-extra-certs	Enable/disable saving extra certificates in CMP mode (default = disable).	option	-	disable
	Option Description			
	<i>enable</i>	Enable saving extra certificates in CMP mode.		
	<i>disable</i>	Disable saving extra certificates in CMP mode.		
cmp-key-usage-checking	Enable/disable server certificate key usage checking in CMP mode (default = enable).	option	-	enable
	Option Description			
	<i>enable</i>	Enable server certificate key usage checking in CMP mode.		
	<i>disable</i>	Disable server certificate key usage checking in CMP mode.		

Parameter	Description	Type	Size	Default
cert-expire-warning	Number of days before a certificate expires to send a warning. Set to 0 to disable sending of the warning (0 - 100, default = 14).	integer	Minimum value: 0 Maximum value: 100	14
certname-rsa1024	1024 bit RSA key certificate for re-signing server certificates for SSL inspection.	string	Maximum length: 35	Fortinet_SSL_RSA1024
certname-rsa2048	2048 bit RSA key certificate for re-signing server certificates for SSL inspection.	string	Maximum length: 35	Fortinet_SSL_RSA2048
certname-rsa4096	4096 bit RSA key certificate for re-signing server certificates for SSL inspection.	string	Maximum length: 35	Fortinet_SSL_RSA4096
certname-dsa1024	1024 bit DSA key certificate for re-signing server certificates for SSL inspection.	string	Maximum length: 35	Fortinet_SSL_DSA1024
certname-dsa2048	2048 bit DSA key certificate for re-signing server certificates for SSL inspection.	string	Maximum length: 35	Fortinet_SSL_DSA2048
certname-ecdsa256	256 bit ECDSA key certificate for re-signing server certificates for SSL inspection.	string	Maximum length: 35	Fortinet_SSL_ECDSA256
certname-ecdsa384	384 bit ECDSA key certificate for re-signing server certificates for SSL inspection.	string	Maximum length: 35	Fortinet_SSL_ECDSA384
certname-ecdsa521	521 bit ECDSA key certificate for re-signing server certificates for SSL inspection.	string	Maximum length: 35	Fortinet_SSL_ECDSA521
certname-ed25519	253 bit EdDSA key certificate for re-signing server certificates for SSL inspection.	string	Maximum length: 35	Fortinet_SSL_ED25519
certname-ed448	456 bit EdDSA key certificate for re-signing server certificates for SSL inspection.	string	Maximum length: 35	Fortinet_SSL_ED448

config crt-verification

Parameter	Description	Type	Size	Default
expiry	CRL verification option when CRL is expired (default = ignore).	option	-	ignore

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ignore</i></td><td>Certificate status will be verified even if CRL is expired.</td></tr><tr><td><i>revoke</i></td><td>Certificate will be revoked if CRL is expired.</td></tr></table>	Option	Description	<i>ignore</i>	Certificate status will be verified even if CRL is expired.	<i>revoke</i>	Certificate will be revoked if CRL is expired.			
Option	Description									
<i>ignore</i>	Certificate status will be verified even if CRL is expired.									
<i>revoke</i>	Certificate will be revoked if CRL is expired.									
leaf-crl-absence	CRL verification option when leaf CRL is absent (default = ignore).	option	-	ignore						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ignore</i></td><td>CRL verification against leaf certificate is ignored if CRL is absent.</td></tr><tr><td><i>revoke</i></td><td>Certificate will be revoked if CRL of leaf certificate is absent.</td></tr></table>	Option	Description	<i>ignore</i>	CRL verification against leaf certificate is ignored if CRL is absent.	<i>revoke</i>	Certificate will be revoked if CRL of leaf certificate is absent.			
Option	Description									
<i>ignore</i>	CRL verification against leaf certificate is ignored if CRL is absent.									
<i>revoke</i>	Certificate will be revoked if CRL of leaf certificate is absent.									
chain-crl-absence	CRL verification option when CRL of any certificate in chain is absent (default = ignore).	option	-	ignore						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ignore</i></td><td>CRL verification is ignored if CRL of any certificate in chain is absent.</td></tr><tr><td><i>revoke</i></td><td>Certificate will be revoked if CRL of any certificate in chain is absent.</td></tr></table>	Option	Description	<i>ignore</i>	CRL verification is ignored if CRL of any certificate in chain is absent.	<i>revoke</i>	Certificate will be revoked if CRL of any certificate in chain is absent.			
Option	Description									
<i>ignore</i>	CRL verification is ignored if CRL of any certificate in chain is absent.									
<i>revoke</i>	Certificate will be revoked if CRL of any certificate in chain is absent.									

config vpn ipsec phase1-interface

Configure VPN remote gateway.

```

config vpn ipsec phase1-interface
  Description: Configure VPN remote gateway.
  edit <name>
    set interface {string}
    set ike-version [1|2]
    set local-gw {ipv4-address}
    set remote-gw {ipv4-address}
    set keylife {integer}
    set certificate <name1>, <name2>, ...
    set authmethod [psk|signature]
    set mode [aggressive|main]
    set peertype {option}
    set peerid {string}
    set peer {string}
    set packet-redistribution [enable|disable]
    set proposal {option1}, {option2}, ...
    set psksecret {password-3}
    set keepalive {integer}
    set distance {integer}
  
```



```

set priority {integer}
set localid {string}
set localid-type [auto|fqdn|...]
set negotiate-timeout {integer}
set fragmentation [enable|disable]
set comments {var-string}
set send-cert-chain [enable|disable]
set dhgrp {option1}, {option2}, ...
set mobike [enable|disable]
set eap [enable|disable]
set eap-identity [use-id-payload|send-request]
set eap-exclude-peergrp {string}
set acct-verify [enable|disable]
set ppk [disable|allow|...]
set ppk-secret {password-3}
set ppk-identity {string}
set wizard-type [custom|dialup-forticlient|...]
set xauthtype [disable|client|...]
set reauth [disable|enable]
set authusr {string}
set authpasswd {password}
set group-authentication [enable|disable]
set group-authentication-secret {password-3}
set authusrgrp {string}
set idle-timeout [enable|disable]
set idle-timeoutinterval {integer}
set fgsp-sync [enable|disable]
set inbound-dscp-copy [enable|disable]
set auto-discovery-sender [enable|disable]
set auto-discovery-receiver [enable|disable]
set auto-discovery-forwarder [enable|disable]
set auto-discovery-psk [enable|disable]
set auto-discovery-shortcuts [independent|dependent]
set auto-discovery-crossover [allow|block]
set auto-discovery-offer-interval {integer}
set fragmentation-mtu {integer}
set childless-ike [enable|disable]
set azure-ad-autoconnect [enable|disable]
set rekey [enable|disable]
set digital-signature-auth [enable|disable]
set signature-hash-alg {option1}, {option2}, ...
set rsa-signature-format [pkcs1|pss]
set rsa-signature-hash-override [enable|disable]
set enforce-unique-id [disable|keep-new|...]
set cert-id-validation [enable|disable]
set network-overlay [disable|enable]
set network-id {integer}
set dev-id-notification [disable|enable]
set dev-id {string}
set loopback-asymroute [enable|disable]
set link-cost {integer}
set exchange-fgt-device-id [enable|disable]

```

```

set ems-sn-check [enable|disable]
set remote-gw-match [any|ipmask|...]
set remote-gw-subnet {ipv4-classnet-any}
set remote-gw-start-ip {ipv4-address-any}
set remote-gw-end-ip {ipv4-address-any}
set remote-gw-country {string}
set remote-gw6-match [any|ipprefix|...]
set remote-gw6-subnet {ipv6-network}
set remote-gw6-start-ip {ipv6-address}
set remote-gw6-end-ip {ipv6-address}
set remote-gw6-country {string}
set cert-trust-store [local|ems]
next
end

```

config vpn ipsec phase1-interface

Parameter	Description	Type	Size	Default						
name	IPsec remote gateway name.	string	Maximum length: 15							
interface	Local physical, aggregate, or VLAN outgoing interface.	string	Maximum length: 35							
ike-version	IKE protocol version.	option	-	1						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>1</td><td>Use IKEv1 protocol.</td></tr><tr><td>2</td><td>Use IKEv2 protocol.</td></tr></table>				Option	Description	1	Use IKEv1 protocol.	2	Use IKEv2 protocol.
	Option	Description								
	1	Use IKEv1 protocol.								
2	Use IKEv2 protocol.									
local-gw	IPv4 address of the local gateway's external interface.	ipv4-address	Not Specified	0.0.0.0						
remote-gw	IPv4 address of the remote gateway's external interface.	ipv4-address	Not Specified	0.0.0.0						
keylife	Time to wait in seconds before phase 1 encryption key expires.	integer	Minimum value: 120 Maximum value: 172800	86400						
certificate <name>	The names of up to 4 signed personal certificates. Certificate name.	string	Maximum length: 79							
authmethod	Authentication method.	option	-	psk						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>psk</i>	PSK authentication method.		
	<i>signature</i>	Signature authentication method.		
mode	The ID protection mode used to establish a secure channel.	option	-	main
	Option	Description		
	<i>aggressive</i>	Aggressive mode.		
	<i>main</i>	Main mode.		
peertype	Accept this peer type.	option	-	
	Option	Description		
	<i>any</i>	Accept any peer ID.		
peerid	Accept this peer identity.	string	Maximum length: 255	
peer	Accept this peer certificate.	string	Maximum length: 35	
packet-redistribution	Enable/disable packet distribution (RPS) on the IPsec interface.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable packet redistribution.		
	<i>disable</i>	Disable packet redistribution.		
proposal	Phase1 proposal.	option	-	
	Option	Description		
	<i>des-md5</i>	des-md5		
	<i>des-sha1</i>	des-sha1		
	<i>des-sha256</i>	des-sha256		
	<i>des-sha384</i>	des-sha384		
	<i>des-sha512</i>	des-sha512		
	<i>3des-md5</i>	3des-md5		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>3des-sha1</i>	3des-sha1		
	<i>3des-sha256</i>	3des-sha256		
	<i>3des-sha384</i>	3des-sha384		
	<i>3des-sha512</i>	3des-sha512		
	<i>aes128-md5</i>	aes128-md5		
	<i>aes128-sha1</i>	aes128-sha1		
	<i>aes128-sha256</i>	aes128-sha256		
	<i>aes128-sha384</i>	aes128-sha384		
	<i>aes128-sha512</i>	aes128-sha512		
	<i>aes128gcm-prfsha1</i>	aes128gcm-prfsha1		
	<i>aes128gcm-prfsha256</i>	aes128gcm-prfsha256		
	<i>aes128gcm-prfsha384</i>	aes128gcm-prfsha384		
	<i>aes128gcm-prfsha512</i>	aes128gcm-prfsha512		
	<i>aes192-md5</i>	aes192-md5		
	<i>aes192-sha1</i>	aes192-sha1		
	<i>aes192-sha256</i>	aes192-sha256		
	<i>aes192-sha384</i>	aes192-sha384		
	<i>aes192-sha512</i>	aes192-sha512		
	<i>aes256-md5</i>	aes256-md5		
	<i>aes256-sha1</i>	aes256-sha1		
	<i>aes256-sha256</i>	aes256-sha256		
	<i>aes256-sha384</i>	aes256-sha384		
	<i>aes256-sha512</i>	aes256-sha512		
	<i>aes256gcm-prfsha1</i>	aes256gcm-prfsha1		
	<i>aes256gcm-prfsha256</i>	aes256gcm-prfsha256		
	<i>aes256gcm-prfsha384</i>	aes256gcm-prfsha384		

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>aes256gcm-prfsha512</i>	aes256gcm-prfsha512		
	<i>chacha20poly1305-prfsha1</i>	chacha20poly1305-prfsha1		
	<i>chacha20poly1305-prfsha256</i>	chacha20poly1305-prfsha256		
	<i>chacha20poly1305-prfsha384</i>	chacha20poly1305-prfsha384		
	<i>chacha20poly1305-prfsha512</i>	chacha20poly1305-prfsha512		
	<i>aria128-md5</i>	aria128-md5		
	<i>aria128-sha1</i>	aria128-sha1		
	<i>aria128-sha256</i>	aria128-sha256		
	<i>aria128-sha384</i>	aria128-sha384		
	<i>aria128-sha512</i>	aria128-sha512		
	<i>aria192-md5</i>	aria192-md5		
	<i>aria192-sha1</i>	aria192-sha1		
	<i>aria192-sha256</i>	aria192-sha256		
	<i>aria192-sha384</i>	aria192-sha384		
	<i>aria192-sha512</i>	aria192-sha512		
	<i>aria256-md5</i>	aria256-md5		
	<i>aria256-sha1</i>	aria256-sha1		
	<i>aria256-sha256</i>	aria256-sha256		
	<i>aria256-sha384</i>	aria256-sha384		
	<i>aria256-sha512</i>	aria256-sha512		
	<i>seed-md5</i>	seed-md5		
	<i>seed-sha1</i>	seed-sha1		
	<i>seed-sha256</i>	seed-sha256		
	<i>seed-sha384</i>	seed-sha384		
	<i>seed-sha512</i>	seed-sha512		

Parameter	Description	Type	Size	Default														
psksecret	Pre-shared secret for PSK authentication (ASCII string or hexadecimal encoded with a leading 0x).	password-3	Not Specified															
keepalive	NAT-T keep alive interval.	integer	Minimum value: 10 Maximum value: 900	10														
distance	Distance for routes added by IKE (1 - 255).	integer	Minimum value: 1 Maximum value: 255	15														
priority	Priority for routes added by IKE (1 - 65535).	integer	Minimum value: 1 Maximum value: 65535	1														
localid	Local ID.	string	Maximum length: 63															
localid-type	Local ID type.	option	-	auto														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>auto</td><td>Select ID type automatically.</td></tr><tr><td>fqdn</td><td>Use fully qualified domain name.</td></tr><tr><td>user-fqdn</td><td>Use user fully qualified domain name.</td></tr><tr><td>keyid</td><td>Use key-id string.</td></tr><tr><td>address</td><td>Use local IP address.</td></tr><tr><td>asn1dn</td><td>Use ASN.1 distinguished name.</td></tr></table>				Option	Description	auto	Select ID type automatically.	fqdn	Use fully qualified domain name.	user-fqdn	Use user fully qualified domain name.	keyid	Use key-id string.	address	Use local IP address.	asn1dn	Use ASN.1 distinguished name.
	Option	Description																
	auto	Select ID type automatically.																
	fqdn	Use fully qualified domain name.																
	user-fqdn	Use user fully qualified domain name.																
	keyid	Use key-id string.																
	address	Use local IP address.																
asn1dn	Use ASN.1 distinguished name.																	
negotiate-timeout	IKE SA negotiation timeout in seconds (1 - 300).	integer	Minimum value: 1 Maximum value: 300	30														
fragmentation	Enable/disable fragment IKE message on re-transmission.	option	-	enable														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable intra-IKE fragmentation support on re-transmission.</td></tr><tr><td>disable</td><td>Disable intra-IKE fragmentation support.</td></tr></table>				Option	Description	enable	Enable intra-IKE fragmentation support on re-transmission.	disable	Disable intra-IKE fragmentation support.								
	Option	Description																
	enable	Enable intra-IKE fragmentation support on re-transmission.																
disable	Disable intra-IKE fragmentation support.																	

Parameter	Description	Type	Size	Default
comments	Comment.	var-string	Maximum length: 255	
send-cert-chain	Enable/disable sending certificate chain.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable sending certificate chain.		
	<i>disable</i>	Disable sending certificate chain.		
dhgrp	DH group.	option	-	14
	Option	Description		
	1	DH Group 1.		
	2	DH Group 2.		
	5	DH Group 5.		
	14	DH Group 14.		
	15	DH Group 15.		
	16	DH Group 16.		
	17	DH Group 17.		
	18	DH Group 18.		
	19	DH Group 19.		
	20	DH Group 20.		
	21	DH Group 21.		
	27	DH Group 27.		
	28	DH Group 28.		
	29	DH Group 29.		
	30	DH Group 30.		
	31	DH Group 31.		
	32	DH Group 32.		
mobike	IKEv2 MOBILE.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable MOBIKE on IKEv2 connections.		
	<i>disable</i>	Disable MOBIKE on IKEv2 connections.		

Parameter	Description	Type	Size	Default
eap	Enable/disable IKEv2 EAP authentication.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable IKEv2 EAP authentication.		
	<i>disable</i>	Disable IKEv2 EAP authentication.		
eap-identity	IKEv2 EAP peer identity type.	option	-	use-id-payload
	Option	Description		
	<i>use-id-payload</i>	Use IKEv2 IDi payload to resolve peer identity.		
	<i>send-request</i>	Use EAP identity request to resolve peer identity.		
eap-exclude-peergrp	Peer group excluded from EAP authentication.	string	Maximum length: 35	
acct-verify	Enable/disable verification of RADIUS accounting record.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable verification of RADIUS accounting record.		
	<i>disable</i>	Disable verification of RADIUS accounting record.		
ppk	Enable/disable IKEv2 Postquantum Preshared Key (PPK).	option	-	disable
	Option	Description		
	<i>disable</i>	Disable use of IKEv2 Postquantum Preshared Key (PPK).		
	<i>allow</i>	Allow, but do not require, use of IKEv2 Postquantum Preshared Key (PPK).		
	<i>require</i>	Require use of IKEv2 Postquantum Preshared Key (PPK).		
ppk-secret	IKEv2 Postquantum Preshared Key (ASCII string or hexadecimal encoded with a leading 0x).	password-3	Not Specified	
ppk-identity	IKEv2 Postquantum Preshared Key Identity.	string	Maximum length: 35	
wizard-type	GUI VPN Wizard Type.	option	-	custom

Parameter	Description	Type	Size	Default																												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>custom</i></td><td>Custom VPN configuration.</td></tr><tr><td><i>dialup-forticlient</i></td><td>Dial Up - FortiClient Windows, Mac and Android.</td></tr><tr><td><i>dialup-ios</i></td><td>Dial Up - iPhone / iPad Native IPsec Client.</td></tr><tr><td><i>dialup-android</i></td><td>Dial Up - Android Native IPsec Client.</td></tr><tr><td><i>dialup-windows</i></td><td>Dial Up - Windows Native IPsec Client.</td></tr><tr><td><i>dialup-cisco</i></td><td>Dial Up - Cisco IPsec Client.</td></tr><tr><td><i>static-fortiproxy</i></td><td>Site to Site - FortiProxy.</td></tr><tr><td><i>dialup-fortiproxy</i></td><td>Dial Up - FortiProxy.</td></tr><tr><td><i>static-cisco</i></td><td>Site to Site - Cisco.</td></tr><tr><td><i>dialup-cisco-fw</i></td><td>Dialup Up - Cisco Firewall.</td></tr><tr><td><i>simplified-static-fortiproxy</i></td><td>Site to Site - FortiProxy (SD-WAN).</td></tr><tr><td><i>hub-fortiproxy-auto-discovery</i></td><td>Hub role in a Hub-and-Spoke auto-discovery VPN.</td></tr><tr><td><i>spoke-fortiproxy-auto-discovery</i></td><td>Spoke role in a Hub-and-Spoke auto-discovery VPN.</td></tr></table>	Option	Description	<i>custom</i>	Custom VPN configuration.	<i>dialup-forticlient</i>	Dial Up - FortiClient Windows, Mac and Android.	<i>dialup-ios</i>	Dial Up - iPhone / iPad Native IPsec Client.	<i>dialup-android</i>	Dial Up - Android Native IPsec Client.	<i>dialup-windows</i>	Dial Up - Windows Native IPsec Client.	<i>dialup-cisco</i>	Dial Up - Cisco IPsec Client.	<i>static-fortiproxy</i>	Site to Site - FortiProxy.	<i>dialup-fortiproxy</i>	Dial Up - FortiProxy.	<i>static-cisco</i>	Site to Site - Cisco.	<i>dialup-cisco-fw</i>	Dialup Up - Cisco Firewall.	<i>simplified-static-fortiproxy</i>	Site to Site - FortiProxy (SD-WAN).	<i>hub-fortiproxy-auto-discovery</i>	Hub role in a Hub-and-Spoke auto-discovery VPN.	<i>spoke-fortiproxy-auto-discovery</i>	Spoke role in a Hub-and-Spoke auto-discovery VPN.			
	Option	Description																														
	<i>custom</i>	Custom VPN configuration.																														
	<i>dialup-forticlient</i>	Dial Up - FortiClient Windows, Mac and Android.																														
	<i>dialup-ios</i>	Dial Up - iPhone / iPad Native IPsec Client.																														
	<i>dialup-android</i>	Dial Up - Android Native IPsec Client.																														
	<i>dialup-windows</i>	Dial Up - Windows Native IPsec Client.																														
	<i>dialup-cisco</i>	Dial Up - Cisco IPsec Client.																														
	<i>static-fortiproxy</i>	Site to Site - FortiProxy.																														
	<i>dialup-fortiproxy</i>	Dial Up - FortiProxy.																														
	<i>static-cisco</i>	Site to Site - Cisco.																														
	<i>dialup-cisco-fw</i>	Dialup Up - Cisco Firewall.																														
	<i>simplified-static-fortiproxy</i>	Site to Site - FortiProxy (SD-WAN).																														
	<i>hub-fortiproxy-auto-discovery</i>	Hub role in a Hub-and-Spoke auto-discovery VPN.																														
<i>spoke-fortiproxy-auto-discovery</i>	Spoke role in a Hub-and-Spoke auto-discovery VPN.																															
xauthtype	XAuth type.	option	-	disable																												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable.</td></tr><tr><td><i>client</i></td><td>Enable as client.</td></tr><tr><td><i>pap</i></td><td>Enable as server PAP.</td></tr><tr><td><i>chap</i></td><td>Enable as server CHAP.</td></tr><tr><td><i>auto</i></td><td>Enable as server auto.</td></tr></table>	Option	Description	<i>disable</i>	Disable.	<i>client</i>	Enable as client.	<i>pap</i>	Enable as server PAP.	<i>chap</i>	Enable as server CHAP.	<i>auto</i>	Enable as server auto.																			
	Option	Description																														
	<i>disable</i>	Disable.																														
	<i>client</i>	Enable as client.																														
	<i>pap</i>	Enable as server PAP.																														
	<i>chap</i>	Enable as server CHAP.																														
<i>auto</i>	Enable as server auto.																															

Parameter	Description	Type	Size	Default						
reauth	Enable/disable re-authentication upon IKE SA lifetime expiration.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable IKE SA re-authentication.</td></tr><tr><td><i>enable</i></td><td>Enable IKE SA re-authentication.</td></tr></table>	Option	Description	<i>disable</i>	Disable IKE SA re-authentication.	<i>enable</i>	Enable IKE SA re-authentication.			
Option	Description									
<i>disable</i>	Disable IKE SA re-authentication.									
<i>enable</i>	Enable IKE SA re-authentication.									
authusr	XAuth user name.	string	Maximum length: 64							
authpasswd	XAuth password (max 35 characters).	password	Not Specified							
group-authentication	Enable/disable IKEv2 IDi group authentication.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable IKEv2 IDi group authentication.</td></tr><tr><td><i>disable</i></td><td>Disable IKEv2 IDi group authentication.</td></tr></table>	Option	Description	<i>enable</i>	Enable IKEv2 IDi group authentication.	<i>disable</i>	Disable IKEv2 IDi group authentication.			
Option	Description									
<i>enable</i>	Enable IKEv2 IDi group authentication.									
<i>disable</i>	Disable IKEv2 IDi group authentication.									
group-authentication-secret	Password for IKEv2 ID group authentication. ASCII string or hexadecimal indicated by a leading 0x.	password-3	Not Specified							
authusrgrp	Authentication user group.	string	Maximum length: 35							
idle-timeout	Enable/disable IPsec tunnel idle timeout.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable IPsec tunnel idle timeout.</td></tr><tr><td><i>disable</i></td><td>Disable IPsec tunnel idle timeout.</td></tr></table>	Option	Description	<i>enable</i>	Enable IPsec tunnel idle timeout.	<i>disable</i>	Disable IPsec tunnel idle timeout.			
Option	Description									
<i>enable</i>	Enable IPsec tunnel idle timeout.									
<i>disable</i>	Disable IPsec tunnel idle timeout.									
idle-timeoutinterval	IPsec tunnel idle timeout in minutes (5 - 43200).	integer	Minimum value: 5 Maximum value: 43200	15						
fgsp-sync	Enable/disable IPsec syncing of tunnels for FGSP IPsec.	option	-	disable						

Parameter	Description	Type	Size	Default
	Option Description			
	<i>enable</i>	Enable IPsec syncing of tunnels to other cluster members.		
	<i>disable</i>	Disable IPsec syncing of tunnels to other cluster members.		
inbound-dscp-copy	Enable/disable copy the dscp in the ESP header to the inner IP Header.	option	-	disable
	Option Description			
	<i>enable</i>	Enable copy the dscp in the ESP header to the inner IP Header.		
	<i>disable</i>	Disable copy the dscp in the ESP header to the inner IP Header.		
auto-discovery-sender	Enable/disable sending auto-discovery short-cut messages.	option	-	disable
	Option Description			
	<i>enable</i>	Enable sending auto-discovery short-cut messages.		
	<i>disable</i>	Disable sending auto-discovery short-cut messages.		
auto-discovery-receiver	Enable/disable accepting auto-discovery short-cut messages.	option	-	disable
	Option Description			
	<i>enable</i>	Enable receiving auto-discovery short-cut messages.		
	<i>disable</i>	Disable receiving auto-discovery short-cut messages.		
auto-discovery-forwarder	Enable/disable forwarding auto-discovery short-cut messages.	option	-	disable
	Option Description			
	<i>enable</i>	Enable forwarding auto-discovery short-cut messages.		
	<i>disable</i>	Disable forwarding auto-discovery short-cut messages.		
auto-discovery-psk	Enable/disable use of pre-shared secrets for authentication of auto-discovery tunnels.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable use of pre-shared-secret authentication for auto-discovery tunnels.		
	<i>disable</i>	Disable use of authentication defined by 'authmethod' for auto-discovery tunnels.		
auto-discovery-shortcuts	Control deletion of child short-cut tunnels when the parent tunnel goes down.	option	-	independent
	Option	Description		
	<i>independent</i>	Short-cut tunnels remain up if the parent tunnel goes down.		
	<i>dependent</i>	Short-cut tunnels are brought down if the parent tunnel goes down.		
auto-discovery-crossover	Allow/block set-up of short-cut tunnels between different network IDs.	option	-	allow
	Option	Description		
	<i>allow</i>	Allow set-up of short-cut tunnels between different network IDs.		
	<i>block</i>	Block set-up of short-cut tunnels between different network IDs.		
auto-discovery-offer-interval	Interval between shortcut offer messages in seconds (1 - 300, default = 5).	integer	Minimum value: 1 Maximum value: 300	5
fragmentation-mtu	IKE fragmentation MTU (500 - 16000).	integer	Minimum value: 500 Maximum value: 16000	1200
childless-ike	Enable/disable childless IKEv2 initiation (RFC 6023).	option	-	disable
	Option	Description		
	<i>enable</i>	Enable childless IKEv2 initiation (RFC 6023).		
	<i>disable</i>	Disable childless IKEv2 initiation (RFC 6023).		

Parameter	Description	Type	Size	Default										
azure-ad-autoconnect	Enable/disable Azure AD Auto-Connect for FortiClient.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable Azure AD Auto-Connect for FortiClient.</td></tr><tr><td><i>disable</i></td><td>Disable Azure AD Auto-Connect for FortiClient.</td></tr></table>	Option	Description	<i>enable</i>	Enable Azure AD Auto-Connect for FortiClient.	<i>disable</i>	Disable Azure AD Auto-Connect for FortiClient.							
Option	Description													
<i>enable</i>	Enable Azure AD Auto-Connect for FortiClient.													
<i>disable</i>	Disable Azure AD Auto-Connect for FortiClient.													
rekey	Enable/disable phase1 rekey.	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable phase1 rekey.</td></tr><tr><td><i>disable</i></td><td>Disable phase1 rekey.</td></tr></table>	Option	Description	<i>enable</i>	Enable phase1 rekey.	<i>disable</i>	Disable phase1 rekey.							
Option	Description													
<i>enable</i>	Enable phase1 rekey.													
<i>disable</i>	Disable phase1 rekey.													
digital-signature-auth	Enable/disable IKEv2 Digital Signature Authentication (RFC 7427).	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable IKEv2 Digital Signature Authentication (RFC 7427).</td></tr><tr><td><i>disable</i></td><td>Disable IKEv2 Digital Signature Authentication (RFC 7427).</td></tr></table>	Option	Description	<i>enable</i>	Enable IKEv2 Digital Signature Authentication (RFC 7427).	<i>disable</i>	Disable IKEv2 Digital Signature Authentication (RFC 7427).							
Option	Description													
<i>enable</i>	Enable IKEv2 Digital Signature Authentication (RFC 7427).													
<i>disable</i>	Disable IKEv2 Digital Signature Authentication (RFC 7427).													
signature-hash-alg	Digital Signature Authentication hash algorithms.	option	-	sha2-512										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>sha1</i></td><td>SHA1.</td></tr><tr><td><i>sha2-256</i></td><td>SHA2-256.</td></tr><tr><td><i>sha2-384</i></td><td>SHA2-384.</td></tr><tr><td><i>sha2-512</i></td><td>SHA2-512.</td></tr></table>	Option	Description	<i>sha1</i>	SHA1.	<i>sha2-256</i>	SHA2-256.	<i>sha2-384</i>	SHA2-384.	<i>sha2-512</i>	SHA2-512.			
Option	Description													
<i>sha1</i>	SHA1.													
<i>sha2-256</i>	SHA2-256.													
<i>sha2-384</i>	SHA2-384.													
<i>sha2-512</i>	SHA2-512.													
rsa-signature-format	Digital Signature Authentication RSA signature format.	option	-	pkcs1										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>pkcs1</i></td><td>RSASSA PKCS#1 v1.5.</td></tr><tr><td><i>pss</i></td><td>RSASSA Probabilistic Signature Scheme (PSS).</td></tr></table>	Option	Description	<i>pkcs1</i>	RSASSA PKCS#1 v1.5.	<i>pss</i>	RSASSA Probabilistic Signature Scheme (PSS).							
Option	Description													
<i>pkcs1</i>	RSASSA PKCS#1 v1.5.													
<i>pss</i>	RSASSA Probabilistic Signature Scheme (PSS).													
rsa-signature-hash-override	Enable/disable IKEv2 RSA signature hash algorithm override.	option	-	disable										

Parameter	Description	Type	Size	Default								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable IKEv2 RSA signature hash algorithm override.</td></tr><tr><td><i>disable</i></td><td>Disable IKEv2 RSA signature hash algorithm override.</td></tr></table>	Option	Description	<i>enable</i>	Enable IKEv2 RSA signature hash algorithm override.	<i>disable</i>	Disable IKEv2 RSA signature hash algorithm override.					
	Option	Description										
	<i>enable</i>	Enable IKEv2 RSA signature hash algorithm override.										
<i>disable</i>	Disable IKEv2 RSA signature hash algorithm override.											
enforce-unique-id	Enable/disable peer ID uniqueness check.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable peer ID uniqueness enforcement.</td></tr><tr><td><i>keep-new</i></td><td>Enforce peer ID uniqueness, keep new connection if collision found.</td></tr><tr><td><i>keep-old</i></td><td>Enforce peer ID uniqueness, keep old connection if collision found.</td></tr></table>	Option	Description	<i>disable</i>	Disable peer ID uniqueness enforcement.	<i>keep-new</i>	Enforce peer ID uniqueness, keep new connection if collision found.	<i>keep-old</i>	Enforce peer ID uniqueness, keep old connection if collision found.			
	Option	Description										
	<i>disable</i>	Disable peer ID uniqueness enforcement.										
	<i>keep-new</i>	Enforce peer ID uniqueness, keep new connection if collision found.										
<i>keep-old</i>	Enforce peer ID uniqueness, keep old connection if collision found.											
cert-id-validation	Enable/disable cross validation of peer ID and the identity in the peer's certificate as specified in RFC 4945.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable cross validation of peer ID and the identity in the peer's certificate as specified in RFC 4945.</td></tr><tr><td><i>disable</i></td><td>Disable cross validation of peer ID and the identity in the peer's certificate as specified in RFC 4945.</td></tr></table>	Option	Description	<i>enable</i>	Enable cross validation of peer ID and the identity in the peer's certificate as specified in RFC 4945.	<i>disable</i>	Disable cross validation of peer ID and the identity in the peer's certificate as specified in RFC 4945.					
	Option	Description										
	<i>enable</i>	Enable cross validation of peer ID and the identity in the peer's certificate as specified in RFC 4945.										
<i>disable</i>	Disable cross validation of peer ID and the identity in the peer's certificate as specified in RFC 4945.											
network-overlay	Enable/disable network overlays.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable network overlays.</td></tr><tr><td><i>enable</i></td><td>Enable network overlays.</td></tr></table>	Option	Description	<i>disable</i>	Disable network overlays.	<i>enable</i>	Enable network overlays.					
	Option	Description										
	<i>disable</i>	Disable network overlays.										
<i>enable</i>	Enable network overlays.											
network-id	VPN gateway network ID.	integer	Minimum value: 0 Maximum value: 255	0								
dev-id-notification	Enable/disable device ID notification.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable device ID notification.</td></tr><tr><td><i>enable</i></td><td>Enable device ID notification.</td></tr></table>	Option	Description	<i>disable</i>	Disable device ID notification.	<i>enable</i>	Enable device ID notification.					
	Option	Description										
	<i>disable</i>	Disable device ID notification.										
<i>enable</i>	Enable device ID notification.											

Parameter	Description	Type	Size	Default										
dev-id	Device ID carried by the device ID notification.	string	Maximum length: 63											
loopback-asymroute	Enable/disable asymmetric routing for IKE traffic on loopback interface.	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Allow ingress/egress IKE traffic to be routed over different interfaces.</td></tr><tr><td><i>disable</i></td><td>Ingress/egress IKE traffic must be routed over the same interface.</td></tr></table>	Option	Description	<i>enable</i>	Allow ingress/egress IKE traffic to be routed over different interfaces.	<i>disable</i>	Ingress/egress IKE traffic must be routed over the same interface.							
Option	Description													
<i>enable</i>	Allow ingress/egress IKE traffic to be routed over different interfaces.													
<i>disable</i>	Ingress/egress IKE traffic must be routed over the same interface.													
link-cost	VPN tunnel underlay link cost.	integer	Minimum value: 0 Maximum value: 255	0										
exchange-fgt-device-id	Enable/disable device identifier exchange with peer FortiGate units for use of VPN monitor data by FortiManager.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable exchange of FortiProxy device identifier.</td></tr><tr><td><i>disable</i></td><td>Disable exchange of FortiProxy device identifier.</td></tr></table>	Option	Description	<i>enable</i>	Enable exchange of FortiProxy device identifier.	<i>disable</i>	Disable exchange of FortiProxy device identifier.							
Option	Description													
<i>enable</i>	Enable exchange of FortiProxy device identifier.													
<i>disable</i>	Disable exchange of FortiProxy device identifier.													
ems-sn-check	Enable/disable verification of EMS serial number.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable EMS serial number verification.</td></tr><tr><td><i>disable</i></td><td>Disable EMS serial number verification.</td></tr></table>	Option	Description	<i>enable</i>	Enable EMS serial number verification.	<i>disable</i>	Disable EMS serial number verification.							
Option	Description													
<i>enable</i>	Enable EMS serial number verification.													
<i>disable</i>	Disable EMS serial number verification.													
remote-gw-match	Set type of IPv4 remote gateway address matching.	option	-	any										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>any</i></td><td>Match any IPv4 gateway address.</td></tr><tr><td><i>ipmask</i></td><td>Match IPv4 gateway address and mask.</td></tr><tr><td><i>iprange</i></td><td>Match IPv4 gateway address range.</td></tr><tr><td><i>geography</i></td><td>Match IPv4 gateway address from a specified country.</td></tr></table>	Option	Description	<i>any</i>	Match any IPv4 gateway address.	<i>ipmask</i>	Match IPv4 gateway address and mask.	<i>iprange</i>	Match IPv4 gateway address range.	<i>geography</i>	Match IPv4 gateway address from a specified country.			
Option	Description													
<i>any</i>	Match any IPv4 gateway address.													
<i>ipmask</i>	Match IPv4 gateway address and mask.													
<i>iprange</i>	Match IPv4 gateway address range.													
<i>geography</i>	Match IPv4 gateway address from a specified country.													

Parameter	Description	Type	Size	Default										
remote-gw-subnet	IPv4 address and subnet mask.	ipv4-classnet-any	Not Specified	0.0.0.0 0.0.0.0										
remote-gw-start-ip	First IPv4 address in the range.	ipv4-address-any	Not Specified	0.0.0.0										
remote-gw-end-ip	Last IPv4 address in the range.	ipv4-address-any	Not Specified	0.0.0.0										
remote-gw-country	IPv4 addresses associated to a specific country.	string	Maximum length: 2											
remote-gw6-match	Set type of IPv6 remote gateway address matching.	option	-	any										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>any</i></td><td>Match any IPv6 gateway address.</td></tr><tr><td><i>ipprefix</i></td><td>Match IPv6 gateway address and prefix.</td></tr><tr><td><i>iprange</i></td><td>Match IPv6 gateway address range.</td></tr><tr><td><i>geography</i></td><td>Match IPv6 gateway address from a specified country.</td></tr></table>				Option	Description	<i>any</i>	Match any IPv6 gateway address.	<i>ipprefix</i>	Match IPv6 gateway address and prefix.	<i>iprange</i>	Match IPv6 gateway address range.	<i>geography</i>	Match IPv6 gateway address from a specified country.
Option	Description													
<i>any</i>	Match any IPv6 gateway address.													
<i>ipprefix</i>	Match IPv6 gateway address and prefix.													
<i>iprange</i>	Match IPv6 gateway address range.													
<i>geography</i>	Match IPv6 gateway address from a specified country.													
remote-gw6-subnet	IPv6 address and prefix.	ipv6-network	Not Specified	::/0										
remote-gw6-start-ip	First IPv6 address in the range.	ipv6-address	Not Specified	::										
remote-gw6-end-ip	Last IPv6 address in the range.	ipv6-address	Not Specified	::										
remote-gw6-country	IPv6 addresses associated to a specific country.	string	Maximum length: 2											
cert-trust-store	CA certificate trust store.	option	-	local										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>local</i></td><td>Use local CA certificate.</td></tr><tr><td><i>ems</i></td><td>Use EMS CA certificate.</td></tr></table>				Option	Description	<i>local</i>	Use local CA certificate.	<i>ems</i>	Use EMS CA certificate.				
Option	Description													
<i>local</i>	Use local CA certificate.													
<i>ems</i>	Use EMS CA certificate.													

config vpn ipsec phase2-interface

Configure VPN autokey tunnel.

```
config vpn ipsec phase2-interface
    Description: Configure VPN autokey tunnel.
```



```

edit <name>
    set phase1name {string}
    set proposal {option1}, {option2}, ...
    set dhgrp {option1}, {option2}, ...
    set replay [enable|disable]
    set keepalive [enable|disable]
    set auto-negotiate [enable|disable]
    set add-route [phase1|enable|...]
    set inbound-dscp-copy [phase1|enable|...]
    set auto-discovery-sender [phase1|enable|...]
    set auto-discovery-forwarder [phase1|enable|...]
    set keylifeseconds {integer}
    set keylifekbs {integer}
    set keylife-type [seconds|kbs|...]
    set single-source [enable|disable]
    set route-overlap [use-old|use-new|...]
    set comments {var-string}
    set protocol {integer}
    set src-name {string}
    set src-name6 {string}
    set src-addr-type [subnet|range|...]
    set src-start-ip {ipv4-address-any}
    set src-start-ip6 {ipv6-address}
    set src-end-ip {ipv4-address-any}
    set src-end-ip6 {ipv6-address}
    set src-subnet {ipv4-classnet-any}
    set src-subnet6 {ipv6-prefix}
    set src-port {integer}
    set dst-name {string}
    set dst-name6 {string}
    set dst-addr-type [subnet|range|...]
    set dst-start-ip {ipv4-address-any}
    set dst-start-ip6 {ipv6-address}
    set dst-end-ip {ipv4-address-any}
    set dst-end-ip6 {ipv6-address}
    set dst-subnet {ipv4-classnet-any}
    set dst-subnet6 {ipv6-prefix}
    set dst-port {integer}
next
end

```

config vpn ipsec phase2-interface

Parameter	Description	Type	Size	Default
name	IPsec tunnel name.	string	Maximum length: 35	
phase1name	Phase 1 determines the options required for phase 2.	string	Maximum length: 15	

Parameter	Description	Type	Size	Default
proposal	Phase2 proposal.	option	-	
	Option	Description		
	<i>null-md5</i>	null-md5		
	<i>null-sha1</i>	null-sha1		
	<i>null-sha256</i>	null-sha256		
	<i>null-sha384</i>	null-sha384		
	<i>null-sha512</i>	null-sha512		
	<i>des-null</i>	des-null		
	<i>des-md5</i>	des-md5		
	<i>des-sha1</i>	des-sha1		
	<i>des-sha256</i>	des-sha256		
	<i>des-sha384</i>	des-sha384		
	<i>des-sha512</i>	des-sha512		
	<i>3des-null</i>	3des-null		
	<i>3des-md5</i>	3des-md5		
	<i>3des-sha1</i>	3des-sha1		
	<i>3des-sha256</i>	3des-sha256		
	<i>3des-sha384</i>	3des-sha384		
	<i>3des-sha512</i>	3des-sha512		
	<i>aes128-null</i>	aes128-null		
	<i>aes128-md5</i>	aes128-md5		
	<i>aes128-sha1</i>	aes128-sha1		
	<i>aes128-sha256</i>	aes128-sha256		
	<i>aes128-sha384</i>	aes128-sha384		
	<i>aes128-sha512</i>	aes128-sha512		
	<i>aes128gcm</i>	aes128gcm		
	<i>aes192-null</i>	aes192-null		
	<i>aes192-md5</i>	aes192-md5		
	<i>aes192-sha1</i>	aes192-sha1		
	<i>aes192-sha256</i>	aes192-sha256		

Parameter	Description	Type	Size	Default

Option	Description
<i>aes192-sha384</i>	aes192-sha384
<i>aes192-sha512</i>	aes192-sha512
<i>aes256-null</i>	aes256-null
<i>aes256-md5</i>	aes256-md5
<i>aes256-sha1</i>	aes256-sha1
<i>aes256-sha256</i>	aes256-sha256
<i>aes256-sha384</i>	aes256-sha384
<i>aes256-sha512</i>	aes256-sha512
<i>aes256gcm</i>	aes256gcm
<i>chacha20poly1305</i>	chacha20poly1305
<i>aria128-null</i>	aria128-null
<i>aria128-md5</i>	aria128-md5
<i>aria128-sha1</i>	aria128-sha1
<i>aria128-sha256</i>	aria128-sha256
<i>aria128-sha384</i>	aria128-sha384
<i>aria128-sha512</i>	aria128-sha512
<i>aria192-null</i>	aria192-null
<i>aria192-md5</i>	aria192-md5
<i>aria192-sha1</i>	aria192-sha1
<i>aria192-sha256</i>	aria192-sha256
<i>aria192-sha384</i>	aria192-sha384
<i>aria192-sha512</i>	aria192-sha512
<i>aria256-null</i>	aria256-null
<i>aria256-md5</i>	aria256-md5
<i>aria256-sha1</i>	aria256-sha1
<i>aria256-sha256</i>	aria256-sha256
<i>aria256-sha384</i>	aria256-sha384
<i>aria256-sha512</i>	aria256-sha512
<i>seed-null</i>	seed-null

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>seed-md5</i>	seed-md5		
	<i>seed-sha1</i>	seed-sha1		
	<i>seed-sha256</i>	seed-sha256		
	<i>seed-sha384</i>	seed-sha384		
	<i>seed-sha512</i>	seed-sha512		
dhgrp	Phase2 DH group.	option	-	14
	Option	Description		
	1	DH Group 1.		
	2	DH Group 2.		
	5	DH Group 5.		
	14	DH Group 14.		
	15	DH Group 15.		
	16	DH Group 16.		
	17	DH Group 17.		
	18	DH Group 18.		
	19	DH Group 19.		
	20	DH Group 20.		
	21	DH Group 21.		
	27	DH Group 27.		
	28	DH Group 28.		
	29	DH Group 29.		
	30	DH Group 30.		
	31	DH Group 31.		
	32	DH Group 32.		
replay	Enable/disable replay detection.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

Parameter	Description	Type	Size	Default								
keepalive	Enable/disable keep alive.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.					
Option	Description											
<i>enable</i>	Enable setting.											
<i>disable</i>	Disable setting.											
auto-negotiate	Enable/disable IPsec SA auto-negotiation.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.					
Option	Description											
<i>enable</i>	Enable setting.											
<i>disable</i>	Disable setting.											
add-route	Enable/disable automatic route addition.	option	-	phase1								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>phase1</i></td><td>Add route according to phase1 add-route setting.</td></tr><tr><td><i>enable</i></td><td>Add route for remote proxy ID.</td></tr><tr><td><i>disable</i></td><td>Do not add route for remote proxy ID.</td></tr></table>	Option	Description	<i>phase1</i>	Add route according to phase1 add-route setting.	<i>enable</i>	Add route for remote proxy ID.	<i>disable</i>	Do not add route for remote proxy ID.			
Option	Description											
<i>phase1</i>	Add route according to phase1 add-route setting.											
<i>enable</i>	Add route for remote proxy ID.											
<i>disable</i>	Do not add route for remote proxy ID.											
inbound-dscp-copy	Enable/disable copying of the DSCP in the ESP header to the inner IP header.	option	-	phase1								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>phase1</i></td><td>copy the DCSP in the ESP header to the inner IP Header according to the phase1 inbound_dscp_copy setting.</td></tr><tr><td><i>enable</i></td><td>Enable copying of the DSCP in the ESP header to the inner IP header.</td></tr><tr><td><i>disable</i></td><td>Disable copying of the DSCP in the ESP header to the inner IP header.</td></tr></table>	Option	Description	<i>phase1</i>	copy the DCSP in the ESP header to the inner IP Header according to the phase1 inbound_dscp_copy setting.	<i>enable</i>	Enable copying of the DSCP in the ESP header to the inner IP header.	<i>disable</i>	Disable copying of the DSCP in the ESP header to the inner IP header.			
Option	Description											
<i>phase1</i>	copy the DCSP in the ESP header to the inner IP Header according to the phase1 inbound_dscp_copy setting.											
<i>enable</i>	Enable copying of the DSCP in the ESP header to the inner IP header.											
<i>disable</i>	Disable copying of the DSCP in the ESP header to the inner IP header.											
auto-discovery-sender	Enable/disable sending short-cut messages.	option	-	phase1								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>phase1</i></td><td>Send short-cut messages according to the phase1 auto-discovery-sender setting.</td></tr><tr><td><i>enable</i></td><td>Enable sending auto-discovery short-cut messages.</td></tr><tr><td><i>disable</i></td><td>Disable sending auto-discovery short-cut messages.</td></tr></table>	Option	Description	<i>phase1</i>	Send short-cut messages according to the phase1 auto-discovery-sender setting.	<i>enable</i>	Enable sending auto-discovery short-cut messages.	<i>disable</i>	Disable sending auto-discovery short-cut messages.			
Option	Description											
<i>phase1</i>	Send short-cut messages according to the phase1 auto-discovery-sender setting.											
<i>enable</i>	Enable sending auto-discovery short-cut messages.											
<i>disable</i>	Disable sending auto-discovery short-cut messages.											

Parameter	Description	Type	Size	Default								
auto-discovery-forwarder	Enable/disable forwarding short-cut messages.	option	-	phase1								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>phase1</i></td><td>Forward short-cut messages according to the phase1 auto-discovery-forwarder setting.</td></tr><tr><td><i>enable</i></td><td>Enable forwarding auto-discovery short-cut messages.</td></tr><tr><td><i>disable</i></td><td>Disable forwarding auto-discovery short-cut messages.</td></tr></table>	Option	Description	<i>phase1</i>	Forward short-cut messages according to the phase1 auto-discovery-forwarder setting.	<i>enable</i>	Enable forwarding auto-discovery short-cut messages.	<i>disable</i>	Disable forwarding auto-discovery short-cut messages.			
Option	Description											
<i>phase1</i>	Forward short-cut messages according to the phase1 auto-discovery-forwarder setting.											
<i>enable</i>	Enable forwarding auto-discovery short-cut messages.											
<i>disable</i>	Disable forwarding auto-discovery short-cut messages.											
keylifeseconds	Phase2 key life in time in seconds (120 - 172800).	integer	Minimum value: 120 Maximum value: 172800	43200								
keylifekbs	Phase2 key life in number of kilobytes of traffic (5120 - 4294967295).	integer	Minimum value: 5120 Maximum value: 4294967295	5120								
keylife-type	Keylife type.	option	-	seconds								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>seconds</i></td><td>Key life in seconds.</td></tr><tr><td><i>kbs</i></td><td>Key life in kilobytes.</td></tr><tr><td><i>both</i></td><td>Key life both.</td></tr></table>	Option	Description	<i>seconds</i>	Key life in seconds.	<i>kbs</i>	Key life in kilobytes.	<i>both</i>	Key life both.			
Option	Description											
<i>seconds</i>	Key life in seconds.											
<i>kbs</i>	Key life in kilobytes.											
<i>both</i>	Key life both.											
single-source	Enable/disable single source IP restriction.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Only single source IP will be accepted.</td></tr><tr><td><i>disable</i></td><td>Source IP range will be accepted.</td></tr></table>	Option	Description	<i>enable</i>	Only single source IP will be accepted.	<i>disable</i>	Source IP range will be accepted.					
Option	Description											
<i>enable</i>	Only single source IP will be accepted.											
<i>disable</i>	Source IP range will be accepted.											
route-overlap	Action for overlapping routes.	option	-	use-new								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>use-old</i></td><td>Use the old route and do not add the new route.</td></tr><tr><td><i>use-new</i></td><td>Delete the old route and add the new route.</td></tr><tr><td><i>allow</i></td><td>Allow overlapping routes.</td></tr></table>	Option	Description	<i>use-old</i>	Use the old route and do not add the new route.	<i>use-new</i>	Delete the old route and add the new route.	<i>allow</i>	Allow overlapping routes.			
Option	Description											
<i>use-old</i>	Use the old route and do not add the new route.											
<i>use-new</i>	Delete the old route and add the new route.											
<i>allow</i>	Allow overlapping routes.											

Parameter	Description	Type	Size	Default
comments	Comment.	var-string	Maximum length: 255	
protocol	Quick mode protocol selector (1 - 255 or 0 for all).	integer	Minimum value: 0 Maximum value: 255	0
src-name	Local proxy ID name.	string	Maximum length: 79	
src-name6	Local proxy ID name.	string	Maximum length: 79	
src-addr-type	Local proxy ID type.	option	-	subnet
	Option	Description		
	subnet	IPv4 subnet.		
	range	IPv4 range.		
	ip	IPv4 IP.		
	name	IPv4 firewall address or group name.		
	subnet6	IPv6 subnet.		
	range6	IPv6 range.		
	ip6	IPv6 IP.		
name6	IPv6 firewall address or group name.			
src-start-ip	Local proxy ID start.	ipv4-address-any	Not Specified	0.0.0.0
src-start-ip6	Local proxy ID IPv6 start.	ipv6-address	Not Specified	::
src-end-ip	Local proxy ID end.	ipv4-address-any	Not Specified	0.0.0.0
src-end-ip6	Local proxy ID IPv6 end.	ipv6-address	Not Specified	::
src-subnet	Local proxy ID subnet.	ipv4-classnet-any	Not Specified	0.0.0.0 0.0.0.0
src-subnet6	Local proxy ID IPv6 subnet.	ipv6-prefix	Not Specified	::/0

Parameter	Description	Type	Size	Default
src-port	Quick mode source port (1 - 65535 or 0 for all).	integer	Minimum value: 0 Maximum value: 65535	0
dst-name	Remote proxy ID name.	string	Maximum length: 79	
dst-name6	Remote proxy ID name.	string	Maximum length: 79	
dst-addr-type	Remote proxy ID type.	option	-	subnet
	Option		Description	
	<i>subnet</i>		IPv4 subnet.	
	<i>range</i>		IPv4 range.	
	<i>ip</i>		IPv4 IP.	
	<i>name</i>		IPv4 firewall address or group name.	
	<i>subnet6</i>		IPv6 subnet.	
	<i>range6</i>		IPv6 range.	
	<i>ip6</i>		IPv6 IP.	
	<i>name6</i>		IPv6 firewall address or group name.	
dst-start-ip	Remote proxy ID IPv4 start.	ipv4-address-any	Not Specified	0.0.0.0
dst-start-ip6	Remote proxy ID IPv6 start.	ipv6-address	Not Specified	::
dst-end-ip	Remote proxy ID IPv4 end.	ipv4-address-any	Not Specified	0.0.0.0
dst-end-ip6	Remote proxy ID IPv6 end.	ipv6-address	Not Specified	::
dst-subnet	Remote proxy ID IPv4 subnet.	ipv4-classnet-any	Not Specified	0.0.0.0 0.0.0.0
dst-subnet6	Remote proxy ID IPv6 subnet.	ipv6-prefix	Not Specified	::/0
dst-port	Quick mode destination port (1 - 65535 or 0 for all).	integer	Minimum value: 0 Maximum value: 65535	0

waf

This section includes syntax for the following commands:

- [config waf main-class on page 1217](#)
- [config waf profile on page 1217](#)
- [config waf signature on page 1242](#)
- [config waf sub-class on page 1243](#)

config waf main-class

Hidden table for datasource.

```
config waf main-class
  Description: Hidden table for datasource.
  edit <id>
    set name {string}
  next
end
```

config waf main-class

Parameter	Description	Type	Size	Default
name	Main signature class name.	string	Maximum length: 127	
id	Main signature class ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

config waf profile

Configure Web application firewall configuration.

```
config waf profile
  Description: Configure Web application firewall configuration.
  edit <name>
    set external [disable|enable]
```

```

set extended-log [enable|disable]
config signature
    Description: WAF signatures.
    config main-class
        Description: Main signature class.
        edit <id>
            set status [enable|disable]
            set action [allow|block|...]
            set log [enable|disable]
            set severity [high|medium|...]
        next
    end
    set disabled-sub-class <id1>, <id2>, ...
    set disabled-signature <id1>, <id2>, ...
    set credit-card-detection-threshold {integer}
    config custom-signature
        Description: Custom signature.
        edit <name>
            set status [enable|disable]
            set action [allow|block|...]
            set log [enable|disable]
            set severity [high|medium|...]
            set direction [request|response]
            set case-sensitivity [disable|enable]
            set pattern {string}
            set target {option1}, {option2}, ...
        next
    end
end
config constraint
    Description: WAF HTTP protocol restrictions.
    config header-length
        Description: HTTP header length in request.
        set status [enable|disable]
        set length {integer}
        set action [allow|block]
        set log [enable|disable]
        set severity [high|medium|...]
    end
    config content-length
        Description: HTTP content length in request.
        set status [enable|disable]
        set length {integer}
        set action [allow|block]
        set log [enable|disable]
        set severity [high|medium|...]
    end
    config param-length
        Description: Maximum length of parameter in URL, HTTP POST request or HTTP body.
        set status [enable|disable]
        set length {integer}
        set action [allow|block]

```

```

        set log [enable|disable]
        set severity [high|medium|...]
    end
    config line-length
        Description: HTTP line length in request.
        set status [enable|disable]
        set length {integer}
        set action [allow|block]
        set log [enable|disable]
        set severity [high|medium|...]
    end
    config url-param-length
        Description: Maximum length of parameter in URL.
        set status [enable|disable]
        set length {integer}
        set action [allow|block]
        set log [enable|disable]
        set severity [high|medium|...]
    end
    config version
        Description: Enable/disable HTTP version check.
        set status [enable|disable]
        set action [allow|block]
        set log [enable|disable]
        set severity [high|medium|...]
    end
    config method
        Description: Enable/disable HTTP method check.
        set status [enable|disable]
        set action [allow|block]
        set log [enable|disable]
        set severity [high|medium|...]
    end
    config hostname
        Description: Enable/disable hostname check.
        set status [enable|disable]
        set action [allow|block]
        set log [enable|disable]
        set severity [high|medium|...]
    end
    config malformed
        Description: Enable/disable malformed HTTP request check.
        set status [enable|disable]
        set action [allow|block]
        set log [enable|disable]
        set severity [high|medium|...]
    end
    config max-cookie
        Description: Maximum number of cookies in HTTP request.
        set status [enable|disable]
        set max-cookie {integer}
        set action [allow|block]

```

```

        set log [enable|disable]
        set severity [high|medium|...]
    end
    config max-header-line
        Description: Maximum number of HTTP header line.
        set status [enable|disable]
        set max-header-line {integer}
        set action [allow|block]
        set log [enable|disable]
        set severity [high|medium|...]
    end
    config max-url-param
        Description: Maximum number of parameters in URL.
        set status [enable|disable]
        set max-url-param {integer}
        set action [allow|block]
        set log [enable|disable]
        set severity [high|medium|...]
    end
    config max-range-segment
        Description: Maximum number of range segments in HTTP range line.
        set status [enable|disable]
        set max-range-segment {integer}
        set action [allow|block]
        set log [enable|disable]
        set severity [high|medium|...]
    end
    config exception
        Description: HTTP constraint exception.
        edit <id>
            set pattern {string}
            set regex [enable|disable]
            set address {string}
            set header-length [enable|disable]
            set content-length [enable|disable]
            set param-length [enable|disable]
            set line-length [enable|disable]
            set url-param-length [enable|disable]
            set version [enable|disable]
            set method [enable|disable]
            set hostname [enable|disable]
            set malformed [enable|disable]
            set max-cookie [enable|disable]
            set max-header-line [enable|disable]
            set max-url-param [enable|disable]
            set max-range-segment [enable|disable]
        next
    end
end
config method
    Description: Method restriction.
    set status [enable|disable]

```

```

set log [enable|disable]
set severity [high|medium|...]
set default-allowed-methods {option1}, {option2}, ...
config method-policy
    Description: HTTP method policy.
    edit <id>
        set pattern {string}
        set regex [enable|disable]
        set address {string}
        set allowed-methods {option1}, {option2}, ...
    next
end
end
config address-list
    Description: Address block and allow lists.
    set status [enable|disable]
    set blocked-log [enable|disable]
    set severity [high|medium|...]
    set trusted-address <name1>, <name2>, ...
    set blocked-address <name1>, <name2>, ...
end
config url-access
    Description: URL access list.
    edit <id>
        set address {string}
        set action [bypass|permit|...]
        set log [enable|disable]
        set severity [high|medium|...]
        config access-pattern
            Description: URL access pattern.
            edit <id>
                set srcaddr {string}
                set pattern {string}
                set regex [enable|disable]
                set negate [enable|disable]
            next
        next
    end
next
end
set comment {var-string}
next
end

```

config waf profile

Parameter	Description	Type	Size	Default
name	WAF Profile name.	string	Maximum length: 35	

Parameter	Description	Type	Size	Default
external	Disable/Enable external HTTP Inspection.	option	-	disable
	Option	Description		
	<i>disable</i>	Disable external inspection.		
	<i>enable</i>	Enable external inspection.		
extended-log	Enable/disable extended logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
comment	Comment.	var-string	Maximum length: 1023	

config signature

Parameter	Description	Type	Size	Default
disabled-sub-class <id>	Disabled signature subclasses. Signature subclass ID.	integer	Minimum value: 0 Maximum value: 4294967295	
disabled-signature <id>	Disabled signatures. Signature ID.	integer	Minimum value: 0 Maximum value: 4294967295	
credit-card-detection-threshold	The minimum number of Credit cards to detect violation.	integer	Minimum value: 0 Maximum value: 128	3

config main-class

Parameter	Description	Type	Size	Default
id	Main signature class ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
status	Status.	option	-	disable
	Option	Description		
	enable	Enable setting.		
	disable	Disable setting.		
action	Action.	option	-	allow
	Option	Description		
	allow	Allow.		
	block	Block.		
	erase	Erase credit card numbers.		
log	Enable/disable logging.	option	-	enable
	Option	Description		
	enable	Enable setting.		
	disable	Disable setting.		
severity	Severity.	option	-	medium
	Option	Description		
	high	High severity.		
	medium	Medium severity.		
	low	Low severity.		

config custom-signature

Parameter	Description	Type	Size	Default
name	Signature name.	string	Maximum length: 35	
status	Status.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
action	Action.	option	-	allow
	Option	Description		
	<i>allow</i>	Allow.		
	<i>block</i>	Block.		
	<i>erase</i>	Erase credit card numbers.		
log	Enable/disable logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
severity	Severity.	option	-	medium
	Option	Description		
	<i>high</i>	High severity.		
	<i>medium</i>	Medium severity.		
	<i>low</i>	Low severity.		
direction	Traffic direction.	option	-	request
	Option	Description		
	<i>request</i>	Match HTTP request.		
	<i>response</i>	Match HTTP response.		
case-sensitivity	Case sensitivity in pattern.	option	-	disable
	Option	Description		
	<i>disable</i>	Case insensitive in pattern.		
	<i>enable</i>	Case sensitive in pattern.		
pattern	Match pattern.	string	Maximum length: 511	

Parameter	Description	Type	Size	Default
target	Match HTTP target.	option	-	
	Option	Description		
	arg	HTTP arguments.		
	arg-name	Names of HTTP arguments.		
	req-body	HTTP request body.		
	req-cookie	HTTP request cookies.		
	req-cookie-name	HTTP request cookie names.		
	req-filename	HTTP request file name.		
	req-header	HTTP request headers.		
	req-header-name	HTTP request header names.		
	req-raw-uri	Raw URI of HTTP request.		
	req-uri	URI of HTTP request.		
	resp-body	HTTP response body.		
	resp-hdr	HTTP response headers.		
	resp-status	HTTP response status.		

config header-length

Parameter	Description	Type	Size	Default						
status	Enable/disable the constraint.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
	Option	Description								
	<i>enable</i>	Enable setting.								
<i>disable</i>	Disable setting.									
length	Length of HTTP header in bytes (0 to 2147483647).	integer	Minimum value: 0 Maximum value: 2147483647	8192						
action	Action.	option	-	allow						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>allow</i>	Allow.		
	<i>block</i>	Block.		
log	Enable/disable logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
severity	Severity.	option	-	medium
	Option	Description		
	<i>high</i>	High severity.		
	<i>medium</i>	Medium severity.		
	<i>low</i>	Low severity.		

config content-length

Parameter	Description	Type	Size	Default
status	Enable/disable the constraint.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
length	Length of HTTP content in bytes (0 to 2147483647).	integer	Minimum value: 0 Maximum value: 2147483647	67108864
action	Action.	option	-	allow
	Option	Description		
	<i>allow</i>	Allow.		
	<i>block</i>	Block.		
log	Enable/disable logging.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
severity	Severity.	option	-	medium
	Option	Description		
	<i>high</i>	High severity.		
	<i>medium</i>	Medium severity.		
	<i>low</i>	Low severity.		

config param-length

Parameter	Description	Type	Size	Default
status	Enable/disable the constraint.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
length	Maximum length of parameter in URL, HTTP POST request or HTTP body in bytes (0 to 2147483647).	integer	Minimum value: 0 Maximum value: 2147483647	8192
action	Action.	option	-	allow
	Option	Description		
	<i>allow</i>	Allow.		
	<i>block</i>	Block.		
log	Enable/disable logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
severity	Severity.	option	-	medium

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>high</i>	High severity.		
	<i>medium</i>	Medium severity.		
	<i>low</i>	Low severity.		

config line-length

Parameter	Description	Type	Size	Default
status	Enable/disable the constraint.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
length	Length of HTTP line in bytes (0 to 2147483647).	integer	Minimum value: 0 Maximum value: 2147483647	1024
action	Action.	option	-	allow
	Option	Description		
	<i>allow</i>	Allow.		
	<i>block</i>	Block.		
log	Enable/disable logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
severity	Severity.	option	-	medium
	Option	Description		
	<i>high</i>	High severity.		
	<i>medium</i>	Medium severity.		
	<i>low</i>	Low severity.		

config url-param-length

Parameter	Description	Type	Size	Default
status	Enable/disable the constraint.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
length	Maximum length of URL parameter in bytes (0 to 2147483647).	integer	Minimum value: 0 Maximum value: 2147483647	8192
action	Action.	option	-	allow
	Option	Description		
	<i>allow</i>	Allow.		
	<i>block</i>	Block.		
log	Enable/disable logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
severity	Severity.	option	-	medium
	Option	Description		
	<i>high</i>	High severity.		
	<i>medium</i>	Medium severity.		
	<i>low</i>	Low severity.		

config version

Parameter	Description	Type	Size	Default
status	Enable/disable the constraint.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

Parameter	Description	Type	Size	Default								
action	Action.	option	-	allow								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow.</td></tr><tr><td><i>block</i></td><td>Block.</td></tr></table>	Option	Description	<i>allow</i>	Allow.	<i>block</i>	Block.					
Option	Description											
<i>allow</i>	Allow.											
<i>block</i>	Block.											
log	Enable/disable logging.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.					
Option	Description											
<i>enable</i>	Enable setting.											
<i>disable</i>	Disable setting.											
severity	Severity.	option	-	medium								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>high</i></td><td>High severity.</td></tr><tr><td><i>medium</i></td><td>Medium severity.</td></tr><tr><td><i>low</i></td><td>Low severity.</td></tr></table>	Option	Description	<i>high</i>	High severity.	<i>medium</i>	Medium severity.	<i>low</i>	Low severity.			
Option	Description											
<i>high</i>	High severity.											
<i>medium</i>	Medium severity.											
<i>low</i>	Low severity.											

config method

Parameter	Description	Type	Size	Default						
status	Enable/disable the constraint.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
action	Action.	option	-	allow						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>allow</i></td><td>Allow.</td></tr><tr><td><i>block</i></td><td>Block.</td></tr></table>	Option	Description	<i>allow</i>	Allow.	<i>block</i>	Block.			
Option	Description									
<i>allow</i>	Allow.									
<i>block</i>	Block.									
log	Enable/disable logging.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									

Parameter	Description	Type	Size	Default
severity	Severity.	option	-	medium
	Option	Description		
	<i>high</i>	High severity.		
	<i>medium</i>	Medium severity.		
	<i>low</i>	Low severity.		

config hostname

Parameter	Description	Type	Size	Default
status	Enable/disable the constraint.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
action	Action.	option	-	allow
	Option	Description		
	<i>allow</i>	Allow.		
	<i>block</i>	Block.		
log	Enable/disable logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
severity	Severity.	option	-	medium
	Option	Description		
	<i>high</i>	High severity.		
	<i>medium</i>	Medium severity.		
	<i>low</i>	Low severity.		

config malformed

Parameter	Description	Type	Size	Default
status	Enable/disable the constraint.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
action	Action.	option	-	allow
	Option	Description		
	<i>allow</i>	Allow.		
	<i>block</i>	Block.		
log	Enable/disable logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
severity	Severity.	option	-	medium
	Option	Description		
	<i>high</i>	High severity.		
	<i>medium</i>	Medium severity.		
	<i>low</i>	Low severity.		

config max-cookie

Parameter	Description	Type	Size	Default
status	Enable/disable the constraint.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
max-cookie	Maximum number of cookies in HTTP request (0 to 2147483647).	integer	Minimum value: 0 Maximum value: 2147483647	16

Parameter	Description	Type	Size	Default
action	Action.	option	-	allow
	Option	Description		
	<i>allow</i>	Allow.		
	<i>block</i>	Block.		
log	Enable/disable logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
severity	Severity.	option	-	medium
	Option	Description		
	<i>high</i>	High severity.		
	<i>medium</i>	Medium severity.		
	<i>low</i>	Low severity.		

config max-header-line

Parameter	Description	Type	Size	Default
status	Enable/disable the constraint.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
max-header-line	Maximum number HTTP header lines (0 to 2147483647).	integer	Minimum value: 0 Maximum value: 2147483647	32
action	Action.	option	-	allow
	Option	Description		
	<i>allow</i>	Allow.		
	<i>block</i>	Block.		
log	Enable/disable logging.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
severity	Severity.	option	-	medium
	Option	Description		
	<i>high</i>	High severity.		
	<i>medium</i>	Medium severity.		
	<i>low</i>	Low severity.		

config max-url-param

Parameter	Description	Type	Size	Default
status	Enable/disable the constraint.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
max-url-param	Maximum number of parameters in URL (0 to 2147483647).	integer	Minimum value: 0 Maximum value: 2147483647	16
action	Action.	option	-	allow
	Option	Description		
	<i>allow</i>	Allow.		
	<i>block</i>	Block.		
log	Enable/disable logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
severity	Severity.	option	-	medium

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>high</i>	High severity.		
	<i>medium</i>	Medium severity.		
	<i>low</i>	Low severity.		

config max-range-segment

Parameter	Description	Type	Size	Default
status	Enable/disable the constraint.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
max-range-segment	Maximum number of range segments in HTTP range line (0 to 2147483647).	integer	Minimum value: 0 Maximum value: 2147483647	5
action	Action.	option	-	allow
	Option	Description		
	<i>allow</i>	Allow.		
	<i>block</i>	Block.		
log	Enable/disable logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
severity	Severity.	option	-	medium
	Option	Description		
	<i>high</i>	High severity.		
	<i>medium</i>	Medium severity.		
	<i>low</i>	Low severity.		

config exception

Parameter	Description	Type	Size	Default						
id	Exception ID.	integer	Minimum value: 0 Maximum value: 4294967295	0						
pattern	URL pattern.	string	Maximum length: 511							
regex	Enable/disable regular expression based pattern match.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
address	Host address.	string	Maximum length: 79							
header-length	HTTP header length in request.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
content-length	HTTP content length in request.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
param-length	Maximum length of parameter in URL, HTTP POST request or HTTP body.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
line-length	HTTP line length in request.	option	-	disable						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
url-param-length	Maximum length of parameter in URL.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
version	Enable/disable HTTP version check.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
method	Enable/disable HTTP method check.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
hostname	Enable/disable hostname check.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
malformed	Enable/disable malformed HTTP request check.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
max-cookie	Maximum number of cookies in HTTP request.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
max-header-line	Maximum number of HTTP header line.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
max-url-param	Maximum number of parameters in URL.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
max-range-segment	Maximum number of range segments in HTTP range line.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

config method

Parameter	Description	Type	Size	Default
status	Status.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
log	Enable/disable logging.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

Parameter	Description	Type	Size	Default
severity	Severity.	option	-	medium
	Option	Description		
	<i>high</i>	High severity		
	<i>medium</i>	medium severity		
	<i>low</i>	low severity		
default-allowed-methods	Methods.	option	-	
	Option	Description		
	<i>get</i>	HTTP GET method.		
	<i>post</i>	HTTP POST method.		
	<i>put</i>	HTTP PUT method.		
	<i>head</i>	HTTP HEAD method.		
	<i>connect</i>	HTTP CONNECT method.		
	<i>trace</i>	HTTP TRACE method.		
	<i>options</i>	HTTP OPTIONS method.		
	<i>delete</i>	HTTP DELETE method.		
	<i>others</i>	Other HTTP methods.		

config method-policy

Parameter	Description	Type	Size	Default
id	HTTP method policy ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
pattern	URL pattern.	string	Maximum length: 511	
regex	Enable/disable regular expression based pattern match.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

Parameter	Description	Type	Size	Default
address	Host address.	string	Maximum length: 79	
allowed-methods	Allowed Methods.	option	-	
	Option	Description		
	<i>get</i>	HTTP GET method.		
	<i>post</i>	HTTP POST method.		
	<i>put</i>	HTTP PUT method.		
	<i>head</i>	HTTP HEAD method.		
	<i>connect</i>	HTTP CONNECT method.		
	<i>trace</i>	HTTP TRACE method.		
	<i>options</i>	HTTP OPTIONS method.		
	<i>delete</i>	HTTP DELETE method.		
	<i>others</i>	Other HTTP methods.		

config address-list

Parameter	Description	Type	Size	Default								
status	Status.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.					
Option	Description											
<i>enable</i>	Enable setting.											
<i>disable</i>	Disable setting.											
blocked-log	Enable/disable logging on blocked addresses.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.					
Option	Description											
<i>enable</i>	Enable setting.											
<i>disable</i>	Disable setting.											
severity	Severity.	option	-	medium								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>high</i></td><td>High severity.</td></tr><tr><td><i>medium</i></td><td>Medium severity.</td></tr><tr><td><i>low</i></td><td>Low severity.</td></tr></table>	Option	Description	<i>high</i>	High severity.	<i>medium</i>	Medium severity.	<i>low</i>	Low severity.			
Option	Description											
<i>high</i>	High severity.											
<i>medium</i>	Medium severity.											
<i>low</i>	Low severity.											

Parameter	Description	Type	Size	Default
trusted-address <name>	Trusted address. Address name.	string	Maximum length: 79	
blocked-address <name>	Blocked address. Address name.	string	Maximum length: 79	

config url-access

Parameter	Description	Type	Size	Default
id	URL access ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
address	Host address.	string	Maximum length: 79	
action	Action.	option	-	permit
	Option	Description		
	bypass	Allow the HTTP request, also bypass further WAF scanning.		
	permit	Allow the HTTP request, and continue further WAF scanning.		
	block	Block HTTP request.		
log	Enable/disable logging.	option	-	disable
	Option	Description		
	enable	Enable setting.		
	disable	Disable setting.		
severity	Severity.	option	-	medium
	Option	Description		
	high	High severity.		
	medium	Medium severity.		
	low	Low severity.		

config access-pattern

Parameter	Description	Type	Size	Default						
id	URL access pattern ID.	integer	Minimum value: 0 Maximum value: 4294967295	0						
srcaddr	Source address.	string	Maximum length: 79							
pattern	URL pattern.	string	Maximum length: 511							
regex	Enable/disable regular expression based pattern match.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
negate	Enable/disable match negation.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									

config waf signature

Hidden table for datasource.

```
config waf signature
  Description: Hidden table for datasource.
  edit <id>
    set desc {string}
  next
end
```

config waf signature

Parameter	Description	Type	Size	Default
desc	Signature description.	string	Maximum length: 511	
id	Signature ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

config waf sub-class

Hidden table for datasource.

```
config waf sub-class
  Description: Hidden table for datasource.
  edit <id>
    set name {string}
  next
end
```

config waf sub-class

Parameter	Description	Type	Size	Default
name	Signature subclass name.	string	Maximum length: 127	
id	Signature subclass ID.	integer	Minimum value: 0 Maximum value: 4294967295	0

wanopt

This section includes syntax for the following commands:

- [config wanopt auth-group on page 1244](#)
- [config wanopt cache-service on page 1245](#)
- [config wanopt content-delivery-network-rule on page 1247](#)
- [config wanopt peer on page 1253](#)
- [config wanopt profile on page 1253](#)
- [config wanopt remote-storage on page 1262](#)
- [config wanopt settings on page 1263](#)

config wanopt auth-group

Configure WAN optimization authentication groups.

```
config wanopt auth-group
  Description: Configure WAN optimization authentication groups.
  edit <name>
    set auth-method [cert|psk]
    set psk {password}
    set cert {string}
    set peer-accept [any|defined|...]
    set peer {string}
  next
end
```

config wanopt auth-group

Parameter	Description	Type	Size	Default
name	Auth-group name.	string	Maximum length: 35	
auth-method	Select certificate or pre-shared key authentication for this authentication group.	option	-	cert
		Option	Description	
		cert	Certificate authentication.	
		psk	Pre-shared secret key authentication.	

Parameter	Description	Type	Size	Default								
psk	Pre-shared key used by the peers in this authentication group.	password	Not Specified									
cert	Name of certificate to identify this peer.	string	Maximum length: 35									
peer-accept	Determine if this auth group accepts, any peer, a list of defined peers, or just one peer.	option	-	any								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>any</i></td><td>Accept any peer that can authenticate with this auth group.</td></tr><tr><td><i>defined</i></td><td>Accept only the peers added with the wanopt peer command.</td></tr><tr><td><i>one</i></td><td>Accept the peer added to this auth group using the peer option.</td></tr></table>				Option	Description	<i>any</i>	Accept any peer that can authenticate with this auth group.	<i>defined</i>	Accept only the peers added with the wanopt peer command.	<i>one</i>	Accept the peer added to this auth group using the peer option.
	Option	Description										
	<i>any</i>	Accept any peer that can authenticate with this auth group.										
	<i>defined</i>	Accept only the peers added with the wanopt peer command.										
<i>one</i>	Accept the peer added to this auth group using the peer option.											
peer	If peer-accept is set to one, select the name of one peer to add to this authentication group. The peer must have added with the wanopt peer command.	string	Maximum length: 35									

config wanopt cache-service

Designate cache-service for wan-optimization and webcache.

```

config wanopt cache-service
  Description: Designate cache-service for wan-optimization and webcache.
  set prefer-scenario [balance|prefer-speed|...]
  set collaboration [enable|disable]
  set device-id {string}
  set acceptable-connections [any|peers]
  config dst-peer
    Description: Modify cache-service destination peer list.
    edit <device-id>
      set auth-type {integer}
      set encode-type {integer}
      set priority {integer}
      set ip {ipv4-address-any}
    next
  end
  config src-peer
    Description: Modify cache-service source peer list.
    edit <device-id>
      set auth-type {integer}
      set encode-type {integer}
      set priority {integer}
      set ip {ipv4-address-any}
    next

```

```
end
end
```

config wanopt cache-service

Parameter	Description	Type	Size	Default
prefer-scenario	Set the preferred cache behavior towards the balance between latency and hit-ratio.	option	-	balance
	Option	Description		
	<i>balance</i>	Balance between speed and cache hit ratio.		
	<i>prefer-speed</i>	Prefer response speed at the expense of increased cache bypasses.		
	<i>prefer-cache</i>	Prefer improving hit-ratio through increasing latency tolerance.		
collaboration	Enable/disable cache-collaboration between cache-service clusters.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable cache cache-collaboration.		
	<i>disable</i>	Disable cache cache-collaboration.		
device-id	Set identifier for this cache device.	string	Maximum length: 35	default_dev_id
acceptable-connections	Set strategy when accepting cache collaboration connection.	option	-	any
	Option	Description		
	<i>any</i>	We can accept any cache-collaboration connection.		
	<i>peers</i>	We can only accept connections that are already in src-peers.		

config dst-peer

Parameter	Description	Type	Size	Default
device-id	Device ID of this peer.	string	Maximum length: 35	
auth-type	Set authentication type for this peer.	integer	Minimum value: 0 Maximum value: 255	0

Parameter	Description	Type	Size	Default
encode-type	Set encode type for this peer.	integer	Minimum value: 0 Maximum value: 255	0
priority	Set priority for this peer.	integer	Minimum value: 0 Maximum value: 255	1
ip	Set cluster IP address of this peer.	ipv4-address-any	Not Specified	0.0.0.0

config src-peer

Parameter	Description	Type	Size	Default
device-id	Device ID of this peer.	string	Maximum length: 35	
auth-type	Set authentication type for this peer.	integer	Minimum value: 0 Maximum value: 255	0
encode-type	Set encode type for this peer.	integer	Minimum value: 0 Maximum value: 255	0
priority	Set priority for this peer.	integer	Minimum value: 0 Maximum value: 255	1
ip	Set cluster IP address of this peer.	ipv4-address-any	Not Specified	0.0.0.0

config wanopt content-delivery-network-rule

Configure WAN optimization content delivery network rules.

```
config wanopt content-delivery-network-rule
    Description: Configure WAN optimization content delivery network rules.
    edit <name>
        set comment {var-string}
```

```

set status [enable|disable]
set host-domain-name-suffix <name1>, <name2>, ...
set category [vcache|youtube]
set request-cache-control [enable|disable]
set response-cache-control [enable|disable]
set response-expires [enable|disable]
set updateserver [enable|disable]
config rules
    Description: WAN optimization content delivery network rule entries.
    edit <name>
        set match-mode [all|any]
        set skip-rule-mode [all|any]
        config match-entries
            Description: List of entries to match.
            edit <id>
                set target [path|parameter|...]
                set pattern <string1>, <string2>, ...
            next
        end
        config skip-entries
            Description: List of entries to skip.
            edit <id>
                set target [path|parameter|...]
                set pattern <string1>, <string2>, ...
            next
        end
        config content-id
            Description: Content ID settings.
            set target [path|parameter|...]
            set start-str {string}
            set start-skip {integer}
            set start-direction [forward|backward]
            set end-str {string}
            set end-skip {integer}
            set end-direction [forward|backward]
            set range-str {string}
        end
    next
end
next
end
end

```

config wanopt content-delivery-network-rule

Parameter	Description	Type	Size	Default
name	Name of table.	string	Maximum length: 35	

Parameter	Description	Type	Size	Default						
comment	Comment about this CDN-rule.	var-string	Maximum length: 255							
status	Enable/disable WAN optimization content delivery network rules.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
host-domain-name-suffix <name>	Suffix portion of the fully qualified domain name. For example, fortinet.com in "www.fortinet.com". Suffix portion of the fully qualified domain name.	string	Maximum length: 79							
category	Content delivery network rule category.	option	-	vcache						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>vcache</i></td><td>Vcache content delivery network.</td></tr><tr><td><i>youtube</i></td><td>Youtube content delivery network.</td></tr></table>	Option	Description	<i>vcache</i>	Vcache content delivery network.	<i>youtube</i>	Youtube content delivery network.			
Option	Description									
<i>vcache</i>	Vcache content delivery network.									
<i>youtube</i>	Youtube content delivery network.									
request-cache-control	Enable/disable HTTP request cache control.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
response-cache-control	Enable/disable HTTP response cache control.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
response-expires	Enable/disable HTTP response cache expires.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									

Parameter	Description	Type	Size	Default
updateserver	Enable/disable update server.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

config rules

Parameter	Description	Type	Size	Default
name	WAN optimization content delivery network rule name.	string	Maximum length: 35	
match-mode	Match criteria for collecting content ID.	option	-	all
	Option	Description		
	<i>all</i>	Must match all of the match entries.		
	<i>any</i>	Must match any of the match entries.		
skip-rule-mode	Skip mode when evaluating skip-rules.	option	-	all
	Option	Description		
	<i>all</i>	Must match all skip entries.		
	<i>any</i>	Must match any skip entries.		

config match-entries

Parameter	Description	Type	Size	Default
id	Rule ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
target	Option in HTTP header or URL parameter to match.	option	-	path
	Option	Description		
	<i>path</i>	Match with the URL path.		
	<i>parameter</i>	Match with the URL parameters.		

Parameter	Description	Type	Size	Default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>referrer</i></td><td>Match with the Referrer option in HTTP header.</td></tr><tr><td><i>youtube-map</i></td><td>Match Youtube content-id collection.</td></tr><tr><td><i>youtube-id</i></td><td>Match Youtube content-id.</td></tr><tr><td><i>youku-id</i></td><td>Match Youku content-id.</td></tr></table>	Option	Description	<i>referrer</i>	Match with the Referrer option in HTTP header.	<i>youtube-map</i>	Match Youtube content-id collection.	<i>youtube-id</i>	Match Youtube content-id.	<i>youku-id</i>	Match Youku content-id.			
	Option	Description												
	<i>referrer</i>	Match with the Referrer option in HTTP header.												
	<i>youtube-map</i>	Match Youtube content-id collection.												
	<i>youtube-id</i>	Match Youtube content-id.												
<i>youku-id</i>	Match Youku content-id.													
pattern <string>	Pattern string for matching target (Referrer or URL pattern). For example, a, a*c, *a*, a*c*e, and *. Pattern strings.	string	Maximum length: 79											

config skip-entries

Parameter	Description	Type	Size	Default														
id	Rule ID.	integer	Minimum value: 0 Maximum value: 4294967295	0														
target	Option in HTTP header or URL parameter to match.	option	-	path														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>path</i></td><td>Match with the URL path.</td></tr><tr><td><i>parameter</i></td><td>Match with the URL parameters.</td></tr><tr><td><i>referrer</i></td><td>Match with the Referrer option in HTTP header.</td></tr><tr><td><i>youtube-map</i></td><td>Match Youtube content-id collection.</td></tr><tr><td><i>youtube-id</i></td><td>Match Youtube content-id.</td></tr><tr><td><i>youku-id</i></td><td>Match Youku content-id.</td></tr></table>				Option	Description	<i>path</i>	Match with the URL path.	<i>parameter</i>	Match with the URL parameters.	<i>referrer</i>	Match with the Referrer option in HTTP header.	<i>youtube-map</i>	Match Youtube content-id collection.	<i>youtube-id</i>	Match Youtube content-id.	<i>youku-id</i>	Match Youku content-id.
	Option	Description																
	<i>path</i>	Match with the URL path.																
	<i>parameter</i>	Match with the URL parameters.																
	<i>referrer</i>	Match with the Referrer option in HTTP header.																
	<i>youtube-map</i>	Match Youtube content-id collection.																
	<i>youtube-id</i>	Match Youtube content-id.																
<i>youku-id</i>	Match Youku content-id.																	
pattern <string>	Pattern string for matching target (Referrer or URL pattern). For example, a, a*c, *a*, a*c*e, and *. Pattern strings.	string	Maximum length: 79															

config content-id

Parameter	Description	Type	Size	Default
target	Option in HTTP header or URL parameter to match.	option	-	path
	Option	Description		
	<i>path</i>	Match with the URL path.		
	<i>parameter</i>	Match with the URL parameters.		
	<i>referrer</i>	Match with the Referrer option in HTTP header.		
	<i>youtube-map</i>	Match Youtube content-id collection.		
	<i>youtube-id</i>	Match Youtube content-id.		
	<i>youku-id</i>	Match Youku content-id.		
	<i>hls-manifest</i>	Match with HLS manifest.		
	<i>dash-manifest</i>	Match with DASH manifest.		
	<i>hls-fragment</i>	Match HLS stream fragment.		
	<i>dash-fragment</i>	Match DASH stream fragment.		
	start-str	String from which to start search.	string	Maximum length: 35
start-skip	Number of characters in URL to skip after start-str has been matched.	integer	Minimum value: 0 Maximum value: 4294967295	0
start-direction	Search direction from start-str match.	option	-	forward
	Option	Description		
	<i>forward</i>	Forward direction.		
	<i>backward</i>	Backward direction.		
end-str	String from which to end search.	string	Maximum length: 35	
end-skip	Number of characters in URL to skip after end-str has been matched.	integer	Minimum value: 0 Maximum value: 4294967295	0

Parameter	Description	Type	Size	Default						
end-direction	Search direction from end-str match.	option	-	forward						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>forward</i></td><td>Forward direction.</td></tr><tr><td><i>backward</i></td><td>Backward direction.</td></tr></table>				Option	Description	<i>forward</i>	Forward direction.	<i>backward</i>	Backward direction.
Option	Description									
<i>forward</i>	Forward direction.									
<i>backward</i>	Backward direction.									
range-str	Name of content ID within the start string and end string.	string	Maximum length: 35							

config wanopt peer

Configure WAN optimization peers.

```
config wanopt peer
  Description: Configure WAN optimization peers.
  edit <peer-host-id>
    set ip {ipv4-address-any}
  next
end
```

config wanopt peer

Parameter	Description	Type	Size	Default
peer-host-id	Peer host ID.	string	Maximum length: 35	
ip	Peer IP address.	ipv4-address-any	Not Specified	0.0.0.0

config wanopt profile

Configure WAN optimization profiles.

```
config wanopt profile
  Description: Configure WAN optimization profiles.
  edit <name>
    set transparent [enable|disable]
    set comments {var-string}
    set auth-group {string}
  config http
```

```

        Description: Enable/disable HTTP WAN Optimization and configure HTTP WAN Optimization
features.
        set status [enable|disable]
        set secure-tunnel [enable|disable]
        set byte-caching [enable|disable]
        set ssl [enable|disable]
        set prefer-chunking [dynamic|fix]
        set protocol-opt [protocol|tcp]
        set tunnel-sharing [shared|express-shared|...]
    end
    config cifs
        Description: Enable/disable CIFS (Windows sharing) WAN Optimization and configure CIFS
WAN Optimization features.
        set status [enable|disable]
        set secure-tunnel [enable|disable]
        set byte-caching [enable|disable]
        set prefer-chunking [dynamic|fix]
        set protocol-opt [protocol|tcp]
        set tunnel-sharing [shared|express-shared|...]
    end
    config mapi
        Description: Enable/disable MAPI email WAN Optimization and configure MAPI WAN
Optimization features.
        set status [enable|disable]
        set secure-tunnel [enable|disable]
        set byte-caching [enable|disable]
        set tunnel-sharing [shared|express-shared|...]
    end
    config ftp
        Description: Enable/disable FTP WAN Optimization and configure FTP WAN Optimization
features.
        set status [enable|disable]
        set secure-tunnel [enable|disable]
        set byte-caching [enable|disable]
        set prefer-chunking [dynamic|fix]
        set protocol-opt [protocol|tcp]
        set tunnel-sharing [shared|express-shared|...]
    end
    config tcp
        Description: Enable/disable TCP WAN Optimization and configure TCP WAN Optimization
features.
        set status [enable|disable]
        set secure-tunnel [enable|disable]
        set byte-caching [enable|disable]
        set byte-caching-opt [mem-only|mem-disk]
        set tunnel-sharing [shared|express-shared|...]
        set port {user}
        set ssl [enable|disable]
        set ssl-port {user}
    end
next
end

```

config wanopt profile

Parameter	Description	Type	Size	Default
name	Profile name.	string	Maximum length: 35	
transparent	Enable/disable transparent mode.	option	-	enable
	Option	Description		
	enable	Determine if WAN Optimization changes client packet source addresses. Affects the routing configuration on the server network.		
	disable	Disable transparent mode. Client packets source addresses are changed to the source address of the FortiProxy internal interface. Similar to source NAT.		
comments	Comment.	var-string	Maximum length: 255	
auth-group	Optionally add an authentication group to restrict access to the WAN Optimization tunnel to peers in the authentication group.	string	Maximum length: 35	

config http

Parameter	Description	Type	Size	Default						
status	Enable/disable WAN Optimization.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable WAN Optimization.</td></tr><tr><td><i>disable</i></td><td>Disable WAN Optimization.</td></tr></table>	Option	Description	<i>enable</i>	Enable WAN Optimization.	<i>disable</i>	Disable WAN Optimization.			
Option	Description									
<i>enable</i>	Enable WAN Optimization.									
<i>disable</i>	Disable WAN Optimization.									
secure-tunnel	Enable/disable securing the WAN Opt tunnel using SSL. Secure and non-secure tunnels use the same TCP port (7810).	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable SSL-secured tunnelling.</td></tr><tr><td><i>disable</i></td><td>Disable SSL-secured tunnelling.</td></tr></table>	Option	Description	<i>enable</i>	Enable SSL-secured tunnelling.	<i>disable</i>	Disable SSL-secured tunnelling.			
Option	Description									
<i>enable</i>	Enable SSL-secured tunnelling.									
<i>disable</i>	Disable SSL-secured tunnelling.									
byte-caching	Enable/disable byte-caching. Byte caching reduces the amount of traffic by caching file data sent across the WAN and in future serving if from the cache.	option	-	enable						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable byte-caching.		
	<i>disable</i>	Disable byte-caching.		
ssl	Enable/disable SSL/TLS offloading (hardware acceleration) for traffic in this tunnel.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable SSL/TLS offloading.		
	<i>disable</i>	Disable SSL/TLS offloading.		
prefer-chunking	Select dynamic or fixed-size data chunking for WAN Optimization.	option	-	fix
	Option	Description		
	<i>dynamic</i>	Select dynamic data chunking to help to detect persistent data chunks in a changed file or in an embedded unknown protocol.		
	<i>fix</i>	Select fixed data chunking.		
protocol-opt	Select protocol specific optimization or generic TCP optimization.	option	-	protocol
	Option	Description		
	<i>protocol</i>	Using protocol-specific optimization.		
	<i>tcp</i>	Using generic TCP optimization.		
tunnel-sharing	Tunnel sharing mode for aggressive/non-aggressive and/or interactive/non-interactive protocols.	option	-	private
	Option	Description		
	<i>shared</i>	For profiles that accept nonaggressive and non-interactive protocols.		
	<i>express-shared</i>	For profiles that accept interactive protocols such as Telnet.		
	<i>private</i>	For profiles that accept aggressive protocols such as HTTP and FTP so that these aggressive protocols do not share tunnels with less-aggressive protocols.		

config cifs

Parameter	Description	Type	Size	Default						
status	Enable/disable WAN Optimization.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable WAN Optimization.</td></tr><tr><td><i>disable</i></td><td>Disable WAN Optimization.</td></tr></table>	Option	Description	<i>enable</i>	Enable WAN Optimization.	<i>disable</i>	Disable WAN Optimization.			
Option	Description									
<i>enable</i>	Enable WAN Optimization.									
<i>disable</i>	Disable WAN Optimization.									
secure-tunnel	Enable/disable securing the WAN Opt tunnel using SSL. Secure and non-secure tunnels use the same TCP port (7810).	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable SSL-secured tunnelling.</td></tr><tr><td><i>disable</i></td><td>Disable SSL-secured tunnelling.</td></tr></table>	Option	Description	<i>enable</i>	Enable SSL-secured tunnelling.	<i>disable</i>	Disable SSL-secured tunnelling.			
Option	Description									
<i>enable</i>	Enable SSL-secured tunnelling.									
<i>disable</i>	Disable SSL-secured tunnelling.									
byte-caching	Enable/disable byte-caching. Byte caching reduces the amount of traffic by caching file data sent across the WAN and in future serving if from the cache.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable byte-caching.</td></tr><tr><td><i>disable</i></td><td>Disable byte-caching.</td></tr></table>	Option	Description	<i>enable</i>	Enable byte-caching.	<i>disable</i>	Disable byte-caching.			
Option	Description									
<i>enable</i>	Enable byte-caching.									
<i>disable</i>	Disable byte-caching.									
prefer-chunking	Select dynamic or fixed-size data chunking for WAN Optimization.	option	-	fix						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>dynamic</i></td><td>Select dynamic data chunking to help to detect persistent data chunks in a changed file or in an embedded unknown protocol.</td></tr><tr><td><i>fix</i></td><td>Select fixed data chunking.</td></tr></table>	Option	Description	<i>dynamic</i>	Select dynamic data chunking to help to detect persistent data chunks in a changed file or in an embedded unknown protocol.	<i>fix</i>	Select fixed data chunking.			
Option	Description									
<i>dynamic</i>	Select dynamic data chunking to help to detect persistent data chunks in a changed file or in an embedded unknown protocol.									
<i>fix</i>	Select fixed data chunking.									
protocol-opt	Select protocol specific optimization or generic TCP optimization.	option	-	protocol						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>protocol</i></td><td>Using protocol-specific optimization.</td></tr><tr><td><i>tcp</i></td><td>Using generic TCP optimization.</td></tr></table>	Option	Description	<i>protocol</i>	Using protocol-specific optimization.	<i>tcp</i>	Using generic TCP optimization.			
Option	Description									
<i>protocol</i>	Using protocol-specific optimization.									
<i>tcp</i>	Using generic TCP optimization.									
tunnel-sharing	Tunnel sharing mode for aggressive/non-aggressive and/or interactive/non-interactive protocols.	option	-	private						

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>shared</i>	For profiles that accept nonaggressive and non-interactive protocols.		
	<i>express-shared</i>	For profiles that accept interactive protocols such as Telnet.		
	<i>private</i>	For profiles that accept aggressive protocols such as HTTP and FTP so that these aggressive protocols do not share tunnels with less-aggressive protocols.		

config mapi

Parameter	Description	Type	Size	Default
status	Enable/disable WAN Optimization.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable WAN Optimization.		
	<i>disable</i>	Disable WAN Optimization.		
secure-tunnel	Enable/disable securing the WAN Opt tunnel using SSL. Secure and non-secure tunnels use the same TCP port (7810).	option	-	disable
	Option	Description		
	<i>enable</i>	Enable SSL-secured tunnelling.		
	<i>disable</i>	Disable SSL-secured tunnelling.		
byte-caching	Enable/disable byte-caching. Byte caching reduces the amount of traffic by caching file data sent across the WAN and in future serving if from the cache.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable byte-caching.		
	<i>disable</i>	Disable byte-caching.		
tunnel-sharing	Tunnel sharing mode for aggressive/non-aggressive and/or interactive/non-interactive protocols.	option	-	private

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>shared</i>	For profiles that accept nonaggressive and non-interactive protocols.		
	<i>express-shared</i>	For profiles that accept interactive protocols such as Telnet.		
	<i>private</i>	For profiles that accept aggressive protocols such as HTTP and FTP so that these aggressive protocols do not share tunnels with less-aggressive protocols.		

config ftp

Parameter	Description	Type	Size	Default
status	Enable/disable WAN Optimization.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable WAN Optimization.		
	<i>disable</i>	Disable WAN Optimization.		
secure-tunnel	Enable/disable securing the WAN Opt tunnel using SSL. Secure and non-secure tunnels use the same TCP port (7810).	option	-	disable
	Option	Description		
	<i>enable</i>	Enable SSL-secured tunnelling.		
	<i>disable</i>	Disable SSL-secured tunnelling.		
byte-caching	Enable/disable byte-caching. Byte caching reduces the amount of traffic by caching file data sent across the WAN and in future serving if from the cache.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable byte-caching.		
	<i>disable</i>	Disable byte-caching.		
prefer-chunking	Select dynamic or fixed-size data chunking for WAN Optimization.	option	-	fix

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>dynamic</i>	Select dynamic data chunking to help to detect persistent data chunks in a changed file or in an embedded unknown protocol.		
	<i>fix</i>	Select fixed data chunking.		
protocol-opt	Select protocol specific optimization or generic TCP optimization.	option	-	protocol
	Option	Description		
	<i>protocol</i>	Using protocol-specific optimization.		
	<i>tcp</i>	Using generic TCP optimization.		
tunnel-sharing	Tunnel sharing mode for aggressive/non-aggressive and/or interactive/non-interactive protocols.	option	-	private
	Option	Description		
	<i>shared</i>	For profiles that accept nonaggressive and non-interactive protocols.		
	<i>express-shared</i>	For profiles that accept interactive protocols such as Telnet.		
	<i>private</i>	For profiles that accept aggressive protocols such as HTTP and FTP so that these aggressive protocols do not share tunnels with less-aggressive protocols.		

config tcp

Parameter	Description	Type	Size	Default
status	Enable/disable WAN Optimization.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable WAN Optimization.		
	<i>disable</i>	Disable WAN Optimization.		
secure-tunnel	Enable/disable securing the WAN Opt tunnel using SSL. Secure and non-secure tunnels use the same TCP port (7810).	option	-	disable

Parameter	Description	Type	Size	Default								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable SSL-secured tunnelling.</td></tr><tr><td><i>disable</i></td><td>Disable SSL-secured tunnelling.</td></tr></table>	Option	Description	<i>enable</i>	Enable SSL-secured tunnelling.	<i>disable</i>	Disable SSL-secured tunnelling.					
	Option	Description										
	<i>enable</i>	Enable SSL-secured tunnelling.										
<i>disable</i>	Disable SSL-secured tunnelling.											
byte-caching	Enable/disable byte-caching. Byte caching reduces the amount of traffic by caching file data sent across the WAN and in future serving if from the cache.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable byte-caching.</td></tr><tr><td><i>disable</i></td><td>Disable byte-caching.</td></tr></table>	Option	Description	<i>enable</i>	Enable byte-caching.	<i>disable</i>	Disable byte-caching.					
	Option	Description										
	<i>enable</i>	Enable byte-caching.										
<i>disable</i>	Disable byte-caching.											
byte-caching-opt	Select whether TCP byte-caching uses system memory only or both memory and disk space.	option	-	mem-only								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>mem-only</i></td><td>Byte caching with memory only.</td></tr><tr><td><i>mem-disk</i></td><td>Byte caching with memory and disk.</td></tr></table>	Option	Description	<i>mem-only</i>	Byte caching with memory only.	<i>mem-disk</i>	Byte caching with memory and disk.					
	Option	Description										
	<i>mem-only</i>	Byte caching with memory only.										
<i>mem-disk</i>	Byte caching with memory and disk.											
tunnel-sharing	Tunnel sharing mode for aggressive/non-aggressive and/or interactive/non-interactive protocols.	option	-	private								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>shared</i></td><td>For profiles that accept nonaggressive and non-interactive protocols.</td></tr><tr><td><i>express-shared</i></td><td>For profiles that accept interactive protocols such as Telnet.</td></tr><tr><td><i>private</i></td><td>For profiles that accept aggressive protocols such as HTTP and FTP so that these aggressive protocols do not share tunnels with less-aggressive protocols.</td></tr></table>	Option	Description	<i>shared</i>	For profiles that accept nonaggressive and non-interactive protocols.	<i>express-shared</i>	For profiles that accept interactive protocols such as Telnet.	<i>private</i>	For profiles that accept aggressive protocols such as HTTP and FTP so that these aggressive protocols do not share tunnels with less-aggressive protocols.			
	Option	Description										
	<i>shared</i>	For profiles that accept nonaggressive and non-interactive protocols.										
<i>express-shared</i>	For profiles that accept interactive protocols such as Telnet.											
<i>private</i>	For profiles that accept aggressive protocols such as HTTP and FTP so that these aggressive protocols do not share tunnels with less-aggressive protocols.											
port	Port numbers or port number ranges for TCP. Only packets with a destination port number that matches this port number or range are accepted by this profile.	user	Not Specified									
ssl	Enable/disable SSL/TLS offloading (hardware acceleration) for traffic in this tunnel.	option	-	disable								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable SSL/TLS offloading.		
	<i>disable</i>	Disable SSL/TLS offloading.		
ssl-port	Port numbers or port number ranges on which to expect HTTPS traffic for SSL/TLS offloading.	user	Not Specified	

config wanopt remote-storage

Configure a remote cache device as Web cache storage.

```
config wanopt remote-storage
  Description: Configure a remote cache device as Web cache storage.
  set status [disable|enable]
  set local-cache-id {string}
  set remote-cache-id {string}
  set remote-cache-ip {ipv4-address-any}
end
```

config wanopt remote-storage

Parameter	Description	Type	Size	Default
status	Enable/disable using remote device as Web cache storage.	option	-	disable
	Option	Description		
	<i>disable</i>	Use local disks as Web cache storage.		
	<i>enable</i>	Use a remote device as Web cache storage.		
local-cache-id	ID that this device uses to connect to the remote device.	string	Maximum length: 35	
remote-cache-id	ID of the remote device to which the device connects.	string	Maximum length: 35	
remote-cache-ip	IP address of the remote device to which the device connects.	ipv4-address-any	Not Specified	0.0.0.0

config wanopt settings

Configure WAN optimization settings.

```
config wanopt settings
  Description: Configure WAN optimization settings.
  set host-id {string}
  set tunnel-ssl-algorithm [high|medium|...]
  set auto-detect-algorithm [simple|diff-req-resp]
  set tunnel-optimization [memory-usage|balanced|...]
end
```

config wanopt settings

Parameter	Description	Type	Size	Default
host-id	Local host ID (must also be entered in the remote FortiProxy's peer list).	string	Maximum length: 35	default-id
tunnel-ssl-algorithm	Relative strength of encryption algorithms accepted during tunnel negotiation.	option	-	high
	Option	Description		
	<i>high</i>	High encryption. Allow only AES and ChaCha.		
	<i>medium</i>	Medium encryption. Allow AES, ChaCha, 3DES, and RC4.		
	<i>low</i>	Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.		
auto-detect-algorithm	Auto detection algorithms used in tunnel negotiations.	option	-	simple
	Option	Description		
	<i>simple</i>	Use the same TCP option value in SYN/SYNACK packets. Backward compatible.		
	<i>diff-req-resp</i>	Use different TCP option values in SYN/SYNACK packets to avoid false positive detection.		
tunnel-optimization	WANOpt tunnel optimization option.	option	-	balanced
	Option	Description		
	<i>memory-usage</i>	Optimize tunnel for low system memory usage.		
	<i>balanced</i>	Optimize tunnel to balance between system memory usage and throughput.		
	<i>throughput</i>	Optimize tunnel for throughput.		

web-proxy

This section includes syntax for the following commands:

- [config web-proxy debug-url on page 1264](#)
- [config web-proxy dynamic-bypass on page 1265](#)
- [config web-proxy explicit-proxy on page 1266](#)
- [config web-proxy forward-server-group on page 1275](#)
- [config web-proxy forward-server on page 1272](#)
- [config web-proxy global on page 1276](#)
- [config web-proxy implicit-proxy-rule on page 1281](#)
- [config web-proxy implicit-proxy-setting on page 1283](#)
- [config web-proxy isolator-server on page 1283](#)
- [config web-proxy pac-policy on page 1285](#)
- [config web-proxy profile on page 1286](#)
- [config web-proxy redirect-profile on page 1291](#)
- [config web-proxy url-list on page 1292](#)
- [config web-proxy url-match on page 1293](#)
- [config web-proxy wisp on page 1295](#)

config web-proxy debug-url

Configure debug URL addresses.

```
config web-proxy debug-url
  Description: Configure debug URL addresses.
  edit <name>
    set url-pattern {string}
    set status [enable|disable]
    set exact [enable|disable]
  next
end
```

config web-proxy debug-url

Parameter	Description	Type	Size	Default
name	Debug URL name.	string	Maximum length: 63	

Parameter	Description	Type	Size	Default						
url-pattern	URL exemption pattern.	string	Maximum length: 511							
status	Enable/disable this URL exemption.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable this URL exemption.</td></tr><tr><td><i>disable</i></td><td>Disable this URL exemption.</td></tr></table>	Option	Description	<i>enable</i>	Enable this URL exemption.	<i>disable</i>	Disable this URL exemption.			
Option	Description									
<i>enable</i>	Enable this URL exemption.									
<i>disable</i>	Disable this URL exemption.									
exact	Enable/disable matching the exact path.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable matching the exact path.</td></tr><tr><td><i>disable</i></td><td>Disable matching the exact path.</td></tr></table>	Option	Description	<i>enable</i>	Enable matching the exact path.	<i>disable</i>	Disable matching the exact path.			
Option	Description									
<i>enable</i>	Enable matching the exact path.									
<i>disable</i>	Disable matching the exact path.									

config web-proxy dynamic-bypass

Configure dynamic bypass settings.

```
config web-proxy dynamic-bypass
    Description: Configure dynamic bypass settings.
    set status [enable|disable]
    set errors {option1}, {option2}, ...
    set total-max {integer}
    set server-max {integer}
    set timeout {integer}
end
```

config web-proxy dynamic-bypass

Parameter	Description	Type	Size	Default
status	Enable/disable dynamic bypass.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable dynamic bypass.		
	<i>disable</i>	Disable dynamic bypass.		
errors	Configure bypass errors.	option	-	

Parameter	Description	Type	Size	Default																										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>connect-error</i></td><td>Connect error.</td></tr><tr><td><i>receive-error</i></td><td>HTTP response is not received.</td></tr><tr><td><i>non-http</i></td><td>HTTP protocol is not detected.</td></tr><tr><td><i>400</i></td><td>HTTP response code is 400.</td></tr><tr><td><i>401</i></td><td>HTTP response code is 401.</td></tr><tr><td><i>403</i></td><td>HTTP response code is 403.</td></tr><tr><td><i>405</i></td><td>HTTP response code is 405.</td></tr><tr><td><i>406</i></td><td>HTTP response code is 406.</td></tr><tr><td><i>500</i></td><td>HTTP response code is 500.</td></tr><tr><td><i>502</i></td><td>HTTP response code is 502.</td></tr><tr><td><i>503</i></td><td>HTTP response code is 503.</td></tr><tr><td><i>504</i></td><td>HTTP response code is 504.</td></tr></table>	Option	Description	<i>connect-error</i>	Connect error.	<i>receive-error</i>	HTTP response is not received.	<i>non-http</i>	HTTP protocol is not detected.	<i>400</i>	HTTP response code is 400.	<i>401</i>	HTTP response code is 401.	<i>403</i>	HTTP response code is 403.	<i>405</i>	HTTP response code is 405.	<i>406</i>	HTTP response code is 406.	<i>500</i>	HTTP response code is 500.	<i>502</i>	HTTP response code is 502.	<i>503</i>	HTTP response code is 503.	<i>504</i>	HTTP response code is 504.			
	Option	Description																												
	<i>connect-error</i>	Connect error.																												
	<i>receive-error</i>	HTTP response is not received.																												
	<i>non-http</i>	HTTP protocol is not detected.																												
	<i>400</i>	HTTP response code is 400.																												
	<i>401</i>	HTTP response code is 401.																												
	<i>403</i>	HTTP response code is 403.																												
	<i>405</i>	HTTP response code is 405.																												
	<i>406</i>	HTTP response code is 406.																												
	<i>500</i>	HTTP response code is 500.																												
	<i>502</i>	HTTP response code is 502.																												
	<i>503</i>	HTTP response code is 503.																												
<i>504</i>	HTTP response code is 504.																													
total-max	Maximum numbers of entries in dynamic bypass list (10 - 50000, default = 5000).	integer	Minimum value: 10 Maximum value: 50000	5000																										
server-max	Maximum numbers of entries in dynamic bypass list belongs to one server, all requests to this server will be bypassed once server-max is reached (1 - 255, default = 16).	integer	Minimum value: 1 Maximum value: 255	16																										
timeout	Maximum time (in minutes) that an entry is kept in dynamic bypass list from its last hit (1 - 21600, default = 60).	integer	Minimum value: 1 Maximum value: 21600	60																										

config web-proxy explicit-proxy

Configure explicit Web proxy settings.

```
config web-proxy explicit-proxy
  Description: Configure explicit Web proxy settings.
  edit <name>
    set status [enable|disable]
    set interface {string}
```

```

set secure-web-proxy [disable|enable|...]
set http [enable|disable]
set ftp-over-http [enable|disable]
set socks [enable|disable]
set http-incoming-port {user}
set http-connection-mode [static|multiplex|...]
set https-incoming-port {user}
set ftp-incoming-port {user}
set socks-incoming-port {user}
set secure-web-proxy-cert <name1>, <name2>, ...
set ssl-dh-bits [768|1024|...]
set incoming-ip {ipv4-address-any}
set ipv6-status [enable|disable]
set incoming-ip6 {ipv6-address}
set pref-dns-result [ipv4|ipv6|...]
set unknown-http-version [reject|best-effort]
set realm {string}
set sec-default-action [accept|deny]
set pac-file-server-status [enable|disable]
set pac-file-url {user}
set pac-file-server-port {user}
set pac-file-through-https [enable|disable]
set pac-file-name {string}
set pac-file-data {user}
set ssl-algorithm [high|medium|...]
set return-to-sender [enable|disable]
set learn-dst-from-sni [enable|disable]
set dstport-from-incoming [enable|disable]
set header-proxy-agent [enable|disable]
set dns-mode [recursive|non-recursive|...]
next
end

```

config web-proxy explicit-proxy

Parameter	Description	Type	Size	Default						
name	object name	string	Maximum length: 35							
status	Enable/disable the explicit Web proxy for HTTP and HTTPS session.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable the explicit web proxy.</td></tr><tr><td><i>disable</i></td><td>Disable the explicit web proxy.</td></tr></table>				Option	Description	<i>enable</i>	Enable the explicit web proxy.	<i>disable</i>	Disable the explicit web proxy.
Option	Description									
<i>enable</i>	Enable the explicit web proxy.									
<i>disable</i>	Disable the explicit web proxy.									
interface	interface name	string	Maximum length: 15							

Parameter	Description	Type	Size	Default								
secure-web-proxy	Enable/disable/require the secure web proxy for HTTP and HTTPS session.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable secure webproxy.</td></tr><tr><td><i>enable</i></td><td>Enable secure webproxy access.</td></tr><tr><td><i>secure</i></td><td>Require secure webproxy access.</td></tr></table>	Option	Description	<i>disable</i>	Disable secure webproxy.	<i>enable</i>	Enable secure webproxy access.	<i>secure</i>	Require secure webproxy access.			
Option	Description											
<i>disable</i>	Disable secure webproxy.											
<i>enable</i>	Enable secure webproxy access.											
<i>secure</i>	Require secure webproxy access.											
http	Enable/disable the HTTP & HTTPS proxy.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable the HTTP & HTTPS proxy.</td></tr><tr><td><i>disable</i></td><td>Disable the HTTP & HTTPS proxy.</td></tr></table>	Option	Description	<i>enable</i>	Enable the HTTP & HTTPS proxy.	<i>disable</i>	Disable the HTTP & HTTPS proxy.					
Option	Description											
<i>enable</i>	Enable the HTTP & HTTPS proxy.											
<i>disable</i>	Disable the HTTP & HTTPS proxy.											
ftp-over-http	Enable to proxy FTP-over-HTTP sessions sent from a web browser.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable FTP-over-HTTP sessions.</td></tr><tr><td><i>disable</i></td><td>Disable FTP-over-HTTP sessions.</td></tr></table>	Option	Description	<i>enable</i>	Enable FTP-over-HTTP sessions.	<i>disable</i>	Disable FTP-over-HTTP sessions.					
Option	Description											
<i>enable</i>	Enable FTP-over-HTTP sessions.											
<i>disable</i>	Disable FTP-over-HTTP sessions.											
socks	Enable/disable the SOCKS proxy.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable the SOCKS proxy.</td></tr><tr><td><i>disable</i></td><td>Disable the SOCKS proxy.</td></tr></table>	Option	Description	<i>enable</i>	Enable the SOCKS proxy.	<i>disable</i>	Disable the SOCKS proxy.					
Option	Description											
<i>enable</i>	Enable the SOCKS proxy.											
<i>disable</i>	Disable the SOCKS proxy.											
http-incoming-port	Accept incoming HTTP requests on one or more ports (0 - 65535, default = 8080).	user	Not Specified									
http-connection-mode	HTTP connection mode (default = static).	option	-	static								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>static</i></td><td>Only one server connection exists during the proxy session.</td></tr><tr><td><i>multiplex</i></td><td>Established connections are held until the proxy session ends.</td></tr><tr><td><i>serverpool</i></td><td>Established connections are shared with other proxy sessions.</td></tr></table>	Option	Description	<i>static</i>	Only one server connection exists during the proxy session.	<i>multiplex</i>	Established connections are held until the proxy session ends.	<i>serverpool</i>	Established connections are shared with other proxy sessions.			
Option	Description											
<i>static</i>	Only one server connection exists during the proxy session.											
<i>multiplex</i>	Established connections are held until the proxy session ends.											
<i>serverpool</i>	Established connections are shared with other proxy sessions.											

Parameter	Description	Type	Size	Default										
https-incoming-port	Accept incoming HTTPS requests on one or more ports (0 - 65535, default = 0, use the same as HTTP).	user	Not Specified											
ftp-incoming-port	Accept incoming FTP-over-HTTP requests on one or more ports (0 - 65535, default = 0; use the same as HTTP).	user	Not Specified											
socks-incoming-port	Accept incoming SOCKS proxy requests on one or more ports (0 - 65535, default = 0; use the same as HTTP).	user	Not Specified											
secure-web-proxy-cert <name>	Name of certificates for secure web proxy. Certificate list.	string	Maximum length: 79											
ssl-dh-bits	Bit-size of Diffie-Hellman (DH) prime used in DHE-RSA negotiation (default = 2048).	option	-	2048										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>768</td><td>768-bit Diffie-Hellman prime.</td></tr><tr><td>1024</td><td>1024-bit Diffie-Hellman prime.</td></tr><tr><td>1536</td><td>1536-bit Diffie-Hellman prime.</td></tr><tr><td>2048</td><td>2048-bit Diffie-Hellman prime.</td></tr></table>	Option	Description	768	768-bit Diffie-Hellman prime.	1024	1024-bit Diffie-Hellman prime.	1536	1536-bit Diffie-Hellman prime.	2048	2048-bit Diffie-Hellman prime.			
Option	Description													
768	768-bit Diffie-Hellman prime.													
1024	1024-bit Diffie-Hellman prime.													
1536	1536-bit Diffie-Hellman prime.													
2048	2048-bit Diffie-Hellman prime.													
incoming-ip	Restrict the explicit HTTP proxy to only accept sessions from this IP address. An interface must have this IP address.	ipv4-address-any	Not Specified	0.0.0.0										
ipv6-status	Enable/disable allowing an IPv6 web proxy destination in policies and all IPv6 related entries in this command.	option	-	disable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable allowing an IPv6 web proxy destination.</td></tr><tr><td>disable</td><td>Disable allowing an IPv6 web proxy destination.</td></tr></table>	Option	Description	enable	Enable allowing an IPv6 web proxy destination.	disable	Disable allowing an IPv6 web proxy destination.							
Option	Description													
enable	Enable allowing an IPv6 web proxy destination.													
disable	Disable allowing an IPv6 web proxy destination.													
incoming-ip6	Restrict the explicit web proxy to only accept sessions from this IPv6 address. An interface must have this IPv6 address.	ipv6-address	Not Specified	::										
pref-dns-result	Prefer resolving addresses using the configured IPv4 or IPv6 DNS server (default = ipv4).	option	-	ipv4										

Parameter	Description	Type	Size	Default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ipv4</i></td><td>Send the IPv4 request first and then the IPv6 request. Use the DNS response that returns to the FortiGate first.</td></tr><tr><td><i>ipv6</i></td><td>Send the IPv6 request first and then the IPv4 request. Use the DNS response that returns to the FortiGate first.</td></tr><tr><td><i>ipv4-strict</i></td><td>Use the IPv4 DNS response. If the IPv6 DNS response arrives first, wait 50ms for the IPv4 response and then use the IPv4 response, otherwise the IPv6.</td></tr><tr><td><i>ipv6-strict</i></td><td>Use the IPv6 DNS response. If the IPv4 DNS response arrives first, wait 50ms for the IPv6 response and then use the IPv6 response, otherwise the IPv4.</td></tr></table>	Option	Description	<i>ipv4</i>	Send the IPv4 request first and then the IPv6 request. Use the DNS response that returns to the FortiGate first.	<i>ipv6</i>	Send the IPv6 request first and then the IPv4 request. Use the DNS response that returns to the FortiGate first.	<i>ipv4-strict</i>	Use the IPv4 DNS response. If the IPv6 DNS response arrives first, wait 50ms for the IPv4 response and then use the IPv4 response, otherwise the IPv6.	<i>ipv6-strict</i>	Use the IPv6 DNS response. If the IPv4 DNS response arrives first, wait 50ms for the IPv6 response and then use the IPv6 response, otherwise the IPv4.			
	Option	Description												
	<i>ipv4</i>	Send the IPv4 request first and then the IPv6 request. Use the DNS response that returns to the FortiGate first.												
	<i>ipv6</i>	Send the IPv6 request first and then the IPv4 request. Use the DNS response that returns to the FortiGate first.												
	<i>ipv4-strict</i>	Use the IPv4 DNS response. If the IPv6 DNS response arrives first, wait 50ms for the IPv4 response and then use the IPv4 response, otherwise the IPv6.												
<i>ipv6-strict</i>	Use the IPv6 DNS response. If the IPv4 DNS response arrives first, wait 50ms for the IPv6 response and then use the IPv6 response, otherwise the IPv4.													
unknown-http-version	How to handle HTTP sessions that do not comply with HTTP 0.9, 1.0, or 1.1.	option	-	reject										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>reject</i></td><td>Reject or tear down HTTP sessions that do not use HTTP 0.9, 1.0, or 1.1.</td></tr><tr><td><i>best-effort</i></td><td>Assume all HTTP sessions comply with HTTP 0.9, 1.0, or 1.1. If a session uses a different HTTP version, it may not parse correctly and the connection may be lost.</td></tr></table>	Option	Description	<i>reject</i>	Reject or tear down HTTP sessions that do not use HTTP 0.9, 1.0, or 1.1.	<i>best-effort</i>	Assume all HTTP sessions comply with HTTP 0.9, 1.0, or 1.1. If a session uses a different HTTP version, it may not parse correctly and the connection may be lost.							
	Option	Description												
	<i>reject</i>	Reject or tear down HTTP sessions that do not use HTTP 0.9, 1.0, or 1.1.												
<i>best-effort</i>	Assume all HTTP sessions comply with HTTP 0.9, 1.0, or 1.1. If a session uses a different HTTP version, it may not parse correctly and the connection may be lost.													
realm	Authentication realm used to identify the explicit web proxy (maximum of 63 characters).	string	Maximum length: 63	default										
sec-default-action	Accept or deny explicit web proxy sessions when no web proxy firewall policy exists.	option	-	deny										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>accept</i></td><td>Accept requests. All explicit web proxy traffic is accepted whether there is an explicit web proxy policy or not.</td></tr><tr><td><i>deny</i></td><td>Deny requests unless there is a matching explicit web proxy policy.</td></tr></table>	Option	Description	<i>accept</i>	Accept requests. All explicit web proxy traffic is accepted whether there is an explicit web proxy policy or not.	<i>deny</i>	Deny requests unless there is a matching explicit web proxy policy.							
	Option	Description												
	<i>accept</i>	Accept requests. All explicit web proxy traffic is accepted whether there is an explicit web proxy policy or not.												
<i>deny</i>	Deny requests unless there is a matching explicit web proxy policy.													
pac-file-server-status	Enable/disable Proxy Auto-Configuration (PAC) for users of this explicit proxy profile.	option	-	disable										

Parameter	Description	Type	Size	Default
	Option Description			
	<i>enable</i>	Enable Proxy Auto-Configuration (PAC).		
	<i>disable</i>	Disable Proxy Auto-Configuration (PAC).		
pac-file-url	PAC file access URL.	user	Not Specified	
pac-file-server-port	Port number that PAC traffic from client web browsers uses to connect to the explicit web proxy (0 - 65535, default = 0; use the same as HTTP).	user	Not Specified	
pac-file-through-https	Enable/disable to get Proxy Auto-Configuration (PAC) through HTTPS.	option	-	disable
	Option Description			
	<i>enable</i>	Enable to get Proxy Auto-Configuration (PAC) through HTTPS.		
	<i>disable</i>	Disable to get Proxy Auto-Configuration (PAC) through HTTPS.		
pac-file-name	Pac file name.	string	Maximum length: 63	proxy.pac
pac-file-data	PAC file contents enclosed in quotes (maximum of 256K bytes).	user	Not Specified	
ssl-algorithm	Relative strength of encryption algorithms accepted in HTTPS deep scan: high, medium, or low.	option	-	low
	Option Description			
	<i>high</i>	High encryption. Allow only AES and ChaCha.		
	<i>medium</i>	Medium encryption. Allow AES, ChaCha, 3DES, and RC4.		
	<i>low</i>	Low encryption. Allow AES, ChaCha, 3DES, RC4, and DES.		
return-to-sender	Enable/disable return-to-sender.	option	-	disable
	Option Description			
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
learn-dst-from-sni	Enable/disable learning destination from SNI in client hello.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable learning destination from SNI in client hello.		
	<i>disable</i>	Disable learning destination from SNI in client hello.		
dstport-from-incoming	Enable/disable reusing incoming port to connect to server.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable reusing incoming port to connect to server.		
	<i>disable</i>	Disable reusing incoming port to connect to server.		
header-proxy-agent	Enable/disable HTTP CONNECT response header Proxy-Agent.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable HTTP CONNECT response header Proxy-Agent.		
	<i>disable</i>	Disable HTTP CONNECT response header Proxy-Agent.		
dns-mode	DNS lookup mode (default=recursive).	option	-	recursive
	Option	Description		
	<i>recursive</i>	Shadow DNS database and forward.		
	<i>non-recursive</i>	Public DNS database only.		
	<i>forward-only</i>	Forward only.		

config web-proxy forward-server

Configure forward-server addresses.

```
config web-proxy forward-server
  Description: Configure forward-server addresses.
  edit <name>
    set addr-type [ip|ipv6|...]
    set ip {ipv4-address-any}
    set ipv6 {ipv6-address}
    set fqdn {string}
    set port {integer}
    set comment {string}
    set masquerade [enable|disable]
    set protocol {option1}, {option2}, ...
    set ippool <name1>, <name2>, ...
    set healthcheck [disable|enable]
```



```

        set monitor {string}
        set server-down-option [block|pass]
        set username {string}
        set password {password}
    next
end

```

config web-proxy forward-server

Parameter	Description	Type	Size	Default
name	Server name.	string	Maximum length: 63	
addr-type	Address type of the forwarding proxy server: IP or FQDN.	option	-	ip
	Option		Description	
	<i>ip</i>		Use an IPv4 address for the forwarding proxy server.	
	<i>ipv6</i>		Use an IPv6 address for the forwarding proxy server.	
	<i>fqdn</i>		Use the FQDN for the forwarding proxy server.	
ip	Forward proxy server IPv4 address.	ipv4-address-any	Not Specified	0.0.0.0
ipv6	Forward proxy server IPv6 address.	ipv6-address	Not Specified	::
fqdn	Forward server Fully Qualified Domain Name (FQDN).	string	Maximum length: 255	
port	Port number that the forwarding server expects to receive HTTP sessions on (1 - 65535, default = 3128).	integer	Minimum value: 1 Maximum value: 65535	3128
comment	Comment.	string	Maximum length: 63	
masquerade	set webproxy to use device address to connect proxy server.	option	-	disable
	Option		Description	
	<i>enable</i>		Enable using device address to connect proxy server.	
	<i>disable</i>		Disable using device address to connect proxy server.	

Parameter	Description	Type	Size	Default
protocol	Supported proxy protocols.	option	-	http socks
	Option Description			
	<i>http</i>	Support forwarding through HTTP proxy.		
	<i>socks</i>	Support forwarding through SOCKS.		
	<i>ftp</i>	Support forwarding through FTP proxy.		
ippool <name>	Name of IP pool object. IP pool name.	string	Maximum length: 79	
healthcheck	Enable/disable forward server health checking. Attempts to connect through the remote forwarding server to a destination to verify that the forwarding server is operating normally.	option	-	disable
	Option Description			
	<i>disable</i>	Disable health checking.		
	<i>enable</i>	Enable health checking.		
monitor	URL for forward server health check monitoring (default = www.google.com).	string	Maximum length: 255	www.google.com
server-down-option	Action to take when the forward server is found to be down: block sessions until the server is back up or pass sessions to their destination.	option	-	block
	Option Description			
	<i>block</i>	Block sessions until the server is back up.		
	<i>pass</i>	Pass sessions to their destination bypassing the forward server.		
username	HTTP authentication user name.	string	Maximum length: 64	
password	HTTP authentication password.	password	Not Specified	

config web-proxy forward-server-group

Configure a forward server group consisting of multiple forward servers. Supports failover and load balancing.

```
config web-proxy forward-server-group
    Description: Configure a forward server group consisting of multiple forward servers. Supports
    failover and load balancing.
    edit <name>
        set affinity [enable|disable]
        set ldb-method [weighted|least-session|...]
        set group-down-option [block|pass]
        config server-list
            Description: Add web forward servers to a list to form a server group. Optionally
            assign weights to each server.
            edit <name>
                set weight {integer}
            next
        end
    next
end
```

config web-proxy forward-server-group

Parameter	Description	Type	Size	Default
name	Configure a forward server group consisting of one or multiple forward servers. Supports failover and load balancing.	string	Maximum length: 63	
affinity	Enable/disable affinity, attaching a source-ip's traffic to the assigned forwarding server until the forward-server-affinity-timeout is reached (under web-proxy global).	option	-	enable
	Option	Description		
	<i>enable</i>	Enable affinity.		
	<i>disable</i>	Disable affinity.		
ldb-method	Load balance method: weighted or least-session.	option	-	weighted
	Option	Description		
	<i>weighted</i>	Load balance traffic to forward servers based on assigned weights. Weights are ratios of total number of sessions.		

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>least-session</i></td><td>Send new sessions to the server with lowest session count.</td></tr><tr><td><i>active-passive</i></td><td>Send new sessions to the next active server in the list. Servers are selected with highest weight first and then in order as they are configured. Traffic switches back to the first server upon failure recovery.</td></tr></table>	Option	Description	<i>least-session</i>	Send new sessions to the server with lowest session count.	<i>active-passive</i>	Send new sessions to the next active server in the list. Servers are selected with highest weight first and then in order as they are configured. Traffic switches back to the first server upon failure recovery.			
	Option	Description								
	<i>least-session</i>	Send new sessions to the server with lowest session count.								
<i>active-passive</i>	Send new sessions to the next active server in the list. Servers are selected with highest weight first and then in order as they are configured. Traffic switches back to the first server upon failure recovery.									
group-down-option	Action to take when all of the servers in the forward server group are down: block sessions until at least one server is back up or pass sessions to their destination.	option	-	block						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>block</i></td><td>Block sessions until at least one server in the group is back up.</td></tr><tr><td><i>pass</i></td><td>Pass sessions to their destination bypassing servers in the forward server group.</td></tr></table>	Option	Description	<i>block</i>	Block sessions until at least one server in the group is back up.	<i>pass</i>	Pass sessions to their destination bypassing servers in the forward server group.			
	Option	Description								
	<i>block</i>	Block sessions until at least one server in the group is back up.								
<i>pass</i>	Pass sessions to their destination bypassing servers in the forward server group.									

config server-list

Parameter	Description	Type	Size	Default
name	Forward server name.	string	Maximum length: 63	
weight	Optionally assign a weight of the forwarding server for weighted load balancing (1 - 100, default = 10).	integer	Minimum value: 1 Maximum value: 100	10

config web-proxy global

Configure Web proxy global settings.

```

config web-proxy global
  Description: Configure Web proxy global settings.
  set ssl-cert {string}
  set ssl-ca-cert {string}
  set fast-policy-match [enable|disable]
  set ldap-user-cache [enable|disable]
  set use-dynamic-pkey [enable|disable]
  set proxy-fqdn {string}
  set max-request-length {integer}
  set max-message-length {integer}
  set strict-web-check [enable|disable]

```

```

set forward-proxy-auth [enable|disable]
set forward-server-affinity-timeout {integer}
set webproxy-profile {string}
set learn-client-ip [disable|traffic-process|...]
set learn-client-ip-from-header {option1}, {option2}, ...
set learn-client-ip-srcaddr <name1>, <name2>, ...
set learn-client-ip-srcaddr6 <name1>, <name2>, ...
set src-affinity-exempt-addr {ipv4-address-any}
set src-affinity-exempt-addr6 {ipv6-address}
set strict-guest [enable|disable]
set https-replacement-message [enable|disable]
set message-upon-server-error [enable|disable]
set trace-auth-no-rsp [enable|disable]
set log-policy-pending [enable|disable]
set extended-log [enable|disable]
set log-http-transaction [disable|enable]
set log-app-id [enable|disable]
set explicit-outgoing-ip {ipv4-address-any}
set explicit-outgoing-ip6 {ipv6-address}
set realm {string}
end

```

config web-proxy global

Parameter	Description	Type	Size	Default
ssl-cert	SSL certificate for SSL interception.	string	Maximum length: 35	default-server-cert
ssl-ca-cert	SSL CA certificate for SSL interception.	string	Maximum length: 35	default-ca
fast-policy-match	Enable/disable fast matching algorithm for explicit and transparent proxy policy.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
ldap-user-cache	Enable/disable ldap user cache for explicit and transparent proxy user.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

Parameter	Description	Type	Size	Default						
use-dynamic-pkey	Enable/disable use dynamic private key in the resigned cert.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.			
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
proxy-fqdn	Fully Qualified Domain Name (FQDN) that clients connect to (default = default.fqdn) to connect to the explicit web proxy.	string	Maximum length: 255	default.fqdn						
max-request-length	Maximum length of HTTP request line (2 - 64 Kbytes, default = 8).	integer	Minimum value: 2 Maximum value: 64	8						
max-message-length	Maximum length of HTTP message, not including body (16 - 256 Kbytes, default = 32).	integer	Minimum value: 16 Maximum value: 256	32						
strict-web-check	Enable/disable strict web checking to block web sites that send incorrect headers that don't conform to HTTP 1.1.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable strict web checking.</td></tr><tr><td><i>disable</i></td><td>Disable strict web checking.</td></tr></table>	Option	Description	<i>enable</i>	Enable strict web checking.	<i>disable</i>	Disable strict web checking.			
Option	Description									
<i>enable</i>	Enable strict web checking.									
<i>disable</i>	Disable strict web checking.									
forward-proxy-auth	Enable/disable forwarding proxy authentication headers.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable forwarding proxy authentication headers.</td></tr><tr><td><i>disable</i></td><td>Disable forwarding proxy authentication headers.</td></tr></table>	Option	Description	<i>enable</i>	Enable forwarding proxy authentication headers.	<i>disable</i>	Disable forwarding proxy authentication headers.			
Option	Description									
<i>enable</i>	Enable forwarding proxy authentication headers.									
<i>disable</i>	Disable forwarding proxy authentication headers.									
forward-server-affinity-timeout	Period of time before the source IP's traffic is no longer assigned to the forwarding server (6 - 60 min, default = 30).	integer	Minimum value: 6 Maximum value: 60	30						

Parameter	Description	Type	Size	Default								
webproxy-profile	Name of the web proxy profile to apply when explicit proxy traffic is allowed by default and traffic is accepted that does not match an explicit proxy policy.	string	Maximum length: 63									
learn-client-ip	Learn the client's IP address from headers.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Do not learn the client's IP address from headers.</td></tr><tr><td><i>traffic-process</i></td><td>Learn the client's IP address from headers and use it for both policy-matching and logging.</td></tr><tr><td><i>log-only</i></td><td>Learn the client's IP address from headers and use it only for logging.</td></tr></table>	Option	Description	<i>disable</i>	Do not learn the client's IP address from headers.	<i>traffic-process</i>	Learn the client's IP address from headers and use it for both policy-matching and logging.	<i>log-only</i>	Learn the client's IP address from headers and use it only for logging.			
Option	Description											
<i>disable</i>	Do not learn the client's IP address from headers.											
<i>traffic-process</i>	Learn the client's IP address from headers and use it for both policy-matching and logging.											
<i>log-only</i>	Learn the client's IP address from headers and use it only for logging.											
learn-client-ip-from-header	Learn client IP address from the specified headers.	option	-									
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>true-client-ip</i></td><td>Learn the client IP address from the True-Client-IP header.</td></tr><tr><td><i>x-real-ip</i></td><td>Learn the client IP address from the X-Real-IP header.</td></tr><tr><td><i>x-forwarded-for</i></td><td>Learn the client IP address from the X-Forwarded-For header.</td></tr></table>	Option	Description	<i>true-client-ip</i>	Learn the client IP address from the True-Client-IP header.	<i>x-real-ip</i>	Learn the client IP address from the X-Real-IP header.	<i>x-forwarded-for</i>	Learn the client IP address from the X-Forwarded-For header.			
Option	Description											
<i>true-client-ip</i>	Learn the client IP address from the True-Client-IP header.											
<i>x-real-ip</i>	Learn the client IP address from the X-Real-IP header.											
<i>x-forwarded-for</i>	Learn the client IP address from the X-Forwarded-For header.											
learn-client-ip-srcaddr <name>	Source address name (srcaddr or srcaddr6 must be set). Address name.	string	Maximum length: 79									
learn-client-ip-srcaddr6 <name>	IPv6 Source address name (srcaddr or srcaddr6 must be set). Address name.	string	Maximum length: 79									
src-affinity-exempt-addr	IPv4 source addresses to exempt proxy affinity.	ipv4-address-any	Not Specified									
src-affinity-exempt-addr6	IPv6 source addresses to exempt proxy affinity.	ipv6-address	Not Specified									
strict-guest	Enable/disable strict guest user checking by the explicit web proxy.	option	-	disable								

Parameter	Description	Type	Size	Default
	Option Description			
	<i>enable</i>	Enable strict guest user checking.		
	<i>disable</i>	Disable strict guest user checking.		
https-replacement-message	Default action to enable or disable return replacement message for HTTPS requests.	option	-	enable
	Option Description			
	<i>enable</i>	Display a replacement message for HTTPS requests.		
	<i>disable</i>	Do not display a replacement message for HTTPS requests.		
message-upon-server-error	Enable/disable return of replacement message upon server error detection.	option	-	enable
	Option Description			
	<i>enable</i>	Display a replacement message when a server error is detected.		
	<i>disable</i>	Do not display a replacement message when a server error is detected.		
trace-auth-no-rsp	Enable/disable logging timed-out authentication requests.	option	-	disable
	Option Description			
	<i>enable</i>	Enable logging timed-out authentication requests.		
	<i>disable</i>	Disable logging timed-out authentication requests.		
log-policy-pending	Enable/disable logging sessions that are pending on policy matching.	option	-	disable
	Option Description			
	<i>enable</i>	Enable logging sessions that are pending on policy matching.		
	<i>disable</i>	Disable logging sessions that are pending on policy matching.		
extended-log	Enable/disable extended log of http transaction for implicit policy.	option	-	disable

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable logging extended http information for implicit policy.</td></tr><tr><td><i>disable</i></td><td>Disable logging extended http information for implicit policy.</td></tr></table>	Option	Description	<i>enable</i>	Enable logging extended http information for implicit policy.	<i>disable</i>	Disable logging extended http information for implicit policy.			
	Option	Description								
	<i>enable</i>	Enable logging extended http information for implicit policy.								
<i>disable</i>	Disable logging extended http information for implicit policy.									
log-http-transaction	Enable/disable http transaction log for implicit policy.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable HTTP transaction log.</td></tr><tr><td><i>enable</i></td><td>Enable HTTP transaction log</td></tr></table>	Option	Description	<i>disable</i>	Disable HTTP transaction log.	<i>enable</i>	Enable HTTP transaction log			
	Option	Description								
	<i>disable</i>	Disable HTTP transaction log.								
<i>enable</i>	Enable HTTP transaction log									
log-app-id	Enable/disable always log application type in traffic log.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable logging application type in traffic log.</td></tr><tr><td><i>disable</i></td><td>Disable logging application type in traffic log.</td></tr></table>	Option	Description	<i>enable</i>	Enable logging application type in traffic log.	<i>disable</i>	Disable logging application type in traffic log.			
	Option	Description								
	<i>enable</i>	Enable logging application type in traffic log.								
<i>disable</i>	Disable logging application type in traffic log.									
explicit-outgoing-ip	Outgoing HTTP requests by explicit webproxy will have this IP address as their source address. An interface must have this IP address.	ipv4-address-any	Not Specified							
explicit-outgoing-ip6	Outgoing HTTP requests by explicit webproxy will leave this IP. An interface must have this IP address.	ipv6-address	Not Specified							
realm	Authentication realm.	string	Maximum length: 63	default						

config web-proxy implicit-proxy-rule

Configure implicit webproxy rule.

```

config web-proxy implicit-proxy-rule
  Description: Configure implicit webproxy rule.
  edit <name>
    set load-balance-method [static|round-robin|...]
    set bypass-list <name1>, <name2>, ...
  config proxy-servers
    Description: Rule proxy server entries.
    edit <id>
      set ip {ipv4-address-any}
      set port {integer}

```

```

        set weight {integer}
      next
    end
  next
end

```

config web-proxy implicit-proxy-rule

Parameter	Description	Type	Size	Default										
name	Rule name.	string	Maximum length: 63											
load-balance-method	Method used to distribute sessions to proxies.	option	-	static										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>static</i></td><td>Distribute to server based on source IP.</td></tr><tr><td><i>round-robin</i></td><td>Distribute to server based round robin order.</td></tr><tr><td><i>first-alive</i></td><td>Distribute to the first server that is alive.</td></tr><tr><td><i>weighted</i></td><td>Distribute to server based on weight.</td></tr></table>				Option	Description	<i>static</i>	Distribute to server based on source IP.	<i>round-robin</i>	Distribute to server based round robin order.	<i>first-alive</i>	Distribute to the first server that is alive.	<i>weighted</i>	Distribute to server based on weight.
	Option	Description												
	<i>static</i>	Distribute to server based on source IP.												
	<i>round-robin</i>	Distribute to server based round robin order.												
	<i>first-alive</i>	Distribute to the first server that is alive.												
<i>weighted</i>	Distribute to server based on weight.													
bypass-list <name>	Addresses for which you do not want to use any proxy Address name.	string	Maximum length: 79											

config proxy-servers

Parameter	Description	Type	Size	Default
id	Server ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
ip	Proxy IP address.	ipv4-address-any	Not Specified	0.0.0.0
port	Proxy port number (1 - 65535, default = 8080).	integer	Minimum value: 1 Maximum value: 65535	8080

Parameter	Description	Type	Size	Default
weight	Weight of the proxy server. If weighted load balancing is enabled, the server with the highest weight gets more connections.	integer	Minimum value: 1 Maximum value: 255	1

config web-proxy implicit-proxy-setting

Configure implicit proxy browser extension setting.

```
config web-proxy implicit-proxy-setting
  Description: Configure implicit proxy browser extension setting.
  edit <name>
    set interface {string}
    set implicit-proxy-rule {string}
  next
end
```

config web-proxy implicit-proxy-setting

Parameter	Description	Type	Size	Default
name	object name	string	Maximum length: 35	
interface	interface name	string	Maximum length: 15	
implicit-proxy-rule	Implicit proxy rule name	string	Maximum length: 63	

config web-proxy isolator-server

Configure forward-server addresses.

```
config web-proxy isolator-server
  Description: Configure forward-server addresses.
  edit <name>
    set addr-type [ip|ipv6|...]
    set ip {ipv4-address-any}
    set ipv6 {ipv6-address}
    set fqdn {string}
    set port {integer}
    set comment {string}
    set masquerade [enable|disable]
    set protocol {option1}, {option2}, ...
```

```

        set ippool <name1>, <name2>, ...
    next
end

```

config web-proxy isolator-server

Parameter	Description	Type	Size	Default								
name	Server name.	string	Maximum length: 63									
addr-type	Address type of the forwarding proxy server: IP or FQDN.	option	-	ip								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>ip</i></td><td>Use an IPv4 address for the forwarding proxy server.</td></tr><tr><td><i>ipv6</i></td><td>Use an IPv6 address for the forwarding proxy server.</td></tr><tr><td><i>fqdn</i></td><td>Use the FQDN for the forwarding proxy server.</td></tr></table>				Option	Description	<i>ip</i>	Use an IPv4 address for the forwarding proxy server.	<i>ipv6</i>	Use an IPv6 address for the forwarding proxy server.	<i>fqdn</i>	Use the FQDN for the forwarding proxy server.
	Option	Description										
	<i>ip</i>	Use an IPv4 address for the forwarding proxy server.										
	<i>ipv6</i>	Use an IPv6 address for the forwarding proxy server.										
<i>fqdn</i>	Use the FQDN for the forwarding proxy server.											
ip	Forward proxy server IPv4 address.	ipv4-address-any	Not Specified	0.0.0.0								
ipv6	Forward proxy server IPv6 address.	ipv6-address	Not Specified	::								
fqdn	Forward server Fully Qualified Domain Name (FQDN).	string	Maximum length: 255									
port	Port number that the forwarding server expects to receive HTTP sessions on (1 - 65535, default = 3128).	integer	Minimum value: 1 Maximum value: 65535	3128								
comment	Comment.	string	Maximum length: 63									
masquerade	set webproxy to use device address to connect proxy server.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable using device address to connect proxy server.</td></tr><tr><td><i>disable</i></td><td>Disable using device address to connect proxy server.</td></tr></table>				Option	Description	<i>enable</i>	Enable using device address to connect proxy server.	<i>disable</i>	Disable using device address to connect proxy server.		
	Option	Description										
	<i>enable</i>	Enable using device address to connect proxy server.										
<i>disable</i>	Disable using device address to connect proxy server.											
protocol	Supported proxy protocols.	option	-	http socks								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>http</i>	Support forwarding through HTTP proxy.		
	<i>socks</i>	Support forwarding through SOCKS.		
ippool <name>	Name of IP pool object. IP pool name.	string	Maximum length: 79	

config web-proxy pac-policy

Configure explicit Web proxy pac policy.

```
config web-proxy pac-policy
  Description: Configure explicit Web proxy pac policy.
  edit <policyid>
    set status [enable|disable]
    set srcaddr <name1>, <name2>, ...
    set srcaddr6 <name1>, <name2>, ...
    set dstaddr <name1>, <name2>, ...
    set pac-file-name {string}
    set pac-file-data {user}
    set comments {var-string}
  next
end
```

config web-proxy pac-policy

Parameter	Description	Type	Size	Default
policyid	Policy ID.	integer	Minimum value: 1 Maximum value: 100	0
status	Enable/disable policy.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable policy.		
	<i>disable</i>	Disable policy.		
srcaddr <name>	Source address objects. Address name.	string	Maximum length: 79	

Parameter	Description	Type	Size	Default
srcaddr6 <name>	Source address6 objects. Address name.	string	Maximum length: 79	
dstaddr <name>	Destination address objects. Address name.	string	Maximum length: 79	
pac-file-name	Pac file name.	string	Maximum length: 63	proxy.pac
pac-file-data	PAC file contents enclosed in quotes (maximum of 256K bytes).	user	Not Specified	
comments	Optional comments.	var- string	Maximum length: 1023	

config web-proxy profile

Configure web proxy profiles.

```

config web-proxy profile
  Description: Configure web proxy profiles.
  edit <name>
    set max-cache-object-size {integer}
    set header-client-ip [pass|add|...]
    set header-via-request [pass|add|...]
    set header-via-response [pass|add|...]
    set header-x-forwarded-for [pass|add|...]
    set header-x-forwarded-client-cert [pass|add|...]
    set header-front-end-https [pass|add|...]
    set header-x-authenticated-user [pass|add|...]
    set header-x-authenticated-groups [pass|add|...]
    set strip-encoding [enable|disable]
    set log-header-change [enable|disable]
  config headers
    Description: Configure HTTP forwarded requests headers.
    edit <id>
      set name {string}
      set dstaddr <name1>, <name2>, ...
      set dstaddr6 <name1>, <name2>, ...
      set action [add-to-request|add-to-response|...]
      set content {string}
      set base64-encoding [disable|enable]
      set add-option [append|new-on-not-found|...]
      set protocol {option1}, {option2}, ...
    next
  end
next
end

```

config web-proxy profile

Parameter	Description	Type	Size	Default
name	Profile name.	string	Maximum length: 63	
max-cache-object-size	Maximum cacheable object size in KB (0-3984384 KB (3.8 GB), default = 0.). When the value is set to 0, the max cache object size will be max-object-size under webcache settings.	integer	Minimum value: 0 Maximum value: 3984384	0
header-client-ip	Action to take on the HTTP client-IP header in forwarded requests: forwards (pass), adds, or removes the HTTP header.	option	-	pass
	Option	Description		
	<i>pass</i>	Forward the same HTTP header.		
	<i>add</i>	Add the HTTP header.		
	<i>remove</i>	Remove the HTTP header.		
header-via-request	Action to take on the HTTP via header in forwarded requests: forwards (pass), adds, or removes the HTTP header.	option	-	pass
	Option	Description		
	<i>pass</i>	Forward the same HTTP header.		
	<i>add</i>	Add the HTTP header.		
	<i>remove</i>	Remove the HTTP header.		
header-via-response	Action to take on the HTTP via header in forwarded responses: forwards (pass), adds, or removes the HTTP header.	option	-	pass
	Option	Description		
	<i>pass</i>	Forward the same HTTP header.		
	<i>add</i>	Add the HTTP header.		
	<i>remove</i>	Remove the HTTP header.		
header-x-forwarded-for	Action to take on the HTTP x-forwarded-for header in forwarded requests: forwards (pass), adds, or removes the HTTP header.	option	-	pass

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>pass</i>	Forward the same HTTP header.		
	<i>add</i>	Add the HTTP header.		
	<i>remove</i>	Remove the HTTP header.		
header-x-forwarded-client-cert	Action to take on the HTTP x-forwarded-client-cert header in forwarded requests: forwards (pass), adds, or removes the HTTP header.	option	-	pass
	Option	Description		
	<i>pass</i>	Forward the same HTTP header.		
	<i>add</i>	Add the HTTP header.		
	<i>remove</i>	Remove the HTTP header.		
header-front-end-https	Action to take on the HTTP front-end-HTTPS header in forwarded requests: forwards (pass), adds, or removes the HTTP header.	option	-	pass
	Option	Description		
	<i>pass</i>	Forward the same HTTP header.		
	<i>add</i>	Add the HTTP header.		
	<i>remove</i>	Remove the HTTP header.		
header-x-authenticated-user	Action to take on the HTTP x-authenticated-user header in forwarded requests: forwards (pass), adds, or removes the HTTP header.	option	-	pass
	Option	Description		
	<i>pass</i>	Forward the same HTTP header.		
	<i>add</i>	Add the HTTP header.		
	<i>remove</i>	Remove the HTTP header.		
header-x-authenticated-groups	Action to take on the HTTP x-authenticated-groups header in forwarded requests: forwards (pass), adds, or removes the HTTP header.	option	-	pass

Parameter	Description	Type	Size	Default								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>pass</i></td><td>Forward the same HTTP header.</td></tr><tr><td><i>add</i></td><td>Add the HTTP header.</td></tr><tr><td><i>remove</i></td><td>Remove the HTTP header.</td></tr></table>	Option	Description	<i>pass</i>	Forward the same HTTP header.	<i>add</i>	Add the HTTP header.	<i>remove</i>	Remove the HTTP header.			
	Option	Description										
	<i>pass</i>	Forward the same HTTP header.										
	<i>add</i>	Add the HTTP header.										
<i>remove</i>	Remove the HTTP header.											
strip-encoding	Enable/disable stripping unsupported encoding from the request header.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable stripping of unsupported encoding from the request header.</td></tr><tr><td><i>disable</i></td><td>Disable stripping of unsupported encoding from the request header.</td></tr></table>	Option	Description	<i>enable</i>	Enable stripping of unsupported encoding from the request header.	<i>disable</i>	Disable stripping of unsupported encoding from the request header.					
	Option	Description										
	<i>enable</i>	Enable stripping of unsupported encoding from the request header.										
<i>disable</i>	Disable stripping of unsupported encoding from the request header.											
log-header-change	Enable/disable logging HTTP header changes.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable Enable/disable logging HTTP header changes.</td></tr><tr><td><i>disable</i></td><td>Disable Enable/disable logging HTTP header changes.</td></tr></table>	Option	Description	<i>enable</i>	Enable Enable/disable logging HTTP header changes.	<i>disable</i>	Disable Enable/disable logging HTTP header changes.					
	Option	Description										
	<i>enable</i>	Enable Enable/disable logging HTTP header changes.										
<i>disable</i>	Disable Enable/disable logging HTTP header changes.											

config headers

Parameter	Description	Type	Size	Default
id	HTTP forwarded header id.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	HTTP forwarded header name.	string	Maximum length: 79	
dstaddr <name>	Destination address and address group names. Address name.	string	Maximum length: 79	
dstaddr6 <name>	Destination address and address group names (IPv6). Address name.	string	Maximum length: 79	
action	Action when the HTTP header is forwarded.	option	-	add-to-request

Parameter	Description	Type	Size	Default												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>add-to-request</i></td><td>Add the HTTP header to request.</td></tr><tr><td><i>add-to-response</i></td><td>Add the HTTP header to response.</td></tr><tr><td><i>remove-from-request</i></td><td>Remove the HTTP header from request.</td></tr><tr><td><i>remove-from-response</i></td><td>Remove the HTTP header from response.</td></tr></table>	Option	Description	<i>add-to-request</i>	Add the HTTP header to request.	<i>add-to-response</i>	Add the HTTP header to response.	<i>remove-from-request</i>	Remove the HTTP header from request.	<i>remove-from-response</i>	Remove the HTTP header from response.					
	Option	Description														
	<i>add-to-request</i>	Add the HTTP header to request.														
	<i>add-to-response</i>	Add the HTTP header to response.														
	<i>remove-from-request</i>	Remove the HTTP header from request.														
<i>remove-from-response</i>	Remove the HTTP header from response.															
content	HTTP header content.	string	Maximum length: 3999													
base64-encoding	Enable/disable use of base64 encoding of HTTP content.	option	-	disable												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable use of base64 encoding of HTTP content.</td></tr><tr><td><i>enable</i></td><td>Enable use of base64 encoding of HTTP content.</td></tr></table>	Option	Description	<i>disable</i>	Disable use of base64 encoding of HTTP content.	<i>enable</i>	Enable use of base64 encoding of HTTP content.									
	Option	Description														
	<i>disable</i>	Disable use of base64 encoding of HTTP content.														
<i>enable</i>	Enable use of base64 encoding of HTTP content.															
add-option	Configure options to append content to existing HTTP header or add new HTTP header.	option	-	new												
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>append</i></td><td>Append content to existing HTTP header or create new header if HTTP header is not found.</td></tr><tr><td><i>new-on-not-found</i></td><td>Create new header only if existing HTTP header is not found.</td></tr><tr><td><i>new</i></td><td>Create new header regardless if existing HTTP header is found or not.</td></tr><tr><td><i>replace</i></td><td>Replace content to existing HTTP header or create new header if HTTP header is not found.</td></tr><tr><td><i>replace-when-match</i></td><td>Replace content to existing HTTP header.</td></tr></table>	Option	Description	<i>append</i>	Append content to existing HTTP header or create new header if HTTP header is not found.	<i>new-on-not-found</i>	Create new header only if existing HTTP header is not found.	<i>new</i>	Create new header regardless if existing HTTP header is found or not.	<i>replace</i>	Replace content to existing HTTP header or create new header if HTTP header is not found.	<i>replace-when-match</i>	Replace content to existing HTTP header.			
	Option	Description														
	<i>append</i>	Append content to existing HTTP header or create new header if HTTP header is not found.														
	<i>new-on-not-found</i>	Create new header only if existing HTTP header is not found.														
	<i>new</i>	Create new header regardless if existing HTTP header is found or not.														
	<i>replace</i>	Replace content to existing HTTP header or create new header if HTTP header is not found.														
<i>replace-when-match</i>	Replace content to existing HTTP header.															
protocol	Configure protocol(s) to take add-option action on (HTTP, HTTPS, or both).	option	-	https http												

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>https</i>	Perform add-option action on HTTPS.		
	<i>http</i>	Perform add-option action on HTTP.		

config web-proxy redirect-profile

URL redirect profile.

```

config web-proxy redirect-profile
  Description: URL redirect profile.
  edit <name>
    config entries
      Description: URL redirect entries.
      edit <id>
        set type [simple|regex|...]
        set url {var-string}
        set redirect-url {var-string}
        set redirect-code [auto|301|...]
      next
    end
  next
end

```

config web-proxy redirect-profile

Parameter	Description	Type	Size	Default
name	Name of the redirect profile.	string	Maximum length: 35	

config entries

Parameter	Description	Type	Size	Default
id	Id.	integer	Minimum value: 0 Maximum value: 4294967295	0
type	URL match type (simple, regex or wildcard).	option	-	simple

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>simple</i>	Simple URL string.		
	<i>regex</i>	Regular expression URL string.		
	<i>wildcard</i>	Wildcard URL string.		
url	URL to be redirected.	var-string	Maximum length: 1023	
redirect-url	Redirect URL for further web proxy processing.	var-string	Maximum length: 1023	
redirect-code	Redirect code.	option	-	auto
	Option	Description		
	<i>auto</i>	Auto select status code.		
	<i>301</i>	Status code 301 Move Permanently.		
	<i>302</i>	Status code 302 Move.		
	<i>303</i>	Status code 303 See Other.		
	<i>307</i>	Status code 307 Temporary Redirect.		
	<i>308</i>	Status code 308 Permanent Redirect.		

config web-proxy url-list

URLs for web proxy.

```

config web-proxy url-list
  Description: URLs for web proxy.
  edit <name>
    set comment {var-string}
    config entries
      Description: URL list entries.
      edit <id>
        set status [enable|disable]
        set url {string}
        set type [simple|wildcard]
      next
    end
  next
end

```

config web-proxy url-list

Parameter	Description	Type	Size	Default
name	Configure a name for the URL list.	string	Maximum length: 63	
comment	Comment.	var-string	Maximum length: 255	

config entries

Parameter	Description	Type	Size	Default
id	Id.	integer	Minimum value: 0 Maximum value: 4294967295	0
status	Enable/disable the entry.	option	-	enable
	Option	Description		
	enable	Enable The URL.		
	disable	Disable The URL.		
url	URL.	string	Maximum length: 511	
type	URL type (simple, wildcard).	option	-	simple
	Option	Description		
	simple	Simple URL string.		
	wildcard	Wildcard URL string (only '*').		

config web-proxy url-match

URLs to be exempted from caching and/or to be redirected to forward server.

```
config web-proxy url-match
  Description: URLs to be exempted from caching and/or to be redirected to forward server.
  edit <name>
    set status [enable|disable]
    set explicit-web-proxy <name1>, <name2>, ...
    set type [simple|wildcard|...]
    set url-pattern {string}
```

```

    set url-list {string}
    set forward-server {string}
    set ftp-forward-server {string}
    set cache-exemption [enable|disable]
    set comment {var-string}
  next
end

```

config web-proxy url-match

Parameter	Description	Type	Size	Default								
name	Configure a name for the URL to be exempted.	string	Maximum length: 63									
status	Enable/disable URLs to be exempted from caching and/or to be redirected to forward server.	option	-	enable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable exempting the matching URLs.</td></tr><tr><td><i>disable</i></td><td>Disable exempting the matching URLs.</td></tr></table>				Option	Description	<i>enable</i>	Enable exempting the matching URLs.	<i>disable</i>	Disable exempting the matching URLs.		
Option	Description											
<i>enable</i>	Enable exempting the matching URLs.											
<i>disable</i>	Disable exempting the matching URLs.											
explicit-web-proxy <name>	Explicit Web proxy names. Explicit Web proxy name.	string	Maximum length: 79									
type	URL type (simple, wildcard, list).	option	-	simple								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>simple</i></td><td>Simple URL string.</td></tr><tr><td><i>wildcard</i></td><td>Wildcard URL string (only '*').</td></tr><tr><td><i>list</i></td><td>URL list.</td></tr></table>				Option	Description	<i>simple</i>	Simple URL string.	<i>wildcard</i>	Wildcard URL string (only '*').	<i>list</i>	URL list.
Option	Description											
<i>simple</i>	Simple URL string.											
<i>wildcard</i>	Wildcard URL string (only '*').											
<i>list</i>	URL list.											
url-pattern	URL pattern to be exempted from caching and/or to be redirected to forward server.	string	Maximum length: 511									
url-list	URL list to be exempted from caching and/or to be redirected to forward server.	string	Maximum length: 63									
forward-server	Forward server name.	string	Maximum length: 63									
ftp-forward-server	ftp forward server name.	string	Maximum length: 63									
cache-exemption	Enable/disable exempting this URL pattern from caching.	option	-	disable								

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable exempting this URL pattern from caching.		
	<i>disable</i>	Disable exempting this URL pattern from caching.		
comment	Comment.	var-string	Maximum length: 255	

config web-proxy wisp

Configure Websense Integrated Services Protocol (WISP) servers.

```

config web-proxy wisp
  Description: Configure Websense Integrated Services Protocol (WISP) servers.
  edit <name>
    set comment {var-string}
    set outgoing-ip {ipv4-address-any}
    set server-ip {ipv4-address-any}
    set server-port {integer}
    set max-connections {integer}
    set timeout {integer}
  next
end

```

config web-proxy wisp

Parameter	Description	Type	Size	Default
name	Server name.	string	Maximum length: 35	
comment	Comment.	var-string	Maximum length: 255	
outgoing-ip	WISP outgoing IP address.	ipv4-address-any	Not Specified	0.0.0.0
server-ip	WISP server IP address.	ipv4-address-any	Not Specified	0.0.0.0
server-port	WISP server port (1 - 65535, default = 15868).	integer	Minimum value: 1 Maximum value: 65535	15868

Parameter	Description	Type	Size	Default
max-connections	Maximum number of web proxy WISP connections (4 - 4096, default = 64).	integer	Minimum value: 4 Maximum value: 4096	64
timeout	Period of time before WISP requests time out (1 - 15 sec, default = 5).	integer	Minimum value: 1 Maximum value: 15	5

webcache

This section includes syntax for the following commands:

- [config webcache prefetch on page 1297](#)
- [config webcache reverse-cache-server on page 1298](#)
- [config webcache settings on page 1299](#)
- [config webcache user-agent on page 1303](#)

config webcache prefetch

Configure cache prefetch.

```
config webcache prefetch
  Description: Configure cache prefetch.
  edit <name>
    set url {string}
    set crawl-depth {integer}
    set ignore-robots [enable|disable]
    set interval {integer}
    set start-delay {integer}
    set repeat {integer}
    set user {string}
    set password {password}
    set user-agent <name1>, <name2>, ...
  next
end
```

config webcache prefetch

Parameter	Description	Type	Size	Default
name	Name of the prefetch item.	string	Maximum length: 35	
url	URL of the target.	string	Maximum length: 1023	
crawl-depth	Depth(0-16) to crawl the whole url.	integer	Minimum value: 0 Maximum value: 16	0

Parameter	Description	Type	Size	Default
ignore-robots	Ignore robots.txt specification.	option	-	disable
	Option	Description		
	<i>enable</i>	Ignore robots.txt config while crawling the url.		
	<i>disable</i>	Obey robots.txt config while crawling the url.		
interval	Time interval (in seconds) to fetch the url.	integer	Minimum value: 0 Maximum value: 608400	43200
start-delay	Delay period to start the fetching (in secondss).	integer	Minimum value: 0 Maximum value: 2422800	0
repeat	How many times repeat to fetch the url (0 - 4,200,000,000).	integer	Minimum value: 0 Maximum value: 4294967295	0
user	Username for the Web resource.	string	Maximum length: 64	
password	Password for the Web resource.	password	Not Specified	
user-agent <name>	User agents can be used by this prefetch. User agent.	string	Maximum length: 79	

config webcache reverse-cache-server

Configure reverse cache server.

```

config webcache reverse-cache-server
  Description: Configure reverse cache server.
  edit <name>
    set ip {ipv4-address-any}
    set port {integer}
    set status [enable|disable]
    set priority {integer}
  next
end

```

config webcache reverse-cache-server

Parameter	Description	Type	Size	Default						
name	Name of the reverse cache server	string	Maximum length: 35							
ip	Server IP address.	ipv4-address-any	Not Specified	0.0.0.0						
port	Server port.	integer	Minimum value: 1 Maximum value: 65535	80						
status	Enable/disable the cache server.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable the reverse-cache-server.</td></tr><tr><td><i>disable</i></td><td>Disable the reverse-cache-server.</td></tr></table>				Option	Description	<i>enable</i>	Enable the reverse-cache-server.	<i>disable</i>	Disable the reverse-cache-server.
	Option	Description								
	<i>enable</i>	Enable the reverse-cache-server.								
<i>disable</i>	Disable the reverse-cache-server.									
priority	Priority of the cache server (reserved).	integer	Minimum value: 0 Maximum value: 15	0						

config webcache settings

Configure global Web cache settings.

```
config webcache settings
  Description: Configure global Web cache settings.
  set max-object-size {integer}
  set neg-resp-time {integer}
  set fresh-factor {integer}
  set max-ttl {integer}
  set min-ttl {integer}
  set default-ttl {integer}
  set ignore-ims [enable|disable]
  set ignore-conditional [enable|disable]
  set ignore-pnc [enable|disable]
  set ignore-ie-reload [enable|disable]
  set cache-expired [enable|disable]
  set cache-cookie [enable|disable]
  set reval-pnc [enable|disable]
  set always-revalidate [enable|disable]
  set cache-by-default [enable|disable]
```

```

set host-validate [enable|disable]
set add-x-cache [enable|disable]
set x-cache-message {string}
set external [enable|disable]
set crawler-user-agent {string}
end

```

config webcache settings

Parameter	Description	Type	Size	Default
max-object-size	Maximum cacheable object size in kB (1 - 2147483 kb (2GB). All objects that exceed this are delivered to the client but not stored in the web cache.	integer	Minimum value: 1 Maximum value: 2147483	512000
neg-resp-time	Time in minutes to cache negative responses or errors (0 - 4294967295, default = 0 which means negative responses are not cached).	integer	Minimum value: 0 Maximum value: 4294967295	0
fresh-factor	Frequency that the server is checked to see if any objects have expired (1 - 100, default = 100). The higher the fresh factor, the less often the checks occur.	integer	Minimum value: 1 Maximum value: 100	100
max-ttl	Maximum time an object can stay in the web cache without checking to see if it has expired on the server (default = 7200 min (5 days); maximum = 5256000 min (10 years)).	integer	Minimum value: 1 Maximum value: 5256000	7200
min-ttl	Minimum time an object can stay in the web cache without checking to see if it has expired on the server (default = 5 min; maximum = 5256000 (10 years)).	integer	Minimum value: 1 Maximum value: 5256000	5
default-ttl	Default object expiry time (default = 1440 min (1 day); maximum = 5256000 min (10 years)). This only applies to those objects that do not have an expiry time set by the web server.	integer	Minimum value: 1 Maximum value: 5256000	1440
ignore-ims	Enable/disable ignoring the if-modified-since (IMS) header.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable ignoring the if-modified-since (IMS) header.		
	<i>disable</i>	Disable ignoring the if-modified-since (IMS) header.		
ignore-conditional	Enable/disable controlling the behavior of cache-control HTTP 1.1 header values.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable ignoring cache-control HTTP 1.1 header values.		
	<i>disable</i>	Disable ignoring cache-control HTTP 1.1 header values.		
ignore-pnc	Enable/disable ignoring the pragma no-cache (PNC) header.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable ignoring the pragma no-cache (PNC) header.		
	<i>disable</i>	Disable ignoring the pragma no-cache (PNC) header.		
ignore-ie-reload	Enable/disable ignoring the PNC-interpretation of Internet Explorer's Accept: / header.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable ignoring the PNC-interpretation of Internet Explorer's Accept: / header.		
	<i>disable</i>	Disable ignoring the PNC-interpretation of Internet Explorer's Accept: / header.		
cache-expired	Enable/disable caching type-1 objects that are already expired on arrival.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable caching type-1 objects that have expired.		
	<i>disable</i>	Disable caching type-1 objects that have expired.		
cache-cookie	Enable/disable caching cookies. Since cookies contain information for or about individual users, they not usually cached.	option	-	disable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Cache cookies.		
	<i>disable</i>	Do not cache cookies.		
reval-pnc	Enable/disable revalidation of pragma-no-cache (PNC) to address bandwidth concerns.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable revalidation of pragma-no-cache (PNC).		
	<i>disable</i>	Disable revalidation of pragma-no-cache (PNC).		
always-revalidate	Enable/disable revalidation of requested cached objects, which have content on the server, before serving it to the client.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable revalidation of requested cached objects.		
	<i>disable</i>	Disable revalidation of requested cached objects.		
cache-by-default	Enable/disable caching content that lacks explicit caching policies from the server.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable caching content that lacks explicit caching policies.		
	<i>disable</i>	Disable caching content that lacks explicit caching policies.		
host-validate	Enable/disable validating "Host:" with original server IP.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable validating "Host:" with original server IP.		
	<i>disable</i>	Disable validating "Host:" with original server IP.		
add-x-cache	Enable/disable appending local "X-Cache: HIT/MISS" information when http-request is cacheable.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

Parameter	Description	Type	Size	Default						
x-cache-message	Config customized x-cache header message (use empty string to set to default).	string	Maximum length: 400							
external	Enable/disable external Web caching.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable external Web caching</td></tr><tr><td><i>disable</i></td><td>Disable external Web caching</td></tr></table>				Option	Description	<i>enable</i>	Enable external Web caching	<i>disable</i>	Disable external Web caching
	Option	Description								
	<i>enable</i>	Enable external Web caching								
<i>disable</i>	Disable external Web caching									
crawler-user-agent	The user agent that the web crawler will use.	string	Maximum length: 255	fpx						

config webcache user-agent

Configure reverse cache user agent.

```
config webcache user-agent
    Description: Configure reverse cache user agent.
    edit <name>
        set value {string}
    next
end
```

config webcache user-agent

Parameter	Description	Type	Size	Default
name	Name of the user agent item.	string	Maximum length: 35	
value	User agent of the URL.	string	Maximum length: 255	

webfilter

This section includes syntax for the following commands:

- [config webfilter categories on page 1304](#)
- [config webfilter content-header on page 1306](#)
- [config webfilter content on page 1304](#)
- [config webfilter domain-list on page 1307](#)
- [config webfilter fortiguard on page 1308](#)
- [config webfilter ftgd-local-cat on page 1311](#)
- [config webfilter ftgd-local-rating on page 1311](#)
- [config webfilter ftgd-local-risk on page 1312](#)
- [config webfilter ftgd-risk-level on page 1313](#)
- [config webfilter ftgd-statistics on page 1314](#)
- [config webfilter ips-urlfilter-cache-setting on page 1314](#)
- [config webfilter ips-urlfilter-setting on page 1314](#)
- [config webfilter ips-urlfilter-setting6 on page 1315](#)
- [config webfilter override-usr on page 1317](#)
- [config webfilter override on page 1316](#)
- [config webfilter profile on page 1318](#)
- [config webfilter search-engine on page 1336](#)
- [config webfilter status on page 1337](#)
- [config webfilter url-list on page 1341](#)
- [config webfilter urlfilter on page 1337](#)

config webfilter categories

List the FortiGuard Web Filter category descriptions.

```
config webfilter categories
    Description: List the FortiGuard Web Filter category descriptions.
end
```

config webfilter content

Configure Web filter banned word table.

```
config webfilter content
    Description: Configure Web filter banned word table.
```



```

edit <id>
  set name {string}
  set comment {var-string}
  config entries
    Description: Configure banned word entries.
    edit <name>
      set pattern-type [wildcard|regexp]
      set status [enable|disable]
      set lang [western|simch|...]
      set score {integer}
      set action [block|exempt]
    next
  end
next
end

```

config webfilter content

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Name of table.	string	Maximum length: 63	
comment	Optional comments.	var-string	Maximum length: 255	

config entries

Parameter	Description	Type	Size	Default
name	Banned word.	string	Maximum length: 127	
pattern-type	Banned word pattern type: wildcard pattern or Perl regular expression.	option	-	wildcard
	Option	Description		
	wildcard	Wildcard pattern.		
	regex	Perl regular expression.		
status	Enable/disable banned word.	option	-	disable

Parameter	Description	Type	Size	Default																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.																	
	Option	Description																						
	<i>enable</i>	Enable setting.																						
<i>disable</i>	Disable setting.																							
lang	Language of banned word.	option	-	western																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>western</i></td><td>Western.</td></tr><tr><td><i>simch</i></td><td>Simplified Chinese.</td></tr><tr><td><i>trach</i></td><td>Traditional Chinese.</td></tr><tr><td><i>japanese</i></td><td>Japanese.</td></tr><tr><td><i>korean</i></td><td>Korean.</td></tr><tr><td><i>french</i></td><td>French.</td></tr><tr><td><i>thai</i></td><td>Thai.</td></tr><tr><td><i>spanish</i></td><td>Spanish.</td></tr><tr><td><i>cyrillic</i></td><td>Cyrillic.</td></tr></table>	Option	Description	<i>western</i>	Western.	<i>simch</i>	Simplified Chinese.	<i>trach</i>	Traditional Chinese.	<i>japanese</i>	Japanese.	<i>korean</i>	Korean.	<i>french</i>	French.	<i>thai</i>	Thai.	<i>spanish</i>	Spanish.	<i>cyrillic</i>	Cyrillic.			
	Option	Description																						
	<i>western</i>	Western.																						
	<i>simch</i>	Simplified Chinese.																						
	<i>trach</i>	Traditional Chinese.																						
	<i>japanese</i>	Japanese.																						
	<i>korean</i>	Korean.																						
	<i>french</i>	French.																						
	<i>thai</i>	Thai.																						
	<i>spanish</i>	Spanish.																						
<i>cyrillic</i>	Cyrillic.																							
score	Score, to be applied every time the word appears on a web page (0 - 4294967295, default = 10).	integer	Minimum value: 0 Maximum value: 4294967295	10																				
action	Block or exempt word when a match is found.	option	-	block																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>block</i></td><td>Block matches.</td></tr><tr><td><i>exempt</i></td><td>Exempt matches.</td></tr></table>	Option	Description	<i>block</i>	Block matches.	<i>exempt</i>	Exempt matches.																	
	Option	Description																						
	<i>block</i>	Block matches.																						
<i>exempt</i>	Exempt matches.																							

config webfilter content-header

Configure content types used by Web filter.

```
config webfilter content-header
  Description: Configure content types used by Web filter.
  edit <id>
    set name {string}
    set comment {var-string}
```

```

config entries
    Description: Configure content types used by web filter.
    edit <pattern>
        set action [block|allow|...]
        set category {user}
    next
end
next
end

```

config webfilter content-header

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Name of table.	string	Maximum length: 63	
comment	Optional comments.	var-string	Maximum length: 255	

config entries

Parameter	Description	Type	Size	Default
pattern	Content type (regular expression).	string	Maximum length: 31	
action	Action to take for this content type.	option	-	allow
	Option	Description		
	<i>block</i>	Block content type.		
	<i>allow</i>	Allow content type.		
	<i>exempt</i>	Exempt content type.		
category	Categories that this content type applies to.	user	Not Specified	all

config webfilter domain-list

Configure Web filter Domain list.

```

config webfilter domain-list
  Description: Configure Web filter Domain list.
  edit <name>
    set uuid {uuid}
    set status [enable|disable]
    set comment {var-string}
    config entries
      Description: Domain list entries.
      edit <domain>
        next
      end
    end
  next
end

```

config webfilter domain-list

Parameter	Description	Type	Size	Default						
name	Domain list name.	string	Maximum length: 35							
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000						
status	Enable/disable Domain list.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable Domain list.</td></tr><tr><td><i>disable</i></td><td>Disable Domain list.</td></tr></table>				Option	Description	<i>enable</i>	Enable Domain list.	<i>disable</i>	Disable Domain list.
	Option	Description								
	<i>enable</i>	Enable Domain list.								
<i>disable</i>	Disable Domain list.									
comment	Comment.	var-string	Maximum length: 255							

config entries

Parameter	Description	Type	Size	Default
domain	Domain.	string	Maximum length: 511	

config webfilter fortiguard

Configure FortiGuard Web Filter service.

```

config webfilter fortiguard
  Description: Configure FortiGuard Web Filter service.

```

```

set cache-mode [ttl|db-ver]
set cache-prefix-match [enable|disable]
set cache-mem-percent {integer}
set ovr-auth-port-http {integer}
set ovr-auth-port-https {integer}
set ovr-auth-port-https-flow {integer}
set ovr-auth-port-warning {integer}
set ovr-auth-https [enable|disable]
set warn-auth-https [enable|disable]
set close-ports [enable|disable]
set request-packet-size-limit {integer}
set embed-image [enable|disable]
end

```

config webfilter fortiguard

Parameter	Description	Type	Size	Default						
cache-mode	Cache entry expiration mode.	option	-	ttl						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>ttl</td><td>Expire cache items by time-to-live.</td></tr><tr><td>db-ver</td><td>Expire cache items when the server DB version changes.</td></tr></table>	Option	Description	ttl	Expire cache items by time-to-live.	db-ver	Expire cache items when the server DB version changes.			
Option	Description									
ttl	Expire cache items by time-to-live.									
db-ver	Expire cache items when the server DB version changes.									
cache-prefix-match	Enable/disable prefix matching in the cache.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable setting.</td></tr><tr><td>disable</td><td>Disable setting.</td></tr></table>	Option	Description	enable	Enable setting.	disable	Disable setting.			
Option	Description									
enable	Enable setting.									
disable	Disable setting.									
cache-mem-percent	Maximum percentage of available memory allocated to caching (1 - 15).	integer	Minimum value: 1 Maximum value: 15	2						
ovrd-auth-port-http	Port to use for FortiGuard Web Filter HTTP override authentication.	integer	Minimum value: 0 Maximum value: 65535	8008						

Parameter	Description	Type	Size	Default						
ovrd-auth-port-https	Port to use for FortiGuard Web Filter HTTPS override authentication in proxy mode.	integer	Minimum value: 0 Maximum value: 65535	8010						
ovrd-auth-port-https-flow	Port to use for FortiGuard Web Filter HTTPS override authentication in flow mode.	integer	Minimum value: 0 Maximum value: 65535	8015						
ovrd-auth-port-warning	Port to use for FortiGuard Web Filter Warning override authentication.	integer	Minimum value: 0 Maximum value: 65535	8020						
ovrd-auth-https	Enable/disable use of HTTPS for override authentication.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>				Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
warn-auth-https	Enable/disable use of HTTPS for warning and authentication.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>				Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
close-ports	Close ports used for HTTP/HTTPS override authentication and disable user overrides.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>				Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.
Option	Description									
<i>enable</i>	Enable setting.									
<i>disable</i>	Disable setting.									
request-packet-size-limit	Limit size of URL request packets sent to FortiGuard server (0 for default).	integer	Minimum value: 576 Maximum value: 10000	0						

Parameter	Description	Type	Size	Default
embed-image	Enable/disable embedding images into replacement messages (default = enable).	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

config webfilter ftgd-local-cat

Configure FortiGuard Web Filter local categories.

```
config webfilter ftgd-local-cat
  Description: Configure FortiGuard Web Filter local categories.
  edit <desc>
    set status [enable|disable]
    set id {integer}
  next
end
```

config webfilter ftgd-local-cat

Parameter	Description	Type	Size	Default
status	Enable/disable the local category.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable the local category.		
	<i>disable</i>	Disable the local category.		
id	Local category ID.	integer	Minimum value: 140 Maximum value: 191	0
desc	Local category description.	string	Maximum length: 79	

config webfilter ftgd-local-rating

Configure local FortiGuard Web Filter local ratings.

```

config webfilter ftgd-local-rating
  Description: Configure local FortiGuard Web Filter local ratings.
  edit <url>
    set status [enable|disable]
    set comment {var-string}
    set rating {user}
  next
end

```

config webfilter ftgd-local-rating

Parameter	Description	Type	Size	Default						
url	URL to rate locally.	string	Maximum length: 511							
status	Enable/disable local rating.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable local rating.</td></tr><tr><td><i>disable</i></td><td>Disable local rating.</td></tr></table>				Option	Description	<i>enable</i>	Enable local rating.	<i>disable</i>	Disable local rating.
	Option	Description								
	<i>enable</i>	Enable local rating.								
<i>disable</i>	Disable local rating.									
comment	Comment.	var-string	Maximum length: 255							
rating	Local rating.	user	Not Specified							

config webfilter ftgd-local-risk

Configure FortiGuard Web Filter local risk score.

```

config webfilter ftgd-local-risk
  Description: Configure FortiGuard Web Filter local risk score.
  edit <url>
    set status [enable|disable]
    set comment {var-string}
    set risk-score {integer}
  next
end

```


config webfilter ftgd-local-risk

Parameter	Description	Type	Size	Default
url	URL to rate locally.	string	Maximum length: 511	
status	Enable/disable local risk score.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable local risk level.		
	<i>disable</i>	Disable local risk level.		
comment	Comment.	var-string	Maximum length: 255	
risk-score	Local risk score.	integer	Minimum value: 0 Maximum value: 100	0

config webfilter ftgd-risk-level

Configure FortiGuard Web Filter risk level.

```
config webfilter ftgd-risk-level
  Description: Configure FortiGuard Web Filter risk level.
  edit <name>
    set high {integer}
    set low {integer}
  next
end
```

config webfilter ftgd-risk-level

Parameter	Description	Type	Size	Default
name	Risk level name.	string	Maximum length: 35	
high	Risk level high.	integer	Minimum value: 0 Maximum value: 100	0

Parameter	Description	Type	Size	Default
low	Risk level low.	integer	Minimum value: 0 Maximum value: 100	0

config webfilter ftgd-statistics

Display rating cache and daemon statistics.

```
config webfilter ftgd-statistics
    Description: Display rating cache and daemon statistics.
end
```

config webfilter ips-urlfilter-cache-setting

Configure IPS URL filter cache settings.

```
config webfilter ips-urlfilter-cache-setting
    Description: Configure IPS URL filter cache settings.
    set dns-retry-interval {integer}
    set extended-ttl {integer}
end
```

config webfilter ips-urlfilter-cache-setting

Parameter	Description	Type	Size	Default
dns-retry-interval	Retry interval. Refresh DNS faster than TTL to capture multiple IPs for hosts. 0 means use DNS server's TTL only.	integer	Minimum value: 0 Maximum value: 2147483	0
extended-ttl	Extend time to live beyond reported by DNS. Use of 0 means use DNS server's TTL.	integer	Minimum value: 0 Maximum value: 2147483	0

config webfilter ips-urlfilter-setting

Configure IPS URL filter settings.

```

config webfilter ips-urlfilter-setting
    Description: Configure IPS URL filter settings.
    set device {string}
    set distance {integer}
    set gateway {ipv4-address}
    set geo-filter {var-string}
end

```

config webfilter ips-urlfilter-setting

Parameter	Description	Type	Size	Default
device	Interface for this route.	string	Maximum length: 35	
distance	Administrative distance (1 - 255) for this route.	integer	Minimum value: 1 Maximum value: 255	1
gateway	Gateway IP address for this route.	ipv4-address	Not Specified	0.0.0.0
geo-filter	Filter based on geographical location. Route will NOT be installed if the resolved IP address belongs to the country in the filter.	var-string	Maximum length: 255	

config webfilter ips-urlfilter-setting6

Configure IPS URL filter settings for IPv6.

```

config webfilter ips-urlfilter-setting6
    Description: Configure IPS URL filter settings for IPv6.
    set device {string}
    set distance {integer}
    set gateway6 {ipv6-address}
    set geo-filter {var-string}
end

```

config webfilter ips-urlfilter-setting6

Parameter	Description	Type	Size	Default
device	Interface for this route.	string	Maximum length: 35	

Parameter	Description	Type	Size	Default
distance	Administrative distance (1 - 255) for this route.	integer	Minimum value: 1 Maximum value: 255	1
gateway6	Gateway IPv6 address for this route.	ipv6-address	Not Specified	::
geo-filter	Filter based on geographical location. Route will NOT be installed if the resolved IPv6 address belongs to the country in the filter.	var-string	Maximum length: 255	

config webfilter override

Configure FortiGuard Web Filter administrative overrides.

```

config webfilter override
  Description: Configure FortiGuard Web Filter administrative overrides.
  edit <id>
    set status [enable|disable]
    set scope [user|user-group|...]
    set ip {ipv4-address}
    set user {string}
    set user-group {string}
    set old-profile {string}
    set new-profile {string}
    set ip6 {ipv6-address}
    set expires {user}
    set initiator {string}
  next
end

```

config webfilter override

Parameter	Description	Type	Size	Default
id	Override rule ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
status	Enable/disable override rule.	option	-	disable

Parameter	Description	Type	Size	Default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable override rule.</td></tr><tr><td><i>disable</i></td><td>Disable override rule.</td></tr></table>	Option	Description	<i>enable</i>	Enable override rule.	<i>disable</i>	Disable override rule.							
	Option	Description												
	<i>enable</i>	Enable override rule.												
<i>disable</i>	Disable override rule.													
scope	Override either the specific user, user group, IPv4 address, or IPv6 address.	option	-	user										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>user</i></td><td>Override the specified user.</td></tr><tr><td><i>user-group</i></td><td>Override the specified user group.</td></tr><tr><td><i>ip</i></td><td>Override the specified IP address.</td></tr><tr><td><i>ip6</i></td><td>Override the specified IPv6 address.</td></tr></table>	Option	Description	<i>user</i>	Override the specified user.	<i>user-group</i>	Override the specified user group.	<i>ip</i>	Override the specified IP address.	<i>ip6</i>	Override the specified IPv6 address.			
	Option	Description												
	<i>user</i>	Override the specified user.												
	<i>user-group</i>	Override the specified user group.												
	<i>ip</i>	Override the specified IP address.												
<i>ip6</i>	Override the specified IPv6 address.													
ip	IPv4 address which the override applies.	ipv4-address	Not Specified	0.0.0.0										
user	Name of the user which the override applies.	string	Maximum length: 64											
user-group	Specify the user group for which the override applies.	string	Maximum length: 63											
old-profile	Name of the web filter profile which the override applies.	string	Maximum length: 35											
new-profile	Name of the new web filter profile used by the override.	string	Maximum length: 35											
ip6	IPv6 address which the override applies.	ipv6-address	Not Specified	::										
expires	Override expiration date and time, from 5 minutes to 365 from now (format: yyyy/mm/dd hh:mm:ss).	user	Not Specified	1970/01/01 12:00:00										
initiator	Initiating user of override (read-only setting).	string	Maximum length: 64											

config webfilter override-usr

Display list of user overrides.

```
config webfilter override-usr
    Description: Display list of user overrides.
end
```

config webfilter profile

Configure Web filter profiles.

```
config webfilter profile
  Description: Configure Web filter profiles.
  edit <name>
    set comment {var-string}
    set replacemsg-group {string}
    set options {option1}, {option2}, ...
    set https-replacemsg [enable|disable]
    set ovr-d-perm {option1}, {option2}, ...
    set post-action [normal|block]
  config override
    Description: Web Filter override settings.
    set ovr-d-cookie [allow|deny]
    set ovr-d-scope [user|user-group|...]
    set profile-type [list|radius]
    set ovr-d-dur-mode [constant|ask]
    set ovr-d-dur {user}
    set profile-attribute [User-Name|NAS-IP-Address|...]
    set ovr-d-user-group <name1>, <name2>, ...
    set profile <name1>, <name2>, ...
  end
config web
  Description: Web content filtering settings.
  set bword-threshold {integer}
  set bword-table {integer}
  set urlfilter-table {integer}
  set content-header-list {integer}
  set blocklist [enable|disable]
  set allowlist {option1}, {option2}, ...
  set safe-search {option1}, {option2}, ...
  set youtube-restrict [none|strict|...]
  set qwant-restrict [none|strict|...]
  set vimeo-restrict {string}
  set log-search [enable|disable]
  set keyword-match <pattern1>, <pattern2>, ...
end
config ftgd-wf
  Description: FortiGuard Web Filter settings.
  set options {option1}, {option2}, ...
  set exempt-quota {user}
  set ovr-d {user}
  config filters
    Description: FortiGuard filters.
    edit <id>
      set category {integer}
      set action [block|authenticate|...]
      set warn-duration {user}
      set auth-usr-grp <name1>, <name2>, ...
```

```

        set log [enable|disable]
        set override-replacemsg {string}
        set warning-prompt [per-domain|per-category]
        set warning-duration-type [session|timeout]
    next
end
config risk
    Description: FortiGuard risk level settings.
    edit <id>
        set risk-level {string}
        set action [block|monitor]
        set log [enable|disable]
    next
end
config quota
    Description: FortiGuard traffic quota settings.
    edit <id>
        set category {user}
        set type [time|traffic]
        set unit [B|KB|...]
        set value {integer}
        set duration {user}
        set override-replacemsg {string}
    next
end
set max-quota-timeout {integer}
set rate-javascript-urls [disable|enable]
set rate-css-urls [disable|enable]
set rate-crl-urls [disable|enable]
end
config antiphish
    Description: AntiPhishing profile.
    set status [enable|disable]
    set default-action [exempt|log|...]
    set check-uri [enable|disable]
    set check-basic-auth [enable|disable]
    set check-username-only [enable|disable]
    set max-body-len {integer}
    config inspection-entries
        Description: AntiPhishing entries.
        edit <name>
            set fortiguard-category {user}
            set action [exempt|log|...]
        next
    end
    config custom-patterns
        Description: Custom username and password regex patterns.
        edit <pattern>
            set category [username|password]
            set type [regex|literal]
        next
    end
end

```

```

        set authentication [domain-controller|ldap]
        set domain-controller {string}
        set ldap {string}
    end
    set wisp [enable|disable]
    set wisp-servers <name1>, <name2>, ...
    set wisp-algorithm [primary-secondary|round-robin|...]
    set ia-categorization [enable|disable]
    set log-all-url [enable|disable]
    set web-content-log [enable|disable]
    set web-filter-activex-log [enable|disable]
    set web-filter-command-block-log [enable|disable]
    set web-filter-cookie-log [enable|disable]
    set web-filter-applet-log [enable|disable]
    set web-filter-jscript-log [enable|disable]
    set web-filter-js-log [enable|disable]
    set web-filter-vbs-log [enable|disable]
    set web-filter-unknown-log [enable|disable]
    set web-filter-referer-log [enable|disable]
    set web-filter-cookie-removal-log [enable|disable]
    set web-url-log [enable|disable]
    set web-invalid-domain-log [enable|disable]
    set web-ftgd-err-log [enable|disable]
    set web-ftgd-quota-usage [enable|disable]
    set web-antiphishing-log [enable|disable]
next
end

```

config webfilter profile

Parameter	Description	Type	Size	Default								
name	Profile name.	string	Maximum length: 35									
comment	Optional comments.	var-string	Maximum length: 255									
replacemsg-group	Replacement message group.	string	Maximum length: 35									
options	Options.	option	-									
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>activexfilter</i></td><td>ActiveX filter.</td></tr><tr><td><i>cookiefilter</i></td><td>Cookie filter.</td></tr><tr><td><i>javafilter</i></td><td>Java applet filter.</td></tr></table>				Option	Description	<i>activexfilter</i>	ActiveX filter.	<i>cookiefilter</i>	Cookie filter.	<i>javafilter</i>	Java applet filter.
	Option	Description										
	<i>activexfilter</i>	ActiveX filter.										
	<i>cookiefilter</i>	Cookie filter.										
<i>javafilter</i>	Java applet filter.											

Parameter	Description	Type	Size	Default																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>block-invalid-url</i></td><td>Block sessions contained an invalid domain name.</td></tr><tr><td><i>jscript</i></td><td>Javascript block.</td></tr><tr><td><i>js</i></td><td>JS block.</td></tr><tr><td><i>vbs</i></td><td>VB script block.</td></tr><tr><td><i>unknown</i></td><td>Unknown script block.</td></tr><tr><td><i>intrinsic</i></td><td>Intrinsic script block.</td></tr><tr><td><i>wf-referer</i></td><td>Referring block.</td></tr><tr><td><i>wf-cookie</i></td><td>Cookie block.</td></tr><tr><td><i>per-user-bal</i></td><td>Per-user block/allow list filter</td></tr></table>	Option	Description	<i>block-invalid-url</i>	Block sessions contained an invalid domain name.	<i>jscript</i>	Javascript block.	<i>js</i>	JS block.	<i>vbs</i>	VB script block.	<i>unknown</i>	Unknown script block.	<i>intrinsic</i>	Intrinsic script block.	<i>wf-referer</i>	Referring block.	<i>wf-cookie</i>	Cookie block.	<i>per-user-bal</i>	Per-user block/allow list filter			
	Option	Description																						
	<i>block-invalid-url</i>	Block sessions contained an invalid domain name.																						
	<i>jscript</i>	Javascript block.																						
	<i>js</i>	JS block.																						
	<i>vbs</i>	VB script block.																						
	<i>unknown</i>	Unknown script block.																						
	<i>intrinsic</i>	Intrinsic script block.																						
	<i>wf-referer</i>	Referring block.																						
	<i>wf-cookie</i>	Cookie block.																						
<i>per-user-bal</i>	Per-user block/allow list filter																							
https-replacemsg	Enable replacement messages for HTTPS.	option	-	enable																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable setting.</td></tr><tr><td><i>disable</i></td><td>Disable setting.</td></tr></table>	Option	Description	<i>enable</i>	Enable setting.	<i>disable</i>	Disable setting.																	
	Option	Description																						
	<i>enable</i>	Enable setting.																						
<i>disable</i>	Disable setting.																							
ovrd-perm	Permitted override types.	option	-																					
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>bannedword-override</i></td><td>Banned word override.</td></tr><tr><td><i>urlfilter-override</i></td><td>URL filter override.</td></tr><tr><td><i>fortiguard-wf-override</i></td><td>FortiGuard Web Filter override.</td></tr><tr><td><i>contenttype-check-override</i></td><td>Content-type header override.</td></tr></table>	Option	Description	<i>bannedword-override</i>	Banned word override.	<i>urlfilter-override</i>	URL filter override.	<i>fortiguard-wf-override</i>	FortiGuard Web Filter override.	<i>contenttype-check-override</i>	Content-type header override.													
	Option	Description																						
	<i>bannedword-override</i>	Banned word override.																						
	<i>urlfilter-override</i>	URL filter override.																						
	<i>fortiguard-wf-override</i>	FortiGuard Web Filter override.																						
<i>contenttype-check-override</i>	Content-type header override.																							
post-action	Action taken for HTTP POST traffic.	option	-	normal																				
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>normal</i></td><td>Normal, POST requests are allowed.</td></tr><tr><td><i>block</i></td><td>POST requests are blocked.</td></tr></table>	Option	Description	<i>normal</i>	Normal, POST requests are allowed.	<i>block</i>	POST requests are blocked.																	
	Option	Description																						
	<i>normal</i>	Normal, POST requests are allowed.																						
<i>block</i>	POST requests are blocked.																							
wisp	Enable/disable web proxy WISP.	option	-	disable																				

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable web proxy WISP.		
	<i>disable</i>	Disable web proxy WISP.		
wisp-servers <name>	WISP servers. Server name.	string	Maximum length: 79	
wisp-algorithm	WISP server selection algorithm.	option	-	auto-learning
	Option	Description		
	<i>primary-secondary</i>	Select the first healthy server in order.		
	<i>round-robin</i>	Select the next healthy server.		
	<i>auto-learning</i>	Select the lightest loading healthy server.		
ia-categorization	Enable/Disable use of image-analyzer engine to help categorize images with unknown category.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
log-all-url	Enable/disable logging all URLs visited.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
web-content-log	Enable/disable logging logging blocked web content.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
web-filter-activex-log	Enable/disable logging ActiveX.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
web-filter-command-block-log	Enable/disable logging blocked commands.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
web-filter-cookie-log	Enable/disable logging cookie filtering.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
web-filter-applet-log	Enable/disable logging Java applets.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
web-filter-jscript-log	Enable/disable logging JScripts.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
web-filter-js-log	Enable/disable logging Java scripts.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
web-filter-vbs-log	Enable/disable logging VBS scripts.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
web-filter-unknown-log	Enable/disable logging unknown scripts.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
web-filter-referer-log	Enable/disable logging referrers.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
web-filter-cookie-removal-log	Enable/disable logging blocked cookies.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
web-url-log	Enable/disable logging URL filtering.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
web-invalid-domain-log	Enable/disable logging invalid domain names.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
web-ftgd-err-log	Enable/disable logging rating errors.	option	-	enable

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
web-ftgd-quota-usage	Enable/disable logging daily quota usage.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
web-antiphishing-log	Enable/disable logging of AntiPhishing checks.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

config override

Parameter	Description	Type	Size	Default
ovrd-cookie	Allow/deny browser-based (cookie) overrides.	option	-	deny
	Option	Description		
	<i>allow</i>	Allow browser-based (cookie) override.		
	<i>deny</i>	Deny browser-based (cookie) override.		
ovrd-scope	Override scope.	option	-	user
	Option	Description		
	<i>user</i>	Override for the user.		
	<i>user-group</i>	Override for the user's group.		
	<i>ip</i>	Override for the initiating IP.		
	<i>browser</i>	Create browser-based (cookie) override.		
	<i>ask</i>	Prompt for scope when initiating an override.		
profile-type	Override profile type.	option	-	list

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>list</i>	Profile chosen from list.		
	<i>radius</i>	Profile determined by RADIUS server.		
ovrd-dur-mode	Override duration mode.	option	-	constant
	Option	Description		
	<i>constant</i>	Constant mode.		
	<i>ask</i>	Prompt for duration when initiating an override.		
ovrd-dur	Override duration.	user	Not Specified	15m
profile-attribute	Profile attribute to retrieve from the RADIUS server.	option	-	Login-LAT-Service
	Option	Description		
	<i>User-Name</i>	Use this attribute.		
	<i>NAS-IP-Address</i>	Use this attribute.		
	<i>Framed-IP-Address</i>	Use this attribute.		
	<i>Framed-IP-Netmask</i>	Use this attribute.		
	<i>Filter-Id</i>	Use this attribute.		
	<i>Login-IP-Host</i>	Use this attribute.		
	<i>Reply-Message</i>	Use this attribute.		
	<i>Callback-Number</i>	Use this attribute.		
	<i>Callback-Id</i>	Use this attribute.		
	<i>Framed-Route</i>	Use this attribute.		
	<i>Framed-IPX-Network</i>	Use this attribute.		
	<i>Class</i>	Use this attribute.		

Parameter	Description	Type	Size	Default																						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>Called-Station-Id</i></td><td>Use this attribute.</td></tr><tr><td><i>Calling-Station-Id</i></td><td>Use this attribute.</td></tr><tr><td><i>NAS-Identifier</i></td><td>Use this attribute.</td></tr><tr><td><i>Proxy-State</i></td><td>Use this attribute.</td></tr><tr><td><i>Login-LAT-Service</i></td><td>Use this attribute.</td></tr><tr><td><i>Login-LAT-Node</i></td><td>Use this attribute.</td></tr><tr><td><i>Login-LAT-Group</i></td><td>Use this attribute.</td></tr><tr><td><i>Framed-AppleTalk-Zone</i></td><td>Use this attribute.</td></tr><tr><td><i>Acct-Session-Id</i></td><td>Use this attribute.</td></tr><tr><td><i>Acct-Multi-Session-Id</i></td><td>Use this attribute.</td></tr></table>	Option	Description	<i>Called-Station-Id</i>	Use this attribute.	<i>Calling-Station-Id</i>	Use this attribute.	<i>NAS-Identifier</i>	Use this attribute.	<i>Proxy-State</i>	Use this attribute.	<i>Login-LAT-Service</i>	Use this attribute.	<i>Login-LAT-Node</i>	Use this attribute.	<i>Login-LAT-Group</i>	Use this attribute.	<i>Framed-AppleTalk-Zone</i>	Use this attribute.	<i>Acct-Session-Id</i>	Use this attribute.	<i>Acct-Multi-Session-Id</i>	Use this attribute.			
	Option	Description																								
	<i>Called-Station-Id</i>	Use this attribute.																								
	<i>Calling-Station-Id</i>	Use this attribute.																								
	<i>NAS-Identifier</i>	Use this attribute.																								
	<i>Proxy-State</i>	Use this attribute.																								
	<i>Login-LAT-Service</i>	Use this attribute.																								
	<i>Login-LAT-Node</i>	Use this attribute.																								
	<i>Login-LAT-Group</i>	Use this attribute.																								
	<i>Framed-AppleTalk-Zone</i>	Use this attribute.																								
<i>Acct-Session-Id</i>	Use this attribute.																									
<i>Acct-Multi-Session-Id</i>	Use this attribute.																									
ovrd-user-group <name>	User groups with permission to use the override. User group name.	string	Maximum length: 79																							
profile <name>	Web filter profile with permission to create overrides. Web profile.	string	Maximum length: 79																							

config web

Parameter	Description	Type	Size	Default
bword-threshold	Banned word score threshold.	integer	Minimum value: 0 Maximum value: 2147483647	10

Parameter	Description	Type	Size	Default														
bword-table	Banned word table ID.	integer	Minimum value: 0 Maximum value: 4294967295	0														
urlfilter-table	URL filter table ID.	integer	Minimum value: 0 Maximum value: 4294967295	0														
content-header-list	Content header list.	integer	Minimum value: 0 Maximum value: 4294967295	0														
blocklist	Enable/disable automatic addition of URLs detected by FortiSandbox to blocklist.	option	-	disable														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>enable</td><td>Enable setting.</td></tr><tr><td>disable</td><td>Disable setting.</td></tr></table>				Option	Description	enable	Enable setting.	disable	Disable setting.								
Option	Description																	
enable	Enable setting.																	
disable	Disable setting.																	
allowlist	FortiGuard allowlist settings.	option	-															
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>exempt-av</td><td>Exempt antivirus.</td></tr><tr><td>exempt-webcontent</td><td>Exempt web content.</td></tr><tr><td>exempt-activex-java-cookie</td><td>Exempt ActiveX-JAVA-Cookie.</td></tr><tr><td>exempt-dlp</td><td>Exempt DLP.</td></tr><tr><td>exempt-rangeblock</td><td>Exempt RangeBlock.</td></tr><tr><td>extended-log-others</td><td>Support extended log.</td></tr></table>				Option	Description	exempt-av	Exempt antivirus.	exempt-webcontent	Exempt web content.	exempt-activex-java-cookie	Exempt ActiveX-JAVA-Cookie.	exempt-dlp	Exempt DLP.	exempt-rangeblock	Exempt RangeBlock.	extended-log-others	Support extended log.
Option	Description																	
exempt-av	Exempt antivirus.																	
exempt-webcontent	Exempt web content.																	
exempt-activex-java-cookie	Exempt ActiveX-JAVA-Cookie.																	
exempt-dlp	Exempt DLP.																	
exempt-rangeblock	Exempt RangeBlock.																	
extended-log-others	Support extended log.																	
safe-search	Safe search type.	option	-															

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>url</i>	Insert safe search string into URL.		
	<i>header</i>	Insert safe search header.		
youtube-restrict	YouTube EDU filter level.	option	-	none
	Option	Description		
	<i>none</i>	Full access for YouTube.		
	<i>strict</i>	Strict access for YouTube.		
	<i>moderate</i>	Moderate access for YouTube.		
qwant-restrict	Qwant safe search level.	option	-	strict
	Option	Description		
	<i>none</i>	Full access for Qwant.		
	<i>strict</i>	Strict access for Qwant.		
	<i>moderate</i>	Moderate access for Qwant.		
vimeo-restrict	Set Vimeo-restrict ("7" = don't show mature content, "134" = don't show unrated and mature content). A value of cookie "content_rating".	string	Maximum length: 63	
log-search	Enable/disable logging all search phrases.	option	-	disable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
keyword-match <pattern>	Search keywords to log when match is found. Pattern/keyword to search for.	string	Maximum length: 79	

config ftgd-wf

Parameter	Description	Type	Size	Default
options	Options for FortiGuard Web Filter.	option	-	ftgd-disable

Parameter	Description	Type	Size	Default										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>error-allow</i></td><td>Allow web pages with a rating error to pass through.</td></tr><tr><td><i>rate-server-ip</i></td><td>Rate the server IP in addition to the domain name.</td></tr><tr><td><i>connect-request-bypass</i></td><td>Bypass connection which has CONNECT request.</td></tr><tr><td><i>ftgd-disable</i></td><td>Disable FortiGuard scanning.</td></tr></table>	Option	Description	<i>error-allow</i>	Allow web pages with a rating error to pass through.	<i>rate-server-ip</i>	Rate the server IP in addition to the domain name.	<i>connect-request-bypass</i>	Bypass connection which has CONNECT request.	<i>ftgd-disable</i>	Disable FortiGuard scanning.			
	Option	Description												
	<i>error-allow</i>	Allow web pages with a rating error to pass through.												
	<i>rate-server-ip</i>	Rate the server IP in addition to the domain name.												
	<i>connect-request-bypass</i>	Bypass connection which has CONNECT request.												
<i>ftgd-disable</i>	Disable FortiGuard scanning.													
exempt-quota	Do not stop quota for these categories.	user	Not Specified	17										
ovrd	Allow web filter profile overrides.	user	Not Specified											
max-quota-timeout	Maximum FortiGuard quota used by single page view in seconds (excludes streams).	integer	Minimum value: 1 Maximum value: 86400	300										
rate-javascript-urls	Enable/disable rating JavaScript by URL.	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable rating JavaScript by URL.</td></tr><tr><td><i>enable</i></td><td>Enable rating JavaScript by URL.</td></tr></table>	Option	Description	<i>disable</i>	Disable rating JavaScript by URL.	<i>enable</i>	Enable rating JavaScript by URL.							
	Option	Description												
	<i>disable</i>	Disable rating JavaScript by URL.												
<i>enable</i>	Enable rating JavaScript by URL.													
rate-css-urls	Enable/disable rating CSS by URL.	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable rating CSS by URL.</td></tr><tr><td><i>enable</i></td><td>Enable rating CSS by URL.</td></tr></table>	Option	Description	<i>disable</i>	Disable rating CSS by URL.	<i>enable</i>	Enable rating CSS by URL.							
	Option	Description												
	<i>disable</i>	Disable rating CSS by URL.												
<i>enable</i>	Enable rating CSS by URL.													
rate-crl-urls	Enable/disable rating CRL by URL.	option	-	enable										
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>disable</i></td><td>Disable rating CRL by URL.</td></tr><tr><td><i>enable</i></td><td>Enable rating CRL by URL.</td></tr></table>	Option	Description	<i>disable</i>	Disable rating CRL by URL.	<i>enable</i>	Enable rating CRL by URL.							
	Option	Description												
	<i>disable</i>	Disable rating CRL by URL.												
<i>enable</i>	Enable rating CRL by URL.													

config filters

Parameter	Description	Type	Size	Default
id	ID number.	integer	Minimum value: 0 Maximum value: 255	0
category	Categories and groups the filter examines.	integer	Minimum value: 0 Maximum value: 255	0
action	Action to take for matches.	option	-	monitor
	Option	Description		
	<i>block</i>	Block access.		
	<i>authenticate</i>	Authenticate user before allowing access.		
	<i>monitor</i>	Allow access while logging the action.		
	<i>warning</i>	Allow access after warning the user.		
warn-duration	Duration of warnings.	user	Not Specified	5m
auth-usr-grp <name>	Groups with permission to authenticate. User group name.	string	Maximum length: 79	
log	Enable/disable logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		
override-replacemsg	Override replacement message.	string	Maximum length: 28	
warning-prompt	Warning prompts in each category or each domain.	option	-	per-category
	Option	Description		
	<i>per-domain</i>	Per-domain warnings.		
	<i>per-category</i>	Per-category warnings.		
warning-duration-type	Re-display warning after closing browser or after a timeout.	option	-	timeout

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>session</i>	After session ends.		
	<i>timeout</i>	After timeout occurs.		

config risk

Parameter	Description	Type	Size	Default
id	ID number.	integer	Minimum value: 0 Maximum value: 255	0
risk-level	Risk level to be examined.	string	Maximum length: 35	
action	Action to take for matches.	option	-	monitor
	Option	Description		
	<i>block</i>	Block access.		
	<i>monitor</i>	Allow access while logging the action.		
log	Enable/disable logging.	option	-	enable
	Option	Description		
	<i>enable</i>	Enable setting.		
	<i>disable</i>	Disable setting.		

config quota

Parameter	Description	Type	Size	Default
id	ID number.	integer	Minimum value: 0 Maximum value: 4294967295	0
category	FortiGuard categories to apply quota to (category action must be set to monitor).	user	Not Specified	
type	Quota type.	option	-	time

Parameter	Description	Type	Size	Default
	Option	Description		
	time	Use a time-based quota.		
	traffic	Use a traffic-based quota.		
unit	Traffic quota unit of measurement.	option	-	MB
	Option	Description		
	B	Quota in bytes.		
	KB	Quota in kilobytes.		
	MB	Quota in megabytes.		
	GB	Quota in gigabytes.		
value	Traffic quota value.	integer	Minimum value: 1 Maximum value: 4294967295	1024
duration	Duration of quota.	user	Not Specified	5m
override-replacemsg	Override replacement message.	string	Maximum length: 28	

config antiphish

Parameter	Description	Type	Size	Default								
status	Toggle AntiPhishing functionality.	option	-	disable								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable AntiPhishing functionality.</td></tr><tr><td><i>disable</i></td><td>Disable AntiPhishing functionality.</td></tr></table>	Option	Description	<i>enable</i>	Enable AntiPhishing functionality.	<i>disable</i>	Disable AntiPhishing functionality.					
Option	Description											
<i>enable</i>	Enable AntiPhishing functionality.											
<i>disable</i>	Disable AntiPhishing functionality.											
default-action	Action to be taken when there is no matching rule.	option	-	exempt								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>exempt</i></td><td>Exempt requests from matching.</td></tr><tr><td><i>log</i></td><td>Log all matched requests.</td></tr><tr><td><i>block</i></td><td>Block all matched requests.</td></tr></table>	Option	Description	<i>exempt</i>	Exempt requests from matching.	<i>log</i>	Log all matched requests.	<i>block</i>	Block all matched requests.			
Option	Description											
<i>exempt</i>	Exempt requests from matching.											
<i>log</i>	Log all matched requests.											
<i>block</i>	Block all matched requests.											

Parameter	Description	Type	Size	Default						
check-uri	Enable/disable checking of GET URI parameters for known credentials.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable checking of GET URI for username and password fields.</td></tr><tr><td><i>disable</i></td><td>Disable checking of GET URI for username and password fields.</td></tr></table>	Option	Description	<i>enable</i>	Enable checking of GET URI for username and password fields.	<i>disable</i>	Disable checking of GET URI for username and password fields.			
Option	Description									
<i>enable</i>	Enable checking of GET URI for username and password fields.									
<i>disable</i>	Disable checking of GET URI for username and password fields.									
check-basic-auth	Enable/disable checking of HTTP Basic Auth field for known credentials.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable checking of HTTP Basic Auth field for known credentials.</td></tr><tr><td><i>disable</i></td><td>Disable checking of HTTP Basic Auth field for known credentials.</td></tr></table>	Option	Description	<i>enable</i>	Enable checking of HTTP Basic Auth field for known credentials.	<i>disable</i>	Disable checking of HTTP Basic Auth field for known credentials.			
Option	Description									
<i>enable</i>	Enable checking of HTTP Basic Auth field for known credentials.									
<i>disable</i>	Disable checking of HTTP Basic Auth field for known credentials.									
check-username-only	Enable/disable username only matching of credentials. Action will be taken for valid usernames regardless of password validity.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable username only credential matches.</td></tr><tr><td><i>disable</i></td><td>Disable username only credential matches.</td></tr></table>	Option	Description	<i>enable</i>	Enable username only credential matches.	<i>disable</i>	Disable username only credential matches.			
Option	Description									
<i>enable</i>	Enable username only credential matches.									
<i>disable</i>	Disable username only credential matches.									
max-body-len	Maximum size of a POST body to check for credentials.	integer	Minimum value: 0 Maximum value: 4294967295	1024						
authentication	Authentication methods.	option	-	domain-controller						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>domain-controller</i></td><td>Domain Controller to verify user credential.</td></tr><tr><td><i>ldap</i></td><td>LDAP to verify user credential.</td></tr></table>	Option	Description	<i>domain-controller</i>	Domain Controller to verify user credential.	<i>ldap</i>	LDAP to verify user credential.			
Option	Description									
<i>domain-controller</i>	Domain Controller to verify user credential.									
<i>ldap</i>	LDAP to verify user credential.									
domain-controller	Domain for which to verify received credentials against.	string	Maximum length: 63							

Parameter	Description	Type	Size	Default
ldap	LDAP server for which to verify received credentials against.	string	Maximum length: 63	

config inspection-entries

Parameter	Description	Type	Size	Default								
name	Inspection target name.	string	Maximum length: 63									
fortiguard-category	FortiGuard category to match.	user	Not Specified	0								
action	Action to be taken upon an AntiPhishing match.	option	-	exempt								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td>exempt</td><td>Exempt requests from matching.</td></tr><tr><td>log</td><td>Log all matched requests.</td></tr><tr><td>block</td><td>Block all matched requests.</td></tr></table>				Option	Description	exempt	Exempt requests from matching.	log	Log all matched requests.	block	Block all matched requests.
Option	Description											
exempt	Exempt requests from matching.											
log	Log all matched requests.											
block	Block all matched requests.											

config custom-patterns

Parameter	Description	Type	Size	Default						
pattern	Target pattern.	string	Maximum length: 255							
category	Category that the pattern matches.	option	-	username						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>username</i></td><td>Pattern matches username fields.</td></tr><tr><td><i>password</i></td><td>Pattern matches password fields.</td></tr></table>				Option	Description	<i>username</i>	Pattern matches username fields.	<i>password</i>	Pattern matches password fields.
	Option	Description								
	<i>username</i>	Pattern matches username fields.								
<i>password</i>	Pattern matches password fields.									
type	Pattern will be treated either as a regex pattern or literal string.	option	-	regex						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>regex</i></td><td>Pattern will be treated as a regex pattern.</td></tr><tr><td><i>literal</i></td><td>Pattern will be treated as a literal string.</td></tr></table>				Option	Description	<i>regex</i>	Pattern will be treated as a regex pattern.	<i>literal</i>	Pattern will be treated as a literal string.
	Option	Description								
	<i>regex</i>	Pattern will be treated as a regex pattern.								
<i>literal</i>	Pattern will be treated as a literal string.									

config webfilter search-engine

Configure web filter search engines.

```
config webfilter search-engine
  Description: Configure web filter search engines.
  edit <name>
    set hostname {string}
    set url {string}
    set query {string}
    set safesearch [disable|url|...]
    set charset [utf-8|gb2312]
    set source-url [enable|disable]
    set safesearch-str {string}
  next
end
```

config webfilter search-engine

Parameter	Description	Type	Size	Default
name	Search engine name.	string	Maximum length: 35	
hostname	Hostname (regular expression).	string	Maximum length: 127	
url	URL (regular expression).	string	Maximum length: 127	
query	Code used to prefix a query (must end with an equals character).	string	Maximum length: 15	
safesearch	Safe search method. You can disable safe search, add the safe search string to URLs, or insert a safe search header.	option	-	disable
		Option	Description	
		<i>disable</i>	Site does not support safe search.	
		<i>url</i>	Safe search selected with a parameter in the URL.	
		<i>header</i>	Safe search selected by search header (i.e. youtube.edu).	
		<i>translate</i>	Perform URL FortiGuard check on translated URL.	
		<i>yt-pattern</i>	Pattern to match YouTube channel ID.	
		<i>yt-scan</i>	Perform IPS scan.	
		<i>yt-video</i>	Pattern to match YouTube video name.	

Parameter	Description	Type	Size	Default						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>yt-channel</i></td><td>Pattern to match YouTube channel name.</td></tr></table>	Option	Description	<i>yt-channel</i>	Pattern to match YouTube channel name.					
Option	Description									
<i>yt-channel</i>	Pattern to match YouTube channel name.									
charset	Search engine charset.	option	-	utf-8						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>utf-8</i></td><td>UTF-8 encoding.</td></tr><tr><td><i>gb2312</i></td><td>GB2312 encoding.</td></tr></table>	Option	Description	<i>utf-8</i>	UTF-8 encoding.	<i>gb2312</i>	GB2312 encoding.			
Option	Description									
<i>utf-8</i>	UTF-8 encoding.									
<i>gb2312</i>	GB2312 encoding.									
source-url	Enable/disable source url in the image search result.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable source url in image search.</td></tr><tr><td><i>disable</i></td><td>Disable source url in image search.</td></tr></table>	Option	Description	<i>enable</i>	Enable source url in image search.	<i>disable</i>	Disable source url in image search.			
Option	Description									
<i>enable</i>	Enable source url in image search.									
<i>disable</i>	Disable source url in image search.									
safesearch-str	Safe search parameter used in the URL in URL mode. In translate mode, it provides either the regex to translate the URL or the special case to translate the URL.	string	Maximum length: 255							

config webfilter status

Display rating info.

```
config webfilter status
    Description: Display rating info.
    set <refresh-rate> {string}
end
```

config webfilter status

Parameter	Description	Type	Size	Default
<refresh-rate>	Frequency to refresh the server list (sec).	string	Maximum length: -	

config webfilter urlfilter

Configure URL filter lists.

```

config webfilter urlfilter
    Description: Configure URL filter lists.
    edit <id>
        set name {string}
        set comment {var-string}
        set one-arm-ips-urlfilter [enable|disable]
        set ip-addr-block [enable|disable]
        set ip4-mapped-ip6 [enable|disable]
        set include-subdomains [enable|disable]
    config entries
        Description: URL filter entries.
        edit <id>
            set url {string}
            set type [simple|regex|...]
            set action [exempt|block|...]
            set antiphish-action [block|log]
            set status [enable|disable]
            set exempt {option1}, {option2}, ...
            set web-proxy-profile {string}
            set referrer-host {string}
            set dns-address-family [ipv4|ipv6|...]
        next
    end
next
end

```

config webfilter urlfilter

Parameter	Description	Type	Size	Default
id	ID.	integer	Minimum value: 0 Maximum value: 4294967295	0
name	Name of URL filter list.	string	Maximum length: 63	
comment	Optional comments.	var-string	Maximum length: 255	
one-arm-ips-urlfilter	Enable/disable DNS resolver for one-arm IPS URL filter operation.	option	-	disable
	Option	Description		
	enable	Enable DNS resolver for one-arm IPS URL filter operation.		
	disable	Disable DNS resolver for one-arm IPS URL filter operation.		

Parameter	Description	Type	Size	Default						
ip-addr-block	Enable/disable blocking URLs when the hostname appears as an IP address.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable blocking URLs when the hostname appears as an IP address.</td></tr><tr><td><i>disable</i></td><td>Disable blocking URLs when the hostname appears as an IP address.</td></tr></table>	Option	Description	<i>enable</i>	Enable blocking URLs when the hostname appears as an IP address.	<i>disable</i>	Disable blocking URLs when the hostname appears as an IP address.			
Option	Description									
<i>enable</i>	Enable blocking URLs when the hostname appears as an IP address.									
<i>disable</i>	Disable blocking URLs when the hostname appears as an IP address.									
ip4-mapped-ip6	Enable/disable matching of IPv4 mapped IPv6 URLs.	option	-	disable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable matching IPv4 mapped IPv6 URLs.</td></tr><tr><td><i>disable</i></td><td>Disable matching IPv4 mapped IPv6 URLs.</td></tr></table>	Option	Description	<i>enable</i>	Enable matching IPv4 mapped IPv6 URLs.	<i>disable</i>	Disable matching IPv4 mapped IPv6 URLs.			
Option	Description									
<i>enable</i>	Enable matching IPv4 mapped IPv6 URLs.									
<i>disable</i>	Disable matching IPv4 mapped IPv6 URLs.									
include-subdomains	Enable/disable matching subdomains, only applies to simple type (default: enable).	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable matching subdomains, only applies to simple type.</td></tr><tr><td><i>disable</i></td><td>Disable matching subdomains, only applies to simple type.</td></tr></table>	Option	Description	<i>enable</i>	Enable matching subdomains, only applies to simple type.	<i>disable</i>	Disable matching subdomains, only applies to simple type.			
Option	Description									
<i>enable</i>	Enable matching subdomains, only applies to simple type.									
<i>disable</i>	Disable matching subdomains, only applies to simple type.									

config entries

Parameter	Description	Type	Size	Default								
id	Id.	integer	Minimum value: 0 Maximum value: 4294967295	0								
url	URL to be filtered.	string	Maximum length: 511									
type	Filter type (simple, regex, or wildcard).	option	-	simple								
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>simple</i></td><td>Simple URL string.</td></tr><tr><td><i>regex</i></td><td>Regular expression URL string.</td></tr><tr><td><i>wildcard</i></td><td>Wildcard URL string.</td></tr></table>				Option	Description	<i>simple</i>	Simple URL string.	<i>regex</i>	Regular expression URL string.	<i>wildcard</i>	Wildcard URL string.
Option	Description											
<i>simple</i>	Simple URL string.											
<i>regex</i>	Regular expression URL string.											
<i>wildcard</i>	Wildcard URL string.											

Parameter	Description	Type	Size	Default														
action	Action to take for URL filter matches.	option	-	exempt														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>exempt</i></td><td>Exempt matches.</td></tr><tr><td><i>block</i></td><td>Block matches.</td></tr><tr><td><i>allow</i></td><td>Allow matches (no log).</td></tr><tr><td><i>monitor</i></td><td>Allow matches (with log).</td></tr></table>	Option	Description	<i>exempt</i>	Exempt matches.	<i>block</i>	Block matches.	<i>allow</i>	Allow matches (no log).	<i>monitor</i>	Allow matches (with log).							
Option	Description																	
<i>exempt</i>	Exempt matches.																	
<i>block</i>	Block matches.																	
<i>allow</i>	Allow matches (no log).																	
<i>monitor</i>	Allow matches (with log).																	
antiphish-action	Action to take for AntiPhishing matches.	option	-	block														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>block</i></td><td>Block matches.</td></tr><tr><td><i>log</i></td><td>Allow matches with log.</td></tr></table>	Option	Description	<i>block</i>	Block matches.	<i>log</i>	Allow matches with log.											
Option	Description																	
<i>block</i>	Block matches.																	
<i>log</i>	Allow matches with log.																	
status	Enable/disable this URL filter.	option	-	enable														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable this URL filter.</td></tr><tr><td><i>disable</i></td><td>Disable this URL filter.</td></tr></table>	Option	Description	<i>enable</i>	Enable this URL filter.	<i>disable</i>	Disable this URL filter.											
Option	Description																	
<i>enable</i>	Enable this URL filter.																	
<i>disable</i>	Disable this URL filter.																	
exempt	If action is set to exempt, select the security profile operations that exempt URLs skip. Separate multiple options with a space.	option	-	av web-content activex-java-cookie dlp fortiguard range-block antiphish all														
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>av</i></td><td>AntiVirus scanning.</td></tr><tr><td><i>web-content</i></td><td>Web filter content matching.</td></tr><tr><td><i>activex-java-cookie</i></td><td>ActiveX, Java, and cookie filtering.</td></tr><tr><td><i>dlp</i></td><td>DLP scanning.</td></tr><tr><td><i>fortiguard</i></td><td>FortiGuard web filtering.</td></tr><tr><td><i>range-block</i></td><td>Range block feature.</td></tr></table>	Option	Description	<i>av</i>	AntiVirus scanning.	<i>web-content</i>	Web filter content matching.	<i>activex-java-cookie</i>	ActiveX, Java, and cookie filtering.	<i>dlp</i>	DLP scanning.	<i>fortiguard</i>	FortiGuard web filtering.	<i>range-block</i>	Range block feature.			
Option	Description																	
<i>av</i>	AntiVirus scanning.																	
<i>web-content</i>	Web filter content matching.																	
<i>activex-java-cookie</i>	ActiveX, Java, and cookie filtering.																	
<i>dlp</i>	DLP scanning.																	
<i>fortiguard</i>	FortiGuard web filtering.																	
<i>range-block</i>	Range block feature.																	

Parameter	Description	Type	Size	Default
	Option	Description		
	<i>pass</i>	Pass single connection from all.		
	<i>antiphish</i>	AntiPhish credential checking.		
	<i>all</i>	Exempt from all security profiles.		
web-proxy-profile	Web proxy profile.	string	Maximum length: 63	
referrer-host	Referrer host name.	string	Maximum length: 255	
dns-address-family	Resolve IPv4 address, IPv6 address, or both from DNS server.	option	-	ipv4
	Option	Description		
	<i>ipv4</i>	Resolve IPv4 address from DNS server.		
	<i>ipv6</i>	Resolve IPv6 address from DNS server.		
	<i>both</i>	Resolve both IPv4 and IPv6 addresses from DNS server.		

config webfilter url-list

Configure Web filter URL list.

```

config webfilter url-list
  Description: Configure Web filter URL list.
  edit <name>
    set uuid {uuid}
    set status [enable|disable]
    set comment {var-string}
    config entries
      Description: URL list entries.
      edit <url>
        next
      end
    end
  next
end

```

config webfilter url-list

Parameter	Description	Type	Size	Default						
name	URL list name.	string	Maximum length: 35							
uuid	Universally Unique Identifier (UUID; automatically assigned but can be manually reset).	uuid	Not Specified	00000000-0000-0000-0000-000000000000						
status	Enable/disable URL list.	option	-	enable						
	<table><tr><th>Option</th><th>Description</th></tr><tr><td><i>enable</i></td><td>Enable URL list.</td></tr><tr><td><i>disable</i></td><td>Disable URL list.</td></tr></table>				Option	Description	<i>enable</i>	Enable URL list.	<i>disable</i>	Disable URL list.
	Option	Description								
	<i>enable</i>	Enable URL list.								
<i>disable</i>	Disable URL list.									
comment	Comment.	var-string	Maximum length: 255							

config entries

Parameter	Description	Type	Size	Default
url	URL.	string	Maximum length: 511	

CLI diagnose commands

Use diagnose commands to run debugging commands.

This section includes syntax for the following commands:

- [diagnose alertconsole on page 1344](#)
- [diagnose antivirus on page 1345](#)
- [diagnose automation on page 1348](#)
- [diagnose autoupdate on page 1348](#)
- [diagnose casb on page 1349](#)
- [diagnose debug on page 1350](#)
- [diagnose disktest on page 1414](#)
- [diagnose emailfilter on page 1416](#)
- [diagnose endpoint on page 1418](#)
- [diagnose fdsm on page 1434](#)
- [diagnose firewall on page 1440](#)
- [diagnose forticlient on page 1458](#)
- [diagnose fortiguard-resources on page 1459](#)
- [diagnose fortitoken-cloud on page 1469](#)
- [diagnose fortitoken on page 1468](#)
- [diagnose fortiview on page 1472](#)
- [diagnose geoip on page 1472](#)
- [diagnose hardware on page 1474](#)
- [diagnose http-view on page 1477](#)
- [diagnose ip on page 1478](#)
- [diagnose ip address on page 1483](#)
- [diagnose ip arp on page 1484](#)
- [diagnose ip route on page 1485](#)
- [diagnose ip tcp on page 1488](#)
- [diagnose ip udp on page 1488](#)
- [diagnose ipsec on page 1488](#)
- [diagnose ipset on page 1490](#)
- [diagnose iptables on page 1490](#)
- [diagnose ipv6 on page 1491](#)
- [diagnose ipv6 address on page 1495](#)
- [diagnose ipv6 devconf on page 1496](#)
- [diagnose ipv6 neighbor-cache on page 1496](#)
- [diagnose ipv6 route on page 1498](#)
- [diagnose lldprx on page 1498](#)
- [diagnose log on page 1502](#)

- [diagnose netlink on page 1503](#)
- [diagnose nodejs on page 1509](#)
- [diagnose oci on page 1511](#)
- [diagnose preload on page 1511](#)
- [diagnose report-runner on page 1513](#)
- [diagnose report on page 1513](#)
- [diagnose settings on page 1514](#)
- [diagnose sniffer on page 1514](#)
- [diagnose snmp on page 1517](#)
- [diagnose sys on page 1521](#)
- [diagnose test analytics-pdf-report on page 1601](#)
- [diagnose test analytics-report on page 1602](#)
- [diagnose test application on page 1602](#)
- [diagnose test authserver on page 1621](#)
- [diagnose test guest on page 1624](#)
- [diagnose test update on page 1625](#)
- [diagnose traffictest on page 1625](#)
- [diagnose user-device-store on page 1636](#)
- [diagnose user on page 1628](#)
- [diagnose vendor-mac on page 1644](#)
- [diagnose vmware on page 1645](#)
- [diagnose vpn ssl on page 1646](#)
- [diagnose wacs on page 1646](#)
- [diagnose wad on page 1647](#)
- [diagnose wadbd on page 1799](#)
- [diagnose waf on page 1800](#)
- [diagnose web-ui on page 1804](#)
- [diagnose webfilter on page 1801](#)

diagnose alertconsole

alertconsole

This topic includes the following commands:

- [diagnose alertconsole clear on page 1345](#)
- [diagnose alertconsole fgd-retrieve on page 1345](#)
- [diagnose alertconsole list on page 1345](#)
- [diagnose alertconsole test on page 1345](#)

diagnose alertconsole clear

Clear alert messages.

```
diagnose alertconsole clear
```

diagnose alertconsole fgd-retrieve

Retrieve FortiGuard alerts.

```
diagnose alertconsole fgd-retrieve
```

diagnose alertconsole list

List current alert messages.

```
diagnose alertconsole list
```

diagnose alertconsole test

Generate alert messages.

```
diagnose alertconsole test
```

diagnose antivirus

antivirus

This topic includes the following commands:

- [diagnose antivirus database-info on page 1346](#)
- [diagnose antivirus outbreak-prevention on page 1346](#)
- [diagnose antivirus outbreak-prevention statistics on page 1346](#)
- [diagnose antivirus outbreak-prevention statistics flush on page 1346](#)
- [diagnose antivirus outbreak-prevention statistics list on page 1346](#)
- [diagnose antivirus quarantine on page 1346](#)
- [diagnose antivirus quarantine delete on page 1347](#)
- [diagnose antivirus quarantine list on page 1347](#)
- [diagnose antivirus quarantine purge on page 1347](#)
- [diagnose antivirus test on page 1347](#)

diagnose antivirus database-info

AntiVirus database info.

```
diagnose antivirus database-info
```

diagnose antivirus outbreak-prevention

FortiGuard - Virus Outbreak Prevention statistics and reporting.

```
diagnose antivirus outbreak-prevention
```

diagnose antivirus outbreak-prevention statistics

Cache and daemon statistics.

```
diagnose antivirus outbreak-prevention statistics
```

diagnose antivirus outbreak-prevention statistics flush

Flush daemon and cache statistics.

```
diagnose antivirus outbreak-prevention statistics flush
```

diagnose antivirus outbreak-prevention statistics list

Display cache and daemon statistics.

```
diagnose antivirus outbreak-prevention statistics list
```

diagnose antivirus quarantine

Quarantine functions.

```
diagnose antivirus quarantine
```

diagnose antivirus quarantine delete

Delete a file in quarantine.

```
diagnose antivirus quarantine delete <checksum>
```

Parameter	Description	Type	Size
<checksum>	Checksum of the file to delete.	string	

diagnose antivirus quarantine list

List the files in quarantine.

```
diagnose antivirus quarantine list <value>
```

Parameter	Description	Type	Size
<value>	service: http, https, ftp, smtp, smtps, pop3, pop3s, imap, imaps, im, nntp status: infected, machine-learning, blocked (optional)	string	

diagnose antivirus quarantine purge

Delete all quarantined files.

```
diagnose antivirus quarantine purge
```

diagnose antivirus test

AV Engine diagnostics.

```
diagnose antivirus test <command>
```

Parameter	Description	Type	Size
<command>	Command to pass into AV engine. Please double quote the command.	string	

diagnose automation

Diagnose commands for automation stitches.

This topic includes the following commands:

- [diagnose automation test on page 1348](#)

diagnose automation test

Test automation stitches.

```
diagnose automation test
```

diagnose autoupdate

Automatic updates.

This topic includes the following commands:

- [diagnose autoupdate downgrade on page 1348](#)
- [diagnose autoupdate downgrade disable on page 1348](#)
- [diagnose autoupdate downgrade enable on page 1349](#)
- [diagnose autoupdate status on page 1349](#)
- [diagnose autoupdate versions on page 1349](#)

diagnose autoupdate downgrade

Update object downgrade status.

```
diagnose autoupdate downgrade
```

diagnose autoupdate downgrade disable

Disable Update object downgrade.

```
diagnose autoupdate downgrade disable
```

diagnose autoupdate downgrade enable

Enable Update object downgrade.

```
diagnose autoupdate downgrade enable
```

diagnose autoupdate status

Status of automatic updates.

```
diagnose autoupdate status
```

diagnose autoupdate versions

Update object versions.

```
diagnose autoupdate versions
```

diagnose casb

CASB diagnose commands.

This topic includes the following commands:

- [diagnose casb show on page 1349](#)
- [diagnose casb show apps on page 1349](#)

diagnose casb show

Show CASB database.

```
diagnose casb show
```

diagnose casb show apps

Show built-in CASB application list.

```
diagnose casb show apps
```

diagnose debug

debug

This topic includes the following commands:

- [diagnose debug admin on page 1356](#)
- [diagnose debug admin error-log on page 1356](#)
- [diagnose debug application on page 1356](#)
- [diagnose debug application acd on page 1357](#)
- [diagnose debug application acid on page 1357](#)
- [diagnose debug application alarmd on page 1357](#)
- [diagnose debug application alertmail on page 1357](#)
- [diagnose debug application alicloud-ha on page 1357](#)
- [diagnose debug application alicloud-sdn on page 1358](#)
- [diagnose debug application authd on page 1358](#)
- [diagnose debug application autod on page 1358](#)
- [diagnose debug application awsd on page 1358](#)
- [diagnose debug application azd on page 1359](#)
- [diagnose debug application azd-ha on page 1359](#)
- [diagnose debug application bfdd on page 1359](#)
- [diagnose debug application cert-update on page 1359](#)
- [diagnose debug application chassis on page 1360](#)
- [diagnose debug application cid on page 1360](#)
- [diagnose debug application clearpass on page 1360](#)
- [diagnose debug application cloudinitd on page 1360](#)
- [diagnose debug application cmp on page 1360](#)
- [diagnose debug application crl-update on page 1361](#)
- [diagnose debug application crwl on page 1361](#)
- [diagnose debug application csfd on page 1361](#)
- [diagnose debug application ddnsd on page 1362](#)
- [diagnose debug application dhcp6c on page 1362](#)
- [diagnose debug application dhcp6r on page 1362](#)
- [diagnose debug application dhcp6s on page 1362](#)
- [diagnose debug application dhcpc on page 1363](#)
- [diagnose debug application dhcprelay on page 1363](#)
- [diagnose debug application dhcps on page 1363](#)
- [diagnose debug application dlpfingerprint on page 1363](#)
- [diagnose debug application dnp on page 1364](#)
- [diagnose debug application dnsproxy on page 1364](#)
- [diagnose debug application eap_proxy on page 1364](#)
- [diagnose debug application eap_supp on page 1364](#)
- [diagnose debug application extenderd on page 1365](#)

- [diagnose debug application fclfd on page 1365](#)
- [diagnose debug application fcnacd on page 1365](#)
- [diagnose debug application fds_notify on page 1365](#)
- [diagnose debug application fgd_alert on page 1365](#)
- [diagnose debug application fgfmd on page 1366](#)
- [diagnose debug application fgtlogd on page 1366](#)
- [diagnose debug application fnbamd on page 1366](#)
- [diagnose debug application foauthd on page 1366](#)
- [diagnose debug application forticldd on page 1367](#)
- [diagnose debug application forticron on page 1367](#)
- [diagnose debug application fsd on page 1367](#)
- [diagnose debug application fsso_ldap on page 1367](#)
- [diagnose debug application fssod on page 1368](#)
- [diagnose debug application fsvrd on page 1368](#)
- [diagnose debug application ftm-push on page 1368](#)
- [diagnose debug application garpd on page 1368](#)
- [diagnose debug application gcpcd on page 1368](#)
- [diagnose debug application hamonitor on page 1369](#)
- [diagnose debug application harelay on page 1369](#)
- [diagnose debug application hasync on page 1369](#)
- [diagnose debug application hatalk on page 1369](#)
- [diagnose debug application httpsd on page 1370](#)
- [diagnose debug application ibmd on page 1370](#)
- [diagnose debug application imap on page 1370](#)
- [diagnose debug application init on page 1370](#)
- [diagnose debug application iotd on page 1371](#)
- [diagnose debug application ipamd on page 1371](#)
- [diagnose debug application ipamsd on page 1371](#)
- [diagnose debug application ipldbd on page 1371](#)
- [diagnose debug application ipsengine on page 1372](#)
- [diagnose debug application ipsmonitor on page 1372](#)
- [diagnose debug application ipsufd on page 1372](#)
- [diagnose debug application iptables on page 1372](#)
- [diagnose debug application kmiglogd on page 1372](#)
- [diagnose debug application kubed on page 1373](#)
- [diagnose debug application l2tp on page 1373](#)
- [diagnose debug application link-monitor on page 1373](#)
- [diagnose debug application link-monitor-passive on page 1373](#)
- [diagnose debug application lldptx on page 1374](#)
- [diagnose debug application locallogd on page 1374](#)
- [diagnose debug application lpmd on page 1374](#)
- [diagnose debug application miglogd on page 1374](#)
- [diagnose debug application mrd on page 1375](#)

- [diagnose debug application nethsm on page 1375](#)
- [diagnose debug application netxd on page 1375](#)
- [diagnose debug application nntp on page 1375](#)
- [diagnose debug application nodejs on page 1375](#)
- [diagnose debug application npd on page 1376](#)
- [diagnose debug application ntnxd on page 1376](#)
- [diagnose debug application ntpd on page 1376](#)
- [diagnose debug application ocid on page 1376](#)
- [diagnose debug application ocvpn on page 1377](#)
- [diagnose debug application openstackd on page 1377](#)
- [diagnose debug application ovrd on page 1377](#)
- [diagnose debug application pop3 on page 1377](#)
- [diagnose debug application ppp on page 1378](#)
- [diagnose debug application pppoe on page 1378](#)
- [diagnose debug application pptp on page 1378](#)
- [diagnose debug application pptpc on page 1378](#)
- [diagnose debug application proxy on page 1378](#)
- [diagnose debug application ptpd on page 1379](#)
- [diagnose debug application quarantine on page 1379](#)
- [diagnose debug application radius-das on page 1379](#)
- [diagnose debug application radiusd on page 1379](#)
- [diagnose debug application radvd on page 1380](#)
- [diagnose debug application reportd on page 1380](#)
- [diagnose debug application rt-router on page 1380](#)
- [diagnose debug application samld on page 1380](#)
- [diagnose debug application sapd on page 1381](#)
- [diagnose debug application sccp on page 1381](#)
- [diagnose debug application scep on page 1381](#)
- [diagnose debug application sdncd on page 1381](#)
- [diagnose debug application sdwan on page 1382](#)
- [diagnose debug application sepmd on page 1382](#)
- [diagnose debug application server-probe on page 1382](#)
- [diagnose debug application sessionsync on page 1382](#)
- [diagnose debug application sflowd on page 1383](#)
- [diagnose debug application sfupgraded on page 1383](#)
- [diagnose debug application sip on page 1383](#)
- [diagnose debug application smbcd on page 1383](#)
- [diagnose debug application smtp on page 1383](#)
- [diagnose debug application snmpd on page 1384](#)
- [diagnose debug application spareblock on page 1384](#)
- [diagnose debug application speedtest on page 1384](#)
- [diagnose debug application speedtestd on page 1384](#)
- [diagnose debug application sshd on page 1385](#)

- [diagnose debug application syslogd on page 1385](#)
- [diagnose debug application tvc on page 1385](#)
- [diagnose debug application update on page 1385](#)
- [diagnose debug application uploadd on page 1386](#)
- [diagnose debug application urlfilter on page 1386](#)
- [diagnose debug application vmtoolsd on page 1386](#)
- [diagnose debug application vmwd on page 1386](#)
- [diagnose debug application vned on page 1386](#)
- [diagnose debug application vpd on page 1387](#)
- [diagnose debug application vrrpd on page 1387](#)
- [diagnose debug application wabcs on page 1387](#)
- [diagnose debug application waocs on page 1387](#)
- [diagnose debug application wccpd on page 1388](#)
- [diagnose debug application wf_monitor on page 1388](#)
- [diagnose debug authd on page 1388](#)
- [diagnose debug authd clear on page 1388](#)
- [diagnose debug authd fsso on page 1388](#)
- [diagnose debug authd fsso clear-logons on page 1389](#)
- [diagnose debug authd fsso filter on page 1389](#)
- [diagnose debug authd fsso filter clear on page 1389](#)
- [diagnose debug authd fsso filter group on page 1389](#)
- [diagnose debug authd fsso filter server on page 1389](#)
- [diagnose debug authd fsso filter source on page 1390](#)
- [diagnose debug authd fsso filter user on page 1390](#)
- [diagnose debug authd fsso list on page 1390](#)
- [diagnose debug authd fsso refresh-groups on page 1390](#)
- [diagnose debug authd fsso refresh-logons on page 1390](#)
- [diagnose debug authd fsso server-status on page 1391](#)
- [diagnose debug authd fsso show-address on page 1391](#)
- [diagnose debug authd fsso summary on page 1391](#)
- [diagnose debug authd memory on page 1391](#)
- [diagnose debug cli on page 1391](#)
- [diagnose debug cloudinit on page 1391](#)
- [diagnose debug cloudinit clear on page 1392](#)
- [diagnose debug cloudinit show on page 1392](#)
- [diagnose debug cmdb-trace on page 1392](#)
- [diagnose debug cmdb-walk on page 1392](#)
- [diagnose debug config-error-log on page 1392](#)
- [diagnose debug config-error-log clear on page 1393](#)
- [diagnose debug config-error-log read on page 1393](#)
- [diagnose debug console on page 1393](#)
- [diagnose debug console no-user-log-msg on page 1393](#)
- [diagnose debug console no-user-log-msg disable on page 1393](#)

- [diagnose debug console no-user-log-msg enable on page 1393](#)
- [diagnose debug console retry-log-msg on page 1394](#)
- [diagnose debug console retry-log-msg disable on page 1394](#)
- [diagnose debug console retry-log-msg enable on page 1394](#)
- [diagnose debug console send on page 1394](#)
- [diagnose debug console timestamp on page 1394](#)
- [diagnose debug console timestamp disable on page 1395](#)
- [diagnose debug console timestamp enable on page 1395](#)
- [diagnose debug crashlog on page 1395](#)
- [diagnose debug crashlog clear on page 1395](#)
- [diagnose debug crashlog get on page 1395](#)
- [diagnose debug crashlog history on page 1395](#)
- [diagnose debug crashlog interval on page 1396](#)
- [diagnose debug disable on page 1396](#)
- [diagnose debug duration on page 1396](#)
- [diagnose debug enable on page 1396](#)
- [diagnose debug flow on page 1396](#)
- [diagnose debug flow filter on page 1397](#)
- [diagnose debug flow filter addr on page 1397](#)
- [diagnose debug flow filter clear on page 1397](#)
- [diagnose debug flow filter daddr on page 1397](#)
- [diagnose debug flow filter dport on page 1397](#)
- [diagnose debug flow filter negate on page 1398](#)
- [diagnose debug flow filter negate addr on page 1398](#)
- [diagnose debug flow filter negate daddr on page 1398](#)
- [diagnose debug flow filter negate dport on page 1398](#)
- [diagnose debug flow filter negate port on page 1398](#)
- [diagnose debug flow filter negate proto on page 1398](#)
- [diagnose debug flow filter negate saddr on page 1399](#)
- [diagnose debug flow filter negate sport on page 1399](#)
- [diagnose debug flow filter negate vd on page 1399](#)
- [diagnose debug flow filter port on page 1399](#)
- [diagnose debug flow filter proto on page 1399](#)
- [diagnose debug flow filter saddr on page 1400](#)
- [diagnose debug flow filter sport on page 1400](#)
- [diagnose debug flow filter vd on page 1400](#)
- [diagnose debug flow filter vd-name on page 1400](#)
- [diagnose debug flow filter6 on page 1401](#)
- [diagnose debug flow filter6 addr on page 1401](#)
- [diagnose debug flow filter6 clear on page 1401](#)
- [diagnose debug flow filter6 daddr on page 1401](#)
- [diagnose debug flow filter6 dport on page 1401](#)
- [diagnose debug flow filter6 negate on page 1402](#)

- [diagnose debug flow filter6 negate addr on page 1402](#)
- [diagnose debug flow filter6 negate daddr on page 1402](#)
- [diagnose debug flow filter6 negate dport on page 1402](#)
- [diagnose debug flow filter6 negate port on page 1402](#)
- [diagnose debug flow filter6 negate proto on page 1402](#)
- [diagnose debug flow filter6 negate saddr on page 1403](#)
- [diagnose debug flow filter6 negate sport on page 1403](#)
- [diagnose debug flow filter6 negate vd on page 1403](#)
- [diagnose debug flow filter6 port on page 1403](#)
- [diagnose debug flow filter6 proto on page 1403](#)
- [diagnose debug flow filter6 saddr on page 1404](#)
- [diagnose debug flow filter6 sport on page 1404](#)
- [diagnose debug flow filter6 vd on page 1404](#)
- [diagnose debug flow filter6 vd-name on page 1404](#)
- [diagnose debug flow show on page 1405](#)
- [diagnose debug flow show function-name on page 1405](#)
- [diagnose debug flow show function-name disable on page 1405](#)
- [diagnose debug flow show function-name enable on page 1405](#)
- [diagnose debug flow trace on page 1405](#)
- [diagnose debug flow trace start on page 1405](#)
- [diagnose debug flow trace start6 on page 1406](#)
- [diagnose debug flow trace stop on page 1406](#)
- [diagnose debug flow trace stop6 on page 1406](#)
- [diagnose debug fsso-polling on page 1406](#)
- [diagnose debug fsso-polling client on page 1406](#)
- [diagnose debug fsso-polling detail on page 1406](#)
- [diagnose debug fsso-polling group on page 1407](#)
- [diagnose debug fsso-polling refresh-user on page 1407](#)
- [diagnose debug fsso-polling set-log-source on page 1407](#)
- [diagnose debug fsso-polling summary on page 1407](#)
- [diagnose debug fsso-polling user on page 1408](#)
- [diagnose debug info on page 1408](#)
- [diagnose debug intf-band-error on page 1408](#)
- [diagnose debug kernel on page 1408](#)
- [diagnose debug kernel ha on page 1408](#)
- [diagnose debug kernel level on page 1409](#)
- [diagnose debug kernel log on page 1409](#)
- [diagnose debug kernel log clear on page 1409](#)
- [diagnose debug kernel log show on page 1409](#)
- [diagnose debug kernel sysrq on page 1409](#)
- [diagnose debug kernel sysrq command on page 1409](#)
- [diagnose debug kernel sysrq command crash on page 1410](#)
- [diagnose debug kernel sysrq disable on page 1410](#)

- [diagnose debug kernel sysrq enable on page 1410](#)
- [diagnose debug kernel sysrq status on page 1410](#)
- [diagnose debug rating on page 1410](#)
- [diagnose debug remote-extender on page 1410](#)
- [diagnose debug remote-extender extenderd on page 1411](#)
- [diagnose debug remote-extender modem-manager on page 1411](#)
- [diagnose debug report on page 1411](#)
- [diagnose debug report reset on page 1411](#)
- [diagnose debug reset on page 1411](#)
- [diagnose debug sdnc on page 1412](#)
- [diagnose debug sql-log-error on page 1412](#)
- [diagnose debug sql-log-error clear on page 1412](#)
- [diagnose debug sql-log-error read on page 1412](#)
- [diagnose debug sql-log-error status on page 1412](#)
- [diagnose debug traffic on page 1412](#)
- [diagnose debug traffic history on page 1413](#)
- [diagnose debug traffic interface on page 1413](#)
- [diagnose debug traffic peek on page 1413](#)
- [diagnose debug urlfilter on page 1413](#)
- [diagnose debug urlfilter src-addr on page 1413](#)
- [diagnose debug urlfilter test-url on page 1414](#)
- [diagnose debug vm-print-license on page 1414](#)

diagnose debug admin

Admin user.

```
diagnose debug admin
```

diagnose debug admin error-log

Last failed admin user login details.

```
diagnose debug admin error-log
```

diagnose debug application

application

```
diagnose debug application
```

diagnose debug application acd

Aggregate Controller

```
diagnose debug application acd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application acid

Cisco Application Centric Infrastructure (Direct Connection) daemon

```
diagnose debug application acid <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application alarmd

Alarmd daemon.

```
diagnose debug application alarmd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application alertmail

Alert mail daemon.

```
diagnose debug application alertmail <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application alicloud-ha

AliCloud HA controller

```
diagnose debug application alicloud-ha <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application alicloud-sdn

AliCloud SDN controller

```
diagnose debug application alicloud-sdn <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application authd

Auth daemon.

```
diagnose debug application authd <Integer> <xxx.xxx.xxx.xxx>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	
<xxx.xxx.xxx.xxx>	Specific source IP to debug some modules (e.g.fsso).	string	

diagnose debug application autod

Automation daemon.

```
diagnose debug application autod <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application awsd

Amazon Web Services (AWS) daemon.

```
diagnose debug application awsd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application azd

Microsoft Azure daemon.

```
diagnose debug application azd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application azd-ha

Microsoft Azure daemon.

```
diagnose debug application azd-ha <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application bfdd

BFD daemon.

```
diagnose debug application bfdd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application cert-update

Certificate update in forticron daemon.

```
diagnose debug application cert-update <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application chassis

Chassis daemon.

```
diagnose debug application chassis <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application cid

Device Identification daemon.

```
diagnose debug application cid <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application clearpass

ClearPass daemon.

```
diagnose debug application clearpass <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application cloudinitd

cloudinitd daemon.

```
diagnose debug application cloudinitd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application cmp

CMPv2.


```
diagnose debug application cmp <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application crl-update

CRL update in forticron daemon.

```
diagnose debug application crl-update <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application crwl

HTTP/S preload feature crawler.

```
diagnose debug application crwl <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application csfd

Security Fabric daemon.

```
diagnose debug application csfd <Integer> <serial <serialnum>|ip <ip>|direction <up|down>> <serial  
<serialnum>|ip <ip>|direction <up|down>> <enter>|negate
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	
<serial <serialnum> ip <ip> direction <up down>>	Filter by serial number, IP, or stream direction.	string	

Parameter	Description	Type	Size
<serial <serialnum> ip <ip> direction <up down>>	Filter by serial number, IP, or stream direction.	string	
<enter> negate	If negate, inverse filter.	string	

diagnose debug application ddnsd

DDNS client daemon.

```
diagnose debug application ddnsd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application dhcp6c

DHCPv6 client.

```
diagnose debug application dhcp6c <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application dhcp6r

DHCPv6 relay.

```
diagnose debug application dhcp6r <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application dhcp6s

DHCPv6 server.

```
diagnose debug application dhcp6s <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application dhcpc

DHCP client module.

```
diagnose debug application dhcpc <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application dhcprelay

DHCP relay daemon.

```
diagnose debug application dhcprelay <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application dhcps

DHCP server.

```
diagnose debug application dhcps <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application dlpfingerprint

DLP fingerprint daemon.

```
diagnose debug application dlpfingerprint <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application dnp

DNP proxy daemon.

```
diagnose debug application dnp <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application dnsproxy

DNS proxy module.

```
diagnose debug application dnsproxy <Integer> <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	
<Integer>	Daemon index.	string	

diagnose debug application eap_proxy

EAP proxy daemon.

```
diagnose debug application eap_proxy <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application eap_supp

EAP supplicant daemon.

```
diagnose debug application eap_supp <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application extenderd

Extender Wan daemon.

```
diagnose debug application extenderd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application fclfd

Fcllicense daemon.

```
diagnose debug application fclfd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application fcnacd

FortiClient NAC daemon.

```
diagnose debug application fcnacd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application fds_notify

Update notification daemon.

```
diagnose debug application fds_notify <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application fgd_alert

FortiGuard alert message.

```
diagnose debug application fgd_alert <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application fgfmd

FortiProxy/FortiManager communication daemon.

```
diagnose debug application fgfmd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application fgtlogd

fgtlogd daemon.

```
diagnose debug application fgtlogd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application fnbamd

Fortiproxy non-blocking auth daemon.

```
diagnose debug application fnbamd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application foauthd

FortiguardOverride auth daemon.

```
diagnose debug application foauthd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application forticldd

FortiCloud daemon.

```
diagnose debug application forticldd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application forticron

Forticron daemon.

```
diagnose debug application forticron <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application fsd

Forti-start daemon.

```
diagnose debug application fsd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application fsso_ldap

FSSO LDAP daemon.

```
diagnose debug application fsso_ldap <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application fssod

FSSO daemon.

```
diagnose debug application fssod <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application fsvrd

FortiService daemon.

```
diagnose debug application fsvrd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application ftm-push

FTM-Push daemon.

```
diagnose debug application ftm-push <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application garpd

VIP gratuitous ARP daemon.

```
diagnose debug application garpd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application gcpd

Google Cloud Platform daemon.


```
diagnose debug application gcpd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application hamonitord

HA monitor module.

```
diagnose debug application hamonitord <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application harelay

HA relay module.

```
diagnose debug application harelay <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application hasync

HA synchronization module.

```
diagnose debug application hasync <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application hatalk

HA protocol module.

```
diagnose debug application hatalk <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application httpsd

HTTPS daemon.

```
diagnose debug application httpsd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level. (Info = 0x01, Warning = 0x02, Error = 0x04, Critical = 0x08, All = -1, Warning/Error/Critical = 0x0E)	string	

diagnose debug application ibmd

IBM Cloud Infrastructure daemon.

```
diagnose debug application ibmd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application imap

IMAP proxy.

```
diagnose debug application imap <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application init

System init process.

```
diagnose debug application init <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application iotd

IoT device info daemon.

```
diagnose debug application iotd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application ipamd

IP Address Management daemon.

```
diagnose debug application ipamd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application ipamsd

IPAM server daemon.

```
diagnose debug application ipamsd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application ipldbd

ipldbd daemon.

```
diagnose debug application ipldbd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application ipsengine

IPS sensor.

```
diagnose debug application ipsengine <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application ipsmonitor

IPS monitor.

```
diagnose debug application ipsmonitor <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application ipsufd

IPS URL filter resolver daemon.

```
diagnose debug application ipsufd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application iptables

iptables debug trace

```
diagnose debug application iptables <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application kmiglogd

Kernel Log daemon.

```
diagnose debug application kmiglogd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application kubed

Kubernetes daemon.

```
diagnose debug application kubed <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application l2tp

L2TP daemon.

```
diagnose debug application l2tp <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application link-monitor

Link monitor daemon.

```
diagnose debug application link-monitor <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application link-monitor-passive

Link monitor daemon.

```
diagnose debug application link-monitor-passive <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application lldptx

Link Layer Discovery Protocol (LLDP) Transmitter

```
diagnose debug application lldptx <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application locallogd

locallogd daemon.

```
diagnose debug application locallogd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application lpmd

LPM daemon.

```
diagnose debug application lpmd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application miglogd

Log daemon.

```
diagnose debug application miglogd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application mrd

Mobile router daemon.

```
diagnose debug application mrd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application nethsm

NETHSM daemon.

```
diagnose debug application nethsm <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application netxd

NetX REST API daemon.

```
diagnose debug application netxd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application nntp

NNTP proxy.

```
diagnose debug application nntp <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application nodejs

Node.js daemon.

```
diagnose debug application nodejs <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level. (Info = 0x01, Warning = 0x02, Error = 0x04, All = -1, Warning/Error = 0x06)	string	

diagnose debug application npd

NP7 daemon.

```
diagnose debug application npd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application ntnxd

Nutanix Prism Central daemon.

```
diagnose debug application ntnxd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application ntpd

NTPd daemon.

```
diagnose debug application ntpd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application ocid

Oracle Cloud Infrastructure (OCI) daemon

```
diagnose debug application ocid <Integer>
```


Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application ocvpn

Overlay Controller VPN.

```
diagnose debug application ocvpn <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application openstackd

OpenStack SDN connector daemon.

```
diagnose debug application openstackd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application ovrd

Override daemon.

```
diagnose debug application ovrd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application pop3

POP3 proxy.

```
diagnose debug application pop3 <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application ppp

PPP daemon.

```
diagnose debug application ppp <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application pppoe

PPPoE client Daemon.

```
diagnose debug application pppoe <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application pptp

PPTP daemon.

```
diagnose debug application pptp <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application pptpc

PPTP client.

```
diagnose debug application pptpc <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application proxy

Proxy.

```
diagnose debug application proxy <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application ptpd

Precision Time Protocol daemon.

```
diagnose debug application ptpd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application quarantine

Quarantine daemon.

```
diagnose debug application quarantine <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application radius-das

RADIUS DAS daemon.

```
diagnose debug application radius-das <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application radiusd

RADIUS daemon.

```
diagnose debug application radiusd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application radvd

Router adv daemon.

```
diagnose debug application radvd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application reportd

report daemon

```
diagnose debug application reportd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application rt-router

RT Router daemon.

```
diagnose debug application rt-router <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application samld

SAML SSO daemon.

```
diagnose debug application samld <Integer> <verbose>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	
<verbose>	Verbose output during process. (v, vv, vvv)	string	

diagnose debug application sapd

SAP Control daemon.

```
diagnose debug application sapd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application sccp

SCCP ALG.

```
diagnose debug application sccp <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application scep

SCEP

```
diagnose debug application scep <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application sdncd

SDN Connector daemon.

```
diagnose debug application sdncd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application sdwan

SD-WAN daemon.

```
diagnose debug application sdwan <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application sepmd

Symantec EPM daemon.

```
diagnose debug application sepmd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application server-probe

Server probe daemon.

```
diagnose debug application server-probe <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application sessionsync

Session sync daemon.

```
diagnose debug application sessionsync <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application sflowd

sFlow protocol module.

```
diagnose debug application sflowd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application sfupgraded

Security Fabric Upgrade daemon.

```
diagnose debug application sfupgraded <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application sip

SIP ALG.

```
diagnose debug application sip <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application smbcd

SMB client daemon.

```
diagnose debug application smbcd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application smtp

SMTP proxy.

```
diagnose debug application smtp <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application snmpd

SNMP daemon.

```
diagnose debug application snmpd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application spareblock

Set debug spare block count.

```
diagnose debug application spareblock <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application speedtest

Speed test execution daemon.

```
diagnose debug application speedtest <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application speedtestd

Speed test server daemon.

```
diagnose debug application speedtestd <Integer>
```


Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application sshd

Sshd daemon.

```
diagnose debug application sshd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application syslogd

syslogd daemon.

```
diagnose debug application syslogd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application tvc

SSL-VPN client

```
diagnose debug application tvc <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application update

Update daemon.

```
diagnose debug application update <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application uploadd

Upload daemon.

```
diagnose debug application uploadd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application urlfilter

Urlfilter daemon.

```
diagnose debug application urlfilter <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application vmtoolsd

vmtoolsd daemon.

```
diagnose debug application vmtoolsd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application vmwd

VMware vSphere daemon

```
diagnose debug application vmwd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application vned

Virtual network enabler daemon.

```
diagnose debug application vned <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application vpd

VPN policy daemon.

```
diagnose debug application vpd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application vrrpd

VRRP daemon.

```
diagnose debug application vrrpd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application wabcs

WAN acceleration byte cache storage.

```
diagnose debug application wabcs <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application waocs

WAN acceleration object cache storage.

```
diagnose debug application waocs <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application wccpd

WCCP daemon.

```
diagnose debug application wccpd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug application wf_monitor

WF monitor, parent of urlfilter daemon.

```
diagnose debug application wf_monitor <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level.	string	

diagnose debug authd

Authentication daemon.

```
diagnose debug authd
```

diagnose debug authd clear

Clear internal data structures and keep alive sessions.

```
diagnose debug authd clear
```

diagnose debug authd fsso

FSSO client module.

```
diagnose debug authd fsso
```

diagnose debug authd fsso clear-logons

Clear logon information.

```
diagnose debug authd fsso clear-logons
```

diagnose debug authd fsso filter

Filters used for list or clear logons.

```
diagnose debug authd fsso filter
```

diagnose debug authd fsso filter clear

Clear all filters.

```
diagnose debug authd fsso filter clear
```

diagnose debug authd fsso filter group

Group name.

```
diagnose debug authd fsso filter group <name>
```

Parameter	Description	Type	Size
<name>	Group name.	string	

diagnose debug authd fsso filter server

FSSO agent name.

```
diagnose debug authd fsso filter server <name>
```

Parameter	Description	Type	Size
<name>	FSSO agent name.	string	

diagnose debug authd fsso filter source

Source IP address.

```
diagnose debug authd fsso filter source <xxx.xxx.xxx.xxx> <xxx.xxx.xxx.xxx>
```

Parameter	Description	Type	Size
<xxx.xxx.xxx.xxx>	Source IP (range from).	string	
<xxx.xxx.xxx.xxx>	Source IP (range to).	string	

diagnose debug authd fsso filter user

User name.

```
diagnose debug authd fsso filter user <name>
```

Parameter	Description	Type	Size
<name>	User name.	string	

diagnose debug authd fsso list

List current logons.

```
diagnose debug authd fsso list
```

diagnose debug authd fsso refresh-groups

Refresh group mappings.

```
diagnose debug authd fsso refresh-groups
```

diagnose debug authd fsso refresh-logons

Resync logon database.

```
diagnose debug authd fsso refresh-logons
```

diagnose debug authd fssso server-status

Show FSSO agent connection status.

```
diagnose debug authd fssso server-status
```

diagnose debug authd fssso show-address

Show FSAE dynamic addresses.

```
diagnose debug authd fssso show-address
```

diagnose debug authd fssso summary

Summary of current logons.

```
diagnose debug authd fssso summary
```

diagnose debug authd memory

Show authd memory usage information.

```
diagnose debug authd memory
```

diagnose debug cli

Debug CLI.

```
diagnose debug cli <Integer>
```

Parameter	Description	Type	Size
<Integer>	Debug level (0 - 8).	string	

diagnose debug cloudinit

Cloudinit info.

```
diagnose debug cloudinit
```

diagnose debug cloudinit clear

Clear cloudinit log info.

```
diagnose debug cloudinit clear
```

diagnose debug cloudinit show

Show cloudinit log info.

```
diagnose debug cloudinit show
```

diagnose debug cmdb-trace

Trace CLI.

```
diagnose debug cmdb-trace <Integer>
```

Parameter	Description	Type	Size
<Integer>	Trace level (0 - 2).	string	

diagnose debug cmdb-walk

enable/disable cmdb-walk.

```
diagnose debug cmdb-walk <Integer>
```

Parameter	Description	Type	Size
<Integer>	walk value (0 - 1).	string	

diagnose debug config-error-log

Configure error log info.

```
diagnose debug config-error-log
```


diagnose debug config-error-log clear

Clear config error log.

```
diagnose debug config-error-log clear
```

diagnose debug config-error-log read

Display config error on console.

```
diagnose debug config-error-log read
```

diagnose debug console

console

```
diagnose debug console
```

diagnose debug console no-user-log-msg

Console does not show user log messages.

```
diagnose debug console no-user-log-msg
```

diagnose debug console no-user-log-msg disable

Disable console no user log message.

```
diagnose debug console no-user-log-msg disable
```

diagnose debug console no-user-log-msg enable

Enable console no user log message.

```
diagnose debug console no-user-log-msg enable
```

diagnose debug console retry-log-msg

Console does not drop user log messages.

```
diagnose debug console retry-log-msg
```

diagnose debug console retry-log-msg disable

Disable console resend of user log message.

```
diagnose debug console retry-log-msg disable
```

diagnose debug console retry-log-msg enable

Enable console resend of user log message.

```
diagnose debug console retry-log-msg enable
```

diagnose debug console send

Send out MODEM AT command.

```
diagnose debug console send <AT command> <character> <integer>
```

Parameter	Description	Type	Size
<AT command>	MODEM AT command to send.	string	
<character>	escape character (optional, default is '+')	string	
<integer>	Escape guard time in milli-second (1 - 10000, optional, default = 1000ms).	string	

diagnose debug console timestamp

timestamp

```
diagnose debug console timestamp
```

diagnose debug console timestamp disable

Disable timestamp.

```
diagnose debug console timestamp disable
```

diagnose debug console timestamp enable

Enable timestamp.

```
diagnose debug console timestamp enable
```

diagnose debug crashlog

Crash log info.

```
diagnose debug crashlog
```

diagnose debug crashlog clear

Clear crash log.

```
diagnose debug crashlog clear
```

diagnose debug crashlog get

Get crashlog.

```
diagnose debug crashlog get
```

diagnose debug crashlog history

Show process crash history.

```
diagnose debug crashlog history
```

diagnose debug crashlog interval

Change crash log interval in seconds.

```
diagnose debug crashlog interval <interval>
```

Parameter	Description	Type	Size
<interval>	Interval at which process crashes are written to storage (0 - 2147483647 sec, default = 3600, 0 = log all crashes).	string	

diagnose debug disable

Disable debug output.

```
diagnose debug disable
```

diagnose debug duration

Set duration of debug activities.

```
diagnose debug duration <Integer>
```

Parameter	Description	Type	Size
<Integer>	Duration in minutes, min = 1, max = 99999, 0 means unlimited.	string	

diagnose debug enable

Enable debug output.

```
diagnose debug enable
```

diagnose debug flow

Trace packet flow in kernel.

```
diagnose debug flow
```

diagnose debug flow filter

Trace packet with filter.

```
diagnose debug flow filter
```

diagnose debug flow filter addr

IP address.

```
diagnose debug flow filter addr <xxx.xxx.xxx.xxx> <xxx.xxx.xxx.xxx> <Enter> | or/and
```

Parameter	Description	Type	Size
<xxx.xxx.xxx.xxx>	Host IP (ip1/from).	string	
<xxx.xxx.xxx.xxx>	Host IP (ip2/to).	string	
<Enter> or/and	If or/and is specific, filter base on ip1 or/and ip2.	string	

diagnose debug flow filter clear

Clear filter.

```
diagnose debug flow filter clear
```

diagnose debug flow filter daddr

Destination IP address.

```
diagnose debug flow filter daddr <xxx.xxx.xxx.xxx> <xxx.xxx.xxx.xxx>
```

Parameter	Description	Type	Size
<xxx.xxx.xxx.xxx>	Destination IP (from).	string	
<xxx.xxx.xxx.xxx>	Destination IP (to).	string	

diagnose debug flow filter dport

Destination port.

```
diagnose debug flow filter dport <xxx> <xxx>
```

Parameter	Description	Type	Size
<xxx>	Destination port (from).	string	
<xxx>	Destination port (to).	string	

diagnose debug flow filter negate

Inverse filter.

```
diagnose debug flow filter negate
```

diagnose debug flow filter negate addr

Inverse host IP.

```
diagnose debug flow filter negate addr
```

diagnose debug flow filter negate daddr

Inverse dest IP.

```
diagnose debug flow filter negate daddr
```

diagnose debug flow filter negate dport

Inverse dest port.

```
diagnose debug flow filter negate dport
```

diagnose debug flow filter negate port

Inverse port.

```
diagnose debug flow filter negate port
```

diagnose debug flow filter negate proto

Inverse protocol.

```
diagnose debug flow filter negate proto
```

diagnose debug flow filter negate saddr

Inverse source IP.

```
diagnose debug flow filter negate saddr
```

diagnose debug flow filter negate sport

Inverse source port.

```
diagnose debug flow filter negate sport
```

diagnose debug flow filter negate vd

Inverse virtual domain.

```
diagnose debug flow filter negate vd
```

diagnose debug flow filter port

port

```
diagnose debug flow filter port <xxx> <xxx>
```

Parameter	Description	Type	Size
<xxx>	Port (from).	string	
<xxx>	Port (to).	string	

diagnose debug flow filter proto

Protocol number.

```
diagnose debug flow filter proto <xxx>
```

Parameter	Description	Type	Size
<xxx>	Protocol number.	string	

diagnose debug flow filter saddr

Source IP address.

```
diagnose debug flow filter saddr <xxx.xxx.xxx.xxx> <xxx.xxx.xxx.xxx>
```

Parameter	Description	Type	Size
<xxx.xxx.xxx.xxx>	Source IP (from).	string	
<xxx.xxx.xxx.xxx>	Source IP (to).	string	

diagnose debug flow filter sport

Source port.

```
diagnose debug flow filter sport <xxx> <xxx>
```

Parameter	Description	Type	Size
<xxx>	Source port (from).	string	
<xxx>	Source port (to).	string	

diagnose debug flow filter vd

Index of virtual domain.

```
diagnose debug flow filter vd <xxx>
```

Parameter	Description	Type	Size
<xxx>	Index of virtual domain.	string	

diagnose debug flow filter vd-name

Name of virtual domain.

```
diagnose debug flow filter vd-name <...>
```

Parameter	Description	Type	Size
<...>	Name of virtual domain.	string	

diagnose debug flow filter6

Trace packet with IPv6 filter.

```
diagnose debug flow filter6
```

diagnose debug flow filter6 addr

IPv6 address.

```
diagnose debug flow filter6 addr <xxx:xxx::xxx:xxx> <xxx:xxx::xxx:xxx>
```

Parameter	Description	Type	Size
<xxx:xxx::xxx:xxx>	Host IPv6 (from).	string	
<xxx:xxx::xxx:xxx>	Host IPv6 (to).	string	

diagnose debug flow filter6 clear

Clear IPv6 filter.

```
diagnose debug flow filter6 clear
```

diagnose debug flow filter6 daddr

Destination IP address.

```
diagnose debug flow filter6 daddr <xxx:xxx::xxx:xxx> <xxx:xxx::xxx:xxx>
```

Parameter	Description	Type	Size
<xxx:xxx::xxx:xxx>	Destination IP (from).	string	
<xxx:xxx::xxx:xxx>	Destination IP (to).	string	

diagnose debug flow filter6 dport

Destination port.

```
diagnose debug flow filter6 dport <xxx> <xxx>
```

Parameter	Description	Type	Size
<xxx>	Destination port (from).	string	
<xxx>	Destination port (to).	string	

diagnose debug flow filter6 negate

Inverse IPv6 filter.

```
diagnose debug flow filter6 negate
```

diagnose debug flow filter6 negate addr

Inverse host IP.

```
diagnose debug flow filter6 negate addr
```

diagnose debug flow filter6 negate daddr

Inverse dest IP.

```
diagnose debug flow filter6 negate daddr
```

diagnose debug flow filter6 negate dport

Inverse dest port.

```
diagnose debug flow filter6 negate dport
```

diagnose debug flow filter6 negate port

Inverse port.

```
diagnose debug flow filter6 negate port
```

diagnose debug flow filter6 negate proto

Inverse protocol.

```
diagnose debug flow filter6 negate proto
```

diagnose debug flow filter6 negate saddr

Inverse source IP.

```
diagnose debug flow filter6 negate saddr
```

diagnose debug flow filter6 negate sport

Inverse source port.

```
diagnose debug flow filter6 negate sport
```

diagnose debug flow filter6 negate vd

Inverse virtual domain.

```
diagnose debug flow filter6 negate vd
```

diagnose debug flow filter6 port

port

```
diagnose debug flow filter6 port <xxx> <xxx>
```

Parameter	Description	Type	Size
<xxx>	Port (from).	string	
<xxx>	Port (to).	string	

diagnose debug flow filter6 proto

Protocol number.

```
diagnose debug flow filter6 proto <xxx>
```

Parameter	Description	Type	Size
<xxx>	Protocol number.	string	

diagnose debug flow filter6 saddr

Source IP address.

```
diagnose debug flow filter6 saddr <xxx:xxx::xxx:xxx> <xxx:xxx::xxx:xxx>
```

Parameter	Description	Type	Size
<xxx:xxx::xxx:xxx>	Source IP (from).	string	
<xxx:xxx::xxx:xxx>	Source IP (to).	string	

diagnose debug flow filter6 sport

Source port.

```
diagnose debug flow filter6 sport <xxx> <xxx>
```

Parameter	Description	Type	Size
<xxx>	Source port (from).	string	
<xxx>	Source port (to).	string	

diagnose debug flow filter6 vd

Index of virtual domain.

```
diagnose debug flow filter6 vd <xxx>
```

Parameter	Description	Type	Size
<xxx>	Index of virtual domain.	string	

diagnose debug flow filter6 vd-name

Name of virtual domain.

```
diagnose debug flow filter6 vd-name <...>
```

Parameter	Description	Type	Size
<...>	Name of virtual domain.	string	

diagnose debug flow show

Enable/disable display of trace on console.

```
diagnose debug flow show
```

diagnose debug flow show function-name

Enable/disable display function name.

```
diagnose debug flow show function-name
```

diagnose debug flow show function-name disable

Disable display of function name.

```
diagnose debug flow show function-name disable
```

diagnose debug flow show function-name enable

Enable display of function name.

```
diagnose debug flow show function-name enable
```

diagnose debug flow trace

Start/stop trace.

```
diagnose debug flow trace
```

diagnose debug flow trace start

Start trace.

```
diagnose debug flow trace start <xxx>
```

Parameter	Description	Type	Size
<xxx>	Repeat number.	string	

diagnose debug flow trace start6

Start IPv6 trace.

```
diagnose debug flow trace start6 <xxx>
```

Parameter	Description	Type	Size
<xxx>	Repeat number.	string	

diagnose debug flow trace stop

Stop trace.

```
diagnose debug flow trace stop
```

diagnose debug flow trace stop6

Stop IPv6 trace.

```
diagnose debug flow trace stop6
```

diagnose debug fsso-polling

FSSO active directory poll module.

```
diagnose debug fsso-polling
```

diagnose debug fsso-polling client

Show FSSO AD Server Clients.

```
diagnose debug fsso-polling client
```

diagnose debug fsso-polling detail

Show FSSO AD Server Detail.

```
diagnose debug fsso-polling detail <id>
```

Parameter	Description	Type	Size
<id>	AD Server Entry ID.	string	

diagnose debug fsso-polling group

Show FSSO LDAP groups for AD users.

```
diagnose debug fsso-polling group <id> <name>
```

Parameter	Description	Type	Size
<id>	AD Server Entry ID.	string	
<name>	AD Server user.	string	

diagnose debug fsso-polling refresh-user

Refresh FSSO AD Server users.

```
diagnose debug fsso-polling refresh-user <id>
```

Parameter	Description	Type	Size
<id>	AD Server Entry ID.	string	

diagnose debug fsso-polling set-log-source

Source of event log.

```
diagnose debug fsso-polling set-log-source <id> <src>
```

Parameter	Description	Type	Size
<id>	AD Server Entry ID.	string	
<src>	0: security, 1:application.	string	

diagnose debug fsso-polling summary

Show FSSO AD Server Summary.

```
diagnose debug fsso-polling summary
```

diagnose debug fsso-polling user

Show FSSO AD Server users.

```
diagnose debug fsso-polling user <id>
```

Parameter	Description	Type	Size
<id>	AD Server Entry ID.	string	

diagnose debug info

Show active debug level settings.

```
diagnose debug info
```

diagnose debug intf-band-error

Show error counter of interface bandwidth.

```
diagnose debug intf-band-error
```

diagnose debug kernel

kernel

```
diagnose debug kernel
```

diagnose debug kernel ha

Debug kernel HA level.

```
diagnose debug kernel ha <Integer>
```

Parameter	Description	Type	Size
<Integer>	Kernel HA level (0 = disable, 1-7 = higher level).	string	

diagnose debug kernel level

Debug kernel level.

```
diagnose debug kernel level <Integer>
```

Parameter	Description	Type	Size
<Integer>	Kernel level.	string	

diagnose debug kernel log

Interact with kernel log

```
diagnose debug kernel log
```

diagnose debug kernel log clear

Clear the kernel log

```
diagnose debug kernel log clear
```

diagnose debug kernel log show

Dump the kernel log

```
diagnose debug kernel log show
```

diagnose debug kernel sysrq

Magic SysRq.

```
diagnose debug kernel sysrq
```

diagnose debug kernel sysrq command

Magic SysRq command.

```
diagnose debug kernel sysrq command
```

diagnose debug kernel sysrq command crash

Perform a system crash.

```
diagnose debug kernel sysrq command crash
```

diagnose debug kernel sysrq disable

Disable magic SysRq.

```
diagnose debug kernel sysrq disable
```

diagnose debug kernel sysrq enable

Enable magic SysRq.

```
diagnose debug kernel sysrq enable
```

diagnose debug kernel sysrq status

Show the status of magic SysRq.

```
diagnose debug kernel sysrq status
```

diagnose debug rating

Display rating info.

```
diagnose debug rating <refresh-rate>
```

Parameter	Description	Type	Size
<refresh-rate>	Frequency to refresh server list (sec).	string	

diagnose debug remote-extender

remote-extender

```
diagnose debug remote-extender
```

diagnose debug remote-extender extenderd

Debug extenderd level.

```
diagnose debug remote-extender extenderd <Integer>
```

Parameter	Description	Type	Size
<Integer>	extenderd debug level.	string	

diagnose debug remote-extender modem-manager

Debug modem-manager level.

```
diagnose debug remote-extender modem-manager <Integer>
```

Parameter	Description	Type	Size
<Integer>	modem-manager debug level.	string	

diagnose debug report

Report for tech support.

```
diagnose debug report
```

diagnose debug report reset

Reset debug report.

```
diagnose debug report reset
```

diagnose debug reset

Reset all debug level to default.

```
diagnose debug reset
```

diagnose debug sdnc

sdnc

```
diagnose debug sdnc
```

diagnose debug sql-log-error

SQL log database error info

```
diagnose debug sql-log-error
```

diagnose debug sql-log-error clear

clear sql log database error log

```
diagnose debug sql-log-error clear
```

diagnose debug sql-log-error read

display sql log database error on console

```
diagnose debug sql-log-error read
```

diagnose debug sql-log-error status

show sql log database error status

```
diagnose debug sql-log-error status
```

diagnose debug traffic

Traffic statistic data

```
diagnose debug traffic
```

diagnose debug traffic history

Dump interface traffic history data.

```
diagnose debug traffic history <String> <Integer>
```

Parameter	Description	Type	Size
<String>	Interface name	string	
<Integer>	Period, hour=0, day=1, week=2.	string	

diagnose debug traffic interface

List traffic monitor interface.

```
diagnose debug traffic interface
```

diagnose debug traffic peek

Display interface traffic real-time data.

```
diagnose debug traffic peek <String> <Integer>
```

Parameter	Description	Type	Size
<String>	Interface name	string	
<Integer>	Disable or enable, disable=0, enable=1.	string	

diagnose debug urlfilter

urlfilter

```
diagnose debug urlfilter
```

diagnose debug urlfilter src-addr

Enable debug messages for selected source IP address.

```
diagnose debug urlfilter src-addr <IP address>
```

Parameter	Description	Type	Size
<IP address>	dot delimited IP address or "stop"	string	

diagnose debug urlfilter test-url

Find the result returned from the URL filter cache for a URL.

```
diagnose debug urlfilter test-url <url>
```

Parameter	Description	Type	Size
<url>	URL to test.	string	

diagnose debug vm-print-license

Print license info

```
diagnose debug vm-print-license
```

diagnose disktest

Disk test

This topic includes the following commands:

- [diagnose disktest block on page 1414](#)
- [diagnose disktest block 1 on page 1415](#)
- [diagnose disktest block 16 on page 1415](#)
- [diagnose disktest block 256 on page 1415](#)
- [diagnose disktest block 4 on page 1415](#)
- [diagnose disktest block 64 on page 1415](#)
- [diagnose disktest device on page 1415](#)
- [diagnose disktest run on page 1416](#)
- [diagnose disktest size on page 1416](#)
- [diagnose disktest time on page 1416](#)

diagnose disktest block

Block size of each read/write operation.

```
diagnose disktest block
```

diagnose disktest block 1

1M

```
diagnose disktest block 1
```

diagnose disktest block 16

16M

```
diagnose disktest block 16
```

diagnose disktest block 256

256M

```
diagnose disktest block 256
```

diagnose disktest block 4

4M

```
diagnose disktest block 4
```

diagnose disktest block 64

64M

```
diagnose disktest block 64
```

diagnose disktest device

Device to test.

```
diagnose disktest device
```

diagnose disktest run

Run test with specified cycles (default = no limit).

```
diagnose disktest run <Integer>
```

Parameter	Description	Type	Size
<Integer>	Enter test cycles (default = no limit).	string	

diagnose disktest size

Test size limit for each cycle (default = no limit).

```
diagnose disktest size <Integer>
```

Parameter	Description	Type	Size
<Integer>	Enter test size limit for each cycle in MB (default = no limit).	string	

diagnose disktest time

Test time limit for each cycle (default = no limit).

```
diagnose disktest time <Integer>
```

Parameter	Description	Type	Size
<Integer>	Enter test time limit for each cycle in seconds (default = no limit).	string	

diagnose emailfilter

emailfilter

This topic includes the following commands:

- [diagnose emailfilter bword on page 1417](#)
- [diagnose emailfilter bword matchfilter on page 1417](#)
- [diagnose emailfilter fortishield on page 1417](#)
- [diagnose emailfilter fortishield servers on page 1417](#)
- [diagnose emailfilter fortishield statistics on page 1417](#)

- [diagnose emailfilter fortishield statistics flush on page 1418](#)
- [diagnose emailfilter fortishield statistics list on page 1418](#)

diagnose emailfilter bword

Spam banned word match filter.

```
diagnose emailfilter bword
```

diagnose emailfilter bword matchfilter

Filtered list display.

```
diagnose emailfilter bword matchfilter <filter string>
```

Parameter	Description	Type	Size
<filter string>	Filter string from end of spam filter banned word log line. For example: '1-n8 4 0 1 4 10 nC 4'	string	

diagnose emailfilter fortishield

FortiGuard

```
diagnose emailfilter fortishield
```

diagnose emailfilter fortishield servers

FortiGuard-AntiSpam server status.

```
diagnose emailfilter fortishield servers <refresh-rate>
```

Parameter	Description	Type	Size
<refresh-rate>	Frequency to refresh server list (sec).	string	

diagnose emailfilter fortishield statistics

FortiGuard-AntiSpam cache and daemon statistics.

```
diagnose emailfilter fortishield statistics
```

diagnose emailfilter fortishield statistics flush

Flush cache and daemon statistics.

```
diagnose emailfilter fortishield statistics flush
```

diagnose emailfilter fortishield statistics list

Display server status, cache and daemon statistics.

```
diagnose emailfilter fortishield statistics list
```

diagnose endpoint

Endpoint compliance diagnostics.

This topic includes the following commands:

- [diagnose endpoint avatar on page 1420](#)
- [diagnose endpoint avatar allow-nodisk on page 1420](#)
- [diagnose endpoint avatar delete-archived on page 1420](#)
- [diagnose endpoint avatar find on page 1420](#)
- [diagnose endpoint avatar find fingerprint on page 1421](#)
- [diagnose endpoint avatar find link on page 1421](#)
- [diagnose endpoint avatar list on page 1421](#)
- [diagnose endpoint avatar list active on page 1421](#)
- [diagnose endpoint avatar list archived on page 1421](#)
- [diagnose endpoint avatar list fingerprint on page 1422](#)
- [diagnose endpoint avatar purge-all on page 1422](#)
- [diagnose endpoint avatar purge-archived on page 1422](#)
- [diagnose endpoint debug-zone on page 1422](#)
- [diagnose endpoint debug-zone dump on page 1422](#)
- [diagnose endpoint debug-zone set-ls-quota on page 1423](#)
- [diagnose endpoint ec-shared on page 1423](#)
- [diagnose endpoint ec-shared find on page 1423](#)
- [diagnose endpoint ec-shared list on page 1423](#)
- [diagnose endpoint fctems on page 1423](#)
- [diagnose endpoint fctems api-status on page 1424](#)

- [diagnose endpoint fctems api-status clear on page 1424](#)
- [diagnose endpoint fctems get-pub-addr on page 1424](#)
- [diagnose endpoint fctems json on page 1424](#)
- [diagnose endpoint fctems json deep-inspect-cert-sync on page 1424](#)
- [diagnose endpoint fctems json gateway-mac-request on page 1425](#)
- [diagnose endpoint fctems queue-complete-calls on page 1425](#)
- [diagnose endpoint fctems test-authorization on page 1425](#)
- [diagnose endpoint fctems test-connectivity on page 1425](#)
- [diagnose endpoint filter on page 1425](#)
- [diagnose endpoint filter avatar-fingerprint on page 1426](#)
- [diagnose endpoint filter clear on page 1426](#)
- [diagnose endpoint filter ems-sn on page 1426](#)
- [diagnose endpoint filter ftcl-uid on page 1426](#)
- [diagnose endpoint filter list on page 1426](#)
- [diagnose endpoint filter show-large-data on page 1427](#)
- [diagnose endpoint lls-comm on page 1427](#)
- [diagnose endpoint lls-comm connect on page 1427](#)
- [diagnose endpoint lls-comm disconnect on page 1427](#)
- [diagnose endpoint lls-comm recv on page 1427](#)
- [diagnose endpoint lls-comm send on page 1428](#)
- [diagnose endpoint lls-comm send echo on page 1428](#)
- [diagnose endpoint lls-comm send echo echo on page 1428](#)
- [diagnose endpoint lls-comm send general on page 1428](#)
- [diagnose endpoint lls-comm send general get-index on page 1428](#)
- [diagnose endpoint lls-comm send general register on page 1428](#)
- [diagnose endpoint lls-comm send general unregister on page 1429](#)
- [diagnose endpoint lls-comm send ping on page 1429](#)
- [diagnose endpoint lls-comm send ping set-interval on page 1429](#)
- [diagnose endpoint lls-comm send ztna on page 1429](#)
- [diagnose endpoint lls-comm send ztna find-ip-vdom on page 1429](#)
- [diagnose endpoint lls-comm send ztna find-uid on page 1430](#)
- [diagnose endpoint lls-comm send ztna message-format on page 1430](#)
- [diagnose endpoint lls-comm send ztna subscribe-all on page 1430](#)
- [diagnose endpoint lls-comm send ztna unsubscribe-all on page 1431](#)
- [diagnose endpoint lls-comm send ztna unsubscribe-uid on page 1431](#)
- [diagnose endpoint lls-comm status on page 1431](#)
- [diagnose endpoint record on page 1431](#)
- [diagnose endpoint record delete on page 1431](#)
- [diagnose endpoint record list on page 1432](#)
- [diagnose endpoint record summary on page 1432](#)
- [diagnose endpoint record update-by-json on page 1432](#)
- [diagnose endpoint tags on page 1432](#)
- [diagnose endpoint tags remove-by-id on page 1433](#)

- [diagnose endpoint tags remove-by-name on page 1433](#)
- [diagnose endpoint tags remove-by-name-legacy on page 1433](#)
- [diagnose endpoint tags remove-by-sn on page 1433](#)
- [diagnose endpoint tags test-common-tag-update on page 1434](#)
- [diagnose endpoint tags test-update on page 1434](#)

diagnose endpoint avatar

FortiClient avatar.

```
diagnose endpoint avatar
```

diagnose endpoint avatar allow-nodisk

Allow no disk for avatar

```
diagnose endpoint avatar allow-nodisk [enable|disable]
```

Parameter	Description	Type	Size
[enable disable]	Allow saving avatars on non-harddisk storage.	string	

diagnose endpoint avatar delete-archived

Delete an archived avatar

```
diagnose endpoint avatar delete-archived <ftcl-uid> <user-name>
```

Parameter	Description	Type	Size
<ftcl-uid>	FortiClient UID	string	
<user-name>	User name	string	

diagnose endpoint avatar find

Find avatar location

```
diagnose endpoint avatar find
```

diagnose endpoint avatar find fingerprint

Find avatar fingerprint location

```
diagnose endpoint avatar find fingerprint <fingerprint>
```

Parameter	Description	Type	Size
<fingerprint>	Avatar fingerprint	string	

diagnose endpoint avatar find link

Find avatar link location

```
diagnose endpoint avatar find link <ftcl-uid> <user-name>
```

Parameter	Description	Type	Size
<ftcl-uid>	FortiClient UID	string	
<user-name>	User name	string	

diagnose endpoint avatar list

Display avatars

```
diagnose endpoint avatar list
```

diagnose endpoint avatar list active

Display active avatars

```
diagnose endpoint avatar list active <number>
```

Parameter	Description	Type	Size
<number>	Number of files to display per page.	string	

diagnose endpoint avatar list archived

Display archived avatars

```
diagnose endpoint avatar list archived <number>
```

Parameter	Description	Type	Size
<number>	Number of files to display per page.	string	

diagnose endpoint avatar list fingerprint

Display fingerprint avatars

```
diagnose endpoint avatar list fingerprint <number>
```

Parameter	Description	Type	Size
<number>	Number of files to display per page.	string	

diagnose endpoint avatar purge-all

Purge ALL avatars

```
diagnose endpoint avatar purge-all
```

diagnose endpoint avatar purge-archived

Purge all archived avatars

```
diagnose endpoint avatar purge-archived
```

diagnose endpoint debug-zone

Debug Zone.

```
diagnose endpoint debug-zone
```

diagnose endpoint debug-zone dump

Dump all debug zone info.

```
diagnose endpoint debug-zone dump
```

diagnose endpoint debug-zone set-lls-quota

Set send quota for each socket

```
diagnose endpoint debug-zone set-lls-quota <quota>
```

Parameter	Description	Type	Size
<quota>	Quota in bytes	string	

diagnose endpoint ec-shared

FortiClient shared record.

```
diagnose endpoint ec-shared
```

diagnose endpoint ec-shared find

Find shared record.

```
diagnose endpoint ec-shared find <ipv4-address> <ENTER|vfid>
```

Parameter	Description	Type	Size
<ipv4-address>	Endpoint IPv4 address.	string	
<ENTER vfid>	VDOM ID of the client.	string	

diagnose endpoint ec-shared list

List shared records.

```
diagnose endpoint ec-shared list <number>
```

Parameter	Description	Type	Size
<number>	Number of records to display per page.	string	

diagnose endpoint fctems

FortiClient EMS.

```
diagnose endpoint fctems
```

diagnose endpoint fctems api-status

Tools to diagnose EMS API status.

```
diagnose endpoint fctems api-status
```

diagnose endpoint fctems api-status clear

Clear EMS API status.

```
diagnose endpoint fctems api-status clear <fctems>
```

Parameter	Description	Type	Size
<fctems>	FortiClient EMS table entry name in CMDB.	string	

diagnose endpoint fctems get-pub-addr

Get FortiClient EMS public address.

```
diagnose endpoint fctems get-pub-addr <fctems>
```

Parameter	Description	Type	Size
<fctems>	FortiClient EMS table entry id in CMDB.	string	

diagnose endpoint fctems json

FortiClient EMS REST-API JSON test.

```
diagnose endpoint fctems json
```

diagnose endpoint fctems json deep-inspect-cert-sync

Print deep inspection certificate sync json.

```
diagnose endpoint fctems json deep-inspect-cert-sync
```


diagnose endpoint fctems json gateway-mac-request

Print gateway-info json.

```
diagnose endpoint fctems json gateway-mac-request
```

diagnose endpoint fctems queue-complete-calls

Add complete (un)quarantine call(s) to FCEMSD queue.

```
diagnose endpoint fctems queue-complete-calls <call>[,<call>[,...]]
```

Parameter	Description	Type	Size
<call> [,<call>[,...]]	Comma separated list of calls. Run without the argument for more help.	string	

diagnose endpoint fctems test-authorization

Authorization test for FortiClient EMS.

```
diagnose endpoint fctems test-authorization <fctems>
```

Parameter	Description	Type	Size
<fctems>	FortiClient EMS table entry id in CMDB.	string	

diagnose endpoint fctems test-connectivity

Connectivity test for FortiClient EMS.

```
diagnose endpoint fctems test-connectivity <fctems>
```

Parameter	Description	Type	Size
<fctems>	FortiClient EMS table entry id in CMDB.	string	

diagnose endpoint filter

Debug filter for fcnacd.

```
diagnose endpoint filter
```

diagnose endpoint filter avatar-fingerprint

Avatar fingerprint to filter by.

```
diagnose endpoint filter avatar-fingerprint <avatar-fingerprint>
```

Parameter	Description	Type	Size
<avatar-fingerprint>	Avatar fingerprint.	string	

diagnose endpoint filter clear

Erase the current filter.

```
diagnose endpoint filter clear
```

diagnose endpoint filter ems-sn

FortiClient EMS serial-number to filter by.

```
diagnose endpoint filter ems-sn <ems-sn>
```

Parameter	Description	Type	Size
<ems-sn>	EMS serial-number.	string	

diagnose endpoint filter ftcl-uid

FortiClient UID to filter by.

```
diagnose endpoint filter ftcl-uid <ftcl-uid>
```

Parameter	Description	Type	Size
<ftcl-uid>	FortiClient UID.	string	

diagnose endpoint filter list

Display the current filter.

```
diagnose endpoint filter list
```

diagnose endpoint filter show-large-data

Show large data.

```
diagnose endpoint filter show-large-data [yes/no]
```

Parameter	Description	Type	Size
[yes/no]	Yes or no.	string	

diagnose endpoint lls-comm

Long-Lived Socket Communication.

```
diagnose endpoint lls-comm
```

diagnose endpoint lls-comm connect

Connect.

```
diagnose endpoint lls-comm connect
```

diagnose endpoint lls-comm disconnect

Disconnect.

```
diagnose endpoint lls-comm disconnect
```

diagnose endpoint lls-comm recv

Receive Messages.

```
diagnose endpoint lls-comm recv <repeat>
```

Parameter	Description	Type	Size
<repeat>	Repeat number of receives	string	

diagnose endpoint lls-comm send

Send Message.

```
diagnose endpoint lls-comm send
```

diagnose endpoint lls-comm send echo

Echo long-lived socket channel

```
diagnose endpoint lls-comm send echo
```

diagnose endpoint lls-comm send echo echo

Echo

```
diagnose endpoint lls-comm send echo echo <msg>
```

Parameter	Description	Type	Size
<msg>	Message to echo	string	

diagnose endpoint lls-comm send general

General long-lived socket channel

```
diagnose endpoint lls-comm send general
```

diagnose endpoint lls-comm send general get-index

Get Long-lived socket channel index.

```
diagnose endpoint lls-comm send general get-index
```

diagnose endpoint lls-comm send general register

Register to Long-lived Socket channel(s)

```
diagnose endpoint lls-comm send general register <channel-mask>
```

Parameter	Description	Type	Size
<channel-mask>	Channel Mask in decimal, octal or hexadecimal	string	

diagnose endpoint lls-comm send general unregister

Unregister from Long-lived Socket channel(s)

```
diagnose endpoint lls-comm send general unregister <channel-mask>
```

Parameter	Description	Type	Size
<channel-mask>	Channel Mask in decimal, octal or hexadecimal	string	

diagnose endpoint lls-comm send ping

Ping long-lived socket channel

```
diagnose endpoint lls-comm send ping
```

diagnose endpoint lls-comm send ping set-interval

Set interval

```
diagnose endpoint lls-comm send ping set-interval <interval>
```

Parameter	Description	Type	Size
<interval>	Period in units of 1/100 seconds	string	

diagnose endpoint lls-comm send ztna

ZTNA long-lived socket channel

```
diagnose endpoint lls-comm send ztna
```

diagnose endpoint lls-comm send ztna find-ip-vdom

Find by IP and VDOM

```
diagnose endpoint lls-comm send ztna find-ip-vdom <ip> <vdom>
```

Parameter	Description	Type	Size
<ip>	IPv4 or IPv6 address of client	string	
<vdom>	VDOM name	string	

diagnose endpoint lls-comm send ztna find-uid

Find by FortiClient UID and EMS SN

```
diagnose endpoint lls-comm send ztna find-uid <ftct-uid> <emssn> <ems-tenant-id>
```

Parameter	Description	Type	Size
<ftct-uid>	Client UID	string	
<emssn>	EMS Serial Number	string	
<ems-tenant-id>	EMS Tenant ID	string	

diagnose endpoint lls-comm send ztna message-format

Select if wad header is sent

```
diagnose endpoint lls-comm send ztna message-format <index>
```

Parameter	Description	Type	Size
<index>	0: standard 1: wad informer	string	

diagnose endpoint lls-comm send ztna subscribe-all

Subscribe to all FortiClients on selected LLS bits

```
diagnose endpoint lls-comm send ztna subscribe-all <mask>
```

Parameter	Description	Type	Size
<mask>	Bit mask	string	

diagnose endpoint lls-comm send ztna unsubscribe-all

Unsubscribe to all FortiClients on issuing LLS

```
diagnose endpoint lls-comm send ztna unsubscribe-all
```

diagnose endpoint lls-comm send ztna unsubscribe-uid

Unsubscribe from FortiClient UID

```
diagnose endpoint lls-comm send ztna unsubscribe-uid <ftct-uid> <emssn> <ems-tenant-id>
```

Parameter	Description	Type	Size
<ftct-uid>	Client UID	string	
<emssn>	EMS Serial Number	string	
<ems-tenant-id>	EMS_Tenant ID	string	

diagnose endpoint lls-comm status

Status.

```
diagnose endpoint lls-comm status
```

diagnose endpoint record

Endpoint records.

```
diagnose endpoint record
```

diagnose endpoint record delete

Delete endpoint records.

```
diagnose endpoint record delete <ipv4-address>
```

Parameter	Description	Type	Size
<ipv4-address>	Source IPv4 address.	string	

diagnose endpoint record list

List endpoint records.

```
diagnose endpoint record list <ipv4-address> <mac-address> <forticlient-uid>
```

Parameter	Description	Type	Size
<ipv4-address>	Source IPv4 address ("any" for all IP addresses).	string	
<mac-address>	Source MAC address ("any" for all MAC addresses).	string	
<forticlient-uid>	FortiClient UID ("any" for all UID's).	string	

diagnose endpoint record summary

List summary of endpoint records.

```
diagnose endpoint record summary
```

diagnose endpoint record update-by-json

Add endpoint record by JSON.

```
diagnose endpoint record update-by-json <uid> <ems-sn> <ems-tenant-id> <json>
```

Parameter	Description	Type	Size
<uid>	FortiClient UID.	string	
<ems-sn>	FortiClient EMS serial number.	string	
<ems-tenant-id>	FortiClient EMS tenant ID.	string	
<json>	JSON string.	string	

diagnose endpoint tags

Tags.

```
diagnose endpoint tags
```


diagnose endpoint tags remove-by-id

Remove Dynamic address tags by EMS ID.

```
diagnose endpoint tags remove-by-id <EMS-ID>
```

Parameter	Description	Type	Size
<EMS-ID>	EMS ID.	string	

diagnose endpoint tags remove-by-name

Remove specific tag by EMS ID and name.

```
diagnose endpoint tags remove-by-name <TAG-Name> <EMS-ID>
```

Parameter	Description	Type	Size
<TAG-Name>	Tag name.	string	
<EMS-ID>	EMS ID.	string	

diagnose endpoint tags remove-by-name-legacy

Remove specific tag by Serial Number and name (LEGACY).

```
diagnose endpoint tags remove-by-name-legacy <TAG-Name> <SN>
```

Parameter	Description	Type	Size
<TAG-Name>	Tag name.	string	
<SN>	Serial Number.	string	

diagnose endpoint tags remove-by-sn

Remove Dynamic address tags by Serial Number (LEGACY).

```
diagnose endpoint tags remove-by-sn <SN>
```

Parameter	Description	Type	Size
<SN>	Serial Number.	string	

diagnose endpoint tags test-common-tag-update

Test update tags for FortiClient EMS

```
diagnose endpoint tags test-common-tag-update <TAG-INFO-JSON>
```

Parameter	Description	Type	Size
<TAG-INFO-JSON>	JSON string for commands.	string	

diagnose endpoint tags test-update

Test update tags.

```
diagnose endpoint tags test-update <EMS-SN> <TAG-INFO-JSON> <TAG-MEMBERS-JSON>
```

Parameter	Description	Type	Size
<EMS-SN>	FortiClient EMS Serial Number.	string	
<TAG-INFO-JSON>	JSON string for tag_info.	string	
<TAG-MEMBERS-JSON>	JSON string for tag_members.	string	

diagnose fdsm

FortiCloud/FortiManager Service.

This topic includes the following commands:

- [diagnose fdsm account-info on page 1435](#)
- [diagnose fdsm central-mgmt-status on page 1435](#)
- [diagnose fdsm cfg-diff on page 1435](#)
- [diagnose fdsm cfg-download on page 1436](#)
- [diagnose fdsm cfg-list on page 1436](#)
- [diagnose fdsm cfg-upload on page 1436](#)
- [diagnose fdsm contract-controller-update on page 1436](#)
- [diagnose fdsm fap-fsw-contract-download on page 1436](#)
- [diagnose fdsm fc-installer-download on page 1437](#)
- [diagnose fdsm fds-update on page 1437](#)

- [diagnose fdsm fmg-auto-discovery-status on page 1437](#)
- [diagnose fdsm forticlient-net-info on page 1437](#)
- [diagnose fdsm forticlient-update on page 1437](#)
- [diagnose fdsm fortiex-download on page 1438](#)
- [diagnose fdsm fortiex-latest-ver on page 1438](#)
- [diagnose fdsm fortisw-download on page 1438](#)
- [diagnose fdsm fortisw-latest-ver on page 1438](#)
- [diagnose fdsm ftk-activate on page 1438](#)
- [diagnose fdsm image-download on page 1439](#)
- [diagnose fdsm image-list on page 1439](#)
- [diagnose fdsm image-upgrade-matrix on page 1439](#)
- [diagnose fdsm log-controller-update on page 1439](#)
- [diagnose fdsm message-update on page 1439](#)
- [diagnose fdsm modem-list on page 1439](#)
- [diagnose fdsm report-download on page 1440](#)
- [diagnose fdsm report-list on page 1440](#)

diagnose fdsm account-info

FortiCloud account information.

```
diagnose fdsm account-info
```

diagnose fdsm central-mgmt-status

Central management registration status.

```
diagnose fdsm central-mgmt-status
```

diagnose fdsm cfg-diff

Configuration difference.

```
diagnose fdsm cfg-diff <revision1> <revision2>
```

Parameter	Description	Type	Size
<revision1>	Revision	string	
<revision2>	Revision	string	

diagnose fdsm cfg-download

Download configuration.

```
diagnose fdsm cfg-download <type> <revision>
```

Parameter	Description	Type	Size
<type>	Configuration type (normal, template, script).	string	
<revision>	Revision	string	

diagnose fdsm cfg-list

Download configuration list.

```
diagnose fdsm cfg-list <type>
```

Parameter	Description	Type	Size
<type>	Configuration type (normal, template, script).	string	

diagnose fdsm cfg-upload

Upload configuration.

```
diagnose fdsm cfg-upload <comments>
```

Parameter	Description	Type	Size
<comments>	Comments	string	

diagnose fdsm contract-controller-update

Update contract controller.

```
diagnose fdsm contract-controller-update
```

diagnose fdsm fap-fsw-contract-download

FAP/FSW contract information.

```
diagnose fdsm fap-fsw-contract-download <serial1*serial2*...>
```

Parameter	Description	Type	Size
<serial1*serial2*...>	Serial numbers of FAP/FSW devices	string	

diagnose fdsm fc-installer-download

Download FortiClient installer.

```
diagnose fdsm fc-installer-download <id>
```

Parameter	Description	Type	Size
<id>	Package ID.	string	

diagnose fdsm fds-update

Perform FortiGuard update.

```
diagnose fdsm fds-update
```

diagnose fdsm fmg-auto-discovery-status

FortiManager auto-discovery status.

```
diagnose fdsm fmg-auto-discovery-status
```

diagnose fdsm forticlient-net-info

FortiClient net information.

```
diagnose fdsm forticlient-net-info
```

diagnose fdsm forticlient-update

FortiClient update.

```
diagnose fdsm forticlient-update
```

diagnose fdsm fortiex-download

Download FortiExtender image.

```
diagnose fdsm fortiex-download <id>
```

Parameter	Description	Type	Size
<id>	Image ID	string	

diagnose fdsm fortiex-latest-ver

Get most recent FortiExtender build information.

```
diagnose fdsm fortiex-latest-ver <model>
```

Parameter	Description	Type	Size
<model>	Model name	string	

diagnose fdsm fortisw-download

Download FortiSwitch image.

```
diagnose fdsm fortisw-download <id>
```

Parameter	Description	Type	Size
<id>	Image ID	string	

diagnose fdsm fortisw-latest-ver

Get most recent FortiSwitch build information.

```
diagnose fdsm fortisw-latest-ver <model>
```

Parameter	Description	Type	Size
<model>	Model name	string	

diagnose fdsm ftk-activate

FortiToken activation.

```
diagnose fdsm ftk-activate
```

diagnose fdsm image-download

Download image.

```
diagnose fdsm image-download <id>
```

Parameter	Description	Type	Size
<id>	Image ID.	string	

diagnose fdsm image-list

Download image list.

```
diagnose fdsm image-list
```

diagnose fdsm image-upgrade-matrix

Download image upgrade matrix.

```
diagnose fdsm image-upgrade-matrix
```

diagnose fdsm log-controller-update

Perform log update.

```
diagnose fdsm log-controller-update
```

diagnose fdsm message-update

Perform message update.

```
diagnose fdsm message-update
```

diagnose fdsm modem-list

MODEM list.

```
diagnose fdsm modem-list
```

diagnose fdsm report-download

Download report.

```
diagnose fdsm report-download <oid>
```

Parameter	Description	Type	Size
<oid>	OID	string	

diagnose fdsm report-list

Download report list.

```
diagnose fdsm report-list <vdom>
```

Parameter	Description	Type	Size
<vdom>	VDOM Name.	string	

diagnose firewall

Firewall

This topic includes the following commands:

- [diagnose firewall auth on page 1442](#)
- [diagnose firewall auth clear on page 1442](#)
- [diagnose firewall auth filter on page 1443](#)
- [diagnose firewall auth filter clear on page 1443](#)
- [diagnose firewall auth filter group on page 1443](#)
- [diagnose firewall auth filter mac on page 1443](#)
- [diagnose firewall auth filter method on page 1443](#)
- [diagnose firewall auth filter policy on page 1444](#)
- [diagnose firewall auth filter source on page 1444](#)
- [diagnose firewall auth filter source6 on page 1444](#)
- [diagnose firewall auth filter user on page 1445](#)
- [diagnose firewall auth ipv6 on page 1445](#)
- [diagnose firewall auth ipv6 clear on page 1445](#)
- [diagnose firewall auth ipv6 list on page 1445](#)

- [diagnose firewall auth list on page 1445](#)
- [diagnose firewall auth mac on page 1446](#)
- [diagnose firewall auth mac clear on page 1446](#)
- [diagnose firewall auth mac list on page 1446](#)
- [diagnose firewall dynamic on page 1446](#)
- [diagnose firewall dynamic address on page 1446](#)
- [diagnose firewall dynamic list on page 1446](#)
- [diagnose firewall dynamic6 on page 1447](#)
- [diagnose firewall dynamic6 address on page 1447](#)
- [diagnose firewall dynamic6 list on page 1447](#)
- [diagnose firewall fqdn on page 1447](#)
- [diagnose firewall fqdn get-ip on page 1447](#)
- [diagnose firewall fqdn get-mac on page 1448](#)
- [diagnose firewall fqdn getinfo-ip on page 1448](#)
- [diagnose firewall fqdn getinfo-mac on page 1448](#)
- [diagnose firewall fqdn list-all on page 1448](#)
- [diagnose firewall fqdn list-ip on page 1449](#)
- [diagnose firewall fqdn list-mac on page 1449](#)
- [diagnose firewall fqdn6 on page 1449](#)
- [diagnose firewall fqdn6 get on page 1449](#)
- [diagnose firewall fqdn6 list on page 1449](#)
- [diagnose firewall internet-service on page 1449](#)
- [diagnose firewall internet-service list on page 1450](#)
- [diagnose firewall internet-service-app-ctrl on page 1450](#)
- [diagnose firewall internet-service-cache on page 1450](#)
- [diagnose firewall internet-service-cache list on page 1450](#)
- [diagnose firewall internet-service-custom on page 1450](#)
- [diagnose firewall internet-service-custom list on page 1450](#)
- [diagnose firewall internet-service-disable on page 1451](#)
- [diagnose firewall internet-service-disable list on page 1451](#)
- [diagnose firewall internet-service-extension on page 1451](#)
- [diagnose firewall internet-service-extension list on page 1451](#)
- [diagnose firewall internet-service-prio-id on page 1451](#)
- [diagnose firewall internet-service-prio-id list on page 1452](#)
- [diagnose firewall internet-service6 on page 1452](#)
- [diagnose firewall internet-service6 list on page 1452](#)
- [diagnose firewall internet-service6-cache on page 1452](#)
- [diagnose firewall internet-service6-cache list on page 1452](#)
- [diagnose firewall internet-service6-custom on page 1452](#)
- [diagnose firewall internet-service6-custom list on page 1453](#)
- [diagnose firewall internet-service6-disable on page 1453](#)
- [diagnose firewall internet-service6-disable list on page 1453](#)
- [diagnose firewall internet-service6-extension on page 1453](#)

- [diagnose firewall internet-service6-extension list on page 1453](#)
- [diagnose firewall internet-service6-prio-id on page 1454](#)
- [diagnose firewall internet-service6-prio-id list on page 1454](#)
- [diagnose firewall ipgeo on page 1454](#)
- [diagnose firewall ipgeo copyright-notice on page 1454](#)
- [diagnose firewall ipgeo country-list on page 1454](#)
- [diagnose firewall ipgeo ip-list on page 1454](#)
- [diagnose firewall ipgeo ip2country on page 1455](#)
- [diagnose firewall ipgeo override on page 1455](#)
- [diagnose firewall network-service-dynamic on page 1455](#)
- [diagnose firewall network-service-dynamic list on page 1455](#)
- [diagnose firewall nslookup on page 1455](#)
- [diagnose firewall shaper on page 1456](#)
- [diagnose firewall shaper per-ip-shaper on page 1456](#)
- [diagnose firewall shaper per-ip-shaper clear on page 1456](#)
- [diagnose firewall shaper per-ip-shaper list on page 1456](#)
- [diagnose firewall shaper per-ip-shaper state on page 1456](#)
- [diagnose firewall shaper per-ip-shaper stats on page 1456](#)
- [diagnose firewall shaper traffic-shaper on page 1457](#)
- [diagnose firewall shaper traffic-shaper list on page 1457](#)
- [diagnose firewall shaper traffic-shaper stats on page 1457](#)
- [diagnose firewall shaper traffic-shaper stats clear on page 1457](#)
- [diagnose firewall shaper traffic-shaper stats list on page 1457](#)
- [diagnose firewall snat-ippool on page 1457](#)
- [diagnose firewall snat-ippool list on page 1458](#)
- [diagnose firewall snat-ippool list6 on page 1458](#)

diagnose firewall auth

Authenticated users.

```
diagnose firewall auth
```

diagnose firewall auth clear

Clear authenticated IPv4 users.

```
diagnose firewall auth clear
```

diagnose firewall auth filter

Filters used to list entries.

```
diagnose firewall auth filter
```

diagnose firewall auth filter clear

Clear all filters.

```
diagnose firewall auth filter clear
```

diagnose firewall auth filter group

Group name.

```
diagnose firewall auth filter group <name>
```

Parameter	Description	Type	Size
<name>	Group name.	string	

diagnose firewall auth filter mac

MAC address.

```
diagnose firewall auth filter mac <xx:xx:xx:xx:xx:xx>
```

Parameter	Description	Type	Size
<xx:xx:xx:xx:xx:xx>	MAC address.	string	

diagnose firewall auth filter method

method

```
diagnose firewall auth filter method <method> <method> <method> <method> <method> <method>
```

Parameter	Description	Type	Size
<method>	Valid method name: fsso, rso, ntlm, fw, wso, disclaimer, fsso_citrix, sso_guest.	string	
<method>	Valid method name: fsso, rso, ntlm, fw, wso, email, disclaimer, fsso_citrix, sso_guest.	string	
<method>	Valid method name: fsso, rso, ntlm, fw, wso, email, disclaimer, fsso_citrix, sso_guest.	string	
<method>	Valid method name: fsso, rso, ntlm, fw, wso, email, disclaimer, fsso_citrix, sso_guest.	string	
<method>	Valid method name: fsso, rso, ntlm, fw, wso, email, disclaimer, fsso_citrix, sso_guest.	string	
<method>	Valid method name: fsso, rso, ntlm, fw, wso, email, disclaimer, fsso_citrix, sso_guest.	string	

diagnose firewall auth filter policy

Policy ID.

```
diagnose firewall auth filter policy <xxx>
```

Parameter	Description	Type	Size
<xxx>	Policy ID.	string	

diagnose firewall auth filter source

IPv4 source address.

```
diagnose firewall auth filter source <xxx.xxx.xxx.xxx> <xxx.xxx.xxx.xxx>
```

Parameter	Description	Type	Size
<xxx.xxx.xxx.xxx>	IPv4 source (range from).	string	
<xxx.xxx.xxx.xxx>	IPv4 source (range to).	string	

diagnose firewall auth filter source6

IPv6 source address.

```
diagnose firewall auth filter source6 <xxxx::xxxx> <xxxx::xxxx>
```

Parameter	Description	Type	Size
<xxxx::xxxx>	IPv6 source (range from).	string	
<xxxx::xxxx>	IPv6 source (range to).	string	

diagnose firewall auth filter user

User name.

```
diagnose firewall auth filter user <name>
```

Parameter	Description	Type	Size
<name>	User name.	string	

diagnose firewall auth ipv6

Authenticated IPv6 users.

```
diagnose firewall auth ipv6
```

diagnose firewall auth ipv6 clear

Clear authenticated IPv6 users.

```
diagnose firewall auth ipv6 clear
```

diagnose firewall auth ipv6 list

List authenticated IPv6 users.

```
diagnose firewall auth ipv6 list
```

diagnose firewall auth list

List authenticated IPv4 users.

```
diagnose firewall auth list
```

diagnose firewall auth mac

Authenticated MAC users.

```
diagnose firewall auth mac
```

diagnose firewall auth mac clear

Clear authenticated MAC users.

```
diagnose firewall auth mac clear
```

diagnose firewall auth mac list

List authenticated MAC users.

```
diagnose firewall auth mac list
```

diagnose firewall dynamic

Show dynamic addresses.

```
diagnose firewall dynamic
```

diagnose firewall dynamic address

Get summary of one or all dynamic addresses.

```
diagnose firewall dynamic address <name>
```

Parameter	Description	Type	Size
<name>	Dynamic address name. (Optional)	string	

diagnose firewall dynamic list

Get list of one or all dynamic addresses.

```
diagnose firewall dynamic list <name>
```

Parameter	Description	Type	Size
<name>	Dynamic address name. (Optional)	string	

diagnose firewall dynamic6

Show IPv6 dynamic addresses.

```
diagnose firewall dynamic6
```

diagnose firewall dynamic6 address

Get summary of IPv6 dynamic addresses.

```
diagnose firewall dynamic6 address <name>
```

Parameter	Description	Type	Size
<name>	Dynamic address name.	string	

diagnose firewall dynamic6 list

List all IPv6 dynamic addresses.

```
diagnose firewall dynamic6 list <name>
```

Parameter	Description	Type	Size
<name>	Dynamic address name.	string	

diagnose firewall fqdn

fqdn

```
diagnose firewall fqdn
```

diagnose firewall fqdn get-ip

Get and display one IP FQDN address.

```
diagnose firewall fqdn get-ip <name>
```

Parameter	Description	Type	Size
<name>	Address Name	string	

diagnose firewall fqdn get-mac

Get and display one MAC FQDN address.

```
diagnose firewall fqdn get-mac <name>
```

Parameter	Description	Type	Size
<name>	Address Name	string	

diagnose firewall fqdn getinfo-ip

Get info of IP FQDN address

```
diagnose firewall fqdn getinfo-ip <name>
```

Parameter	Description	Type	Size
<name>	name	string	

diagnose firewall fqdn getinfo-mac

Get info of MAC FQDN address

```
diagnose firewall fqdn getinfo-mac <name>
```

Parameter	Description	Type	Size
<name>	name	string	

diagnose firewall fqdn list-all

List FQDN.

```
diagnose firewall fqdn list-all
```


diagnose firewall fqdn list-ip

List IP FQDN.

```
diagnose firewall fqdn list-ip
```

diagnose firewall fqdn list-mac

List MAC FQDN.

```
diagnose firewall fqdn list-mac
```

diagnose firewall fqdn6

IPv6 FQDN.

```
diagnose firewall fqdn6
```

diagnose firewall fqdn6 get

Get and display one IPv6 FQDN address.

```
diagnose firewall fqdn6 get <name>
```

Parameter	Description	Type	Size
<name>	Address Name	string	

diagnose firewall fqdn6 list

List all IPv6 FQDN.

```
diagnose firewall fqdn6 list
```

diagnose firewall internet-service

Internet service in the kernel.

```
diagnose firewall internet-service
```

diagnose firewall internet-service list

List Internet Service.

```
diagnose firewall internet-service list <section>
```

Parameter	Description	Type	Size
<section>	Internet Service table section.(0: entry, 1: index, <integer>: singularity)	string	

diagnose firewall internet-service-app-ctrl

Application control internet service in the kernel.

```
diagnose firewall internet-service-app-ctrl
```

diagnose firewall internet-service-cache

Internet Service database cache entries in the kernel.

```
diagnose firewall internet-service-cache
```

diagnose firewall internet-service-cache list

List Internet Service database cache entries in the kernel.

```
diagnose firewall internet-service-cache list
```

diagnose firewall internet-service-custom

Custom Internet Service in the kernel.

```
diagnose firewall internet-service-custom
```

diagnose firewall internet-service-custom list

List Custom Internet Service.

```
diagnose firewall internet-service-custom list <name>
```

Parameter	Description	Type	Size
<name>	Custom Internet Service name.	string	

diagnose firewall internet-service-disable

Internet Service disable entries in the kernel.

```
diagnose firewall internet-service-disable
```

diagnose firewall internet-service-disable list

List Internet Service disable entries.

```
diagnose firewall internet-service-disable list <ID>
```

Parameter	Description	Type	Size
<ID>	Internet Service ID.	string	

diagnose firewall internet-service-extension

Internet Service extension in the kernel.

```
diagnose firewall internet-service-extension
```

diagnose firewall internet-service-extension list

List Internet Service extension.

```
diagnose firewall internet-service-extension list <ID>
```

Parameter	Description	Type	Size
<ID>	Internet Service ID.	string	

diagnose firewall internet-service-prio-id

Internet service ID in firewall policy, shaping policy, SD-WAN rule, static route, and router policy.

```
diagnose firewall internet-service-prio-id
```

diagnose firewall internet-service-prio-id list

List Internet Service Priority ID.

```
diagnose firewall internet-service-prio-id list
```

diagnose firewall internet-service6

Internet service6 in the kernel.

```
diagnose firewall internet-service6
```

diagnose firewall internet-service6 list

List Internet Service6.

```
diagnose firewall internet-service6 list <section>
```

Parameter	Description	Type	Size
<section>	Internet Service6 table section.(0: entry, 1: index, <integer>: singularity)	string	

diagnose firewall internet-service6-cache

Internet Service database cache entries for IPv6 in the kernel.

```
diagnose firewall internet-service6-cache
```

diagnose firewall internet-service6-cache list

List Internet Service database cache entries for IPv6 in the kernel.

```
diagnose firewall internet-service6-cache list
```

diagnose firewall internet-service6-custom

Custom Internet Service6 in the kernel.

```
diagnose firewall internet-service6-custom
```

diagnose firewall internet-service6-custom list

List Custom Internet Service.

```
diagnose firewall internet-service6-custom list <name>
```

Parameter	Description	Type	Size
<name>	Custom Internet Service name.	string	

diagnose firewall internet-service6-disable

Internet Service6 disable entries in the kernel.

```
diagnose firewall internet-service6-disable
```

diagnose firewall internet-service6-disable list

List Internet Service6 disable entries.

```
diagnose firewall internet-service6-disable list <ID>
```

Parameter	Description	Type	Size
<ID>	Internet Service6 ID.	string	

diagnose firewall internet-service6-extension

Internet Service6 extension in the kernel.

```
diagnose firewall internet-service6-extension
```

diagnose firewall internet-service6-extension list

List Internet Service6 extension.

```
diagnose firewall internet-service6-extension list <ID>
```

Parameter	Description	Type	Size
<ID>	Internet Service6 ID.	string	

diagnose firewall internet-service6-prio-id

Internet service ID in firewall policy, SD-WAN rule, and router policy.

```
diagnose firewall internet-service6-prio-id
```

diagnose firewall internet-service6-prio-id list

List Internet Service6 Priority ID.

```
diagnose firewall internet-service6-prio-id list
```

diagnose firewall ipgeo

IP geolocation.

```
diagnose firewall ipgeo
```

diagnose firewall ipgeo copyright-notice

Copyright note.

```
diagnose firewall ipgeo copyright-notice
```

diagnose firewall ipgeo country-list

List all countries.

```
diagnose firewall ipgeo country-list
```

diagnose firewall ipgeo ip-list

List IP info of country.

```
diagnose firewall ipgeo ip-list <name>
```

Parameter	Description	Type	Size
<name>	Country ID.	string	

diagnose firewall ipgeo ip2country

Get country info for the IP.

```
diagnose firewall ipgeo ip2country <ip>
```

Parameter	Description	Type	Size
<ip>	IPv4/IPv6 address.	string	

diagnose firewall ipgeo override

Print out all user defined IP geolocation data.

```
diagnose firewall ipgeo override
```

diagnose firewall network-service-dynamic

Dynamic Network Service in the kernel.

```
diagnose firewall network-service-dynamic
```

diagnose firewall network-service-dynamic list

List Dynamic Network Service.

```
diagnose firewall network-service-dynamic list <name>
```

Parameter	Description	Type	Size
<name>	Dynamic Network Service name.	string	

diagnose firewall nslookup

Name server lookup.

```
diagnose firewall nslookup <FQDN> <DNS-server>
```

Parameter	Description	Type	Size
<FQDN>	FQDN.	string	

Parameter	Description	Type	Size
<DNS-server>	DNS-server.	string	

diagnose firewall shaper

shapers

```
diagnose firewall shaper
```

diagnose firewall shaper per-ip-shaper

Traffic shapers.

```
diagnose firewall shaper per-ip-shaper
```

diagnose firewall shaper per-ip-shaper clear

Per-IP clear statistic data.

```
diagnose firewall shaper per-ip-shaper clear
```

diagnose firewall shaper per-ip-shaper list

List per-IP shapers.

```
diagnose firewall shaper per-ip-shaper list
```

diagnose firewall shaper per-ip-shaper state

Per-IP shapers state.

```
diagnose firewall shaper per-ip-shaper state
```

diagnose firewall shaper per-ip-shaper stats

Per-IP shapers statistic.


```
diagnose firewall shaper per-ip-shaper stats
```

diagnose firewall shaper traffic-shaper

Traffic shapers.

```
diagnose firewall shaper traffic-shaper
```

diagnose firewall shaper traffic-shaper list

List traffic shapers.

```
diagnose firewall shaper traffic-shaper list
```

diagnose firewall shaper traffic-shaper stats

Traffic shaper statistics.

```
diagnose firewall shaper traffic-shaper stats
```

diagnose firewall shaper traffic-shaper stats clear

Clear traffic shaper statistics.

```
diagnose firewall shaper traffic-shaper stats clear <name>
```

Parameter	Description	Type	Size
<name>	Name of traffic shaper to clear.	string	

diagnose firewall shaper traffic-shaper stats list

List traffic shaper statistics.

```
diagnose firewall shaper traffic-shaper stats list
```

diagnose firewall snat-ippool

All IP pool.

```
diagnose firewall snat-ippool
```

diagnose firewall snat-ippool list

List IPv4.

```
diagnose firewall snat-ippool list
```

diagnose firewall snat-ippool list6

List IPv6.

```
diagnose firewall snat-ippool list6
```

diagnose forticlient

forticlient

This topic includes the following commands:

- [diagnose forticlient add-connection on page 1458](#)
- [diagnose forticlient close-all-connection on page 1459](#)
- [diagnose forticlient close-connection on page 1459](#)

diagnose forticlient add-connection

Add test FortiClient connection.

```
diagnose forticlient add-connection <name> <user> <id> <host os> <ip>
```

Parameter	Description	Type	Size
<name>	FortiClient name.	string	
<user>	User name.	string	
<id>	Client ID.	string	
<host os>	Host OS.	string	
<ip>	Source IP.	string	

diagnose forticlient close-all-connection

Close all test FortiClient connection.

```
diagnose forticlient close-all-connection
```

diagnose forticlient close-connection

Close test FortiClient connection.

```
diagnose forticlient close-connection <handle>
```

Parameter	Description	Type	Size
<handle>	FortiClient connection handle. Type enter to list current handles.	string	

diagnose fortiguard-resources

FortiGuard resources.

This topic includes the following commands:

- [diagnose fortiguard-resources delete on page 1460](#)
- [diagnose fortiguard-resources delete app-categories on page 1460](#)
- [diagnose fortiguard-resources delete app-info on page 1460](#)
- [diagnose fortiguard-resources delete fortiap-end-of-support on page 1461](#)
- [diagnose fortiguard-resources delete fortiextender-end-of-support on page 1461](#)
- [diagnose fortiguard-resources delete fortigate-end-of-support on page 1461](#)
- [diagnose fortiguard-resources delete fortiswitch-end-of-support on page 1461](#)
- [diagnose fortiguard-resources delete ips-information on page 1461](#)
- [diagnose fortiguard-resources delete prefix-links on page 1462](#)
- [diagnose fortiguard-resources delete sprite-isdb on page 1462](#)
- [diagnose fortiguard-resources delete sprite-map on page 1462](#)
- [diagnose fortiguard-resources delete static-links on page 1462](#)
- [diagnose fortiguard-resources delete wf-categories on page 1462](#)
- [diagnose fortiguard-resources downloads on page 1462](#)
- [diagnose fortiguard-resources downloads disable on page 1463](#)
- [diagnose fortiguard-resources downloads enable on page 1463](#)
- [diagnose fortiguard-resources info on page 1463](#)
- [diagnose fortiguard-resources info app-categories on page 1463](#)
- [diagnose fortiguard-resources info app-info on page 1463](#)

- [diagnose fortiguard-resources info fortiap-end-of-support on page 1464](#)
- [diagnose fortiguard-resources info fortiextender-end-of-support on page 1464](#)
- [diagnose fortiguard-resources info fortigate-end-of-support on page 1464](#)
- [diagnose fortiguard-resources info fortiswitch-end-of-support on page 1464](#)
- [diagnose fortiguard-resources info ips-information on page 1464](#)
- [diagnose fortiguard-resources info prefix-links on page 1465](#)
- [diagnose fortiguard-resources info sprite-isdb.css on page 1465](#)
- [diagnose fortiguard-resources info sprite-isdb.png on page 1465](#)
- [diagnose fortiguard-resources info sprite-map.css on page 1465](#)
- [diagnose fortiguard-resources info sprite-map.png on page 1465](#)
- [diagnose fortiguard-resources info static-links on page 1465](#)
- [diagnose fortiguard-resources info wf-categories on page 1466](#)
- [diagnose fortiguard-resources update on page 1466](#)
- [diagnose fortiguard-resources update app-categories on page 1466](#)
- [diagnose fortiguard-resources update app-info on page 1466](#)
- [diagnose fortiguard-resources update fortiap-end-of-support on page 1466](#)
- [diagnose fortiguard-resources update fortiextender-end-of-support on page 1466](#)
- [diagnose fortiguard-resources update fortigate-end-of-support on page 1467](#)
- [diagnose fortiguard-resources update fortiswitch-end-of-support on page 1467](#)
- [diagnose fortiguard-resources update ips-information on page 1467](#)
- [diagnose fortiguard-resources update prefix-links on page 1467](#)
- [diagnose fortiguard-resources update sprite-isdb on page 1467](#)
- [diagnose fortiguard-resources update sprite-map on page 1468](#)
- [diagnose fortiguard-resources update static-links on page 1468](#)
- [diagnose fortiguard-resources update wf-categories on page 1468](#)

diagnose fortiguard-resources delete

Deletes all downloaded files for a FortiGuard resource, restores the original copy if available.

```
diagnose fortiguard-resources delete
```

diagnose fortiguard-resources delete app-categories

Application categories.

```
diagnose fortiguard-resources delete app-categories
```

diagnose fortiguard-resources delete app-info

Application info for a given ID. If no ID given, deletes all application info resources.

```
diagnose fortiguard-resources delete app-info <id>
```

Parameter	Description	Type	Size
<id>	ID of application to be deleted.	string	

diagnose fortiguard-resources delete fortiap-end-of-support

FortiAP product life cycle information.

```
diagnose fortiguard-resources delete fortiap-end-of-support
```

diagnose fortiguard-resources delete fortiextender-end-of-support

FortiExtender product life cycle information.

```
diagnose fortiguard-resources delete fortiextender-end-of-support
```

diagnose fortiguard-resources delete fortigate-end-of-support

FortiGate product life cycle information.

```
diagnose fortiguard-resources delete fortigate-end-of-support
```

diagnose fortiguard-resources delete fortiswitch-end-of-support

FortiSwitch product life cycle information.

```
diagnose fortiguard-resources delete fortiswitch-end-of-support
```

diagnose fortiguard-resources delete ips-information

IPS information for a given ID. If no ID given, deletes all IPS info resources.

```
diagnose fortiguard-resources delete ips-information <id>
```

Parameter	Description	Type	Size
<id>	ID of IPS to be deleted.	string	

diagnose fortiguard-resources delete prefix-links

Prefix links.

```
diagnose fortiguard-resources delete prefix-links
```

diagnose fortiguard-resources delete sprite-isdb

Application icon sprite ISDB (CSS & PNG).

```
diagnose fortiguard-resources delete sprite-isdb
```

diagnose fortiguard-resources delete sprite-map

Application icon sprite map (CSS & PNG).

```
diagnose fortiguard-resources delete sprite-map
```

diagnose fortiguard-resources delete static-links

Static links.

```
diagnose fortiguard-resources delete static-links
```

diagnose fortiguard-resources delete wf-categories

Web filter categories.

```
diagnose fortiguard-resources delete wf-categories
```

diagnose fortiguard-resources downloads

Settings for download of FortiGuard resources.

```
diagnose fortiguard-resources downloads
```

diagnose fortiguard-resources downloads disable

Disable GUI downloading of resources from FortiGuard.

```
diagnose fortiguard-resources downloads disable
```

diagnose fortiguard-resources downloads enable

Enable GUI downloading of resources from FortiGuard.

```
diagnose fortiguard-resources downloads enable
```

diagnose fortiguard-resources info

View file information of a downloaded FortiGuard resource.

```
diagnose fortiguard-resources info
```

diagnose fortiguard-resources info app-categories

Application categories.

```
diagnose fortiguard-resources info app-categories
```

diagnose fortiguard-resources info app-info

Application info for a given ID.

```
diagnose fortiguard-resources info app-info <id>
```

Parameter	Description	Type	Size
<id>	ID of application to be retrieved.	string	

diagnose fortiguard-resources info fortiap-end-of-support

FortiAP product life cycle information.

```
diagnose fortiguard-resources info fortiap-end-of-support
```

diagnose fortiguard-resources info fortiextender-end-of-support

FortiExtender product life cycle information.

```
diagnose fortiguard-resources info fortiextender-end-of-support
```

diagnose fortiguard-resources info fortigate-end-of-support

FortiGate product life cycle information.

```
diagnose fortiguard-resources info fortigate-end-of-support
```

diagnose fortiguard-resources info fortiswitch-end-of-support

FortiSwitch product life cycle information.

```
diagnose fortiguard-resources info fortiswitch-end-of-support
```

diagnose fortiguard-resources info ips-information

IPS information for a given ID.

```
diagnose fortiguard-resources info ips-information <id>
```

Parameter	Description	Type	Size
<id>	ID of IPS to be retrieved.	string	

diagnose fortiguard-resources info prefix-links

Prefix links.

```
diagnose fortiguard-resources info prefix-links
```

diagnose fortiguard-resources info sprite-isdb.css

Application icon sprite ISDB (CSS).

```
diagnose fortiguard-resources info sprite-isdb.css
```

diagnose fortiguard-resources info sprite-isdb.png

Application icon sprite ISDB (PNG).

```
diagnose fortiguard-resources info sprite-isdb.png
```

diagnose fortiguard-resources info sprite-map.css

Application icon sprite map (CSS).

```
diagnose fortiguard-resources info sprite-map.css
```

diagnose fortiguard-resources info sprite-map.png

Application icon sprite map (PNG).

```
diagnose fortiguard-resources info sprite-map.png
```

diagnose fortiguard-resources info static-links

Static links.

```
diagnose fortiguard-resources info static-links
```

diagnose fortiguard-resources info wf-categories

Web filter categories.

```
diagnose fortiguard-resources info wf-categories
```

diagnose fortiguard-resources update

Deletes cached files and force downloads the FortiGuard resource (ignores GUI enable/disable).

```
diagnose fortiguard-resources update
```

diagnose fortiguard-resources update app-categories

Application categories.

```
diagnose fortiguard-resources update app-categories
```

diagnose fortiguard-resources update app-info

Application info for a given ID.

```
diagnose fortiguard-resources update app-info <id>
```

Parameter	Description	Type	Size
<id>	ID of application to be retrieved.	string	

diagnose fortiguard-resources update fortiap-end-of-support

FortiAP product life cycle information.

```
diagnose fortiguard-resources update fortiap-end-of-support
```

diagnose fortiguard-resources update fortiextender-end-of-support

FortiExtender product life cycle information.

```
diagnose fortiguard-resources update fortiextender-end-of-support
```

diagnose fortiguard-resources update fortigate-end-of-support

FortiGate product life cycle information.

```
diagnose fortiguard-resources update fortigate-end-of-support
```

diagnose fortiguard-resources update fortiswitch-end-of-support

FortiSwitch product life cycle information.

```
diagnose fortiguard-resources update fortiswitch-end-of-support
```

diagnose fortiguard-resources update ips-information

IPS information for a given ID.

```
diagnose fortiguard-resources update ips-information <id>
```

Parameter	Description	Type	Size
<id>	ID of IPS to be retrieved.	string	

diagnose fortiguard-resources update prefix-links

Prefix links.

```
diagnose fortiguard-resources update prefix-links
```

diagnose fortiguard-resources update sprite-isdb

Application icon sprite ISDB (CSS & PNG).

```
diagnose fortiguard-resources update sprite-isdb
```

diagnose fortiguard-resources update sprite-map

Application icon sprite map (CSS & PNG).

```
diagnose fortiguard-resources update sprite-map
```

diagnose fortiguard-resources update static-links

Static links.

```
diagnose fortiguard-resources update static-links
```

diagnose fortiguard-resources update wf-categories

Web filter categories.

```
diagnose fortiguard-resources update wf-categories
```

diagnose fortitoken

FortiToken

This topic includes the following commands:

- [diagnose fortitoken debug on page 1468](#)
- [diagnose fortitoken debug disable on page 1468](#)
- [diagnose fortitoken debug enable on page 1469](#)
- [diagnose fortitoken info on page 1469](#)
- [diagnose fortitoken test on page 1469](#)

diagnose fortitoken debug

Debug enable/disable.

```
diagnose fortitoken debug
```

diagnose fortitoken debug disable

Disable debug output.

```
diagnose fortitoken debug disable
```

diagnose fortitoken debug enable

Enable debug output.

```
diagnose fortitoken debug enable
```

diagnose fortitoken info

Show current drift and status for each FortiToken.

```
diagnose fortitoken info <id>
```

Parameter	Description	Type	Size
<id>	FortiToken ID.	string	

diagnose fortitoken test

Test FortiToken with screen setting for drift of internal clock.

```
diagnose fortitoken test <id> <code> <next code> <screen size>
```

Parameter	Description	Type	Size
<id>	FortiToken ID.	string	
<code>	FortiToken code.	string	
<next code>	Next FortiToken code.	string	
<screen size>	Screen size for drift of internal clock.	string	

diagnose fortitoken-cloud

FortiToken Cloud Service.

This topic includes the following commands:

- [diagnose fortitoken-cloud clear on page 1470](#)
- [diagnose fortitoken-cloud debug on page 1470](#)

- [diagnose fortitoken-cloud debug disable on page 1470](#)
- [diagnose fortitoken-cloud debug enable on page 1470](#)
- [diagnose fortitoken-cloud debug info on page 1470](#)
- [diagnose fortitoken-cloud delete on page 1471](#)
- [diagnose fortitoken-cloud migrate-ftm on page 1471](#)
- [diagnose fortitoken-cloud server on page 1471](#)
- [diagnose fortitoken-cloud set-http on page 1471](#)
- [diagnose fortitoken-cloud show on page 1472](#)
- [diagnose fortitoken-cloud sync on page 1472](#)

diagnose fortitoken-cloud clear

Clear server connection settings for diagnostics.

```
diagnose fortitoken-cloud clear
```

diagnose fortitoken-cloud debug

Enable/disable debug output.

```
diagnose fortitoken-cloud debug
```

diagnose fortitoken-cloud debug disable

Disable debug output.

```
diagnose fortitoken-cloud debug disable
```

diagnose fortitoken-cloud debug enable

Enable debug output.

```
diagnose fortitoken-cloud debug enable
```

diagnose fortitoken-cloud debug info

Debug status.

```
diagnose fortitoken-cloud debug info
```

diagnose fortitoken-cloud delete

Command to delete a user.

```
diagnose fortitoken-cloud delete <string> <string>
```

Parameter	Description	Type	Size
<string>	User name.	string	
<string>	VDOM name.	string	

diagnose fortitoken-cloud migrate-ftm

Perform FTM license migration.

```
diagnose fortitoken-cloud migrate-ftm <string> <string> <string>
```

Parameter	Description	Type	Size
<string>	Enter command: show, start, abort, add-users, delete-users, ftm2ftc.	string	
<string>	FTM license number.	string	
<string>	<return> or VDOM name if add-users delete-users and ftm2ftc.	string	

diagnose fortitoken-cloud server

IP address port number and https.

```
diagnose fortitoken-cloud server <xxx.xxx.xxx.xxx> <xxx>
```

Parameter	Description	Type	Size
<xxx.xxx.xxx.xxx>	IP address.	string	
<xxx>	Port number <0-65535>.	string	

diagnose fortitoken-cloud set-http

Set HTTP status return code for diagnostics only.

```
diagnose fortitoken-cloud set-http <number>
```

Parameter	Description	Type	Size
<number>	Status code (value < 300 clears the error diagnostics).	string	

diagnose fortitoken-cloud show

Display diagnostics information.

```
diagnose fortitoken-cloud show <string> <string> <string>
```

Parameter	Description	Type	Size
<string>	Enter <server service realm users user>.	string	
<string>	Enter username to get user information otherwise enter return.	string	
<string>	Enter VDOM name if getting user information.	string	

diagnose fortitoken-cloud sync

Synchronize user information with FortiToken Cloud.

```
diagnose fortitoken-cloud sync <user type>
```

Parameter	Description	Type	Size
<user type>	Enter <return>, all, local, or remote.	string	

diagnose fortiview

Fortiview backend diagnostic

```
diagnose fortiview
```

diagnose geoip

Diagnose geography IP database and service.

This topic includes the following commands:

- [diagnose geoip delete-geoip-db](#) on page 1473
- [diagnose geoip geoip-query](#) on page 1473
- [diagnose geoip ip2country](#) on page 1473
- [diagnose geoip iprange](#) on page 1473
- [diagnose geoip iprange6](#) on page 1473

diagnose geoip delete-geoip-db

Delete geography IP database currently saved on this FortiProxy unit.

```
diagnose geoip delete-geoip-db
```

diagnose geoip geoip-query

Query FortiGuard service for geography information based on IP address.

```
diagnose geoip geoip-query <ip>
```

Parameter	Description	Type	Size
<ip>	IPv4 address.	string	

diagnose geoip ip2country

Query local geography IP database for country information based on IP address.

```
diagnose geoip ip2country <ip>
```

Parameter	Description	Type	Size
<ip>	IPv4/IPv6 address.	string	

diagnose geoip iprange

List IP ranges of specified country.

```
diagnose geoip iprange
```

diagnose geoip iprange6

List IPv6 ranges of specified country.

```
diagnose geoip iprange6
```

diagnose hardware

hardware

This topic includes the following commands:

- [diagnose hardware certificate on page 1474](#)
- [diagnose hardware deviceinfo on page 1474](#)
- [diagnose hardware deviceinfo disk on page 1475](#)
- [diagnose hardware deviceinfo nic on page 1475](#)
- [diagnose hardware deviceinfo nic-channel on page 1475](#)
- [diagnose hardware deviceinfo nic-stats on page 1475](#)
- [diagnose hardware lspci on page 1475](#)
- [diagnose hardware mii on page 1475](#)
- [diagnose hardware sysinfo on page 1476](#)
- [diagnose hardware sysinfo conserve on page 1476](#)
- [diagnose hardware sysinfo cpu on page 1476](#)
- [diagnose hardware sysinfo interrupts on page 1476](#)
- [diagnose hardware sysinfo iomem on page 1476](#)
- [diagnose hardware sysinfo ioports on page 1476](#)
- [diagnose hardware sysinfo memory on page 1477](#)
- [diagnose hardware sysinfo mtrr on page 1477](#)
- [diagnose hardware sysinfo slab on page 1477](#)

diagnose hardware certificate

Verify certificates.

```
diagnose hardware certificate
```

diagnose hardware deviceinfo

Get device information.

```
diagnose hardware deviceinfo
```

diagnose hardware deviceinfo disk

Display information of all disks.

```
diagnose hardware deviceinfo disk
```

diagnose hardware deviceinfo nic

Display NIC information.

```
diagnose hardware deviceinfo nic
```

diagnose hardware deviceinfo nic-channel

Display NIC channels.

```
diagnose hardware deviceinfo nic-channel
```

diagnose hardware deviceinfo nic-stats

Display NIC statistics.

```
diagnose hardware deviceinfo nic-stats
```

diagnose hardware lspci

List PCI parameters.

```
diagnose hardware lspci
```

diagnose hardware mii

Access mii registers.

```
diagnose hardware mii
```

diagnose hardware sysinfo

Get system information.

```
diagnose hardware sysinfo
```

diagnose hardware sysinfo conserve

Display information about memory conservation status.

```
diagnose hardware sysinfo conserve
```

diagnose hardware sysinfo cpu

Display detailed information for all installed CPU(s).

```
diagnose hardware sysinfo cpu
```

diagnose hardware sysinfo interrupts

Display system interrupts information.

```
diagnose hardware sysinfo interrupts
```

diagnose hardware sysinfo iomem

Display memory map of I/O ports.

```
diagnose hardware sysinfo iomem
```

diagnose hardware sysinfo ioports

Display address list of I/O ports.

```
diagnose hardware sysinfo ioports
```

diagnose hardware sysinfo memory

Display system memory information.

```
diagnose hardware sysinfo memory
```

diagnose hardware sysinfo mtrr

Display memory type range register.

```
diagnose hardware sysinfo mtrr
```

diagnose hardware sysinfo slab

Display memory allocation information.

```
diagnose hardware sysinfo slab
```

diagnose http-view

HTTP/S traffic daemon

This topic includes the following commands:

- [diagnose http-view clear on page 1477](#)
- [diagnose http-view debug on page 1477](#)
- [diagnose http-view log-show on page 1478](#)
- [diagnose http-view restart on page 1478](#)
- [diagnose http-view stats on page 1478](#)

diagnose http-view clear

Restart daemon, reset statistics & remove all history

```
diagnose http-view clear
```

diagnose http-view debug

Set debug level for deamon

```
diagnose http-view debug <debug level>
```

Parameter	Description	Type	Size
<debug level>	Hexadecimal number	string	

diagnose http-view log-show

Show log of daemon

```
diagnose http-view log-show <log generation> <time format>
```

Parameter	Description	Type	Size
<log generation>	Log generation: default 0	string	
<time format>	Time format: 0 for human readable and 1 for raw, default 0	string	

diagnose http-view restart

Restart the daemon and reset statistics

```
diagnose http-view restart
```

diagnose http-view stats

Show statistics.

```
diagnose http-view stats
```

diagnose ip

ip

This topic includes the following commands:

- [diagnose ip address on page 1479](#)
- [diagnose ip address add on page 1479](#)
- [diagnose ip address delete on page 1479](#)

- [diagnose ip address list on page 1480](#)
- [diagnose ip arp on page 1480](#)
- [diagnose ip arp add on page 1480](#)
- [diagnose ip arp delete on page 1480](#)
- [diagnose ip arp list on page 1481](#)
- [diagnose ip route on page 1481](#)
- [diagnose ip route add on page 1481](#)
- [diagnose ip route delete on page 1481](#)
- [diagnose ip route list on page 1482](#)
- [diagnose ip route match on page 1482](#)
- [diagnose ip route verify on page 1482](#)
- [diagnose ip tcp on page 1483](#)
- [diagnose ip tcp list on page 1483](#)
- [diagnose ip udp on page 1483](#)
- [diagnose ip udp list on page 1483](#)

diagnose ip address

IP addresses.

```
diagnose ip address
```

diagnose ip address add

Add IP address.

```
diagnose ip address add <intf-name> <XXX.XXX.XXX.XXX> <XXX.XXX.XXX.XXX>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<XXX.XXX.XXX.XXX>	IP address.	string	
<XXX.XXX.XXX.XXX>	IP network mask.	string	

diagnose ip address delete

Delete IP address.

```
diagnose ip address delete <intf-name> <XXX.XXX.XXX.XXX>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<XXX.XXX.XXX.XXX>	IP address.	string	

diagnose ip address list

List IP addresses.

```
diagnose ip address list
```

diagnose ip arp

ARP table.

```
diagnose ip arp
```

diagnose ip arp add

Add an ARP entry.

```
diagnose ip arp add <intf-name> <XXX.XXX.XXX.XXX> <XX:XX:XX:XX:XX:XX>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<XXX.XXX.XXX.XXX>	IP address.	string	
<XX:XX:XX:XX:XX:XX>	MAC address.	string	

diagnose ip arp delete

Delete an ARP entry.

```
diagnose ip arp delete <intf-name> <XXX.XXX.XXX.XXX>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<XXX.XXX.XXX.XXX>	IP address.	string	

diagnose ip arp list

Show ARP table.

```
diagnose ip arp list
```

diagnose ip route

Routing table.

```
diagnose ip route
```

diagnose ip route add

Add static route.

```
diagnose ip route add <intf-name> <XXX.XXX.XXX.XXX> <XXX.XXX.XXX.XXX> <XXX.XXX.XXX.XXX> <1-255>  
<0-4294967295> <verify> <ha>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<XXX.XXX.XXX.XXX>	IP address.	string	
<XXX.XXX.XXX.XXX>	IP network mask.	string	
<XXX.XXX.XXX.XXX>	Nexthop IP address.	string	
<1-255>	Route distance.	string	
<0-4294967295>	Route priority.	string	
<verify>	Verify operation.	string	
<ha>	HA protocol	string	

diagnose ip route delete

Delete static route.

```
diagnose ip route delete <intf-name> <XXX.XXX.XXX.XXX> <XXX.XXX.XXX.XXX> <XXX.XXX.XXX.XXX> <1-255>  
<0-4294967295> <verify> <ha>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<XXX.XXX.XXX.XXX>	IP address.	string	
<XXX.XXX.XXX.XXX>	IP network mask.	string	
<XXX.XXX.XXX.XXX>	Nexthop IP address.	string	
<1-255>	Route distance.	string	
<0-4294967295>	Route priority.	string	
<verify>	Verify operation.	string	
<ha>	HA protocol	string	

diagnose ip route list

List routing table.

```
diagnose ip route list
```

diagnose ip route match

Match kernel route.

```
diagnose ip route match <XXX.XXX.XXX.XXX> <XXX.XXX.XXX.XXX> <intf-name> <intf-name> <0-31>
```

Parameter	Description	Type	Size
<XXX.XXX.XXX.XXX>	Destination address.	string	
<XXX.XXX.XXX.XXX>	Source address.	string	
<intf-name>	Outgoing interface.	string	
<intf-name>	Incoming interface.	string	
<0-31>	VRF.	string	

diagnose ip route verify

Verify static route.

```
diagnose ip route verify <intf-name> <XXX.XXX.XXX.XXX> <XXX.XXX.XXX.XXX> <XXX.XXX.XXX.XXX> <1-255>  
<0-4294967295>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<XXX.XXX.XXX.XXX>	IP address.	string	
<XXX.XXX.XXX.XXX>	IP network mask.	string	
<XXX.XXX.XXX.XXX>	Nexthop IP address.	string	
<1-255>	Route distance.	string	
<0-4294967295>	Route priority.	string	

diagnose ip tcp

TCP sockets.

```
diagnose ip tcp
```

diagnose ip tcp list

List TCP sockets.

```
diagnose ip tcp list
```

diagnose ip udp

UDP sockets.

```
diagnose ip udp
```

diagnose ip udp list

List UDP sockets.

```
diagnose ip udp list
```

diagnose ip address

IP addresses.

This topic includes the following commands:

- [diagnose ip address add on page 1484](#)
- [diagnose ip address delete on page 1484](#)
- [diagnose ip address list on page 1484](#)

diagnose ip address add

Add IP address.

```
diagnose ip address add <intf-name> <XXX.XXX.XXX.XXX> <XXX.XXX.XXX.XXX>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<XXX.XXX.XXX.XXX>	IP address.	string	
<XXX.XXX.XXX.XXX>	IP network mask.	string	

diagnose ip address delete

Delete IP address.

```
diagnose ip address delete <intf-name> <XXX.XXX.XXX.XXX>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<XXX.XXX.XXX.XXX>	IP address.	string	

diagnose ip address list

List IP addresses.

```
diagnose ip address list
```

diagnose ip arp

ARP table.

This topic includes the following commands:

- [diagnose ip arp add on page 1485](#)
- [diagnose ip arp delete on page 1485](#)
- [diagnose ip arp list on page 1485](#)

diagnose ip arp add

Add an ARP entry.

```
diagnose ip arp add <intf-name> <XXX.XXX.XXX.XXX> <XX:XX:XX:XX:XX:XX>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<XXX.XXX.XXX.XXX>	IP address.	string	
<XX:XX:XX:XX:XX:XX>	MAC address.	string	

diagnose ip arp delete

Delete an ARP entry.

```
diagnose ip arp delete <intf-name> <XXX.XXX.XXX.XXX>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<XXX.XXX.XXX.XXX>	IP address.	string	

diagnose ip arp list

Show ARP table.

```
diagnose ip arp list
```

diagnose ip route

Routing table.

This topic includes the following commands:

- [diagnose ip route add on page 1486](#)
- [diagnose ip route delete on page 1486](#)

- [diagnose ip route list on page 1487](#)
- [diagnose ip route match on page 1487](#)
- [diagnose ip route verify on page 1487](#)

diagnose ip route add

Add static route.

```
diagnose ip route add <intf-name> <XXX.XXX.XXX.XXX> <XXX.XXX.XXX.XXX> <XXX.XXX.XXX.XXX> <1-255>  
<0-4294967295> <verify> <ha>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<XXX.XXX.XXX.XXX>	IP address.	string	
<XXX.XXX.XXX.XXX>	IP network mask.	string	
<XXX.XXX.XXX.XXX>	Nexthop IP address.	string	
<1-255>	Route distance.	string	
<0-4294967295>	Route priority.	string	
<verify>	Verify operation.	string	
<ha>	HA protocol	string	

diagnose ip route delete

Delete static route.

```
diagnose ip route delete <intf-name> <XXX.XXX.XXX.XXX> <XXX.XXX.XXX.XXX> <XXX.XXX.XXX.XXX> <1-255>  
<0-4294967295> <verify> <ha>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<XXX.XXX.XXX.XXX>	IP address.	string	
<XXX.XXX.XXX.XXX>	IP network mask.	string	
<XXX.XXX.XXX.XXX>	Nexthop IP address.	string	
<1-255>	Route distance.	string	
<0-4294967295>	Route priority.	string	
<verify>	Verify operation.	string	
<ha>	HA protocol	string	

diagnose ip route list

List routing table.

```
diagnose ip route list
```

diagnose ip route match

Match kernel route.

```
diagnose ip route match <XXX.XXX.XXX.XXX> <XXX.XXX.XXX.XXX> <intf-name> <intf-name> <0-31>
```

Parameter	Description	Type	Size
<XXX.XXX.XXX.XXX>	Destination address.	string	
<XXX.XXX.XXX.XXX>	Source address.	string	
<intf-name>	Outgoing interface.	string	
<intf-name>	Incoming interface.	string	
<0-31>	VRF.	string	

diagnose ip route verify

Verify static route.

```
diagnose ip route verify <intf-name> <XXX.XXX.XXX.XXX> <XXX.XXX.XXX.XXX> <XXX.XXX.XXX.XXX> <1-255>  
<0-4294967295>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<XXX.XXX.XXX.XXX>	IP address.	string	
<XXX.XXX.XXX.XXX>	IP network mask.	string	
<XXX.XXX.XXX.XXX>	Nexthop IP address.	string	
<1-255>	Route distance.	string	
<0-4294967295>	Route priority.	string	

diagnose ip tcp

TCP sockets.

This topic includes the following commands:

- [diagnose ip tcp list on page 1488](#)

diagnose ip tcp list

List TCP sockets.

```
diagnose ip tcp list
```

diagnose ip udp

UDP sockets.

This topic includes the following commands:

- [diagnose ip udp list on page 1488](#)

diagnose ip udp list

List UDP sockets.

```
diagnose ip udp list
```

diagnose ipsec

ipsec

This topic includes the following commands:

- [diagnose ipsec connect on page 1489](#)
- [diagnose ipsec list-conn on page 1489](#)
- [diagnose ipsec list-sa on page 1489](#)
- [diagnose ipsec p1-status on page 1489](#)
- [diagnose ipsec reload-ca on page 1489](#)
- [diagnose ipsec reload-ipsec on page 1489](#)

diagnose ipsec connect

connect sa

```
diagnose ipsec connect <phase1> <phase2>
```

Parameter	Description	Type	Size
<phase1>	phase1 name	string	
<phase2>	phase2 name	string	

diagnose ipsec list-conn

list ipsec conn

```
diagnose ipsec list-conn
```

diagnose ipsec list-sa

list ipsec sa

```
diagnose ipsec list-sa
```

diagnose ipsec p1-status

get phase1 tunnel status

```
diagnose ipsec p1-status
```

diagnose ipsec reload-ca

reload ipsec ca

```
diagnose ipsec reload-ca
```

diagnose ipsec reload-ipsec

reload ipsec

```
diagnose ipsec reload-ipsec
```

diagnose ipset

ipset

This topic includes the following commands:

- [diagnose ipset list on page 1490](#)

diagnose ipset list

list ipset entries

```
diagnose ipset list
```

diagnose iptables

iptables

This topic includes the following commands:

- [diagnose iptables dry-run on page 1490](#)
- [diagnose iptables list on page 1490](#)
- [diagnose iptables list6 on page 1491](#)
- [diagnose iptables refresh on page 1491](#)
- [diagnose iptables shaper on page 1491](#)
- [diagnose iptables shaper-stats on page 1491](#)

diagnose iptables dry-run

dump iptables rule

```
diagnose iptables dry-run
```

diagnose iptables list

list iptables

```
diagnose iptables list
```

diagnose iptables list6

list ip6tables

```
diagnose iptables list6
```

diagnose iptables refresh

refresh iptables

```
diagnose iptables refresh
```

diagnose iptables shaper

refresh shaper profile

```
diagnose iptables shaper
```

diagnose iptables shaper-stats

print shaper stats

```
diagnose iptables shaper-stats
```

diagnose ipv6

ipv6

This topic includes the following commands:

- [diagnose ipv6 address on page 1492](#)
- [diagnose ipv6 address add on page 1492](#)
- [diagnose ipv6 address delete on page 1492](#)
- [diagnose ipv6 address list on page 1492](#)
- [diagnose ipv6 devconf on page 1493](#)
- [diagnose ipv6 devconf accept-dad on page 1493](#)
- [diagnose ipv6 devconf disable_ipv6 on page 1493](#)
- [diagnose ipv6 neighbor-cache on page 1493](#)
- [diagnose ipv6 neighbor-cache add on page 1493](#)
- [diagnose ipv6 neighbor-cache delete on page 1494](#)

- [diagnose ipv6 neighbor-cache flush on page 1494](#)
- [diagnose ipv6 neighbor-cache list on page 1494](#)
- [diagnose ipv6 route on page 1494](#)
- [diagnose ipv6 route list on page 1495](#)

diagnose ipv6 address

IPv6 addresses.

```
diagnose ipv6 address
```

diagnose ipv6 address add

Add IPv6 address.

```
diagnose ipv6 address add <intf-name> <xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx/xxx>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx/xxx>	IPv6 prefix.	string	

diagnose ipv6 address delete

Delete IPv6 address.

```
diagnose ipv6 address delete <intf-name> <xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx/xxx>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx/xxx>	IPv6 prefix.	string	

diagnose ipv6 address list

List IPv6 addresses.

```
diagnose ipv6 address list
```

diagnose ipv6 devconf

IPv6 device config.

```
diagnose ipv6 devconf
```

diagnose ipv6 devconf accept-dad

IPv6 Duplicate Address Detection.

```
diagnose ipv6 devconf accept-dad <0, 1 or 2>
```

Parameter	Description	Type	Size
<0, 1 or 2>	0: disable DAD; 1: enable DAD; 2: enable DAD, and disable IPv6 operation if MAC-based duplicate link-local address has been found	string	

diagnose ipv6 devconf disable_ipv6

Disable/enable IPv6 operation.

```
diagnose ipv6 devconf disable_ipv6 <0 or 1>
```

Parameter	Description	Type	Size
<0 or 1>	0: enabling IPv6 operation; 1: disabling.	string	

diagnose ipv6 neighbor-cache

IPv6 neighbor-cache table.

```
diagnose ipv6 neighbor-cache
```

diagnose ipv6 neighbor-cache add

Add an IPv6 neighbor cache entry.

```
diagnose ipv6 neighbor-cache add <intf-name> <xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx>  
<XX:XX:XX:XX:XX:XX>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx>	IPv6 address.	string	
<XX:XX:XX:XX:XX:XX>	MAC address.	string	

diagnose ipv6 neighbor-cache delete

Delete an IPv6 neighbor cache entry.

```
diagnose ipv6 neighbor-cache delete <intf-name> <xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx>	IPv6 address.	string	

diagnose ipv6 neighbor-cache flush

Flush IPv6 neighbor cache table.

```
diagnose ipv6 neighbor-cache flush <intf-name>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	

diagnose ipv6 neighbor-cache list

Show IPv6 neighbor cache table.

```
diagnose ipv6 neighbor-cache list
```

diagnose ipv6 route

IPv6 routing table.

```
diagnose ipv6 route
```

diagnose ipv6 route list

List IPv6 routing table.

```
diagnose ipv6 route list
```

diagnose ipv6 address

IPv6 addresses.

This topic includes the following commands:

- [diagnose ipv6 address add on page 1495](#)
- [diagnose ipv6 address delete on page 1495](#)
- [diagnose ipv6 address list on page 1496](#)

diagnose ipv6 address add

Add IPv6 address.

```
diagnose ipv6 address add <intf-name> <xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx/xxx>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx/xxx>	IPv6 prefix.	string	

diagnose ipv6 address delete

Delete IPv6 address.

```
diagnose ipv6 address delete <intf-name> <xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx/xxx>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx/xxx>	IPv6 prefix.	string	

diagnose ipv6 address list

List IPv6 addresses.

```
diagnose ipv6 address list
```

diagnose ipv6 devconf

IPv6 device config.

This topic includes the following commands:

- [diagnose ipv6 devconf accept-dad](#) on page 1496
- [diagnose ipv6 devconf disable_ipv6](#) on page 1496

diagnose ipv6 devconf accept-dad

IPv6 Duplicate Address Detection.

```
diagnose ipv6 devconf accept-dad <0, 1 or 2>
```

Parameter	Description	Type	Size
<0, 1 or 2>	0: disable DAD; 1: enable DAD; 2: enable DAD, and disable IPv6 operation if MAC-based duplicate link-local address has been found	string	

diagnose ipv6 devconf disable_ipv6

Disable/enable IPv6 operation.

```
diagnose ipv6 devconf disable_ipv6 <0 or 1>
```

Parameter	Description	Type	Size
<0 or 1>	0: enabling IPv6 operation; 1: disabling.	string	

diagnose ipv6 neighbor-cache

IPv6 neighbor-cache table.

This topic includes the following commands:

- [diagnose ipv6 neighbor-cache add on page 1497](#)
- [diagnose ipv6 neighbor-cache delete on page 1497](#)
- [diagnose ipv6 neighbor-cache flush on page 1497](#)
- [diagnose ipv6 neighbor-cache list on page 1498](#)

diagnose ipv6 neighbor-cache add

Add an IPv6 neighbor cache entry.

```
diagnose ipv6 neighbor-cache add <intf-name> <xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx>  
<XX:XX:XX:XX:XX:XX>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx>	IPv6 address.	string	
<XX:XX:XX:XX:XX:XX>	MAC address.	string	

diagnose ipv6 neighbor-cache delete

Delete an IPv6 neighbor cache entry.

```
diagnose ipv6 neighbor-cache delete <intf-name> <xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx>	IPv6 address.	string	

diagnose ipv6 neighbor-cache flush

Flush IPv6 neighbor cache table.

```
diagnose ipv6 neighbor-cache flush <intf-name>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	

diagnose ipv6 neighbor-cache list

Show IPv6 neighbor cache table.

```
diagnose ipv6 neighbor-cache list
```

diagnose ipv6 route

IPv6 routing table.

This topic includes the following commands:

- [diagnose ipv6 route list on page 1498](#)

diagnose ipv6 route list

List IPv6 routing table.

```
diagnose ipv6 route list
```

diagnose lldprx

Link Layer Description Protocol (LLDP) Receiver diagnostics.

This topic includes the following commands:

- [diagnose lldprx config on page 1499](#)
- [diagnose lldprx neighbor on page 1499](#)
- [diagnose lldprx neighbor clear on page 1499](#)
- [diagnose lldprx neighbor details on page 1499](#)
- [diagnose lldprx neighbor summary on page 1499](#)
- [diagnose lldprx port on page 1499](#)
- [diagnose lldprx port details on page 1500](#)
- [diagnose lldprx port neighbor on page 1500](#)
- [diagnose lldprx port neighbor clear on page 1500](#)
- [diagnose lldprx port neighbor details on page 1500](#)
- [diagnose lldprx port neighbor summary on page 1500](#)
- [diagnose lldprx port summary on page 1500](#)
- [diagnose lldprx restart on page 1501](#)
- [diagnose lldprx stats on page 1501](#)

- [diagnose lldprx stats config on page 1501](#)
- [diagnose lldprx stats crash on page 1501](#)
- [diagnose lldprx stats manager on page 1501](#)
- [diagnose lldprx stats scan on page 1501](#)

diagnose lldprx config

Display LLDP configuration.

```
diagnose lldprx config
```

diagnose lldprx neighbor

Display LLDP neighbors.

```
diagnose lldprx neighbor
```

diagnose lldprx neighbor clear

Clear the LLDP from all ports.

```
diagnose lldprx neighbor clear
```

diagnose lldprx neighbor details

Display details of each LLDP neighbor.

```
diagnose lldprx neighbor details
```

diagnose lldprx neighbor summary

Display summary of each LLDP neighbor.

```
diagnose lldprx neighbor summary
```

diagnose lldprx port

Display summary information about each port with LLDP reception enabled.

```
diagnose lldprx port
```

diagnose lldprx port details

Display details of the LLDP enabled ports.

```
diagnose lldprx port details
```

diagnose lldprx port neighbor

Display information about each LLDP neighbor for one or more ports.

```
diagnose lldprx port neighbor
```

diagnose lldprx port neighbor clear

Clear the LLDP neighbor information for one or more ports.

```
diagnose lldprx port neighbor clear
```

diagnose lldprx port neighbor details

Display details of each LLDP neighbor for one or more ports.

```
diagnose lldprx port neighbor details
```

diagnose lldprx port neighbor summary

Display summary of each LLDP neighbor for one or more ports.

```
diagnose lldprx port neighbor summary
```

diagnose lldprx port summary

Display summary of the LLDP enabled ports.

```
diagnose lldprx port summary
```

diagnose lldprx restart

Restart the LLDPRX process

```
diagnose lldprx restart
```

diagnose lldprx stats

Display LLDPRX statistics.

```
diagnose lldprx stats
```

diagnose lldprx stats config

Display LLDPRX statistics for the configuration handling process.

```
diagnose lldprx stats config
```

diagnose lldprx stats crash

Display LLDPRX statistics for the crash log generating process.

```
diagnose lldprx stats crash
```

diagnose lldprx stats manager

Display LLDPRX statistics for the manager process.

```
diagnose lldprx stats manager
```

diagnose lldprx stats scan

Display LLDPRX statistics for the scanning process.

```
diagnose lldprx stats scan
```

diagnose log

log

This topic includes the following commands:

- [diagnose log alertmail on page 1502](#)
- [diagnose log alertmail authcode on page 1502](#)
- [diagnose log alertmail test on page 1502](#)
- [diagnose log clear-kernel-stats on page 1503](#)
- [diagnose log kernel-stats on page 1503](#)
- [diagnose log show on page 1503](#)
- [diagnose log test on page 1503](#)
- [diagnose log test-text on page 1503](#)

diagnose log alertmail

alertmail

```
diagnose log alertmail
```

diagnose log alertmail authcode

Send a test authentication code.

```
diagnose log alertmail authcode <recipient>
```

Parameter	Description	Type	Size
<recipient>	recipient's email address	string	

diagnose log alertmail test

Send a test alert mail.

```
diagnose log alertmail test <level> <number>
```

Parameter	Description	Type	Size
<level>	Log level number.	string	
<number>	Number of messages.	string	

diagnose log clear-kernel-stats

Clear logging statistics.

```
diagnose log clear-kernel-stats
```

diagnose log kernel-stats

Query logging statistics.

```
diagnose log kernel-stats
```

diagnose log show

Display the contents of a log file.

```
diagnose log show
```

diagnose log test

Test miglog.

```
diagnose log test
```

diagnose log test-text

Test miglog.

```
diagnose log test-text
```

diagnose netlink

netlink

This topic includes the following commands:

- [diagnose netlink backlog on page 1504](#)
- [diagnose netlink backlog get on page 1504](#)
- [diagnose netlink backlog set on page 1504](#)

- [diagnose netlink brctl on page 1505](#)
- [diagnose netlink brctl forward-domain-status on page 1505](#)
- [diagnose netlink brctl interface-stats on page 1505](#)
- [diagnose netlink brctl list on page 1505](#)
- [diagnose netlink brctl name on page 1505](#)
- [diagnose netlink brctl vlan-filt-conf on page 1506](#)
- [diagnose netlink device on page 1506](#)
- [diagnose netlink device list on page 1506](#)
- [diagnose netlink interface on page 1506](#)
- [diagnose netlink interface clear on page 1506](#)
- [diagnose netlink interface list on page 1506](#)
- [diagnose netlink interface packet-rate on page 1507](#)
- [diagnose netlink interface speed-test on page 1507](#)
- [diagnose netlink interface speed-test-result on page 1507](#)
- [diagnose netlink interface speed-test-result-clear on page 1507](#)
- [diagnose netlink intf-class on page 1507](#)
- [diagnose netlink intf-class list on page 1508](#)
- [diagnose netlink intf-qdisc on page 1508](#)
- [diagnose netlink intf-qdisc list on page 1508](#)
- [diagnose netlink qlen on page 1508](#)
- [diagnose netlink qlen get on page 1508](#)
- [diagnose netlink qlen set on page 1509](#)

diagnose netlink backlog

UDP sockets.

```
diagnose netlink backlog
```

diagnose netlink backlog get

Show backlog.

```
diagnose netlink backlog get
```

diagnose netlink backlog set

Backlog.

```
diagnose netlink backlog set <backlog>
```


Parameter	Description	Type	Size
<backlog>	Backlog value.	string	

diagnose netlink brctl

bridge

```
diagnose netlink brctl
```

diagnose netlink brctl forward-domain-status

forward-domain-status

```
diagnose netlink brctl forward-domain-status
```

diagnose netlink brctl interface-stats

interface-stats

```
diagnose netlink brctl interface-stats
```

diagnose netlink brctl list

list

```
diagnose netlink brctl list
```

diagnose netlink brctl name

name

```
diagnose netlink brctl name <type> <name>
```

Parameter	Description	Type	Size
<type>	"host" or "port"	string	
<name>	name	string	

diagnose netlink brctl vlan-filt-conf

vlan-filt-conf

```
diagnose netlink brctl vlan-filt-conf
```

diagnose netlink device

devices

```
diagnose netlink device
```

diagnose netlink device list

List devices.

```
diagnose netlink device list
```

diagnose netlink interface

Network interfaces.

```
diagnose netlink interface
```

diagnose netlink interface clear

Clear interface counters.

```
diagnose netlink interface clear
```

diagnose netlink interface list

List interfaces.

```
diagnose netlink interface list
```

diagnose netlink interface packet-rate

Show send/receive rate of interfaces.

```
diagnose netlink interface packet-rate
```

diagnose netlink interface speed-test

Execute speed-test on the interface.

```
diagnose netlink interface speed-test <intf-name> <server> <mode> <dry-run>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<server>	server name.	string	
<mode>	Optional. Auto(default), TCP or UDP.	string	
<dry-run>	Optional. <0> execute speed-test; <1> dry run to verify routing etc.	string	

diagnose netlink interface speed-test-result

Get speed-test result for a specific test ID.

```
diagnose netlink interface speed-test-result <test-id>
```

Parameter	Description	Type	Size
<test-id>	Test ID from executing speed-test.	string	

diagnose netlink interface speed-test-result-clear

Remove speed test results from disk.

```
diagnose netlink interface speed-test-result-clear
```

diagnose netlink intf-class

Network interface class.

```
diagnose netlink intf-class
```

diagnose netlink intf-class list

list

```
diagnose netlink intf-class list <string>
```

Parameter	Description	Type	Size
<string>	Interface name.	string	

diagnose netlink intf-qdisc

Network interface qdisc.

```
diagnose netlink intf-qdisc
```

diagnose netlink intf-qdisc list

list

```
diagnose netlink intf-qdisc list <string>
```

Parameter	Description	Type	Size
<string>	Interface name.	string	

diagnose netlink qlen

Interface queue length.

```
diagnose netlink qlen
```

diagnose netlink qlen get

Get queue length.

```
diagnose netlink qlen get <intf-name>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	

diagnose netlink qlen set

Queue length.

```
diagnose netlink qlen set <intf-name> <len_integer>
```

Parameter	Description	Type	Size
<intf-name>	Interface Name.	string	
<len_integer>	Length value.	string	

diagnose nodejs

Node.JS web server diagnostics.

This topic includes the following commands:

- [diagnose nodejs health-check on page 1509](#)
- [diagnose nodejs health-check ping on page 1509](#)
- [diagnose nodejs logs on page 1510](#)
- [diagnose nodejs logs delete on page 1510](#)
- [diagnose nodejs logs list on page 1510](#)
- [diagnose nodejs logs show on page 1510](#)
- [diagnose nodejs logs show-all on page 1510](#)
- [diagnose nodejs process on page 1511](#)
- [diagnose nodejs process restart on page 1511](#)

diagnose nodejs health-check

Node.JS health check commands.

```
diagnose nodejs health-check
```

diagnose nodejs health-check ping

Send HTTP request to Node.JS, and check if Node.JS can handle HTTP request.

```
diagnose nodejs health-check ping
```

diagnose nodejs logs

Show/List Node.JS debug log.

```
diagnose nodejs logs
```

diagnose nodejs logs delete

Delete one of the Node.JS debug log files. Use log sequence number as an argument.

```
diagnose nodejs logs delete <log sequence number>
```

Parameter	Description	Type	Size
<log sequence number>	Log sequence number.	string	

diagnose nodejs logs list

List all of the Node.JS debug log files.

```
diagnose nodejs logs list
```

diagnose nodejs logs show

Show one of the Node.JS debug logs files. Use log sequence number as an argument.

```
diagnose nodejs logs show <log sequence number>
```

Parameter	Description	Type	Size
<log sequence number>	Log sequence number.	string	

diagnose nodejs logs show-all

Show all of the Node.JS debug log files.

```
diagnose nodejs logs show-all
```

diagnose nodejs process

Actions to Node.JS process.

```
diagnose nodejs process
```

diagnose nodejs process restart

Send SIGKILL and restart Node.JS.

```
diagnose nodejs process restart
```

diagnose oci

Oracle Cloud Infrastructure platform diagnose commands.

This topic includes the following commands:

- [diagnose oci pubkey on page 1511](#)

diagnose oci pubkey

Display OCI public key information.

```
diagnose oci pubkey <name>
```

Parameter	Description	Type	Size
<name>	OCI SDN connector name	string	

diagnose preload

HTTP preload daemon

This topic includes the following commands:

- [diagnose preload clear on page 1512](#)
- [diagnose preload debug on page 1512](#)
- [diagnose preload log-show on page 1512](#)
- [diagnose preload restart on page 1512](#)

- [diagnose preload stats on page 1512](#)

diagnose preload clear

Restart daemon, reset statistics & remove scheduled tasks

```
diagnose preload clear
```

diagnose preload debug

Set debug level for deamon

```
diagnose preload debug <debug level>
```

Parameter	Description	Type	Size
<debug level>	Hexadecimal number	string	

diagnose preload log-show

Show log of daemon

```
diagnose preload log-show <log generation> <time format>
```

Parameter	Description	Type	Size
<log generation>	Log generation: default 0	string	
<time format>	Time format: 0 for human readable and 1 for raw, default 0	string	

diagnose preload restart

Restart the daemon and reset statistics

```
diagnose preload restart
```

diagnose preload stats

Show statistics.


```
diagnose preload stats
```

diagnose report

report

```
diagnose report
```

diagnose report-runner

Report Runner service.

This topic includes the following commands:

- [diagnose report-runner clean on page 1513](#)
- [diagnose report-runner trigger on page 1513](#)
- [diagnose report-runner trigger security-rating-reports on page 1513](#)

diagnose report-runner clean

Delete all Report Runner results.

```
diagnose report-runner clean
```

diagnose report-runner trigger

Execute a report.

```
diagnose report-runner trigger
```

diagnose report-runner trigger security-rating-reports

Execute the Security Rating reports (Security Posture, Fabric Coverage, Optimization).

```
diagnose report-runner trigger security-rating-reports
```

diagnose settings

settings

This topic includes the following commands:

- [diagnose settings info on page 1514](#)
- [diagnose settings reset on page 1514](#)

diagnose settings info

Show all diagnose settings.

```
diagnose settings info
```

diagnose settings reset

Reset all diagnose settings.

```
diagnose settings reset
```

diagnose sniffer

Sniffer command.

This topic includes the following commands:

- [diagnose sniffer migsock on page 1515](#)
- [diagnose sniffer migsock debug-trace on page 1515](#)
- [diagnose sniffer migsock debug-trace disable on page 1515](#)
- [diagnose sniffer migsock debug-trace enable on page 1515](#)
- [diagnose sniffer migsock filter on page 1515](#)
- [diagnose sniffer migsock ssl-trace on page 1515](#)
- [diagnose sniffer migsock ssl-trace disable on page 1516](#)
- [diagnose sniffer migsock ssl-trace enable on page 1516](#)
- [diagnose sniffer migsock start on page 1516](#)
- [diagnose sniffer migsock timestamp on page 1516](#)
- [diagnose sniffer migsock timestamp disable on page 1516](#)
- [diagnose sniffer migsock timestamp enable on page 1516](#)
- [diagnose sniffer packet on page 1517](#)

diagnose sniffer migsock

Sniff migsock packets.

```
diagnose sniffer migsock
```

diagnose sniffer migsock debug-trace

Enable/disable debug trace.

```
diagnose sniffer migsock debug-trace
```

diagnose sniffer migsock debug-trace disable

Disable debug trace.

```
diagnose sniffer migsock debug-trace disable
```

diagnose sniffer migsock debug-trace enable

Enable debug trace.

```
diagnose sniffer migsock debug-trace enable
```

diagnose sniffer migsock filter

Filter flow.

```
diagnose sniffer migsock filter <filter>
```

Parameter	Description	Type	Size
<filter>	Filter string.	string	

diagnose sniffer migsock ssl-trace

Enable/disable SSL trace.

```
diagnose sniffer migsock ssl-trace
```

diagnose sniffer migsock ssl-trace disable

Disable SSL trace.

```
diagnose sniffer migsock ssl-trace disable
```

diagnose sniffer migsock ssl-trace enable

Enable SSL trace.

```
diagnose sniffer migsock ssl-trace enable
```

diagnose sniffer migsock start

Start sniffer.

```
diagnose sniffer migsock start
```

diagnose sniffer migsock timestamp

Enable/disable timestamp trace.

```
diagnose sniffer migsock timestamp
```

diagnose sniffer migsock timestamp disable

Disable timestamp trace.

```
diagnose sniffer migsock timestamp disable
```

diagnose sniffer migsock timestamp enable

Enable timestamp trace.

```
diagnose sniffer migsock timestamp enable
```

diagnose sniffer packet

Sniff packets.

```
diagnose sniffer packet <interface> <filter> <verbose> <count> <tsformat> <frame size> <hostnames>
```

Parameter	Description	Type	Size
<interface>	Network interfaces to sniff (or "any").	string	
<filter>	Flexible logical filters for sniffer (or "none"). For example: To print UDP 1812 traffic between forti1 and either forti2 or forti3 'udp and port 1812 and host forti1 and (forti2 or forti3)'	string	
<verbose>	1: print header of packets 2: print header and data from ip of packets 3: print header and data from ethernet of packets (if available) 4: print header of packets with interface name 5: print header and data from ip of packets with interface name 6: print header and data from ethernet of packets (if available) with intf name	string	
<count>	Sniffer count.	string	
<tsformat>	Format of timestamp. a: absolute UTC time, yyyy-mm-dd hh:mm:ss.ms l: absolute LOCAL time, yyyy-mm-dd hh:mm:ss.ms otherwise: relative to the start of sniffing, ss.ms	string	
<frame size>	Set the frame size that is printed before truncation. Defaults to the interface MTU.	string	
<hostnames>	Hostnames to filter sniffed packets with.	string	

diagnose snmp

snmp

This topic includes the following commands:

- [diagnose snmp ip on page 1518](#)
- [diagnose snmp ip frags on page 1518](#)
- [diagnose snmp ip icmp on page 1518](#)
- [diagnose snmp ip ip on page 1518](#)
- [diagnose snmp ip tcp on page 1519](#)
- [diagnose snmp ip udp on page 1519](#)
- [diagnose snmp ip6 on page 1519](#)

- [diagnose snmp ip6 frags on page 1519](#)
- [diagnose snmp ip6 icmp6 on page 1520](#)
- [diagnose snmp ip6 ip6 on page 1520](#)
- [diagnose snmp ip6 udp6 on page 1520](#)
- [diagnose snmp net on page 1520](#)
- [diagnose snmp net stat on page 1520](#)
- [diagnose snmp trap on page 1521](#)
- [diagnose snmp trap send on page 1521](#)

diagnose snmp ip

Some IP stats.

```
diagnose snmp ip
```

diagnose snmp ip frags

Fragmentation and reassembly info.

```
diagnose snmp ip frags <rate>
```

Parameter	Description	Type	Size
<rate>	Fragmentation and reassembly info per second	string	

diagnose snmp ip icmp

ICMP related statistics info.

```
diagnose snmp ip icmp <rate>
```

Parameter	Description	Type	Size
<rate>	ICMP related statistics per second	string	

diagnose snmp ip ip

IP related statistics info.

```
diagnose snmp ip ip <rate>
```

Parameter	Description	Type	Size
<rate>	IP related statistics per second	string	

diagnose snmp ip tcp

TCP related statistics info.

```
diagnose snmp ip tcp <rate>
```

Parameter	Description	Type	Size
<rate>	TCP related statistics per second	string	

diagnose snmp ip udp

UDP related statistics info.

```
diagnose snmp ip udp <rate>
```

Parameter	Description	Type	Size
<rate>	UDP related statistics per second	string	

diagnose snmp ip6

Some IPv6 stats.

```
diagnose snmp ip6
```

diagnose snmp ip6 frags

Fragmentation and reassembly info.

```
diagnose snmp ip6 frags <rate>
```

Parameter	Description	Type	Size
<rate>	Fragmentation and reassembly info per second	string	

diagnose snmp ip6 icmp6

ICMP related statistics info.

```
diagnose snmp ip6 icmp6 <rate>
```

Parameter	Description	Type	Size
<rate>	ICMP related statistics per second	string	

diagnose snmp ip6 ip6

IP related statistics info.

```
diagnose snmp ip6 ip6 <rate>
```

Parameter	Description	Type	Size
<rate>	IPv6 related statistics per second	string	

diagnose snmp ip6 udp6

UDP related statistics info.

```
diagnose snmp ip6 udp6 <rate>
```

Parameter	Description	Type	Size
<rate>	UDP related statistics per second	string	

diagnose snmp net

Some network statistics.

```
diagnose snmp net
```

diagnose snmp net stat

Network statistics.

```
diagnose snmp net stat
```


diagnose snmp trap

SNMP trap diagnostics.

```
diagnose snmp trap
```

diagnose snmp trap send

Generate a trap event.

```
diagnose snmp trap send
```

diagnose sys

system

This topic includes the following commands:

- [diagnose sys botnet-domain on page 1530](#)
- [diagnose sys botnet-domain hit on page 1530](#)
- [diagnose sys botnet-domain list on page 1530](#)
- [diagnose sys botnet-ip on page 1530](#)
- [diagnose sys botnet-ip find on page 1531](#)
- [diagnose sys botnet-ip flush on page 1531](#)
- [diagnose sys botnet-ip hit on page 1531](#)
- [diagnose sys botnet-ip list on page 1531](#)
- [diagnose sys cmdb on page 1531](#)
- [diagnose sys cmdb check-lock on page 1532](#)
- [diagnose sys cmdb dump on page 1532](#)
- [diagnose sys cmdb dump vdom on page 1532](#)
- [diagnose sys cmdb flag on page 1532](#)
- [diagnose sys cmdb flag info on page 1532](#)
- [diagnose sys cmdb flag reset on page 1532](#)
- [diagnose sys cmdb flag reset script-running on page 1533](#)
- [diagnose sys cmdb info on page 1533](#)
- [diagnose sys cmdb refcnt on page 1533](#)
- [diagnose sys cmdb refcnt reset on page 1533](#)
- [diagnose sys cmdb refcnt show on page 1533](#)
- [diagnose sys config-transaction on page 1534](#)
- [diagnose sys config-transaction show on page 1534](#)
- [diagnose sys config-transaction show entity-by-txn on page 1534](#)

- [diagnose sys config-transaction show mctx on page 1534](#)
- [diagnose sys config-transaction show txn-cli-commands on page 1534](#)
- [diagnose sys config-transaction show txn-entity on page 1535](#)
- [diagnose sys config-transaction show txn-info on page 1535](#)
- [diagnose sys config-transaction show txn-lock on page 1535](#)
- [diagnose sys config-transaction show txn-meta on page 1535](#)
- [diagnose sys config-transaction status on page 1535](#)
- [diagnose sys conntrack on page 1535](#)
- [diagnose sys conntrack clear on page 1536](#)
- [diagnose sys conntrack count on page 1536](#)
- [diagnose sys conntrack list-dying4 on page 1536](#)
- [diagnose sys conntrack list-dying6 on page 1536](#)
- [diagnose sys conntrack list-unconfirmed4 on page 1536](#)
- [diagnose sys conntrack list-unconfirmed6 on page 1536](#)
- [diagnose sys conntrack list4 on page 1537](#)
- [diagnose sys conntrack list6 on page 1537](#)
- [diagnose sys conntrack stats on page 1537](#)
- [diagnose sys csf on page 1537](#)
- [diagnose sys csf authorization on page 1537](#)
- [diagnose sys csf authorization accept on page 1537](#)
- [diagnose sys csf authorization deny on page 1538](#)
- [diagnose sys csf authorization pending-list on page 1538](#)
- [diagnose sys csf downstream on page 1538](#)
- [diagnose sys csf downstream-devices on page 1538](#)
- [diagnose sys csf dynamic-sync-read on page 1539](#)
- [diagnose sys csf dynamic-sync-request on page 1539](#)
- [diagnose sys csf dynamic-sync-update on page 1539](#)
- [diagnose sys csf fabric-device on page 1539](#)
- [diagnose sys csf fabric-device list on page 1539](#)
- [diagnose sys csf file on page 1540](#)
- [diagnose sys csf file cat on page 1540](#)
- [diagnose sys csf file top-mem on page 1540](#)
- [diagnose sys csf forticloud-id-list on page 1540](#)
- [diagnose sys csf get-bulk-global-view on page 1540](#)
- [diagnose sys csf global on page 1541](#)
- [diagnose sys csf initialize-cmd on page 1541](#)
- [diagnose sys csf license on page 1541](#)
- [diagnose sys csf merge-cmd on page 1541](#)
- [diagnose sys csf neighbor on page 1542](#)
- [diagnose sys csf neighbor flush on page 1542](#)
- [diagnose sys csf neighbor list on page 1542](#)
- [diagnose sys csf query on page 1542](#)
- [diagnose sys csf tunnel-test-listener on page 1543](#)

- [diagnose sys csf tunnel-test-sender on page 1543](#)
- [diagnose sys csf upstream on page 1543](#)
- [diagnose sys csf versions on page 1543](#)
- [diagnose sys dayst-info on page 1543](#)
- [diagnose sys device on page 1544](#)
- [diagnose sys device add on page 1544](#)
- [diagnose sys device delete on page 1544](#)
- [diagnose sys device list on page 1544](#)
- [diagnose sys external-resource on page 1544](#)
- [diagnose sys external-resource list on page 1545](#)
- [diagnose sys external-resource push-add on page 1545](#)
- [diagnose sys external-resource push-api-json-commands on page 1545](#)
- [diagnose sys external-resource push-remove on page 1545](#)
- [diagnose sys external-resource push-snapshot on page 1545](#)
- [diagnose sys external-resource stats on page 1546](#)
- [diagnose sys filesystem on page 1546](#)
- [diagnose sys filesystem hash on page 1546](#)
- [diagnose sys filesystem last-modified-files on page 1546](#)
- [diagnose sys filesystem tree on page 1546](#)
- [diagnose sys fips on page 1547](#)
- [diagnose sys fips error-mode on page 1547](#)
- [diagnose sys ha on page 1547](#)
- [diagnose sys ha check-vc on page 1547](#)
- [diagnose sys ha checksum on page 1547](#)
- [diagnose sys ha checksum cached on page 1547](#)
- [diagnose sys ha checksum cluster on page 1548](#)
- [diagnose sys ha checksum log on page 1548](#)
- [diagnose sys ha checksum log clear on page 1548](#)
- [diagnose sys ha checksum log disable on page 1548](#)
- [diagnose sys ha checksum log enable on page 1548](#)
- [diagnose sys ha checksum recalculate on page 1549](#)
- [diagnose sys ha checksum show on page 1549](#)
- [diagnose sys ha checksum show-nonsync on page 1549](#)
- [diagnose sys ha checksum test on page 1549](#)
- [diagnose sys ha dump-by on page 1550](#)
- [diagnose sys ha dump-by debug-zone on page 1550](#)
- [diagnose sys ha dump-by device on page 1550](#)
- [diagnose sys ha dump-by group on page 1550](#)
- [diagnose sys ha dump-by kernel on page 1550](#)
- [diagnose sys ha dump-by rcache on page 1550](#)
- [diagnose sys ha dump-by vcluster on page 1551](#)
- [diagnose sys ha dump-by vdom on page 1551](#)
- [diagnose sys ha extfile-sig on page 1551](#)

- [diagnose sys ha fgsp-zone on page 1551](#)
- [diagnose sys ha fib on page 1551](#)
- [diagnose sys ha hactx-stats on page 1551](#)
- [diagnose sys ha hactx-stats clear on page 1552](#)
- [diagnose sys ha hadiff on page 1552](#)
- [diagnose sys ha hadiff log on page 1552](#)
- [diagnose sys ha hadiff log clear on page 1552](#)
- [diagnose sys ha hadiff log disable on page 1552](#)
- [diagnose sys ha hadiff log enable on page 1552](#)
- [diagnose sys ha hadiff max-sync-turns on page 1553](#)
- [diagnose sys ha hadiff max-unsync-wait on page 1553](#)
- [diagnose sys ha hadiff status on page 1553](#)
- [diagnose sys ha hasync-conn-max-buf on page 1553](#)
- [diagnose sys ha hasync-stats on page 1553](#)
- [diagnose sys ha hasync-stats all on page 1554](#)
- [diagnose sys ha hasync-stats by-object on page 1554](#)
- [diagnose sys ha hasync-stats most-recent on page 1554](#)
- [diagnose sys ha hasync-stats most-time on page 1554](#)
- [diagnose sys ha heartbeat on page 1554](#)
- [diagnose sys ha history on page 1555](#)
- [diagnose sys ha history clear on page 1555](#)
- [diagnose sys ha history read on page 1555](#)
- [diagnose sys ha mac on page 1555](#)
- [diagnose sys ha pingsvr-secondary-force-reset on page 1555](#)
- [diagnose sys ha recalculate-extfile-signature on page 1555](#)
- [diagnose sys ha reset-health-status on page 1556](#)
- [diagnose sys ha reset-uptime on page 1556](#)
- [diagnose sys ha session-sync-dev on page 1556](#)
- [diagnose sys ha session-sync-dev clear on page 1556](#)
- [diagnose sys ha session-sync-dev set on page 1556](#)
- [diagnose sys ha standalone-peers on page 1556](#)
- [diagnose sys ha standalone-peers reset-stats on page 1557](#)
- [diagnose sys ha stats on page 1557](#)
- [diagnose sys ha status on page 1557](#)
- [diagnose sys ha sync-stats on page 1557](#)
- [diagnose sys ha sync-stats-reset on page 1557](#)
- [diagnose sys ha vlan-hb-monitor on page 1557](#)
- [diagnose sys icap-remote-server on page 1558](#)
- [diagnose sys icap-remote-server status on page 1558](#)
- [diagnose sys iotop on page 1558](#)
- [diagnose sys link-monitor on page 1558](#)
- [diagnose sys link-monitor filter on page 1558](#)
- [diagnose sys link-monitor filter clear on page 1558](#)

- [diagnose sys link-monitor filter name on page 1559](#)
- [diagnose sys link-monitor interface on page 1559](#)
- [diagnose sys link-monitor launch on page 1559](#)
- [diagnose sys link-monitor status on page 1559](#)
- [diagnose sys mpstat on page 1560](#)
- [diagnose sys nmi-watchdog on page 1560](#)
- [diagnose sys nmi-watchdog disable on page 1560](#)
- [diagnose sys nmi-watchdog enable on page 1560](#)
- [diagnose sys nmi-watchdog reboot on page 1560](#)
- [diagnose sys nmi-watchdog reboot disable on page 1560](#)
- [diagnose sys nmi-watchdog reboot enable on page 1561](#)
- [diagnose sys nmi-watchdog threshold on page 1561](#)
- [diagnose sys ntp on page 1561](#)
- [diagnose sys ntp status on page 1561](#)
- [diagnose sys pair on page 1561](#)
- [diagnose sys process on page 1561](#)
- [diagnose sys process dump on page 1562](#)
- [diagnose sys process nameof on page 1562](#)
- [diagnose sys process pidof on page 1562](#)
- [diagnose sys process pstack on page 1562](#)
- [diagnose sys process sock-mem on page 1562](#)
- [diagnose sys process socket on page 1563](#)
- [diagnose sys process trace on page 1563](#)
- [diagnose sys profile on page 1563](#)
- [diagnose sys profile cpumask on page 1563](#)
- [diagnose sys profile show on page 1563](#)
- [diagnose sys profile show detail on page 1564](#)
- [diagnose sys profile show order on page 1564](#)
- [diagnose sys profile start on page 1564](#)
- [diagnose sys profile step on page 1564](#)
- [diagnose sys profile stop on page 1564](#)
- [diagnose sys profile sysmap on page 1564](#)
- [diagnose sys ptp on page 1565](#)
- [diagnose sys ptp status on page 1565](#)
- [diagnose sys scanunit on page 1565](#)
- [diagnose sys scanunit av-filetype-reuse on page 1565](#)
- [diagnose sys scanunit av-filetype-reuse disable on page 1565](#)
- [diagnose sys scanunit av-filetype-reuse enable on page 1565](#)
- [diagnose sys scanunit bypass on page 1566](#)
- [diagnose sys scanunit bypass clear on page 1566](#)
- [diagnose sys scanunit bypass disable on page 1566](#)
- [diagnose sys scanunit bypass disable category on page 1566](#)
- [diagnose sys scanunit bypass disable category all on page 1566](#)

- [diagnose sys scanunit bypass disable category av-engine on page 1566](#)
- [diagnose sys scanunit bypass disable category scanunit on page 1567](#)
- [diagnose sys scanunit bypass disable protocol on page 1567](#)
- [diagnose sys scanunit bypass disable protocol all on page 1567](#)
- [diagnose sys scanunit bypass disable protocol cifs on page 1567](#)
- [diagnose sys scanunit bypass disable protocol ftp on page 1567](#)
- [diagnose sys scanunit bypass disable protocol http on page 1567](#)
- [diagnose sys scanunit bypass disable protocol imap on page 1568](#)
- [diagnose sys scanunit bypass disable protocol nntp on page 1568](#)
- [diagnose sys scanunit bypass disable protocol pop3 on page 1568](#)
- [diagnose sys scanunit bypass disable protocol smtp on page 1568](#)
- [diagnose sys scanunit bypass enable on page 1568](#)
- [diagnose sys scanunit bypass enable category on page 1568](#)
- [diagnose sys scanunit bypass enable category all on page 1569](#)
- [diagnose sys scanunit bypass enable category av-engine on page 1569](#)
- [diagnose sys scanunit bypass enable category scanunit on page 1569](#)
- [diagnose sys scanunit bypass enable protocol on page 1569](#)
- [diagnose sys scanunit bypass enable protocol all on page 1569](#)
- [diagnose sys scanunit bypass enable protocol cifs on page 1569](#)
- [diagnose sys scanunit bypass enable protocol ftp on page 1570](#)
- [diagnose sys scanunit bypass enable protocol http on page 1570](#)
- [diagnose sys scanunit bypass enable protocol imap on page 1570](#)
- [diagnose sys scanunit bypass enable protocol nntp on page 1570](#)
- [diagnose sys scanunit bypass enable protocol pop3 on page 1570](#)
- [diagnose sys scanunit bypass enable protocol smtp on page 1570](#)
- [diagnose sys scanunit bypass show on page 1571](#)
- [diagnose sys scanunit crash-dump on page 1571](#)
- [diagnose sys scanunit crash-dump clear on page 1571](#)
- [diagnose sys scanunit crash-dump disable on page 1571](#)
- [diagnose sys scanunit crash-dump enable on page 1571](#)
- [diagnose sys scanunit crash-dump read on page 1571](#)
- [diagnose sys scanunit debug on page 1572](#)
- [diagnose sys scanunit debug all on page 1572](#)
- [diagnose sys scanunit debug analytics on page 1572](#)
- [diagnose sys scanunit debug antisipam on page 1572](#)
- [diagnose sys scanunit debug daemon on page 1572](#)
- [diagnose sys scanunit debug dlp on page 1573](#)
- [diagnose sys scanunit debug file-filter on page 1573](#)
- [diagnose sys scanunit debug ia on page 1573](#)
- [diagnose sys scanunit debug icb on page 1573](#)
- [diagnose sys scanunit debug job on page 1574](#)
- [diagnose sys scanunit debug level on page 1574](#)
- [diagnose sys scanunit debug level error on page 1574](#)

- [diagnose sys scanunit debug level info on page 1574](#)
- [diagnose sys scanunit debug level verbose on page 1574](#)
- [diagnose sys scanunit debug level warning on page 1574](#)
- [diagnose sys scanunit debug outbreak-prevention on page 1575](#)
- [diagnose sys scanunit debug quarantine on page 1575](#)
- [diagnose sys scanunit debug reset on page 1575](#)
- [diagnose sys scanunit debug sane on page 1575](#)
- [diagnose sys scanunit debug show on page 1575](#)
- [diagnose sys scanunit file-hash on page 1576](#)
- [diagnose sys scanunit file-hash list on page 1576](#)
- [diagnose sys scanunit file-hash list all on page 1576](#)
- [diagnose sys scanunit file-hash list md5 on page 1576](#)
- [diagnose sys scanunit file-hash list sha1 on page 1576](#)
- [diagnose sys scanunit file-hash list sha256 on page 1576](#)
- [diagnose sys scanunit file-hash query on page 1577](#)
- [diagnose sys scanunit file-hash query md5 on page 1577](#)
- [diagnose sys scanunit file-hash query sha1 on page 1577](#)
- [diagnose sys scanunit file-hash query sha256 on page 1577](#)
- [diagnose sys scanunit file-hash status on page 1577](#)
- [diagnose sys scanunit filter on page 1578](#)
- [diagnose sys scanunit filter clear on page 1578](#)
- [diagnose sys scanunit filter list on page 1578](#)
- [diagnose sys scanunit filter negate on page 1578](#)
- [diagnose sys scanunit filter negate vd on page 1578](#)
- [diagnose sys scanunit filter vd on page 1578](#)
- [diagnose sys scanunit log on page 1579](#)
- [diagnose sys scanunit log filter on page 1579](#)
- [diagnose sys scanunit log filter clear on page 1579](#)
- [diagnose sys scanunit log filter list on page 1579](#)
- [diagnose sys scanunit log filter negate on page 1579](#)
- [diagnose sys scanunit log filter negate vd on page 1579](#)
- [diagnose sys scanunit log filter vd on page 1580](#)
- [diagnose sys scanunit reload-avdb on page 1580](#)
- [diagnose sys scanunit reload-aveng on page 1580](#)
- [diagnose sys scanunit restart on page 1580](#)
- [diagnose sys scanunit stats on page 1580](#)
- [diagnose sys scanunit stats all on page 1580](#)
- [diagnose sys scanunit stats clear on page 1581](#)
- [diagnose sys scanunit stats list on page 1581](#)
- [diagnose sys scanunit vdom-stats on page 1581](#)
- [diagnose sys scanunit vdom-stats all on page 1581](#)
- [diagnose sys scanunit vdom-stats clear on page 1581](#)
- [diagnose sys scanunit vdom-stats clear-all on page 1581](#)

- [diagnose sys scanunit vdom-stats list on page 1582](#)
- [diagnose sys sdn on page 1582](#)
- [diagnose sys sdn cache on page 1582](#)
- [diagnose sys sdn status on page 1582](#)
- [diagnose sys server-probe on page 1583](#)
- [diagnose sys server-probe response on page 1583](#)
- [diagnose sys session on page 1583](#)
- [diagnose sys session clear on page 1583](#)
- [diagnose sys session count on page 1583](#)
- [diagnose sys session exp-stat on page 1583](#)
- [diagnose sys session expectation on page 1584](#)
- [diagnose sys session filter on page 1584](#)
- [diagnose sys session filter clear on page 1584](#)
- [diagnose sys session filter clear dintf on page 1584](#)
- [diagnose sys session filter clear dport on page 1584](#)
- [diagnose sys session filter clear dst on page 1584](#)
- [diagnose sys session filter clear nsrc on page 1585](#)
- [diagnose sys session filter clear policy on page 1585](#)
- [diagnose sys session filter clear proto on page 1585](#)
- [diagnose sys session filter clear proto-state on page 1585](#)
- [diagnose sys session filter clear sintf on page 1585](#)
- [diagnose sys session filter clear sport on page 1585](#)
- [diagnose sys session filter clear src on page 1586](#)
- [diagnose sys session filter dintf on page 1586](#)
- [diagnose sys session filter dport on page 1586](#)
- [diagnose sys session filter dst on page 1586](#)
- [diagnose sys session filter nsrc on page 1586](#)
- [diagnose sys session filter policy on page 1587](#)
- [diagnose sys session filter proto on page 1587](#)
- [diagnose sys session filter sintf on page 1587](#)
- [diagnose sys session filter sport on page 1587](#)
- [diagnose sys session filter src on page 1588](#)
- [diagnose sys session full-stat on page 1588](#)
- [diagnose sys session list on page 1588](#)
- [diagnose sys session list-verbose on page 1588](#)
- [diagnose sys session stat on page 1588](#)
- [diagnose sys session ttl on page 1589](#)
- [diagnose sys session6 on page 1589](#)
- [diagnose sys session6 clear on page 1589](#)
- [diagnose sys session6 expectation on page 1589](#)
- [diagnose sys session6 filter on page 1589](#)
- [diagnose sys session6 filter clear on page 1589](#)
- [diagnose sys session6 filter clear dintf on page 1590](#)

- [diagnose sys session6 filter clear dport on page 1590](#)
- [diagnose sys session6 filter clear dst on page 1590](#)
- [diagnose sys session6 filter clear nsrc on page 1590](#)
- [diagnose sys session6 filter clear policy on page 1590](#)
- [diagnose sys session6 filter clear proto on page 1590](#)
- [diagnose sys session6 filter clear proto-state on page 1591](#)
- [diagnose sys session6 filter clear sintf on page 1591](#)
- [diagnose sys session6 filter clear sport on page 1591](#)
- [diagnose sys session6 filter clear src on page 1591](#)
- [diagnose sys session6 filter clear vd on page 1591](#)
- [diagnose sys session6 filter dintf on page 1591](#)
- [diagnose sys session6 filter dport on page 1592](#)
- [diagnose sys session6 filter dst on page 1592](#)
- [diagnose sys session6 filter nsrc on page 1592](#)
- [diagnose sys session6 filter policy on page 1592](#)
- [diagnose sys session6 filter proto on page 1593](#)
- [diagnose sys session6 filter sintf on page 1593](#)
- [diagnose sys session6 filter sport on page 1593](#)
- [diagnose sys session6 filter src on page 1593](#)
- [diagnose sys session6 list on page 1594](#)
- [diagnose sys session6 list-verbose on page 1594](#)
- [diagnose sys tcp-option on page 1594](#)
- [diagnose sys tcp-option disable on page 1594](#)
- [diagnose sys tcp-option enable on page 1594](#)
- [diagnose sys tcpsock on page 1594](#)
- [diagnose sys tcpsock6 on page 1595](#)
- [diagnose sys top on page 1595](#)
- [diagnose sys top-all on page 1595](#)
- [diagnose sys top-fd on page 1595](#)
- [diagnose sys top-fd detail on page 1596](#)
- [diagnose sys top-mem on page 1596](#)
- [diagnose sys top-mem detail on page 1596](#)
- [diagnose sys top-sockmem on page 1596](#)
- [diagnose sys traffic on page 1597](#)
- [diagnose sys traffic app-stats on page 1597](#)
- [diagnose sys traffic app-stats list on page 1597](#)
- [diagnose sys udpsock on page 1597](#)
- [diagnose sys udpsock6 on page 1597](#)
- [diagnose sys uuid on page 1598](#)
- [diagnose sys uuid allow-manual-set on page 1598](#)
- [diagnose sys uuid allow-manual-set disable on page 1598](#)
- [diagnose sys uuid allow-manual-set enable on page 1598](#)
- [diagnose sys uuid generate on page 1598](#)

- [diagnose sys var-zone on page 1598](#)
- [diagnose sys var-zone show on page 1599](#)
- [diagnose sys vd on page 1599](#)
- [diagnose sys vd add on page 1599](#)
- [diagnose sys vd delete on page 1599](#)
- [diagnose sys vd list on page 1599](#)
- [diagnose sys vd set on page 1600](#)
- [diagnose sys vd stats on page 1600](#)
- [diagnose sys vlan on page 1600](#)
- [diagnose sys vlan list on page 1600](#)
- [diagnose sys vxlan on page 1600](#)
- [diagnose sys vxlan fdb on page 1600](#)
- [diagnose sys vxlan fdb list on page 1601](#)

diagnose sys botnet-domain

Botnet domain diagnostics.

```
diagnose sys botnet-domain
```

diagnose sys botnet-domain hit

Botnet domain hits.

```
diagnose sys botnet-domain hit
```

diagnose sys botnet-domain list

List botnet domain entry.

```
diagnose sys botnet-domain list
```

diagnose sys botnet-ip

Botnet IP diagnostics.

```
diagnose sys botnet-ip
```

diagnose sys botnet-ip find

Find botnet IP entry.

```
diagnose sys botnet-ip find <ip> <port> <proto>
```

Parameter	Description	Type	Size
<ip>	IP address.	string	
<port>	Port number.	string	
<proto>	Protocol number.	string	

diagnose sys botnet-ip flush

Flush botnet IP entry hit count data.

```
diagnose sys botnet-ip flush
```

diagnose sys botnet-ip hit

Show botnet IP entry hit count data.

```
diagnose sys botnet-ip hit
```

diagnose sys botnet-ip list

List botnet IP entry.

```
diagnose sys botnet-ip list <offset> <number>
```

Parameter	Description	Type	Size
<offset>	Botnet IP entry offset.	string	
<number>	The number of botnet IP entries to display.	string	

diagnose sys cmdb

CMDB related information.

```
diagnose sys cmdb
```

diagnose sys cmdb check-lock

Check CMDB lock.

```
diagnose sys cmdb check-lock
```

diagnose sys cmdb dump

Dump cmdb internal data.

```
diagnose sys cmdb dump
```

diagnose sys cmdb dump vdom

Dump vdom data.

```
diagnose sys cmdb dump vdom <global/vdom-name>
```

Parameter	Description	Type	Size
<global/vdom-name>	Dump global or vdom-name data details.	string	

diagnose sys cmdb flag

CMDB related flags.

```
diagnose sys cmdb flag
```

diagnose sys cmdb flag info

CMDB related flags information.

```
diagnose sys cmdb flag info
```

diagnose sys cmdb flag reset

Reset CMDB related flags.

```
diagnose sys cmdb flag reset
```

diagnose sys cmdb flag reset script-running

Reset CMDB script-running flag.

```
diagnose sys cmdb flag reset script-running
```

diagnose sys cmdb info

CMDB information.

```
diagnose sys cmdb info
```

diagnose sys cmdb refcnt

Datasource reference count.

```
diagnose sys cmdb refcnt
```

diagnose sys cmdb refcnt reset

Reset reference count to be consistent with real reference.

```
diagnose sys cmdb refcnt reset <path.object.mkey> <tablename>
```

Parameter	Description	Type	Size
<path.object.mkey>	Table.	string	
<tablename>	Entry.	string	

diagnose sys cmdb refcnt show

Show datasource reference details.

```
diagnose sys cmdb refcnt show <path.object.mkey> <tablename>
```

Parameter	Description	Type	Size
<path.object.mkey>	Table.	string	
<tablename>	Entry.	string	

diagnose sys config-transaction

Config transaction related information.

```
diagnose sys config-transaction
```

diagnose sys config-transaction show

Show config transaction information.

```
diagnose sys config-transaction show
```

diagnose sys config-transaction show entity-by-txn

Show configuration objects being configured by individual transactions.

```
diagnose sys config-transaction show entity-by-txn <txn-id>
```

Parameter	Description	Type	Size
<txn-id>	Transaction ID.	string	

diagnose sys config-transaction show mctx

Show mctx.

```
diagnose sys config-transaction show mctx
```

diagnose sys config-transaction show txn-cli-commands

Show CLI commands used in a given transaction.

```
diagnose sys config-transaction show txn-cli-commands <txn-id>
```

Parameter	Description	Type	Size
<txn-id>	Transaction ID.	string	

diagnose sys config-transaction show txn-entity

Show configuration objects being configured in transactions.

```
diagnose sys config-transaction show txn-entity
```

diagnose sys config-transaction show txn-info

Show config transaction details.

```
diagnose sys config-transaction show txn-info
```

diagnose sys config-transaction show txn-lock

Show transaction lock status.

```
diagnose sys config-transaction show txn-lock
```

diagnose sys config-transaction show txn-meta

Show config transaction meta information.

```
diagnose sys config-transaction show txn-meta
```

diagnose sys config-transaction status

Show config transaction status in current CLI.

```
diagnose sys config-transaction status
```

diagnose sys conntrack

conntrack diagnostics.

```
diagnose sys conntrack
```

diagnose sys conntrack clear

Clear all conntrack.

```
diagnose sys conntrack clear
```

diagnose sys conntrack count

Show number of conntrack.

```
diagnose sys conntrack count
```

diagnose sys conntrack list-dying4

List IPv4 dying conntrack.

```
diagnose sys conntrack list-dying4
```

diagnose sys conntrack list-dying6

List IPv6 dying conntrack.

```
diagnose sys conntrack list-dying6
```

diagnose sys conntrack list-unconfirmed4

List IPv4 unconfirmed conntrack.

```
diagnose sys conntrack list-unconfirmed4
```

diagnose sys conntrack list-unconfirmed6

List IPv6 unconfirmed conntrack.

```
diagnose sys conntrack list-unconfirmed6
```


diagnose sys conntrack list4

List IPv4 conntrack.

```
diagnose sys conntrack list4
```

diagnose sys conntrack list6

List IPv6 conntrack.

```
diagnose sys conntrack list6
```

diagnose sys conntrack stats

Show conntrack statistics.

```
diagnose sys conntrack stats
```

diagnose sys csf

Security Fabric diagnostics.

```
diagnose sys csf
```

diagnose sys csf authorization

Authorization requests and permits.

```
diagnose sys csf authorization
```

diagnose sys csf authorization accept

Authorize device to join CSF tree.

```
diagnose sys csf authorization accept <SN> [Name]
```

Parameter	Description	Type	Size
<SN>	Serial number.	string	
[Name]	Optional entry name (if not passed SN is used).	string	

diagnose sys csf authorization deny

Deny device from joining CSF tree.

```
diagnose sys csf authorization deny <SN> [Name]
```

Parameter	Description	Type	Size
<SN>	Serial number.	string	
[Name]	Optional entry name (if not passed SN is used).	string	

diagnose sys csf authorization pending-list

List of pending requests to join security fabric.

```
diagnose sys csf authorization pending-list
```

diagnose sys csf downstream

Show connected downstream FortiProxies.

```
diagnose sys csf downstream [-x] [-a]
```

Parameter	Description	Type	Size
[-x]	Show encrypted tokens	string	
[-a]	Show all devices	string	

diagnose sys csf downstream-devices

Show downstream fabric device.

```
diagnose sys csf downstream-devices <device type> [vdom] [group]
```

Parameter	Description	Type	Size
<device type>	fabric device type (e.g. fortinac, fortimail, fortivoice, any).	string	
[vdom]	Connecting VDOM.	string	
[group]	CSF key group.	string	

diagnose sys csf dynamic-sync-read

Read incoming dynamic sync data updates

```
diagnose sys csf dynamic-sync-read <count>
```

Parameter	Description	Type	Size
<count>	Number of updates to read	string	

diagnose sys csf dynamic-sync-request

Get the current dynamic sync data from csfd

```
diagnose sys csf dynamic-sync-request
```

diagnose sys csf dynamic-sync-update

Change the dynamic sync update data

```
diagnose sys csf dynamic-sync-update <content>
```

Parameter	Description	Type	Size
<content>	New data content string	string	

diagnose sys csf fabric-device

Debug fabric device handling.

```
diagnose sys csf fabric-device
```

diagnose sys csf fabric-device list

List all known fabric devices.

```
diagnose sys csf fabric-device list
```

diagnose sys csf file

csfd file management.

```
diagnose sys csf file
```

diagnose sys csf file cat

Dump file.

```
diagnose sys csf file cat <name>
```

Parameter	Description	Type	Size
<name>	Name of the file to be dumped.	string	

diagnose sys csf file top-mem

Display largest files.

```
diagnose sys csf file top-mem [count]
```

Parameter	Description	Type	Size
[count]	Number of files to be displayed ([1 - 20] default = 5).	string	

diagnose sys csf forticloud-id-list

List of FortiCloud IDs of downstreams.

```
diagnose sys csf forticloud-id-list
```

diagnose sys csf get-bulk-global-view

Request global view file

```
diagnose sys csf get-bulk-global-view [refresh seconds]
```

Parameter	Description	Type	Size
[refresh seconds]	Acceptable age for cached global file in seconds.	string	

diagnose sys csf global

Show a summary of all connected members in Security Fabric.

```
diagnose sys csf global
```

diagnose sys csf initialize-cmd

send an init command for merge.

```
diagnose sys csf initialize-cmd <path> <cmdb_path> <cmdb_table>
```

Parameter	Description	Type	Size
<path>	fabric path made of serial numbers e.g: SNCURRENT:SNMIDDLE:SNDESTINATION.	string	
<cmdb_path>	path for cmdb table	string	
<cmdb_table>	cmdb table name	string	

diagnose sys csf license

Show a summary of FPX license sharing in the cluster.

```
diagnose sys csf license
```

diagnose sys csf merge-cmd

send a merge command to downstream.

```
diagnose sys csf merge-cmd <path> <cmdb_path> <cmdb_table> <key> <new_key>
```

Parameter	Description	Type	Size
<path>	fabric path made of serial numbers e.g: SNCURRENT:SNMIDDLE:SNDESTINATION.	string	
<cmdb_path>	path for cmdb table	string	
<cmdb_table>	cmdb table name	string	

Parameter	Description	Type	Size
<key>	current entry name	string	
<new_key>	new entry name	string	

diagnose sys csf neighbor

CSF enabled devices in adjacency.

```
diagnose sys csf neighbor
```

diagnose sys csf neighbor flush

Clear discovered physical addresses of adjacent devices.

```
diagnose sys csf neighbor flush [interface]
```

Parameter	Description	Type	Size
[interface]	Receiving local interface name.	string	

diagnose sys csf neighbor list

List discovered physical addresses of adjacent devices.

```
diagnose sys csf neighbor list [interface]
```

Parameter	Description	Type	Size
[interface]	Receiving local interface name.	string	

diagnose sys csf query

Query through CSF.

```
diagnose sys csf query <path> [-p]
```

Parameter	Description	Type	Size
<path>	FGT1(SN):FGT2(SN):...:FGTn(SN)	string	
[-p]	partial process.	string	

diagnose sys csf tunnel-test-listener

Test the reliable tunnel, listener side

```
diagnose sys csf tunnel-test-listener
```

diagnose sys csf tunnel-test-sender

Test the reliable tunnel, sender side

```
diagnose sys csf tunnel-test-sender <target-sn> <msg-content> <repeats>
```

Parameter	Description	Type	Size
<target-sn>	SN to send the message to	string	
<msg-content>	Content of the message	string	
<repeats>	Number of times to repeat the message	string	

diagnose sys csf upstream

Show connected upstream FortiProxies.

```
diagnose sys csf upstream
```

diagnose sys csf versions

get latest incremental version of CSF groups.

```
diagnose sys csf versions
```

diagnose sys dayst-info

Daylight saving time information.

```
diagnose sys dayst-info <timezone-index> [year]
```

Parameter	Description	Type	Size
<timezone-index>	Timezone index.	string	
[year]	year	string	

diagnose sys device

Virtual domain device management.

```
diagnose sys device
```

diagnose sys device add

Add device to Virtual Domain.

```
diagnose sys device add <vdname> <devname>
```

Parameter	Description	Type	Size
<vdname>	Virtual Domain Name.	string	
<devname>	Device Name.	string	

diagnose sys device delete

Delete device from Virtual Domain.

```
diagnose sys device delete <vdname> <devname>
```

Parameter	Description	Type	Size
<vdname>	Virtual Domain Name.	string	
<devname>	Device Name.	string	

diagnose sys device list

List devices in Virtual Domain.

```
diagnose sys device list <vdname>
```

Parameter	Description	Type	Size
<vdname>	Virtual Domain Name.	string	

diagnose sys external-resource

External resource.


```
diagnose sys external-resource
```

diagnose sys external-resource list

Dump external resource file by name.

```
diagnose sys external-resource list <name>
```

Parameter	Description	Type	Size
<name>	Name of external resource.	string	

diagnose sys external-resource push-add

Add entry to external resource set to push updates.

```
diagnose sys external-resource push-add
```

diagnose sys external-resource push-api-json-commands

Test push commands JSON API

```
diagnose sys external-resource push-api-json-commands <COMMANDS-JSON>
```

Parameter	Description	Type	Size
<COMMANDS-JSON>	JSON string for commands.	string	

diagnose sys external-resource push-remove

Remove entry to push external resource set to push updates.

```
diagnose sys external-resource push-remove
```

diagnose sys external-resource push-snapshot

Overwrite external resource set to push updates.

```
diagnose sys external-resource push-snapshot
```

diagnose sys external-resource stats

Display external resource file info.

```
diagnose sys external-resource stats <name>
```

Parameter	Description	Type	Size
<name>	Name of external resource.	string	

diagnose sys filesystem

File system.

```
diagnose sys filesystem
```

diagnose sys filesystem hash

Generate hash for files within the filesystem.

```
diagnose sys filesystem hash
```

diagnose sys filesystem last-modified-files

List the last modified files.

```
diagnose sys filesystem last-modified-files [path] [number]
```

Parameter	Description	Type	Size
[path]	Path for listing modified files (default = /data).	string	
[number]	Number of files to list (default = 10).	string	

diagnose sys filesystem tree

List the top files/folders tree.

```
diagnose sys filesystem tree [path] [number]
```

Parameter	Description	Type	Size
[path]	Path for listing files/folder (default = /var/log).	string	
[number]	Number of files in each current folder and subfolder to be listed (default = 10).	string	

diagnose sys fips

FIPS mode.

```
diagnose sys fips
```

diagnose sys fips error-mode

Go to error mode.

```
diagnose sys fips error-mode
```

diagnose sys ha

High availability.

```
diagnose sys ha
```

diagnose sys ha check-vc

check-vc

```
diagnose sys ha check-vc
```

diagnose sys ha checksum

checksum.

```
diagnose sys ha checksum
```

diagnose sys ha checksum cached

Show HA cached checksum.

```
diagnose sys ha checksum cached <global/vdom-name>
```

Parameter	Description	Type	Size
<global/vdom-name>	Show global or a specific vdom's cached HA checksum.	string	

diagnose sys ha checksum cluster

Show HA cluster checksum by serial number.

```
diagnose sys ha checksum cluster
```

diagnose sys ha checksum log

Enable/disable log.

```
diagnose sys ha checksum log
```

diagnose sys ha checksum log clear

Clear log.

```
diagnose sys ha checksum log clear
```

diagnose sys ha checksum log disable

Disable log.

```
diagnose sys ha checksum log disable
```

diagnose sys ha checksum log enable

Enable log.

```
diagnose sys ha checksum log enable
```

diagnose sys ha checksum recalculate

Re-calculate HA checksum.

```
diagnose sys ha checksum recalculate <Enter> or <global/vdom-name>
```

Parameter	Description	Type	Size
<Enter> or <global/vdom-name>	<Enter> to re-calculate all checksums, or global/vdom-name to re-calculate global or a specific vdom HA checksum.	string	

diagnose sys ha checksum show

Show HA checksum.

```
diagnose sys ha checksum show <Enter> or <global/vdom-name> <Enter> or <object-fullpath> <Enter> or <entry-name>
```

Parameter	Description	Type	Size
<Enter> or <global/vdom-name>	<Enter> to show system checksum; <global/vdom-name> to show global/vdom-name detail checksum.	string	
<Enter> or <object-fullpath>	<Enter> to show objects checksum; <object-fullpath> to show individual object's detail checksum.	string	
<Enter> or <entry-name>	<Enter> to show the specific object's detail checksum; <entry-name> to show a single entry's detail checksum.	string	

diagnose sys ha checksum show-nonsync

Show non-sync HA checksum.

```
diagnose sys ha checksum show-nonsync
```

diagnose sys ha checksum test

test.

```
diagnose sys ha checksum test
```

diagnose sys ha dump-by

Dump HA data by name.

```
diagnose sys ha dump-by
```

diagnose sys ha dump-by debug-zone

Dump HA debug zone.

```
diagnose sys ha dump-by debug-zone
```

diagnose sys ha dump-by device

Dump HA device.

```
diagnose sys ha dump-by device
```

diagnose sys ha dump-by group

Dump all group.

```
diagnose sys ha dump-by group
```

diagnose sys ha dump-by kernel

Dump HA kernel info.

```
diagnose sys ha dump-by kernel
```

diagnose sys ha dump-by rcache

Dump rcache.

```
diagnose sys ha dump-by rcache
```

diagnose sys ha dump-by vcluster

Dump all vcluster.

```
diagnose sys ha dump-by vcluster
```

diagnose sys ha dump-by vdom

Dump HA vdom info.

```
diagnose sys ha dump-by vdom
```

diagnose sys ha extfile-sig

Dump extfile's signature.

```
diagnose sys ha extfile-sig
```

diagnose sys ha fgsp-zone

FGSP zone information.

```
diagnose sys ha fgsp-zone
```

diagnose sys ha fib

FIB information.

```
diagnose sys ha fib
```

diagnose sys ha hactx-stats

HA context statistics

```
diagnose sys ha hactx-stats
```

diagnose sys ha hactx-stats clear

HA context statistics

```
diagnose sys ha hactx-stats clear
```

diagnose sys ha hadiff

HA diff debug.

```
diagnose sys ha hadiff
```

diagnose sys ha hadiff log

Enable/disable log.

```
diagnose sys ha hadiff log
```

diagnose sys ha hadiff log clear

Clear log.

```
diagnose sys ha hadiff log clear
```

diagnose sys ha hadiff log disable

Disable log.

```
diagnose sys ha hadiff log disable
```

diagnose sys ha hadiff log enable

Enable log.

```
diagnose sys ha hadiff log enable
```


diagnose sys ha hadiff max-sync-turns

Set/get max number of sync turns.

```
diagnose sys ha hadiff max-sync-turns <integer>
```

Parameter	Description	Type	Size
<integer>	Set/get max number of sync turns.	string	

diagnose sys ha hadiff max-unsync-wait

Set/get max unsync wait times.

```
diagnose sys ha hadiff max-unsync-wait <integer>
```

Parameter	Description	Type	Size
<integer>	Maximum unsync wait times.	string	

diagnose sys ha hadiff status

HA diff status.

```
diagnose sys ha hadiff status
```

diagnose sys ha hasync-conn-max-buf

Set the hasync connection maximum buffer number.

```
diagnose sys ha hasync-conn-max-buf <hasync-conn-max-buf>
```

Parameter	Description	Type	Size
<hasync-conn-max-buf>	Max number of buffers.	string	

diagnose sys ha hasync-stats

hasync daemon stats.

```
diagnose sys ha hasync-stats
```

diagnose sys ha hasync-stats all

Display hasync all objects' stats.

```
diagnose sys ha hasync-stats all
```

diagnose sys ha hasync-stats by-object

Display hasync stats by object.

```
diagnose sys ha hasync-stats by-object <integer>
```

Parameter	Description	Type	Size
<integer>	Object number.	string	

diagnose sys ha hasync-stats most-recent

Display hasync objects recent stats.

```
diagnose sys ha hasync-stats most-recent [integer]
```

Parameter	Description	Type	Size
[integer]	Most recent # of objects to display.	string	

diagnose sys ha hasync-stats most-time

Display hasync objects ranked by total time.

```
diagnose sys ha hasync-stats most-time [integer]
```

Parameter	Description	Type	Size
[integer]	# of top objects to display.	string	

diagnose sys ha heartbeat

Show kernel heartbeat stats.

```
diagnose sys ha heartbeat
```

diagnose sys ha history

Cluster history information.

```
diagnose sys ha history
```

diagnose sys ha history clear

Clear cluster history.

```
diagnose sys ha history clear
```

diagnose sys ha history read

Display cluster history.

```
diagnose sys ha history read
```

diagnose sys ha mac

Mac Information.

```
diagnose sys ha mac
```

diagnose sys ha pingsvr-secondary-force-reset

Reset HA up time.

```
diagnose sys ha pingsvr-secondary-force-reset
```

diagnose sys ha recalculate-extfile-signature

Recalculate external files signature in hasync daemon.

```
diagnose sys ha recalculate-extfile-signature
```

diagnose sys ha reset-health-status

Reset HA health status.

```
diagnose sys ha reset-health-status
```

diagnose sys ha reset-uptime

Reset HA up time.

```
diagnose sys ha reset-uptime
```

diagnose sys ha session-sync-dev

Session sync ports.

```
diagnose sys ha session-sync-dev
```

diagnose sys ha session-sync-dev clear

Clear session sync ports.

```
diagnose sys ha session-sync-dev clear
```

diagnose sys ha session-sync-dev set

Configure session sync ports.

```
diagnose sys ha session-sync-dev set
```

diagnose sys ha standalone-peers

Standalone peers on kernel.

```
diagnose sys ha standalone-peers
```

diagnose sys ha standalone-peers reset-stats

Reset standalone peers session/packet type counters in kernel.

```
diagnose sys ha standalone-peers reset-stats
```

diagnose sys ha stats

statistics

```
diagnose sys ha stats
```

diagnose sys ha status

status

```
diagnose sys ha status
```

diagnose sys ha sync-stats

Dump HA sync statistics.

```
diagnose sys ha sync-stats
```

diagnose sys ha sync-stats-reset

Reset HA sync statistics.

```
diagnose sys ha sync-stats-reset
```

diagnose sys ha vlan-hb-monitor

Dump vlan heartbeat monitor list.

```
diagnose sys ha vlan-hb-monitor
```

diagnose sys icap-remote-server

Display remote icap servers status.

```
diagnose sys icap-remote-server
```

diagnose sys icap-remote-server status

List remote icap servers status.

```
diagnose sys icap-remote-server status
```

diagnose sys iotop

Show disk-accessing processes.

```
diagnose sys iotop <interval>
```

Parameter	Description	Type	Size
<interval>	Print interval in seconds (default to 5). Accept value from 5 to 3600.	string	

diagnose sys link-monitor

Link Monitor.

```
diagnose sys link-monitor
```

diagnose sys link-monitor filter

Filter link-monitor

```
diagnose sys link-monitor filter
```

diagnose sys link-monitor filter clear

Clear all filters.

```
diagnose sys link-monitor filter clear
```

diagnose sys link-monitor filter name

Link monitor names <name>.

```
diagnose sys link-monitor filter name <name>
```

Parameter	Description	Type	Size
<name>	Link monitor name.	string	

diagnose sys link-monitor interface

interface quality.

```
diagnose sys link-monitor interface <name> <childname>
```

Parameter	Description	Type	Size
<name>	Show details of an interface entry.	string	
<childname>	Child interface name.	string	

diagnose sys link-monitor launch

Launching a link monitor entry manually.

```
diagnose sys link-monitor launch <entry name>
```

Parameter	Description	Type	Size
<entry name>	Entry.	string	

diagnose sys link-monitor status

status

```
diagnose sys link-monitor status <name | all>
```

Parameter	Description	Type	Size
<name all>	Show details of monitor entry.	string	

diagnose sys mpstat

mpstat

```
diagnose sys mpstat <value> <value>
```

Parameter	Description	Type	Size
<value>	Delay in seconds (default 5).	string	
<value>	Loop times (default = 1,000,000).	string	

diagnose sys nmi-watchdog

nmi-watchdog

```
diagnose sys nmi-watchdog
```

diagnose sys nmi-watchdog disable

Disable NMI watchdog.

```
diagnose sys nmi-watchdog disable
```

diagnose sys nmi-watchdog enable

Enable NMI watchdog.

```
diagnose sys nmi-watchdog enable
```

diagnose sys nmi-watchdog reboot

reboot on lockup detection.

```
diagnose sys nmi-watchdog reboot
```

diagnose sys nmi-watchdog reboot disable

Disable reboot on lockup detection.

```
diagnose sys nmi-watchdog reboot disable
```


diagnose sys nmi-watchdog reboot enable

Enable reboot on lockup detection.

```
diagnose sys nmi-watchdog reboot enable
```

diagnose sys nmi-watchdog threshold

Duration of lockup that register as a detection.

```
diagnose sys nmi-watchdog threshold <seconds>
```

Parameter	Description	Type	Size
<seconds>	(6 to 40 seconds)	string	

diagnose sys ntp

NTP daemon command.

```
diagnose sys ntp
```

diagnose sys ntp status

List NTP servers information.

```
diagnose sys ntp status
```

diagnose sys pair

Pair device.

```
diagnose sys pair
```

diagnose sys process

Dump process stack.

```
diagnose sys process
```

diagnose sys process dump

Dump process kernel stack.

```
diagnose sys process dump <pid>
```

Parameter	Description	Type	Size
<pid>	PID of the process to dump.	string	

diagnose sys process nameof

List name of process with a specific PID.

```
diagnose sys process nameof <integer>
```

Parameter	Description	Type	Size
<integer>	PID to find the process name.	string	

diagnose sys process pidof

List PIDs of processes with a specific name.

```
diagnose sys process pidof <string>
```

Parameter	Description	Type	Size
<string>	Name to find PIDs for.	string	

diagnose sys process pstack

Dump process userspace stack.

```
diagnose sys process pstack <pid>
```

Parameter	Description	Type	Size
<pid>	PID of the process to dump.	string	

diagnose sys process sock-mem

Show process socket mem usage.

```
diagnose sys process sock-mem
```

diagnose sys process socket

Find PID of processes which owns the socket.

```
diagnose sys process socket <socket-inode>
```

Parameter	Description	Type	Size
<socket-inode>	Socket to find PID for.	string	

diagnose sys process trace

Sample process instructions.

```
diagnose sys process trace
```

diagnose sys profile

kernel profiling

```
diagnose sys profile
```

diagnose sys profile cpumask

profile which CPUs

```
diagnose sys profile cpumask
```

diagnose sys profile show

show kernel profiling result

```
diagnose sys profile show
```

diagnose sys profile show detail

show detail of kernel profiling

```
diagnose sys profile show detail
```

diagnose sys profile show order

order kernel profiling result

```
diagnose sys profile show order
```

diagnose sys profile start

start kernel profiling data

```
diagnose sys profile start
```

diagnose sys profile step

set profile step

```
diagnose sys profile step <Integer>
```

Parameter	Description	Type	Size
<Integer>	Profile step for CPU profiling. Argument should be a power of two between 2 to 32	string	

diagnose sys profile stop

copy kernel profiling data

```
diagnose sys profile stop
```

diagnose sys profile sysmap

show kernel sysmap

```
diagnose sys profile sysmap
```

diagnose sys ptp

PTP daemon command.

```
diagnose sys ptp
```

diagnose sys ptp status

List PTP information.

```
diagnose sys ptp status
```

diagnose sys scanunit

Scanunit diagnostics.

```
diagnose sys scanunit
```

diagnose sys scanunit av-filetype-reuse

Enable/disable AV filetype reuse.

```
diagnose sys scanunit av-filetype-reuse
```

diagnose sys scanunit av-filetype-reuse disable

Disable scanunit AV filetype reuse.

```
diagnose sys scanunit av-filetype-reuse disable
```

diagnose sys scanunit av-filetype-reuse enable

Enable scanunit AV filetype reuse.

```
diagnose sys scanunit av-filetype-reuse enable
```

diagnose sys scanunit bypass

Bypass setting.

```
diagnose sys scanunit bypass
```

diagnose sys scanunit bypass clear

Clear bypass settings.

```
diagnose sys scanunit bypass clear
```

diagnose sys scanunit bypass disable

Disable bypass settings.

```
diagnose sys scanunit bypass disable
```

diagnose sys scanunit bypass disable category

Disable category bypass.

```
diagnose sys scanunit bypass disable category
```

diagnose sys scanunit bypass disable category all

Bypass all.

```
diagnose sys scanunit bypass disable category all
```

diagnose sys scanunit bypass disable category av-engine

Bypass AV engine.

```
diagnose sys scanunit bypass disable category av-engine
```

diagnose sys scanunit bypass disable category scanunit

Bypass scanunit.

```
diagnose sys scanunit bypass disable category scanunit
```

diagnose sys scanunit bypass disable protocol

Disable protocol bypass.

```
diagnose sys scanunit bypass disable protocol
```

diagnose sys scanunit bypass disable protocol all

All proxy protocols

```
diagnose sys scanunit bypass disable protocol all
```

diagnose sys scanunit bypass disable protocol cifs

CIFS protocol

```
diagnose sys scanunit bypass disable protocol cifs
```

diagnose sys scanunit bypass disable protocol ftp

FTP(S) protocol

```
diagnose sys scanunit bypass disable protocol ftp
```

diagnose sys scanunit bypass disable protocol http

HTTP(S) protocol

```
diagnose sys scanunit bypass disable protocol http
```

diagnose sys scanunit bypass disable protocol imap

IMAP(S) protocol

```
diagnose sys scanunit bypass disable protocol imap
```

diagnose sys scanunit bypass disable protocol nntp

NNTP protocol

```
diagnose sys scanunit bypass disable protocol nntp
```

diagnose sys scanunit bypass disable protocol pop3

POP3(S) protocol

```
diagnose sys scanunit bypass disable protocol pop3
```

diagnose sys scanunit bypass disable protocol smtp

SMTP(S) protocol

```
diagnose sys scanunit bypass disable protocol smtp
```

diagnose sys scanunit bypass enable

Enable bypass settings.

```
diagnose sys scanunit bypass enable
```

diagnose sys scanunit bypass enable category

Enable category bypass.

```
diagnose sys scanunit bypass enable category
```


diagnose sys scanunit bypass enable category all

Bypass all.

```
diagnose sys scanunit bypass enable category all
```

diagnose sys scanunit bypass enable category av-engine

Bypass AV engine.

```
diagnose sys scanunit bypass enable category av-engine
```

diagnose sys scanunit bypass enable category scanunit

Bypass scanunit.

```
diagnose sys scanunit bypass enable category scanunit
```

diagnose sys scanunit bypass enable protocol

Enable protocol bypass.

```
diagnose sys scanunit bypass enable protocol
```

diagnose sys scanunit bypass enable protocol all

All proxy protocols

```
diagnose sys scanunit bypass enable protocol all
```

diagnose sys scanunit bypass enable protocol cifs

CIFS protocol

```
diagnose sys scanunit bypass enable protocol cifs
```

diagnose sys scanunit bypass enable protocol ftp

FTP(S) protocol

```
diagnose sys scanunit bypass enable protocol ftp
```

diagnose sys scanunit bypass enable protocol http

HTTP(S) protocol

```
diagnose sys scanunit bypass enable protocol http
```

diagnose sys scanunit bypass enable protocol imap

IMAP(S) protocol

```
diagnose sys scanunit bypass enable protocol imap
```

diagnose sys scanunit bypass enable protocol nntp

NNTP protocol

```
diagnose sys scanunit bypass enable protocol nntp
```

diagnose sys scanunit bypass enable protocol pop3

POP3(S) protocol

```
diagnose sys scanunit bypass enable protocol pop3
```

diagnose sys scanunit bypass enable protocol smtp

SMTP(S) protocol

```
diagnose sys scanunit bypass enable protocol smtp
```

diagnose sys scanunit bypass show

Show bypass settings.

```
diagnose sys scanunit bypass show
```

diagnose sys scanunit crash-dump

Enable/disable crash dump.

```
diagnose sys scanunit crash-dump
```

diagnose sys scanunit crash-dump clear

Clear scanunit crash dump.

```
diagnose sys scanunit crash-dump clear
```

diagnose sys scanunit crash-dump disable

Disable scanunit crash dump.

```
diagnose sys scanunit crash-dump disable
```

diagnose sys scanunit crash-dump enable

Enable scanunit crash dump.

```
diagnose sys scanunit crash-dump enable
```

diagnose sys scanunit crash-dump read

Read the last crash dump.

```
diagnose sys scanunit crash-dump read
```

diagnose sys scanunit debug

Debug settings.

```
diagnose sys scanunit debug
```

diagnose sys scanunit debug all

Enable all debug categories.

```
diagnose sys scanunit debug all <status>
```

Parameter	Description	Type	Size
<status>	Enable or disable debug category.	string	

diagnose sys scanunit debug analytics

Enable analytics category.

```
diagnose sys scanunit debug analytics <status>
```

Parameter	Description	Type	Size
<status>	Enable or disable debug category.	string	

diagnose sys scanunit debug antispam

Enable antispam category.

```
diagnose sys scanunit debug antispam <status>
```

Parameter	Description	Type	Size
<status>	Enable or disable debug category.	string	

diagnose sys scanunit debug daemon

Enable scanunit daemon category.

```
diagnose sys scanunit debug daemon <status>
```

Parameter	Description	Type	Size
<status>	Enable or disable debug category.	string	

diagnose sys scanunit debug dlp

Enable DLP category.

```
diagnose sys scanunit debug dlp <status>
```

Parameter	Description	Type	Size
<status>	Enable or disable debug category.	string	

diagnose sys scanunit debug file-filter

Enable file filter category.

```
diagnose sys scanunit debug file-filter <status>
```

Parameter	Description	Type	Size
<status>	Enable or disable debug category.	string	

diagnose sys scanunit debug ia

Enable IA category.

```
diagnose sys scanunit debug ia <status>
```

Parameter	Description	Type	Size
<status>	Enable or disable debug category.	string	

diagnose sys scanunit debug icb

Enable ICB category.

```
diagnose sys scanunit debug icb <status>
```

Parameter	Description	Type	Size
<status>	Enable or disable debug category.	string	

diagnose sys scanunit debug job

Enable scanunit job category.

```
diagnose sys scanunit debug job <status>
```

Parameter	Description	Type	Size
<status>	Enable or disable debug category.	string	

diagnose sys scanunit debug level

Set debug level.

```
diagnose sys scanunit debug level
```

diagnose sys scanunit debug level error

Error level.

```
diagnose sys scanunit debug level error
```

diagnose sys scanunit debug level info

Info level.

```
diagnose sys scanunit debug level info
```

diagnose sys scanunit debug level verbose

Verbose level.

```
diagnose sys scanunit debug level verbose
```

diagnose sys scanunit debug level warning

Warning level.

```
diagnose sys scanunit debug level warning
```

diagnose sys scanunit debug outbreak-prevention

Enable outbreak prevention category.

```
diagnose sys scanunit debug outbreak-prevention <status>
```

Parameter	Description	Type	Size
<status>	Enable or disable debug category.	string	

diagnose sys scanunit debug quarantine

Enable quarantine category.

```
diagnose sys scanunit debug quarantine <status>
```

Parameter	Description	Type	Size
<status>	Enable or disable debug category.	string	

diagnose sys scanunit debug reset

Reset debug category and level.

```
diagnose sys scanunit debug reset
```

diagnose sys scanunit debug sane

Enable a sane group of categories.

```
diagnose sys scanunit debug sane <status>
```

Parameter	Description	Type	Size
<status>	Enable or disable debug category.	string	

diagnose sys scanunit debug show

Show current debug settings.

```
diagnose sys scanunit debug show
```

diagnose sys scanunit file-hash

File hash list.

```
diagnose sys scanunit file-hash
```

diagnose sys scanunit file-hash list

List malware hashes.

```
diagnose sys scanunit file-hash list
```

diagnose sys scanunit file-hash list all

List all malware hashes.

```
diagnose sys scanunit file-hash list all
```

diagnose sys scanunit file-hash list md5

List md5 malware hashes.

```
diagnose sys scanunit file-hash list md5
```

diagnose sys scanunit file-hash list sha1

List sha1 malware hashes.

```
diagnose sys scanunit file-hash list sha1
```

diagnose sys scanunit file-hash list sha256

List sha256 malware hashes.

```
diagnose sys scanunit file-hash list sha256
```


diagnose sys scanunit file-hash query

Query a malware hash.

```
diagnose sys scanunit file-hash query
```

diagnose sys scanunit file-hash query md5

Query an md5 malware hash.

```
diagnose sys scanunit file-hash query md5 <value>
```

Parameter	Description	Type	Size
<value>	md5 hash	string	

diagnose sys scanunit file-hash query sha1

Query a sha1 malware hash.

```
diagnose sys scanunit file-hash query sha1 <value>
```

Parameter	Description	Type	Size
<value>	sha1 hash	string	

diagnose sys scanunit file-hash query sha256

Query a sha256 malware hash.

```
diagnose sys scanunit file-hash query sha256 <value>
```

Parameter	Description	Type	Size
<value>	sha256 hash	string	

diagnose sys scanunit file-hash status

File hash database status.

```
diagnose sys scanunit file-hash status
```

diagnose sys scanunit filter

Diagnostics filter.

```
diagnose sys scanunit filter
```

diagnose sys scanunit filter clear

Clear the current filter.

```
diagnose sys scanunit filter clear
```

diagnose sys scanunit filter list

Display the current filter.

```
diagnose sys scanunit filter list
```

diagnose sys scanunit filter negate

Negate the specified filter parameter.

```
diagnose sys scanunit filter negate
```

diagnose sys scanunit filter negate vd

Negate virtual domain.

```
diagnose sys scanunit filter negate vd
```

diagnose sys scanunit filter vd

Index of virtual domain. -1 matches all.

```
diagnose sys scanunit filter vd <index>
```

Parameter	Description	Type	Size
<index>	Index of virtual domain. -1 matches all.	string	

diagnose sys scanunit log

Logging diagnostics.

```
diagnose sys scanunit log
```

diagnose sys scanunit log filter

Debug log filter.

```
diagnose sys scanunit log filter
```

diagnose sys scanunit log filter clear

Clear the current filter.

```
diagnose sys scanunit log filter clear
```

diagnose sys scanunit log filter list

Display the current filter.

```
diagnose sys scanunit log filter list
```

diagnose sys scanunit log filter negate

Negate the specified filter parameter.

```
diagnose sys scanunit log filter negate
```

diagnose sys scanunit log filter negate vd

Negate virtual domain.

```
diagnose sys scanunit log filter negate vd
```

diagnose sys scanunit log filter vd

Index of virtual domain. -1 matches all.

```
diagnose sys scanunit log filter vd <index>
```

Parameter	Description	Type	Size
<index>	Index of virtual domain. -1 matches all.	string	

diagnose sys scanunit reload-avdb

Reload AVDB.

```
diagnose sys scanunit reload-avdb
```

diagnose sys scanunit reload-aveng

Reload AV engine.

```
diagnose sys scanunit reload-aveng
```

diagnose sys scanunit restart

Restart scanunit.

```
diagnose sys scanunit restart
```

diagnose sys scanunit stats

Statistics.

```
diagnose sys scanunit stats
```

diagnose sys scanunit stats all

Per-process statistics.

```
diagnose sys scanunit stats all
```

diagnose sys scanunit stats clear

Clear all statistics.

```
diagnose sys scanunit stats clear
```

diagnose sys scanunit stats list

List statistics.

```
diagnose sys scanunit stats list
```

diagnose sys scanunit vdom-stats

Current VDOM statistics.

```
diagnose sys scanunit vdom-stats
```

diagnose sys scanunit vdom-stats all

List all VDOM statistics.

```
diagnose sys scanunit vdom-stats all
```

diagnose sys scanunit vdom-stats clear

Clear current VDOM statistics.

```
diagnose sys scanunit vdom-stats clear
```

diagnose sys scanunit vdom-stats clear-all

Clear all VDOM statistics.

```
diagnose sys scanunit vdom-stats clear-all
```

diagnose sys scanunit vdom-stats list

List current VDOM statistics.

```
diagnose sys scanunit vdom-stats list
```

diagnose sys sdn

SDN Connector diagnostics.

```
diagnose sys sdn
```

diagnose sys sdn cache

Show SDN Connector cache.

```
diagnose sys sdn cache <sdn-data-type> <sdn-connector-name>
```

Parameter	Description	Type	Size
<sdn-data-type>	Specify the data type of the SDN Connector: address/service.	string	
<sdn-connector-name>	Specify the name of the SDN connector.	string	

diagnose sys sdn status

Show SDN Connector status.

```
diagnose sys sdn status <sdn-connector-name> <server-ip-address>
```

Parameter	Description	Type	Size
<sdn-connector-name>	Specify the name of the SDN Connector.	string	
<server-ip-address>	Specify the IP address of the SDN connector.	string	

diagnose sys server-probe

Server probe.

```
diagnose sys server-probe
```

diagnose sys server-probe response

Probe response.

```
diagnose sys server-probe response
```

diagnose sys session

IPv4 session.

```
diagnose sys session
```

diagnose sys session clear

Clear the sessions defined by filter.

```
diagnose sys session clear
```

diagnose sys session count

Show number of sessions.

```
diagnose sys session count
```

diagnose sys session exp-stat

Expectation session statistics.

```
diagnose sys session exp-stat
```

diagnose sys session expectation

List expectation session.

```
diagnose sys session expectation
```

diagnose sys session filter

List session with filters.

```
diagnose sys session filter
```

diagnose sys session filter clear

Clear session filter.

```
diagnose sys session filter clear
```

diagnose sys session filter clear dintf

Clear destination interface filter.

```
diagnose sys session filter clear dintf
```

diagnose sys session filter clear dport

Clear destination port filter.

```
diagnose sys session filter clear dport
```

diagnose sys session filter clear dst

Clear destination IP filter.

```
diagnose sys session filter clear dst
```


diagnose sys session filter clear nsrc

clear NAT'd source IP filter

```
diagnose sys session filter clear nsrc
```

diagnose sys session filter clear policy

Clear policy ID filter.

```
diagnose sys session filter clear policy
```

diagnose sys session filter clear proto

Clear protocol filter.

```
diagnose sys session filter clear proto
```

diagnose sys session filter clear proto-state

Clear protocol state filter.

```
diagnose sys session filter clear proto-state
```

diagnose sys session filter clear sintf

Clear source interface filter.

```
diagnose sys session filter clear sintf
```

diagnose sys session filter clear sport

Clear source port filter.

```
diagnose sys session filter clear sport
```

diagnose sys session filter clear src

Clear source IP filter.

```
diagnose sys session filter clear src
```

diagnose sys session filter dintf

Destination interface.

```
diagnose sys session filter dintf <xxxx>
```

Parameter	Description	Type	Size
<xxxx>	Interface name.	string	

diagnose sys session filter dport

Destination port.

```
diagnose sys session filter dport <xxxx> <xxxx>
```

Parameter	Description	Type	Size
<xxxx>	<0-65535> (from).	string	
<xxxx>	<0-65535> (to).	string	

diagnose sys session filter dst

Destination IP address.

```
diagnose sys session filter dst <xxx.xxx.xxx.xxx> <xxx.xxx.xxx.xxx>
```

Parameter	Description	Type	Size
<xxx.xxx.xxx.xxx>	Destination IP (from).	string	
<xxx.xxx.xxx.xxx>	Destination IP (to).	string	

diagnose sys session filter nsrc

NAT'd source ip address

```
diagnose sys session filter nsrc <xxx.xxx.xxx.xxx> <xxx.xxx.xxx.xxx>
```

Parameter	Description	Type	Size
<xxx.xxx.xxx.xxx>	NAT'd source ip (from)	string	
<xxx.xxx.xxx.xxx>	NAT'd source ip (to)	string	

diagnose sys session filter policy

Policy ID.

```
diagnose sys session filter policy <xxx> <xxx>
```

Parameter	Description	Type	Size
<xxx>	Policy ID (from).	string	
<xxx>	Policy ID (to).	string	

diagnose sys session filter proto

Protocol number.

```
diagnose sys session filter proto <xx>
```

Parameter	Description	Type	Size
<xx>	<0-255>.	string	

diagnose sys session filter intf

Source interface.

```
diagnose sys session filter intf <xxxx>
```

Parameter	Description	Type	Size
<xxxx>	Interface name.	string	

diagnose sys session filter sport

Source port.

```
diagnose sys session filter sport <xxxx> <xxxx>
```

Parameter	Description	Type	Size
<xxxx>	<0-65535> (from).	string	
<xxxx>	<0-65535> (to).	string	

diagnose sys session filter src

Source IP address.

```
diagnose sys session filter src <xxx.xxx.xxx.xxx> <xxx.xxx.xxx.xxx>
```

Parameter	Description	Type	Size
<xxx.xxx.xxx.xxx>	Source IP (from).	string	
<xxx.xxx.xxx.xxx>	Source IP (to).	string	

diagnose sys session full-stat

Fully stat session.

```
diagnose sys session full-stat
```

diagnose sys session list

List session.

```
diagnose sys session list
```

diagnose sys session list-verbose

List sessions in verbose detail.

```
diagnose sys session list-verbose
```

diagnose sys session stat

Stat session.

```
diagnose sys session stat
```

diagnose sys session ttl

TTL session.

```
diagnose sys session ttl
```

diagnose sys session6

IPv6 session.

```
diagnose sys session6
```

diagnose sys session6 clear

Clear IPv6 sessions defined by filter.

```
diagnose sys session6 clear
```

diagnose sys session6 expectation

List IPv6 expectation session.

```
diagnose sys session6 expectation
```

diagnose sys session6 filter

List IPv6 session with filters.

```
diagnose sys session6 filter
```

diagnose sys session6 filter clear

Clear IPv6 session filter.

```
diagnose sys session6 filter clear
```

diagnose sys session6 filter clear dintf

Clear destination interface filter.

```
diagnose sys session6 filter clear dintf
```

diagnose sys session6 filter clear dport

Clear destination port filter.

```
diagnose sys session6 filter clear dport
```

diagnose sys session6 filter clear dst

Clear destination IP filter.

```
diagnose sys session6 filter clear dst
```

diagnose sys session6 filter clear nsrc

Clear NAT'd source IP filter.

```
diagnose sys session6 filter clear nsrc
```

diagnose sys session6 filter clear policy

Clear policy ID filter.

```
diagnose sys session6 filter clear policy
```

diagnose sys session6 filter clear proto

Clear protocol filter.

```
diagnose sys session6 filter clear proto
```

diagnose sys session6 filter clear proto-state

Clear protocol state filter.

```
diagnose sys session6 filter clear proto-state
```

diagnose sys session6 filter clear intf

Clear source interface filter.

```
diagnose sys session6 filter clear intf
```

diagnose sys session6 filter clear sport

Clear source port filter.

```
diagnose sys session6 filter clear sport
```

diagnose sys session6 filter clear src

Clear source IP filter.

```
diagnose sys session6 filter clear src
```

diagnose sys session6 filter clear vd

Clear virtual domain filter.

```
diagnose sys session6 filter clear vd
```

diagnose sys session6 filter dintf

Destination interface.

```
diagnose sys session6 filter dintf <xxxxxx>
```

Parameter	Description	Type	Size
<xxxxxx>	Interface name.	string	

diagnose sys session6 filter dport

Destination port.

```
diagnose sys session6 filter dport <xxxx> <xxxx>
```

Parameter	Description	Type	Size
<xxxx>	<0-65535> (from).	string	
<xxxx>	<0-65535> (to).	string	

diagnose sys session6 filter dst

Destination IP address.

```
diagnose sys session6 filter dst <xxx:xxx::xxx:xxx> <xxx:xxx::xxx:xxx>
```

Parameter	Description	Type	Size
<xxx:xxx::xxx:xxx>	Destination IP (from).	string	
<xxx:xxx::xxx:xxx>	Destination IP (to).	string	

diagnose sys session6 filter nsrc

NAT'd source IP address.

```
diagnose sys session6 filter nsrc <xxx:xxx::xxx:xxx> <xxx:xxx::xxx:xxx>
```

Parameter	Description	Type	Size
<xxx:xxx::xxx:xxx>	NAT'd source IP (from).	string	
<xxx:xxx::xxx:xxx>	NAT'd Source IP (to).	string	

diagnose sys session6 filter policy

Policy ID.

```
diagnose sys session6 filter policy <xxx> <xxx>
```


Parameter	Description	Type	Size
<xxx>	Policy ID (from).	string	
<xxx>	Policy ID (to).	string	

diagnose sys session6 filter proto

Protocol number.

```
diagnose sys session6 filter proto <xx>
```

Parameter	Description	Type	Size
<xx>	<0-255>.	string	

diagnose sys session6 filter intf

Source interface.

```
diagnose sys session6 filter intf <xxxxx>
```

Parameter	Description	Type	Size
<xxxxx>	Interface name.	string	

diagnose sys session6 filter sport

Source port.

```
diagnose sys session6 filter sport <xxxx> <xxxx>
```

Parameter	Description	Type	Size
<xxxx>	<0-65535> (from).	string	
<xxxx>	<0-65535> (to).	string	

diagnose sys session6 filter src

Source IP address.

```
diagnose sys session6 filter src <xxx:xxx::xxx:xxx> <xxx:xxx::xxx:xxx>
```

Parameter	Description	Type	Size
<xxx:xxx::xxx:xxx>	Source IP (from).	string	
<xxx:xxx::xxx:xxx>	Source IP (to).	string	

diagnose sys session6 list

List IPv6 session.

```
diagnose sys session6 list
```

diagnose sys session6 list-verbose

List sessions in verbose detail.

```
diagnose sys session6 list-verbose
```

diagnose sys tcp-option

Enable/disable TCP option.

```
diagnose sys tcp-option
```

diagnose sys tcp-option disable

disable

```
diagnose sys tcp-option disable
```

diagnose sys tcp-option enable

enable

```
diagnose sys tcp-option enable
```

diagnose sys tcpsock

TCP sock info.

```
diagnose sys tcpsock
```

diagnose sys tcpsock6

TCP sock6 info.

```
diagnose sys tcpsock6
```

diagnose sys top

Show top processes information.

```
diagnose sys top <value> <Integer> <value>
```

Parameter	Description	Type	Size
<value>	Delay in seconds (default 5).	string	
<Integer>	Maximum lines to display (default 20). Show all the running processes if larger than its total number.	string	
<value>	Iterations to run (default unlimited).	string	

diagnose sys top-all

Show top threads information.

```
diagnose sys top-all <value> <Integer> <value>
```

Parameter	Description	Type	Size
<value>	Delay in seconds (default 5).	string	
<Integer>	Maximum lines to display (default 20). Show all the running threads if larger than its total number.	string	
<value>	Iterations to run (default unlimited).	string	

diagnose sys top-fd

Display processes with the most active file descriptors (default 5 processes).

```
diagnose sys top-fd [process-count]
```

Parameter	Description	Type	Size
[process-count]	Number of processes to include info for (default 5).	string	

diagnose sys top-fd detail

Display per-process active fd info along with details (default 5 processes, 50 fds).

```
diagnose sys top-fd detail [process-count] [fd-count]
```

Parameter	Description	Type	Size
[process-count]	Number of processes to include info for (default 5).	string	
[fd-count]	Number of FDs to include (per process, default 50).	string	

diagnose sys top-mem

Display processes with the most used memory (default 5 processes).

```
diagnose sys top-mem [process-count]
```

Parameter	Description	Type	Size
[process-count]	Number of processes to include info for (default 5).	string	

diagnose sys top-mem detail

Display per-process memory info along with details (default 5 processes).

```
diagnose sys top-mem detail [process-count]
```

Parameter	Description	Type	Size
[process-count]	Number of processes to include info for (default 5).	string	

diagnose sys top-sockmem

Display processes with the most used socket memory (default 5 processes).

```
diagnose sys top-sockmem [process-count]
```

Parameter	Description	Type	Size
[process-count]	Number of processes to include info for (default 5).	string	

diagnose sys traffic

Traffic information

```
diagnose sys traffic
```

diagnose sys traffic app-stats

Traffic application statistics.

```
diagnose sys traffic app-stats
```

diagnose sys traffic app-stats list

List traffic application statistics entry.

```
diagnose sys traffic app-stats list
```

diagnose sys udpsock

UDP sock info.

```
diagnose sys udpsock
```

diagnose sys udpsock6

UDP sock6 info.

```
diagnose sys udpsock6
```

diagnose sys uuid

UUID debug.

```
diagnose sys uuid
```

diagnose sys uuid allow-manual-set

Allow to set UUID manually.

```
diagnose sys uuid allow-manual-set
```

diagnose sys uuid allow-manual-set disable

Disable.

```
diagnose sys uuid allow-manual-set disable
```

diagnose sys uuid allow-manual-set enable

Enable.

```
diagnose sys uuid allow-manual-set enable
```

diagnose sys uuid generate

Generate a UUID.

```
diagnose sys uuid generate
```

diagnose sys var-zone

var-zone information.

```
diagnose sys var-zone
```

diagnose sys var-zone show

Show var-zone data.

```
diagnose sys var-zone show
```

diagnose sys vd

Virtual domain management.

```
diagnose sys vd
```

diagnose sys vd add

Add a Virtual System.

```
diagnose sys vd add <vdname>
```

Parameter	Description	Type	Size
<vdname>	Virtual Domain Name.	string	

diagnose sys vd delete

Delete a Virtual System.

```
diagnose sys vd delete <vdname>
```

Parameter	Description	Type	Size
<vdname>	Virtual Domain Name.	string	

diagnose sys vd list

List Virtual Domains.

```
diagnose sys vd list
```

diagnose sys vd set

Set current VDOM.

```
diagnose sys vd set <vdname>
```

Parameter	Description	Type	Size
<vdname>	Virtual Domain Name.	string	

diagnose sys vd stats

Show VDOM statistics.

```
diagnose sys vd stats
```

diagnose sys vlan

vlan

```
diagnose sys vlan
```

diagnose sys vlan list

List VLAN.

```
diagnose sys vlan list
```

diagnose sys vxlan

VXLAN diagnostics.

```
diagnose sys vxlan
```

diagnose sys vxlan fdb

VXLAN forwarding DB.

```
diagnose sys vxlan fdb
```


diagnose sys vxlan fdb list

Display VXLAN forwarding DB.

```
diagnose sys vxlan fdb list <string>
```

Parameter	Description	Type	Size
<string>	Interface name.	string	

diagnose test analytics-pdf-report

Retrieve analytics PDF report from FortiSandbox.

This topic includes the following commands:

- [diagnose test analytics-pdf-report list on page 1601](#)
- [diagnose test analytics-pdf-report max on page 1601](#)
- [diagnose test analytics-pdf-report request on page 1601](#)
- [diagnose test analytics-pdf-report status on page 1602](#)

diagnose test analytics-pdf-report list

List the PDF report requested.

```
diagnose test analytics-pdf-report list
```

diagnose test analytics-pdf-report max

Maximum number of PDF reports to cache in this FortiGate (<1> - <100>, default = 10).

```
diagnose test analytics-pdf-report max
```

diagnose test analytics-pdf-report request

Send the checksum of file to download.

```
diagnose test analytics-pdf-report request
```

diagnose test analytics-pdf-report status

Send the checksum of file to query status.

```
diagnose test analytics-pdf-report status
```

diagnose test analytics-report

Retrieve analytics report from FortiSandbox.

This topic includes the following commands:

- [diagnose test analytics-report checksum on page 1602](#)

diagnose test analytics-report checksum

Checksum of file to query.

```
diagnose test analytics-report checksum
```

diagnose test application

application

This topic includes the following commands:

- [diagnose test application acd on page 1604](#)
- [diagnose test application acsd on page 1604](#)
- [diagnose test application autod on page 1604](#)
- [diagnose test application awsd on page 1605](#)
- [diagnose test application azd on page 1605](#)
- [diagnose test application bfd on page 1605](#)
- [diagnose test application csfd on page 1605](#)
- [diagnose test application ddnsd on page 1606](#)
- [diagnose test application dhcp6c on page 1606](#)
- [diagnose test application dhcp6r on page 1606](#)
- [diagnose test application dhcprelay on page 1606](#)
- [diagnose test application dlpfingerprint on page 1607](#)
- [diagnose test application dlpfpcache on page 1607](#)
- [diagnose test application dnsproxy on page 1607](#)

- [diagnose test application dsd on page 1607](#)
- [diagnose test application eap_supp on page 1608](#)
- [diagnose test application fas on page 1608](#)
- [diagnose test application fcnacd on page 1608](#)
- [diagnose test application fds_notify on page 1608](#)
- [diagnose test application fgtlogd on page 1608](#)
- [diagnose test application fnbamd on page 1609](#)
- [diagnose test application forticldd on page 1609](#)
- [diagnose test application forticron on page 1609](#)
- [diagnose test application fsd on page 1609](#)
- [diagnose test application fsvrd on page 1610](#)
- [diagnose test application gcpcd on page 1610](#)
- [diagnose test application harelay on page 1610](#)
- [diagnose test application hasync on page 1610](#)
- [diagnose test application hataik on page 1611](#)
- [diagnose test application ibmd on page 1611](#)
- [diagnose test application imap on page 1611](#)
- [diagnose test application init on page 1611](#)
- [diagnose test application iotd on page 1611](#)
- [diagnose test application ipamd on page 1612](#)
- [diagnose test application ipamsd on page 1612](#)
- [diagnose test application ipldbd on page 1612](#)
- [diagnose test application ipsengine on page 1612](#)
- [diagnose test application ipsmonitor on page 1613](#)
- [diagnose test application ipsufd on page 1613](#)
- [diagnose test application kubed on page 1613](#)
- [diagnose test application l2tpcd on page 1613](#)
- [diagnose test application lnkmtcd on page 1614](#)
- [diagnose test application locallogd on page 1614](#)
- [diagnose test application miglogd on page 1614](#)
- [diagnose test application mrd on page 1614](#)
- [diagnose test application netxd on page 1615](#)
- [diagnose test application nntp on page 1615](#)
- [diagnose test application ocid on page 1615](#)
- [diagnose test application openstackd on page 1615](#)
- [diagnose test application ovrd on page 1615](#)
- [diagnose test application pop3 on page 1616](#)
- [diagnose test application pptpcd on page 1616](#)
- [diagnose test application quarantined on page 1616](#)
- [diagnose test application radius-das on page 1616](#)
- [diagnose test application radiusd on page 1617](#)
- [diagnose test application radvd on page 1617](#)
- [diagnose test application reportd on page 1617](#)

- [diagnose test application rt_router on page 1617](#)
- [diagnose test application sdncd on page 1618](#)
- [diagnose test application sdnd on page 1618](#)
- [diagnose test application sepmc on page 1618](#)
- [diagnose test application sessionsync on page 1618](#)
- [diagnose test application sfupgraded on page 1618](#)
- [diagnose test application smtp on page 1619](#)
- [diagnose test application snmpd on page 1619](#)
- [diagnose test application syslogd on page 1619](#)
- [diagnose test application updated on page 1619](#)
- [diagnose test application uploadd on page 1620](#)
- [diagnose test application urlfilter on page 1620](#)
- [diagnose test application vned on page 1620](#)
- [diagnose test application wad on page 1620](#)
- [diagnose test application wccpd on page 1621](#)
- [diagnose test application wf_monitor on page 1621](#)
- [diagnose test application wiredapd on page 1621](#)

diagnose test application acd

Aggregate Controller.

```
diagnose test application acd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application acsd

Ali Cloud Service daemon.

```
diagnose test application acsd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application autod

Automation daemon.

```
diagnose test application autod <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application awsd

Amazon Web Services (AWS) daemon.

```
diagnose test application awsd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application azd

Microsoft Azure daemon.

```
diagnose test application azd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application bfd

BFD daemon.

```
diagnose test application bfd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application csfd

Security Fabric daemon.

```
diagnose test application csfd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application ddnsd

DDNS client daemon.

```
diagnose test application ddnsd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application dhcp6c

DHCP6 client daemon.

```
diagnose test application dhcp6c <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application dhcp6r

DHCP6 relay daemon.

```
diagnose test application dhcp6r <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application dhcprelay

DHCP relay daemon.

```
diagnose test application dhcprelay <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application dlpfingerprint

DLP fingerprint daemon.

```
diagnose test application dlpfingerprint <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application dlpfpcache

DLP fingerprint cache daemon.

```
diagnose test application dlpfpcache <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application dnsproxy

DNS proxy.

```
diagnose test application dnsproxy <Integer> <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	
<Integer>	Daemon index.	string	

diagnose test application dsd

DLP Statistics daemon.

```
diagnose test application dsd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application eap_supp

EAP Supplicant daemon.

```
diagnose test application eap_supp <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application fas

FortiToken Cloud daemon.

```
diagnose test application fas <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application fcnacd

FortiClient NAC daemon.

```
diagnose test application fcnacd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application fds_notify

Update Notification daemon.

```
diagnose test application fds_notify <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application fgtlogd

Fgtlog daemon.


```
diagnose test application fgtlogd <Integer> <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	
<Integer>	Daemon index.	string	

diagnose test application fnbamd

Fortiproxy non-blocking auth daemon.

```
diagnose test application fnbamd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application forticldd

FortiCloud daemon.

```
diagnose test application forticldd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application forticron

Forticron daemon.

```
diagnose test application forticron <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application fsd

FortiExplorer daemon.

```
diagnose test application fsd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application fsvrd

FortiService daemon.

```
diagnose test application fsvrd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application gcpd

Google Cloud Platform (GCP) daemon.

```
diagnose test application gcpd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application harelay

HA relay daemon.

```
diagnose test application harelay <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application hasync

HA sync daemon.

```
diagnose test application hasync <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application hataalk

HA talk daemon.

```
diagnose test application hataalk <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application ibmd

IBM Cloud Infrastructure daemon.

```
diagnose test application ibmd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application imap

IMAP proxy.

```
diagnose test application imap <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application init

init process.

```
diagnose test application init <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application iotd

IoT device info daemon.

```
diagnose test application iotd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application ipamd

IP Address Management daemon.

```
diagnose test application ipamd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application ipamsd

IPAM server daemon.

```
diagnose test application ipamsd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application ipldbd

IP load balancing daemon.

```
diagnose test application ipldbd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application ipsengine

IPS sensor.

```
diagnose test application ipsengine <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application ipsmonitor

IPS monitor.

```
diagnose test application ipsmonitor <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application ipsufd

IPS urlfilter daemon.

```
diagnose test application ipsufd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application kubed

Kubernetes daemon.

```
diagnose test application kubed <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application l2tpcd

L2TP client daemon.

```
diagnose test application l2tpcd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application lnkmtd

Link monitor daemon.

```
diagnose test application lnkmtd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application locallogd

Locallogd daemon.

```
diagnose test application locallogd <Integer> <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	
<Integer>	Daemon index.	string	

diagnose test application miglogd

Miglog logging daemon.

```
diagnose test application miglogd <Integer> <Integer> <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	
<Integer>	Daemon index.	string	
<Integer>	test level 26: 255 for all miglogds test level 31: 0 -- summary only, 1 -- each log summary, 2 -- log details	string	

diagnose test application mrd

Mobile router daemon.

```
diagnose test application mrd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application netxd

VMWare NetX service manager daemon.

```
diagnose test application netxd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application nntp

NNTP proxy.

```
diagnose test application nntp <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application ocid

Oracle Cloud Infrastructure.

```
diagnose test application ocid <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application openstackd

OpenStack SDN connector daemon.

```
diagnose test application openstackd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application ovrd

Override daemon.

```
diagnose test application ovrd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application pop3

POP3 proxy.

```
diagnose test application pop3 <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application pptpcd

PPTP client.

```
diagnose test application pptpcd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application quarantined

Quarantine daemon.

```
diagnose test application quarantined <Integer> <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	
<Integer>	Daemon index.	string	

diagnose test application radius-das

Radius-das daemon.

```
diagnose test application radius-das <Integer>
```


Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application radiusd

RADIUS daemon.

```
diagnose test application radiusd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application radvd

radvd daemon.

```
diagnose test application radvd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application reportd

Report daemon.

```
diagnose test application reportd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application rt_router

Router daemon

```
diagnose test application rt_router <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application sdncd

SDN Connector daemon.

```
diagnose test application sdncd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application sdnd

SDN connector daemon.

```
diagnose test application sdnd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application sepmd

Symantec Endpoint Protection Manager daemon.

```
diagnose test application sepmd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application sessionsync

Session sync daemon.

```
diagnose test application sessionsync <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application sfupgraded

Security Fabric Upgrade daemon.

```
diagnose test application sfupgraded <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application smtp

SMTP proxy.

```
diagnose test application smtp <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application snmpd

SNMP daemon.

```
diagnose test application snmpd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application syslogd

Syslog daemon.

```
diagnose test application syslogd <Integer> <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	
<Integer>	Daemon index.	string	

diagnose test application updated

Update daemon.

```
diagnose test application updated <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application uploadd

Upload daemon.

```
diagnose test application uploadd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application urlfilter

URL filter daemon.

```
diagnose test application urlfilter <Integer> <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	
<Integer>	Daemon index.	string	

diagnose test application vned

Virtual network enabler daemon.

```
diagnose test application vned <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application wad

WAD related processes.

```
diagnose test application wad <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application wccpd

WCCP daemon.

```
diagnose test application wccpd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application wf_monitor

WF monitor.

```
diagnose test application wf_monitor <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test application wiredapd

Wiredapd daemon.

```
diagnose test application wiredapd <Integer>
```

Parameter	Description	Type	Size
<Integer>	Test level.	string	

diagnose test authserver

Test authentication server.

This topic includes the following commands:

- [diagnose test authserver cert on page 1622](#)
- [diagnose test authserver ext-idp on page 1622](#)

- [diagnose test authserver ldap on page 1622](#)
- [diagnose test authserver ldap-digest on page 1622](#)
- [diagnose test authserver ldap-direct on page 1622](#)
- [diagnose test authserver ldap-search on page 1623](#)
- [diagnose test authserver local on page 1623](#)
- [diagnose test authserver pop3 on page 1623](#)
- [diagnose test authserver radius on page 1623](#)
- [diagnose test authserver radius-direct on page 1623](#)
- [diagnose test authserver tacacs+ on page 1623](#)
- [diagnose test authserver tacacs+-direct on page 1624](#)
- [diagnose test authserver user on page 1624](#)

diagnose test authserver cert

Test certificate authentication.

```
diagnose test authserver cert
```

diagnose test authserver ext-idp

Test external identity provider.

```
diagnose test authserver ext-idp
```

diagnose test authserver ldap

Test LDAP server.

```
diagnose test authserver ldap
```

diagnose test authserver ldap-digest

Test LDAP HA1 password query.

```
diagnose test authserver ldap-digest
```

diagnose test authserver ldap-direct

Test LDAP server directly.

```
diagnose test authserver ldap-direct
```

diagnose test authserver ldap-search

Search LDAP server.

```
diagnose test authserver ldap-search
```

diagnose test authserver local

Test local user.

```
diagnose test authserver local
```

diagnose test authserver pop3

Test POP3 server.

```
diagnose test authserver pop3
```

diagnose test authserver radius

Test RADIUS server.

```
diagnose test authserver radius
```

diagnose test authserver radius-direct

Test RADIUS server directly.

```
diagnose test authserver radius-direct
```

diagnose test authserver tacacs+

test TACACS+ server.

```
diagnose test authserver tacacs+
```

diagnose test authserver tacacs+-direct

Test TACACS+ server directly.

```
diagnose test authserver tacacs+-direct
```

diagnose test authserver user

Test user with group/user ID/name(s).

```
diagnose test authserver user
```

diagnose test guest

Guest user add/delete/list.

This topic includes the following commands:

- [diagnose test guest add on page 1624](#)
- [diagnose test guest del on page 1624](#)
- [diagnose test guest list on page 1624](#)

diagnose test guest add

Add a guest user.

```
diagnose test guest add
```

diagnose test guest del

Delete guest users.

```
diagnose test guest del
```

diagnose test guest list

List guest users.

```
diagnose test guest list
```


diagnose test update

Update daemon test.

This topic includes the following commands:

- [diagnose test update info on page 1625](#)

diagnose test update info

Display debug info.

```
diagnose test update info
```

diagnose traffictest

Offloading traffic test using internal TX/RX

This topic includes the following commands:

- [diagnose traffictest client-intf on page 1625](#)
- [diagnose traffictest port on page 1626](#)
- [diagnose traffictest proto on page 1626](#)
- [diagnose traffictest proto 0 on page 1626](#)
- [diagnose traffictest proto 1 on page 1626](#)
- [diagnose traffictest run on page 1626](#)
- [diagnose traffictest server-intf on page 1627](#)
- [diagnose traffictest show on page 1627](#)

diagnose traffictest client-intf

Client interface.

```
diagnose traffictest client-intf <string>
```

Parameter	Description	Type	Size
<string>	Interface name	string	

diagnose traffictest port

TCP or UDP port number (1 - 65535).

```
diagnose traffictest port <port>
```

Parameter	Description	Type	Size
<port>	Port number	string	

diagnose traffictest proto

0 for TCP or 1 for UDP (default = 0).

```
diagnose traffictest proto
```

diagnose traffictest proto 0

TCP

```
diagnose traffictest proto 0
```

diagnose traffictest proto 1

UDP

```
diagnose traffictest proto 1
```

diagnose traffictest run

Start traffic.

```
diagnose traffictest run [-h/arg] [arg] [arg] [arg] [arg] [arg] [arg] [arg] [arg] [arg] [arg] [arg] [arg] [arg] [arg] [arg] [arg] [arg] [arg] [arg]
```

Parameter	Description	Type	Size
[-h/arg]	Help/Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	

Parameter	Description	Type	Size
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	
[arg]	Multi-Arguments for client	string	

diagnose traffictest server-intf

Server interface.

```
diagnose traffictest server-intf <string>
```

Parameter	Description	Type	Size
<string>	Interface name	string	

diagnose traffictest show

Traffic settings show

```
diagnose traffictest show
```

diagnose user

User

This topic includes the following commands:

- [diagnose user banned-ip on page 1629](#)
- [diagnose user banned-ip add on page 1629](#)
- [diagnose user banned-ip add src4 on page 1629](#)
- [diagnose user banned-ip add src6 on page 1629](#)
- [diagnose user banned-ip clear on page 1630](#)
- [diagnose user banned-ip delete on page 1630](#)
- [diagnose user banned-ip delete src4 on page 1630](#)
- [diagnose user banned-ip delete src6 on page 1630](#)
- [diagnose user banned-ip list on page 1630](#)
- [diagnose user banned-ip list all on page 1631](#)
- [diagnose user banned-ip list src4 on page 1631](#)
- [diagnose user banned-ip list src6 on page 1631](#)
- [diagnose user banned-ip stat on page 1631](#)
- [diagnose user device on page 1631](#)
- [diagnose user device clear on page 1631](#)
- [diagnose user device del on page 1632](#)
- [diagnose user device filter on page 1632](#)
- [diagnose user device filter addr on page 1632](#)
- [diagnose user device filter clear on page 1632](#)
- [diagnose user device filter clear addr on page 1632](#)
- [diagnose user device filter clear generation on page 1633](#)
- [diagnose user device filter clear index on page 1633](#)
- [diagnose user device filter clear joined on page 1633](#)
- [diagnose user device filter clear vd on page 1633](#)
- [diagnose user device filter generation on page 1633](#)
- [diagnose user device filter joined on page 1633](#)
- [diagnose user device filter list on page 1634](#)
- [diagnose user device filter negate on page 1634](#)
- [diagnose user device filter negate addr on page 1634](#)
- [diagnose user device filter negate generation on page 1634](#)
- [diagnose user device filter negate index on page 1634](#)
- [diagnose user device filter negate joined on page 1634](#)
- [diagnose user device filter negate vd on page 1635](#)
- [diagnose user device filter vd on page 1635](#)
- [diagnose user device get on page 1635](#)
- [diagnose user device list on page 1635](#)
- [diagnose user device stats on page 1635](#)

diagnose user banned-ip

Banned IP addresses.

```
diagnose user banned-ip
```

diagnose user banned-ip add

Add banned IP address.

```
diagnose user banned-ip add
```

diagnose user banned-ip add src4

IPv4 source ban.

```
diagnose user banned-ip add src4 <src-ipv4> <expiry> <ban-source>
```

Parameter	Description	Type	Size
<src-ipv4>	Source IPv4 address.	string	
<expiry>	Expiry in seconds.	string	
<ban-source>	Ban source (admin/dlp/ips/av/dos/app).	string	

diagnose user banned-ip add src6

IPv6 source ban.

```
diagnose user banned-ip add src6 <src-ipv6> <expiry> <ban-source>
```

Parameter	Description	Type	Size
<src-ipv6>	Source IPv6 address.	string	
<expiry>	Expiry in seconds.	string	
<ban-source>	Ban source (admin/dlp/ips/av/dos/app).	string	

diagnose user banned-ip clear

Clear all banned IP addresses.

```
diagnose user banned-ip clear
```

diagnose user banned-ip delete

Delete banned IP address.

```
diagnose user banned-ip delete
```

diagnose user banned-ip delete src4

IPv4 source ban.

```
diagnose user banned-ip delete src4 <src-ipv4>
```

Parameter	Description	Type	Size
<src-ipv4>	Source IPv4 address.	string	

diagnose user banned-ip delete src6

IPv6 source ban.

```
diagnose user banned-ip delete src6 <src-ipv6>
```

Parameter	Description	Type	Size
<src-ipv6>	Source IPv6 address.	string	

diagnose user banned-ip list

List banned IPs.

```
diagnose user banned-ip list
```

diagnose user banned-ip list all

List all bans.

```
diagnose user banned-ip list all
```

diagnose user banned-ip list src4

IPv4 source ban.

```
diagnose user banned-ip list src4
```

diagnose user banned-ip list src6

IPv6 source ban.

```
diagnose user banned-ip list src6
```

diagnose user banned-ip stat

stat

```
diagnose user banned-ip stat
```

diagnose user device

User devices.

```
diagnose user device
```

diagnose user device clear

Clear discovered hosts.

```
diagnose user device clear
```

diagnose user device del

Remove a specific host.

```
diagnose user device del <mac>
```

Parameter	Description	Type	Size
<mac>	MAC address (xx:xx:xx:xx:xx:xx).	string	

diagnose user device filter

Filter for various src-vis diagnostics.

```
diagnose user device filter
```

diagnose user device filter addr

IPv4 address range.

```
diagnose user device filter addr <from> <to>
```

Parameter	Description	Type	Size
<from>	IPv4 address range.	string	
<to>	IPv4 address range.	string	

diagnose user device filter clear

Clear the filter or parameter.

```
diagnose user device filter clear
```

diagnose user device filter clear addr

Clear parameter.

```
diagnose user device filter clear addr
```


diagnose user device filter clear generation

Clear parameter.

```
diagnose user device filter clear generation
```

diagnose user device filter clear index

Clear parameter.

```
diagnose user device filter clear index
```

diagnose user device filter clear joined

Clear parameter.

```
diagnose user device filter clear joined
```

diagnose user device filter clear vd

Clear parameter.

```
diagnose user device filter clear vd
```

diagnose user device filter generation

Device generation.

```
diagnose user device filter generation <from> <to>
```

Parameter	Description	Type	Size
<from>	<from>	string	
<to>	<to>	string	

diagnose user device filter joined

Device is joined to another.

```
diagnose user device filter joined <value>
```

Parameter	Description	Type	Size
<value>	<value>	string	

diagnose user device filter list

Display the current filter.

```
diagnose user device filter list
```

diagnose user device filter negate

Negate the specified filter parameter.

```
diagnose user device filter negate
```

diagnose user device filter negate addr

Negate parameter.

```
diagnose user device filter negate addr
```

diagnose user device filter negate generation

Negate parameter.

```
diagnose user device filter negate generation
```

diagnose user device filter negate index

Negate parameter.

```
diagnose user device filter negate index
```

diagnose user device filter negate joined

Negate parameter.

```
diagnose user device filter negate joined
```

diagnose user device filter negate vd

Negate parameter.

```
diagnose user device filter negate vd
```

diagnose user device filter vd

Index of virtual domain.

```
diagnose user device filter vd <index>
```

Parameter	Description	Type	Size
<index>	Index of virtual domain.	string	

diagnose user device get

List a specific host.

```
diagnose user device get <mac>
```

Parameter	Description	Type	Size
<mac>	MAC address (xx:xx:xx:xx:xx:xx).	string	

diagnose user device list

List known hosts.

```
diagnose user device list
```

diagnose user device stats

User device stats.

```
diagnose user device stats
```

diagnose user-device-store

User device store diagnostics.

This topic includes the following commands:

- [diagnose user-device-store device on page 1637](#)
- [diagnose user-device-store device memory on page 1637](#)
- [diagnose user-device-store device memory list on page 1637](#)
- [diagnose user-device-store device memory ot-purdue-set on page 1637](#)
- [diagnose user-device-store device memory query on page 1637](#)
- [diagnose user-device-store device memory uid on page 1638](#)
- [diagnose user-device-store device memory uid add on page 1638](#)
- [diagnose user-device-store device memory uid delete on page 1638](#)
- [diagnose user-device-store device memory uid update on page 1638](#)
- [diagnose user-device-store device memory vulnerability-fetch on page 1638](#)
- [diagnose user-device-store iot-vuln on page 1638](#)
- [diagnose user-device-store iot-vuln list on page 1639](#)
- [diagnose user-device-store iot-vuln query on page 1639](#)
- [diagnose user-device-store unified on page 1639](#)
- [diagnose user-device-store unified clear on page 1639](#)
- [diagnose user-device-store unified debug on page 1639](#)
- [diagnose user-device-store unified debug disable on page 1639](#)
- [diagnose user-device-store unified debug enable on page 1640](#)
- [diagnose user-device-store unified delete on page 1640](#)
- [diagnose user-device-store unified device-memory-query on page 1640](#)
- [diagnose user-device-store unified device-memory-query filters-and on page 1640](#)
- [diagnose user-device-store unified device-memory-query filters-or on page 1640](#)
- [diagnose user-device-store unified device-query on page 1640](#)
- [diagnose user-device-store unified device-query filters-and on page 1641](#)
- [diagnose user-device-store unified device-query filters-or on page 1641](#)
- [diagnose user-device-store unified dump on page 1641](#)
- [diagnose user-device-store unified list on page 1641](#)
- [diagnose user-device-store unified re-query on page 1641](#)
- [diagnose user-device-store unified stats on page 1641](#)
- [diagnose user-device-store unified user-memory-query on page 1642](#)
- [diagnose user-device-store unified user-memory-query filters-and on page 1642](#)
- [diagnose user-device-store unified user-memory-query filters-or on page 1642](#)
- [diagnose user-device-store unified user-query on page 1642](#)
- [diagnose user-device-store unified user-query filters-and on page 1642](#)
- [diagnose user-device-store unified user-query filters-or on page 1642](#)
- [diagnose user-device-store user on page 1643](#)
- [diagnose user-device-store user memory on page 1643](#)

- [diagnose user-device-store user memory list on page 1643](#)
- [diagnose user-device-store user memory query on page 1643](#)
- [diagnose user-device-store user-count on page 1643](#)
- [diagnose user-device-store user-count list on page 1643](#)
- [diagnose user-device-store user-count query on page 1644](#)
- [diagnose user-device-store user-stats on page 1644](#)
- [diagnose user-device-store user-stats query on page 1644](#)

diagnose user-device-store device

Device sessions info.

```
diagnose user-device-store device
```

diagnose user-device-store device memory

In memory sessions info.

```
diagnose user-device-store device memory
```

diagnose user-device-store device memory list

List all records.

```
diagnose user-device-store device memory list
```

diagnose user-device-store device memory ot-purdue-set

OT purdue level set.

```
diagnose user-device-store device memory ot-purdue-set
```

diagnose user-device-store device memory query

Query by <type> <op> <value1|value2|...

```
diagnose user-device-store device memory query
```

diagnose user-device-store device memory uid

In memory devices info with UID present.

```
diagnose user-device-store device memory uid
```

diagnose user-device-store device memory uid add

Test add UID devices by <count>.

```
diagnose user-device-store device memory uid add
```

diagnose user-device-store device memory uid delete

Test delete UID device by <uid> <mac> <ip>.

```
diagnose user-device-store device memory uid delete
```

diagnose user-device-store device memory uid update

Test update UID device by <uid> <tags-value-delimited-by-;>.

```
diagnose user-device-store device memory uid update
```

diagnose user-device-store device memory vulnerability-fetch

Vulnerability info fetch.

```
diagnose user-device-store device memory vulnerability-fetch
```

diagnose user-device-store iot-vuln

IoT Vulnerabilities.

```
diagnose user-device-store iot-vuln
```

diagnose user-device-store iot-vuln list

List all records.

```
diagnose user-device-store iot-vuln list
```

diagnose user-device-store iot-vuln query

Query by <type> <op> <value1|value2|...

```
diagnose user-device-store iot-vuln query
```

diagnose user-device-store unified

Unified queries info.

```
diagnose user-device-store unified
```

diagnose user-device-store unified clear

Delete all unified queries.

```
diagnose user-device-store unified clear
```

diagnose user-device-store unified debug

Enable/Disable debug logs for unified queries.

```
diagnose user-device-store unified debug
```

diagnose user-device-store unified debug disable

Disable debug logs for unified queries.

```
diagnose user-device-store unified debug disable
```

diagnose user-device-store unified debug enable

Enable debug logs for unified queries.

```
diagnose user-device-store unified debug enable
```

diagnose user-device-store unified delete

Delete unified query by <query-id>.

```
diagnose user-device-store unified delete
```

diagnose user-device-store unified device-memory-query

Get Device records along with associated User records from memory.

```
diagnose user-device-store unified device-memory-query
```

diagnose user-device-store unified device-memory-query filters-and

Query by <iteration-count> <type1;op1;values1-delimited-by-|;type2;op2;values2-delimited-by-|...>

```
diagnose user-device-store unified device-memory-query filters-and
```

diagnose user-device-store unified device-memory-query filters-or

Query by <iteration-count> <type1;op1;values1-delimited-by-|;type2;op2;values2-delimited-by-|...>

```
diagnose user-device-store unified device-memory-query filters-or
```

diagnose user-device-store unified device-query

Get Device records along with associated User records from memory and disk.

```
diagnose user-device-store unified device-query
```


diagnose user-device-store unified device-query filters-and

Query by <iteration-count> <start-time> <end-time> <type1;op1;values1-delimited-by-|;type2;op2;values2-delimited-by-|...>

```
diagnose user-device-store unified device-query filters-and
```

diagnose user-device-store unified device-query filters-or

Query by <iteration-count> <start-time> <end-time> <type1;op1;values1-delimited-by-|;type2;op2;values2-delimited-by-|...>

```
diagnose user-device-store unified device-query filters-or
```

diagnose user-device-store unified dump

Dump unified query stats by <query-id>.

```
diagnose user-device-store unified dump
```

diagnose user-device-store unified list

List unified queries.

```
diagnose user-device-store unified list
```

diagnose user-device-store unified re-query

Retrieve Query by <query-id> <iteration-start> <iteration-count>

```
diagnose user-device-store unified re-query
```

diagnose user-device-store unified stats

Get Stats for unified queries.

```
diagnose user-device-store unified stats
```

diagnose user-device-store unified user-memory-query

Get User records along with associated Device records from memory.

```
diagnose user-device-store unified user-memory-query
```

diagnose user-device-store unified user-memory-query filters-and

Query by <iteration-count> <type1;op1;values1-delimited-by-|;type2;op2;values2-delimited-by-|...>

```
diagnose user-device-store unified user-memory-query filters-and
```

diagnose user-device-store unified user-memory-query filters-or

Query by <iteration-count> <type1;op1;values1-delimited-by-|;type2;op2;values2-delimited-by-|...>

```
diagnose user-device-store unified user-memory-query filters-or
```

diagnose user-device-store unified user-query

Get User records along with associated Device records from memory and disk.

```
diagnose user-device-store unified user-query
```

diagnose user-device-store unified user-query filters-and

Query by <iteration-count> <start-time> <end-time> <type1;op1;values1-delimited-by-|;type2;op2;values2-delimited-by-|...>

```
diagnose user-device-store unified user-query filters-and
```

diagnose user-device-store unified user-query filters-or

Query by <iteration-count> <start-time> <end-time> <type1;op1;values1-delimited-by-|;type2;op2;values2-delimited-by-|...>

```
diagnose user-device-store unified user-query filters-or
```

diagnose user-device-store user

User sessions info.

```
diagnose user-device-store user
```

diagnose user-device-store user memory

In memory sessions info.

```
diagnose user-device-store user memory
```

diagnose user-device-store user memory list

List all records.

```
diagnose user-device-store user memory list
```

diagnose user-device-store user memory query

Query by <type> <op> <value1|value2|...>.

```
diagnose user-device-store user memory query
```

diagnose user-device-store user-count

User count info.

```
diagnose user-device-store user-count
```

diagnose user-device-store user-count list

List all group user count records.

```
diagnose user-device-store user-count list
```

diagnose user-device-store user-count query

Query by groupname <value>.

```
diagnose user-device-store user-count query
```

diagnose user-device-store user-stats

User stats.

```
diagnose user-device-store user-stats
```

diagnose user-device-store user-stats query

Query by <yyyy-mm-dd> <time-range days>

```
diagnose user-device-store user-stats query
```

diagnose vendor-mac

Vendor MAC Database.

This topic includes the following commands:

- [diagnose vendor-mac id on page 1644](#)
- [diagnose vendor-mac id-summary on page 1645](#)
- [diagnose vendor-mac info on page 1645](#)
- [diagnose vendor-mac match on page 1645](#)

diagnose vendor-mac id

Vendor MAC ID.

```
diagnose vendor-mac id <id>
```

Parameter	Description	Type	Size
<id>	Vendor MAC ID (a nonzero integer).	string	

diagnose vendor-mac id-summary

Vendor MAC ID summary.

```
diagnose vendor-mac id-summary <id>
```

Parameter	Description	Type	Size
<id>	Vendor MAC ID (a nonzero integer).	string	

diagnose vendor-mac info

MAC Address information.

```
diagnose vendor-mac info <xx:xx:xx:xx:xx:xx>
```

Parameter	Description	Type	Size
<xx:xx:xx:xx:xx:xx>	Service MAC address.	string	

diagnose vendor-mac match

Find Vendor MAC for a specific MAC address and mask.

```
diagnose vendor-mac match <xx:xx:xx:xx:xx:xx> <mask>
```

Parameter	Description	Type	Size
<xx:xx:xx:xx:xx:xx>	MAC address.	string	
<mask>	mask (0 - 48).	string	

diagnose vmware

VMWare platform diagnose commands.

This topic includes the following commands:

- [diagnose vmware ovfenv on page 1646](#)

diagnose vmware ovfenv

Display OVF environment information.

```
diagnose vmware ovfenv
```

diagnose vpn ssl

SSL-VPN.

```
diagnose vpn ssl
```

diagnose wacs

Web cache DB daemon.

This topic includes the following commands:

- [diagnose wacs clear on page 1646](#)
- [diagnose wacs restart on page 1646](#)
- [diagnose wacs stats on page 1646](#)

diagnose wacs clear

Remove all entries from the database.

```
diagnose wacs clear
```

diagnose wacs restart

Restart the daemon and reset the statistical parameters.

```
diagnose wacs restart
```

diagnose wacs stats

Show statistics.

```
diagnose wacs stats
```

diagnose wad

WAD diagnostics.

This topic includes the following commands:

- [diagnose wad access-proxy on page 1659](#)
- [diagnose wad access-proxy health-check on page 1659](#)
- [diagnose wad access-proxy health-check status on page 1659](#)
- [diagnose wad console-log on page 1659](#)
- [diagnose wad console-log disable on page 1659](#)
- [diagnose wad console-log enable on page 1659](#)
- [diagnose wad csvc on page 1660](#)
- [diagnose wad csvc bytcache on page 1660](#)
- [diagnose wad csvc bytcache clear on page 1660](#)
- [diagnose wad csvc bytcache flush on page 1660](#)
- [diagnose wad csvc bytcache lists on page 1660](#)
- [diagnose wad csvc bytcache stats on page 1661](#)
- [diagnose wad csvc memcache on page 1661](#)
- [diagnose wad csvc memcache clear on page 1661](#)
- [diagnose wad csvc memcache flush on page 1661](#)
- [diagnose wad csvc memcache lists on page 1661](#)
- [diagnose wad csvc memcache stats on page 1662](#)
- [diagnose wad csvc restart on page 1662](#)
- [diagnose wad csvc webcache on page 1662](#)
- [diagnose wad csvc webcache clear on page 1662](#)
- [diagnose wad csvc webcache flush on page 1663](#)
- [diagnose wad csvc webcache lists on page 1663](#)
- [diagnose wad csvc webcache stats on page 1663](#)
- [diagnose wad debug on page 1663](#)
- [diagnose wad debug clear on page 1663](#)
- [diagnose wad debug crash on page 1664](#)
- [diagnose wad debug crash clear on page 1664](#)
- [diagnose wad debug crash disable on page 1664](#)
- [diagnose wad debug crash enable on page 1664](#)
- [diagnose wad debug crash list on page 1664](#)
- [diagnose wad debug crash max on page 1664](#)
- [diagnose wad debug crash read on page 1665](#)
- [diagnose wad debug disable on page 1665](#)
- [diagnose wad debug disable category on page 1665](#)

- [diagnose wad debug disable category aio on page 1665](#)
- [diagnose wad debug disable category antiphish on page 1665](#)
- [diagnose wad debug disable category auth on page 1665](#)
- [diagnose wad debug disable category autotest on page 1666](#)
- [diagnose wad debug disable category bytcache on page 1666](#)
- [diagnose wad debug disable category cache_server on page 1666](#)
- [diagnose wad debug disable category casb on page 1666](#)
- [diagnose wad debug disable category cifs on page 1666](#)
- [diagnose wad debug disable category config on page 1666](#)
- [diagnose wad debug disable category csvc on page 1667](#)
- [diagnose wad debug disable category detail on page 1667](#)
- [diagnose wad debug disable category devuln on page 1667](#)
- [diagnose wad debug disable category diag on page 1667](#)
- [diagnose wad debug disable category dispatcher on page 1667](#)
- [diagnose wad debug disable category dns on page 1667](#)
- [diagnose wad debug disable category dskd on page 1668](#)
- [diagnose wad debug disable category extension on page 1668](#)
- [diagnose wad debug disable category ftp on page 1668](#)
- [diagnose wad debug disable category http on page 1668](#)
- [diagnose wad debug disable category http2 on page 1668](#)
- [diagnose wad debug disable category http3 on page 1668](#)
- [diagnose wad debug disable category icap on page 1669](#)
- [diagnose wad debug disable category icap_server on page 1669](#)
- [diagnose wad debug disable category icbsvc on page 1669](#)
- [diagnose wad debug disable category info on page 1669](#)
- [diagnose wad debug disable category ips on page 1669](#)
- [diagnose wad debug disable category isolator on page 1669](#)
- [diagnose wad debug disable category license on page 1670](#)
- [diagnose wad debug disable category mapi on page 1670](#)
- [diagnose wad debug disable category memblk on page 1670](#)
- [diagnose wad debug disable category monitor on page 1670](#)
- [diagnose wad debug disable category packet on page 1670](#)
- [diagnose wad debug disable category policy on page 1670](#)
- [diagnose wad debug disable category policy_test on page 1671](#)
- [diagnose wad debug disable category proc on page 1671](#)
- [diagnose wad debug disable category quic on page 1671](#)
- [diagnose wad debug disable category quic_cc on page 1671](#)
- [diagnose wad debug disable category rpc on page 1671](#)
- [diagnose wad debug disable category scan on page 1671](#)
- [diagnose wad debug disable category scp on page 1672](#)
- [diagnose wad debug disable category session on page 1672](#)
- [diagnose wad debug disable category sftp on page 1672](#)
- [diagnose wad debug disable category socks on page 1672](#)

- [diagnose wad debug disable category ssh on page 1672](#)
- [diagnose wad debug disable category ssl on page 1672](#)
- [diagnose wad debug disable category sys on page 1673](#)
- [diagnose wad debug disable category tls_fingerprint on page 1673](#)
- [diagnose wad debug disable category tunnel on page 1673](#)
- [diagnose wad debug disable category uih on page 1673](#)
- [diagnose wad debug disable category video on page 1673](#)
- [diagnose wad debug disable category vs on page 1673](#)
- [diagnose wad debug disable category waf on page 1674](#)
- [diagnose wad debug disable category webcache on page 1674](#)
- [diagnose wad debug display on page 1674](#)
- [diagnose wad debug display pid on page 1674](#)
- [diagnose wad debug display pid disable on page 1674](#)
- [diagnose wad debug display pid enable on page 1674](#)
- [diagnose wad debug enable on page 1675](#)
- [diagnose wad debug enable all on page 1675](#)
- [diagnose wad debug enable category on page 1675](#)
- [diagnose wad debug enable category aio on page 1675](#)
- [diagnose wad debug enable category all on page 1675](#)
- [diagnose wad debug enable category antiphish on page 1675](#)
- [diagnose wad debug enable category auth on page 1676](#)
- [diagnose wad debug enable category autotest on page 1676](#)
- [diagnose wad debug enable category bytcache on page 1676](#)
- [diagnose wad debug enable category cache_server on page 1676](#)
- [diagnose wad debug enable category casb on page 1676](#)
- [diagnose wad debug enable category cifs on page 1676](#)
- [diagnose wad debug enable category config on page 1677](#)
- [diagnose wad debug enable category csvc on page 1677](#)
- [diagnose wad debug enable category detail on page 1677](#)
- [diagnose wad debug enable category devuln on page 1677](#)
- [diagnose wad debug enable category diag on page 1677](#)
- [diagnose wad debug enable category dispatcher on page 1677](#)
- [diagnose wad debug enable category dns on page 1678](#)
- [diagnose wad debug enable category dskd on page 1678](#)
- [diagnose wad debug enable category extension on page 1678](#)
- [diagnose wad debug enable category ftp on page 1678](#)
- [diagnose wad debug enable category http on page 1678](#)
- [diagnose wad debug enable category http2 on page 1678](#)
- [diagnose wad debug enable category http3 on page 1679](#)
- [diagnose wad debug enable category icap on page 1679](#)
- [diagnose wad debug enable category icap_server on page 1679](#)
- [diagnose wad debug enable category icbsvc on page 1679](#)
- [diagnose wad debug enable category info on page 1679](#)

- [diagnose wad debug enable category ips on page 1679](#)
- [diagnose wad debug enable category isolator on page 1680](#)
- [diagnose wad debug enable category license on page 1680](#)
- [diagnose wad debug enable category mapi on page 1680](#)
- [diagnose wad debug enable category memblk on page 1680](#)
- [diagnose wad debug enable category monitor on page 1680](#)
- [diagnose wad debug enable category packet on page 1680](#)
- [diagnose wad debug enable category policy on page 1681](#)
- [diagnose wad debug enable category policy_test on page 1681](#)
- [diagnose wad debug enable category proc on page 1681](#)
- [diagnose wad debug enable category quic on page 1681](#)
- [diagnose wad debug enable category quic_cc on page 1681](#)
- [diagnose wad debug enable category rpc on page 1681](#)
- [diagnose wad debug enable category scan on page 1682](#)
- [diagnose wad debug enable category scp on page 1682](#)
- [diagnose wad debug enable category session on page 1682](#)
- [diagnose wad debug enable category sftp on page 1682](#)
- [diagnose wad debug enable category socks on page 1682](#)
- [diagnose wad debug enable category ssh on page 1682](#)
- [diagnose wad debug enable category ssl on page 1683](#)
- [diagnose wad debug enable category sys on page 1683](#)
- [diagnose wad debug enable category tls_fingerprint on page 1683](#)
- [diagnose wad debug enable category tunnel on page 1683](#)
- [diagnose wad debug enable category uih on page 1683](#)
- [diagnose wad debug enable category video on page 1683](#)
- [diagnose wad debug enable category vs on page 1684](#)
- [diagnose wad debug enable category waf on page 1684](#)
- [diagnose wad debug enable category webcache on page 1684](#)
- [diagnose wad debug enable level on page 1684](#)
- [diagnose wad debug enable level error on page 1684](#)
- [diagnose wad debug enable level info on page 1684](#)
- [diagnose wad debug enable level verbose on page 1685](#)
- [diagnose wad debug enable level warn on page 1685](#)
- [diagnose wad debug ips-db on page 1685](#)
- [diagnose wad debug ips-db status on page 1685](#)
- [diagnose wad debug save-http-req-crash on page 1685](#)
- [diagnose wad debug save-http-req-crash disable on page 1685](#)
- [diagnose wad debug save-http-req-crash enable on page 1686](#)
- [diagnose wad debug show on page 1686](#)
- [diagnose wad dev on page 1686](#)
- [diagnose wad dev fcnacd on page 1686](#)
- [diagnose wad dev fcnacd delete on page 1686](#)
- [diagnose wad dev fcnacd ip-err on page 1686](#)

- [diagnose wad dev fcnacd uid-err on page 1687](#)
- [diagnose wad dev fcnacd update on page 1687](#)
- [diagnose wad dev query-by on page 1687](#)
- [diagnose wad dev query-by ipv4 on page 1687](#)
- [diagnose wad dev query-by ipv6 on page 1687](#)
- [diagnose wad dev query-by uid on page 1687](#)
- [diagnose wad dev-vuln on page 1688](#)
- [diagnose wad dev-vuln query on page 1688](#)
- [diagnose wad dev-vuln query-by-id on page 1688](#)
- [diagnose wad dev-vuln query-ftgd on page 1688](#)
- [diagnose wad dynamic-bypass on page 1688](#)
- [diagnose wad dynamic-bypass clear on page 1688](#)
- [diagnose wad dynamic-bypass flush on page 1689](#)
- [diagnose wad dynamic-bypass show on page 1689](#)
- [diagnose wad exp-fw-policy-test on page 1689](#)
- [diagnose wad exp-fw-policy-test-save on page 1689](#)
- [diagnose wad filter on page 1690](#)
- [diagnose wad filter clear on page 1690](#)
- [diagnose wad filter dport on page 1690](#)
- [diagnose wad filter drop-unknown-session on page 1690](#)
- [diagnose wad filter dst on page 1691](#)
- [diagnose wad filter dst6 on page 1691](#)
- [diagnose wad filter explicit-policy on page 1691](#)
- [diagnose wad filter firewall-policy on page 1692](#)
- [diagnose wad filter list on page 1692](#)
- [diagnose wad filter negate on page 1692](#)
- [diagnose wad filter process-id on page 1692](#)
- [diagnose wad filter process-id-by-src on page 1692](#)
- [diagnose wad filter process-type on page 1693](#)
- [diagnose wad filter protocol on page 1693](#)
- [diagnose wad filter proxy-policy-list-increment on page 1693](#)
- [diagnose wad filter sport on page 1694](#)
- [diagnose wad filter src on page 1694](#)
- [diagnose wad filter src6 on page 1694](#)
- [diagnose wad filter vd on page 1695](#)
- [diagnose wad fw-policy-test-get on page 1695](#)
- [diagnose wad health on page 1695](#)
- [diagnose wad health debug on page 1695](#)
- [diagnose wad health fs on page 1695](#)
- [diagnose wad health worker on page 1696](#)
- [diagnose wad history on page 1696](#)
- [diagnose wad history clear on page 1696](#)
- [diagnose wad history list on page 1696](#)

- [diagnose wad icap on page 1696](#)
- [diagnose wad icap list on page 1696](#)
- [diagnose wad kxp on page 1697](#)
- [diagnose wad kxp clear on page 1697](#)
- [diagnose wad kxp list on page 1697](#)
- [diagnose wad license on page 1697](#)
- [diagnose wad license clear on page 1697](#)
- [diagnose wad license detail on page 1697](#)
- [diagnose wad license glob-usage on page 1698](#)
- [diagnose wad license summary on page 1698](#)
- [diagnose wad license test on page 1698](#)
- [diagnose wad license usage on page 1698](#)
- [diagnose wad memory on page 1698](#)
- [diagnose wad memory monitor on page 1699](#)
- [diagnose wad memory monitor disable on page 1699](#)
- [diagnose wad memory monitor enable on page 1699](#)
- [diagnose wad memory monitor interval on page 1699](#)
- [diagnose wad memory monitor list on page 1699](#)
- [diagnose wad memory monitor max-report-files on page 1699](#)
- [diagnose wad memory monitor mem-threshold-red on page 1700](#)
- [diagnose wad memory overused on page 1700](#)
- [diagnose wad memory report on page 1700](#)
- [diagnose wad memory sum on page 1700](#)
- [diagnose wad memory track on page 1700](#)
- [diagnose wad memory workers on page 1701](#)
- [diagnose wad nbi on page 1701](#)
- [diagnose wad nbi license on page 1701](#)
- [diagnose wad nbi packages on page 1701](#)
- [diagnose wad nbi status on page 1701](#)
- [diagnose wad process on page 1701](#)
- [diagnose wad process YouTube-filter-cache-service on page 1702](#)
- [diagnose wad process algo on page 1704](#)
- [diagnose wad process byte-cache on page 1706](#)
- [diagnose wad process cache-service-cs on page 1708](#)
- [diagnose wad process cache-service-db on page 1710](#)
- [diagnose wad process cert-inspection on page 1712](#)
- [diagnose wad process config-notify on page 1714](#)
- [diagnose wad process debug on page 1716](#)
- [diagnose wad process dev-vuln on page 1718](#)
- [diagnose wad process dispatcher on page 1720](#)
- [diagnose wad process ia-cache on page 1722](#)
- [diagnose wad process informer on page 1724](#)
- [diagnose wad process isolator on page 1726](#)

- [diagnose wad process manager on page 1728](#)
- [diagnose wad process object-cache on page 1730](#)
- [diagnose wad process preload daemon on page 1732](#)
- [diagnose wad process staled-worker on page 1734](#)
- [diagnose wad process tls-fgpt-service on page 1736](#)
- [diagnose wad process traffic aggregator on page 1738](#)
- [diagnose wad process user-info on page 1740](#)
- [diagnose wad process user-info-history on page 1742](#)
- [diagnose wad process worker on page 1744](#)
- [diagnose wad report on page 1746](#)
- [diagnose wad report policy on page 1746](#)
- [diagnose wad report session on page 1746](#)
- [diagnose wad report user on page 1746](#)
- [diagnose wad restore on page 1746](#)
- [diagnose wad restore cdn-rules on page 1746](#)
- [diagnose wad restore cdn-rules all on page 1747](#)
- [diagnose wad session on page 1747](#)
- [diagnose wad session clear on page 1747](#)
- [diagnose wad session count on page 1747](#)
- [diagnose wad session list on page 1747](#)
- [diagnose wad session list-http2 on page 1747](#)
- [diagnose wad sshproxy on page 1748](#)
- [diagnose wad sshproxy clear on page 1748](#)
- [diagnose wad sshproxy list on page 1748](#)
- [diagnose wad stats on page 1748](#)
- [diagnose wad stats algo on page 1748](#)
- [diagnose wad stats algo.antiphish on page 1749](#)
- [diagnose wad stats algo.casb on page 1749](#)
- [diagnose wad stats algo.dev_info on page 1749](#)
- [diagnose wad stats algo.dev_stats on page 1749](#)
- [diagnose wad stats algo.fast_tb on page 1749](#)
- [diagnose wad stats algo.fw_policy on page 1750](#)
- [diagnose wad stats algo.icap_client on page 1750](#)
- [diagnose wad stats algo.inet_app on page 1750](#)
- [diagnose wad stats algo.ips_builder on page 1750](#)
- [diagnose wad stats algo.ipsscan on page 1751](#)
- [diagnose wad stats algo.krl on page 1751](#)
- [diagnose wad stats algo.pattern_match on page 1751](#)
- [diagnose wad stats algo.proc_common on page 1751](#)
- [diagnose wad stats algo.sec_prof on page 1752](#)
- [diagnose wad stats algo.ssl on page 1752](#)
- [diagnose wad stats algo.url_filter on page 1752](#)
- [diagnose wad stats algo.urlredir on page 1752](#)

- [diagnose wad stats algo.wisp on page 1752](#)
- [diagnose wad stats cache_service on page 1753](#)
- [diagnose wad stats cache_service.proc_common on page 1753](#)
- [diagnose wad stats cache_service.tcp on page 1753](#)
- [diagnose wad stats cic on page 1753](#)
- [diagnose wad stats cic.proc_common on page 1754](#)
- [diagnose wad stats cic.ssl_cic on page 1754](#)
- [diagnose wad stats common on page 1754](#)
- [diagnose wad stats config on page 1754](#)
- [diagnose wad stats config.config on page 1755](#)
- [diagnose wad stats config.proc_common on page 1755](#)
- [diagnose wad stats config.shm_stats on page 1755](#)
- [diagnose wad stats config.sscan on page 1755](#)
- [diagnose wad stats debug on page 1755](#)
- [diagnose wad stats debug.crash_handler on page 1756](#)
- [diagnose wad stats debug.proc_common on page 1756](#)
- [diagnose wad stats debug.tls_fgpt_svc_cp on page 1756](#)
- [diagnose wad stats dispatcher on page 1756](#)
- [diagnose wad stats dispatcher.cifs on page 1757](#)
- [diagnose wad stats dispatcher.dns_proxy on page 1757](#)
- [diagnose wad stats dispatcher.http_msg on page 1757](#)
- [diagnose wad stats dispatcher.icap_local_server on page 1757](#)
- [diagnose wad stats dispatcher.llm on page 1758](#)
- [diagnose wad stats dispatcher.proc_common on page 1758](#)
- [diagnose wad stats dispatcher.ssh on page 1758](#)
- [diagnose wad stats dispatcher.tcp on page 1758](#)
- [diagnose wad stats dispatcher.tunnel on page 1758](#)
- [diagnose wad stats fgpt on page 1759](#)
- [diagnose wad stats fgpt.fgpt_self on page 1759](#)
- [diagnose wad stats fgpt.proc_common on page 1759](#)
- [diagnose wad stats fgpt.tls_fgpt_svc_cp on page 1759](#)
- [diagnose wad stats ia_cache on page 1760](#)
- [diagnose wad stats ia_cache.proc_common on page 1760](#)
- [diagnose wad stats informer on page 1760](#)
- [diagnose wad stats informer.dev_info on page 1760](#)
- [diagnose wad stats informer.dev_stats on page 1761](#)
- [diagnose wad stats informer.fsae on page 1761](#)
- [diagnose wad stats informer.informer_dev on page 1761](#)
- [diagnose wad stats informer.informer_self on page 1761](#)
- [diagnose wad stats informer.proc_common on page 1761](#)
- [diagnose wad stats informer.ztna_jwt on page 1762](#)
- [diagnose wad stats isolator on page 1762](#)
- [diagnose wad stats isolator.dns_req on page 1762](#)

- [diagnose wad stats isolator.isolator_self on page 1762](#)
- [diagnose wad stats isolator.proc_common on page 1763](#)
- [diagnose wad stats isolator.ssl on page 1763](#)
- [diagnose wad stats isolator.tcp on page 1763](#)
- [diagnose wad stats mgr on page 1763](#)
- [diagnose wad stats mgr.mgr_self on page 1764](#)
- [diagnose wad stats mgr.proc_common on page 1764](#)
- [diagnose wad stats mgr.shm_stats on page 1764](#)
- [diagnose wad stats uih on page 1764](#)
- [diagnose wad stats uih.proc_common on page 1764](#)
- [diagnose wad stats uih.uih_self on page 1765](#)
- [diagnose wad stats usr_info on page 1765](#)
- [diagnose wad stats usr_info.dev_info on page 1765](#)
- [diagnose wad stats usr_info.dev_stats on page 1765](#)
- [diagnose wad stats usr_info.dns_req on page 1766](#)
- [diagnose wad stats usr_info.ftgd_agent on page 1766](#)
- [diagnose wad stats usr_info.ldap on page 1766](#)
- [diagnose wad stats usr_info.pattern_match on page 1766](#)
- [diagnose wad stats usr_info.proc_common on page 1767](#)
- [diagnose wad stats usr_info.ssl on page 1767](#)
- [diagnose wad stats usr_info.tcp on page 1767](#)
- [diagnose wad stats usr_info.user_device_store on page 1767](#)
- [diagnose wad stats usr_info.usr_info_self on page 1767](#)
- [diagnose wad stats vfcs on page 1768](#)
- [diagnose wad stats vfcs.proc_common on page 1768](#)
- [diagnose wad stats worker on page 1768](#)
- [diagnose wad stats worker.aio on page 1768](#)
- [diagnose wad stats worker.antiphish on page 1769](#)
- [diagnose wad stats worker.app_mgr on page 1769](#)
- [diagnose wad stats worker.auth on page 1769](#)
- [diagnose wad stats worker.auth_rule on page 1769](#)
- [diagnose wad stats worker.auth_user on page 1770](#)
- [diagnose wad stats worker.cache_resource on page 1770](#)
- [diagnose wad stats worker.cache_store on page 1770](#)
- [diagnose wad stats worker.casb on page 1770](#)
- [diagnose wad stats worker.cert_cache on page 1770](#)
- [diagnose wad stats worker.chunk_cache on page 1771](#)
- [diagnose wad stats worker.cifs on page 1771](#)
- [diagnose wad stats worker.config_delta on page 1771](#)
- [diagnose wad stats worker.conn_pool on page 1771](#)
- [diagnose wad stats worker.db on page 1772](#)
- [diagnose wad stats worker.dev_info on page 1772](#)
- [diagnose wad stats worker.dev_stats on page 1772](#)

- [diagnose wad stats worker.dns_proxy on page 1772](#)
- [diagnose wad stats worker.dns_req on page 1773](#)
- [diagnose wad stats worker.fast_match on page 1773](#)
- [diagnose wad stats worker.fnbam on page 1773](#)
- [diagnose wad stats worker.fsae on page 1773](#)
- [diagnose wad stats worker.ftgd_agent on page 1773](#)
- [diagnose wad stats worker.ftp on page 1774](#)
- [diagnose wad stats worker.fw_policy on page 1774](#)
- [diagnose wad stats worker.fwd_svr on page 1774](#)
- [diagnose wad stats worker.http_auth on page 1774](#)
- [diagnose wad stats worker.http_engine on page 1775](#)
- [diagnose wad stats worker.http_ffbk on page 1775](#)
- [diagnose wad stats worker.http_msg on page 1775](#)
- [diagnose wad stats worker.http_scan on page 1775](#)
- [diagnose wad stats worker.http_srv_selector on page 1776](#)
- [diagnose wad stats worker.http_view on page 1776](#)
- [diagnose wad stats worker.icap_client on page 1776](#)
- [diagnose wad stats worker.icap_local_server on page 1776](#)
- [diagnose wad stats worker.icap_parser on page 1776](#)
- [diagnose wad stats worker.icap_remote_server on page 1777](#)
- [diagnose wad stats worker.inet_app on page 1777](#)
- [diagnose wad stats worker.infection_cache on page 1777](#)
- [diagnose wad stats worker.ipseng on page 1777](#)
- [diagnose wad stats worker.krb_pac on page 1778](#)
- [diagnose wad stats worker.krl on page 1778](#)
- [diagnose wad stats worker.kwd_dfa on page 1778](#)
- [diagnose wad stats worker.ldap on page 1778](#)
- [diagnose wad stats worker.llm on page 1779](#)
- [diagnose wad stats worker.pattern_match on page 1779](#)
- [diagnose wad stats worker.pol_test on page 1779](#)
- [diagnose wad stats worker.policy_profile on page 1779](#)
- [diagnose wad stats worker.proc_common on page 1779](#)
- [diagnose wad stats worker.protos on page 1780](#)
- [diagnose wad stats worker.quic on page 1780](#)
- [diagnose wad stats worker.runtime_info on page 1780](#)
- [diagnose wad stats worker.scan_cache on page 1780](#)
- [diagnose wad stats worker.sec_prof on page 1781](#)
- [diagnose wad stats worker.shaping on page 1781](#)
- [diagnose wad stats worker.shm_stats on page 1781](#)
- [diagnose wad stats worker.smb_prot on page 1781](#)
- [diagnose wad stats worker.ssh on page 1782](#)
- [diagnose wad stats worker.ssl on page 1782](#)
- [diagnose wad stats worker.ssl_cic on page 1782](#)

- [diagnose wad stats worker.sysmem on page 1782](#)
- [diagnose wad stats worker.tcp on page 1782](#)
- [diagnose wad stats worker.tls_fgpt_svc_cp on page 1783](#)
- [diagnose wad stats worker.traffic_mirror on page 1783](#)
- [diagnose wad stats worker.tunnel on page 1783](#)
- [diagnose wad stats worker.url_filter on page 1783](#)
- [diagnose wad stats worker.url_match on page 1784](#)
- [diagnose wad stats worker.urlredirect on page 1784](#)
- [diagnose wad stats worker.wisp on page 1784](#)
- [diagnose wad stats worker.worker_self on page 1784](#)
- [diagnose wad stats worker.ztna_jwt on page 1785](#)
- [diagnose wad stream-scan on page 1785](#)
- [diagnose wad stream-scan av-intf on page 1785](#)
- [diagnose wad stream-scan av-intf disable on page 1785](#)
- [diagnose wad stream-scan av-intf enable on page 1785](#)
- [diagnose wad stream-scan av-test on page 1785](#)
- [diagnose wad tcp-connection on page 1786](#)
- [diagnose wad tcp-connection list on page 1786](#)
- [diagnose wad toggle on page 1786](#)
- [diagnose wad tp-fw-policy-test on page 1786](#)
- [diagnose wad tp-fw-policy-test-save on page 1787](#)
- [diagnose wad tunnel on page 1787](#)
- [diagnose wad tunnel clear on page 1787](#)
- [diagnose wad tunnel list on page 1788](#)
- [diagnose wad url-lookup on page 1788](#)
- [diagnose wad user on page 1788](#)
- [diagnose wad user clear on page 1788](#)
- [diagnose wad user count on page 1788](#)
- [diagnose wad user device on page 1789](#)
- [diagnose wad user domain-controller on page 1789](#)
- [diagnose wad user domain-controller dns on page 1789](#)
- [diagnose wad user domain-controller dns list on page 1789](#)
- [diagnose wad user domain-controller dns test on page 1789](#)
- [diagnose wad user exchange on page 1789](#)
- [diagnose wad user exchange get-matches on page 1790](#)
- [diagnose wad user exchange query-rows on page 1790](#)
- [diagnose wad user exchange reset on page 1790](#)
- [diagnose wad user exchange resolve-names on page 1790](#)
- [diagnose wad user exchange test-auto-discover on page 1790](#)
- [diagnose wad user filter on page 1790](#)
- [diagnose wad user list on page 1791](#)
- [diagnose wad webcache on page 1791](#)
- [diagnose wad webcache clear on page 1791](#)

- [diagnose wad webcache list on page 1791](#)
- [diagnose wad webproxy on page 1791](#)
- [diagnose wad webproxy clear on page 1792](#)
- [diagnose wad webproxy forward-server on page 1792](#)
- [diagnose wad webproxy forward-server detail on page 1792](#)
- [diagnose wad webproxy forward-server summary on page 1792](#)
- [diagnose wad webproxy forward-server-group on page 1792](#)
- [diagnose wad webproxy list on page 1792](#)
- [diagnose wad worker on page 1793](#)
- [diagnose wad worker avscan on page 1793](#)
- [diagnose wad worker avscan clear on page 1793](#)
- [diagnose wad worker avscan list on page 1793](#)
- [diagnose wad worker bytcache on page 1793](#)
- [diagnose wad worker bytcache clear on page 1793](#)
- [diagnose wad worker bytcache flush on page 1794](#)
- [diagnose wad worker bytcache stats on page 1794](#)
- [diagnose wad worker cookie on page 1794](#)
- [diagnose wad worker cookie map on page 1794](#)
- [diagnose wad worker filter on page 1794](#)
- [diagnose wad worker filter clear on page 1795](#)
- [diagnose wad worker filter list on page 1795](#)
- [diagnose wad worker imagecache on page 1795](#)
- [diagnose wad worker imagecache flush on page 1795](#)
- [diagnose wad worker imagecache stats on page 1795](#)
- [diagnose wad worker memcache on page 1795](#)
- [diagnose wad worker memcache clear on page 1796](#)
- [diagnose wad worker memcache flush on page 1796](#)
- [diagnose wad worker memcache stats on page 1796](#)
- [diagnose wad worker peer on page 1796](#)
- [diagnose wad worker peer clear on page 1796](#)
- [diagnose wad worker peer list on page 1797](#)
- [diagnose wad worker policy on page 1797](#)
- [diagnose wad worker policy clear on page 1797](#)
- [diagnose wad worker policy list on page 1797](#)
- [diagnose wad worker restart on page 1797](#)
- [diagnose wad worker scripts on page 1797](#)
- [diagnose wad worker scripts clear on page 1798](#)
- [diagnose wad worker scripts list on page 1798](#)
- [diagnose wad worker webcache on page 1798](#)
- [diagnose wad worker webcache clear on page 1798](#)
- [diagnose wad worker webcache flush on page 1798](#)
- [diagnose wad worker webcache stats on page 1799](#)
- [diagnose wad worker webcache summary on page 1799](#)

diagnose wad access-proxy

Show connectivity status with the real server.

```
diagnose wad access-proxy
```

diagnose wad access-proxy health-check

Show connectivity status with the real server.

```
diagnose wad access-proxy health-check
```

diagnose wad access-proxy health-check status

Show connectivity status with the real server.

```
diagnose wad access-proxy health-check status
```

diagnose wad console-log

Send WAD log messages to the console.

```
diagnose wad console-log
```

diagnose wad console-log disable

Disable logging.

```
diagnose wad console-log disable
```

diagnose wad console-log enable

Enable logging.

```
diagnose wad console-log enable
```

diagnose wad csvc

Cache service diagnostics.

```
diagnose wad csvc
```

diagnose wad csvc bytecache

Bytecache diagnostics.

```
diagnose wad csvc bytecache
```

diagnose wad csvc bytecache clear

Purge all entries.

```
diagnose wad csvc bytecache clear [<index>]
```

Parameter	Description	Type	Size
[<index>]	CSVC index or all cache services if not set.	string	

diagnose wad csvc bytecache flush

Reset statistics.

```
diagnose wad csvc bytecache flush [<index>]
```

Parameter	Description	Type	Size
[<index>]	CSVC index or all cache services if not set.	string	

diagnose wad csvc bytecache lists

Show entry lists.

```
diagnose wad csvc bytecache lists [<index>]
```

Parameter	Description	Type	Size
[<index>]	CSVC index or all cache services if not set.	string	

diagnose wad csvc bytecache stats

Show statistics.

```
diagnose wad csvc bytecache stats [<index>]
```

Parameter	Description	Type	Size
[<index>]	CSVC index or all cache services if not set.	string	

diagnose wad csvc memcache

Memcache diagnostics.

```
diagnose wad csvc memcache
```

diagnose wad csvc memcache clear

Purge all entries.

```
diagnose wad csvc memcache clear [<index>]
```

Parameter	Description	Type	Size
[<index>]	CSVC index or all cache services if not set.	string	

diagnose wad csvc memcache flush

Reset statistics.

```
diagnose wad csvc memcache flush [<index>]
```

Parameter	Description	Type	Size
[<index>]	CSVC index or all cache services if not set.	string	

diagnose wad csvc memcache lists

Show entry lists.

```
diagnose wad csvc memcache lists [<index>]
```

Parameter	Description	Type	Size
[<index>]	CSVC index or all cache services if not set.	string	

diagnose wad csvc memcache stats

Show statistics.

```
diagnose wad csvc memcache stats [<index>]
```

Parameter	Description	Type	Size
[<index>]	CSVC index or all cache services if not set.	string	

diagnose wad csvc restart

Restart cache service.

```
diagnose wad csvc restart [<type>] [<index>]
```

Parameter	Description	Type	Size
[<type>]	CSVC type {0:web_cache, 1:byte_and_mem_cache} or all if not set.	string	
[<index>]	CSVC index or all cache services if not set.	string	

diagnose wad csvc webcache

Webcache diagnostics.

```
diagnose wad csvc webcache
```

diagnose wad csvc webcache clear

Purge all entries.

```
diagnose wad csvc webcache clear [<index>]
```

Parameter	Description	Type	Size
[<index>]	CSVC index or all cache services if not set.	string	

diagnose wad csvc webcache flush

Reset statistics.

```
diagnose wad csvc webcache flush [<index>]
```

Parameter	Description	Type	Size
[<index>]	CSVC index or all cache services if not set.	string	

diagnose wad csvc webcache lists

Show entry lists.

```
diagnose wad csvc webcache lists [<index>]
```

Parameter	Description	Type	Size
[<index>]	CSVC index or all cache services if not set.	string	

diagnose wad csvc webcache stats

Show statistics.

```
diagnose wad csvc webcache stats [<index>]
```

Parameter	Description	Type	Size
[<index>]	CSVC index or all cache services if not set.	string	

diagnose wad debug

Debug setting.

```
diagnose wad debug
```

diagnose wad debug clear

Clear debug setting.

```
diagnose wad debug clear
```

diagnose wad debug crash

Saved debug message.

```
diagnose wad debug crash
```

diagnose wad debug crash clear

Clear saved debug log.

```
diagnose wad debug crash clear
```

diagnose wad debug crash disable

Disable saving debug messages when process crashes.

```
diagnose wad debug crash disable
```

diagnose wad debug crash enable

Enable saving debug messages when process crashes.

```
diagnose wad debug crash enable
```

diagnose wad debug crash list

List a summary of crash logs.

```
diagnose wad debug crash list
```

diagnose wad debug crash max

Max save size. 1-10 (MB)

```
diagnose wad debug crash max <size>
```

Parameter	Description	Type	Size
<size>	1-10 (MB).	string	

diagnose wad debug crash read

Display saved debug log.

```
diagnose wad debug crash read <proc_type> <id>
```

Parameter	Description	Type	Size
<proc_type>	Please input proc_type number.	string	
<id>	Please input crash id.	string	

diagnose wad debug disable

Disable debug setting.

```
diagnose wad debug disable
```

diagnose wad debug disable category

Category debug setting.

```
diagnose wad debug disable category
```

diagnose wad debug disable category aio

async io

```
diagnose wad debug disable category aio
```

diagnose wad debug disable category antiphish

Anti-Phishing

```
diagnose wad debug disable category antiphish
```

diagnose wad debug disable category auth

authentication

```
diagnose wad debug disable category auth
```

diagnose wad debug disable category autotest

auto test

```
diagnose wad debug disable category autotest
```

diagnose wad debug disable category bytecache

byte cache

```
diagnose wad debug disable category bytecache
```

diagnose wad debug disable category cache_server

reverse cache server

```
diagnose wad debug disable category cache_server
```

diagnose wad debug disable category casb

casb

```
diagnose wad debug disable category casb
```

diagnose wad debug disable category cifs

cifs

```
diagnose wad debug disable category cifs
```

diagnose wad debug disable category config

learn config

```
diagnose wad debug disable category config
```

diagnose wad debug disable category csvc

cache service

```
diagnose wad debug disable category csvc
```

diagnose wad debug disable category detail

troubleshoot detail

```
diagnose wad debug disable category detail
```

diagnose wad debug disable category devuln

device vulnerability

```
diagnose wad debug disable category devuln
```

diagnose wad debug disable category diag

debug daemon

```
diagnose wad debug disable category diag
```

diagnose wad debug disable category dispatcher

dispatcher

```
diagnose wad debug disable category dispatcher
```

diagnose wad debug disable category dns

DNS proxy

```
diagnose wad debug disable category dns
```

diagnose wad debug disable category dskd

cache disks

```
diagnose wad debug disable category dskd
```

diagnose wad debug disable category extension

implicit proxy extension

```
diagnose wad debug disable category extension
```

diagnose wad debug disable category ftp

ftp

```
diagnose wad debug disable category ftp
```

diagnose wad debug disable category http

http

```
diagnose wad debug disable category http
```

diagnose wad debug disable category http2

http2

```
diagnose wad debug disable category http2
```

diagnose wad debug disable category http3

http3

```
diagnose wad debug disable category http3
```

diagnose wad debug disable category icap

icap

```
diagnose wad debug disable category icap
```

diagnose wad debug disable category icap_server

Local ICAP server

```
diagnose wad debug disable category icap_server
```

diagnose wad debug disable category icbsvc

icb service

```
diagnose wad debug disable category icbsvc
```

diagnose wad debug disable category info

user device info

```
diagnose wad debug disable category info
```

diagnose wad debug disable category ips

ips

```
diagnose wad debug disable category ips
```

diagnose wad debug disable category isolator

isolator

```
diagnose wad debug disable category isolator
```

diagnose wad debug disable category license

license

```
diagnose wad debug disable category license
```

diagnose wad debug disable category mapi

mapi

```
diagnose wad debug disable category mapi
```

diagnose wad debug disable category memblk

memory block

```
diagnose wad debug disable category memblk
```

diagnose wad debug disable category monitor

worker health monitor

```
diagnose wad debug disable category monitor
```

diagnose wad debug disable category packet

packet

```
diagnose wad debug disable category packet
```

diagnose wad debug disable category policy

policy matching

```
diagnose wad debug disable category policy
```

diagnose wad debug disable category policy_test

firewall policy test

```
diagnose wad debug disable category policy_test
```

diagnose wad debug disable category proc

process management

```
diagnose wad debug disable category proc
```

diagnose wad debug disable category quic

quic

```
diagnose wad debug disable category quic
```

diagnose wad debug disable category quic_cc

quic congestion control and loss detection

```
diagnose wad debug disable category quic_cc
```

diagnose wad debug disable category rpc

rpc

```
diagnose wad debug disable category rpc
```

diagnose wad debug disable category scan

UTM scan

```
diagnose wad debug disable category scan
```

diagnose wad debug disable category scp

scp

```
diagnose wad debug disable category scp
```

diagnose wad debug disable category session

session

```
diagnose wad debug disable category session
```

diagnose wad debug disable category sftp

sftp

```
diagnose wad debug disable category sftp
```

diagnose wad debug disable category socks

socks

```
diagnose wad debug disable category socks
```

diagnose wad debug disable category ssh

ssh

```
diagnose wad debug disable category ssh
```

diagnose wad debug disable category ssl

ssl

```
diagnose wad debug disable category ssl
```


diagnose wad debug disable category sys

sys

```
diagnose wad debug disable category sys
```

diagnose wad debug disable category tls_fingerprint

tls_fingerprint

```
diagnose wad debug disable category tls_fingerprint
```

diagnose wad debug disable category tunnel

wanopt_tunnel

```
diagnose wad debug disable category tunnel
```

diagnose wad debug disable category uih

uih

```
diagnose wad debug disable category uih
```

diagnose wad debug disable category video

cache_video

```
diagnose wad debug disable category video
```

diagnose wad debug disable category vs

virtual_server

```
diagnose wad debug disable category vs
```

diagnose wad debug disable category waf

waf

```
diagnose wad debug disable category waf
```

diagnose wad debug disable category webcache

webcache

```
diagnose wad debug disable category webcache
```

diagnose wad debug display

Display setting.

```
diagnose wad debug display
```

diagnose wad debug display pid

Pid display in the trace.

```
diagnose wad debug display pid
```

diagnose wad debug display pid disable

Disable pid display.

```
diagnose wad debug display pid disable
```

diagnose wad debug display pid enable

Enable pid display.

```
diagnose wad debug display pid enable
```

diagnose wad debug enable

Enable debug setting.

```
diagnose wad debug enable
```

diagnose wad debug enable all

Enable all debug categories and set to the maximum level.

```
diagnose wad debug enable all
```

diagnose wad debug enable category

Category debug setting.

```
diagnose wad debug enable category
```

diagnose wad debug enable category aio

async io

```
diagnose wad debug enable category aio
```

diagnose wad debug enable category all

all category

```
diagnose wad debug enable category all
```

diagnose wad debug enable category antiphish

Anti-Phishing

```
diagnose wad debug enable category antiphish
```

diagnose wad debug enable category auth

authentication

```
diagnose wad debug enable category auth
```

diagnose wad debug enable category autotest

auto test

```
diagnose wad debug enable category autotest
```

diagnose wad debug enable category bytecache

byte cache

```
diagnose wad debug enable category bytecache
```

diagnose wad debug enable category cache_server

reverse cache server

```
diagnose wad debug enable category cache_server
```

diagnose wad debug enable category casb

casb

```
diagnose wad debug enable category casb
```

diagnose wad debug enable category cifs

cifs

```
diagnose wad debug enable category cifs
```

diagnose wad debug enable category config

learn config

```
diagnose wad debug enable category config
```

diagnose wad debug enable category csvc

cache service

```
diagnose wad debug enable category csvc
```

diagnose wad debug enable category detail

troubleshoot detail

```
diagnose wad debug enable category detail
```

diagnose wad debug enable category devuln

device vulnerability

```
diagnose wad debug enable category devuln
```

diagnose wad debug enable category diag

debug daemon

```
diagnose wad debug enable category diag
```

diagnose wad debug enable category dispatcher

dispatcher

```
diagnose wad debug enable category dispatcher
```

diagnose wad debug enable category dns

DNS proxy

```
diagnose wad debug enable category dns
```

diagnose wad debug enable category dskd

cache disks

```
diagnose wad debug enable category dskd
```

diagnose wad debug enable category extension

implicit proxy extension

```
diagnose wad debug enable category extension
```

diagnose wad debug enable category ftp

ftp

```
diagnose wad debug enable category ftp
```

diagnose wad debug enable category http

http

```
diagnose wad debug enable category http
```

diagnose wad debug enable category http2

http2

```
diagnose wad debug enable category http2
```

diagnose wad debug enable category http3

http3

```
diagnose wad debug enable category http3
```

diagnose wad debug enable category icap

icap

```
diagnose wad debug enable category icap
```

diagnose wad debug enable category icap_server

Local ICAP server

```
diagnose wad debug enable category icap_server
```

diagnose wad debug enable category icbsvc

icb service

```
diagnose wad debug enable category icbsvc
```

diagnose wad debug enable category info

user device info

```
diagnose wad debug enable category info
```

diagnose wad debug enable category ips

ips

```
diagnose wad debug enable category ips
```

diagnose wad debug enable category isolator

isolator

```
diagnose wad debug enable category isolator
```

diagnose wad debug enable category license

license

```
diagnose wad debug enable category license
```

diagnose wad debug enable category mapi

mapi

```
diagnose wad debug enable category mapi
```

diagnose wad debug enable category memblk

memory block

```
diagnose wad debug enable category memblk
```

diagnose wad debug enable category monitor

worker health monitor

```
diagnose wad debug enable category monitor
```

diagnose wad debug enable category packet

packet

```
diagnose wad debug enable category packet
```


diagnose wad debug enable category policy

policy matching

```
diagnose wad debug enable category policy
```

diagnose wad debug enable category policy_test

firewall policy test

```
diagnose wad debug enable category policy_test
```

diagnose wad debug enable category proc

process management

```
diagnose wad debug enable category proc
```

diagnose wad debug enable category quic

quic

```
diagnose wad debug enable category quic
```

diagnose wad debug enable category quic_cc

quic congestion control and loss detection

```
diagnose wad debug enable category quic_cc
```

diagnose wad debug enable category rpc

rpc

```
diagnose wad debug enable category rpc
```

diagnose wad debug enable category scan

UTM scan

```
diagnose wad debug enable category scan
```

diagnose wad debug enable category scp

scp

```
diagnose wad debug enable category scp
```

diagnose wad debug enable category session

session

```
diagnose wad debug enable category session
```

diagnose wad debug enable category sftp

sftp

```
diagnose wad debug enable category sftp
```

diagnose wad debug enable category socks

socks

```
diagnose wad debug enable category socks
```

diagnose wad debug enable category ssh

ssh

```
diagnose wad debug enable category ssh
```

diagnose wad debug enable category ssl

ssl

```
diagnose wad debug enable category ssl
```

diagnose wad debug enable category sys

sys

```
diagnose wad debug enable category sys
```

diagnose wad debug enable category tls_fingerprint

tls fingerprint

```
diagnose wad debug enable category tls_fingerprint
```

diagnose wad debug enable category tunnel

wanopt tunnel

```
diagnose wad debug enable category tunnel
```

diagnose wad debug enable category uih

uih

```
diagnose wad debug enable category uih
```

diagnose wad debug enable category video

cache video

```
diagnose wad debug enable category video
```

diagnose wad debug enable category vs

virtual server

```
diagnose wad debug enable category vs
```

diagnose wad debug enable category waf

waf

```
diagnose wad debug enable category waf
```

diagnose wad debug enable category webcache

webcache

```
diagnose wad debug enable category webcache
```

diagnose wad debug enable level

Level debug setting.

```
diagnose wad debug enable level
```

diagnose wad debug enable level error

error

```
diagnose wad debug enable level error
```

diagnose wad debug enable level info

information

```
diagnose wad debug enable level info
```

diagnose wad debug enable level verbose

verbose

```
diagnose wad debug enable level verbose
```

diagnose wad debug enable level warn

warning

```
diagnose wad debug enable level warn
```

diagnose wad debug ips-db

Inline-IPS database.

```
diagnose wad debug ips-db
```

diagnose wad debug ips-db status

Inline-IPS database status.

```
diagnose wad debug ips-db status
```

diagnose wad debug save-http-req-crash

Save HTTP request when WAD worker crashes.

```
diagnose wad debug save-http-req-crash
```

diagnose wad debug save-http-req-crash disable

Disable saving HTTP request when WAD worker crashes.

```
diagnose wad debug save-http-req-crash disable
```

diagnose wad debug save-http-req-crash enable

Enable saving HTTP request when WAD worker crashes.

```
diagnose wad debug save-http-req-crash enable
```

diagnose wad debug show

Show debug setting.

```
diagnose wad debug show
```

diagnose wad dev

Dev. diagnostics.

```
diagnose wad dev
```

diagnose wad dev fcnacd

Emulate fcnacd messages.

```
diagnose wad dev fcnacd
```

diagnose wad dev fcnacd delete

Delete a device by uid, sn, and tenant id. (EC_LLS_ZTNA_CMD_DEV_DELETE)

```
diagnose wad dev fcnacd delete
```

diagnose wad dev fcnacd ip-err

Generate an EMS IP address error response. (EC_LLS_ZTNA_CMD_FIND_BY_IPVD_ER_CODE)

```
diagnose wad dev fcnacd ip-err
```

diagnose wad dev fcnacd uid-err

Generate an EMS UID error response. (EC_LLS_ZTNA_CMD_FIND_BY_UID)

```
diagnose wad dev fcnacd uid-err
```

diagnose wad dev fcnacd update

Insert a dummy device. (EC_LLS_ZTNA_CMD_DEV_UPDATE)

```
diagnose wad dev fcnacd update
```

diagnose wad dev query-by

Query a device.

```
diagnose wad dev query-by
```

diagnose wad dev query-by ipv4

Query by IPv4 address.

```
diagnose wad dev query-by ipv4
```

diagnose wad dev query-by ipv6

Query by IPv6 address.

```
diagnose wad dev query-by ipv6
```

diagnose wad dev query-by uid

Query by UID.

```
diagnose wad dev query-by uid
```

diagnose wad dev-vuln

Device vulnerability diagnostics.

```
diagnose wad dev-vuln
```

diagnose wad dev-vuln query

Query dev-vuln by vendor=<xxx>&version=<xxx>&product=<xxx>&model=<xxx>

```
diagnose wad dev-vuln query
```

diagnose wad dev-vuln query-by-id

Query dev-vuln by vulnerability id=<xxx>.

```
diagnose wad dev-vuln query-by-id
```

diagnose wad dev-vuln query-ftgd

Query dev-vuln by vendor=<xxx>&version=<xxx>&product=<xxx>&model=<xxx>

```
diagnose wad dev-vuln query-ftgd
```

diagnose wad dynamic-bypass

Dynamic-bypass diagnostics.

```
diagnose wad dynamic-bypass
```

diagnose wad dynamic-bypass clear

Clear dynamic-bypass stats.

```
diagnose wad dynamic-bypass clear
```


diagnose wad dynamic-bypass flush

Flush dynamic-bypass entries.

```
diagnose wad dynamic-bypass flush
```

diagnose wad dynamic-bypass show

Show dynamic-bypass summary.

```
diagnose wad dynamic-bypass show
```

diagnose wad exp-fw-policy-test

Explicit firewall policy test.

```
diagnose wad exp-fw-policy-test <SRC> <WEBPROXY> <REQ> <AUTH_TYPE> <USER/GROUP> <SERVER>
```

Parameter	Description	Type	Size
<SRC>	Please input source IP.	string	
<WEBPROXY>	Please input webproxy name.	string	
<REQ>	Please input uri=<uri> or ipport=<ip:port> or multi-line http request.	string	
<AUTH_TYPE>	Please input authentication type: none, user or group.	string	
<USER/GROUP>	Please input username or name of matching user/group on remote authentication server.	string	
<SERVER>	Please input name of auth server.	string	

diagnose wad exp-fw-policy-test-save

Save explicit firewall policy test.

```
diagnose wad exp-fw-policy-test-save <SRC> <WEBPROXY> <REQ> <AUTH_TYPE> <USER/GROUP> <SERVER>
```

Parameter	Description	Type	Size
<SRC>	Please input source IP.	string	
<WEBPROXY>	Please input webproxy name.	string	

Parameter	Description	Type	Size
<REQ>	Please input uri=<uri> or ipport=<ip:port> or multi-line http request.	string	
<AUTH_TYPE>	Please input authentication type: none, user or group.	string	
<USER/GROUP>	Please input username or name of matching user/group on remote authentication server.	string	
<SERVER>	Please input name of auth server.	string	

diagnose wad filter

Filter for listing sessions or tunnels.

```
diagnose wad filter
```

diagnose wad filter clear

Erase current filter settings.

```
diagnose wad filter clear
```

diagnose wad filter dport

Destination port range to filter by.

```
diagnose wad filter dport <port> <port>
```

Parameter	Description	Type	Size
<port>	Destination port (from).	string	
<port>	Destination port (to).	string	

diagnose wad filter drop-unknown-session

Enable drop message unknown sessions.

```
diagnose wad filter drop-unknown-session <Drop unknown sessions>
```

Parameter	Description	Type	Size
<Drop unknown sessions>	(1 = enable, 0 = do not drop).	string	

diagnose wad filter dst

Destination address range to filter by.

```
diagnose wad filter dst <ip-address> <ip-address>
```

Parameter	Description	Type	Size
<ip- address>	Destination IP address (from).	string	
<ip- address>	Destination IP address (to).	string	

diagnose wad filter dst6

Destination address6 range to filter by.

```
diagnose wad filter dst6 <ip-address6> <ip-address6>
```

Parameter	Description	Type	Size
<ip- address6>	Destination IPv6 address (from).	string	
<ip- address6>	Destination IPv6 address (to).	string	

diagnose wad filter explicit-policy

Index of explicit-policy. -1 matches all.

```
diagnose wad filter explicit-policy <index>
```

Parameter	Description	Type	Size
<index>	Index of explicit-policy. -1 matches all.	string	

diagnose wad filter firewall-policy

Index of firewall-policy. -1 matches all.

```
diagnose wad filter firewall-policy <index>
```

Parameter	Description	Type	Size
<index>	Index of firewall-policy. -1 matches all.	string	

diagnose wad filter list

Display current filter.

```
diagnose wad filter list
```

diagnose wad filter negate

Negate the specified filter parameter.

```
diagnose wad filter negate <parm>
```

Parameter	Description	Type	Size
<parm>	Filter parameter to negate.	string	

diagnose wad filter process-id

Select process ID to filter by.

```
diagnose wad filter process-id <Process ID>
```

Parameter	Description	Type	Size
<Process ID>	Process ID to filter (0 = disable).	string	

diagnose wad filter process-id-by-src

Process id affined with the selected source IPv4/IPv6 to filter by.

```
diagnose wad filter process-id-by-src <ip-address>
```

Parameter	Description	Type	Size
<ip-address>	Source IPv4/IPv6.	string	

diagnose wad filter process-type

Select process type to filter by.

```
diagnose wad filter process-type <Process types (0 = disable):>
```

Parameter	Description	Type	Size
<Process types (0 = disable):>	1. manager 2. dispatcher 3. worker 4. algo 5. informer 6. user-info 7. cache-service-cs 8. cache-service-db 9. cert-inspection 10. youtube-filter-cache-service 11. user-info-history 12. debug 13. config-notify 14. object-cache 15. byte-cache 16. traffic aggregator 17. preload daemon	string	

diagnose wad filter protocol

Select protocols to filter by.

```
diagnose wad filter protocol <http> <mapi> <cifs> <ftp> <tcp>
```

Parameter	Description	Type	Size
<http>	To match (1), otherwise (0).	string	
<mapi>	To match (1), otherwise (0).	string	
<cifs>	To match (1), otherwise (0).	string	
<ftp>	To match (1), otherwise (0).	string	
<tcp>	To match (1), otherwise (0).	string	

diagnose wad filter proxy-policy-list-increment

Increment in steps per proxy policy list call.

```
diagnose wad filter proxy-policy-list-increment <increment steps>
```

Parameter	Description	Type	Size
<increment steps>	Incremental steps per proxy policy call (10 - 100, default = 20)	string	

diagnose wad filter sport

Source port range to filter by.

```
diagnose wad filter sport <port> <port>
```

Parameter	Description	Type	Size
<port>	Source port (from).	string	
<port>	Source port (to).	string	

diagnose wad filter src

Source address range to filter by.

```
diagnose wad filter src <ip-address> <ip-address>
```

Parameter	Description	Type	Size
<ip-address>	Source IP address (from).	string	
<ip-address>	Source IP address (to).	string	

diagnose wad filter src6

Source address6 range to filter by.

```
diagnose wad filter src6 <ip-address6> <ip-address6>
```

Parameter	Description	Type	Size
<ip-address6>	Source IPv6 address (from).	string	
<ip-address6>	Source IPv6 address (to).	string	

diagnose wad filter vd

Virtual Domain Name.

```
diagnose wad filter vd <vdom>
```

Parameter	Description	Type	Size
<vdom>	Virtual Domain Name. ALL all vdoms	string	

diagnose wad fw-policy-test-get

Get firewall policy test.

```
diagnose wad fw-policy-test-get
```

diagnose wad health

Check if wad processes are health.

```
diagnose wad health
```

diagnose wad health debug

Check if debug daemon works or not.

```
diagnose wad health debug
```

diagnose wad health fs

Check if filesystem works or not.

```
diagnose wad health fs <File system type (0 = all):> <Lines>
```

Parameter	Description	Type	Size
<File system type (0 = all):>	1. data file system 2. data2 file system 3. log file system	string	
<Lines>	Max write lines (1-50)	string	

diagnose wad health worker

Check if worker processes work or not.

```
diagnose wad health worker
```

diagnose wad history

Statistics history.

```
diagnose wad history
```

diagnose wad history clear

Clear statistics history.

```
diagnose wad history clear
```

diagnose wad history list

List statistics history.

```
diagnose wad history list <proto> <period>
```

Parameter	Description	Type	Size
<proto>	All HTTP FTP CIFS MAPI TCP.	string	
<period>	10min hour day 30days.	string	

diagnose wad icap

ICAP diagnostics.

```
diagnose wad icap
```

diagnose wad icap list

List ICAP servers

```
diagnose wad icap list
```


diagnose wad kxp

SSL KXP diagnostics.

```
diagnose wad kxp
```

diagnose wad kxp clear

Clear all KXP queue stats.

```
diagnose wad kxp clear
```

diagnose wad kxp list

List KXP queue size.

```
diagnose wad kxp list
```

diagnose wad license

Show License Info.

```
diagnose wad license
```

diagnose wad license clear

Clear all license usage history

```
diagnose wad license clear
```

diagnose wad license detail

Show License Detail.

```
diagnose wad license detail
```

diagnose wad license glob-usage

Show Total License Usage History of the Fabric Group

```
diagnose wad license glob-usage <period>
```

Parameter	Description	Type	Size
<period>	seconds minutes hour day week month year	string	

diagnose wad license summary

Show License summary.

```
diagnose wad license summary
```

diagnose wad license test

Add targeted value to test update function

```
diagnose wad license test <value> <repeats>
```

Parameter	Description	Type	Size
<value>	any non-negative integer in 0~65536	string	
<repeats>	any non-negative interger smaller than 2147483647	string	

diagnose wad license usage

Show License Usage History

```
diagnose wad license usage <period>
```

Parameter	Description	Type	Size
<period>	seconds minutes hour day week month year	string	

diagnose wad memory

WAD memory diagnostics.

```
diagnose wad memory
```

diagnose wad memory monitor

Monitor wad memory usage.

```
diagnose wad memory monitor
```

diagnose wad memory monitor disable

Disable wad memory monitor.

```
diagnose wad memory monitor disable
```

diagnose wad memory monitor enable

Enable wad memory monitor.

```
diagnose wad memory monitor enable
```

diagnose wad memory monitor interval

Set the time interval (in min) for memory monitoring.

```
diagnose wad memory monitor interval <Integer>
```

Parameter	Description	Type	Size
<Integer>	Please enter an integer from <5> to <60>.	string	

diagnose wad memory monitor list

List wad memory monitor parameters.

```
diagnose wad memory monitor list
```

diagnose wad memory monitor max-report-files

Max number of report files to save.

```
diagnose wad memory monitor max-report-files <Integer>
```

Parameter	Description	Type	Size
<Integer>	Please enter an integer from <1> to <10>.	string	

diagnose wad memory monitor mem-threshold-red

Set threshold at which wad workers' total memory usage triggers saving memory report in a disk file.

```
diagnose wad memory monitor mem-threshold-red <Integer>
```

Parameter	Description	Type	Size
<Integer>	Please enter an integer from <0> to <100>.	string	

diagnose wad memory overused

List suspiciously overused WAD memory buckets.

```
diagnose wad memory overused <Integer>
```

Parameter	Description	Type	Size
<Integer>	Overused threshold filter value.	string	

diagnose wad memory report

List a report of wad memory usage.

```
diagnose wad memory report
```

diagnose wad memory sum

Sum all WAD process memory modules stats.

```
diagnose wad memory sum
```

diagnose wad memory track

Track cmem alloc.

```
diagnose wad memory track <Integer>
```

Parameter	Description	Type	Size
<Integer>	Id for cmem stats.	string	

diagnose wad memory workers

List WAD worker memory modules.

```
diagnose wad memory workers
```

diagnose wad nbi

Native Browser Isolator diagnostics.

```
diagnose wad nbi
```

diagnose wad nbi license

Show license information.

```
diagnose wad nbi license
```

diagnose wad nbi packages

List information for NBI packages.

```
diagnose wad nbi packages
```

diagnose wad nbi status

(Default) Display the full NBI status.

```
diagnose wad nbi status
```

diagnose wad process

Wad process diagnostics.

```
diagnose wad process
```

diagnose wad process YouTube-filter-cache-service

Diagnose YouTube-filter-cache-s

```
diagnose wad process YouTube-filter-cache-service <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process algo

Diagnose algo process.

```
diagnose wad process algo <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process byte-cache

Diagnose byte-cache process.

```
diagnose wad process byte-cache <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process cache-service-cs

Diagnose cache-service-cs proce

```
diagnose wad process cache-service-cs <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process cache-service-db

Diagnose cache-service-db proce

```
diagnose wad process cache-service-db <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process cert-inspection

Diagnose cert-inspection proces

```
diagnose wad process cert-inspection <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process config-notify

Diagnose config-notify process.

```
diagnose wad process config-notify <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process debug

Diagnose debug process.

```
diagnose wad process debug <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process dev-vuln

Diagnose dev-vuln process.

```
diagnose wad process dev-vuln <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process dispatcher

Diagnose dispatcher process.

```
diagnose wad process dispatcher <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process ia-cache

Diagnose ia-cache process.

```
diagnose wad process ia-cache <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process informer

Diagnose informer process.

```
diagnose wad process informer <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process isolator

Diagnose isolator process.

```
diagnose wad process isolator <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process manager

Diagnose manager process.

```
diagnose wad process manager <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process object-cache

Diagnose object-cache process.

```
diagnose wad process object-cache <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process preload daemon

Diagnose preload daemon process

```
diagnose wad process preload daemon <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process staled-worker

Diagnose staled-worker process.

```
diagnose wad process staled-worker <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process tls-fgpt-service

Diagnose tls-fgpt-service proce

```
diagnose wad process tls-fgpt-service <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process traffic aggregator

Diagnose traffic aggregator pro

```
diagnose wad process traffic aggregator <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process user-info

Diagnose user-info process.

```
diagnose wad process user-info <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process user-info-history

Diagnose user-info-history proc

```
diagnose wad process user-info-history <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad process worker

Diagnose worker process.

```
diagnose wad process worker <index> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
<cmd> <cmd> <cmd> <cmd> <cmd> <cmd>
```

Parameter	Description	Type	Size
<index>	Process index to send command to. (0 for the 1st process; -1 for all)	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

Parameter	Description	Type	Size
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	
<cmd>	Diagnostic command (0 for help). Support up to 32 commands.	string	

diagnose wad report

A consolidated report and shorthand access to various 'diag test app xxx' commands.

```
diagnose wad report
```

diagnose wad report policy

Wad policy related diagnostics.

```
diagnose wad report policy
```

diagnose wad report session

Wad TCP, HTTP, and FTP session related diagnostics.

```
diagnose wad report session
```

diagnose wad report user

Wad user and auth related diagnostics.

```
diagnose wad report user
```

diagnose wad restore

Restore configuration defaults.

```
diagnose wad restore
```

diagnose wad restore cdn-rules

Restore default cdn rules.

```
diagnose wad restore cdn-rules
```

diagnose wad restore cdn-rules all

Restore default cdn rules.

```
diagnose wad restore cdn-rules all
```

diagnose wad session

Session diagnostics.

```
diagnose wad session
```

diagnose wad session clear

Clear all active sessions.

```
diagnose wad session clear
```

diagnose wad session count

Show number of active sessions.

```
diagnose wad session count
```

diagnose wad session list

List active sessions.

```
diagnose wad session list
```

diagnose wad session list-http2

List active http2 sessions.

```
diagnose wad session list-http2
```

diagnose wad sshproxy

sshproxy diagnostics.

```
diagnose wad sshproxy
```

diagnose wad sshproxy clear

Clear sshproxy stats.

```
diagnose wad sshproxy clear
```

diagnose wad sshproxy list

List sshproxy stats.

```
diagnose wad sshproxy list
```

diagnose wad stats

Statistics.

```
diagnose wad stats <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo

Show proc_algo statistics.

```
diagnose wad stats algo <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.antiphish

Show antiphish statistics.

```
diagnose wad stats algo.antiphish <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.casb

Show casb statistics.

```
diagnose wad stats algo.casb <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.dev_info

Show dev_info statistics.

```
diagnose wad stats algo.dev_info <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.dev_stats

Show dev_stats statistics.

```
diagnose wad stats algo.dev_stats <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.fast_tb

Show fast_tb statistics.

```
diagnose wad stats algo.fast_tb <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.fw_policy

Show fw_policy statistics.

```
diagnose wad stats algo.fw_policy <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.icap_client

Show icap_client statistics.

```
diagnose wad stats algo.icap_client <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.inet_app

Show inet_app statistics.

```
diagnose wad stats algo.inet_app <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.ips_builder

Show ips_builder statistics.

```
diagnose wad stats algo.ips_builder <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.ipsscan

Show ipsscan statistics.

```
diagnose wad stats algo.ipsscan <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.krl

Show krl statistics.

```
diagnose wad stats algo.krl <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.pattern_match

Show pattern_match statistics.

```
diagnose wad stats algo.pattern_match <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.proc_common

Show proc_common statistics.

```
diagnose wad stats algo.proc_common <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.sec_prof

Show sec_prof statistics.

```
diagnose wad stats algo.sec_prof <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.ssl

Show ssl statistics.

```
diagnose wad stats algo.ssl <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.url_filter

Show url_filter statistics.

```
diagnose wad stats algo.url_filter <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.urlredir

Show urlredir statistics.

```
diagnose wad stats algo.urlredir <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats algo.wisp

Show wisp statistics.


```
diagnose wad stats algo.wisp <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats cache_service

Show proc_cache_service statistics.

```
diagnose wad stats cache_service <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats cache_service.proc_common

Show proc_common statistics.

```
diagnose wad stats cache_service.proc_common <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats cache_service.tcp

Show tcp statistics.

```
diagnose wad stats cache_service.tcp <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats cic

Show proc_cic statistics.

```
diagnose wad stats cic <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats cic.proc_common

Show proc_common statistics.

```
diagnose wad stats cic.proc_common <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats cic.ssl_cic

Show ssl_cic statistics.

```
diagnose wad stats cic.ssl_cic <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats common

Show proc statistics.

```
diagnose wad stats common <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats config

Show proc_config statistics.

```
diagnose wad stats config <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats config.config

Show config statistics.

```
diagnose wad stats config.config <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats config.proc_common

Show proc_common statistics.

```
diagnose wad stats config.proc_common <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats config.shm_stats

Show shm_stats statistics.

```
diagnose wad stats config.shm_stats <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats config.sscan

Show sscan statistics.

```
diagnose wad stats config.sscan <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats debug

Show proc_debug statistics.

```
diagnose wad stats debug <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats debug.crash_handler

Show crash_handler statistics.

```
diagnose wad stats debug.crash_handler <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats debug.proc_common

Show proc_common statistics.

```
diagnose wad stats debug.proc_common <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats debug.tls_fgpt_svc_cp

Show tls_fgpt_svc_cp statistics.

```
diagnose wad stats debug.tls_fgpt_svc_cp <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats dispatcher

Show proc_dispatcher statistics.

```
diagnose wad stats dispatcher <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats dispatcher.cifs

Show cifs statistics.

```
diagnose wad stats dispatcher.cifs <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats dispatcher.dns_proxy

Show dns_proxy statistics.

```
diagnose wad stats dispatcher.dns_proxy <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats dispatcher.http_msg

Show http_msg statistics.

```
diagnose wad stats dispatcher.http_msg <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats dispatcher.icap_local_server

Show icap_local_server statistics.

```
diagnose wad stats dispatcher.icap_local_server <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats dispatcher.llm

Show llm statistics.

```
diagnose wad stats dispatcher.llm <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats dispatcher.proc_common

Show proc_common statistics.

```
diagnose wad stats dispatcher.proc_common <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats dispatcher.ssh

Show ssh statistics.

```
diagnose wad stats dispatcher.ssh <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats dispatcher.tcp

Show tcp statistics.

```
diagnose wad stats dispatcher.tcp <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats dispatcher.tunnel

Show tunnel statistics.

```
diagnose wad stats dispatcher.tunnel <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats fgpt

Show proc_fgpt statistics.

```
diagnose wad stats fgpt <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats fgpt.fgpt_self

Show fgpt_self statistics.

```
diagnose wad stats fgpt.fgpt_self <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats fgpt.proc_common

Show proc_common statistics.

```
diagnose wad stats fgpt.proc_common <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats fgpt.tls_fgpt_svc_cp

Show tls_fgpt_svc_cp statistics.

```
diagnose wad stats fgpt.tls_fgpt_svc_cp <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats ia_cache

Show proc_ia_cache statistics.

```
diagnose wad stats ia_cache <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats ia_cache.proc_common

Show proc_common statistics.

```
diagnose wad stats ia_cache.proc_common <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats informer

Show proc_informer statistics.

```
diagnose wad stats informer <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats informer.dev_info

Show dev_info statistics.

```
diagnose wad stats informer.dev_info <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats informer.dev_stats

Show dev_stats statistics.

```
diagnose wad stats informer.dev_stats <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats informer.fsae

Show fsae statistics.

```
diagnose wad stats informer.fsae <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats informer.informer_dev

Show informer_dev statistics.

```
diagnose wad stats informer.informer_dev <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats informer.informer_self

Show informer_self statistics.

```
diagnose wad stats informer.informer_self <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats informer.proc_common

Show proc_common statistics.

```
diagnose wad stats informer.proc_common <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats informer.ztna_jwt

Show ztna_jwt statistics.

```
diagnose wad stats informer.ztna_jwt <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats isolator

Show proc_isolator statistics.

```
diagnose wad stats isolator <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats isolator.dns_req

Show dns_req statistics.

```
diagnose wad stats isolator.dns_req <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats isolator.isolator_self

Show isolator_self statistics.

```
diagnose wad stats isolator.isolator_self <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats isolator.proc_common

Show proc_common statistics.

```
diagnose wad stats isolator.proc_common <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats isolator.ssl

Show ssl statistics.

```
diagnose wad stats isolator.ssl <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats isolator.tcp

Show tcp statistics.

```
diagnose wad stats isolator.tcp <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats mgr

Show proc_mgr statistics.

```
diagnose wad stats mgr <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats mgr.mgr_self

Show mgr_self statistics.

```
diagnose wad stats mgr.mgr_self <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats mgr.proc_common

Show proc_common statistics.

```
diagnose wad stats mgr.proc_common <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats mgr.shm_stats

Show shm_stats statistics.

```
diagnose wad stats mgr.shm_stats <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats uih

Show proc_uih statistics.

```
diagnose wad stats uih <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats uih.proc_common

Show proc_common statistics.

```
diagnose wad stats uih.proc_common <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats uih.uih_self

Show uih_self statistics.

```
diagnose wad stats uih.uih_self <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats usr_info

Show proc_usr_info statistics.

```
diagnose wad stats usr_info <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats usr_info.dev_info

Show dev_info statistics.

```
diagnose wad stats usr_info.dev_info <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats usr_info.dev_stats

Show dev_stats statistics.

```
diagnose wad stats usr_info.dev_stats <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats usr_info.dns_req

Show dns_req statistics.

```
diagnose wad stats usr_info.dns_req <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats usr_info.ftgd_agent

Show ftgd_agent statistics.

```
diagnose wad stats usr_info.ftgd_agent <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats usr_info.ldap

Show ldap statistics.

```
diagnose wad stats usr_info.ldap <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats usr_info.pattern_match

Show pattern_match statistics.

```
diagnose wad stats usr_info.pattern_match <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats usr_info.proc_common

Show proc_common statistics.

```
diagnose wad stats usr_info.proc_common <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats usr_info.ssl

Show ssl statistics.

```
diagnose wad stats usr_info.ssl <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats usr_info.tcp

Show tcp statistics.

```
diagnose wad stats usr_info.tcp <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats usr_info.user_device_store

Show user_device_store statistics.

```
diagnose wad stats usr_info.user_device_store <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats usr_info usr_info_self

Show usr_info_self statistics.

```
diagnose wad stats usr_info.usr_info_self <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats vfcs

Show proc_vfcs statistics.

```
diagnose wad stats vfcs <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats vfcs.proc_common

Show proc_common statistics.

```
diagnose wad stats vfcs.proc_common <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker

Show proc_worker statistics.

```
diagnose wad stats worker <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.aio

Show aio statistics.

```
diagnose wad stats worker.aio <action>
```


Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.antiphish

Show antiphish statistics.

```
diagnose wad stats worker.antiphish <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.app_mgr

Show app_mgr statistics.

```
diagnose wad stats worker.app_mgr <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.auth

Show auth statistics.

```
diagnose wad stats worker.auth <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.auth_rule

Show auth_rule statistics.

```
diagnose wad stats worker.auth_rule <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.auth_user

Show auth_user statistics.

```
diagnose wad stats worker.auth_user <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.cache_resource

Show cache_resource statistics.

```
diagnose wad stats worker.cache_resource <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.cache_store

Show cache_store statistics.

```
diagnose wad stats worker.cache_store <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.casb

Show casb statistics.

```
diagnose wad stats worker.casb <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.cert_cache

Show cert_cache statistics.

```
diagnose wad stats worker.cert_cache <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.chunk_cache

Show chunk_cache statistics.

```
diagnose wad stats worker.chunk_cache <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.cifs

Show cifs statistics.

```
diagnose wad stats worker.cifs <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.config_delta

Show config_delta statistics.

```
diagnose wad stats worker.config_delta <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.conn_pool

Show conn_pool statistics.

```
diagnose wad stats worker.conn_pool <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.db

Show db statistics.

```
diagnose wad stats worker.db <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.dev_info

Show dev_info statistics.

```
diagnose wad stats worker.dev_info <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.dev_stats

Show dev_stats statistics.

```
diagnose wad stats worker.dev_stats <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.dns_proxy

Show dns_proxy statistics.

```
diagnose wad stats worker.dns_proxy <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.dns_req

Show dns_req statistics.

```
diagnose wad stats worker.dns_req <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.fast_match

Show fast_match statistics.

```
diagnose wad stats worker.fast_match <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.fnbam

Show fnbam statistics.

```
diagnose wad stats worker.fnbam <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.fsae

Show fsae statistics.

```
diagnose wad stats worker.fsae <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.ftgd_agent

Show ftgd_agent statistics.

```
diagnose wad stats worker.ftgd_agent <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.ftp

Show ftp statistics.

```
diagnose wad stats worker.ftp <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.fw_policy

Show fw_policy statistics.

```
diagnose wad stats worker.fw_policy <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.fwd_svr

Show fwd_svr statistics.

```
diagnose wad stats worker.fwd_svr <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.http_auth

Show http_auth statistics.

```
diagnose wad stats worker.http_auth <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.http_engine

Show http_engine statistics.

```
diagnose wad stats worker.http_engine <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.http_ffbk

Show http_ffbk statistics.

```
diagnose wad stats worker.http_ffbk <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.http_msg

Show http_msg statistics.

```
diagnose wad stats worker.http_msg <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.http_scan

Show http_scan statistics.

```
diagnose wad stats worker.http_scan <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.http_srv_selector

Show http_srv_selector statistics.

```
diagnose wad stats worker.http_srv_selector <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.http_view

Show http_view statistics.

```
diagnose wad stats worker.http_view <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.icap_client

Show icap_client statistics.

```
diagnose wad stats worker.icap_client <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.icap_local_server

Show icap_local_server statistics.

```
diagnose wad stats worker.icap_local_server <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.icap_parser

Show icap_parser statistics.


```
diagnose wad stats worker.icap_parser <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.icap_remote_server

Show icap_remote_server statistics.

```
diagnose wad stats worker.icap_remote_server <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.inet_app

Show inet_app statistics.

```
diagnose wad stats worker.inet_app <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.infection_cache

Show infection_cache statistics.

```
diagnose wad stats worker.infection_cache <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.ipseng

Show ipseng statistics.

```
diagnose wad stats worker.ipseng <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.krb_pac

Show krb_pac statistics.

```
diagnose wad stats worker.krb_pac <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.krl

Show krl statistics.

```
diagnose wad stats worker.krl <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.kwd_dfa

Show kwd_dfa statistics.

```
diagnose wad stats worker.kwd_dfa <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.ldap

Show ldap statistics.

```
diagnose wad stats worker.ldap <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.llm

Show llm statistics.

```
diagnose wad stats worker.llm <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.pattern_match

Show pattern_match statistics.

```
diagnose wad stats worker.pattern_match <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.pol_test

Show pol_test statistics.

```
diagnose wad stats worker.pol_test <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.policy_profile

Show policy_profile statistics.

```
diagnose wad stats worker.policy_profile <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.proc_common

Show proc_common statistics.

```
diagnose wad stats worker.proc_common <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.protos

Show protos statistics.

```
diagnose wad stats worker.protos <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.quic

Show quic statistics.

```
diagnose wad stats worker.quic <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.runtime_info

Show runtime_info statistics.

```
diagnose wad stats worker.runtime_info <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.scan_cache

Show scan_cache statistics.

```
diagnose wad stats worker.scan_cache <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.sec_prof

Show sec_prof statistics.

```
diagnose wad stats worker.sec_prof <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.shaping

Show shaping statistics.

```
diagnose wad stats worker.shaping <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.shm_stats

Show shm_stats statistics.

```
diagnose wad stats worker.shm_stats <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.smb_prot

Show smb_prot statistics.

```
diagnose wad stats worker.smb_prot <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.ssh

Show ssh statistics.

```
diagnose wad stats worker.ssh <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.ssl

Show ssl statistics.

```
diagnose wad stats worker.ssl <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.ssl_cic

Show ssl_cic statistics.

```
diagnose wad stats worker.ssl_cic <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.systemem

Show systemem statistics.

```
diagnose wad stats worker.systemem <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.tcp

Show tcp statistics.

```
diagnose wad stats worker.tcp <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.tls_fgpt_svc_cp

Show tls_fgpt_svc_cp statistics.

```
diagnose wad stats worker.tls_fgpt_svc_cp <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.traffic_mirror

Show traffic_mirror statistics.

```
diagnose wad stats worker.traffic_mirror <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.tunnel

Show tunnel statistics.

```
diagnose wad stats worker.tunnel <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.url_filter

Show url_filter statistics.

```
diagnose wad stats worker.url_filter <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.url_match

Show url_match statistics.

```
diagnose wad stats worker.url_match <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.urlredir

Show urlredir statistics.

```
diagnose wad stats worker.urlredir <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.wisp

Show wisp statistics.

```
diagnose wad stats worker.wisp <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.worker_self

Show worker_self statistics.

```
diagnose wad stats worker.worker_self <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stats worker.ztna_jwt

Show ztna_jwt statistics.

```
diagnose wad stats worker.ztna_jwt <action>
```

Parameter	Description	Type	Size
<action>	show(default) clear history.	string	

diagnose wad stream-scan

Stream scan diagnostics.

```
diagnose wad stream-scan
```

diagnose wad stream-scan av-intf

Enable/disable AV interface.

```
diagnose wad stream-scan av-intf
```

diagnose wad stream-scan av-intf disable

Disable stream scan AV interface and restart workers.

```
diagnose wad stream-scan av-intf disable
```

diagnose wad stream-scan av-intf enable

Enable stream scan AV interface and restart workers.

```
diagnose wad stream-scan av-intf enable
```

diagnose wad stream-scan av-test

AV Engine diagnostics.

```
diagnose wad stream-scan av-test <command> <worker-id>
```

Parameter	Description	Type	Size
<command>	Command to pass into AV engine. Please double quote the command.	string	
<worker-id>	Optional worker index.	string	

diagnose wad tcp-connection

TCP connection diagnostics.

```
diagnose wad tcp-connection
```

diagnose wad tcp-connection list

List first 100 tcp connections of each worker.

```
diagnose wad tcp-connection list <worker-index>/all
```

Parameter	Description	Type	Size
<worker-index>/all	Please enter worker index or all for all workers	string	

diagnose wad toggle

Toggle diagnose method(direct/debug proc).

```
diagnose wad toggle
```

diagnose wad tp-fw-policy-test

Transparent firewall policy test.

```
diagnose wad tp-fw-policy-test <SRC> <SRC-INTF> <REQ> <AUTH_TYPE> <USER/GROUP> <SERVER>
```

Parameter	Description	Type	Size
<SRC>	Please input source IP.	string	
<SRC-INTF>	Please input source interface.	string	

Parameter	Description	Type	Size
<REQ>	Please input uri=<uri> or ipport=<ip:port> or multi-line http request.	string	
<AUTH_TYPE>	Please input authentication type: none, user or group.	string	
<USER/GROUP>	Please input username or name of matching user/group on remote authentication server.	string	
<SERVER>	Please input name of auth server.	string	

diagnose wad tp-fw-policy-test-save

Save transparent firewall policy test.

```
diagnose wad tp-fw-policy-test-save <SRC> <SRC-INTF> <REQ> <AUTH_TYPE> <USER/GROUP> <SERVER>
```

Parameter	Description	Type	Size
<SRC>	Please input source IP.	string	
<SRC-INTF>	Please input source interface.	string	
<REQ>	Please input uri=<uri> or ipport=<ip:port> or multi-line http request.	string	
<AUTH_TYPE>	Please input authentication type: none, user or group.	string	
<USER/GROUP>	Please input username or name of matching user/group on remote authentication server.	string	
<SERVER>	Please input name of auth server.	string	

diagnose wad tunnel

Tunnel diagnostics.

```
diagnose wad tunnel
```

diagnose wad tunnel clear

Clear all active tunnels.

```
diagnose wad tunnel clear
```

diagnose wad tunnel list

List active tunnels.

```
diagnose wad tunnel list <id>
```

Parameter	Description	Type	Size
<id>	Optional tunnel ID.	string	

diagnose wad url-lookup

URL category/list lookup.

```
diagnose wad url-lookup <URL>
```

Parameter	Description	Type	Size
<URL>	Please input URL.	string	

diagnose wad user

User diagnostics.

```
diagnose wad user
```

diagnose wad user clear

Clear all users or clear a particular user using: diagnose wad user clear <ID> <IP|IPv6> <VDOM>.

```
diagnose wad user clear <ID> <IP> <VDOM>
```

Parameter	Description	Type	Size
<ID>	Please input user ID.	string	
<IP>	Please input user IP.	string	
<VDOM>	Please input VDOM name the user belongs to.	string	

diagnose wad user count

Count users in each WAD worker.

```
diagnose wad user count
```

diagnose wad user device

Get device info.

```
diagnose wad user device
```

diagnose wad user domain-controller

Test connectivity with domain-controller.

```
diagnose wad user domain-controller
```

diagnose wad user domain-controller dns

Test DNS resolve function.

```
diagnose wad user domain-controller dns
```

diagnose wad user domain-controller dns list

Show DNS discover status on all configured user domain-controller.

```
diagnose wad user domain-controller dns list
```

diagnose wad user domain-controller dns test

Test if DNS discover function works for all configured user domain-controller.

```
diagnose wad user domain-controller dns test
```

diagnose wad user exchange

Test connectivity with user-exchange.

```
diagnose wad user exchange
```

diagnose wad user exchange get-matches

Test exact match search for Administrator.

```
diagnose wad user exchange get-matches
```

diagnose wad user exchange query-rows

Show address-book database up to 50 entries.

```
diagnose wad user exchange query-rows
```

diagnose wad user exchange reset

Close all connections related to user-exchange.

```
diagnose wad user exchange reset
```

diagnose wad user exchange resolve-names

Test pattern match search for Administrator.

```
diagnose wad user exchange resolve-names
```

diagnose wad user exchange test-auto-discover

Test if automatic discovery can work on all configured user-exchanges.

```
diagnose wad user exchange test-auto-discover
```

diagnose wad user filter

Set filter to query proxy users.

```
diagnose wad user filter <string>
```

Parameter	Description	Type	Size
<string>	user name.	string	

diagnose wad user list

List proxy users.

```
diagnose wad user list [verbose]
```

Parameter	Description	Type	Size
[verbose]	Verbose mode.	string	

diagnose wad webcache

Web cache statistics.

```
diagnose wad webcache
```

diagnose wad webcache clear

Clear web cache statistics.

```
diagnose wad webcache clear
```

diagnose wad webcache list

List web cache statistics.

```
diagnose wad webcache list <period>
```

Parameter	Description	Type	Size
<period>	10min hour day 30days.	string	

diagnose wad webproxy

Webproxy diagnostics.

```
diagnose wad webproxy
```

diagnose wad webproxy clear

Enter a webproxy name to clear this particular webproxy, otherwise this clears all webproxies.

```
diagnose wad webproxy clear <webproxy>
```

Parameter	Description	Type	Size
<webproxy>	webproxy name.	string	

diagnose wad webproxy forward-server

Forward server diagnostics.

```
diagnose wad webproxy forward-server
```

diagnose wad webproxy forward-server detail

Per worker forward server diagnostics.

```
diagnose wad webproxy forward-server detail
```

diagnose wad webproxy forward-server summary

General forward server diagnostics.

```
diagnose wad webproxy forward-server summary
```

diagnose wad webproxy forward-server-group

Forward server group diagnostics.

```
diagnose wad webproxy forward-server-group
```

diagnose wad webproxy list

List webproxies.

```
diagnose wad webproxy list
```


diagnose wad worker

Worker diagnostics.

```
diagnose wad worker
```

diagnose wad worker avscan

Scan results statistics.

```
diagnose wad worker avscan
```

diagnose wad worker avscan clear

Clear scan results statistics.

```
diagnose wad worker avscan clear
```

diagnose wad worker avscan list

List scan results statistics.

```
diagnose wad worker avscan list
```

diagnose wad worker bytecache

Bytecache diagnostics.

```
diagnose wad worker bytecache
```

diagnose wad worker bytecache clear

Purge all entries.

```
diagnose wad worker bytecache clear [<index>]
```

Parameter	Description	Type	Size
[<index>]	Worker index or all workers if not set.	string	

diagnose wad worker bytcache flush

Reset statistics.

```
diagnose wad worker bytcache flush [<index>]
```

Parameter	Description	Type	Size
[<index>]	Worker index or all workers if not set.	string	

diagnose wad worker bytcache stats

Show statistics.

```
diagnose wad worker bytcache stats [<index>]
```

Parameter	Description	Type	Size
[<index>]	Worker index or all workers if not set.	string	

diagnose wad worker cookie

Cookie information.

```
diagnose wad worker cookie
```

diagnose wad worker cookie map

Show cookie map info.

```
diagnose wad worker cookie map
```

diagnose wad worker filter

Show filter statistics.

```
diagnose wad worker filter
```

diagnose wad worker filter clear

Clear filter statistics.

```
diagnose wad worker filter clear
```

diagnose wad worker filter list

List filter statistics.

```
diagnose wad worker filter list
```

diagnose wad worker imagecache

Imagecache diagnostics.

```
diagnose wad worker imagecache
```

diagnose wad worker imagecache flush

Flush all blocked images in the ram disk.

```
diagnose wad worker imagecache flush
```

diagnose wad worker imagecache stats

Show statistics of blocked image cache.

```
diagnose wad worker imagecache stats
```

diagnose wad worker memcache

Memcache diagnostics.

```
diagnose wad worker memcache
```

diagnose wad worker memcache clear

Purge all entries.

```
diagnose wad worker memcache clear [<index>]
```

Parameter	Description	Type	Size
[<index>]	Worker index or all workers if not set.	string	

diagnose wad worker memcache flush

Reset statistics.

```
diagnose wad worker memcache flush [<index>]
```

Parameter	Description	Type	Size
[<index>]	Worker index or all workers if not set.	string	

diagnose wad worker memcache stats

Show statistics.

```
diagnose wad worker memcache stats [<index>]
```

Parameter	Description	Type	Size
[<index>]	Worker index or all workers if not set.	string	

diagnose wad worker peer

Show peer statistics.

```
diagnose wad worker peer
```

diagnose wad worker peer clear

Clear peer statistics.

```
diagnose wad worker peer clear
```

diagnose wad worker peer list

List peer statistics.

```
diagnose wad worker peer list
```

diagnose wad worker policy

Show policy statistics.

```
diagnose wad worker policy
```

diagnose wad worker policy clear

Clear policy statistics.

```
diagnose wad worker policy clear
```

diagnose wad worker policy list

List policy statistics.

```
diagnose wad worker policy list
```

diagnose wad worker restart

Restart workers.

```
diagnose wad worker restart [<index>]
```

Parameter	Description	Type	Size
[<index>]	Worker index or all workers if not set.	string	

diagnose wad worker scripts

Show scripts statistics.

```
diagnose wad worker scripts
```

diagnose wad worker scripts clear

Clear scripts statistics.

```
diagnose wad worker scripts clear
```

diagnose wad worker scripts list

List scripts statistics.

```
diagnose wad worker scripts list
```

diagnose wad worker webcache

Webcache diagnostics.

```
diagnose wad worker webcache
```

diagnose wad worker webcache clear

Purge all entries.

```
diagnose wad worker webcache clear [<index>]
```

Parameter	Description	Type	Size
[<index>]	Worker index or all workers if not set.	string	

diagnose wad worker webcache flush

Reset statistics.

```
diagnose wad worker webcache flush [<index>]
```

Parameter	Description	Type	Size
[<index>]	Worker index or all workers if not set.	string	

diagnose wad worker webcache stats

Show statistics.

```
diagnose wad worker webcache stats [<index>]
```

Parameter	Description	Type	Size
[<index>]	Worker index or all workers if not set.	string	

diagnose wad worker webcache summary

List statistics summary.

```
diagnose wad worker webcache summary
```

diagnose wadbd

WAN accelerator DB daemon.

This topic includes the following commands:

- [diagnose wadbd clear on page 1799](#)
- [diagnose wadbd log-show on page 1799](#)
- [diagnose wadbd restart on page 1800](#)
- [diagnose wadbd stats on page 1800](#)

diagnose wadbd clear

Remove all entries from the database.

```
diagnose wadbd clear
```

diagnose wadbd log-show

Show log of daemon

```
diagnose wadbd log-show <Disk index> <log generation> <time format>
```

Parameter	Description	Type	Size
<Disk index>	Disk index	string	
<log generation>	Log generation: default 0	string	
<time format>	Time format: 0 for human readable and 1 for raw, default 0	string	

diagnose wadbd restart

Restart the daemon and reset the statistical parameters.

```
diagnose wadbd restart
```

diagnose wadbd stats

Show statistics.

```
diagnose wadbd stats
```

diagnose waf

WAF diagnostics.

This topic includes the following commands:

- [diagnose waf dump on page 1800](#)
- [diagnose waf info on page 1800](#)

diagnose waf dump

Dump WAF name table.

```
diagnose waf dump
```

diagnose waf info

Init WAF name table.


```
diagnose waf info
```

diagnose webfilter

webfilter

This topic includes the following commands:

- [diagnose webfilter bword on page 1801](#)
- [diagnose webfilter bword matchfilter on page 1801](#)
- [diagnose webfilter fortiguard on page 1802](#)
- [diagnose webfilter fortiguard cache on page 1802](#)
- [diagnose webfilter fortiguard cache dump on page 1802](#)
- [diagnose webfilter fortiguard cache obs on page 1802](#)
- [diagnose webfilter fortiguard cache prefix on page 1802](#)
- [diagnose webfilter fortiguard cache tree on page 1802](#)
- [diagnose webfilter fortiguard cache ttl on page 1803](#)
- [diagnose webfilter fortiguard override on page 1803](#)
- [diagnose webfilter fortiguard override all-admin-override on page 1803](#)
- [diagnose webfilter fortiguard override all-user-override on page 1803](#)
- [diagnose webfilter fortiguard override all-warning on page 1803](#)
- [diagnose webfilter fortiguard override obs on page 1803](#)
- [diagnose webfilter fortiguard override statistics on page 1804](#)
- [diagnose webfilter fortiguard statistics on page 1804](#)
- [diagnose webfilter fortiguard statistics flush on page 1804](#)
- [diagnose webfilter fortiguard statistics list on page 1804](#)

diagnose webfilter bword

Web banned word match filter.

```
diagnose webfilter bword
```

diagnose webfilter bword matchfilter

Filtered list display.

```
diagnose webfilter bword matchfilter <filter string>
```

Parameter	Description	Type	Size
<filter string>	Filter string from end of web filter banned word log line. For example: '1-n8 4 0 1 4 10 nC 4'	string	

diagnose webfilter fortiguard

FortiGuard Web Filter information

```
diagnose webfilter fortiguard
```

diagnose webfilter fortiguard cache

Display WF cache content.

```
diagnose webfilter fortiguard cache
```

diagnose webfilter fortiguard cache dump

Display WF cache contents.

```
diagnose webfilter fortiguard cache dump
```

diagnose webfilter fortiguard cache obs

Display WF cache OBS info.

```
diagnose webfilter fortiguard cache obs
```

diagnose webfilter fortiguard cache prefix

Display WF cache contents of prefix type.

```
diagnose webfilter fortiguard cache prefix
```

diagnose webfilter fortiguard cache tree

Display WF cache in tree format.

```
diagnose webfilter fortiguard cache tree
```

diagnose webfilter fortiguard cache ttl

Display WF cache TTL list.

```
diagnose webfilter fortiguard cache ttl
```

diagnose webfilter fortiguard override

Display override content.

```
diagnose webfilter fortiguard override
```

diagnose webfilter fortiguard override all-admin-override

Display admin override entries of all vdoms.

```
diagnose webfilter fortiguard override all-admin-override
```

diagnose webfilter fortiguard override all-user-override

Display user override entries of all vdoms.

```
diagnose webfilter fortiguard override all-user-override
```

diagnose webfilter fortiguard override all-warning

Display warning/authentication entries of all vdoms.

```
diagnose webfilter fortiguard override all-warning
```

diagnose webfilter fortiguard override obs

Display override cache OBS info.

```
diagnose webfilter fortiguard override obs
```

diagnose webfilter fortiguard override statistics

Display override cache statistics.

```
diagnose webfilter fortiguard override statistics
```

diagnose webfilter fortiguard statistics

Rating cache and daemon statistics.

```
diagnose webfilter fortiguard statistics
```

diagnose webfilter fortiguard statistics flush

Flush rating cache and daemon statistics.

```
diagnose webfilter fortiguard statistics flush
```

diagnose webfilter fortiguard statistics list

Display rating cache and daemon statistics.

```
diagnose webfilter fortiguard statistics list
```

diagnose web-ui

Web user interface.

This topic includes the following commands:

- [diagnose web-ui api-cache on page 1805](#)
- [diagnose web-ui api-cache statistic on page 1805](#)
- [diagnose web-ui api-stats on page 1805](#)
- [diagnose web-ui api-stats disable on page 1805](#)
- [diagnose web-ui api-stats enable on page 1805](#)
- [diagnose web-ui api-stats list on page 1805](#)
- [diagnose web-ui api-stats reset on page 1806](#)
- [diagnose web-ui api-stats status on page 1806](#)
- [diagnose web-ui backtrace on page 1806](#)
- [diagnose web-ui backtrace clear on page 1806](#)

- [diagnose web-ui backtrace disable on page 1806](#)
- [diagnose web-ui backtrace enable on page 1806](#)
- [diagnose web-ui backtrace httpsd on page 1807](#)
- [diagnose web-ui backtrace status on page 1807](#)

diagnose web-ui api-cache

shows statistics of REST API caching.

```
diagnose web-ui api-cache
```

diagnose web-ui api-cache statistic

Show REST API cache statistics.

```
diagnose web-ui api-cache statistic
```

diagnose web-ui api-stats

REST API performance statistics.

```
diagnose web-ui api-stats
```

diagnose web-ui api-stats disable

Disable REST API performance statistics.

```
diagnose web-ui api-stats disable
```

diagnose web-ui api-stats enable

Enable REST API performance statistics.

```
diagnose web-ui api-stats enable
```

diagnose web-ui api-stats list

List all REST API performance statistics.

```
diagnose web-ui api-stats list <api-uri>
```

Parameter	Description	Type	Size
<api-uri>	API access URI/prefix. (type.path.name.action)	string	

diagnose web-ui api-stats reset

Reset all REST API performance statistics.

```
diagnose web-ui api-stats reset
```

diagnose web-ui api-stats status

Status of REST API performance statistics.

```
diagnose web-ui api-stats status
```

diagnose web-ui backtrace

Web-ui backtrace.

```
diagnose web-ui backtrace
```

diagnose web-ui backtrace clear

Clear all backtrace log.

```
diagnose web-ui backtrace clear
```

diagnose web-ui backtrace disable

Disable web-ui backtrace.

```
diagnose web-ui backtrace disable
```

diagnose web-ui backtrace enable

Enable web-ui backtrace.

```
diagnose web-ui backtrace enable
```

diagnose web-ui backtrace httpsd

List all httpsd backtrace.

```
diagnose web-ui backtrace httpsd <pid>
```

Parameter	Description	Type	Size
<pid>	Details of httpsd backtrace.	string	

diagnose web-ui backtrace status

Status of web-ui backtrace.

```
diagnose web-ui backtrace status
```

CLI execute commands

Use execute commands to run system commands.

This section includes syntax for the following commands:

- [execute api-user on page 1810](#)
- [execute auto-script on page 1810](#)
- [execute backup on page 1813](#)
- [execute batch on page 1827](#)
- [execute central-mgmt on page 1828](#)
- [execute cfg on page 1829](#)
- [execute clear on page 1830](#)
- [execute cli on page 1830](#)
- [execute config-transaction on page 1831](#)
- [execute cpu on page 1832](#)
- [execute date on page 1832](#)
- [execute device-upgrade on page 1833](#)
- [execute dhcp on page 1833](#)
- [execute dhcp6 on page 1834](#)
- [execute disconnect-admin-session on page 1835](#)
- [execute disk on page 1835](#)
- [execute enter on page 1836](#)
- [execute erase-disk on page 1836](#)
- [execute fabric-vpn on page 1837](#)
- [execute factoryreset-for-central-management on page 1838](#)
- [execute factoryreset-shutdown on page 1838](#)
- [execute factoryreset on page 1837](#)
- [execute factoryreset2 on page 1837](#)
- [execute fctems on page 1838](#)
- [execute federated-upgrade on page 1839](#)
- [execute firewall on page 1841](#)
- [execute formatlogdisk on page 1842](#)
- [execute forticloud-sandbox on page 1842](#)
- [execute fortiguard-log on page 1843](#)
- [execute fortiguard-message on page 1844](#)
- [execute fortitoken-cloud on page 1847](#)
- [execute fortitoken-mobile on page 1849](#)
- [execute fortitoken on page 1844](#)
- [execute fsso on page 1850](#)
- [execute ha on page 1850](#)

- [execute http-view on page 1852](#)
- [execute interface on page 1853](#)
- [execute internet-service4 on page 1854](#)
- [execute internet-service6 on page 1854](#)
- [execute ipam on page 1854](#)
- [execute log on page 1855](#)
- [execute mem on page 1863](#)
- [execute nethsm on page 1863](#)
- [execute nsx on page 1871](#)
- [execute ping-options on page 1876](#)
- [execute ping on page 1872](#)
- [execute ping6-options on page 1872](#)
- [execute ping6 on page 1872](#)
- [execute policy-packet-capture on page 1880](#)
- [execute preload on page 1880](#)
- [execute private-encryption-key on page 1882](#)
- [execute reboot on page 1883](#)
- [execute report-config on page 1884](#)
- [execute report on page 1883](#)
- [execute restore on page 1884](#)
- [execute revision on page 1895](#)
- [execute send-fds-statistics on page 1896](#)
- [execute send-fmg-list on page 1896](#)
- [execute set on page 1896](#)
- [execute shutdown on page 1903](#)
- [execute speed-test-dynamic on page 1903](#)
- [execute speed-test-server on page 1904](#)
- [execute speed-test on page 1903](#)
- [execute ssh-options on page 1906](#)
- [execute ssh-regen-keys on page 1907](#)
- [execute ssh on page 1904](#)
- [execute ssh6-options on page 1905](#)
- [execute ssh6 on page 1904](#)
- [execute sync-IPSec on page 1907](#)
- [execute sync-session on page 1907](#)
- [execute system on page 1907](#)
- [execute tac on page 1908](#)
- [execute telnet-options on page 1909](#)
- [execute telnet on page 1909](#)
- [execute time on page 1910](#)
- [execute traceroute-options on page 1911](#)
- [execute traceroute on page 1910](#)
- [execute tracert6 on page 1912](#)

- [execute upd-vd-license on page 1914](#)
- [execute update-av on page 1912](#)
- [execute update-external-resource on page 1912](#)
- [execute update-ffdb-on-demand on page 1913](#)
- [execute update-geo-ip on page 1913](#)
- [execute update-ips on page 1913](#)
- [execute update-list on page 1913](#)
- [execute update-now on page 1913](#)
- [execute update-src-vis on page 1914](#)
- [execute upload on page 1914](#)
- [execute usb-device on page 1918](#)
- [execute usb-disk on page 1919](#)
- [execute vm-license-options on page 1921](#)
- [execute vm-license on page 1920](#)
- [execute vpn on page 1923](#)
- [execute wake-on-lan on page 1934](#)
- [execute webcache on page 1934](#)
- [execute webfilter on page 1935](#)

execute api-user

api-user

This topic includes the following commands:

- [execute api-user generate-key on page 1810](#)

execute api-user generate-key

Generate key for API users.

```
execute api-user generate-key <name>
```

Parameter	Description	Type	Size
<name>	API user name.	string	

execute auto-script

auto-script

This topic includes the following commands:

- [execute auto-script backup ftp on page 1811](#)
- [execute auto-script backup tftp on page 1811](#)
- [execute auto-script delete on page 1811](#)
- [execute auto-script result on page 1812](#)
- [execute auto-script start on page 1812](#)
- [execute auto-script status on page 1812](#)
- [execute auto-script stop on page 1812](#)
- [execute auto-script stopall on page 1813](#)

execute auto-script backup ftp

Backup output file to FTP sever.

```
execute auto-script backup ftp <name> <ftp server>[:ftp port] <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<name>	Script name.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute auto-script backup tftp

Backup output file to TFTP sever.

```
execute auto-script backup tftp <name> <tftp server>
```

Parameter	Description	Type	Size
<name>	Script name.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute auto-script delete

Delete output of executed scripts.

```
execute auto-script delete <name>
```

Parameter	Description	Type	Size
<name>	Script name.	string	

execute auto-script result

Display output of executed scripts.

```
execute auto-script result <name>
```

Parameter	Description	Type	Size
<name>	Script name.	string	

execute auto-script start

Start script.

```
execute auto-script start <name>
```

Parameter	Description	Type	Size
<name>	Script name.	string	

execute auto-script status

List of scripts currently running or executed.

```
execute auto-script status
```

execute auto-script stop

Stop script.

```
execute auto-script stop <name>
```

Parameter	Description	Type	Size
<name>	Script name.	string	

execute auto-script stopall

Stop all scripts currently running.

```
execute auto-script stopall
```

execute backup

backup

This topic includes the following commands:

- [execute backup config flash on page 1814](#)
- [execute backup config ftp on page 1814](#)
- [execute backup config management-station on page 1815](#)
- [execute backup config sftp on page 1815](#)
- [execute backup config tftp on page 1815](#)
- [execute backup config usb on page 1816](#)
- [execute backup config usb-mode on page 1816](#)
- [execute backup disk alllogs ftp on page 1816](#)
- [execute backup disk alllogs tftp on page 1816](#)
- [execute backup disk alllogs usb on page 1817](#)
- [execute backup disk ipsarchives ftp on page 1817](#)
- [execute backup disk ipsarchives tftp on page 1817](#)
- [execute backup disk ipsarchives usb on page 1817](#)
- [execute backup disk log ftp on page 1818](#)
- [execute backup disk log tftp on page 1818](#)
- [execute backup disk log usb on page 1818](#)
- [execute backup full-config ftp on page 1819](#)
- [execute backup full-config sftp on page 1819](#)
- [execute backup full-config tftp on page 1819](#)
- [execute backup full-config usb on page 1820](#)
- [execute backup full-config usb-mode on page 1820](#)
- [execute backup ipsuserdefsig ftp on page 1820](#)
- [execute backup ipsuserdefsig tftp on page 1821](#)
- [execute backup memory alllogs ftp on page 1821](#)
- [execute backup memory alllogs tftp on page 1821](#)
- [execute backup memory log ftp on page 1821](#)
- [execute backup memory log tftp on page 1822](#)
- [execute backup obfuscated-config ftp on page 1822](#)
- [execute backup obfuscated-config management-station on page 1823](#)
- [execute backup obfuscated-config sftp on page 1823](#)

- [execute backup obfuscated-config tftp on page 1823](#)
- [execute backup obfuscated-config usb on page 1824](#)
- [execute backup obfuscated-full-config ftp on page 1824](#)
- [execute backup obfuscated-full-config sftp on page 1824](#)
- [execute backup obfuscated-full-config tftp on page 1825](#)
- [execute backup obfuscated-full-config usb on page 1825](#)
- [execute backup obfuscated-yaml-config ftp on page 1825](#)
- [execute backup obfuscated-yaml-config tftp on page 1826](#)
- [execute backup tls-finger-print tftp on page 1826](#)
- [execute backup yaml-config ftp on page 1826](#)
- [execute backup yaml-config tftp on page 1827](#)

execute backup config flash

Backup config file to flash.

```
execute backup config flash <comment>
```

Parameter	Description	Type	Size
<comment>	Make a comment for this config backup.	string	

execute backup config ftp

Backup config file to FTP server.

```
execute backup config ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd>  
<Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the FTP server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup config management-station

Backup config file to management station.

```
execute backup config management-station <comment>
```

Parameter	Description	Type	Size
<comment>	Make a comment for this config backup.	string	

execute backup config sftp

Backup config file to SFTP server.

```
execute backup config sftp <string> <sftp server>[:sftp port] <user> <passwd> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the SFTP server.	string	
<sftp server>[:sftp port]	SFTP server IPv4, IPv6 can be attached with port.	string	
<user>	SFTP username.	string	
<passwd>	SFTP password.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup config tftp

Backup config file to TFTP server.

```
execute backup config tftp <string> <tftp server> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup config usb

Backup config file to USB disk.

```
execute backup config usb <string> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name on the USB disk.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup config usb-mode

Backup config file for USB mode.

```
execute backup config usb-mode <Enter>|<passwd>
```

Parameter	Description	Type	Size
<Enter> <passwd>	Optional password to protect the backup file.	string	

execute backup disk alllogs ftp

Backup all log files to FTP server.

```
execute backup disk alllogs ftp <ftp server>[:ftp port] <Enter>|<user> <passwd> <Enter>|<string>
```

Parameter	Description	Type	Size
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	
<Enter> <string>	Optional log file compression option [uncompressed compressed].	string	

execute backup disk alllogs tftp

Backup all log file(s) to TFTP server.

```
execute backup disk alllogs tftp <tftp server>
```


Parameter	Description	Type	Size
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute backup disk alllogs usb

Backup all log files to USB.

```
execute backup disk alllogs usb
```

execute backup disk ipsarchives ftp

Backup IPS archive file(s) to FTP server.

```
execute backup disk ipsarchives ftp <ftp server>[:ftp port] <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute backup disk ipsarchives tftp

Backup IPS archive file(s) to TFTP server.

```
execute backup disk ipsarchives tftp <tftp server>
```

Parameter	Description	Type	Size
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute backup disk ipsarchives usb

Backup IPS archive file(s) to USB.

```
execute backup disk ipsarchives usb
```

execute backup disk log ftp

Backup specific log file(s) to FTP server.

```
execute backup disk log ftp <ftp server>[:ftp port] <user> <passwd> <string> <Enter>|<string>
```

Parameter	Description	Type	Size
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<user>	FTP username.	string	
<passwd>	FTP password.	string	
<string>	, traffic, event, virus, webfilter, ips, emailfilter, anomaly, voip, dlp, app-ctrl, waf, dns, ssh, ssl, file-filter, icap, sctp-filter, forti-switch, casb	string	
<Enter> <string>	Optional log file compression option [uncompressed compressed].	string	

execute backup disk log tftp

Backup specific log file(s) to TFTP server.

```
execute backup disk log tftp <tftp server> <string>
```

Parameter	Description	Type	Size
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	
<string>	, traffic, event, virus, webfilter, ips, emailfilter, anomaly, voip, dlp, app-ctrl, waf, dns, ssh, ssl, file-filter, icap, sctp-filter, forti-switch, casb	string	

execute backup disk log usb

Backup specific log file(s) to USB.

```
execute backup disk log usb <string>
```

Parameter	Description	Type	Size
<string>	, traffic, event, virus, webfilter, ips, emailfilter, anomaly, voip, dlp, app-ctrl, waf, dns, ssh, ssl, file-filter, icap, sctp-filter, forti-switch, casb	string	

execute backup full-config ftp

Backup full config file to FTP server.

```
execute backup full-config ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd>  
<Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the FTP server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup full-config sftp

Backup full config file to SFTP server.

```
execute backup full-config sftp <string> <sftp server>[:sftp port] <user> <passwd>  
<Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the SFTP server.	string	
<sftp server>[:sftp port]	SFTP server IPv4, IPv6 can be attached with port.	string	
<user>	SFTP username.	string	
<passwd>	SFTP password.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup full-config tftp

Backup full config file to TFTP server.

```
execute backup full-config tftp <string> <tftp server> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup full-config usb

Backup full config file to USB disk.

```
execute backup full-config usb <string> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name on the USB disk.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup full-config usb-mode

Backup full config file for USB mode.

```
execute backup full-config usb-mode <Enter>|<passwd>
```

Parameter	Description	Type	Size
<Enter> <passwd>	Optional password to protect the backup file.	string	

execute backup ipsuserdefsig ftp

Backup user defined IPS signatures to FTP server.

```
execute backup ipsuserdefsig ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the FTP server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute backup ipsuserdefsig tftp

Backup user defined IPS signatures to TFTP server.

```
execute backup ipsuserdefsig tftp <string> <tftp server>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute backup memory alllogs ftp

Backup all log files to FTP server.

```
execute backup memory alllogs ftp <ftp server>[:ftp port] <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute backup memory alllogs tftp

Backup all log file(s) to TFTP server.

```
execute backup memory alllogs tftp <tftp server>
```

Parameter	Description	Type	Size
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute backup memory log ftp

Backup specific log file(s) to FTP server.

```
execute backup memory log ftp <ftp server>[:ftp port] <user> <passwd> <string>
```

Parameter	Description	Type	Size
<ftp server> [:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<user>	FTP username.	string	
<passwd>	FTP password.	string	
<string>	, traffic, event, virus, webfilter, ips, emailfilter, anomaly, voip, dlp, app-ctrl, waf, dns, ssh, ssl, file-filter, icap, sctp-filter, forti-switch, casb	string	

execute backup memory log tftp

Backup specific log file(s) to TFTP server.

```
execute backup memory log tftp <tftp server> <string>
```

Parameter	Description	Type	Size
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	
<string>	, traffic, event, virus, webfilter, ips, emailfilter, anomaly, voip, dlp, app-ctrl, waf, dns, ssh, ssl, file-filter, icap, sctp-filter, forti-switch, casb	string	

execute backup obfuscated-config ftp

Backup obfuscated config file to FTP server.

```
execute backup obfuscated-config ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd>  
<Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the FTP server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup obfuscated-config management-station

Backup obfuscated config file to management station.

```
execute backup obfuscated-config management-station <comment>
```

Parameter	Description	Type	Size
<comment>	Make a comment for this config backup.	string	

execute backup obfuscated-config sftp

Backup obfuscated config file to SFTP server.

```
execute backup obfuscated-config sftp <string> <sftp server>[:sftp port] <user> <passwd>  
<Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the SFTP server.	string	
<sftp server>[:sftp port]	SFTP server IPv4, IPv6 can be attached with port.	string	
<user>	SFTP username.	string	
<passwd>	SFTP password.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup obfuscated-config tftp

Backup obfuscated config file to TFTP server.

```
execute backup obfuscated-config tftp <string> <tftp server> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup obfuscated-config usb

Backup obfuscated config file to USB disk.

```
execute backup obfuscated-config usb <string> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name on the USB disk.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup obfuscated-full-config ftp

Backup obfuscated full config file to FTP server.

```
execute backup obfuscated-full-config ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd>  
<Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the FTP server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup obfuscated-full-config sftp

Backup obfuscated full config file to SFTP server.

```
execute backup obfuscated-full-config sftp <string> <sftp server>[:sftp port] <user> <passwd>  
<Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the SFTP server.	string	
<sftp server>[:sftp port]	SFTP server IPv4, IPv6 can be attached with port.	string	

Parameter	Description	Type	Size
<user>	SFTP username.	string	
<passwd>	SFTP password.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup obfuscated-full-config tftp

Backup obfuscated full config file to TFTP server.

```
execute backup obfuscated-full-config tftp <string> <tftp server> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup obfuscated-full-config usb

Backup obfuscated full config file to USB disk.

```
execute backup obfuscated-full-config usb <string> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name on the USB disk.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup obfuscated-yaml-config ftp

Backup obfuscated YAML config file to FTP server.

```
execute backup obfuscated-yaml-config ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the FTP server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup obfuscated-yaml-config tftp

Backup obfuscated YAML config file to TFTP server.

```
execute backup obfuscated-yaml-config tftp <string> <tftp server> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup tls-finger-print tftp

Backup config file to TFTP server.

```
execute backup tls-finger-print tftp <string> <tftp server> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup yaml-config ftp

Backup YAML config file to FTP server.

```
execute backup yaml-config ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd>  
<Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the FTP server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute backup yaml-config tftp

Backup YAML config file to TFTP server.

```
execute backup yaml-config tftp <string> <tftp server> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Make a file name (path) on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	
<Enter> <passwd>	Optional password to protect the backup content.	string	

execute batch

batch

This topic includes the following commands:

- [execute batch end on page 1827](#)
- [execute batch lastlog on page 1828](#)
- [execute batch start on page 1828](#)
- [execute batch status on page 1828](#)

execute batch end

Batch mode end.

```
execute batch end
```

execute batch lastlog

Read the result of last batch commands.

```
execute batch lastlog
```

execute batch start

Batch mode start.

```
execute batch start
```

execute batch status

Batch mode status.

```
execute batch status
```

execute central-mgmt

central-mgmt

This topic includes the following commands:

- [execute central-mgmt register-device on page 1828](#)
- [execute central-mgmt set-mgmt-id on page 1829](#)
- [execute central-mgmt unregister-device on page 1829](#)

execute central-mgmt register-device

Register device to FortiManager from unregistered device list.

```
execute central-mgmt register-device <fmg-serial-no> <fmg-register-password>
```

Parameter	Description	Type	Size
<fmg-serial-no>	FortiManager serial number.	string	
<fmg-register-password>	Register password in to FortiManager.	string	

execute central-mgmt set-mgmt-id

Management ID of Central Management Service.

```
execute central-mgmt set-mgmt-id <management id>
```

Parameter	Description	Type	Size
<management id>	Management ID (must be entered in encrypted format).	string	

execute central-mgmt unregister-device

Remove device from its manager's device list.

```
execute central-mgmt unregister-device <fmg-serial-no>
```

Parameter	Description	Type	Size
<fmg-serial-no>	FortiManager serial number.	string	

execute cfg

cfg

This topic includes the following commands:

- [execute cfg reload on page 1829](#)
- [execute cfg save on page 1830](#)

execute cfg reload

Reboot to reload the configs.

```
execute cfg reload
```

execute cfg save

Save configs.

```
execute cfg save
```

execute clear

clear

This topic includes the following commands:

- [execute clear system arp table on page 1830](#)

execute clear system arp table

Clear system ARP table.

```
execute clear system arp table
```

execute cli

cli

This topic includes the following commands:

- [execute cli check-template-status on page 1830](#)
- [execute cli status-msg-only on page 1831](#)

execute cli check-template-status

Check SCP script template running status.

```
execute cli check-template-status
```

execute cli status-msg-only

CLI standardized error output.

```
execute cli status-msg-only <enable/disable>
```

Parameter	Description	Type	Size
<enable/disable>	Enable/disable CLI standardized error output.	string	

execute config-transaction

config-transaction

This topic includes the following commands:

- [execute config-transaction abort on page 1831](#)
- [execute config-transaction commit on page 1831](#)
- [execute config-transaction start on page 1831](#)

execute config-transaction abort

Abort configuration transaction.

```
execute config-transaction abort
```

execute config-transaction commit

Commit configuration transaction.

```
execute config-transaction commit
```

execute config-transaction start

Start configuration transaction.

```
execute config-transaction start <integer>
```

Parameter	Description	Type	Size
<integer>	Transaction timeout in minutes (1 - 60). Default value is 5.	string	

execute cpu

cpu

This topic includes the following commands:

- [execute cpu add on page 1832](#)
- [execute cpu show on page 1832](#)

execute cpu add

Activate new CPU.

```
execute cpu add <number>
```

Parameter	Description	Type	Size
<number>	New Active CPU Number.	string	

execute cpu show

Show CPU number.

```
execute cpu show
```

execute date

System date.

```
execute date <yyyy-mm-dd>
```

Parameter	Description	Type	Size
<yyyy-mm-dd>	yyyy: 2001-2037, mm: 1-12, dd: 1-31.	string	

execute device-upgrade

device-upgrade

This topic includes the following commands:

- [execute device-upgrade cancel on page 1833](#)
- [execute device-upgrade immediate on page 1833](#)

execute device-upgrade cancel

Cancel a Fortinet device's upgrade by removing it from the upgrade table.

```
execute device-upgrade cancel <serial>
```

Parameter	Description	Type	Size
<serial>	Serial number of the Fortinet device to upgrade.	string	

execute device-upgrade immediate

Configure a Fortinet device to upgrade immediately.

```
execute device-upgrade immediate <device-type> <serial> <major> <minor> <patch>
```

Parameter	Description	Type	Size
<device-type>	Fortinet device type to upgrade.	string	
<serial>	Fortinet device serial number to upgrade.	string	
<major>	Major version of the Fortinet OS image being upgraded to.	string	
<minor>	Minor version of the Fortinet OS image being upgraded to.	string	
<patch>	Patch version of the Fortinet OS image being upgraded to.	string	

execute dhcp

dhcp

This topic includes the following commands:

- [execute dhcp lease-clear on page 1834](#)
- [execute dhcp lease-list on page 1834](#)

execute dhcp lease-clear

Clear all DHCP leases.

```
execute dhcp lease-clear <IPv4 address> or <IPv4 starting address-IPv4 ending address> <all>
```

Parameter	Description	Type	Size
<IPv4 address> or <IPv4 starting address-IPv4 ending address>	Clear lease(s) on this IP address.	string	
<all>	Clear all leases.	string	

execute dhcp lease-list

List all DHCP leases.

```
execute dhcp lease-list <interface>
```

Parameter	Description	Type	Size
<interface>	List leases on this interface.	string	

execute dhcp6

dhcp6

This topic includes the following commands:

- [execute dhcp6 lease-clear on page 1835](#)
- [execute dhcp6 lease-list on page 1835](#)

execute dhcp6 lease-clear

Clear all DHCPv6 leases.

```
execute dhcp6 lease-clear <IPv6 address> or <IPv6 starting address-IPv6 ending address> <all>
```

Parameter	Description	Type	Size
<IPv6 address> or <IPv6 starting address-IPv6 ending address>	Clear lease(s) on this IPv6 address.	string	
<all>	Clear all leases.	string	

execute dhcp6 lease-list

List all DHCPv6 leases.

```
execute dhcp6 lease-list <interface>
```

Parameter	Description	Type	Size
<interface>	List leases on this interface.	string	

execute disconnect-admin-session

Disconnect logged-in admin user.

```
execute disconnect-admin-session <integer>
```

Parameter	Description	Type	Size
<integer>	Index of user to be disconnected in logged-users table.	string	

execute disk

disk

This topic includes the following commands:

- [execute disk format on page 1836](#)
- [execute disk list on page 1836](#)
- [execute disk scan on page 1836](#)

execute disk format

Format a partition.

```
execute disk format
```

execute disk list

List disk devices and partitions.

```
execute disk list
```

execute disk scan

Scan a partition and fix errors.

```
execute disk scan
```

execute enter

Select virtual domain.

```
execute enter <name>
```

Parameter	Description	Type	Size
<name>	VDOM name.	string	

execute erase-disk

Erase a disk.

```
execute erase-disk
```

execute fabric-vpn

fabric-vpn

This topic includes the following commands:

- [execute fabric-vpn flush-setup on page 1837](#)
- [execute fabric-vpn update-setup on page 1837](#)

execute fabric-vpn flush-setup

Remove fabric VPN settings.

```
execute fabric-vpn flush-setup
```

execute fabric-vpn update-setup

Update fabric VPN setup.

```
execute fabric-vpn update-setup
```

execute factoryreset

Reset to factory default now.

```
execute factoryreset <keepvmlicense>
```

Parameter	Description	Type	Size
<keepvmlicense>	Keep VM license.	string	

execute factoryreset2

Reset to factory default except system.global.vdom-mode/system.global.long-vdom-name/VDOMS/system.virtual-switch/system.interface/system.settings/router.static/router.static6.

```
execute factoryreset2 <keepvmlicense>
```

Parameter	Description	Type	Size
<keepvmlicense>	Keep VM license.	string	

execute factoryreset-for-central-management

Reset to factory default except system.central-management.serial-number/system.central-management.fmg.

```
execute factoryreset-for-central-management <keepvmlicense>
```

Parameter	Description	Type	Size
<keepvmlicense>	Keep VM license.	string	

execute factoryreset-shutdown

Reset to factory default and shutdown.

```
execute factoryreset-shutdown <keepvmlicense>
```

Parameter	Description	Type	Size
<keepvmlicense>	Keep VM license.	string	

execute fctems

fctems

This topic includes the following commands:

- [execute fctems is-verified on page 1839](#)
- [execute fctems unverify on page 1839](#)
- [execute fctems verify on page 1839](#)

execute fctems is-verified

Check if Configured EMS server has a verified certificate.

```
execute fctems is-verified <fctems>
```

Parameter	Description	Type	Size
<fctems>	FortiClient EMS table entry id in CMDB.	string	

execute fctems unverify

Unverify FortiClient EMS server.

```
execute fctems unverify <fctems>
```

Parameter	Description	Type	Size
<fctems>	FortiClient EMS table entry id in CMDB.	string	

execute fctems verify

Verify FortiClient EMS server.

```
execute fctems verify <fctems>
```

Parameter	Description	Type	Size
<fctems>	FortiClient EMS table entry id in CMDB.	string	

execute federated-upgrade

federated-upgrade

This topic includes the following commands:

- [execute federated-upgrade cancel on page 1840](#)
- [execute federated-upgrade initialize on page 1840](#)
- [execute federated-upgrade quick-fortigate-upgrade on page 1840](#)
- [execute federated-upgrade quick-full-upgrade on page 1840](#)
- [execute federated-upgrade restart on page 1841](#)
- [execute federated-upgrade status on page 1841](#)

execute federated-upgrade cancel

Cancel the currently configured upgrade.

```
execute federated-upgrade cancel
```

execute federated-upgrade initialize

Set up a federated upgrade.

```
execute federated-upgrade initialize
```

execute federated-upgrade quick-fortigate-upgrade

Set up a 15 minute immediate mode upgrade for all FortiGates in the CSF tree.

```
execute federated-upgrade quick-fortigate-upgrade <major> <minor> <patch> <delay-minutes> <max-minutes>
```

Parameter	Description	Type	Size
<major>	Major version of the Fortinet OS image being upgraded to.	string	
<minor>	Minor version of the Fortinet OS image being upgraded to.	string	
<patch>	Patch version of the Fortinet OS image being upgraded to.	string	
<delay-minutes>	Minutes to delay before starting the upgrade setup.	string	
<max-minutes>	Number of minutes allowed for upgrade preparation.	string	

execute federated-upgrade quick-full-upgrade

Set up a 15 minute immediate mode upgrade for all CSF devices.

```
execute federated-upgrade quick-full-upgrade <major> <minor> <patch> <delay-minutes> <max-minutes>
```


Parameter	Description	Type	Size
<major>	Major version of the Fortinet OS image being upgraded to.	string	
<minor>	Minor version of the Fortinet OS image being upgraded to.	string	
<patch>	Patch version of the Fortinet OS image being upgraded to.	string	
<delay-minutes>	Minutes to delay before starting the upgrade setup.	string	
<max-minutes>	Number of minutes allowed for upgrade preparation.	string	

execute federated-upgrade restart

Restart the currently configured federated upgrade.

```
execute federated-upgrade restart
```

execute federated-upgrade status

Show the current status of federated upgrade.

```
execute federated-upgrade status
```

execute firewall

firewall

This topic includes the following commands:

- [execute firewall ssh generate local-ca on page 1841](#)
- [execute firewall ssh generate local-key on page 1842](#)

execute firewall ssh generate local-ca

Generate the default ssh local key.

```
execute firewall ssh generate local-ca <string>
```

Parameter	Description	Type	Size
<string>	Local CA name.	string	

execute firewall ssh generate local-key

Generate the default ssh local key.

```
execute firewall ssh generate local-key <string>
```

Parameter	Description	Type	Size
<string>	Local key name.	string	

execute formatlogdisk

Format log disk.

```
execute formatlogdisk
```

execute forticloud-sandbox

forticloud-sandbox

This topic includes the following commands:

- [execute forticloud-sandbox region on page 1842](#)
- [execute forticloud-sandbox update on page 1842](#)

execute forticloud-sandbox region

Get FortiCloud sandbox region.

```
execute forticloud-sandbox region
```

execute forticloud-sandbox update

Update FortiCloud sandbox contract.

```
execute forticloud-sandbox update
```

execute fortiguard-log

fortiguard-log

This topic includes the following commands:

- [execute fortiguard-log certificate-activation on page 1843](#)
- [execute fortiguard-log migration on page 1843](#)
- [execute fortiguard-log update on page 1843](#)

execute fortiguard-log certificate-activation

Activate FortiCloud certification.

```
execute fortiguard-log certificate-activation <code>
```

Parameter	Description	Type	Size
<code>	Activation code.	string	

execute fortiguard-log migration

Migrate standalone FortiProxy Cloud account to FortiCloud.

```
execute fortiguard-log migration <password>
```

Parameter	Description	Type	Size
<password>	Password.	string	

execute fortiguard-log update

Update FortiCloud Contract.

```
execute fortiguard-log update
```

execute fortiguard-message

fortiguard-message

This topic includes the following commands:

- [execute fortiguard-message add on page 1844](#)
- [execute fortiguard-message info on page 1844](#)
- [execute fortiguard-message update on page 1844](#)

execute fortiguard-message add

Add FortiGuard Message Service activation code.

```
execute fortiguard-message add <activation code>
```

Parameter	Description	Type	Size
<activation code>	Activation code for FortiGuard Message Service.	string	

execute fortiguard-message info

Show info about FortiGuard Message Service.

```
execute fortiguard-message info
```

execute fortiguard-message update

Force to update FortiGuard Message Service.

```
execute fortiguard-message update
```

execute fortitoken

fortitoken

This topic includes the following commands:

- [execute fortitoken activate on page 1845](#)
- [execute fortitoken import ftp on page 1846](#)

- [execute fortitoken import tftp on page 1846](#)
- [execute fortitoken import usb on page 1846](#)
- [execute fortitoken import-sn-file on page 1846](#)
- [execute fortitoken sync on page 1847](#)

execute fortitoken activate

Activate FortiToken(s) with FortiGuard.

```
execute fortitoken activate <id> <id> <id> <id> <id> <id> <id> <id> <id> <id> <id> <id> <id> <id> <id> <id> <id> <id> <id> <id>
```

Parameter	Description	Type	Size
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	
<id>	FortiToken ID.	string	

execute fortitoken import ftp

Import FortiToken seeds file from FTP server.

```
execute fortitoken import ftp <file name> <ftp server>[:ftp port] <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<file name>	FortiToken seeds file name.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute fortitoken import tftp

Import FortiToken seeds file from TFTP server.

```
execute fortitoken import tftp <file name> <tftp server>
```

Parameter	Description	Type	Size
<file name>	FortiToken seeds file name.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute fortitoken import usb

Import FortiToken seeds file from USB drive.

```
execute fortitoken import usb <file name>
```

Parameter	Description	Type	Size
<file name>	FortiToken seeds file name.	string	

execute fortitoken import-sn-file

Import FTK_200 serial number from FortiCare.

```
execute fortitoken import-sn-file <FTK_200 Serial Number>
```

Parameter	Description	Type	Size
<FTK_200 Serial Number>	FTK_200 serial number.	string	

execute fortitoken sync

Synchronize FortiToken by adjusting for drift of internal clock.

```
execute fortitoken sync <id> <code> <next code>
```

Parameter	Description	Type	Size
<id>	FortiToken ID.	string	
<code>	FortiToken code.	string	
<next code>	Next FortiToken code.	string	

execute fortitoken-cloud

fortitoken-cloud

This topic includes the following commands:

- [execute fortitoken-cloud migrate-ftm on page 1847](#)
- [execute fortitoken-cloud new on page 1848](#)
- [execute fortitoken-cloud show on page 1848](#)
- [execute fortitoken-cloud sync on page 1848](#)
- [execute fortitoken-cloud trial on page 1848](#)
- [execute fortitoken-cloud update on page 1848](#)

execute fortitoken-cloud migrate-ftm

Migrate FortiToken service to FortiToken Cloud.

```
execute fortitoken-cloud migrate-ftm <license number> <vdom>
```

Parameter	Description	Type	Size
<license number>	FortiToken mobile license number.	string	
<vdom>	VDOM name.	string	

execute fortitoken-cloud new

Send new activation code for a user.

```
execute fortitoken-cloud new <user name> <user type> <vdom>
```

Parameter	Description	Type	Size
<user name>	User name for new token.	string	
<user type>	Enter admin, local or remote.	string	
<vdom>	VDOM name.	string	

execute fortitoken-cloud show

Show service status of this FortiProxy.

```
execute fortitoken-cloud show
```

execute fortitoken-cloud sync

Synchronize users to FortiToken Cloud.

```
execute fortitoken-cloud sync <user type>
```

Parameter	Description	Type	Size
<user type>	Enter <return>, all, local or remote.	string	

execute fortitoken-cloud trial

Activate free trial.

```
execute fortitoken-cloud trial
```

execute fortitoken-cloud update

Update VDOM list to FortiToken Cloud.

```
execute fortitoken-cloud update
```


execute fortitoken-mobile

fortitoken-mobile

This topic includes the following commands:

- [execute fortitoken-mobile import on page 1849](#)
- [execute fortitoken-mobile poll on page 1849](#)
- [execute fortitoken-mobile provision on page 1849](#)
- [execute fortitoken-mobile renew on page 1849](#)

execute fortitoken-mobile import

Import a list of tokens from FortiGuard to the FortiProxy unit.

```
execute fortitoken-mobile import <code>
```

Parameter	Description	Type	Size
<code>	Software Token Redemption Certificate.	string	

execute fortitoken-mobile poll

Poll soft token states.

```
execute fortitoken-mobile poll
```

execute fortitoken-mobile provision

Provision a soft token.

```
execute fortitoken-mobile provision <sn>
```

Parameter	Description	Type	Size
<sn>	MobileToken serial number.	string	

execute fortitoken-mobile renew

Renew a locked mobile FortiToken.

```
execute fortitoken-mobile renew <sn>
```

Parameter	Description	Type	Size
<sn>	MobileToken serial number.	string	

execute fsso

fsso

This topic includes the following commands:

- [execute fsso refresh on page 1850](#)

execute fsso refresh

Refresh FSSO groups.

```
execute fsso refresh
```

execute ha

ha

This topic includes the following commands:

- [execute ha disconnect on page 1850](#)
- [execute ha failover set on page 1851](#)
- [execute ha failover status on page 1851](#)
- [execute ha failover unset on page 1851](#)
- [execute ha manage on page 1852](#)
- [execute ha synchronize on page 1852](#)

execute ha disconnect

Disconnect from HA cluster.

```
execute ha disconnect <string> <string> <ip> <netmask>
```

Parameter	Description	Type	Size
<string>	Serial number.	string	

Parameter	Description	Type	Size
<string>	Interface name.	string	
<ip>	IP or subnet of the interface.	string	
<netmask>	Netmask of the interface.	string	

execute ha failover set

Set the given virtual cluster as slave and trigger failover. Argument optional; if argument omitted, all virtual clusters are affected.

```
execute ha failover set [integer]
```

Parameter	Description	Type	Size
[integer]	Virtual cluster ID. Optional; if not given, all virtual clusters are affected.	string	

execute ha failover status

Display whether the given virtual cluster has been set as slave for failover. Argument optional; if no argument given, display statuses of all virtual clusters.

```
execute ha failover status [integer]
```

Parameter	Description	Type	Size
[integer]	Virtual cluster ID. Optional; if not given, all virtual clusters are affected.	string	

execute ha failover unset

If the given virtual cluster has been set as slave before, unset it so HA will use normal criteria to decide the master. May trigger a failover. Argument optional; if argument not given, all virtual clusters are affected.

```
execute ha failover unset [integer]
```

Parameter	Description	Type	Size
[integer]	Virtual cluster ID. Optional; if not given, all virtual clusters are affected.	string	

execute ha manage

HA cluster index.

```
execute ha manage <string> <string>
```

Parameter	Description	Type	Size
<string>	HA cluster index.	string	
<string>	Login admin name.	string	

execute ha synchronize

HA synchronize commands.

```
execute ha synchronize <string>
```

Parameter	Description	Type	Size
<string>	File type.	string	

execute http-view

http-view

This topic includes the following commands:

- [execute http-view report on page 1852](#)

execute http-view report

Report latest HTTP/S traffic statistics

```
execute http-view report <type> <top n> <minutes>
```

Parameter	Description	Type	Size
<type>	Numeric, report type	string	
<top n>	Number of top entries to display (5 - 100)	string	
<minutes>	Duration of recent time to report (1 - Max-Configured)	string	

execute interface

interface

This topic includes the following commands:

- [execute interface dhcp6client-renew on page 1853](#)
- [execute interface dhcpclient-renew on page 1853](#)
- [execute interface pppoe-reconnect on page 1853](#)

execute interface dhcp6client-renew

Renew DHCPv6 lease.

```
execute interface dhcp6client-renew <interface>
```

Parameter	Description	Type	Size
<interface>	Renew DHCPv6 lease on this interface.	string	

execute interface dhcpclient-renew

Renew DHCP lease.

```
execute interface dhcpclient-renew <interface>
```

Parameter	Description	Type	Size
<interface>	Renew DHCP lease on this interface.	string	

execute interface pppoe-reconnect

Reconnect to PPPoE server.

```
execute interface pppoe-reconnect <interface>
```

Parameter	Description	Type	Size
<interface>	Reconnect PPPoE on this interface.	string	

execute internet-service4

internet-service4

This topic includes the following commands:

- [execute internet-service4 refresh on page 1854](#)

execute internet-service4 refresh

Refresh Internet Service database (IPv4).

```
execute internet-service4 refresh
```

execute internet-service6

internet-service6

This topic includes the following commands:

- [execute internet-service6 refresh on page 1854](#)

execute internet-service6 refresh

Refresh Internet Service database (IPv6).

```
execute internet-service6 refresh
```

execute ipam

ipam

This topic includes the following commands:

- [execute ipam create-dhcp-server on page 1854](#)

execute ipam create-dhcp-server

Create a DHCP server managed by IPAM.

```
execute ipam create-dhcp-server <interface>
```

Parameter	Description	Type	Size
<interface>	Interface for the DHCP server.	string	

execute log

log

This topic includes the following commands:

- [execute log backup ftp on page 1856](#)
- [execute log backup local on page 1856](#)
- [execute log backup tftp on page 1856](#)
- [execute log delete on page 1857](#)
- [execute log delete-all on page 1857](#)
- [execute log detail on page 1857](#)
- [execute log display on page 1857](#)
- [execute log filter category on page 1857](#)
- [execute log filter device on page 1858](#)
- [execute log filter dump on page 1858](#)
- [execute log filter field on page 1858](#)
- [execute log filter free-style on page 1859](#)
- [execute log filter ha-member on page 1859](#)
- [execute log filter local-search-mode on page 1859](#)
- [execute log filter max-checklines on page 1859](#)
- [execute log filter pre-fetch-pages on page 1859](#)
- [execute log filter reset on page 1860](#)
- [execute log filter start-line on page 1860](#)
- [execute log filter view-lines on page 1860](#)
- [execute log flush-cache on page 1860](#)
- [execute log flush-cache-all on page 1861](#)
- [execute log fortianalyzer manual-failover on page 1861](#)
- [execute log fortianalyzer test-connectivity on page 1861](#)
- [execute log fortianalyzer-cloud test-connectivity on page 1861](#)
- [execute log fortianalyzer2 manual-failover on page 1861](#)
- [execute log fortianalyzer3 manual-failover on page 1861](#)
- [execute log fortiguard test-connectivity on page 1862](#)
- [execute log list on page 1862](#)
- [execute log raw-backup ftp on page 1862](#)
- [execute log raw-backup tftp on page 1862](#)

- [execute log roll on page 1863](#)
- [execute log upload on page 1863](#)
- [execute log upload-progress on page 1863](#)

execute log backup ftp

Backup logs and report databases to remote FTP server.

```
execute log backup ftp <filename> <ftp server>[:ftp port] <user> <passwd>
```

Parameter	Description	Type	Size
<filename>	Make file name on the remote FTP server	string	
<ftp server> [:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<user>	FTP username.	string	
<passwd>	FTP password.	string	

execute log backup local

Backup logs and report databases to local storage device.

```
execute log backup local <path>
```

Parameter	Description	Type	Size
<path>	Path to store logs and report databases.	string	

execute log backup tftp

Backup logs and report databases to remote TFTP server.

```
execute log backup tftp <filename> <tftp server>
```

Parameter	Description	Type	Size
<filename>	Make file name on the remote TFTP server	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute log delete

Delete local logs of one category.

```
execute log delete
```

execute log delete-all

Delete all local logs and recreate report database.

```
execute log delete-all
```

execute log detail

Display utm log entries for a particular traffic log.

```
execute log detail <category> <utmref>
```

Parameter	Description	Type	Size
<category>	Category for UTM logs	string	
<utmref>	You can copy and paste it from log display result by tuning on it using 'exec log filter show-utm-ref 1'	string	

execute log display

Display filtered log entries.

```
execute log display
```

execute log filter category

Category.

```
execute log filter category <category>
```

Parameter	Description	Type	Size
<category>	Category name, press enter for options.	string	

execute log filter device

Device to get log from.

```
execute log filter device <device>
```

Parameter	Description	Type	Size
<device>	Device name, press enter for options.	string	

execute log filter dump

Dump current filter settings.

```
execute log filter dump
```

execute log filter field

Filter by field.

```
execute log filter field <name> <argument 1> <argument 2> <argument 3> <argument 4> <argument 5>  
<argument 6> <argument 7>
```

Parameter	Description	Type	Size
<name>	Field name, press enter for options.	string	
<argument 1>	Field search argument 1, press enter for more help.	string	
<argument 2>	<argument 2>	string	
<argument 3>	<argument 3>	string	
<argument 4>	<argument 4>	string	
<argument 5>	<argument 5>	string	
<argument 6>	<argument 6>	string	
<argument 7>	<argument 7>	string	

execute log filter free-style

Filter by free-style expression.

```
execute log filter free-style <expression>
```

Parameter	Description	Type	Size
<expression>	Log filter expression.	string	

execute log filter ha-member

HA member.

```
execute log filter ha-member <sn>
```

Parameter	Description	Type	Size
<sn>	Serial number of HA member.	string	

execute log filter local-search-mode

local log search mode

```
execute log filter local-search-mode <mode>
```

Parameter	Description	Type	Size
<mode>	Local log search mode, press enter for options.	string	

execute log filter max-checklines

Maximum number of lines to check.

```
execute log filter max-checklines <number>
```

Parameter	Description	Type	Size
<number>	0 or (100 - 1000000).	string	

execute log filter pre-fetch-pages

Number of pages to check in advance under on-demand log search mode.

```
execute log filter pre-fetch-pages <number>
```

Parameter	Description	Type	Size
<number>	(2 - 10).	string	

execute log filter reset

Reset filter.

```
execute log filter reset <enter|all|field>
```

Parameter	Description	Type	Size
<enter all field>	<enter all> to reset all, <field> to reset field only.	string	

execute log filter start-line

Start line to display.

```
execute log filter start-line <number>
```

Parameter	Description	Type	Size
<number>	>=1	string	

execute log filter view-lines

Lines per view.

```
execute log filter view-lines <number>
```

Parameter	Description	Type	Size
<number>	Number of lines to view (5 - 1000).	string	

execute log flush-cache

Write disk log cache of current category to disk in compressed format.

```
execute log flush-cache
```

execute log flush-cache-all

Write disk log cache of all categories to disk in compressed format.

```
execute log flush-cache-all
```

execute log fortianalyzer manual-failover

Manually failover to use the other server.

```
execute log fortianalyzer manual-failover
```

execute log fortianalyzer test-connectivity

Query FortiAnalyzer connection status.

```
execute log fortianalyzer test-connectivity
```

execute log fortianalyzer-cloud test-connectivity

Query FortiAnalyzer Cloud connection status.

```
execute log fortianalyzer-cloud test-connectivity
```

execute log fortianalyzer2 manual-failover

Manually failover to use the other server.

```
execute log fortianalyzer2 manual-failover
```

execute log fortianalyzer3 manual-failover

Manually failover to use the other server.

```
execute log fortianalyzer3 manual-failover
```

execute log fortiguard test-connectivity

Query FortiGuard connection status.

```
execute log fortiguard test-connectivity
```

execute log list

List current and rolled log files info.

```
execute log list <category>
```

Parameter	Description	Type	Size
<category>	Category name, press enter for options.	string	

execute log raw-backup ftp

Backup raw logs to remote FTP server.

```
execute log raw-backup ftp <remotedir> <ftp server>[:ftp port] <user> <passwd>
```

Parameter	Description	Type	Size
<remotedir>	Remote directory on FTP server	string	
<ftp server> [:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<user>	FTP username.	string	
<passwd>	FTP password.	string	

execute log raw-backup tftp

Backup raw logs to remote TFTP server.

```
execute log raw-backup tftp <remotedir> <tftp server>
```

Parameter	Description	Type	Size
<remotedir>	Existing remote directory on TFTP server	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute log roll

Roll log files now.

```
execute log roll
```

execute log upload

Upload log and archives to FortiAnalyzer/FortiCloud.

```
execute log upload
```

execute log upload-progress

Check FortiCloud upload progress.

```
execute log upload-progress
```

execute mem

mem

This topic includes the following commands:

- [execute mem add on page 1863](#)

execute mem add

Online new memory blocks.

```
execute mem add
```

execute nethsm

nethsm

This topic includes the following commands:

- [execute nethsm primus clear-pkcs-provider-log on page 1864](#)
- [execute nethsm primus clear-primus-log on page 1864](#)
- [execute nethsm primus delete-object on page 1865](#)
- [execute nethsm primus dump-pkcs-provider-log on page 1865](#)
- [execute nethsm primus dump-primus-log on page 1865](#)
- [execute nethsm primus inspect-primus-library-info on page 1865](#)
- [execute nethsm primus list-objects on page 1865](#)
- [execute nethsm primus upload-primus-cfg on page 1865](#)
- [execute nethsm primus upload-primus-cfg-raw on page 1866](#)
- [execute nethsm safenet clear-log on page 1866](#)
- [execute nethsm safenet client-cert-create on page 1866](#)
- [execute nethsm safenet client-cert-export ftp on page 1867](#)
- [execute nethsm safenet client-cert-export tftp on page 1867](#)
- [execute nethsm safenet client-cert-show on page 1867](#)
- [execute nethsm safenet config-export ftp on page 1867](#)
- [execute nethsm safenet config-export tftp on page 1868](#)
- [execute nethsm safenet config-import ftp on page 1868](#)
- [execute nethsm safenet config-import tftp on page 1868](#)
- [execute nethsm safenet config-show on page 1869](#)
- [execute nethsm safenet diagnose on page 1869](#)
- [execute nethsm safenet hagroup-add on page 1869](#)
- [execute nethsm safenet hagroup-del on page 1869](#)
- [execute nethsm safenet hagroup-list on page 1869](#)
- [execute nethsm safenet register on page 1870](#)
- [execute nethsm safenet reset on page 1870](#)
- [execute nethsm safenet restore-conf on page 1870](#)
- [execute nethsm safenet set-conf-opt on page 1870](#)
- [execute nethsm safenet show-log on page 1870](#)
- [execute nethsm safenet status on page 1870](#)
- [execute nethsm safenet unregister on page 1871](#)

execute nethsm primus clear-pkcs-provider-log

Clear logs from /var/log/pkcs11.log, generated by pkcs11.so, the OpenSSL provider.

```
execute nethsm primus clear-pkcs-provider-log
```

execute nethsm primus clear-primus-log

Clear logs from /var/log/primus.log, generated by libprimusP11.so.

```
execute nethsm primus clear-primus-log
```


execute nethsm primus delete-object

Delete Hardware Security Module object(s).

```
execute nethsm primus delete-object <label>
```

Parameter	Description	Type	Size
<label>	Label of the HSM object(s) to delete.	string	

execute nethsm primus dump-pkcs-provider-log

Dump logs from /var/log/pkcs11.log, generated by pkcs11.so, the OpenSSL provider.

```
execute nethsm primus dump-pkcs-provider-log
```

execute nethsm primus dump-primus-log

Dump logs from /var/log/primus.log, generated by libprimusP11.so.

```
execute nethsm primus dump-primus-log
```

execute nethsm primus inspect-primus-library-info

Display information about the integrated libprimusP11.so library.

```
execute nethsm primus inspect-primus-library-info
```

execute nethsm primus list-objects

List Hardware Security Module objects.

```
execute nethsm primus list-objects
```

execute nethsm primus upload-primus-cfg

Upload nethsm primus.cfg file.

```
execute nethsm primus upload-primus-cfg <filename> <tftp server>
```

Parameter	Description	Type	Size
<filename>	File name on the TFTP server.	string	
<tftp server>	TFTP server IP or FQDN.	string	

execute nethsm primus upload-primus-cfg-raw

Upload nethsm primus.cfg file.

```
execute nethsm primus upload-primus-cfg-raw <filename> <tftp server>
```

Parameter	Description	Type	Size
<filename>	File name on the TFTP server.	string	
<tftp server>	TFTP server IP or FQDN.	string	

execute nethsm safenet clear-log

Clear NETHSM log.

```
execute nethsm safenet clear-log
```

execute nethsm safenet client-cert-create

(Re)Create client certificate.

```
execute nethsm safenet client-cert-create <string> <string> <string> <string> <string> <string>
```

Parameter	Description	Type	Size
<string>	Country name (e.g. Canada) or country code (e.g. ca).	string	
<string>	State.	string	
<string>	City.	string	
<string>	Org.	string	
<string>	Unit.	string	
<string>	Email.	string	

execute nethsm safenet client-cert-export ftp

Export client certificate over FTP

```
execute nethsm safenet client-cert-export ftp <ftp server>[:ftp port] <remote-path> <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<ftp server>[:ftp port]	FTP server IP, can be attached with port.	string	
<remote-path>	FTP remote directory.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute nethsm safenet client-cert-export tftp

Export client certificate over TFTP

```
execute nethsm safenet client-cert-export tftp <ip>
```

Parameter	Description	Type	Size
<ip>	IP address of TFTP server.	string	

execute nethsm safenet client-cert-show

Display client certificate

```
execute nethsm safenet client-cert-show
```

execute nethsm safenet config-export ftp

Import nethsm config from a FTP server.

```
execute nethsm safenet config-export ftp <ip>[:ftp port] <remote-path> <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<ip>[:ftp port]	FTP server IP, can also include port.	string	
<remote-path>	FTP remote directory.	string	

Parameter	Description	Type	Size
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute nethsm safenet config-export tftp

Export nethsm config over TFTP

```
execute nethsm safenet config-export tftp <ip>
```

Parameter	Description	Type	Size
<ip>	IP address of TFTP server.	string	

execute nethsm safenet config-import ftp

Export nethsm config over FTP

```
execute nethsm safenet config-import ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<string>	File name on the FTP server.	string	
<ftp server>[:ftp port]	FTP server IP, can also include port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute nethsm safenet config-import tftp

Import nethsm config from a TFTP server.

```
execute nethsm safenet config-import tftp <string> <ip>
```

Parameter	Description	Type	Size
<string>	File name on the TFTP server.	string	
<ip>	IP address of TFTP server.	string	

execute nethsm safenet config-show

Display nethsm config

```
execute nethsm safenet config-show
```

execute nethsm safenet diagnose

Partition diagnose.

```
execute nethsm safenet diagnose
```

execute nethsm safenet hagroup-add

Add HA group.

```
execute nethsm safenet hagroup-add <hagroup>
```

Parameter	Description	Type	Size
<hagroup>	HSM HA group name.	string	

execute nethsm safenet hagroup-del

Delete HA group.

```
execute nethsm safenet hagroup-del <hagroup>
```

Parameter	Description	Type	Size
<hagroup>	HSM HA group name.	string	

execute nethsm safenet hagroup-list

List HA group.

```
execute nethsm safenet hagroup-list <hagroup>
```

Parameter	Description	Type	Size
<hagroup>	HSM HA group name.	string	

execute nethsm safenet register

Register to network HSM server.

```
execute nethsm safenet register <server>
```

Parameter	Description	Type	Size
<server>	HSM server name.	string	

execute nethsm safenet reset

Erase all NETHSM config.

```
execute nethsm safenet reset
```

execute nethsm safenet restore-conf

Restore NETHSM config.

```
execute nethsm safenet restore-conf
```

execute nethsm safenet set-conf-opt

Set NETHSM config option.

```
execute nethsm safenet set-conf-opt
```

execute nethsm safenet show-log

Show NETHSM log.

```
execute nethsm safenet show-log
```

execute nethsm safenet status

Client status.

```
execute nethsm safenet status <server>
```

Parameter	Description	Type	Size
<server>	HSM server name.	string	

execute nethsm safenet unregister

Unregister from network HSM server.

```
execute nethsm safenet unregister <server>
```

Parameter	Description	Type	Size
<server>	HSM server name.	string	

execute nsx

nsx

This topic includes the following commands:

- [execute nsx group delete on page 1871](#)
- [execute nsx group import on page 1871](#)
- [execute nsx group list on page 1872](#)

execute nsx group delete

Delete NSX Security Groups.

```
execute nsx group delete <vdom> <filter>
```

Parameter	Description	Type	Size
<vdom>	VDOM.	string	
<filter>	Name Filter.	string	

execute nsx group import

Import NSX Security Groups.

```
execute nsx group import <name> <vdom> <filter>
```

Parameter	Description	Type	Size
<name>	SDN connector.	string	
<vdom>	VDOM.	string	
<filter>	Name Filter.	string	

execute nsx group list

List NSX Security Groups.

```
execute nsx group list <name> <filter>
```

Parameter	Description	Type	Size
<name>	SDN connector.	string	
<filter>	Name Filter.	string	

execute ping

PING command.

```
execute ping <ip>
```

Parameter	Description	Type	Size
<ip>	IP address or domain name.	string	

execute ping6

PINGv6 command.

```
execute ping6
```

execute ping6-options

ping6-options

This topic includes the following commands:

- [execute ping6-options adaptive-ping on page 1873](#)
- [execute ping6-options data-size on page 1873](#)
- [execute ping6-options interface on page 1873](#)
- [execute ping6-options interval on page 1874](#)
- [execute ping6-options pattern on page 1874](#)
- [execute ping6-options repeat-count on page 1874](#)
- [execute ping6-options reset on page 1874](#)
- [execute ping6-options source6 on page 1875](#)
- [execute ping6-options timeout on page 1875](#)
- [execute ping6-options tos on page 1875](#)
- [execute ping6-options ttl on page 1875](#)
- [execute ping6-options validate-reply on page 1876](#)
- [execute ping6-options view-settings on page 1876](#)

execute ping6-options adaptive-ping

Adaptive ping <enable|disable>.

```
execute ping6-options adaptive-ping <string>
```

Parameter	Description	Type	Size
<string>	<enable disable>.	string	

execute ping6-options data-size

Integer value to specify datagram size in bytes.

```
execute ping6-options data-size <integer>
```

Parameter	Description	Type	Size
<integer>	Integer value [0,65507].	string	

execute ping6-options interface

Auto | <outgoing interface>.

```
execute ping6-options interface <string>
```

Parameter	Description	Type	Size
<string>	Auto <outgoing interface>.	string	

execute ping6-options interval

Integer value to specify seconds to wait between two pings.

```
execute ping6-options interval <integer>
```

Parameter	Description	Type	Size
<integer>	Integer value [1, 2147483647]	string	

execute ping6-options pattern

Hex format of pattern, e.g. 00ffaabb.

```
execute ping6-options pattern <string>
```

Parameter	Description	Type	Size
<string>	Hex format of pattern, e.g. 00ffaabb.	string	

execute ping6-options repeat-count

Integer value to specify how many times to repeat PING.

```
execute ping6-options repeat-count <string>
```

Parameter	Description	Type	Size
<string>	Integer value [1, 2147483647]	string	

execute ping6-options reset

Reset settings.

```
execute ping6-options reset
```

execute ping6-options source6

Auto | <source interface IPv6>.

```
execute ping6-options source6 <xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx>
```

Parameter	Description	Type	Size
<xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx>	<source interface IPv6> Auto	string	

execute ping6-options timeout

Integer value to specify timeout in seconds.

```
execute ping6-options timeout <integer>
```

Parameter	Description	Type	Size
<integer>	Integer value [0, 2147483647]	string	

execute ping6-options tos

IPv6 type-of-service (traffic class) value.

```
execute ping6-options tos <integer>
```

Parameter	Description	Type	Size
<integer>	Hex number [0x00, 0xFF]	string	

execute ping6-options ttl

Integer value to specify time-to-live.

```
execute ping6-options ttl <integer>
```

Parameter	Description	Type	Size
<integer>	Integer value [1,255]	string	

execute ping6-options validate-reply

Validate reply data <yes | no>.

```
execute ping6-options validate-reply <string>
```

Parameter	Description	Type	Size
<string>	<yes no>.	string	

execute ping6-options view-settings

View the current settings for PING option.

```
execute ping6-options view-settings
```

execute ping-options

ping-options

This topic includes the following commands:

- [execute ping-options adaptive-ping on page 1876](#)
- [execute ping-options data-size on page 1877](#)
- [execute ping-options df-bit on page 1877](#)
- [execute ping-options interface on page 1877](#)
- [execute ping-options interval on page 1877](#)
- [execute ping-options pattern on page 1878](#)
- [execute ping-options repeat-count on page 1878](#)
- [execute ping-options reset on page 1878](#)
- [execute ping-options source on page 1878](#)
- [execute ping-options timeout on page 1879](#)
- [execute ping-options tos on page 1879](#)
- [execute ping-options ttl on page 1879](#)
- [execute ping-options use-sdwan on page 1879](#)
- [execute ping-options validate-reply on page 1880](#)
- [execute ping-options view-settings on page 1880](#)

execute ping-options adaptive-ping

Adaptive ping <enable|disable>.

```
execute ping-options adaptive-ping <string>
```

Parameter	Description	Type	Size
<string>	<enable disable>.	string	

execute ping-options data-size

Integer value to specify datagram size in bytes.

```
execute ping-options data-size <integer>
```

Parameter	Description	Type	Size
<integer>	Integer value [0,65507].	string	

execute ping-options df-bit

Set DF bit in IP header <yes | no>.

```
execute ping-options df-bit <string>
```

Parameter	Description	Type	Size
<string>	<yes no>.	string	

execute ping-options interface

Auto | <outgoing interface>.

```
execute ping-options interface <string>
```

Parameter	Description	Type	Size
<string>	Auto <outgoing interface>.	string	

execute ping-options interval

Integer value to specify seconds between two pings.

```
execute ping-options interval <integer>
```

Parameter	Description	Type	Size
<integer>	Integer value [1, 2147483647]	string	

execute ping-options pattern

Hex format of pattern, e.g. 00ffaabb.

```
execute ping-options pattern <string>
```

Parameter	Description	Type	Size
<string>	Hex format of pattern, e.g. 00ffaabb.	string	

execute ping-options repeat-count

Integer value to specify how many times to repeat PING.

```
execute ping-options repeat-count <integer>
```

Parameter	Description	Type	Size
<integer>	Integer value [1, 2147483647]	string	

execute ping-options reset

Reset settings.

```
execute ping-options reset
```

execute ping-options source

Auto | <source interface IP>.

```
execute ping-options source <xxx.xxx.xxx.xxx>
```

Parameter	Description	Type	Size
<xxx.xxx.xxx.xxx>	<source interface IP> Auto	string	

execute ping-options timeout

Integer value to specify timeout in seconds.

```
execute ping-options timeout <integer>
```

Parameter	Description	Type	Size
<integer>	Integer value [0, 2147483647]	string	

execute ping-options tos

IP type-of-service option.

```
execute ping-options tos <string>
```

Parameter	Description	Type	Size
<string>	default IP TOS defaults to 0 lowcost IP TOS minimize cost lowdelay IP TOS minimize delay reliability IP TOS maximize reliability throughput IP TOS maximize throughput	string	

execute ping-options ttl

Integer value to specify time-to-live.

```
execute ping-options ttl <integer>
```

Parameter	Description	Type	Size
<integer>	Integer value [1,255].	string	

execute ping-options use-sdwan

Use SD-WAN rules to get output interface <yes | no>.

```
execute ping-options use-sdwan <string>
```

Parameter	Description	Type	Size
<string>	<yes no>.	string	

execute ping-options validate-reply

Validate reply data <yes | no>.

```
execute ping-options validate-reply <string>
```

Parameter	Description	Type	Size
<string>	<yes no>.	string	

execute ping-options view-settings

View the current settings for PING option.

```
execute ping-options view-settings
```

execute policy-packet-capture

policy-packet-capture

This topic includes the following commands:

- [execute policy-packet-capture delete-all on page 1880](#)

execute policy-packet-capture delete-all

Delete all captured packet.

```
execute policy-packet-capture delete-all
```

execute preload

preload

This topic includes the following commands:

- [execute preload http-transaction-log disable on page 1881](#)
- [execute preload http-transaction-log enable on page 1881](#)
- [execute preload list on page 1881](#)
- [execute preload show-log on page 1881](#)

- [execute preload url on page 1881](#)
- [execute preload url-delete on page 1882](#)

execute preload http-transaction-log disable

Disables preload http transaction log

```
execute preload http-transaction-log disable
```

execute preload http-transaction-log enable

Enables preload http transaction log

```
execute preload http-transaction-log enable
```

execute preload list

Lists scheduled URLs

```
execute preload list
```

execute preload show-log

Show log of last preload runs

```
execute preload show-log
```

execute preload url

Schedule a new preload operation for a URL

```
execute preload url <url> <depth> <ignore-robots> <at_time> <repeat_after> <repetitions> <user-agent> <user>
```

Parameter	Description	Type	Size
<url>	URL to preload	string	
<depth>	Depth of preload. Defaults to 0	string	
<ignore-robots>	Ignore robots.txt rules. Defaults to disable[0]	string	

Parameter	Description	Type	Size
<at_time>	HHH:MM. HHH - hours from now [0-672], MM - Minutes from now [0-59]. Default is 0:00	string	
<repeat_after>	HHH:MM. HHH - hours from now [0-168], MM - Minutes from now [0-59]. Default is max	string	
<repetitions>	End after this many repetitions. Defaulted to 1.	string	
<user-agent>	Specify client type (Free text) to identify as	string	
<user>	Specify user (Password will be on separate prompt)	string	

execute preload url-delete

Deletes scheduled preload operation for the URL

```
execute preload url-delete <url-delete>
```

Parameter	Description	Type	Size
<url-delete>	Delete scheduled URLfor preload	string	

execute private-encryption-key

private-encryption-key

This topic includes the following commands:

- [execute private-encryption-key sample on page 1882](#)
- [execute private-encryption-key verify on page 1882](#)

execute private-encryption-key sample

Generate base64 clear text and its HMAC signature encrypted by private key.

```
execute private-encryption-key sample
```

execute private-encryption-key verify

Verify if the input base64 HMAC is encrypted by private key.

```
execute private-encryption-key verify <string> <string>
```

Parameter	Description	Type	Size
<string>	base64-clear-text.	string	
<string>	base64-hmac-signature.	string	

execute reboot

Reboot now.

```
execute reboot <comment> <string>
```

Parameter	Description	Type	Size
<comment>	comment	string	
<string>	Reboot comments.	string	

execute report

report

This topic includes the following commands:

- [execute report flush-cache on page 1883](#)
- [execute report recreate-db on page 1883](#)
- [execute report run on page 1884](#)

execute report flush-cache

Flush report caches

```
execute report flush-cache
```

execute report recreate-db

Recreate the report database

```
execute report recreate-db
```

execute report run

generate a report, only last 7-days data available

```
execute report run [layout name] [Start Time] [End Time]
```

Parameter	Description	Type	Size
[layout name]	Layout name for a report. If not provided, the default layout will be used.	string	
[Start Time]	Start time of the report time period ("yyyy-mm-dd hh").	string	
[End Time]	End time of the report time period ("yyyy-mm-dd hh").	string	

execute report-config

report-config

This topic includes the following commands:

- [execute report-config reset on page 1884](#)

execute report-config reset

Reset report templates to the factory default

```
execute report-config reset
```

execute restore

restore

This topic includes the following commands:

- [execute restore av ftp on page 1885](#)
- [execute restore av tftp on page 1886](#)
- [execute restore config dhcp on page 1886](#)
- [execute restore config flash on page 1886](#)
- [execute restore config ftp on page 1886](#)
- [execute restore config management-station normal on page 1887](#)
- [execute restore config management-station script on page 1887](#)

- [execute restore config management-station template on page 1887](#)
- [execute restore config tftp on page 1888](#)
- [execute restore config usb on page 1888](#)
- [execute restore config usb-mode on page 1888](#)
- [execute restore image flash on page 1888](#)
- [execute restore image ftp on page 1889](#)
- [execute restore image management-station on page 1889](#)
- [execute restore image tftp on page 1889](#)
- [execute restore image url on page 1889](#)
- [execute restore image usb on page 1890](#)
- [execute restore ips ftp on page 1890](#)
- [execute restore ips tftp on page 1890](#)
- [execute restore ipsuserdefsig ftp on page 1891](#)
- [execute restore ipsuserdefsig tftp on page 1891](#)
- [execute restore manual-license ftp on page 1891](#)
- [execute restore manual-license tftp on page 1892](#)
- [execute restore other-objects ftp on page 1892](#)
- [execute restore other-objects tftp on page 1892](#)
- [execute restore script ftp on page 1893](#)
- [execute restore script lastlog on page 1893](#)
- [execute restore script scp on page 1893](#)
- [execute restore script tftp on page 1893](#)
- [execute restore tls-finger-print tftp on page 1894](#)
- [execute restore vmlicense ftp on page 1894](#)
- [execute restore vmlicense tftp on page 1894](#)

execute restore av ftp

Restore antivirus database from FTP server.

```
execute restore av ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<string>	Antivirus data base file name (path) on the remote server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute restore av tftp

Restore antivirus database from TFTP server.

```
execute restore av tftp <string> <tftp server>
```

Parameter	Description	Type	Size
<string>	Antivirus database file name on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute restore config dhcp

Load config file via DHCP.

```
execute restore config dhcp <port> <Enter> | <vlanid>
```

Parameter	Description	Type	Size
<port>	Port to be DHCP client.	string	
<Enter> <vlanid>	Enter or specify VLAN ID to create a VLAN on the <port>.	string	

execute restore config flash

Load config file from flash to firewall.

```
execute restore config flash <revision>
```

Parameter	Description	Type	Size
<revision>	Revision ID on the flash.	string	

execute restore config ftp

Load config file from FTP server.

```
execute restore config ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd>  
<Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Configure file name(path) on the remote server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	
<Enter> <passwd>	Password may be needed to restore.	string	

execute restore config management-station normal

Load normal config file from management station to firewall.

```
execute restore config management-station normal <revision>
```

Parameter	Description	Type	Size
<revision>	Revision to retrieve, or enter '0' to get latest revision list.	string	

execute restore config management-station script

Load script config file from management station to firewall.

```
execute restore config management-station script <revision>
```

Parameter	Description	Type	Size
<revision>	Revision to retrieve, or enter '0' to get latest revision list.	string	

execute restore config management-station template

Load template config file from management station to firewall.

```
execute restore config management-station template <revision>
```

Parameter	Description	Type	Size
<revision>	Revision to retrieve, or enter '0' to get latest revision list.	string	

execute restore config tftp

Load config file from TFTP server to firewall.

```
execute restore config tftp <string> <tftp server> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	File name on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	
<Enter> <passwd>	Password may be needed to restore.	string	

execute restore config usb

Load config file from USB disk to firewall.

```
execute restore config usb <string> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	File name on USB disk.	string	
<Enter> <passwd>	Password may be needed to restore.	string	

execute restore config usb-mode

Load config file from USB disk and reboot.

```
execute restore config usb-mode <Enter>|<passwd>
```

Parameter	Description	Type	Size
<Enter> <passwd>	Optional password to protect.	string	

execute restore image flash

Restore image from flash.

```
execute restore image flash <revision>
```

Parameter	Description	Type	Size
<revision>	Image revision ID on flash.	string	

execute restore image ftp

Load image from FTP server.

```
execute restore image ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<string>	Image file name(path) on the remote server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute restore image management-station

Restore image from Management station.

```
execute restore image management-station <string>
```

Parameter	Description	Type	Size
<string>	Image ID on the server.	string	

execute restore image tftp

Restore image from TFTP server.

```
execute restore image tftp <string> <tftp address>
```

Parameter	Description	Type	Size
<string>	Image file name on the TFTP server.	string	
<tftp address>	TFTP server IPv4, IPv6, or FQDN.	string	

execute restore image url

Restore image from URL with HTTP/HTTPS protocols. Decrypt image if needed.

```
execute restore image url <string> <Enter>|<passwd>|<force> <Enter>|<force>
```

Parameter	Description	Type	Size
<string>	URL string with protocol prefix. e.g: https://example.com/image.aes	string	
<Enter> <passwd> <force>	Image encryption passphrase.	string	
<Enter> <force>	Bypass signature and validity checking.	string	

execute restore image usb

Restore image from USB disk.

```
execute restore image usb <string>
```

Parameter	Description	Type	Size
<string>	Image file name on the USB disk.	string	

execute restore ips ftp

Restore IPS database from FTP server.

```
execute restore ips ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<string>	IPS data base file name (path) on the remote server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute restore ips tftp

Restore IPS database from TFTP server.

```
execute restore ips tftp <string> <tftp server>
```

Parameter	Description	Type	Size
<string>	IPS database file name on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute restore ipsuserdefsig ftp

Restore user-defined ips signatures file from FTP server.

```
execute restore ipsuserdefsig ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<string>	User-defined ips signatures file on the remote server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute restore ipsuserdefsig tftp

Restore user defined IPS signatures file from TFTP server.

```
execute restore ipsuserdefsig tftp <string> <tftp server>
```

Parameter	Description	Type	Size
<string>	File name on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute restore manual-license ftp

Restore Manual License from FTP server.

```
execute restore manual-license ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<string>	FortiGuard Contract License file name on the FTP server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute restore manual-license tftp

Restore Manual License from TFTP server.

```
execute restore manual-license tftp <string> <tftp server>
```

Parameter	Description	Type	Size
<string>	Fortiguard Contract License file name on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute restore other-objects ftp

Restore other FortiGuard packages from FTP server. Current support: Internet-service Database Apps/Maps, URL Allow List and CASB signatures.

```
execute restore other-objects ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<string>	Other FortiGuard package file name on the FTP server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute restore other-objects tftp

Restore other FortiGuard packages from TFTP server. Current support: Internet-service Database Apps/Maps, URL Allow List and CASB signatures.

```
execute restore other-objects tftp <string> <tftp server>
```

Parameter	Description	Type	Size
<string>	Other FortiGuard package file name on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute restore script ftp

Load script from FTP server.

```
execute restore script ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<string>	Script on the remote server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute restore script lastlog

Read the result of last restored script.

```
execute restore script lastlog
```

execute restore script scp

Load script from SCP server to firewall.

```
execute restore script scp <string> <ip> <user> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	File name on the SCP server.	string	
<ip>	IP address.	string	
<user>	User name.	string	
<Enter> <passwd>	Enter or input password.	string	

execute restore script tftp

Load script from TFTP server to firewall.

```
execute restore script tftp <string> <tftp server> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	File name on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	
<Enter> <passwd>	Password may be needed to restore.	string	

execute restore tls-finger-print tftp

Restore TLS fingerprint file from TFTP server.

```
execute restore tls-finger-print tftp <string> <ip>
```

Parameter	Description	Type	Size
<string>	File name on the TFTP server.	string	
<ip>	IP address of TFTP server.	string	

execute restore vmlicense ftp

Restore VM license from FTP server.

```
execute restore vmlicense ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<string>	VM license file name(path) on the remote server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute restore vmlicense tftp

restore VM license from tftp server

```
execute restore vmlicense tftp <string> <tftp server>
```

Parameter	Description	Type	Size
<string>	VM license file name on the tftp server	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute revision

revision

This topic includes the following commands:

- [execute revision delete config on page 1895](#)
- [execute revision delete image on page 1895](#)
- [execute revision list config on page 1895](#)
- [execute revision list image on page 1896](#)

execute revision delete config

Delete config revision on local disk.

```
execute revision delete config <revision> <rev_id>
```

Parameter	Description	Type	Size
<revision>	Revision ID(s) on local disk. Eg. 1 3-6 8	string	
<rev_id>	place holder for multiple Revision IDs, at most 10 a time.	string	

execute revision delete image

Delete image revision on local disk.

```
execute revision delete image <revision> <rev_id>
```

Parameter	Description	Type	Size
<revision>	Revision ID(s) on local disk. Eg. 1 3-6 8	string	
<rev_id>	place holder for multiple Revision IDs, at most 10 a time.	string	

execute revision list config

List config revision on local disk.

```
execute revision list config
```

execute revision list image

List image revision on local disk.

```
execute revision list image
```

execute send-fds-statistics

Send FortiGuard statistics.

```
execute send-fds-statistics
```

execute send-fmg-list

Send connected FortiManager list to FortiGuard.

```
execute send-fmg-list
```

execute set

set

This topic includes the following commands:

- [execute set system session filter clear all on page 1897](#)
- [execute set system session filter clear dport on page 1897](#)
- [execute set system session filter clear dst on page 1897](#)
- [execute set system session filter clear duration on page 1897](#)
- [execute set system session filter clear expire on page 1898](#)
- [execute set system session filter clear policy on page 1898](#)
- [execute set system session filter clear proto on page 1898](#)
- [execute set system session filter clear sport on page 1898](#)
- [execute set system session filter clear src on page 1898](#)
- [execute set system session filter clear vd on page 1898](#)
- [execute set system session filter dport on page 1899](#)
- [execute set system session filter dst on page 1899](#)
- [execute set system session filter duration on page 1899](#)
- [execute set system session filter expire on page 1899](#)

- [execute set system session filter list on page 1900](#)
- [execute set system session filter negate dport on page 1900](#)
- [execute set system session filter negate dst on page 1900](#)
- [execute set system session filter negate duration on page 1900](#)
- [execute set system session filter negate expire on page 1900](#)
- [execute set system session filter negate policy on page 1900](#)
- [execute set system session filter negate proto on page 1901](#)
- [execute set system session filter negate sport on page 1901](#)
- [execute set system session filter negate src on page 1901](#)
- [execute set system session filter negate vd on page 1901](#)
- [execute set system session filter policy on page 1901](#)
- [execute set system session filter proto on page 1902](#)
- [execute set system session filter sport on page 1902](#)
- [execute set system session filter src on page 1902](#)
- [execute set system session filter vd on page 1902](#)

execute set system session filter clear all

Clear session filter.

```
execute set system session filter clear all
```

execute set system session filter clear dport

Clear destination port.

```
execute set system session filter clear dport
```

execute set system session filter clear dst

Clear destination IP.

```
execute set system session filter clear dst
```

execute set system session filter clear duration

Clear duration.

```
execute set system session filter clear duration
```

execute set system session filter clear expire

Clear expire.

```
execute set system session filter clear expire
```

execute set system session filter clear policy

Clear policy ID.

```
execute set system session filter clear policy
```

execute set system session filter clear proto

Clear protocol.

```
execute set system session filter clear proto
```

execute set system session filter clear sport

Clear source port.

```
execute set system session filter clear sport
```

execute set system session filter clear src

Clear source IP.

```
execute set system session filter clear src
```

execute set system session filter clear vd

Clear virtual domain.

```
execute set system session filter clear vd
```

execute set system session filter dport

Destination port.

```
execute set system session filter dport <xxxx> <xxxx>
```

Parameter	Description	Type	Size
<xxxx>	<0-65535> (from).	string	
<xxxx>	<0-65535> (to).	string	

execute set system session filter dst

Destination IP address.

```
execute set system session filter dst <xxx.xxx.xxx.xxx> <xxx.xxx.xxx.xxx>
```

Parameter	Description	Type	Size
<xxx.xxx.xxx.xxx>	Destination IP (from).	string	
<xxx.xxx.xxx.xxx>	Destination IP (to).	string	

execute set system session filter duration

duration

```
execute set system session filter duration <xxx> <xxx>
```

Parameter	Description	Type	Size
<xxx>	Duration (from).	string	
<xxx>	Duration (to).	string	

execute set system session filter expire

expire

```
execute set system session filter expire <xxx> <xxx>
```

Parameter	Description	Type	Size
<xxx>	Expire (from).	string	
<xxx>	Expire (to).	string	

execute set system session filter list

List system session filter.

```
execute set system session filter list
```

execute set system session filter negate dport

Inverse destination port.

```
execute set system session filter negate dport
```

execute set system session filter negate dst

Inverse destination IP.

```
execute set system session filter negate dst
```

execute set system session filter negate duration

Inverse duration.

```
execute set system session filter negate duration
```

execute set system session filter negate expire

Inverse expire.

```
execute set system session filter negate expire
```

execute set system session filter negate policy

Inverse policy ID.

```
execute set system session filter negate policy
```

execute set system session filter negate proto

Inverse protocol.

```
execute set system session filter negate proto
```

execute set system session filter negate sport

Inverse source port.

```
execute set system session filter negate sport
```

execute set system session filter negate src

Inverse source IP.

```
execute set system session filter negate src
```

execute set system session filter negate vd

Inverse virtual domain.

```
execute set system session filter negate vd
```

execute set system session filter policy

Policy ID.

```
execute set system session filter policy <xxx> <xxx>
```

Parameter	Description	Type	Size
<xxx>	Policy ID (from).	string	
<xxx>	Policy ID (to).	string	

execute set system session filter proto

Protocol number.

```
execute set system session filter proto <xx> <xx>
```

Parameter	Description	Type	Size
<xx>	<0-255> (from).	string	
<xx>	<0-255> (to).	string	

execute set system session filter sport

Source port.

```
execute set system session filter sport <xxxx> <xxxx>
```

Parameter	Description	Type	Size
<xxxx>	<0-65535> (from).	string	
<xxxx>	<0-65535> (to).	string	

execute set system session filter src

Source IP address.

```
execute set system session filter src <xxx.xxx.xxx.xxx> <xxx.xxx.xxx.xxx>
```

Parameter	Description	Type	Size
<xxx.xxx.xxx.xxx>	Source IP (from).	string	
<xxx.xxx.xxx.xxx>	Source IP (to).	string	

execute set system session filter vd

Index of virtual domain. -1 matches all.

```
execute set system session filter vd <xxx>
```

Parameter	Description	Type	Size
<xxx>	Index of virtual domain. -1 matches all.	string	

execute shutdown

Shutdown now.

```
execute shutdown <comment> <string>
```

Parameter	Description	Type	Size
<comment>	comment	string	
<string>	Shutdown comments.	string	

execute speed-test

A bandwidth measuring tool.

```
execute speed-test <interface> <server> <mode>
```

Parameter	Description	Type	Size
<interface>	auto <outgoing interface name>.	string	
<server>	server name.	string	
<mode>	optional, Auto(default), TCP or UDP.	string	

execute speed-test-dynamic

A bandwidth measuring tool for ipsec tunnel.

```
execute speed-test-dynamic <interface> <tunnel_name> <'y'/'n'> <max-out> <min-out>
```

Parameter	Description	Type	Size
<interface>	ipsec phase1 interface.	string	
<tunnel_name>	all <specific tunnel name>.	string	
<'y'/'n'>	Set result to tunnels' shaper.	string	
<max-out>	Maximum allowed uploading bandwidth (kbps).	string	
<min-out>	Minimum allowed uploading bandwidth (kbps).	string	

execute speed-test-server

speed-test-server

This topic includes the following commands:

- [execute speed-test-server download on page 1904](#)
- [execute speed-test-server list on page 1904](#)

execute speed-test-server download

Download server list from FortiProxy Cloud.

```
execute speed-test-server download
```

execute speed-test-server list

List all available servers.

```
execute speed-test-server list
```

execute ssh

Simple SSH client.

```
execute ssh <user@host> <port>
```

Parameter	Description	Type	Size
<user@host>	User-name @ IP address or domain name.	string	
<port>	port.	string	

execute ssh6

Simple IPv6 SSH client.

```
execute ssh6 <user@host> <port>
```


Parameter	Description	Type	Size
<user@host>	User-name @ IPv6 address or domain name.	string	
<port>	port.	string	

execute ssh6-options

ssh6-options

This topic includes the following commands:

- [execute ssh6-options interface on page 1905](#)
- [execute ssh6-options reset on page 1905](#)
- [execute ssh6-options source6 on page 1905](#)
- [execute ssh6-options view-settings on page 1906](#)

execute ssh6-options interface

Auto | <outgoing interface>.

```
execute ssh6-options interface <string>
```

Parameter	Description	Type	Size
<string>	Auto <outgoing interface>.	string	

execute ssh6-options reset

Reset settings.

```
execute ssh6-options reset
```

execute ssh6-options source6

Auto | <source interface IPv6>.

```
execute ssh6-options source6 <xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx>
```

Parameter	Description	Type	Size
<xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx:xxxx>	<source interface IPv6> Auto	string	

execute ssh6-options view-settings

View current settings for SSH (IPv6) option.

```
execute ssh6-options view-settings
```

execute ssh-options

ssh-options

This topic includes the following commands:

- [execute ssh-options interface on page 1906](#)
- [execute ssh-options reset on page 1906](#)
- [execute ssh-options source on page 1906](#)
- [execute ssh-options view-settings on page 1907](#)

execute ssh-options interface

Auto | <outgoing interface>.

```
execute ssh-options interface <string>
```

Parameter	Description	Type	Size
<string>	Auto <outgoing interface>.	string	

execute ssh-options reset

Reset settings.

```
execute ssh-options reset
```

execute ssh-options source

Auto | <source interface IP>.

```
execute ssh-options source <xxx.xxx.xxx.xxx>
```

Parameter	Description	Type	Size
<xxx.xxx.xxx.xxx>	<source interface IP> Auto	string	

execute ssh-options view-settings

View the current settings for SSH option.

```
execute ssh-options view-settings
```

execute ssh-regen-keys

Regenerate SSH server keys.

```
execute ssh-regen-keys
```

execute sync-IPSec

Sync all IPSec from peers.

```
execute sync-IPSec
```

execute sync-session

Sync all sessions from peers.

```
execute sync-session
```

execute system

system

This topic includes the following commands:

- [execute system custom-language import on page 1908](#)
- [execute system fortisandbox test-alternative-connectivity on page 1908](#)
- [execute system fortisandbox test-primary-connectivity on page 1908](#)

execute system custom-language import

Import a custom language from the TFTP server.

```
execute system custom-language import <string> <string> <ip>
```

Parameter	Description	Type	Size
<string>	The language name.	string	
<string>	The file name on the TFTP server.	string	
<ip>	IP address of the TFTP server.	string	

execute system fortisandbox test-alternative-connectivity

Query alternative FortiSandbox connection status.

```
execute system fortisandbox test-alternative-connectivity
```

execute system fortisandbox test-primary-connectivity

Query FortiSandbox connection status.

```
execute system fortisandbox test-primary-connectivity
```

execute tac

tac

This topic includes the following commands:

- [execute tac report on page 1909](#)

execute tac report

Debug report.

```
execute tac report
```

execute telnet

Simple telnet client.

```
execute telnet <dest> <port>
```

Parameter	Description	Type	Size
<dest>	IP address or domain name.	string	
<port>	port	string	

execute telnet-options

telnet-options

This topic includes the following commands:

- [execute telnet-options interface on page 1909](#)
- [execute telnet-options reset on page 1910](#)
- [execute telnet-options source on page 1910](#)
- [execute telnet-options view-settings on page 1910](#)

execute telnet-options interface

Auto | <outgoing interface>.

```
execute telnet-options interface <string>
```

Parameter	Description	Type	Size
<string>	Auto <outgoing interface>.	string	

execute telnet-options reset

Reset settings.

```
execute telnet-options reset
```

execute telnet-options source

Auto | <source interface IP>.

```
execute telnet-options source <xxx.xxx.xxx.xxx>
```

Parameter	Description	Type	Size
<xxx.xxx.xxx.xxx>	<source interface IP> Auto	string	

execute telnet-options view-settings

View the current settings for TELNET option.

```
execute telnet-options view-settings
```

execute time

System time.

```
execute time <hh:mm:ss>
```

Parameter	Description	Type	Size
<hh:mm:ss>	hh: 0-23, mm: 0-59, ss: 0-59.	string	

execute traceroute

Traceroute {IP|hostname}.

```
execute traceroute <dest>
```

Parameter	Description	Type	Size
<dest>	IP address or hostname.	string	

execute traceroute-options

traceroute-options

This topic includes the following commands:

- [execute traceroute-options device on page 1911](#)
- [execute traceroute-options queries on page 1911](#)
- [execute traceroute-options source on page 1911](#)
- [execute traceroute-options use-sdwan on page 1912](#)
- [execute traceroute-options view-settings on page 1912](#)

execute traceroute-options device

Auto | <ifname>.

```
execute traceroute-options device <string>
```

Parameter	Description	Type	Size
<string>	Auto <ifname>	string	

execute traceroute-options queries

Integer value to specify number of queries per hop.

```
execute traceroute-options queries <integer>
```

Parameter	Description	Type	Size
<integer>	Integer value [1, 10].	string	

execute traceroute-options source

Auto | <source interface IP>.

```
execute traceroute-options source <string>
```

Parameter	Description	Type	Size
<string>	Auto <source interface IP>.	string	

execute traceroute-options use-sdwan

Use SD-WAN rules to get output interface <yes | no>.

```
execute traceroute-options use-sdwan <string>
```

Parameter	Description	Type	Size
<string>	<yes no>.	string	

execute traceroute-options view-settings

View the current options of traceroute.

```
execute traceroute-options view-settings
```

execute tracert6

Traceroute for IPv6.

```
execute tracert6
```

execute update-av

Update AV engine/definitions.

```
execute update-av
```

execute update-external-resource

Download external resource.


```
execute update-external-resource <name>
```

Parameter	Description	Type	Size
<name>	External resource name	string	

execute update-ffdb-on-demand

Update ondemand FFDB from FDS.

```
execute update-ffdb-on-demand
```

execute update-geo-ip

Update IP Geography DB.

```
execute update-geo-ip
```

execute update-ips

Update IPS engine/definitions.

```
execute update-ips
```

execute update-list

Download update server list.

```
execute update-list
```

execute update-now

Update now.

```
execute update-now
```

execute update-src-vis

Update src-vis object.

```
execute update-src-vis
```

execute upd-vd-license

Update VDOM license.

```
execute upd-vd-license <license key>
```

Parameter	Description	Type	Size
<license key>	VDOM license key.	string	

execute upload

upload

This topic includes the following commands:

- [execute upload config ftp on page 1915](#)
- [execute upload config tftp on page 1915](#)
- [execute upload config usb on page 1915](#)
- [execute upload fortinbi-installer cloud on page 1916](#)
- [execute upload fortinbi-installer tftp on page 1916](#)
- [execute upload fortinbi-isolator-image cloud on page 1916](#)
- [execute upload fortinbi-isolator-image tftp on page 1916](#)
- [execute upload image ftp on page 1916](#)
- [execute upload image tftp on page 1917](#)
- [execute upload image usb on page 1917](#)
- [execute upload report-img ftp on page 1917](#)
- [execute upload report-img tftp on page 1918](#)

execute upload config ftp

Load config file from FTP server.

```
execute upload config ftp <string> <comment> <ftp server>[:ftp port] <Enter>|<user> <passwd>  
<Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	Configure file name(path) on the remote server.	string	
<comment>	comments	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	
<Enter> <passwd>	Password may be needed to restore.	string	

execute upload config tftp

Load config from TFTP server to local disk.

```
execute upload config tftp <string> <comment> <tftp server>
```

Parameter	Description	Type	Size
<string>	File name on the TFTP server.	string	
<comment>	comments	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute upload config usb

Load config from USB to local disk.

```
execute upload config usb <string> <comment>
```

Parameter	Description	Type	Size
<string>	File name on USB disk.	string	
<comment>	comments	string	

execute upload fortinbi-installer cloud

Upload the FortiNBI installer from cloud.

```
execute upload fortinbi-installer cloud
```

execute upload fortinbi-installer tftp

Upload the FortiNBI installer from a TFTP server.

```
execute upload fortinbi-installer tftp <string> <tftp server>
```

Parameter	Description	Type	Size
<string>	File name on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute upload fortinbi-isolator-image cloud

Upload the FortiNBI isolator image from cloud.

```
execute upload fortinbi-isolator-image cloud
```

execute upload fortinbi-isolator-image tftp

Upload the FortiNBI isolator image from a TFTP server.

```
execute upload fortinbi-isolator-image tftp <string> <tftp server>
```

Parameter	Description	Type	Size
<string>	File name on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute upload image ftp

Load image from FTP server.

```
execute upload image ftp <string> <comment> <ftp server>[:ftp port] <Enter>|<user> <passwd>
```

Parameter	Description	Type	Size
<string>	Image file name(path) on the remote server.	string	
<comment>	comments	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	

execute upload image tftp

Load image from TFTP server to local disk.

```
execute upload image tftp <string> <comment> <tftp server>
```

Parameter	Description	Type	Size
<string>	File name on the TFTP server.	string	
<comment>	comments	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute upload image usb

Load image from USB to local disk.

```
execute upload image usb <string> <comment>
```

Parameter	Description	Type	Size
<string>	File name on USB disk.	string	
<comment>	comments	string	

execute upload report-img ftp

upload report image file from ftp server

```
execute upload report-img ftp <string> <ftp server>[:ftp port] <Enter>|<user> <passwd> <Enter>
```

Parameter	Description	Type	Size
<string>	Image file name(path) on the remote server.	string	
<ftp server>[:ftp port]	FTP server IPv4, IPv6, or FQDN can be attached with port.	string	
<Enter> <user>	FTP username may be needed.	string	
<passwd>	FTP password.	string	
<Enter>		string	

execute upload report-img tftp

upload report image file from tftp server

```
execute upload report-img tftp <string> <tftp server> <Enter>
```

Parameter	Description	Type	Size
<string>	File name on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	
<Enter>		string	

execute usb-device

usb-device

This topic includes the following commands:

- [execute usb-device disconnect on page 1918](#)
- [execute usb-device list on page 1919](#)
- [execute usb-device modeswitch on page 1919](#)

execute usb-device disconnect

Disconnect a USB device.

```
execute usb-device disconnect
```

execute usb-device list

Display the lists of the USB device.

```
execute usb-device list
```

execute usb-device modeswitch

Perform usb device mode switch

```
execute usb-device modeswitch <argument string>
```

Parameter	Description	Type	Size
<argument string>	usb_modeswitch arguments. e.g: usb_modeswitch '-v 0x12d1 -p 0x1f01 -V 0x12d1 -P 0x14dc'	string	

execute usb-disk

usb-disk

This topic includes the following commands:

- [execute usb-disk delete on page 1919](#)
- [execute usb-disk eject on page 1920](#)
- [execute usb-disk format on page 1920](#)
- [execute usb-disk list on page 1920](#)
- [execute usb-disk rename on page 1920](#)

execute usb-disk delete

Delete file from the USB disk.

```
execute usb-disk delete <filename>
```

Parameter	Description	Type	Size
<filename>	File in the USB disk.	string	

execute usb-disk eject

Eject the USB disk.

```
execute usb-disk eject
```

execute usb-disk format

Format the USB disk.

```
execute usb-disk format
```

execute usb-disk list

Display the contents of the USB disk.

```
execute usb-disk list
```

execute usb-disk rename

Rename file in the USB disk.

```
execute usb-disk rename <old> <new>
```

Parameter	Description	Type	Size
<old>	Old file in the USB disk.	string	
<new>	New file in the USB disk.	string	

execute vm-license

Download VM license from FortiCare.

```
execute vm-license <token> <proxy>
```

Parameter	Description	Type	Size
<token>	VM License Token.	string	
<proxy>	HTTP Proxy URL.	string	

execute vm-license-options

vm-license-options

This topic includes the following commands:

- [execute vm-license-options account-id on page 1921](#)
- [execute vm-license-options account-password on page 1921](#)
- [execute vm-license-options count on page 1921](#)
- [execute vm-license-options government on page 1922](#)
- [execute vm-license-options interval on page 1922](#)
- [execute vm-license-options proxy on page 1922](#)
- [execute vm-license-options reset on page 1922](#)
- [execute vm-license-options show on page 1923](#)
- [execute vm-license-options token on page 1923](#)

execute vm-license-options account-id

Account ID.

```
execute vm-license-options account-id <string>
```

Parameter	Description	Type	Size
<string>	Account ID.	string	

execute vm-license-options account-password

Account password.

```
execute vm-license-options account-password <string>
```

Parameter	Description	Type	Size
<string>	Account password.	string	

execute vm-license-options count

FortiFlex license donwload count (default=1, 0 means infinite).

```
execute vm-license-options count <integer>
```

Parameter	Description	Type	Size
<integer>	API call count.	string	

execute vm-license-options government

For government use <yes | no>.

```
execute vm-license-options government <string>
```

Parameter	Description	Type	Size
<string>	<yes no>.	string	

execute vm-license-options interval

FortiFlex license download interval (1-3600 sec, default=60).

```
execute vm-license-options interval <integer>
```

Parameter	Description	Type	Size
<integer>	API call interval.	string	

execute vm-license-options proxy

HTTP proxy URL.

```
execute vm-license-options proxy <string>
```

Parameter	Description	Type	Size
<string>	HTTP proxy URL.	string	

execute vm-license-options reset

Reset options.

```
execute vm-license-options reset
```

execute vm-license-options show

Show options.

```
execute vm-license-options show
```

execute vm-license-options token

Token.

```
execute vm-license-options token <string>
```

Parameter	Description	Type	Size
<string>	Token.	string	

execute vpn

vpn

This topic includes the following commands:

- [execute vpn certificate ca export tftp on page 1924](#)
- [execute vpn certificate ca import auto on page 1924](#)
- [execute vpn certificate ca import bundle on page 1924](#)
- [execute vpn certificate ca import tftp on page 1925](#)
- [execute vpn certificate crl import auto on page 1925](#)
- [execute vpn certificate ems_ca import tftp on page 1925](#)
- [execute vpn certificate hsm primus generate ec on page 1925](#)
- [execute vpn certificate hsm primus generate rsa on page 1926](#)
- [execute vpn certificate hsm primus load-key on page 1927](#)
- [execute vpn certificate hsm safenet generate rsa on page 1928](#)
- [execute vpn certificate local export tftp on page 1928](#)
- [execute vpn certificate local generate cmp on page 1929](#)
- [execute vpn certificate local generate default-gui-mgmt-cert on page 1929](#)
- [execute vpn certificate local generate default-ssl-ca on page 1930](#)
- [execute vpn certificate local generate default-ssl-ca-untrusted on page 1930](#)
- [execute vpn certificate local generate default-ssl-key-certs on page 1930](#)
- [execute vpn certificate local generate default-ssl-serv-key on page 1930](#)
- [execute vpn certificate local generate ec on page 1930](#)
- [execute vpn certificate local generate rsa on page 1931](#)
- [execute vpn certificate local import tftp on page 1932](#)

- [execute vpn certificate local verify on page 1932](#)
- [execute vpn certificate remote export tftp on page 1933](#)
- [execute vpn certificate remote import tftp on page 1933](#)
- [execute vpn ipsec tunnel down on page 1933](#)
- [execute vpn ipsec tunnel up on page 1933](#)

execute vpn certificate ca export tftp

Export CA certificate to a TFTP server.

```
execute vpn certificate ca export tftp <string> <string> <ip>
```

Parameter	Description	Type	Size
<string>	CA certificate name.	string	
<string>	File name on the TFTP server.	string	
<ip>	IP address of TFTP server.	string	

execute vpn certificate ca import auto

Import CA certificate via SCEP.

```
execute vpn certificate ca import auto <string> <string> <ip> <fingerprint>
```

Parameter	Description	Type	Size
<string>	URL of the CA server.	string	
<string>	CA Identifier (optional).	string	
<ip>	Source-IP for communications to the CA server (optional).	string	
<fingerprint>	Fingerprint for authenticating CA certificate from server (optional).	string	

execute vpn certificate ca import bundle

Import certificate bundle from a TFTP server.

```
execute vpn certificate ca import bundle <string> <ip>
```

Parameter	Description	Type	Size
<string>	File name on the TFTP server.	string	
<ip>	IP address of TFTP server.	string	

execute vpn certificate ca import tftp

Import CA certificate from a TFTP server.

```
execute vpn certificate ca import tftp <string> <tftp server>
```

Parameter	Description	Type	Size
<string>	File name on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute vpn certificate crl import auto

Update CRL.

```
execute vpn certificate crl import auto <string>
```

Parameter	Description	Type	Size
<string>	CRL name.	string	

execute vpn certificate ems_ca import tftp

Import Testing EMS CA certificate from a TFTP server.

```
execute vpn certificate ems_ca import tftp <string> <tftp server>
```

Parameter	Description	Type	Size
<string>	File name on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute vpn certificate hsm primus generate ec

Generate a Primus HSM elliptic curve certificate request.

```
execute vpn certificate hsm primus generate ec <string> <string> <string> <string> <string>
<string> <string> <string> <string> <string> <string> <string> <string> <ip> <string> <string>
<string> <string>
```

Parameter	Description	Type	Size
<string>	Hardware Security Module partition name.	string	
<string>	Local and Hardware Security Module certificate and key name.	string	
<string>	Elliptic curve name: secp256r1, secp384r1 and secp521r1.	string	
<string>	Subject (Host IP/Domain Name/E-Mail).	string	
<string>	Country name (e.g. Canada) or country code (e.g. ca).	string	
<string>	State.	string	
<string>	City.	string	
<string>	Org.	string	
<string>	Unit(s); ',' as delimiter.	string	
<string>	Email.	string	
<string>	Subject alternative name (optional).	string	
<string>	URL of the CA server for signing via SCEP (optional).	string	
<string>	Challenge password for signing via SCEP (optional).	string	
<ip>	Source-IP for communications to the CA server (optional).	string	
<string>	CA identifier of the CA server for signing via SCEP (optional).	string	
<string>	Password for private-key (optional).	string	
<string>	Installed CA certificate for generating fingerprint for validating CA from SCEP server (optional).	string	
<string>	Fingerprint for authenticating CA certificate from SCEP server. Ignored if valid CA for generating fingerprint is specified (optional).	string	

execute vpn certificate hsm primus generate rsa

Generate a Primus HSM RSA certificate request.

```
execute vpn certificate hsm primus generate rsa <string> <string> <number> <string> <string>
<string> <string> <string> <string> <string> <string> <string> <string> <ip> <string> <string>
<string> <string>
```

Parameter	Description	Type	Size
<string>	Hardware Security Module partition name.	string	
<string>	Local and Hardware Security Module certificate and key name.	string	
<number>	Key size: 1024, 1536, 2048, 4096.	string	
<string>	Subject (Host IP/Domain Name/E-Mail).	string	
<string>	Country name (e.g. Canada) or country code (e.g. ca).	string	
<string>	State.	string	
<string>	City.	string	
<string>	Org.	string	
<string>	Unit(s); ',' as delimiter.	string	
<string>	Email.	string	
<string>	Subject alternative name (optional).	string	
<string>	URL of the CA server for signing via SCEP (optional).	string	
<string>	Challenge password for signing via SCEP (optional).	string	
<ip>	Source-IP for communications to the CA server (optional).	string	
<string>	CA identifier of the CA server for signing via SCEP (optional).	string	
<string>	Password for private-key (optional).	string	
<string>	Installed CA certificate for generating fingerprint for validating CA from SCEP server (optional).	string	
<string>	Fingerprint for authenticating CA certificate from SCEP server. Ignored if valid CA for generating fingerprint is specified (optional).	string	

execute vpn certificate hsm primus load-key

Try to load in a certificate from the Primus HSM.

```
execute vpn certificate hsm primus load-key <string>
```

Parameter	Description	Type	Size
<string>	Local and Hardware Security Module key name.	string	

execute vpn certificate hsm safenet generate rsa

Generate a SafeNet HSM RSA certificate request.

```
execute vpn certificate hsm safenet generate rsa <string> <string> <number> <string> <string>
<string> <string> <string> <string> <string> <string> <string> <string> <ip> <string> <string>
<string> <string>
```

Parameter	Description	Type	Size
<string>	HSM slot name.	string	
<string>	Local certificate name.	string	
<number>	Key size: 1024, 1536, 2048, 4096.	string	
<string>	Subject (Host IP/Domain Name/E-Mail).	string	
<string>	Country name (e.g. Canada) or country code (e.g. ca).	string	
<string>	State.	string	
<string>	City.	string	
<string>	Org.	string	
<string>	Unit(s); ',' as delimiter.	string	
<string>	Email.	string	
<string>	Subject alternative name (optional).	string	
<string>	URL of the CA server for signing via SCEP (optional).	string	
<string>	Challenge password for signing via SCEP (optional).	string	
<ip>	Source-IP for communications to the CA server (optional).	string	
<string>	CA identifier of the CA server for signing via SCEP (optional).	string	
<string>	Password for private-key (optional).	string	
<string>	Installed CA certificate for generating fingerprint for validating CA from SCEP server (optional).	string	
<string>	Fingerprint for authenticating CA certificate from SCEP server. Ignored if valid CA for generating fingerprint is specified (optional).	string	

execute vpn certificate local export tftp

Export local certificate or certificate request to a TFTP server.

```
execute vpn certificate local export tftp <string> <string> <string> <tftp server>
```


Parameter	Description	Type	Size
<string>	Local certificate name.	string	
<string>	Certificate file type ('cer' 'p12' 'csr').	string	
<string>	File name on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute vpn certificate local generate cmp

Generate a certificate request over CMPv2.

```
execute vpn certificate local generate cmp <string> <number> <string> <string> <string> <string>
<string> <string> <string> <string> <ip>
```

Parameter	Description	Type	Size
<string>	Local certificate name.	string	
<number>	Key size: 1024, 1536, 2048, 4096.	string	
<string>	Server ('ADDRESS:PORT' for CMP server, add 'https://' before address to enable ssl/tls).	string	
<string>	Path (Path location inside CMP server)	string	
<string>	SrvCert (CMDB name of CMP server's certificate/root-CA)	string	
<string>	AuthCert (CMDB name of client's current certificate)	string	
<string>	User (Username for doing the IR with a pre-shared key)	string	
<string>	Password (Password for doing the IR with a pre-shared key)	string	
<string>	Subject (optional, e.g. "CN=User,O=Org,OU=Unit").	string	
<string>	Subject alternative name (optional, e.g. "DNS:dns1.com,IP:192.168.1.99").	string	
<ip>	Source-IP for communications to the CMP server (optional).	string	

execute vpn certificate local generate default-gui-mgmt-cert

Generate the default GUI mgmt admin-server certificate.

```
execute vpn certificate local generate default-gui-mgmt-cert
```

execute vpn certificate local generate default-ssl-ca

Generate the default CA certificate used by SSL Inspection.

```
execute vpn certificate local generate default-ssl-ca
```

execute vpn certificate local generate default-ssl-ca-untrusted

Generate the default untrusted CA certificate used by SSL Inspection.

```
execute vpn certificate local generate default-ssl-ca-untrusted
```

execute vpn certificate local generate default-ssl-key-certs

Generate the default RSA, DSA and ECDSA key certs for ssl resign.

```
execute vpn certificate local generate default-ssl-key-certs
```

execute vpn certificate local generate default-ssl-serv-key

Generate the default server key used by SSL Inspection.

```
execute vpn certificate local generate default-ssl-serv-key
```

execute vpn certificate local generate ec

Generate an elliptic curve certificate request.

```
execute vpn certificate local generate ec <string> <string> <string> <string> <string> <string>
<string> <string> <string> <string> <string> <string> <ip> <string> <string> <string> <string>
```

Parameter	Description	Type	Size
<string>	Local certificate name.	string	
<string>	Elliptic curve name: secp256r1, secp384r1 and secp521r1.	string	
<string>	Subject (Host IP/Domain Name/E-Mail).	string	
<string>	Country name (e.g. Canada) or country code (e.g. ca).	string	
<string>	State.	string	
<string>	City.	string	
<string>	Org.	string	
<string>	Unit(s); ',' as delimiter.	string	
<string>	Email.	string	
<string>	Subject alternative name (optional).	string	
<string>	URL of the CA server for signing via SCEP (optional).	string	
<string>	Challenge password for signing via SCEP (optional).	string	
<ip>	Source-IP for communications to the CA server (optional).	string	
<string>	CA identifier of the CA server for signing via SCEP (optional).	string	
<string>	Password for private-key (optional).	string	
<string>	Installed CA certificate for generating fingerprint for validating CA from SCEP server (optional).	string	
<string>	Fingerprint for authenticating CA certificate from SCEP server. Ignored if valid CA for generating fingerprint is specified (optional).	string	

execute vpn certificate local generate rsa

Generate a RSA certificate request.

```
execute vpn certificate local generate rsa <string> <number> <string> <string> <string> <string>
<string> <string> <string> <string> <string> <string> <ip> <string> <string> <string> <string>
```

Parameter	Description	Type	Size
<string>	Local certificate name.	string	
<number>	Key size: 1024, 1536, 2048, 4096.	string	
<string>	Subject (Host IP/Domain Name/E-Mail).	string	

Parameter	Description	Type	Size
<string>	Country name (e.g. Canada) or country code (e.g. ca).	string	
<string>	State.	string	
<string>	City.	string	
<string>	Org.	string	
<string>	Unit(s); ',' as delimiter.	string	
<string>	Email.	string	
<string>	Subject alternative name (optional).	string	
<string>	URL of the CA server for signing via SCEP (optional).	string	
<string>	Challenge password for signing via SCEP (optional).	string	
<ip>	Source-IP for communications to the CA server (optional).	string	
<string>	CA identifier of the CA server for signing via SCEP (optional).	string	
<string>	Password for private-key (optional).	string	
<string>	Installed CA certificate for generating fingerprint for validating CA from SCEP server (optional).	string	
<string>	Fingerprint for authenticating CA certificate from SCEP server. Ignored if valid CA for generating fingerprint is specified (optional).	string	

execute vpn certificate local import tftp

Import the signed certificate from a TFTP server.

```
execute vpn certificate local import tftp <string> <tftp server> <string> <Enter>|<passwd>
```

Parameter	Description	Type	Size
<string>	File name on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	
<string>	Certificate file type ('cer' 'p12').	string	
<Enter> <passwd>	Password for PKCS12 file.	string	

execute vpn certificate local verify

Verify certificate and private key files match and regenerate if mismatched.

```
execute vpn certificate local verify <string>
```

Parameter	Description	Type	Size
<string>	Local certificate name.	string	

execute vpn certificate remote export tftp

Export REMOTE certificate to a TFTP server.

```
execute vpn certificate remote export tftp <string> <string> <tftp server>
```

Parameter	Description	Type	Size
<string>	REMOTE certificate name.	string	
<string>	File name on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute vpn certificate remote import tftp

Import REMOTE certificate from a TFTP server.

```
execute vpn certificate remote import tftp <string> <tftp server>
```

Parameter	Description	Type	Size
<string>	File name on the TFTP server.	string	
<tftp server>	TFTP server IPv4, IPv6, or FQDN.	string	

execute vpn ipsec tunnel down

Shut down the specified IPsec tunnel.

```
execute vpn ipsec tunnel down <phase1>
```

Parameter	Description	Type	Size
<phase1>	Phase1 name.	string	

execute vpn ipsec tunnel up

Activate the specified IPsec tunnel.

```
execute vpn ipsec tunnel up <phase1>
```

Parameter	Description	Type	Size
<phase1>	Phase1 name.	string	

execute wake-on-lan

Wake On LAN command.

```
execute wake-on-lan <interface> <host-mac> <protocol> <port> <ip> <password>
```

Parameter	Description	Type	Size
<interface>	Network interface to send out WoL packets.	string	
<host-mac>	Host MAC address to be woken up.	string	
<protocol>	Protocol used by WoL packets (1-WoL, 2-UDP, default = 2).	string	
<port>	Port used by UDP WoL packets, (0, 7, or 9, default = 9).	string	
<ip>	Broadcast IP used by UDP WoL packets.	string	
<password>	Password of the destination host if SecureOn is enabled.	string	

execute webcache

webcache

This topic includes the following commands:

- [execute webcache delete regular-expression on page 1934](#)
- [execute webcache delete simple-string on page 1935](#)
- [execute webcache delete status on page 1935](#)
- [execute webcache delete wildcard on page 1935](#)

execute webcache delete regular-expression

Delete objects matching a regular expression in webcache.

```
execute webcache delete regular-expression <pattern>
```

Parameter	Description	Type	Size
<pattern>	Pattern.	string	

execute webcache delete simple-string

Delete objects matching a simple string in webcache.

```
execute webcache delete simple-string <pattern>
```

Parameter	Description	Type	Size
<pattern>	Pattern.	string	

execute webcache delete status

Query pattern deletion status.

```
execute webcache delete status
```

execute webcache delete wildcard

Delete objects matching a wildcard in webcache.

```
execute webcache delete wildcard <pattern>
```

Parameter	Description	Type	Size
<pattern>	Pattern.	string	

execute webfilter

webfilter

This topic includes the following commands:

- [execute webfilter quota-reset on page 1936](#)

execute webfilter quota-reset

Reset the WF quota for a given user.

```
execute webfilter quota-reset <wf-profile> <endpoint>
```

Parameter	Description	Type	Size
<wf-profile>	Web filter profile.	string	
<endpoint>	Authenticated user or IP address.	string	



www.fortinet.com

Copyright© 2025 Fortinet, Inc. All rights reserved. Fortinet®, FortiGate®, FortiCare® and FortiGuard®, and certain other marks are registered trademarks of Fortinet, Inc., and other Fortinet names herein may also be registered and/or common law trademarks of Fortinet. All other product or company names may be trademarks of their respective owners. Performance and other metrics contained herein were attained in internal lab tests under ideal conditions, and actual performance and other results may vary. Network variables, different network environments and other conditions may affect performance results. Nothing herein represents any binding commitment by Fortinet, and Fortinet disclaims all warranties, whether express or implied, except to the extent Fortinet enters a binding written contract, signed by Fortinet's Chief Legal Officer, with a purchaser that expressly warrants that the identified product will perform according to certain expressly-identified performance metrics and, in such event, only the specific performance metrics expressly identified in such binding written contract shall be binding on Fortinet. For absolute clarity, any such warranty will be limited to performance in the same ideal conditions as in Fortinet's internal lab tests. Fortinet disclaims in full any covenants, representations, and guarantees pursuant hereto, whether express or implied. Fortinet reserves the right to change, modify, transfer, or otherwise revise this publication without notice, and the most current version of the publication shall be applicable.